



**LTE;
Telecommunication management;
Licensed Shared Access (LSA) Controller (LC)
Integration Reference Point (IRP);
Requirements
(3GPP TS 28.301 version 19.0.0 Release 19)**



Reference

RTS/TSGS-0528301vj00

Keywords

LTE

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from the
[ETSI Search & Browse Standards application](#).

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on [ETSI deliver repository](#).

Users should be aware that the present document may be revised or have its status changed,
this information is available in the [Milestones listing](#).

If you find errors in the present document, please send your comments to
the relevant service listed under [Committee Support Staff](#).

If you find a security vulnerability in the present document, please report it through our
[Coordinated Vulnerability Disclosure \(CVD\)](#) program.

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2025.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the [ETSI IPR online database](#).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™**, **LTE™** and **5G™** logo are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found at [3GPP to ETSI numbering cross-referencing](#).

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights	2
Legal Notice	2
Modal verbs terminology.....	2
Foreword.....	4
Introduction	4
1 Scope	5
2 References	5
3 Definitions and abbreviations.....	5
3.1 Definitions	5
3.2 Abbreviations	6
4 Concepts and background	6
4.1 General	6
4.2 Architecture	6
4.3 Functionality.....	6
5 Business level requirements	6
5.1 Requirements.....	6
5.1.1 Requirements for scenario 1	6
5.1.2 Requirements for scenario 2	6
5.2 Actor roles	7
5.3 Telecommunications resources	7
5.4 High-level use cases	7
5.4.1 High-level use cases for scenario 1.....	7
5.4.1.1 Use Case: LSA spectrum resources usage	7
5.4.2 High-level use cases for scenario 2.....	8
5.4.2.1 Use Case: LSA spectrum resources usage	8
6 Specification level requirements	8
6.1 Requirements.....	8
6.1.1 Requirements for scenario 1	8
6.1.2 Requirements for scenario 2	9
6.2 Actor roles	9
6.3 Telecommunications resources	9
6.4 Use cases	9
6.4.1 Use cases for scenario 1.....	9
6.4.1.1 Use case 1: Trigger LC registration	9
6.4.1.2 Use case 2: LC registration	10
6.4.1.3 Use case 3: Trigger LC de-registration	10
6.4.1.4 Use case 4: LC de-registration	11
6.4.1.5 Use case 5: LSRAI request	11
6.4.1.6 Use case 6: LSRAI notification.....	12
6.4.2 Use cases for scenario 2.....	12
6.4.2.1 Use case 1: Trigger LC registration	12
6.4.2.2 Use case 2: LC registration	12
6.4.2.3 Use case 3: Trigger LC de-registration	12
6.4.2.4 Use case 4: LC de-registration	12
6.4.2.5 Use case 5: LC initialization	13
6.4.2.6 Use case 6: LSA spectrum resource availability change.....	14
6.4.2.7 Use case 7: Network deployment update	15
6.4.2.8 Use case 8: Loss of connectivity with the LR	16
Annex A (informative): Change history	17
History	18

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

Introduction

The present document is part of a TS-family covering the 3rd Generation Partnership Project; Technical Specification Group Services and System Aspects; Telecommunication management; as identified below:

- 28.301 LSA Controller (LC) Integration Reference Point (IRP); Requirements**
- 28.302 LSA Controller (LC) Integration Reference Point (IRP); Information Service (IS)
- 28.303 LSA Controller (LC) Integration Reference Point (IRP); Solution Set (SS) definitions

1 Scope

The present document specifies the requirements of the Licensed Shared Access (LSA) Controller (LC) Integration Reference Point (IRP). This IRP allows the NM to interact with the LC. This interaction with the LC enables the NM to configure NEs utilizing LSA spectrum resources.

The following two deployment scenarios are supported:

- one scenario in which the LC communicates LSA spectrum resource availability information to the NM, and
- one scenario in which the LC determines and communicates to the NM constraints on parameters of cells liable to use LSA spectrum resources.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 32.101: "Telecommunication management; Principles and high level requirements".
- [3] ETSI TS 103 235 (V1.1.1): "Reconfigurable Radio Systems (RRS); system architecture and high level procedures for operation of Licensed Shared Access (LSA) in the 2300 MHz-2400 MHz band".
- [4] ETSI TS 103 379 (V1.1.1): "Reconfigurable Radio Systems (RRS); Information elements and protocols for the interface between LSA Controller (LC) and LSA Repository (LR) for operation of Licensed Shared Access (LSA) in the 2 300 MHz - 2 400 MHz band".
- [5] ETSI TS 103 154 (V1.1.1): "Reconfigurable Radio Systems (RRS); System requirements for operation of Mobile Broadband Systems in the 2 300 MHz - 2 400 MHz band under Licensed Shared Access (LSA)".
- [6] ETSI TR 103 113 (V1.1.1): "Electromagnetic compatibility and Radio spectrum Matters (ERM); System Reference document (SRdoc); Mobile broadband services in the 2 300 MHz - 2 400 MHz frequency band under Licensed Shared Access regime".

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

3.2 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

CEPT	Conference of Postal and Telecommunications Administrations
LC	LSA Controller
LR	LSA Repository
LSA	Licensed Shared Access
LSRAI	LSA Spectrum Resource Availability Information
NE	Network Element
NM	Network Manager
NMLS	Network Management Layer Service

4 Concepts and background

4.1 General

ETSI TS 103 235 [3], ETSI TS 103 379 [4], ETSI TS 103 154 [5] and ETSI TR 103 113 [6] describe a system architecture for operation of mobile broadband services in the 2 300 MHz - 2 400 MHz band under Licensed Shared Access (LSA), aimed at enabling access for mobile/fixed communication networks (MFCNs) in those CEPT countries where access to the band is foreseen but cannot be provided without restrictions due to incumbent usage.

This specification series describes the interface between the NM and LC.

4.2 Architecture

The LC is a kind of NMLS (see TS 32.101 [2]). The interface between the NM and LC is a Type 7 interface.

4.3 Functionality

Two deployment scenarios are considered and different functionality is specified for the interface between the LC and NM.

Deployment scenario 1: In this scenario the LC is a relay for the LSRAI received from the LR. The LC forwards it to the NM.

Deployment scenario 2: In this scenario the LSRAI is not forwarded to the NM. The LC computes radio configuration constraints based on the LSRAI received from the LR and radio planning parameters received from the NM. These radio configuration constraints are sent to the NM.

5 Business level requirements

5.1 Requirements

5.1.1 Requirements for scenario 1

REQ-LC-IRP-SC1-CON-001: The LSA licensee shall be able to use LSA spectrum resources.

5.1.2 Requirements for scenario 2

REQ-LC-IRP-SC2-CON-001: The LSA licensee shall be able to use LSA spectrum resources.

5.2 Actor roles

See detailed description of actor roles in clause 5.4.

5.3 Telecommunications resources

See detailed description of telecommunication resources in clause 5.4.

5.4 High-level use cases

5.4.1 High-level use cases for scenario 1

5.4.1.1 Use Case: LSA spectrum resources usage

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	The goal is to enable usage of LSA spectrum resources by the LSA licensee.	
Actors and Roles	MFCN, NM, LC, LR	
Telecom resources	MFCN, NM, LC, LR	
Assumptions	Connectivity between NM and LC Connectivity between LR and LC	
Pre-conditions	LSA spectrum resources are available. The LR, LC and MFCN are set up and running.	
Begins when	The LC registers with the LR	
Step 1 (M)	The LC receives LSRAI from the LR and forwards this information to the NM.	
Step 2 (M)	The NM informs the LC that necessary configuration changes in the MFCN have been applied. The LC forwards this information to the LR	
Step 3 (M)	The LC receives LSRAI updates and forwards these to the NM. When the necessary configuration changes have been applied in the MFCN the LC is notified. The LC forwards this information to the LR.	
Ends when	The LC deregisters from the LR, and forwards this information to the NM.	
Exceptions		
Post-conditions	The LC is deregistered from the LR, and LSA spectrum resources cannot be used any more by the LSA licensee.	
Traceability	REQ-LC-IRP-CON-001	

5.4.2 High-level use cases for scenario 2

5.4.2.1 Use Case: LSA spectrum resources usage

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	The mobile network uses LSA spectrum resources within the constraints provided by the LC.	
Actors and Roles	The LC providing constraints on parameters of cells operating on LSA frequencies to the NM The NM providing ranges for cells parameters to the LC	
Telecom resources	NM, LC	
Assumptions	Connectivity between NM and LC is established. Connectivity between LR and LC is established.	
Preconditions	LSA spectrum resources are available. The LR, LC and MFCN are set up and running.	
Begins when	The LC receives information on LSA spectrum resource usage by incumbents from the LR.	
Step 1 (M)	The LC requests to the NM the cell parameters range suitable for the mobile network.	
Step 2 (M)	The LC determines the constraints on the mobile network that need to be fulfilled taking into account the ranges provided by the NM.	
Step 3 (M)	The LC provides the NM with the constraints on the mobile network.	
Step 4 (M)	The NM applies the constraints and confirms to the LC when constraints are fulfilled.	
Ends when	The LC has received a confirmation from the mobile network that the constraints are fulfilled.	
Traceability	REQ-LC-IRP-CON-001	

6 Specification level requirements

6.1 Requirements

6.1.1 Requirements for scenario 1

REQ-LC-IRP-SC1-FUN-001: The LC shall support a capability allowing the NM to trigger the registration of the LC with the LR.

REQ-LC-IRP-SC1-FUN-002: The LC shall support a capability allowing to inform the NM about completion of the registration with the LR.

REQ-LC-IRP-SC1-FUN-003: The LC shall support a capability allowing the NM to trigger the de-registration of the LC with the LR.

REQ-LC-IRP-SC1-FUN-004: The LC shall support a capability allowing to inform the NM about completion of the de-registration with the LR.

REQ-LC-IRP-SC1-FUN-005: The LC shall support a capability allowing the NM to read the LSRAI that the LC has received from the LR.

REQ-LC-IRP-SC1-FUN-006: The LC shall support a capability allowing to inform the NM about changes of the LSRAI that the LC has received from the LR.

REQ-LC-IRP-SC1-FUN-007: The NM shall support a capability allowing to inform the LC that configuration changes in the MFCN (if needed) have been applied according to previously received LSRAI.

REQ-LC-IRP-SC1-FUN-008: The NM shall support a capability allowing LC to read if configuration changes in the MFCN (if needed) have been applied according to previously received LSRAI.

6.1.2 Requirements for scenario 2

REQ-LC-IRP-SC2-FUN-001: see REQ-LC-IRP-SC1-FUN-001

REQ-LC-IRP-SC2-FUN-002: see REQ-LC-IRP-SC1-FUN-002

REQ-LC-IRP-SC2-FUN-003: see REQ-LC-IRP-SC1-FUN-003

REQ-LC-IRP-SC2-FUN-004: see REQ-LC-IRP-SC1-FUN-004

REQ-LC-IRP-SC2-FUN-005: The LC shall support a capability allowing the NM to obtain the constraints on cells parameters that need to be satisfied in order to use LSA spectrum resources.

REQ-LC-IRP-SC2-FUN-006: The NM shall support a capability allowing the LC to obtain ranges of acceptable parameters for the cells operating on LSA frequencies.

REQ-LC-IRP-SC2-FUN-007: The LC shall take into account LSRAI in the LSA cells constraints calculation.

REQ-LC-IRP-SC2-FUN-008: The LC shall take into account the range for cell parameters provided by NM in the LSA cells constraints calculation.

6.2 Actor roles

See detailed description of actor roles in clause 6.4.

6.3 Telecommunications resources

See detailed description of telecommunications resources in clause 6.4.

6.4 Use cases

6.4.1 Use cases for scenario 1

6.4.1.1 Use case 1: Trigger LC registration

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	The goal is to trigger by the NM the registration of the LC with the LR	
Actors and Roles	NM, LC	
Telecom resources	NM, LC	
Assumptions	Connectivity between NM and LC Connectivity between LR and LC The actor triggering the LC registration is located at the NM.	
Pre-conditions	LSA spectrum resources are available. The LR, LC, NM and MFCN are set up and running.	
Begins when	The LSA licensee decides to use LSA spectrum resources	
Step 1 (M)	The NM triggers the LC to register with the LR.	
Step 2 (M)	The LC registers with the LR according to the registration procedure described in [3], clause 5.5.2.	
Step 3 (M)	The LC notifies the NM about the completion of the registration procedure with the LR.	
Ends when	The NM has received the information on the completion of the registration procedure.	
Exceptions	Connectivity between NM and LC, or LR and LC is lost.	
Post-conditions	The LSA licensee can use LSA spectrum resources.	
Traceability	REQ-LC-IRP-SC1-FUN-001	

6.4.1.2 Use case 2: LC registration

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	The goal is to register the LC with the LR, and to inform the NM about this.	
Actors and Roles	NM, LC	
Telecom resources	NM, LC	
Assumptions	Connectivity between NM and LC Connectivity between LR and LC The actor triggering the LC registration is located at the LC.	
Pre-conditions	LSA spectrum resources are available. The LR, LC, NM and MFCN are set up and running.	
Begins when	The LSA licensee decides to use LSA spectrum resources	
Step 1 (M)	The LC registers with the LR according to the registration procedure described in [3], clause 5.5.2.	
Step 2 (M)	The LC notifies the NM about the completion of the registration procedure with the LR.	
Ends when	The NM has received the information on the completion of the registration procedure.	
Exceptions	Connectivity between NM and LC, or LR and LC is lost.	
Post-conditions	The LSA licensee can use LSA spectrum resources.	
Traceability	REQ-LC-IRP-SC1-FUN-002	

6.4.1.3 Use case 3: Trigger LC de-registration

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	The goal is to de-register the LC with the LR, and to inform the NM about this.	
Actors and Roles	NM, LC	
Telecom resources	NM, LC	
Assumptions	Connectivity between NM and LC Connectivity between LR and LC The actor triggering the LC de-registration is located at the NM.	
Pre-conditions	The LR, LC, NM and MFCN are set up and running. The LC has registered with the LR. The LSA licensee is using LSA spectrum resources.	
Begins when	The LSA licensee decides to not use LSA spectrum resources any more, and stops using them.	
Step 1 (M)	The NM triggers the LC to de-register with the LR.	
Step 2 (M)	The LC de-registers with the LR according to the de-registration procedure described in [3], clause 5.5.3.	
Step 3 (M)	The LC notifies the NM about the completion of the de-registration procedure with the LR.	
Ends when	The NM has received the information on the completion of the de-registration procedure.	
Exceptions	Connectivity between NM and LC, or LR and LC is lost.	
Post-conditions	The LSA licensee cannot use LSA spectrum resources any more.	
Traceability	REQ-LC-IRP-SC1-FUN-003	

6.4.1.4 Use case 4: LC de-registration

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	The goal is to de-register the LC with the LR, and to inform the NM about this.	
Actors and Roles	NM, LC	
Telecom resources	NM, LC	
Assumptions	Connectivity between NM and LC Connectivity between LR and LC The actor triggering the LC de-registration is located at the LC.	
Pre-conditions	The LR, LC, NM and MFCN are set up and running. The LC has registered with the LR. The LSA licensee is using LSA spectrum resources.	
Begins when	The LSA licensee decides to not use LSA spectrum resources any more, and stops using them.	
Step 1 (M)	The LC de-registers with the LR according to the de-registration procedure described in [3], clause 5.5.3.	
Step 2 (M)	The LC notifies the NM about the completion of the de-registration procedure with the LR.	
Ends when	The NM has received the information on the completion of the de-registration procedure.	
Exceptions	Connectivity between NM and LC, or LR and LC is lost.	
Post-conditions	The LSA licensee cannot use LSA spectrum resources any more.	
Traceability	REQ-LC-IRP-SC1-FUN-004	

6.4.1.5 Use case 5: LSRAI request

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	The goal is to allow the NM to trigger synchronisation of the LSRAI in the NM with the LSRAI in the LR.	
Actors and Roles	NM, LC	
Telecom resources	NM, LC	
Assumptions	Connectivity between NM and LC Connectivity between LR and LC	
Pre-conditions	The LR, LC, NM and MFCN are set up and running. The LC has registered with the LR. The LSA licensee wants to start using LSA spectrum resources or is already using it.	
Begins when	The LSA licensee wants to synchronise the LSRAI in the NM with the LSRAI in the LC received from the LR.	
Step 1 (M)	The NM sends a LSRAI request message to the LC	
Step 2 (M)	The LC processes this request and forwards it to the LR according to the LSRAI request procedure described in [3], clause 5.5.4.	
Step 3 (M)	The LR sends the LSRAI response message to the LC according to the LSRAI request procedure described in [3], clause 5.5.4.	
Step 4 (M)	The LC processes the LSRAI response message and forwards it to the NM.	
Ends when	The NM has received the updated LSRAI.	
Exceptions	Connectivity between NM and LC, or LR and LC is lost.	
Post-conditions	The LSA licensee can use updated LSRAI.	
Traceability	REQ-LC-IRP-SC1-FUN-005	

6.4.1.6 Use case 6: LSRAI notification

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	The goal is to allow the LR to trigger synchronisation of the LSRAI in the NM with the LSRAI in the LR	
Actors and Roles	NM, LC	
Telecom resources	NM, LC	
Assumptions	Connectivity between NM and LC Connectivity between LR and LC	
Pre-conditions	The LR, LC, NM and MFCN are set up and running. The LC has registered with the LR. The LSA licensee wants to start using LSA spectrum resources or is already using it.	
Begins when	The LR wants to synchronise the LSRAI in the LC (and NM) with the LSRAI in the LR.	
Step 1 (M)	The LR sends a LSRAI notification to the LC according to the LSRAI notification procedure described in [3], clause 5.5.5.	
Step 2 (M)	The LC processes the notification and forwards it to the NM.	
Step 3 (M)	The NM acknowledges reception of the notification to the LC.	
Step 4 (M)	An LSRAI notification ack is sent back to the LR according to the LSRAI notification procedure described in [3], clause 5.5.5.	
Ends when	The LR has received the LSRAI notification ack.	
Exceptions	Connectivity between NM and LC, or LR and LC is lost.	
Post-conditions	The LSA licensee can use updated LSRAI.	
Traceability	REQ-LC-IRP-SC1-FUN-006	

6.4.2 Use cases for scenario 2

6.4.2.1 Use case 1: Trigger LC registration

See clause 6.4.1.1.

6.4.2.2 Use case 2: LC registration

See clause 6.4.1.2.

6.4.2.3 Use case 3: Trigger LC de-registration

See clause 6.4.1.3.

6.4.2.4 Use case 4: LC de-registration

See clause 6.4.1.4.

6.4.2.5 Use case 5: LC initialization

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	The mobile network can start using LSA spectrum resources.	
Actors and Roles	The function in the NM providing ranges for the parameters of cells operating on LSA frequencies to the LC. The function in the LC providing constraints on parameters of cells operating on LSA frequencies to the NM, taking into account the related ranges provided by NM and the LSRAI provided by LR	
Telecom resources	NM, LC	
Assumptions	Connectivity between NM and LC is established. Connectivity between LR and LC is established. The LC has the functionality to convert LSRAI and parameters ranges provided by NM to constraints on some parameters of cells operating on LSA frequencies and to inform the NM about changes on those constraints.	
Pre-conditions	The LR, LC, NM and MFCN are set up and running. The NM has access to the list of cells operating on LSA frequencies.	
Begins when	The LC has received up-to-date information on current LSA spectrum resource usage by LSA incumbent from the LR.	
Step 1 (M)	The LC asks to the NM the list of geographical areas containing the cells operating on LSA frequencies to the LC, as well as related ranges for cells parameters.	
Step 2 (M)	The LC computes, for each geographical area provided by NM, the constraints on parameters, taking into the LSRAI provided by LR in order to satisfy current LSA spectrum resource usage by incumbents and also taking into account the ranges on parameters provided by NM in order to satisfy the LSA Licensee requirements. NOTE: The LSA Licensee requirements are useful in order to find a suitable solution (LSA cell configuration parameters) by LC to minimize the probability of LSA cell switch off event (in the case in which the new LSA cell configuration parameters, calculated by LC, introduce a coverage or capacity or QoS degradation in the whole LSA licensee network).	
Step 3 (M)	The LC provides the NM with the constraints on cells parameters for cells operating on LSA frequencies.	
Step 4 (M)	The NM applies the necessary configuration changes	
Step 5 (M)	The NM confirms to the LC that the necessary configuration changes have been applied or not.	
Ends when	Ends when all steps identified above are completed or when an exception occurs.	
Exceptions	LC loses connectivity with the LR.	6.4.2.4
Post-conditions	The NM is able to properly configure and activate cells operating on LSA frequencies, using the constraints on cells parameters provided by the LC.	
Traceability	REQ-LC-IRP-SC2-FUN-005, REQ-LC-IRP-SC2-FUN-006, REQ-LC-IRP-SC2-FUN-007, REQ-LC-IRP-SC2-FUN-008	

6.4.2.6 Use case 6: LSA spectrum resource availability change

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	The mobile network operates according to the changed LSRAI given to the LC from the LR and according to the ranges for cell parameters given to the LC from the NM.	
Actors and Roles	The function in the NM providing parameters ranges for the parameters of cells operating on LSA frequencies to the LC. The function in the LC providing constraints on parameters of cells operating on LSA frequencies to the NM, taking into account the related ranges provided by NM and the LSRAI provided by LR	
Telecom resources	NM, LC	
Assumptions	Connectivity between NM and LC is established. Connectivity between LR and LC is established. The LC has the functionality to convert LSRAI and parameters ranges provided by NM to constraints on some parameters of cells operating on LSA frequencies and to inform the NM about changes on those constraints.	
Pre-conditions	The LR, LC, NM and MFCN are set up and running. The LC has the knowledge of which cells are operating on LSA frequency and what constraints are applied in the network. Cells are working according to previously provided constraints from the LC via the NM.	
Begins when	The LC has received up-to-date information on current LSA spectrum resource usage by incumbents from the LR.	
Step 1 (M)	The LC determines, also taking into account the validity ranges for cell parameters provided by NM, if the constraints on cells parameters need to be updated in order to satisfy the changes in LSA spectrum resources availability	
Step 2 (M)	If required, the LC provides the NM with the new constraints on parameters, for each cell impacted by the changes in LSA spectrum resources availability.	
Step 3 (M)	The NM configures the impacted cells according to the new constraints.	
Step 4 (M)	The NM confirms to the LC that the necessary configuration changes have been applied.	
Ends when	The LC has received a confirmation from the NM that the necessary configuration changes have been applied.	
Exception	The LC loses connectivity with the LR.	6.4.2.4
Exception	The configuration of the affected cells is not successful.	
Post-conditions	The affected cells are working according to the new constraints.	
Traceability	REQ-LC-IRP-SC2-FUN-005, REQ-LC-IRP-SC2-FUN-007, REQ-LC-IRP-SC2-FUN-008	

6.4.2.7 Use case 7: Network deployment update

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	The mobile network can start using LSA spectrum resources according to the new constraints on parameters, following a change in network deployment.	
Actors and Roles	The function in the NM providing ranges for the parameters of cells operating on LSA frequencies to the LC. The function in the LC providing constraints on parameters of cells operating on LSA frequencies to the NM, taking into account the related ranges provided by NM and the LSRAI provided by LR	
Telecom resources	NM, LC	
Assumptions	Connectivity between NM and LC is established. Connectivity between LR and LC is established. The LC has the functionality to convert LSRAI and parameters ranges provided by NM to constraints on some parameters of cells operating on LSA frequencies and to inform the NM about changes on those constraints.	
Pre-conditions	The LR, LC, NM and MFCN are set up and running. The NM has access to the list of cells operating on LSA frequencies. The LC has received up-to-date information on current LSA spectrum resource usage by incumbents from the LR.	
Begins when	The NM detects a change in the deployment of cells operating on LSA frequencies (e.g., a cell has been added to the network, removed from the network or updated). Editor's note: it is FFS whether details need to be described on how the NM detects a change in the deployment of cells operating on LSA frequencies.	
Step 1 (M)	The NM provides the LC with the geographical areas related to the new cells, if any, as well as cells range parameters. The NM provides the LC with the geographical areas related to the cells operating on LSA frequencies that have been removed from the network, if any. The NM provides the LC with the geographical areas related to the cells operating on LSA frequencies and whose parameters have been modified, if any. NOTE: The NM does not need to inform the LC when parameters of cells operating on LSA frequencies have been modified within the constraints provided by the LC.	
Step 2 (M)	The LC computes the constraints on parameters of cells operating on LSA frequencies that need to be satisfied in order to satisfy current LSA spectrum resource usage by incumbents and taking into account the ranges on parameters provided by the NM to satisfy LSA Licensee requirements.	
Step 3 (M)	The LC provides the NM with the constraints on cells parameters.	
Step 4 (M)	The NM reconfigures cells utilizing LSA spectrum resources, if necessary.	
Step 5 (M)	The NM confirms to the LC that the necessary configuration changes have been applied.	
Ends when	The NM has received the constraints on cells parameters and applied the necessary configuration changes.	
Exception	The LC loses connectivity with the LR.	6.4.2.4
Exception	The configuration of the affected cells is not successful.	
Post-conditions	The NM is able to properly configure and activate new cells that are using LSA spectrum resources, using the constraints on cells parameters provided by the LC. The NM is able to properly reconfigure existing cells that are using LSA spectrum resources, using the updated constraints on cells parameters provided by the LC.	
Traceability	REQ-LC-IRP-SC2-FUN-005, REQ-LC-IRP-SC2-FUN-006, REQ-LC-IRP-SC2-FUN-007, REQ-LC-IRP-SC2-FUN-008	

6.4.2.8 Use case 8: Loss of connectivity with the LR

Use case stage	Evolution/Specification	<<Uses>> Related use
Goal	To provide the NM with default constraints on parameters of cells operating on LSA frequencies, following a loss of connectivity with the LR. The LC has received a confirmation from the NM that the necessary configuration changes have been applied.	
Actors and Roles	The function in the LC providing constraints on parameters of cells operating on LSA frequencies to the NM taking into account the related ranges provided by NM and the LSRAI provided by LR. The function in the NM providing a confirmation that the constraints are satisfied.	
Telecom resources	NM, LC	
Assumptions	Connectivity between NM and LC is established. Connectivity between LR and LC is established. The LC has the functionality to convert LSRAI and parameters ranges provided by NM to constraints on some parameters of cells operating on LSA frequencies and to inform the NM about changes on those constraints. The LC has been configured with a fall-back measure (such as one of the measures described in Annex D of [3]), to execute in case of loss of connectivity with the LR.	
Pre-conditions	The LR, LC, NM and MFCN are set up and running. The NM has access to the list of cells operating on LSA frequencies. The LC is configured with default LSA spectrum resource availability information, intended to be used when connectivity is lost with the LR.	
Begins when	The LC loses connectivity with the LR.	
Step 1 (M)	The LC asks to the NM the list of cells operating on LSA frequencies to the LC, as well as ranges for cells parameters.	
Step 2 (M)	The LC computes the default constraints on parameters of cells operating on LSA frequencies, according to the fall-back measure configured at the LC and taking into account the ranges on parameters provided by the NM.	
Step 3 (M)	The LC provides the NM with the new constraints on parameters.	
Step 4 (M)	The NM reconfigures cells operating on LSA frequencies, if necessary.	
Step 5 (M)	The NM confirms to the LC that the necessary configuration changes have been applied.	
Ends when	The LC has received a confirmation from the NM that the necessary configuration changes have been applied.	
Exceptions	The configuration of the affected cells is not successful.	
Post-conditions	The NM is able to use LSA spectrum resources according to the updates provided by the LC.	
Traceability	REQ-LC-IRP-SC2-FUN-005, REQ-LC-IRP-SC2-FUN-006, REQ-LC-IRP-SC2-FUN-007, REQ-LC-IRP-SC2-FUN-008	

Annex A (informative): Change history

Change history							
Date	Meeting	TDoc	CR	Rev	Cat	Subject/Comment	New version
2017-06	SA#76	SP-170469				Presented for information and approval	1.0.0
2017-06	SA#76					Upgrade to change control version	14.0.0
2018-06	-	-	-	-	-	Update to Rel-15 version (MCC)	15.0.0
2020-07	-	-	-	-	-	Update to Rel-16 version (MCC)	16.0.0
2022-03	-	-	-	-	-	Update to Rel-17 version (MCC)	17.0.0
2024-04	-	-	-	-	-	Update to Rel-18 version (MCC)	18.0.0
2025-09	SA#109	-	-	-	-	Update to Rel-19 version (MCC)	19.0.0

History

Document history		
V19.0.0	October 2025	Publication