

Draft **ETSI EN 300 962** V7.0.0 (1999-08)

European Standard (Telecommunications series)

**Digital cellular telecommunications system (Phase 2+);
Full rate speech;
Substitution and muting of lost frames for
full rate speech channels
(GSM 06.11 version 7.0.0 Release 1998)**



GSM®
GLOBAL SYSTEM FOR
MOBILE COMMUNICATIONS

ETSI 

Reference

REN/SMG-110611Q7 (8wo03i00.PDF)

Keywords

Digital cellular telecommunications system,
Global System for Mobile communications (GSM)

ETSI

Postal address

F-06921 Sophia Antipolis Cedex - FRANCE

Office address

650 Route des Lucioles - Sophia Antipolis
Valbonne - FRANCE
Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16
Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Internet

secretariat@etsi.fr
Individual copies of this ETSI deliverable
can be downloaded from
<http://www.etsi.org>
If you find errors in the present document, send your
comment to: editor@etsi.fr

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1999.
All rights reserved.

Contents

Intellectual Property Rights.....	4
Foreword	4
1 Scope.....	5
2 References.....	5
3 Definitions and abbreviations	5
4 General	5
5 Requirements.....	5
5.1 First lost speech frame	5
5.2 Subsequent lost speech frames.....	6
5.3 First lost SID frame.....	6
5.4 Subsequent lost SID frame.....	6
6 Example solution.....	6
Annex A (informative): Change Request History	8
History	9

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available **free of charge** from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://www.etsi.org/ipr>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This European Standard (Telecommunications series) has been produced by ETSI Technical Committee Special Mobile Group (SMG), and is now submitted for the ETSI standards One-step Approval Procedure.

The present document specifies the substitution and muting of lost frames for full rate speech channels for the digital cellular telecommunications system.

The contents of the present document is subject to continuing work within SMG and may change following formal SMG approval. Should SMG modify the contents of the present document it will be re-released with an identifying change of release date and an increase in version number as follows:

Version 7.x.y

where:

- 7 indicates Release 1998 of GSM Phase 2+
- x the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- y the third digit is incremented when editorial only changes have been incorporated in the specification.

Proposed national transposition dates	
Date of latest announcement of this EN (doa):	3 months after ETSI publication
Date of latest publication of new National Standard or endorsement of this EN (dop/e):	6 months after doa
Date of withdrawal of any conflicting National Standard (dow):	6 months after doa

1 Scope

The present document defines a frame substitution and muting procedure which shall be used by the RX DTX handler when one or more lost speech or SID frames are received from the radio subsystem.

The requirements of the present document are mandatory for implementation in all GSM Base Station Systems (BSS) and Mobile Stations (MS).

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies.
- A non-specific reference to an ETS shall also be taken to refer to later versions published as an EN with the same number.
- For this Release 1998 document, references to GSM documents are for Release 1998 versions (version 7.x.y).

- [1] GSM 01.04: "Digital cellular telecommunications system (Phase 2+); Abbreviations and acronyms".
- [2] GSM 06.10: "Digital cellular telecommunications system (Phase 2+); Full rate speech; Transcoding".
- [3] GSM 06.31: "Digital cellular telecommunications system (Phase 2+); Full rate speech; Discontinuous Transmission (DTX) for full rate speech traffic channel".

3 Definitions and abbreviations

Abbreviations used in the present document are listed in GSM 01.04 [1].

The definitions of terms used in the present document can be found in GSM 06.31 [3].

4 General

The purpose of the frame substitution is to conceal the effect of lost frames.

The purpose of muting the output in the case of several lost frames is to indicate the breakdown of the channel to the user.

5 Requirements

5.1 First lost speech frame

Normal decoding of lost speech frames would result in very unpleasant noise effects. In order to improve the subjective quality, the first lost speech frame shall be substituted with either a repetition or an extrapolation of the previous good speech frame(s). Lost speech frames shall not be delivered to the speech decoder, nor shall the output be muted directly.

5.2 Subsequent lost speech frames

For subsequent lost speech frames, a muting technique shall be used that will gradually decrease the output level, resulting in silencing of the output after a maximum of 320 ms. Clause 6 gives an example solution.

5.3 First lost SID frame

A single lost SID frame shall be substituted by the last valid SID frame and the procedure for valid SID frames be applied as described in GSM 06.31 [3].

5.4 Subsequent lost SID frame

For the second lost SID frame, a muting technique shall be used on the comfort noise that will gradually decrease the output level, resulting in silencing of the output after a maximum of 320 ms. Clause 6 gives an example solution.

For subsequent lost SID frames, the muting of the output shall be maintained.

6 Example solution

For guidance, an example solution is given.

The first lost speech frame is replaced at the speech decoder input by the previous good speech frame. Normal decoding is then performed.

The muting procedure to be used in the case of subsequent lost speech frames or for comfort noise frames following the second lost SID frame is as follows:

The pseudo-logarithmic encoded block amplitude X_{maxcr} (GSM 06.10 [2]), coded on the interval from 0 to 63, is decreased with a constant value $d=4$ in each frame, down to the lowest possible value. Consequently, X_{maxcr} will be reduced gradually, and the output muted after a maximum of 320 ms. The grid position parameters are chosen randomly between 0 and 3 during this time.

For subsequent unusable frames, after the frame where X_{maxcr} reached the lowest possible value, "silence frames" are passed from the RX DTX handler to the speech decoder to guarantee a low output level under all conditions. The silence frame is defined in table 1.

Table 1: Encoded parameters (GSM 06.10) of the silence frame

Log area ratio 1 = 42
Log area ratio 2 = 39
Log area ratio 3 = 21
Log area ratio 4 = 10
Log area ratio 5 = 9
Log area ratio 6 = 4
Log area ratio 7 = 3
Log area ratio 8 = 2

LTP gain = 0
LTP lag = 40

Grid position = 1
Block amplitude = 0

RPE pulse no. 1 = 3
RPE pulse no. 2 = 4
RPE pulse no. 3 = 3
RPE pulse no. 4 = 4
RPE pulse no. 5 = 4

RPE pulse no. 6 = 3
RPE pulse no. 7 = 3
RPE pulse no. 8 = 3
RPE pulse no. 9 = 3
RPE pulse no. 10 = 4
RPE pulse no. 11 = 4
RPE pulse no. 12 = 3
RPE pulse no. 13 = 3

- repeated for each subsegment

Annex A (informative): Change Request History

Change history					
SMG No.	TDoc. No.	CR. No.	Section affected	New version	Subject/Comments
SMG#07				4.0.4	ETSI Publication
SMG#20				5.0.1	Release 1996 version
SMG#27				6.0.0	Release 1997 version
SMG#28				6.0.1	ETSI Publication
SMG#29				7.0.0	Specification version 6.0.0 upgrade to Release 1998 version 7.0.0

History

Document history			
V7.0.0	August 1999	One-step Approval Procedure	OAP 9954: 1999-08-11 to 1999-12-10