

Draft **ETSI EN 300 970** V8.0.0 (2000-07)

---

*European Standard (Telecommunications series)*

**Digital cellular telecommunications system (Phase 2+);  
Half rate speech;  
Substitution and muting of lost frames for half rate  
speech traffic channels  
(GSM 06.21 version 8.0.0 Release 1999)**

---

**GSM**®

GLOBAL SYSTEM FOR  
MOBILE COMMUNICATIONS



Reference

---

REN/SMG-110621Q8

Keywords

---

Digital cellular telecommunications system,  
Global System for Mobile communications (GSM)

**ETSI**

650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

---

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° 7803/88

***Important notice***

---

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF).

In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at <http://www.etsi.org/tb/status/>

If you find errors in the present document, send your comment to:

editor@etsi.fr

***Copyright Notification***

---

No part may be reproduced except as authorized by written permission.  
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2000.  
All rights reserved.

---

# Contents

Intellectual Property Rights .....	4
Foreword .....	4
1 Scope .....	6
2 References .....	6
3 Definitions and abbreviations .....	6
3.1 Definitions .....	6
3.2 Abbreviations .....	6
4 General .....	7
5 Requirements.....	7
5.1 Error detection and concealment in case of unreliable speech or SID frames .....	7
5.1.1 Error detection .....	7
5.1.2 Output signal concealment.....	7
5.2 Frame substitution and muting in case of lost speech or SID frames .....	7
5.2.1 First and second lost speech frame .....	7
5.2.2 Subsequent lost speech frames.....	8
5.2.3 First and second lost SID frame.....	8
5.2.4 Subsequent lost SID frames .....	8
6 Example solutions .....	8
6.1 Example solution for error detection in case of unreliable frames .....	8
6.2 Example solution for output signal concealment in case of unreliable frames .....	8
6.3 Example solution for substitution and muting of lost speech frames.....	8
6.4 Example solution for substitution and muting of lost SID frames .....	9
<b>Annex A (informative): Change Request History .....</b>	<b>10</b>
History .....	11

---

## Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://www.etsi.org/ipr>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

---

## Foreword

This European Standard (Telecommunications series) has been produced by ETSI Technical Committee Special Mobile Group (SMG), and is now submitted for the ETSI standards One-step Approval Procedure.

The present document defines a frame substitution and muting procedure which shall be used by the Receive (RX) Discontinuous Transmission (DTX) handler for the half rate speech traffic channels within the digital cellular telecommunications system. The present document is part of a series covering the half rate speech traffic channels as described below:

- GSM 06.02 "Digital cellular telecommunications system (Phase 2+); Half rate speech; Half rate speech processing functions".
- GSM 06.20 "Digital cellular telecommunications system (Phase 2+); Half rate speech; Half rate speech transcoding".
- GSM 06.21 "Digital cellular telecommunications system (Phase 2+); Half rate speech; Substitution and muting of lost frames for half rate speech traffic channels".**
- GSM 06.22 "Digital cellular telecommunications system (Phase 2+); Half rate speech; Comfort noise aspects for half rate speech traffic channels".
- GSM 06.41 "Digital cellular telecommunications system (Phase 2+); Half rate speech; Discontinuous Transmission (DTX) for half rate speech traffic channels".
- GSM 06.42 "Digital cellular telecommunications system (Phase 2+); Half rate speech; Voice Activity Detector (VAD) for half rate speech traffic channels".
- GSM 06.06 "Digital cellular telecommunications system (Phase 2+); Half rate speech; ANSI-C code for the GSM half rate speech codec".
- GSM 06.07 "Digital cellular telecommunications system (Phase 2+); Half rate speech; Test sequences for the GSM half rate speech codec".

The contents of the present document is subject to continuing work within SMG and may change following formal SMG approval. Should SMG modify the contents of the present document it will be re-released with an identifying change of release date and an increase in version number as follows:

Version 8.x.y

where:

- 8 indicates Release 1999of GSM Phase 2+
- x the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- y the third digit is incremented when editorial only changes have been incorporated in the specification.

<b>Proposed national transposition dates</b>	
Date of latest announcement of this EN (doa):	3 months after ETSI publication
Date of latest publication of new National Standard or endorsement of this EN (dop/e):	6 months after doa
Date of withdrawal of any conflicting National Standard (dow):	6 months after doa

---

# 1 Scope

The present document defines a frame substitution and muting procedure which shall be used by the Receive (RX) Discontinuous Transmission (DTX) handler when one or more lost or unreliable speech or Silence Descriptor (SID) frames are received from the Radio Sub System (RSS).

The requirements of the present document are mandatory for implementation in all GSM Base Station Systems (BSS)s and Mobile Stations (MS)s capable of supporting the half rate speech traffic channel.

---

# 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies.
- A non-specific reference to an ETS shall also be taken to refer to later versions published as an EN with the same number.
- For this Release 1999 document, references to GSM documents are for Release 1999 versions (version 8.x.y).

- [1] GSM 01.04: "Digital cellular telecommunication system (Phase 2+); Abbreviations and acronyms".
- [2] GSM 05.03: "Digital cellular telecommunications system (Phase 2+); Channel coding".
- [3] GSM 06.20: "Digital cellular telecommunications system (Phase 2+); Half rate speech; Half rate speech transcoding".
- [4] GSM 06.41: "Digital cellular telecommunications system (Phase 2+); Half rate speech; Discontinuous Transmission (DTX) for half rate speech traffic channels".
- [5] GSM 06.06: "Digital cellular telecommunications system (Phase 2+); Half rate speech; ANSI-C code for the GSM half rate speech codec".

---

# 3 Definitions and abbreviations

## 3.1 Definitions

The definitions of terms used in the present document can be found in GSM 06.20 [3], GSM 06.41 [4], GSM 05.03 [2].

## 3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

BFI	Bad Frame Indication
BSS	Base Station System
DTX	Discontinuous Transmission
GSM	Global System for Mobile communications
LPC	Linear Predictive Coding
MS	Mobile Station
RX	Receive
RSS	Radio Sub System

SID	Silence Descriptor
UFI	Unreliable Frame Indication

For abbreviations not given in this subclause, see GSM 01.04 [1].

---

## 4 General

The RSS indicates lost speech or SID frames by setting the Bad Frame Indication (BFI) flag and unreliably decoded speech or SID frames by setting the Unreliable Frame Indication (UFI) flag.

If the BFI flag is set, the speech decoder performs frame substitution and muting of the speech output. The purpose of frame substitution is to conceal the effect of lost frames. The purpose of muting the speech output in case of several lost frames is to indicate the breakdown of the channel to the Mobile Station (MS) user in a way that avoids excessively unpleasant sounds.

If the UFI flag is set, the speech decoder performs a plausibility analysis of the received frame parameters and of the output signal aiming at the detection and concealment of erroneous frames which are not marked with the BFI flag.

---

## 5 Requirements

### 5.1 Error detection and concealment in case of unreliable speech or SID frames

A cleared BFI flag (BFI="0") and a set UFI flag (UFI="1") indicate a probably erroneous speech or SID frame. To improve the subjective quality, the probability of decoding erroneous frames shall be decreased by additional error detection which is based on both the exploitation of the frame parameters' properties and the decoder output signal's properties.

#### 5.1.1 Error detection

By investigating the frame parameter properties, it shall be decided whether the frame is to be considered as usable or unusable. In the latter case, the BFI flag is set and substitution and muting is performed (subclause 5.2). Subclause 6.1 gives an example solution for error detection in case of unreliable frames.

#### 5.1.2 Output signal concealment

If the frame is considered as usable, properties of the decoder output signal shall be compared to the corresponding signal properties of the previous valid frames. In case of large differences, the output signal shall be modified such that these differences are limited. Subclause 6.2 gives an example solution for output signal concealment in case of unreliable frames.

### 5.2 Frame substitution and muting in case of lost speech or SID frames

A set BFI flag (BFI="1") indicates a lost speech or SID frame. Normal decoding of these frames would result in a degradation of the subjective quality of the speech. To improve the subjective quality of the speech, the frame parameters shall be appropriately modified prior to the execution of the speech decoder functions.

#### 5.2.1 First and second lost speech frame

The first and second lost speech frame shall be partly or completely substituted with the last valid speech frame. For the first and second lost speech frame, the output shall not be muted directly.

## 5.2.2 Subsequent lost speech frames

For subsequent lost speech frames, a muting technique shall be used that will gradually decrease the output level, resulting in silencing of the output after a maximum of 80 ms. For subsequent lost speech frames, the muting of the output shall be maintained. Subclause 6.3 gives an example of such a method.

## 5.2.3 First and second lost SID frame

The first and second lost SID frame shall be substituted with the last good SID frame. For the first and second lost SID frame, the output shall not be muted directly.

## 5.2.4 Subsequent lost SID frames

For subsequent lost SID frames, a muting technique shall be used that will gradually decrease the output level, resulting in silencing of the output after a maximum of 320 ms. For subsequent lost SID frames, the muting of the output shall be maintained. Subclause 6.4 gives an example of such a method.

---

# 6 Example solutions

The C code of the following example solutions are given in GSM 06.06 [5].

## 6.1 Example solution for error detection in case of unreliable frames

With the parameter R0, the average signal energy is transmitted. Except at the beginning or the end of a talk spurt, this parameter shows a smooth behaviour from frame to frame. For error detection purposes, the difference of the R0-value between the actual and the last good frame is computed. If this difference exceeds a level dependent threshold and the frame is marked as unreliable, it is declared unusable by setting the BFI flag equal to "1".

## 6.2 Example solution for output signal concealment in case of unreliable frames

In the speech decoder, the output signal is created by processing an excitation sequence through an LPC synthesis filter. The output signal energy of each subframe is calculated and compared to the output signal energy of the previous subframes. If the difference exceeds a level dependent threshold, the excitation sequence is attenuated such that the output signal energy corresponds to the output signal energy of the previous subframes.

## 6.3 Example solution for substitution and muting of lost speech frames

For the half rate speech decoder, a possible substitution and muting strategy is based on an 8-state machine.

The state, with the exception of states 6 and 7, indicates how many consecutive frames were lost. For example, state 5 indicates that 5 consecutive frames (including the current frame) were lost. State 7 is the initial state of the system, so that if the first decoded frame is lost, the frame is muted. Usually, the system will operate in state 0. The state machine remains in this state unless a frame is lost. On each successive lost speech frame, the state machine moves to the next higher numbered state. As soon as a frame is not declared lost, the machine returns to state 0 (unless it is in state 6). The machine remains in state 6 in the case of additional lost speech frames. If the machine is in state 6, a single frame without detected errors moves the machine to state 7 (i.e., two successive frames with no detected errors are needed to return to state 0 from state 6). This provides additional protection during prolonged intervals of very poor channel conditions which might cause false indications of valid speech data. If the machine is in state 7 and a lost speech frame is received, the machine returns to state 6.



In each state, the following occurs:

- State 0: No error is detected. The received decoded speech data is output. The current frame parameters are stored.
- State 1: An error has been detected in the frame. If the last speech frame in state 0 is in the unvoiced mode, then the parameters  $R_0$ ,  $INT\_LPC$  and the LPC coefficients in the current frame are replaced with the corresponding values from the last good frame. All  $GSP0$  parameters are replaced with the  $GSP0\_4$  parameter from the last good frame. If the  $MODE$  bits for the current frame indicate unvoiced, the current frame of codevectors is used. If not, the codevectors from the last good frame are used. The frame's remaining decoded bits are passed to the speech decoder without modification.
- Alternatively, if the last speech frame in state 0 was in the voiced mode, the long term predictor lag from the last good frame is used for all subframes in the current frame. The parameters  $MODE$ ,  $R_0$ ,  $INT\_LPC$  and the LPC coefficients are replaced with those from the last good frame. All  $GSP0$  parameters are replaced with the  $GSP0\_4$  parameter from the last good frame. If the  $MODE$  bits for the current frame indicate voiced ( $MODE = 1, 2$  or  $3$ ), the current frame of codevectors is used. If not, the codevectors from the last good frame are used. The frame's remaining decoded bits are passed to the speech decoder without modification.
- State 2: Same action as in state 1.
- State 3: As in state 1 and 2, a frame repetition is performed, but the frame energy  $R_0$  (coded on the interval from 0 to 31) is decreased by a value of 2.
- State 4: Same action as in state 3.
- State 5: Same action as in state 3.
- State 6: Again a frame repetition is performed. The output speech signal is muted by setting  $R_0$  to zero.
- State 7: The speech signal remains muted,  $R_0$  remains zero.

## 6.4 Example solution for substitution and muting of lost SID frames

The first and second lost SID frame is replaced by the last good SID frame.

For subsequent lost SID frames the last good SID frame is repeated, but the frame energy  $R_0$  (coded on the interval from 0 to 31) is decreased with a constant value of 2 in each frame down to  $R_0 = 0$ . This value is maintained if additional lost SID frames occur.

---

## Annex A (informative): Change Request History

Change history					
SMG No.	TDoc. No.	CR. No.	Section affected	New version	Subject/Comments
SMG#15				4.0.2	ETSI Publication
SMG#20				5.0.1	Release 1996 version
SMG#27				6.0.0	Release 1997 version
SMG#29				7.0.0	Release 1998 version
SMG#31				8.0.0	Release 1999 version

---

# History

<b>Document history</b>			
V8.0.0	July 2000	One-step Approval Procedure	OAP 20001103: 2000-07-05 to 2000-11-03