



**E**UROPEAN  
**T**ELECOMMUNICATION  
**S**TANDARD

**ETS 300 580-4**

September 1994

---

Source: ETSI TC-SMG

Reference: GSM 06.12

ICS: 33.060.30

**Key words:** European digital cellular communications system, Global System for Mobile communications (GSM)

**European digital cellular telecommunications system (Phase 2);  
Comfort noise aspect for full rate speech traffic channels  
(GSM 06.12)**

**ETSI**

European Telecommunications Standards Institute

**ETSI Secretariat**

**Postal address:** F-06921 Sophia Antipolis CEDEX - FRANCE

**Office address:** 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE

**X.400:** c=fr, a=atlas, p=etsi, s=secretariat - **Internet:** secretariat@etsi.fr

Tel.: +33 92 94 42 00 - Fax: +33 93 65 47 16

---

**Copyright Notification:** No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1994. All rights reserved.



## Contents

Foreword .....	5
0.1 Scope .....	7
0.2 Normative references .....	7
0.3 Definitions and abbreviations .....	7
1 General.....	7
2 Functions on the transmit side .....	8
2.1 Background acoustic noise evaluation .....	8
2.2 SID-frame encoding.....	8
3 Functions on the receive side.....	8
3.1 Comfort noise generation and updating.....	9
History.....	10

Blank page

## Foreword

This European Telecommunication Standard (ETS) has been produced by the Special Mobile Group (SMG) Technical Committee (TC) of the European Telecommunications Standards Institute (ETSI).

This ETS specifies the comfort noise aspect for full rate speech traffic channels for the European digital cellular telecommunications system (Phase 2).

This ETS correspond to GSM technical specification, GSM 06.12 version 4.0.4.

The specification from which this ETS has been derived was originally based on CEPT documentation, hence the presentation of this ETS may not be entirely in accordance with the ETSI/PNE rules.

Reference is made within this ETS to GSM Technical Specifications (GSM-TSs) (NOTE).

NOTE: TC-SMG has produced documents which give the technical specifications for the implementation of the European digital cellular telecommunications system. Historically, these documents have been identified as GSM Technical Specifications (GSM-TS). These TSs may have subsequently become I-ETSS (Phase 1), or ETSS (Phase 2), whilst others may become ETSI Technical Reports (ETRs). GSM-TSs are, for editorial reasons, still referred to in GSM ETSS.

Blank page

## 0.1 Scope

This technical specification gives the detailed requirements for the correct operation of the background acoustic noise evaluation, noise parameter encoding/decoding and comfort noise generation in GSM Mobile Stations and Base Station Systems during Discontinuous Transmission (DTX) on full rate speech traffic channels.

The requirements described in this technical specification are mandatory for implementation in all GSM Mobile Stations. The receiver requirements are mandatory for implementation in all GSM Base Station Systems, the transmitter requirements only for those where downlink DTX will be used.

## 0.2 Normative references

This ETS incorporates by dated and undated reference, provisions from other publications. These normative references are cited at the appropriate places in the text and the publications are listed hereafter. For dated references, subsequent amendments to or revisions of any of these publications apply to this ETS only when incorporated in it by amendment or revision. For undated references, the latest edition of the publication referred to applies.

- [1] GSM 01.04 (ETR 100): "European digital cellular telecommunication system (Phase 2); Definitions, abbreviations and acronyms".
- [2] GSM 05.03 (ETS 300 575): "European digital cellular telecommunication system (Phase 2); Channel coding".
- [3] GSM 06.10 (ETS 300 580-2): "European digital cellular telecommunication system (Phase 2); Full rate speech transcoding".
- [4] GSM 06.31 (ETS 300 580-5): "European digital cellular telecommunication system (Phase 2); Discontinuous Transmission (DTX) for full rate speech traffic channel".

## 0.3 Definitions and abbreviations

Definitions and abbreviations used in this specification are listed in GSM 01.04.

### 1 General

The definitions of terms used in this technical specification can be found in GSM 06.31.

The overall operation of Discontinuous Transmission is described in GSM 06.31.

A basic problem when using DTX is that the background acoustic noise, which is transmitted together with the speech, would disappear when the radio transmission is cut, resulting in a modulation of the background noise. Since the DTX switching can take place rapidly, it has been found that this effect can be very annoying for the listener - especially in a car environment with high background noise levels. In bad cases the speech may be hardly intelligible.

This technical specification specifies the way to overcome this problem by generating on the receive side synthetic noise similar to the transmit side background noise. The parameters of this so called comfort noise are estimated on the transmit side and transmitted to the receive side before the radio transmission is cut and at a regular low rate afterwards. This allows the comfort noise to adapt to the changes of the noise on the transmit side.

## 2 Functions on the transmit side

The comfort noise evaluation algorithm uses the unquantized block amplitude and Log Area Ratio (LAR) parameters of the full rate speech encoder, defined in section 4.2.15 and 4.2.6 of GSM 06.10. These parameters give information on the level and the spectrum of the background noise, respectively.

The evaluated comfort noise parameters are encoded into a special frame, called a SID (Silence Descriptor) frame, for transmission to the receive side.

The SID frame also serves to initiate the comfort noise generation on the receive side, as a SID frame is always sent at the end of a speech burst, ie before the radio transmission is cut.

The scheduling of SID or speech frames on the radio path is described in GSM 06.31.

### 2.1 Background acoustic noise evaluation

The comfort noise parameters to be encoded into a SID frame are calculated over N=4 consecutive frames marked with VAD=0, as follows:

The Log Area Ratio parameters shall be averaged according to the equation:

$$\text{mean (LAR}(i)) = 1/N \text{ SUM } [n=1 \text{ to } N] \text{ LAR}[j-n](i) \quad i = 1,2..8$$

where LAR[j](i) is the i'th Log Area Ratio coefficient of the current frame j and j-n indicates the previous frames.

The block amplitude parameter shall be averaged according to the equation:

$$\text{mean (xmax)} = 1/(4N) \text{ SUM } [n=1 \text{ to } N] \text{ SUM } [i=1 \text{ to } 4] \text{ xmax}[j-n](i) \quad i = 1,2,..8$$

where xmax[j](i) is the block amplitude in subsegment i of the current frame. The SID frame containing these averaged parameters is passed to the Radio Subsystem instead of frame number j.

### 2.2 SID-frame encoding

The SID-frame encoding algorithm exploits the fact that only some of the 260 bits in a frame are needed to code the comfort noise parameters. The other bits can then be used to mark the SID-frame by means of a fixed bit pattern, called the SID code word.

The log area ratio coefficients are replaced by the mean (LAR(i)) values defined above and encoded as described in GSM 06.10.

The block amplitude values are replaced by the mean (xmax) value defined above, repeated four times inside the frame and encoded as described in GSM 06.10.

The SID code word consists of 95 bits which are all zero. The bits of the SID code word are inserted in the SID field defined as the positions of those 95 bits of the encoded RPE-pulses Xmc, which are in the error protection class I (see GSM 05.03, table 2).

The remaining bits in the SID frame are set to zero. The use of these bits is for further study.

## 3 Functions on the receive side

The situations in which comfort noise shall be generated on the receive side are defined in GSM 06.31. Generally speaking, the comfort noise generation is started or updated whenever a valid SID frame is received.



### 3.1 Comfort noise generation and updating

The comfort noise generation procedure uses the RPE-LTP speech decoder algorithm defined in GSM 06.10.

When comfort noise is to be generated, then the various encoded parameters are set as follows:

The RPE pulses ( $X_{mcr}$ ) are replaced by a locally generated random integer sequence, uniformly distributed between 1 and 6.

Also the grid position parameters ( $M_{cr}$ ) are set to random integer values, uniformly distributed between 0 and 3.

The LTP gain values ( $b_{cr}$ ) are set to 0.

The LTP lag values ( $N_{cr}$ ) of the 4 subsegments are set to 40, 120, 40 and 120 respectively.

The 4 block amplitude values ( $X_{maxcr}$ ) used are those received in the SID frame.

The log area ratio parameters ( $LAR_{cr}$ ) used are those received in the SID frame.

With these parameters, the speech decoder now performs the standard operations described in GSM 06.10 and synthesizes comfort noise.

Updating of the comfort noise parameters occurs each time a valid SID frame is received, as described in GSM 06.31.

When updating the comfort noise, the parameters above should preferably be interpolated over a few frames to obtain smooth transitions.

## History

<b>Document history</b>	
September 1994	First Edition
December 1995	Converted into Adobe Acrobat Portable Document Format (PDF)