

ETSI TS 102 230-1 V16.0.0 (2023-08)



**Smart Cards;
UICC-Terminal interface;
Physical, electrical and logical test specification;
Part 1: Terminal features
(Release 16)**

Reference

RTS/SET-00102230-1vg00

Keywords

smart card, testing

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from:

<https://www.etsi.org/standards-search>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

<https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx>

If you find errors in the present document, please send your comment to one of the following services:

<https://portal.etsi.org/People/CommitteeSupportStaff.aspx>

If you find a security vulnerability in the present document, please report it through our
Coordinated Vulnerability Disclosure Program:

<https://www.etsi.org/standards/coordinated-vulnerability-disclosure>

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2023.
All rights reserved.

Contents

Intellectual Property Rights	13
Foreword.....	13
Modal verbs terminology.....	14
Introduction	14
1 Scope	15
2 References	15
2.1 Normative references	15
2.2 Informative references.....	16
3 Definition of terms, symbols, abbreviations and coding conventions.....	16
3.1 Terms.....	16
3.2 Symbols.....	16
3.3 Abbreviations	17
3.4 Coding conventions	18
3.5 Applicability.....	18
3.5.1 Applicability of the present document	18
3.5.2 Applicability of the individual test cases	18
3.5.3 Applicability to terminal equipment	18
3.6 Definitions.....	18
3.6.1 Format of table of the table of optional features	18
3.6.2 Format of the applicability table	19
3.6.3 Status and Notations	19
3.7 Table of optional features.....	20
3.8 Applicability table	21
4 Physical characteristic tests	25
4.1 Contact pressure	25
4.1.1 Definition and applicability	25
4.1.2 Conformance requirement	25
4.1.2.0 Description	25
4.1.2.1 Reference	25
4.1.3 Test purpose.....	25
4.1.4 Method of test.....	25
4.1.4.1 Initial conditions	25
4.1.4.2 Procedure	25
4.1.5 Acceptance criteria	25
4.2 Curvature of the contacting elements	25
4.2.1 Definition and applicability	25
4.2.2 Conformance requirement	26
4.2.2.0 Description	26
4.2.2.1 Reference	26
4.2.3 Test purpose.....	26
4.2.4 Method of test.....	26
4.2.4.1 Initial conditions	26
4.2.4.2 Procedure	26
4.2.5 Acceptance criteria	26
5 Electrical characteristic tests	26
5.1 Test of the power transition phases	26
5.1.1 Phase preceding Terminal power on.....	26
5.1.1.1 Definition and applicability.....	26
5.1.1.2 Conformance requirement.....	26
5.1.1.3 Reference	26
5.1.1.4 Test purpose	27
5.1.1.5 Method of test	27
5.1.1.5.1 Initial condition	27

5.1.1.5.2	Procedure	27
5.1.1.6	Acceptance criteria	27
5.1.2	Phase during UICC power on	27
5.1.2.1	Phase during UICC power on: 3 V - 5 V	27
5.1.2.1.1	Definition and applicability	27
5.1.2.1.2	Conformance requirement	27
5.1.2.1.3	Reference	27
5.1.2.1.4	Test purpose	28
5.1.2.1.5	Method of test	28
5.1.2.1.6	Acceptance criteria	28
5.1.2.2	Phase during UICC power on: 1,8 V - 3 V	28
5.1.2.2.1	Definition and applicability	28
5.1.2.2.2	Conformance requirement	28
5.1.2.2.3	Reference	28
5.1.2.2.4	Test purpose	28
5.1.2.2.5	Method of test	29
5.1.2.2.6	Acceptance criteria	29
5.1.3	Phase during Terminal power off	29
5.1.3.1	Phase during Terminal power off: 3 V - 5 V	29
5.1.3.1.1	Definition and applicability	29
5.1.3.1.2	Conformance requirement	29
5.1.3.1.3	Reference	29
5.1.3.1.4	Test purpose	30
5.1.3.1.5	Method of test	30
5.1.3.1.6	Acceptance criteria	30
5.1.3.2	Phase during Terminal power off: 1,8 V - 3 V	30
5.1.3.2.1	Definition and applicability	30
5.1.3.2.2	Conformance requirement	30
5.1.3.2.3	Reference	31
5.1.3.2.4	Test purpose	31
5.1.3.2.5	Method of test	31
5.1.3.2.6	Acceptance criteria	31
5.1.4	Warm reset timing	31
5.1.4.1	Definition and applicability	31
5.1.4.2	Conformance requirement	31
5.1.4.2.0	Description	31
5.1.4.2.1	Reference	32
5.1.4.3	Test purpose	32
5.1.4.4	Method of test	32
5.1.4.4.1	Initial conditions	32
5.1.4.4.2	Procedure	32
5.1.4.5	Acceptance criteria	32
5.1.5	UICC type recognition and voltage switching	32
5.1.5.1	Reaction of 3 V technology Terminals on type recognition of 3 V technology UICCs	32
5.1.5.1.1	Definition and applicability	32
5.1.5.1.2	Conformance requirement	32
5.1.5.1.3	Reference	32
5.1.5.1.4	Test purpose	33
5.1.5.1.5	Method of test	33
5.1.5.1.6	Acceptance criteria	33
5.1.5.2	Reaction of 3 V technology Terminals on type recognition of 1,8 V technology UICCs	33
5.1.5.2.1	Definition and applicability	33
5.1.5.2.2	Conformance requirement	33
5.1.5.2.3	Reference	33
5.1.5.2.4	Test purpose	34
5.1.5.2.5	Method of test	34
5.1.5.2.6	Acceptance criteria	34
5.1.5.3	Reaction of 1,8 V technology Terminals on type recognition of 1,8 V technology UICCs	34
5.1.5.3.1	Definition and applicability	34
5.1.5.3.2	Conformance requirement	34
5.1.5.3.3	Reference	34
5.1.5.3.4	Test purpose	34

5.1.5.3.5	Method of test.....	35
5.1.5.3.6	Acceptance criteria	35
5.1.5.4	Reaction of 1,8 V technology Terminals on type recognition of 3 V technology UICCs	35
5.1.5.4.1	Definition and applicability	35
5.1.5.4.2	Conformance requirement	35
5.1.5.4.3	Reference.....	35
5.1.5.4.4	Test purpose	35
5.1.5.4.5	Method of test.....	36
5.1.5.4.6	Acceptance criteria	36
5.1.5.5	Void.....	36
5.1.5.6	Reaction of Terminals receiving no ATR	36
5.1.5.6.1	Reaction of Terminals receiving no ATR: 3 V - 5 V.....	36
5.1.5.6.2	Reaction of Terminals receiving no ATR: 1,8 V - 3 V.....	37
5.1.5.7	FFS	38
5.1.5.8	FFS	38
5.1.5.9	Reaction of Terminals not supporting any voltage class indicated in the ATR	38
5.1.5.9.1.	Definition and applicability	38
5.1.5.9.2	Conformance requirement	38
5.1.5.9.2.0	Description.....	38
5.1.5.9.2.1	Reference	38
5.1.5.9.3	Test purpose	38
5.1.5.9.4	Method of test.....	38
5.1.5.9.4.1	Initial condition.....	38
5.1.5.9.4.2	Procedure	38
5.1.5.9.5	Acceptance criteria	38
5.2	Electrical tests on each Terminal contact	39
5.2.1	Nominal test conditions	39
5.2.2	Electrical tests on contact C1 (Card power supply - V _{CC})	40
5.2.2.1	Electrical tests on contact C1, Test 1: 3 V - 5 V	40
5.2.2.1.1	Definition and applicability	40
5.2.2.1.2	Conformance requirement	40
5.2.2.1.3	Reference.....	40
5.2.2.1.4	Test purpose	40
5.2.2.1.5	Method of test.....	40
5.2.2.1.6	Acceptance criteria	41
5.2.2.2	Electrical tests on contact C1, Test 2: 3 V - 5 V	41
5.2.2.2.1	Definition and applicability	41
5.2.2.2.2	Conformance requirement	41
5.2.2.2.3	Reference.....	41
5.2.2.2.4	Test purpose	41
5.2.2.2.5	Method of test.....	41
5.2.2.2.6	Acceptance criteria	44
5.2.2.3	Electrical tests on contact C1, Test 1: 1,8 V - 3 V	44
5.2.2.3.1	Definition and applicability	44
5.2.2.3.2	Conformance requirement	44
5.2.2.3.3	Reference.....	44
5.2.2.3.4	Test purpose	44
5.2.2.3.5	Method of test.....	44
5.2.2.3.6	Acceptance criteria	45
5.2.2.4	Electrical tests on contact C1, Test 2: 1,8 V - 3 V	45
5.2.2.4.1	Definition and applicability	45
5.2.2.4.2	Conformance requirement	45
5.2.2.4.3	Reference.....	45
5.2.2.4.4	Test purpose	45
5.2.2.4.5	Method of test.....	45
5.2.2.4.6	Acceptance criteria	46
5.2.3	Electrical tests on contact C2 (Reset - RST).....	47
5.2.3.1	Electrical tests on contact C2: 3 V - 5 V	47
5.2.3.1.1	Definition and applicability	47
5.2.3.1.2	Conformance requirement	47
5.2.3.1.3	Reference.....	47
5.2.3.1.4	Test purpose	47

5.2.3.1.5	Method of test.....	47
5.2.3.1.6	Acceptance criteria	47
5.2.3.2	Electrical tests on contact C2: 1,8 V - 3 V	47
5.2.3.2.1	Definition and applicability	47
5.2.3.2.2	Conformance requirement	48
5.2.3.2.3	Reference.....	48
5.2.3.2.4	Test purpose	48
5.2.3.2.5	Method of test.....	48
5.2.3.2.6	Acceptance criteria	48
5.2.4	Electrical tests on contact C3 (Clock - CLK)	48
5.2.4.1	Electrical tests on contact C3: 3 V - 5 V	48
5.2.4.1.1	Definition and applicability	48
5.2.4.1.2	Conformance requirement	48
5.2.4.1.3	Reference.....	49
5.2.4.1.4	Test purpose	49
5.2.4.1.5	Method of test.....	49
5.2.4.1.6	Acceptance criteria	49
5.2.4.2	Electrical tests on contact C3: 1,8 V - 3 V	49
5.2.4.2.1	Definition and applicability	49
5.2.4.2.2	Conformance requirement	50
5.2.4.2.3	Reference.....	50
5.2.4.2.4	Test purpose	50
5.2.4.2.5	Method of test.....	50
5.2.4.2.6	Acceptance criteria	50
5.2.5	Electrical tests on contact C7 (Input/Output - I/O)	51
5.2.5.1	Electrical tests on contact C7, Test 1: 3 V - 5 V	51
5.2.5.1.1	Definition and applicability	51
5.2.5.1.2	Conformance requirement	51
5.2.5.1.3	Reference.....	51
5.2.5.1.4	Test purpose	51
5.2.5.1.5	Method of test.....	52
5.2.5.1.6	Acceptance criteria	52
5.2.5.2	Electrical tests on contact C7, Test 2: 3 V - 5 V	52
5.2.5.2.1	Definition and applicability	52
5.2.5.2.2	Conformance requirement	52
5.2.5.2.3	Reference.....	53
5.2.5.2.4	Test purpose	53
5.2.5.2.5	Method of test.....	53
5.2.5.2.6	Acceptance criteria	53
5.2.5.3	Electrical tests on contact C7, Test 1: 1,8 V - 3 V	53
5.2.5.3.1	Definition and applicability	53
5.2.5.3.2	Conformance requirement	53
5.2.5.3.3	Reference.....	54
5.2.5.3.4	Test purpose	54
5.2.5.3.5	Method of test.....	54
5.2.5.3.6	Acceptance criteria	54
5.2.5.4	Electrical tests on contact C7, Test 2: 1,8 V - 3 V	55
5.2.5.4.1	Definition and applicability	55
5.2.5.4.2	Conformance requirement	55
5.2.5.4.3	Reference.....	55
5.2.5.4.4	Test purpose	55
5.2.5.4.5	Method of test.....	56
5.2.5.4.6	Acceptance criteria	56
6	Initial communication tests	56
6.1	ATR.....	56
6.1.1	ATR characters	56
6.1.1.1	Definition and applicability.....	56
6.1.1.2	Conformance requirement.....	56
6.1.1.2.0	Description	56
6.1.1.2.1	Reference.....	56
6.1.1.3	Test purpose	56

6.1.1.4	Method of test	57
6.1.1.4.1	Initial conditions	57
6.1.1.4.2	Procedure.....	57
6.1.1.5	Acceptance criteria.....	59
6.2	Clock stop mode with 1,8 V technology UICC.....	60
6.2.1	Definition and applicability	60
6.2.2	Conformance requirement	60
6.2.2.0	Description	60
6.2.2.1	Reference	60
6.2.3	Test purpose.....	60
6.2.4	Method of test	60
6.2.4.1	Initial conditions	60
6.2.4.2	Procedure	60
6.2.5	Acceptance criteria	62
6.3	Clock stop mode with 3 V technology UICC.....	62
6.3.1	Definition and applicability	62
6.3.2	Conformance requirement	63
6.3.2.0	Description	63
6.3.2.1	Reference	63
6.3.3	Test purpose.....	63
6.3.4	Method of test	63
6.3.4.1	Initial conditions	63
6.3.4.2	Procedure	63
6.3.5	Acceptance criteria	65
6.4	Void.....	65
6.5	Speed enhancement	65
6.5.1	Definition and applicability	65
6.5.2	Conformance requirement	65
6.5.3	Test purpose.....	65
6.5.4	Method of test	65
6.5.4.1	Initial conditions	65
6.5.4.2	Procedure	66
6.5.5	Acceptance criteria	67
7	Transmission protocol tests	67
7.1	Character transmission	67
7.1.1	Bit/character duration during the transmission from the Terminal to the UICC.....	67
7.1.1.1	Definition and applicability.....	67
7.1.1.2	Conformance requirement.....	67
7.1.1.2.0	Description	67
7.1.1.2.1	Reference.....	67
7.1.1.3	Test purpose	67
7.1.1.4	Method of test	67
7.1.1.4.1	Initial conditions	67
7.1.1.4.2	Procedure.....	67
7.1.1.5	Acceptance criteria.....	68
7.1.2	Bit/character duration during the transmission from the UICC to the Terminal.....	68
7.1.2.1	Definition and applicability.....	68
7.1.2.2	Conformance requirement.....	68
7.1.2.2.0	Description	68
7.1.2.2.1	Reference.....	68
7.1.2.3	Test purpose	68
7.1.2.4	Method of test	68
7.1.2.4.1	Initial conditions.....	68
7.1.2.4.2	Procedure.....	68
7.1.2.5	Acceptance criteria.....	68
7.2	T=0 protocol.....	69
7.2.1	Timing	69
7.2.1.1	Definition and applicability.....	69
7.2.1.2	Conformance requirement.....	69
7.2.1.2.0	Description	69
7.2.1.2.1	Reference.....	69

7.2.1.3	Test purpose	69
7.2.1.4	Method of test	69
7.2.1.4.1	Initial conditions	69
7.2.1.4.2	Procedure.....	69
7.2.1.5	Acceptance criteria.....	70
7.2.2	Command processing, ACK, NACK, NULL procedure bytes	70
7.2.2.1	Definition and applicability.....	70
7.2.2.2	Conformance requirement.....	71
7.2.2.2.0	Description	71
7.2.2.2.1	Reference.....	71
7.2.2.3	Test purpose	71
7.2.2.4	Method of test	71
7.2.2.4.1	Initial conditions.....	71
7.2.2.4.2	Procedure.....	71
7.2.2.5	Acceptance criteria.....	71
7.2.3	Case 2 command, use of procedure bytes '61xx' and '6Cxx'	71
7.2.3.1	Definition and applicability.....	71
7.2.3.2	Conformance requirement.....	72
7.2.3.2.0	Description	72
7.2.3.2.1	Reference.....	72
7.2.3.3	Test purpose	72
7.2.3.4	Method of test	72
7.2.3.4.1	Initial conditions.....	72
7.2.3.4.2	Procedure.....	72
7.2.3.5	Acceptance criteria.....	72
7.2.4	Case 4 command, use of procedure bytes '61xx'	72
7.2.4.1	Definition and applicability.....	72
7.2.4.2	Conformance requirement.....	73
7.2.4.2.0	Description	73
7.2.4.2.1	Reference.....	73
7.2.4.3	Test purpose	73
7.2.4.4	Method of test	73
7.2.4.4.1	Initial conditions.....	73
7.2.4.4.2	Procedure.....	73
7.2.4.5	Acceptance criteria.....	73
7.2.5	Command processing, warning and error status bytes.....	73
7.2.5.1	Definition and applicability.....	73
7.2.5.2	Conformance requirement.....	73
7.2.5.2.0	Description	73
7.2.5.2.1	Reference.....	74
7.2.5.3	Test purpose	74
7.2.5.4	Method of test	74
7.2.5.4.1	Initial conditions.....	74
7.2.5.4.2	Procedure.....	74
7.2.5.5	Acceptance criteria.....	74
7.2.6	Error correction.....	74
7.2.6.1	Definition and applicability.....	74
7.2.6.2	Conformance requirement.....	74
7.2.6.2.0	Description	74
7.2.6.2.1	Reference.....	74
7.2.6.3	Test purpose	75
7.2.6.4	Method of test	75
7.2.6.4.1	Initial conditions.....	75
7.2.6.4.2	Procedure.....	75
7.2.6.5	Acceptance criteria.....	75
7.2.7	Error detection	75
7.2.7.1	Definition and applicability.....	75
7.2.7.2	Conformance requirement.....	75
7.2.7.2.0	Description	75
7.2.7.2.1	Reference.....	75
7.2.7.3	Test purpose	75
7.2.7.4	Method of test	75

7.2.7.4.1	Initial conditions	75
7.2.7.4.2	Procedure	75
7.2.7.5	Acceptance criteria	76
7.3	T=1 protocol	76
7.3.1	Character Waiting Time	76
7.3.1.1	Definition and applicability	76
7.3.1.2	Conformance requirement	76
7.3.1.2.0	Description	76
7.3.1.2.1	Reference	76
7.3.1.3	Test purpose	76
7.3.1.4	Method of test	76
7.3.1.4.1	Initial conditions	76
7.3.1.4.2	Procedure	76
7.3.1.5	Acceptance criteria	77
7.3.2	Block Timing	77
7.3.2.1	Definition and applicability	77
7.3.2.2	Conformance requirement	77
7.3.2.2.0	Description	77
7.3.2.2.1	Reference	77
7.3.2.3	Test purpose	77
7.3.2.4	Method of test	78
7.3.2.4.1	Initial conditions	78
7.3.2.4.2	Procedure	78
7.3.2.5	Acceptance criteria	78
7.3.3	Block Waiting Time extension	79
7.3.3.1	Definition and applicability	79
7.3.3.2	Conformance requirement	79
7.3.3.2.0	Description	79
7.3.3.2.1	Reference	79
7.3.3.3	Test purpose	79
7.3.3.4	Method of test	79
7.3.3.4.1	Initial conditions	79
7.3.3.4.2	Procedure	79
7.3.3.5	Acceptance criteria	80
7.3.4	Chaining - Respect of IFSC by Terminal	80
7.3.4.1	Definition and applicability	80
7.3.4.2	Conformance requirement	81
7.3.4.2.0	Description	81
7.3.4.2.1	Reference	81
7.3.4.3	Test purpose	81
7.3.4.4	Method of test	81
7.3.4.4.1	Initial conditions	81
7.3.4.4.2	Procedure	81
7.3.4.5	Acceptance criteria	82
7.3.5	Chaining - IFSD management	82
7.3.5.1	Definition and applicability	82
7.3.5.2	Conformance requirement	83
7.3.5.2.0	Description	83
7.3.5.2.1	Reference	83
7.3.5.3	Test purpose	83
7.3.5.4	Method of test	83
7.3.5.4.1	Initial conditions	83
7.3.5.4.2	Procedure	83
7.3.5.5	Acceptance criteria	83
7.3.6	I-Block error correction	83
7.3.6.1	Definition and applicability	83
7.3.6.2	Conformance requirement	84
7.3.6.2.0	Description	84
7.3.6.2.1	Reference	84
7.3.6.3	Test purpose	84
7.3.6.4	Method of test	84
7.3.6.4.1	Initial conditions	84

7.3.6.4.2	Procedure.....	84
7.3.6.5	Acceptance criteria.....	84
7.3.7	I-Block error detection.....	84
7.3.7.1	Definition and applicability.....	84
7.3.7.2	Conformance requirement.....	84
7.3.7.2.0	Description.....	84
7.3.7.2.1	Reference.....	85
7.3.7.3	Test purpose.....	85
7.3.7.4	Method of test.....	85
7.3.7.4.1	Initial conditions.....	85
7.3.7.4.2	Procedure.....	85
7.3.7.5	Acceptance criteria.....	85
7.3.8	R-Block error handling in non-chaining mode.....	85
7.3.8.1	Definition and applicability.....	85
7.3.8.2	Conformance requirement.....	86
7.3.8.2.0	Description.....	86
7.3.8.2.1	Reference.....	86
7.3.8.3	Test purpose.....	86
7.3.8.4	Method of test.....	86
7.3.8.4.1	Initial conditions.....	86
7.3.8.4.2	Procedure.....	86
7.3.8.5	Acceptance criteria.....	86
7.3.9	R-Block error handling in chaining mode.....	87
7.3.9.1	Definition and applicability.....	87
7.3.9.2	Conformance requirement.....	87
7.3.9.2.0	Description.....	87
7.3.9.2.1	Reference.....	87
7.3.9.3	Test purpose.....	87
7.3.9.4	Method of test.....	87
7.3.9.4.1	Initial conditions.....	87
7.3.9.4.2	Procedure.....	87
7.3.9.5	Acceptance criteria.....	88
7.3.10	Successive errors in both directions.....	88
7.3.10.1	Definition and applicability.....	88
7.3.10.2	Conformance requirement.....	88
7.3.10.2.0	Description.....	88
7.3.10.2.1	Reference.....	88
7.3.10.3	Test purpose.....	88
7.3.10.4	Method of test.....	88
7.3.10.4.1	Initial conditions.....	88
7.3.10.4.2	Procedure.....	88
7.3.10.5	Acceptance criteria.....	89
7.3.11	Chaining - Abortion.....	89
7.3.11.1	Definition and applicability.....	89
7.3.11.2	Conformance requirement.....	89
7.3.11.2.0	Description.....	89
7.3.11.2.1	Reference.....	89
7.3.11.3	Test purpose.....	89
7.3.11.4	Method of test.....	89
7.3.11.4.1	Initial conditions.....	89
7.3.11.4.2	Procedure.....	90
7.3.11.5	Acceptance criteria.....	90
7.3.12	Block repetition and resynchronization.....	90
7.3.12.1	Definition and applicability.....	90
7.3.12.2	Conformance requirement.....	91
7.3.12.2.0	Description.....	91
7.3.12.2.1	Reference.....	91
7.3.12.3	Test purpose.....	91
7.3.12.4	Method of test.....	91
7.3.12.4.1	Initial conditions.....	91
7.3.12.4.2	Procedure.....	91
7.3.12.5	Acceptance criteria.....	92

7.3.13	UICC is unresponsive	92
7.3.13.1	Definition and applicability	92
7.3.13.2	Conformance requirement	92
7.3.13.2.0	Description	92
7.3.13.2.1	Reference	92
7.3.13.3	Test purpose	92
7.3.13.4	Method of test	92
7.3.13.4.1	Initial conditions	92
7.3.13.4.2	Procedure	93
7.3.13.5	Acceptance criteria	93
8	Application dependent procedures	93
8.1	UICC presence detection	93
8.1.1	Definition and applicability	93
8.1.2	Conformance requirement	94
8.1.2.0	Description	94
8.1.2.1	Reference	94
8.1.3	Test purpose	94
8.1.4	Method of test	94
8.1.4.1	Initial conditions	94
8.1.4.2	Procedure	94
8.1.5	Acceptance criteria	94
9	Commands	95
9.1	TERMINAL CAPABILITY	95
9.1.1	Additional interfaces support	95
9.1.1.1	Definition and applicability	95
9.1.1.2	Conformance requirement	95
9.1.1.2.1	Description	95
9.1.1.2.2	Reference	95
9.1.1.3	Test purpose	95
9.1.1.4	Method of test	95
9.1.1.4.1	Initial conditions	95
9.1.1.4.2	Procedure	95
9.1.1.5	Acceptance criteria	96
9.2	SUSPEND UICC	96
9.2.1	Support of the SUSPEND UICC command	96
9.2.1.1	SUSPEND UICC - Nominal Condition	96
9.2.1.1.1	Definition and applicability	96
9.2.1.1.2	Conformance requirement	96
9.2.1.1.3	Test purpose	96
9.2.1.1.4	Method of test	97
9.2.1.1.5	Acceptance criteria	98
9.2.1.2	SUSPEND UICC - Nominal Condition - Events	98
9.2.1.2.1	Definition and applicability	98
9.2.1.2.2	Conformance requirement	98
9.2.1.2.3	Test purpose	99
9.2.1.2.4	Method of test	99
9.2.1.2.5	Acceptance criteria	100
9.2.1.3	SUSPEND UICC - Suspension not supported by the UICC	100
9.2.1.3.1	Definition and applicability	100
9.2.1.3.2	Conformance requirement	100
9.2.1.3.3	Test purpose	101
9.2.1.3.4	Method of test	101
9.2.1.3.5	Acceptance criteria	101
9.2.1.4	SUSPEND UICC - Rejection of the UICC suspension with status word '6985'	101
9.2.1.4.1	Definition and applicability	101
9.2.1.4.2	Conformance requirement	101
9.2.1.4.3	Test purpose	101
9.2.1.4.4	Method of test	102
9.2.1.4.5	Acceptance criteria	102
9.2.1.5	SUSPEND UICC - Rejection of the UICC suspension with status word '9864'	102

9.2.1.5.1	Definition and applicability	102
9.2.1.5.2	Conformance requirement	102
9.2.1.5.3	Test purpose	102
9.2.1.5.4	Method of test.....	103
9.2.1.5.5	Acceptance criteria	103
9.2.1.6	SUSPEND UICC - Rejection of the UICC resume with status word '6982'	103
9.2.1.6.1	Definition and applicability	103
9.2.1.6.2	Conformance requirement	103
9.2.1.6.3	Test purpose	103
9.2.1.6.4	Method of test.....	104
9.2.1.6.5	Acceptance criteria	104
9.2.1.7	SUSPEND UICC - Rejection of the UICC resume with status word '6982' - Events	105
9.2.1.7.1	Definition and applicability	105
9.2.1.7.2	Conformance requirement	105
9.2.1.7.3	Test purpose	105
9.2.1.7.4	Method of test.....	105
9.2.1.7.5	Acceptance criteria	106
9.2.1.8	SUSPEND UICC - Rejection of the UICC resume with status word '6985'	106
9.2.1.8.1	Definition and applicability	106
9.2.1.8.2	Conformance requirement	106
9.2.1.8.3	Test purpose	106
9.2.1.8.4	Method of test.....	106
9.2.1.8.5	Acceptance criteria	107
9.2.1.9	SUSPEND UICC - Rejection of the UICC resume with status word '6985' - Events	107
9.2.1.9.1	Definition and applicability	107
9.2.1.9.2	Conformance requirement	107
9.2.1.9.3	Test purpose	108
9.2.1.9.4	Method of test.....	108
9.2.1.9.5	Acceptance criteria	108
Annex A (normative):	UICC simulator functional requirement	109
A.1	General	109
A.2	Contacts C1, C3, C7	109
A.2.1	Default measurement/setting uncertainties	109
A.2.2	Contact C1	109
A.2.3	Contact C7	110
A.2.4	Contact C3	110
A.3	Definition of timing	110
Annex B (informative):	Change history	111
Annex C (informative):	Core specification version information.....	113
History		114

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<https://ipr.etsi.org/>).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

Foreword

This Technical Specification (TS) has been produced by ETSI Technical Committee Secure Element Technologies (SET).

The contents of the present document are subject to continuing work within TC SET and may change following formal TC SET approval. If TC SET modifies the contents of the present document, it will then be republished by ETSI with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TC SET for information;
 - 2 presented to TC SET for approval;
 - 3 or greater indicates TC SET approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

The present document is part 1 of a multi-part deliverable covering the UICC-Terminal interface; Physical, electrical and logical test specification, as identified below:

Part 1: "Terminal features";

Part 2: "UICC features".

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Introduction

The present document defines the interface tests for the Terminal/UICC interface.

The aim of the present document is to ensure interoperability between an UICC and a Terminal independently of the respective manufacturer, card issuer or operator.

Application specific tests for applications residing on an UICC are specified in ETSI TS 131 121 [4].

1 Scope

The present document specifies the interface test for the Terminal/UICC.

The present document specifies the tests of:

- physical characteristics of the UICC;
- the electrical interface between the UICC and the Terminal;
- the initial communication establishment and the transport protocols;
- the application independent procedures.

2 References

2.1 Normative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

- In the case of a reference to a TC SET document, a non-specific reference implicitly refers to the latest version of that document in the same Release as the present document.

Referenced documents which are not found to be publicly available in the expected location might be found at <http://docbox.etsi.org/Reference>.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are necessary for the application of the present document.

- [1] [ETSI TS 102 221](#): "Smart Cards; UICC-Terminal interface; Physical and logical characteristics".
- [2] [ISO/IEC 7816-3](#): "Identification cards -- Integrated circuit cards -- Part 3: Cards with contacts -- Electrical interface and transmission protocols".
- [3] [ETSI TS 121 111](#): "Universal Mobile Telecommunications System (UMTS); LTE; USIM and IC card requirements (3GPP TS 21.111)".
- [4] [ETSI TS 131 121](#): "Universal Mobile Telecommunications System (UMTS); LTE; UICC-terminal interface; Universal Subscriber Identity Module (USIM) application test specification (3GPP TS 31.121)".
- [5] [ISO/IEC 9646-7](#): "Information technology -- Open Systems Interconnection -- Conformance testing methodology and framework -- Part 7: Implementation Conformance Statements".
- [6] [ETSI TS 102 613](#): "Smart Cards; UICC - Contactless Front-end (CLF) Interface; Physical and data link layer characteristics".
- [7] [ETSI TS 102 223](#): "Smart Cards; Card Application Toolkit (CAT)".

2.2 Informative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

- In the case of a reference to a TC SET document, a non-specific reference implicitly refers to the latest version of that document in the same Release as the present document.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long term validity.

The following referenced documents are not necessary for the application of the present document but they assist the user with regard to a particular subject area.

Not applicable.

3 Definition of terms, symbols, abbreviations and coding conventions

3.1 Terms

For the purposes of the present document, the following terms apply:

3 V technology Smart Card: Smart Card operating at $3\text{ V} \pm 10\%$ and $5\text{ V} \pm 10\%$

1,8 V technology Smart Card: Smart Card operating at $1,8\text{ V} \pm 10\%$ and $3\text{ V} \pm 10\%$

3 V technology Terminal: Terminal operating the Smart Card - Terminal interface at $3\text{ V} \pm 10\%$ and $5\text{ V} \pm 10\%$

1,8 V technology Terminal: Terminal operating the Smart Card - Terminal interface at $1,8\text{ V} \pm 10\%$ and $3\text{ V} \pm 10\%$

access conditions: set of security attributes associated with a file

data object: information coded as TLV objects, i.e. consisting of a Tag, a Length and a Value part

Dedicated File (DF): file containing access conditions and, optionally, Elementary Files (EFs) or other Dedicated Files (DFs)

directory: general term for MF, DF and ADF

Elementary File (EF): file containing access conditions and data and no other files

file: directory or an organized set of bytes or records in the UICC

file identifier: 2 bytes which address a file in the UICC

Master File (MF): unique mandatory file containing access conditions and optionally DFs and/or EFs

plug-in UICC: second format of UICC

soft power off: Terminal ends operation in a graceful way (i.e. without abruptly removing the battery/power)

SWP interface: UICC-CLF interface according to ETSI TS 102 613 [6]

3.2 Symbols

For the purposes of the present document, the following symbols apply:

f	frequency
Fi	Clock rate conversion factor

I	Current
I _{cc}	Current at supply voltage
L _c	Length of Command data sent by the application layer in a case 3 or 4 Command
L _e	Maximum length of data Expected by the application layer in response to a case 2 or 4 Command
L _{uicc}	Exact Length of data available in the UICC to be returned in response to the case 2 or 4 Command received by the UICC
t _F	fall time
t _R	rise time
V _{cc}	Voltage at V _{CC}

3.3 Abbreviations

For the purposes of the present document, the following abbreviations apply:

ACK	ACKnowledge
ADF	Application Dedicated File
AID	Application IDentifier
ATR	Answer To Reset
BGT	Block Guard Time
BWI	Block Waiting Integer
BWT	Block Waiting Time
CLF	ContactLess Frontend
CLK	CLocK
CWI	Character Waiting Integer
CWT	Character Waiting Time
DF	Dedicated File
EDC	Error Detection Code byte
EF	Elementary File
etu	elementary time unit
FCP	File Control Parameters
GND	GrouND
GSM	Global System for Mobile communications
I/O	Input/Output
I-Block	Information-Block
ID	IDentifier
IEC	International Electrotechnical Commission
IFSC	Information Field Size for the UICC
IFSD	Information Field Size for the Terminal
INS	INstruction
ISO	International Organization for Standardization
LEN	LENgth
LSB	Least Significant Bit
MF	Master File
MSB	Most Significant Bit
N/A	Not Applicable
NAD	Node ADdress byte
PCB	Protocol Control Byte
PIN	Personal Identification Number
PPS	Protocol and Parameter Selection
R-Block	Receive-ready Block
RFU	Reserved for Future Use
RST	Reset
S-Block	Supervisory-Block
SFI	Short (elementary) File Identifier
SWP	Single Wire Protocol
TBD	To Be Defined
TE	Terminal Equipment
TLV	Tag Length Value
UE	User Equipment
USIM	Universal Subscriber Identity Module

V _{CC}	Power supply input
WI	Waiting time Integer
WTX	Waiting Time eXtension
WWT	Work Waiting Time

3.4 Coding conventions

For the purposes of the present document, the following coding conventions apply.

All lengths are presented in bytes, unless otherwise stated. Each byte is represented by bits b8 to b1, where b8 is the Most Significant Bit (MSB) and b1 is the Least Significant Bit (LSB). In each representation, the leftmost bit is the MSB.

In the UICC, all bytes specified as RFU is to be set to '00' and all bits specified as RFU are to be set to 0. If the GSM and/or USIM application exists on a UICC or is built on a generic telecommunications card, then other values may apply for the non- GSM or non-USIM applications. The values will be defined in the appropriate specifications for such cards and applications. These bytes and bits are not to be interpreted by a Terminal in a GSM or 3G session.

The coding of all data objects in the present document is according to ETSI TS 102 221 [1]. All data objects are BER-TLV except if otherwise defined.

3.5 Applicability

3.5.1 Applicability of the present document

This present test specification applies to terminal equipment that supports UICC according to ETSI TS 102 221 [1].

3.5.2 Applicability of the individual test cases

Table A.1 lists the optional features for which the supplier of the implementation states the support.

3.5.3 Applicability to terminal equipment

The applicability to terminal equipment specified in table B.1 of the present document applies, unless otherwise specified.

3.6 Definitions

3.6.1 Format of table of the table of optional features

The columns in table A.1 have the following meaning:

Column	Meaning
Option:	The optional feature supported or not by the implementation.
Status:	See clause 3.6.3 'Status and Notations'.
Support:	The support columns are to be filled in by the supplier of the implementation. The following common notations, defined in ISO/IEC 9646-7 [5], are used for the support column in table A.1: Y or y supported by the implementation. N or n not supported by the implementation. N/A, n/a or - no answer required (allowed only if the status is N/A, directly or after evaluation of a conditional status).
Mnemonic:	The mnemonic column contains mnemonic identifiers for each item.

3.6.2 Format of the applicability table

The applicability of every test in table B.1 is formally expressed by the use of Boolean expression defined in the following clause.

The columns in table B.1 have the following meaning:

Column	Meaning
Test case:	The "Test case" column gives a reference to the test case number(s) detailed in the present document and required to validate the implementation of the corresponding item in the "Description" column.
Description:	In the "Description" column a short non-exhaustive description of the requirement is found.
Release:	The "Release" column gives the Release applicable and onwards, for the item in the "Description" column.
Rel x TE:	For a given Release, the corresponding "Rel X Terminal" column lists the tests required for a Terminal to be declared compliant to this Release.
Support:	The "Support" column is blank in the proforma, and is to be completed by the manufacturer in respect of each particular requirement to indicate the choices, which have been made in the implementation.

3.6.3 Status and Notations

The "Release X Terminal" columns show the status of the entries as follows:

The following notations, defined in ISO/IEC 9646-7 [5], are used for the status column:

M	mandatory - the capability is required to be supported.
O	optional - the capability may be supported or not.
N/A	not applicable - in the given context, it is impossible to use the capability.
X	prohibited (excluded) - there is a requirement not to use this capability in the given context.
O.i	qualified optional - for mutually exclusive or selectable options from a set. "i" is an integer which identifies an unique group of related optional items and the logic of their selection which is defined immediately following the table.
Ci	conditional - the requirement on the capability ("M", "O", "X" or "N/A") depends on the support of other optional or conditional items. "i" is an integer identifying a unique conditional status expression which is defined immediately following the table. For nested conditional expressions, the syntax "IF ... THEN (IF ... THEN ... ELSE...) ELSE ..." is to be used to avoid ambiguities.

References to items

For each possible item answer (answer in the support column) there exists a unique reference, used, for example, in the conditional expressions. It is defined as the table identifier, followed by a solidus character "/", followed by the item number in the table. If there is more than one support column in a table, the columns are to be discriminated by letters (a, b, etc.), respectively.

EXAMPLE: A.1/4 is the reference to the answer of item 4 in table A.1.

3.7 Table of optional features

Table A.1: Options

Item	Option	Status	Support	Mnemonic
1	Void	O		Void
2	Void	O		Void
3	Class A	O		O_CLASS_A
4	Class B	O		O_CLASS_B
5	Class C	O		O_CLASS_C
6	Compliant to ETSI TS 121 111 [3]	O		O_COMP_121_111
7	Low impedance buffer	O		O_LIB
8	SWP interface	O		O_SWP
9	Support of SUSPEND UICC	O		O_SUSPEND_UICC
10	Terminal supports keypad	C001		O_NO_TYPE_NK
C001	If feature is implemented according to Rel-8 or later then O, else M.			
NOTE:	The DUT manufacturer shall provide sufficient information for how to cause the terminal to suspend the UICC and to resume the UICC. This could be active (e.g. a user action) or automatic (e.g. a timeout), and could involve suitable configuration of the Terminal.			

3.8 Applicability table

Table B.1a: Applicability of tests (Rel-99 to Rel-11)

Test case	Description	Release	R99 TE	Rel-4 TE	Rel-5 TE	Rel-6 TE	Rel-7 TE	Rel-8 TE	Rel-9 TE	Rel-10 TE	Rel-11 TE	Support
4.1	Contact pressure	R99	M	M	M	M	M	M	M	M	M	
4.2	Curvature of the contacting elements	R99	M	M	M	M	M	M	M	M	M	
5.1.1	Phase preceding Terminal power on	R99	M	M	M	M	M	M	M	M	M	
5.1.2.1	Phase during UICC power on: 3 V - 5 V	R99	C001	C001	C001	C001	C001	C001	C001	C001	C001	
5.1.2.2	Phase during UICC power on: 1,8 V - 3 V	R99	C002	C002	C002	C002	C002	C002	C002	C002	C002	
5.1.3.1	Phase during Terminal power off: 3 V - 5 V	R99	C001	C001	C001	C001	C001	C001	C001	C001	C001	
5.1.3.2	Phase during Terminal power off: 1,8 V - 3 V	R99	C002	C002	C002	C002	C002	C002	C002	C002	C002	
5.1.4	Warm reset timing	R99	M	M	M	M	M	M	M	M	M	
5.1.5.1	Reaction of 3 V technology Terminals on type recognition of 3 V technology UICCs	R99	C001	C001	C001	C001	C001	C001	C001	C001	C001	
5.1.5.2	Reaction of 3 V technology Terminals on type recognition of 1,8 V technology UICCs	R99	C001	C001	C001	C001	C001	C001	C001	C001	C001	
5.1.5.3	Reaction of 1,8 V technology Terminals on type recognition of 1,8 V technology UICCs	R99	C002	C002	C002	C002	C002	C002	C002	C001	C001	
5.1.5.4	Reaction of 1,8 V technology Terminals on type recognition of 3 V technology UICCs	R99	C002	C002	C002	C002	C002	C002	C002	C002	C002	
5.1.5.6.1	Reaction of Terminals receiving no ATR, 3 V - 5 V	R99	C001	C001	C001	C001	C001	C001	C001	C001	C001	
5.1.5.6.2	Reaction of Terminals receiving no ATR, 1,8 V - 3 V	R99	C002	C002	C002	C002	C002	C002	C002	C002	C002	
5.2.2.1	Electrical tests on contact C1, Test 1: 3 V - 5 V	R99	C001	C001	C001	C001	C001	C001	C001	C001	C001	
5.2.2.2	Electrical tests on contact C1, Test 2: 3 V - 5 V	R99	C001	C001	C001	C001	C001	C001	C001	C001	C001	
5.2.2.3	Electrical tests on contact C1, Test 1: 1,8 V - 3 V	R99	C002	C002	C002	C002	C002	C002	C002	C002	C002	
5.2.2.4	Electrical tests on contact C1, Test 2: 1,8 V - 3 V	R99	C002	C002	C002	C002	C002	C002	C002	C002	C002	
5.2.3.1	Electrical tests on contact C2: 3 V - 5 V	R99	C001	C001	C001	C001	C001	C001	C001	C001	C001	
5.2.3.2	Electrical tests on contact C2: 1,8 V - 3 V	R99	C002	C002	C002	C002	C002	C002	C002	C002	C002	
5.2.4.1	Electrical tests on contact C3: 3 V - 5 V	R99	C001	C001	C001	C001	C001	C001	C001	C001	C001	
5.2.4.2	Electrical tests on contact C3: 1,8 V - 3 V	R99	C002	C002	C002	C002	C002	C002	C002	C002	C002	
5.2.5.1	Electrical tests on contact C7, Test 1: 3 V - 5 V	R99	C001	C001	C001	C001	C001	C001	C001	C001	C001	
5.2.5.2	Electrical tests on contact C7, Test 2: 3 V - 5 V	Rel-6	N/A	N/A	N/A	C001 AND C007						
5.2.5.3	Electrical tests on contact C7, Test 1: 1,8 V - 3 V	R99	C002	C002	C002	C002	C002	C002	C002	C002	C002	
5.2.5.4	Electrical tests on contact C7, Test 2: 1,8 V - 3 V	Rel-6	N/A	N/A	N/A	C002 AND C007						
6.1	ATR characters	R99	M	M	M	M	M	M	M	M	M	
6.2	Clock stop mode with 1,8 V technology UICC	R99	C003	C003	C003	C003	C003	C003	C003	C003	C003	
6.3	Clock stop mode with 3 V technology UICC	R99	C004	C004	C004	C004	C004	C004	C004	C004	C004	
6.5	Speed enhancement	R99	M	M	M	M	M	M	M	M	M	

Test case	Description	Release	R99 TE	Rel-4 TE	Rel-5 TE	Rel-6 TE	Rel-7 TE	Rel-8 TE	Rel-9 TE	Rel-10 TE	Rel-11 TE	Support
7.1.1	Bit/character duration during the transmission from the Terminal to the UICC	R99	M	M	M	M	M	M	M	M	M	
7.1.2	Bit/character duration during the transmission from the UICC to the Terminal	R99	M	M	M	M	M	M	M	M	M	
7.2.1	Timing	R99	M	M	M	M	M	M	M	M	M	
7.2.2	Command processing, ACK, NACK, NULL procedure bytes	R99	M	M	M	M	M	M	M	M	M	
7.2.3	Case 2 command, use of procedure bytes '61xx' and '6Cxx'	R99	M	M	M	M	M	M	M	M	M	
7.2.4	Case 4 command, use of procedure bytes '61xx'	R99	M	M	M	M	M	M	M	M	M	
7.2.5	Command processing, warning and error status bytes	R99	M	M	M	M	M	M	M	M	M	
7.2.6	Error correction	R99	M	M	M	M	M	M	M	M	M	
7.2.7	Error detection	R99	M	M	M	M	M	M	M	M	M	
7.3.1	Character Waiting Time	R99	M	M	M	M	M	M	M	M	M	
7.3.2	Block Timing	R99	M	M	M	M	M	M	M	M	M	
7.3.3	Block Waiting Time extension	R99	M	M	M	M	M	M	M	M	M	
7.3.4	Chaining - Respect of IFSC by Terminal	R99	M	M	M	M	M	M	M	M	M	
7.3.5	Chaining - IFSD management	R99	M	M	M	M	M	M	M	M	M	
7.3.6	I-Block error correction	R99	M	M	M	M	M	M	M	M	M	
7.3.7	I-Block error detection	R99	M	M	M	M	M	M	M	M	M	
7.3.8	R-Block error handling in non-chaining mode	R99	M	M	M	M	M	M	M	M	M	
7.3.9	R-Block error handling in chaining mode	R99	M	M	M	M	M	M	M	M	M	
7.3.10	Successive errors in both directions	R99	M	M	M	M	M	M	M	M	M	
7.3.11	Chaining - Abortion	R99	M	M	M	M	M	M	M	M	M	
7.3.12	Block repetition and resynchronization	R99	M	M	M	M	M	M	M	M	M	
7.3.13	UICC is unresponsive	R99	M	M	M	M	M	M	M	M	M	
8.1	UICC presence detection	R99	M	M	N/A	N/A	N/A	N/A	N/A	N/A	N/A	
9.1.1	TERMINAL CAPABILITY - Additional interfaces support	Rel-7	N/A	N/A	N/A	N/A	N/A	N/A	C008	C008	C008	

Table B.1b: Applicability of tests (from release 12)

Test case	Description	Release			Rel-12 TE	Rel-13 TE	Rel-14 TE	Rel-15 TE	Rel-16 TE	Support
4.1	Contact pressure	R99			M	M	M	M	M	
4.2	Curvature of the contacting elements	R99			M	M	M	M	M	
5.1.1	Phase preceding Terminal power on	R99			M	M	M	M	M	
5.1.2.1	Phase during UICC power on: 3 V - 5 V	R99			C001	C009	C009	C009	C009	
5.1.2.2	Phase during UICC power on: 1,8 V - 3 V	R99			C002	C010	C010	C010	C010	
5.1.3.1	Phase during Terminal power off: 3 V - 5 V	R99			C001	C009	C009	C009	C009	
5.1.3.2	Phase during Terminal power off: 1,8 V - 3 V	R99			C002	C010	C010	C010	C010	
5.1.4	Warm reset timing	R99			M	M	M	M	M	
5.1.5.1	Reaction of 3 V technology Terminals on type recognition of 3 V technology UICCs	R99			C001	C001	C001	C001	C001	

Test case	Description	Release			Rel-12 TE	Rel-13 TE	Rel-14 TE	Rel-15 TE	Rel-16 TE	Support
5.1.5.2	Reaction of 3 V technology Terminals on type recognition of 1,8 V technology UICCs	R99			C001	C001	C001	C001	C001	
5.1.5.3	Reaction of 1,8 V technology Terminals on type recognition of 1,8 V technology UICCs	R99			C002	C002	C002	C002	C002	
5.1.5.4	Reaction of 1,8 V technology Terminals on type recognition of 3 V technology UICCs	R99			C002	C002	C002	C002	C002	
5.1.5.6.1	Reaction of Terminals receiving no ATR, 3 V - 5 V	R99			C001	C001	C001	C001	C001	
5.1.5.6.2	Reaction of Terminals receiving no ATR, 1,8 V - 3 V	R99			C002	C002	C002	C002	C002	
5.1.5.9	Reaction of Terminals not supporting any voltage class indicated in the ATR	Rel-14			N/A	N/A	M	M	M	
5.2.2.1	Electrical tests on contact C1, Test 1: 3 V - 5 V	R99			C001	C009	C009	C009	C009	
5.2.2.2	Electrical tests on contact C1, Test 2: 3 V - 5 V	R99			C001	C009	C009	C009	C009	
5.2.2.3	Electrical tests on contact C1, Test 1: 1,8 V - 3 V	R99			C002	C010	C010	C010	C010	
5.2.2.4	Electrical tests on contact C1, Test 2: 1,8 V - 3 V	R99			C002	C010	C010	C010	C010	
5.2.3.1	Electrical tests on contact C2: 3 V - 5 V	R99			C001	C009	C009	C009	C009	
5.2.3.2	Electrical tests on contact C2: 1,8 V - 3 V	R99			C002	C010	C010	C010	C010	
5.2.4.1	Electrical tests on contact C3: 3 V - 5 V	R99			C001	C009	C009	C009	C009	
5.2.4.2	Electrical tests on contact C3: 1,8 V - 3 V	R99			C002	C010	C010	C010	C010	
5.2.5.1	Electrical tests on contact C7, Test 1: 3 V - 5 V	R99			C001	C009	C009	C009	C009	
5.2.5.2	Electrical tests on contact C7, Test 2: 3 V - 5 V	Rel-6			C001 AND C007	C009 AND C007	C009 AND C007	C009 AND C007	C009 AND C007	
5.2.5.3	Electrical tests on contact C7, Test 1: 1,8 V - 3 V	R99			C002	C010	C010	C010	C010	
5.2.5.4	Electrical tests on contact C7, Test 2: 1,8 V - 3 V	Rel-6			C002 AND C007	C010 AND C007	C010 AND C007	C010 AND C007	C010 AND C007	
6.1	ATR characters	R99			M	M	M	M	M	
6.2	Clock stop mode with 1,8 V technology UICC	R99			C003	C003	C003	C003	C003	
6.3	Clock stop mode with 3 V technology UICC	R99			C004	C004	C004	C004	C004	
6.5	Speed enhancement	R99			M	M	M	M	M	
7.1.1	Bit/character duration during the transmission from the Terminal to the UICC	R99			M	M	M	M	M	
7.1.2	Bit/character duration during the transmission from the UICC to the Terminal	R99			M	M	M	M	M	
7.2.1	Timing	R99			M	M	M	M	M	
7.2.2	Command processing, ACK, NACK, NULL procedure bytes	R99			M	M	M	M	M	
7.2.3	Case 2 command, use of procedure bytes '61xx' and '6Cxx'	R99			M	M	M	M	M	
7.2.4	Case 4 command, use of procedure bytes '61xx'	R99			M	M	M	M	M	
7.2.5	Command processing, warning and error status bytes	R99			M	M	M	M	M	
7.2.6	Error correction	R99			M	M	M	M	M	
7.2.7	Error detection	R99			M	M	M	M	M	
7.3.1	Character Waiting Time	R99			M	M	M	M	M	
7.3.2	Block Timing	R99			M	M	M	M	M	
7.3.3	Block Waiting Time extension	R99			M	M	M	M	M	

Test case	Description	Release			Rel-12 TE	Rel-13 TE	Rel-14 TE	Rel-15 TE	Rel-16 TE	Support
7.3.4	Chaining - Respect of IFSC by Terminal	R99			M	M	M	M	M	
7.3.5	Chaining - IFSD management	R99			M	M	M	M	M	
7.3.6	I-Block error correction	R99			M	M	M	M	M	
7.3.7	I-Block error detection	R99			M	M	M	M	M	
7.3.8	R-Block error handling in non-chaining mode	R99			M	M	M	M	M	
7.3.9	R-Block error handling in chaining mode	R99			M	M	M	M	M	
7.3.10	Successive errors in both directions	R99			M	M	M	M	M	
7.3.11	Chaining - Abortion	R99			M	M	M	M	M	
7.3.12	Block repetition and resynchronization	R99			M	M	M	M	M	
7.3.13	UICC is unresponsive	R99			M	M	M	M	M	
8.1	UICC presence detection	R99			N/A	N/A	N/A	N/A	N/A	
9.1.1	TERMINAL CAPABILITY - Additional interfaces support	Rel-7			C008	C008	C008	C008	C008	
9.2.1.1	SUSPEND UICC - Nominal Condition	Rel-14			N/A	N/A	C011	C011	C011	
9.2.1.2	SUSPEND UICC - Nominal Condition - Events	Rel-14			N/A	N/A	C012	C012	C012	
9.2.1.3	SUSPEND UICC - Suspension not supported by the UICC	Rel-14			N/A	N/A	C011	C011	C011	
9.2.1.4	SUSPEND UICC - Rejection of the UICC suspension with status word '6985	Rel-14			N/A	N/A	C011	C011	C011	
9.2.1.5	SUSPEND UICC - Rejection of the UICC suspension with status word '9864'	Rel-14			N/A	N/A	C011	C011	C011	
9.2.1.6	SUSPEND UICC - Rejection of the UICC resume with status word '6982'	Rel-14			N/A	N/A	C011	C011	C011	
9.2.1.7	SUSPEND UICC - Rejection of the UICC resume with status word '6982' - Events	Rel-14			N/A	N/A	C012	C012	C012	
9.2.1.8	SUSPEND UICC - Rejection of the UICC resume with status word '6985'	Rel-14			N/A	N/A	C011	C011	C011	
9.2.1.9	SUSPEND UICC - Rejection of the UICC resume with status word '6985' - Events	Rel-14			N/A	N/A	C012	C012	C012	

Table B.1c: Applicability of tests (conditions and options list)

C001	IF (O_CLASS_A AND O_CLASS_B AND NOT O_COMP_121_111) THEN M ELSE N/A.
C002	IF (O_CLASS_B AND O_CLASS_C) THEN M ELSE N/A.
C003	IF O_CLASS_C THEN M ELSE N/A.
C004	IF O_CLASS_B THEN M ELSE N/A.
C005	Void.
C006	Void.
C007	IF O_LIB THEN M ELSE N/A.
C008	IF O_SWP THEN M ELSE N/A.
C009	IF ((O_CLASS_B AND NOT O_CLASS_A AND NOT O_CLASS_C) OR (O_CLASS_A AND O_CLASS_B AND NOT O_COMP_121_111)) THEN M ELSE N/A.
C010	IF (O_CLASS_C AND NOT O_CLASS_A AND NOT O_CLASS_B) OR (O_CLASS_B AND O_CLASS_C)) THEN M ELSE N/A.
C011	IF (O_SUSPEND_UICC AND NOT O_SWP) THEN M ELSE N/A.
C012	IF (O_SUSPEND_UICC AND NOT O_SWP AND O_NO_TYPE_NK) THEN M ELSE N/A.

4 Physical characteristic tests

4.1 Contact pressure

4.1.1 Definition and applicability

The contact pressure shall be large enough to ensure reliable and continuous contact (e.g. to overcome oxidization and to prevent interruption caused by vibration).

For applicability of this test case see clause 3.8.

4.1.2 Conformance requirement

4.1.2.0 Description

Under no circumstances shall the contact force exceed 0,5 N per contact.

4.1.2.1 Reference

ETSI TS 102 221 [1], clause 4.5.4.

4.1.3 Test purpose

To verify that the contact pressure of each contacting element is not greater than 0,5 N when each of the following types of card is used:

- 1) Unembossed.
- 2) Embossed on the contact side.

NOTE: Only type 1) applies to the plug-in UICC.

4.1.4 Method of test

4.1.4.1 Initial conditions

The Terminal manufacturers shall provide, if possible, a separate card reader (mechanical components) to allow measurements.

4.1.4.2 Procedure

The pressure of each contacting element is measured.

4.1.5 Acceptance criteria

The contact force shall not exceed 0,5 N per contact.

4.2 Curvature of the contacting elements

4.2.1 Definition and applicability

The contact pressure shall be large enough to ensure reliable and continuous contact (e.g. to overcome oxidization and to prevent interruption caused by vibration).

For applicability of this test case see clause 3.8.

4.2.2 Conformance requirement

4.2.2.0 Description

The radius of any curvature of the contacting elements shall be greater than or equal to 0,8 mm over the contact area.

4.2.2.1 Reference

ETSI TS 102 221 [1], clause 4.5.4.

4.2.3 Test purpose

To verify that the radius of curvature of the contacting elements is greater than or equal to 0,8 mm over the contact area.

4.2.4 Method of test

4.2.4.1 Initial conditions

The Terminal manufacturers shall provide, if possible, a separate card reader (mechanical components) to allow measurements.

4.2.4.2 Procedure

The radius of curvature of the contacting elements is measured on both axes.

4.2.5 Acceptance criteria

The radius of any curvature of the contacting elements shall be greater than or equal to 0,8 mm over the contact area.

5 Electrical characteristic tests

5.1 Test of the power transition phases

5.1.1 Phase preceding Terminal power on

5.1.1.1 Definition and applicability

When the mobile equipment is switched off, the contacts of the UICC-Terminal interface remain in an inactive state in order to prevent any damage to the UICC.

For applicability of this test case see clause 3.8.

5.1.1.2 Conformance requirement

The residual voltage across the contacts of the UICC-Terminal interface (C1, C2, C3, C7) shall not exceed $\pm 0,4$ V referenced to GND.

5.1.1.3 Reference

ETSI TS 102 221 [1], clause 4.4.3.

5.1.1.4 Test purpose

To verify that the residual voltage across the contacts of the UICC-Terminal interface (C1, C2, C3, C7) is not greater than $\pm 0,4$ V referenced to GND.

5.1.1.5 Method of test

5.1.1.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The contact C1 (V_{CC}) of the UICC-Terminal interface shall be loaded with an impedance of 10 k Ω .

The other contacts (C2, C3, C7) shall be loaded with an impedance of 50 k Ω .

5.1.1.5.2 Procedure

The residual voltage on each contact shall be measured.

5.1.1.6 Acceptance criteria

The residual voltage on each contact shall not exceed $\pm 0,4$ V referenced to GND.

5.1.2 Phase during UICC power on

5.1.2.1 Phase during UICC power on: 3 V - 5 V

5.1.2.1.1 Definition and applicability

When the user equipment is switched on or when the UICC-Terminal interface is being activated after supply voltage switching, the contacts shall be activated in a defined sequence in order to prevent any damage to the UICC.

A 3 V technology Terminal may switch from 3 V to 5 V after it has analysed the ATR and identified the UICC voltage class by deactivating the UICC and activating it at the new supply voltage.

For applicability of this test case see clause 3.8.

5.1.2.1.2 Conformance requirement

- 1) When the UE is soft powered on, the contacts of the UICC-Terminal interface shall be activated to 3 V mode in the following order:
 - V_{CC} at state H and stable;
 - CLK stable;
 - RST at state L for at least 400 clock cycles after the clock signal is applied to CLK;
 - I/O at state Z within 200 clock cycles after the clock signal is applied to CLK.
- 2) For a 3 V Technology Terminal: When the UICC - Terminal interface is being activated after the 3 V/5 V switching the contacts shall be activated to 5 V mode in the order given in 1).

5.1.2.1.3 Reference

ETSI TS 102 221 [1], clause 4.5.2.1.

5.1.2.1.4 Test purpose

To verify that the contacts of the UICC-Terminal interface are activated in the correct order, as described in the conformance requirement.

5.1.2.1.5 Method of test

5.1.2.1.5.1 Initial condition

The Terminal shall be connected to an UICC-Terminal simulator.

5.1.2.1.5.2 Procedure

To test the requirements 1), the UE shall be soft powered on.

For a 3 V Technology Terminal: To test the requirement 2), the Terminal shall be caused to switch the voltage on the UICC-Terminal interface.

The verification of the activation procedure shall be started with the first contact leaving the inactive state. The UICC-Terminal interface shall be monitored until it is fully activated.

5.1.2.1.6 Acceptance criteria

The contacts of the UICC-Terminal interface shall be activated in the correct order, as described in the conformance requirement.

5.1.2.2 Phase during UICC power on: 1,8 V - 3 V

5.1.2.2.1 Definition and applicability

When the user equipment is switched on or when the UICC-Terminal interface is being activated after supply voltage switching, the contacts shall be activated in a defined sequence in order to prevent any damage to the UICC.

A 1,8 V technology Terminal may switch from 1,8 V to 3 V after it has analysed the ATR and identified the UICC voltage class by deactivating the UICC and activating it at the new supply voltage.

For applicability of this test case see clause 3.8.

5.1.2.2.2 Conformance requirement

- 1) When the UE is soft powered on, the contacts of the UICC-Terminal interface shall be activated to 1,8 V mode in the following order:
 - V_{CC} at state H and stable;
 - CLK stable;
 - RST at state L for at least 400 clock cycles after the clock signal is applied to CLK;
 - I/O at state Z within 200 clock cycles after the clock signal is applied to CLK.
- 2) For a 1,8 V Technology Terminal: When the UICC - Terminal interface is being activated after the 1,8 V/3 V switching the contacts shall be activated to 3 V mode in the order given in 1).

5.1.2.2.3 Reference

ETSI TS 102 221 [1], clause 4.5.2.1.

5.1.2.2.4 Test purpose

To verify that the contacts of the UICC-Terminal interface are activated in the correct order, as described in the conformance requirement.

5.1.2.2.5 Method of test

5.1.2.2.5.1 Initial condition

The Terminal shall be connected to an UICC-Terminal simulator.

5.1.2.2.5.2 Procedure

To test the requirement 1), the UE shall be soft powered on.

For a 1,8 V Technology Terminal: To test the requirement 2), the Terminal shall be caused to switch the voltage on the UICC-Terminal interface.

The verification of the activation procedure shall be started with the first contact leaving the inactive state. The UICC-Terminal interface shall be monitored until it is fully activated.

5.1.2.2.6 Acceptance criteria

The contacts of the UICC-Terminal interface shall be activated in the correct order, as described in the conformance requirement.

5.1.3 Phase during Terminal power off

5.1.3.1 Phase during Terminal power off: 3 V - 5 V

5.1.3.1.1 Definition and applicability

When the user equipment is soft powered off or when the UICC-Terminal interface is being deactivated for 3 V/5 V switching, the contacts shall be deactivated in a defined sequence in order to prevent any damage to the UICC.

NOTE: If during UE operation the UICC is physically removed it is impractical to ensure correct sequencing of deactivation and the possible damage to the UICC cannot be safeguarded by a type approval test. Furthermore, in this situation the integrity of the UICC data is not guaranteed.

For applicability of this test case see clause 3.8.

5.1.3.1.2 Conformance requirement

- 1) Depending on the state of the clock at the time of deactivation, the contacts of the UICC-Terminal shall be deactivated in one of two ways.

If the clock is running, the contacts of the UICC-Terminal interface shall be deactivated in the following order:

- RST at low level;
- Clock stopped at low level;
- I/O at status A;
- V_{CC} inactive.

If the clock is stopped and is not restarted, the Terminal is allowed to deactivate all the contacts in any order, provided that all signals reach low level before V_{CC} leaves high level.

- 2) For a 3 V Technology Terminal: When the UICC - Terminal interface is deactivated for 3 V/5 V switching, the contacts shall be deactivated as given in 1).

5.1.3.1.3 Reference

ETSI TS 102 221 [1], clause 4.5.2.1.

5.1.3.1.4 Test purpose

To verify that, depending on the state of the clock (running or stopped), the contacts of the UICC-Terminal interface become deactivated in the correct order, as given in the conformance requirement.

5.1.3.1.5 Method of test

5.1.3.1.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UICC characteristics of the directories (see ETSI TS 102 221 [1], clause 11.1.1.4.6.1) shall indicate that clock stop is allowed.

5.1.3.1.5.2 Procedure

To test the requirements 1), the UE shall be soft powered off.

For a 3 V Technology Terminal: To test the requirement 2), the Terminal shall be caused to switch the voltage on the UICC-Terminal interface.

The UICC-Terminal interface shall be monitored until it is fully deactivated.

5.1.3.1.6 Acceptance criteria

The contacts of the UICC-Terminal interface shall be deactivated in the correct order, as given in the conformance requirements.

5.1.3.2 Phase during Terminal power off: 1,8 V - 3 V

5.1.3.2.1 Definition and applicability

When the user equipment is soft powered off or when the UICC-Terminal interface is being deactivated for 1,8 V/3 V switching, the contacts shall be deactivated in a defined sequence in order to prevent any damage to the UICC.

NOTE: If during UE operation the UICC is physically removed it is impractical to ensure correct sequencing of deactivation and the possible damage to the UICC cannot be safeguarded by a type approval test. Furthermore, in this situation the integrity of the UICC data is not guaranteed.

For applicability of this test case see clause 3.8.

5.1.3.2.2 Conformance requirement

- 1) Depending on the state of the clock at the time of deactivation, the contacts of the UICC-Terminal shall be deactivated in one of two ways.

If the clock is running, the contacts of the UICC-Terminal interface shall be deactivated in the following order:

- RST at low level;
- Clock stopped at low level;
- I/O at status A;
- V_{CC} inactive.

If the clock is stopped and is not restarted, the Terminal is allowed to deactivate all the contacts in any order, provided that all signals reach low level before V_{CC} leaves high level.

- 2) For a 1,8 V Technology Terminal: When the UICC-Terminal interface is deactivated for 1,8 V/3 V switching, the contacts shall be deactivated as given in 1).

5.1.3.2.3 Reference

ETSI TS 102 221 [1], clause 4.4.2.

5.1.3.2.4 Test purpose

To verify that, depending on the state of the clock (running or stopped), the contacts of the UICC-Terminal interface become deactivated in the correct order, as given in the conformance requirement.

5.1.3.2.5 Method of test

5.1.3.2.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UICC characteristics of the directories (see ETSI TS 102 221 [1], clause 11.1.1.4.6.1) shall indicate that clock stop is allowed.

5.1.3.2.5.2 Procedure

To test the requirement 1), the UE shall be soft powered off.

For a 1,8 V Technology Terminal: To test the requirement 2), the Terminal shall be caused to switch the voltage on the UICC-Terminal interface.

The UICC-Terminal interface shall be monitored until it is fully deactivated.

5.1.3.2.6 Acceptance criteria

The contacts of the UICC-Terminal interface shall be deactivated in the correct order, as given in the conformance requirements.

5.1.4 Warm reset timing

5.1.4.1 Definition and applicability

The warm reset is performed according to clause 5.3.3 of ISO/IEC 7816-3 [2] and the UICC shall enter either the negotiable or the specific mode.

For applicability of this test case see clause 3.8.

5.1.4.2 Conformance requirement

5.1.4.2.0 Description

- 1) V_{CC} at state H and stable.
- 2) CLK stable.
- 3) RST at state H.
- 4) RST at state L for 400 clock cycles.
- 5) RST at state H for at least 400 clock cycles.
- 6) RST at state H for 40 000 clock cycles before deactivation if no answer is received.

5.1.4.2.1 Reference

ETSI TS 102 221 [1], clause 6.6.

ISO/IEC 7816-3 [2], clause 5.3.3.

5.1.4.3 Test purpose

To verify that the contacts of the UICC-Terminal interface are activated in the correct order, as described in the conformance requirement.

5.1.4.4 Method of test

5.1.4.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator.

5.1.4.4.2 Procedure

- a) The Terminal shall be made to initiate a warm reset (TBD).
- b) The UICC simulator shall send a valid ATR:
 - b-1) 400 clock cycles after RST is set to state H.
 - b-2) 39 990 clock cycles after RST is set to state H. The contacts of the UICC-Terminal interface shall be monitored during the warm reset sequence.

5.1.4.5 Acceptance criteria

The Terminal shall perform a warm reset as described in the conformance requirement.

In steps b-1) and b-2) the Terminal shall read the answer to the warm reset and work with the UICC.

5.1.5 UICC type recognition and voltage switching

5.1.5.1 Reaction of 3 V technology Terminals on type recognition of 3 V technology UICCs

5.1.5.1.1 Definition and applicability

When a 3 V technology Terminal detects a 3 V technology UICC during the ATR analysis the Terminal may either switch to 5 V operation or stay in 3 V operation.

For applicability of this test case see clause 3.8.

5.1.5.1.2 Conformance requirement

- 1) A 3 V technology Terminal shall initially activate the UICC with 3 V (i.e. the first activation of a card session).
- 2) The Terminal shall analyse the ATR and identify the voltage class supported by the UICC.
- 3) If a 3 V technology Terminal identifies a 3 V technology UICC the Terminal may switch to 5 V operation. Switching from 3 V to 5 V shall only be performed by deactivating the UICC and activating it with 5 V supply voltage immediately after the analysis of the ATR without issuing any commands.

5.1.5.1.3 Reference

ETSI TS 102 221 [1], clause 6.2.

5.1.5.1.4 Test purpose

- 1) To verify that a 3 V technology Terminal initially activates the UICC with 3 V.
- 2) To verify that a 3 V technology Terminal correctly identifies the voltage class.
- 3) To verify that a 3 V technology Terminal deactivates the UICC-Terminal interface immediately after the analysis of the ATR without issuing any command and activates it with 5 V supply voltage or proceeds with the 3 V operation during the whole card session without switching to 5 V supply voltage.

5.1.5.1.5 Method of test

5.1.5.1.5.1 Initial condition

The Terminal shall be connected to an UICC simulator simulating a 3 V technology UICC with nominal test conditions (see clause 5.2.1). All elementary files shall be coded as default.

The Terminal shall be powered on.

5.1.5.1.5.2 Procedure

The UICC simulator shall send an ATR indicating a 3 V technology UICC.

The UICC-Terminal interface shall be monitored for at least 1 minute until the UE is switched off.

5.1.5.1.6 Acceptance criteria

- 1) The initial activation of the UICC-Terminal interface shall be performed with 3 V supply voltage.
- 2) The Terminal shall react in one of the following ways:
 - a) The Terminal deactivates the UICC-Terminal interface immediately after the receipt of the ATR from the UICC and activates it with 5 V supply voltage.
 - b) The Terminal proceeds with the card session without switching to another supply voltage.

5.1.5.2 Reaction of 3 V technology Terminals on type recognition of 1,8 V technology UICCs

5.1.5.2.1 Definition and applicability

When a 3 V technology Terminal detects a 1,8 V technology UICC during the ATR analysis the Terminal shall stay in 3 V operation.

For applicability of this test case see clause 3.8.

5.1.5.2.2 Conformance requirement

- 1) A 3 V technology Terminal shall initially activate the UICC with 3 V (i.e. the first activation of a card session).
- 2) The Terminal shall analyse the ATR and identify the voltage class supported by the UICC.
- 3) If a 3 V technology Terminal identifies a 1,8 V technology UICC during the ATR analysis the Terminal shall stay in 3 V operation.

5.1.5.2.3 Reference

ETSI TS 102 221 [1], clause 6.2.

5.1.5.2.4 Test purpose

- 1) To verify that a 3 V technology Terminal initially activates the UICC with 3 V.
- 2) To verify that a 3 V technology Terminal correctly identifies the voltage class.
- 3) To verify that a 3 V technology Terminal stays in 3 V operation during the whole card session.

5.1.5.2.5 Method of test

5.1.5.2.5.1 Initial condition

The Terminal shall be connected to an UICC simulator simulating a 1,8 V technology UICC with nominal test conditions (see clause 5.2.1). All elementary files shall be coded as default.

The Terminal shall be powered on.

5.1.5.2.5.2 Procedure

The UICC simulator shall send an ATR indicating a 1,8 V technology UICC.

The UICC-Terminal interface shall be monitored for at least 1 minute until the UE is switched off.

5.1.5.2.6 Acceptance criteria

- 1) The initial activation of the UICC-Terminal interface shall be performed with 3 V supply voltage.
- 2) The Terminal shall react in the following way:
 - The Terminal proceeds with the card session without switching to another supply voltage.

5.1.5.3 Reaction of 1,8 V technology Terminals on type recognition of 1,8 V technology UICCs

5.1.5.3.1 Definition and applicability

When a 1,8 V technology Terminal detects a 1,8 V technology UICC during the ATR analysis the Terminal may either switch to 3 V operation or stay in 1,8 V operation.

For applicability of this test case see clause 3.8.

5.1.5.3.2 Conformance requirement

- 1) A 1,8 V technology Terminal shall initially activate the UICC with 1,8 V (i.e. the first activation of a card session).
- 2) The Terminal shall analyse the ATR and identify the voltage class supported by the UICC.
- 3) If a 1,8 V technology Terminal identifies a 1,8 V technology UICC the Terminal may switch to 3 V operation. Switching from 1,8 V to 3 V shall only be performed by deactivating the UICC and activating it with 3 V supply voltage immediately after the analysis of the ATR without issuing any commands.

5.1.5.3.3 Reference

ETSI TS 102 221 [1], clause 6.2.

5.1.5.3.4 Test purpose

- 1) To verify that a 1,8 V technology Terminal initially activates the UICC with 1,8 V.
- 2) To verify that a 1,8 V technology Terminal correctly identifies the voltage class.

- 3) To verify that a 1,8 V technology Terminal deactivates the UICC-Terminal interface immediately after the analysis of the ATR without issuing any command and activates it with 3 V supply voltage or proceeds with the 1,8 V operation during the whole card session without switching to 3 V supply voltage.

5.1.5.3.5 Method of test

5.1.5.3.5.1 Initial condition

The Terminal shall be connected to an UICC simulator simulating a 1,8 V technology UICC with nominal test conditions (see clause 5.2.1). All elementary files are coded as default.

The Terminal shall be powered on.

5.1.5.3.5.2 Procedure

The UICC simulator shall send the ATR indicating a 3 V technology UICC.

The UICC-Terminal interface shall be monitored for at least 1 minute until the UE is switched off.

5.1.5.3.6 Acceptance criteria

- 1) The initial activation of the UICC-Terminal interface shall be performed with 1,8 V supply voltage.
- 2) The Terminal shall react in one of the following ways:
 - a) The Terminal deactivates the UICC-Terminal interface immediately after the analysis of the ATR from the UICC and activates it with 3 V supply voltage.
 - b) The Terminal proceeds with the card session without switching to another supply voltage.

5.1.5.4 Reaction of 1,8 V technology Terminals on type recognition of 3 V technology UICCs

5.1.5.4.1 Definition and applicability

When a 1,8 V technology Terminal detects a 3 V technology UICC during the ATR analysis the Terminal shall switch to 3 V operation.

For applicability of this test case see clause 3.8.

5.1.5.4.2 Conformance requirement

- 1) A 1,8 V technology Terminal shall initially activate the UICC with 1,8 V (i.e. the first activation of a card session).
- 2) The Terminal shall analyse the ATR and identify the voltage class supported by the UICC.
- 3) If a 1,8 V technology Terminal identifies a 3 V technology UICC the Terminal shall switch to 3 V operation. Switching from 1,8 V to 3 V shall only be performed by deactivating the UICC and activating it with 3 V supply voltage immediately after the analysis of the ATR without issuing any commands.

5.1.5.4.3 Reference

ETSI TS 102 221 [1], clause 6.2.

5.1.5.4.4 Test purpose

- 1) To verify that a 1,8 V technology Terminal initially activates the UICC with 1,8 V.
- 2) To verify that a 1,8 V technology Terminal correctly identifies the voltage class.

- 3) To verify that a 1,8 V technology Terminal deactivates the UICC-Terminal interface immediately after the recognition of a 3 V technology UICC (in order to switch the supply voltage).
- 4) To verify that a 1,8 V technology Terminal activates the UICC with 3 V.

5.1.5.4.5 Method of test

5.1.5.4.5.1 Initial condition

The Terminal shall be connected to an UICC simulator simulating a 3 V technology UICC with nominal test conditions (see clause 5.2.1). All elementary files are coded as default.

The Terminal shall be powered on.

5.1.5.4.5.2 Procedure

The UICC simulator shall send the ATR indicating a 3 V technology UICC.

The UICC-Terminal interface shall be monitored for at least 1 minute until the UE is switched off.

5.1.5.4.6 Acceptance criteria

- 1) The initial activation of the UICC-Terminal interface shall be performed with 1,8 V supply voltage.
- 2) The Terminal shall react in the following way:
 - The Terminal deactivates the UICC-Terminal interface immediately after the analysis of the ATR from the UICC and activates it with 3 V supply voltage. The Terminal proceeds with the card session.

5.1.5.5 Void

5.1.5.6 Reaction of Terminals receiving no ATR

5.1.5.6.1 Reaction of Terminals receiving no ATR: 3 V - 5 V

5.1.5.6.1.1 Definition and applicability

A Terminal supporting 3 V - 5 V shall initially activate the UICC with 3V. If no ATR is received, the UICC-Terminal interface shall be deactivated and activated with 5 V.

For applicability of this test case see clause 3.8.

5.1.5.6.1.2 Conformance requirement

If a Terminal does not receive an ATR, the Terminal shall deactivate the UICC-Terminal interface and repeat the activation with the next higher voltage class.

5.1.5.6.1.3 Reference

ETSI TS 102 221 [1], see clause 6.2.

5.1.5.6.1.4 Test purpose

To verify that a Terminal deactivates the UICC-Terminal interface and repeats the activation with the next higher voltage class in case that the Terminal cannot receive an ATR.

5.1.5.6.1.5 Method of test

5.1.5.6.1.5.1 Initial condition

The Terminal shall be connected to an UICC simulator. All elementary files shall be coded as default. The Terminal shall be powered on.

5.1.5.6.1.5.2 Procedure

The UICC simulator shall send no ATR.

5.1.5.6.1.6 Acceptance criteria

If no ATR is received by the Terminal, the Terminal shall wait at least 40 000 clock cycles before deactivating the UICC-Terminal interface. The Terminal shall then repeat the activation procedure with the next higher voltage class.

5.1.5.6.2 Reaction of Terminals receiving no ATR: 1,8 V - 3 V

5.1.5.6.2.1 Definition and applicability

A Terminal supporting 1,8 V - 3 V shall initially activate the UICC with 1,8 V. If no ATR is received, the UICC-Terminal interface shall be deactivated and activated with 3 V.

For applicability of this test case see clause 3.8.

5.1.5.6.2.2 Conformance requirement

If a Terminal does not receive an ATR, the Terminal shall deactivate the UICC-Terminal interface and repeat the activation with the next higher voltage class.

5.1.5.6.2.3 Reference

ETSI TS 102 221 [1], see clause 6.2.

5.1.5.6.2.4 Test purpose

To verify that a Terminal deactivates the UICC-Terminal interface and repeats the activation with the next higher voltage class in case that the Terminal cannot receive an ATR.

5.1.5.6.2.5 Method of test

5.1.5.6.2.5.1 Initial condition

The Terminal shall be connected to an UICC simulator. All elementary files shall be coded as default. The Terminal shall be powered on.

5.1.5.6.2.5.2 Procedure

The UICC simulator shall send no ATR.

5.1.5.6.2.6 Acceptance criteria

If no ATR is received by the Terminal, the Terminal shall wait at least 40 000 clock cycles before deactivating the UICC-Terminal interface. The Terminal shall then repeat the activation procedure with the next higher voltage class.

5.1.5.7 FFS

5.1.5.8 FFS

5.1.5.9 Reaction of Terminals not supporting any voltage class indicated in the ATR

5.1.5.9.1 Definition and applicability

If a Terminal is not supporting any of the voltage classes indicated in the ATR send from the UICC, it shall not send any APDU in response and may deactivate the UICC.

For applicability of this test case see clause 3.8.

5.1.5.9.2 Conformance requirement

5.1.5.9.2.0 Description

RQ	Description
RQ_1	If an ATR is received at the first applied voltage class, the contents of the ATR shall be analysed by the Terminal.
RQ_2	If the Terminal does not support any of the voltage classes indicated in the ATR, the Terminal shall not send any APDU to the UICC.
RQ_3	The Terminal may deactivate the UICC at any time.
NOTE:	According to ISO/IEC 7816-3 [2], clause 8.1 a format character shall be sent within $WT = 9\ 600$ etu. It can be assumed that the terminal is not sending an APDU if none is sent within this timeframe.

5.1.5.9.2.1 Reference

ETSI TS 102 221 [1], clause 6.2.

5.1.5.9.3 Test purpose

To verify that a Terminal does not send APDUs to a UICC providing an ATR indicating only voltage classes not supported by the Terminal.

5.1.5.9.4 Method of test

5.1.5.9.4.1 Initial condition

The Terminal shall be connected to an UICC simulator. All elementary files shall be coded as default. The Terminal shall be powered on.

5.1.5.9.4.2 Procedure

Step	Direction	Description	RQ
1	UICC > T	Send an ATR indicating support of at least one voltage class ($TA_i, i > 2$), where none of the voltage classes indicated are supported by the Terminal.	RQ_1
2	T > UICC	The Terminal shall not send any APDU	RQ_2
3	User	Deactivate the Terminal	
4	T	The Terminal may deactivate the UICC at any time after receiving the ATR indication a voltage class not supported by the Terminal in step 1)	RQ_3

5.1.5.9.5 Acceptance criteria

- 1) If the Terminal is not sending any APDU for at least 5 seconds, it is assumed that it has analysed the ATR (RQ_1) and handles compliant to RQ_2.
- 2) The deactivation of the UICC by the Terminal (RQ_3) is optional.

5.2 Electrical tests on each Terminal contact

5.2.1 Nominal test conditions

If a pre-Release 12 terminal is being tested, tables 5.1, 5.2a and 5.3a give the electrical conditions that shall be applied by the UICC simulator to all contacts during a test if not stated otherwise.

If a Release 12 or later terminal is being tested, tables 5.1, 5.2b and 5.3b give the electrical conditions that shall be applied by the UICC simulator to all contacts during a test if not stated otherwise.

Table 5.1: Nominal test conditions for the 5 V UICC - Terminal interface

Contacts	Low level	High level	Max. capacitive load
C1 (VCC)	---	I = 10 mA	
C2 (RST)	I = -200 μ A	I = +20 μ A	30 pF
C3 (CLK)	I = -200 μ A	I = +20 μ A	30 pF
C5 (GND)	---	---	
C7 (I/O)			
Terminal input	I = +1 mA	I = +20 μ A	30 pF
Terminal output	I = -1 mA	I = +20 μ A	

Table 5.2a: Nominal test conditions for the pre-Release 12 3 V UICC-Terminal interface

Contacts	Low level	High level	Max. capacitive load
C1 (VCC)	---	I = 7.5 mA	
C2 (RST)	I = -200 μ A	I = +20 μ A	30 pF
C3 (CLK)	I = -20 μ A	I = +20 μ A	30 pF
C5 (GND)	---	---	
C7 (I/O)			
Terminal input	I = +1 mA	I = +20 μ A	30 pF
Terminal output	I = -1 mA	I = +20 μ A	

Table 5.2b: Nominal test conditions for the 3 V UICC - Terminal interface (Release 12 and higher)

Contacts	Low level	High level	Max. capacitive load
C1 (VCC)	---	I = 10 mA	
C2 (RST)	I = -200 μ A	I = +20 μ A	30 pF
C3 (CLK)	I = -20 μ A	I = +20 μ A	30 pF
C5 (GND)	---	---	
C7 (I/O)			
Terminal input	I = +1 mA	I = +20 μ A	30 pF
Terminal output	I = -1 mA	I = +20 μ A	

Table 5.3a: Nominal test conditions for the pre-Release 12 1,8 V UICC-Terminal interface

Contacts	Low level	High level	Max. capacitive load
C1 (VCC)	---	I = 5 mA	
C2 (RST)	I = -200 μ A	I = +20 μ A	30 pF
C3 (CLK)	I = -20 μ A	I = +20 μ A	30 pF
C5 (GND)	---	---	
C7 (I/O)			
Terminal input	I = +1 mA	I = +20 μ A	30 pF
Terminal output	I = -1 mA	I = +20 μ A	

Table 5.3b: Nominal test conditions for the pre-Release 12 1,8 V UICC-Terminal interface

Contacts	Low level	High level	Max. capacitive load
C1 (VCC)	---	I = 10 mA	
C2 (RST)	I = -200 μ A	I = +20 μ A	30 pF
C3 (CLK)	I = -20 μ A	I = +20 μ A	30 pF
C5 (GND)	---	---	
C7 (I/O)			
Terminal input	I = +1 mA	I = +20 μ A	30 pF
Terminal output	I = -1 mA	I = +20 μ A	

NOTE 1: Measurements of contacts voltage levels can be done at any time since the beginning of activation of the UICC and the end of deactivation of the UICC (ISO/IEC 7816-3 [2], clause 5.1).

NOTE 2: The reference point of all measurements is the contact C5 (Ground).

NOTE 3: Currents flowing into the UICC are considered positive.

5.2.2 Electrical tests on contact C1 (Card power supply - V_{CC})

5.2.2.1 Electrical tests on contact C1, Test 1: 3 V - 5 V

5.2.2.1.1 Definition and applicability

When the user equipment is activated, the supply voltage on the UICC -Terminal interface shall remain in the specified range in order to ensure correct operation and to prevent any damage to the UICC.

For applicability of this test case see clause 3.8.

5.2.2.1.2 Conformance requirement

RQ	REL	Description
RQ_1		The voltage on contact C1 of the UICC-Terminal interface shall be 5 V \pm 10 % for I _{cc} up to 10 mA when the Terminal is in 5 V operation mode.
RQ_2a	up to Rel-11	The voltage on contact C1 of the UICC-Terminal interface shall be 3 V \pm 10 % for I _{cc} up to 7.5 mA when the Terminal is in 3 V operation mode.
RQ_2b	Rel-12 upwards	The voltage on contact C1 of the UICC-Terminal interface shall be 3 V \pm 10 % for I _{cc} up to 10 mA when the Terminal is in 3 V operation mode.

5.2.2.1.3 Reference

- 1) ETSI TS 102 221 [1], clause 5.1.
- 2) ETSI TS 102 221 [1], clause 5.2.

5.2.2.1.4 Test purpose

To verify that the Terminal keeps the voltage on contact C1 of the UICC-Terminal interface within the ranges specified in the conformance requirements.

5.2.2.1.5 Method of test

5.2.2.1.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UE shall be activated.

The remaining contacts of the UICC-Terminal interface shall be in nominal test conditions:

- For an interface operated in class A see clause 5.2.1, Table 5.1 of the present document.
- For an interface as defined for releases up to 11, operated in class B see clause 5.2.1, Table 5.2a of the present document.
- For an interface as defined for Release 12 and upwards, operated in class B see clause 5.2.1, Table 5.2b of the present document.

5.2.2.1.5.2 Test Procedure

The voltage of contact C1 (V_{CC}) of the UICC-Terminal interface shall be measured.

5.2.2.1.6 Acceptance criteria

The voltage on contact C1 of the UICC-Terminal interface shall be within the ranges specified in the conformance requirements.

5.2.2.2 Electrical tests on contact C1, Test 2: 3 V - 5 V

5.2.2.2.1 Definition and applicability

When the user equipment is activated, the supply voltage on the UICC-Terminal interface shall be able to counteract spikes in the current consumption of the UICC up to the limits given in the conformance requirement, ensuring that the supply voltage stays in the specified range.

For applicability of this test case see clause 3.8.

5.2.2.2.2 Conformance requirement

- 1) The voltage on contact C1 of the UICC-Terminal interface shall be $5\text{ V} \pm 10\%$ for spikes in the current consumption with a maximum charge of 40 n. As with no more than 400 ns duration and an amplitude of at most 200 mA when the Terminal is in 5 V operation mode.
- 2) The voltage on contact C1 of the UICC-Terminal interface shall be $3\text{ V} \pm 10\%$ for spikes in the current consumption with a maximum charge of 12 n. As with no more than 400 ns duration and an amplitude of at most 60 mA when the Terminal is in 3 V operation mode.

NOTE: For compatibility reasons a maximum spike duration of 400 ns is kept also for terminals implemented in accordance to ETSI TS 102 221 [1] - Release 12 and upwards.

5.2.2.2.3 Reference

- 1) ETSI TS 102 221 [1], clause 5.1.
- 2) ETSI TS 102 221 [1], clause 5.2.

5.2.2.2.4 Test purpose

To verify that the Terminal keeps the voltage on contact C1 of the UICC-Terminal interface within the specified range for the conditions given in the UICC-Terminal conformance requirement.

5.2.2.2.5 Method of test

5.2.2.2.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UE shall be activated.

The remaining contacts of the interface shall held in nominal test condition (see clause 5.2.1).

5.2.2.2.5.2 Procedure

In order to test the requirements 1), the voltage on contact C1 of the UICC-Terminal interface shall be monitored and the following current spikes shall be applied:

- 1) Continuous spikes:
 - current amplitude 20 mA;
 - current offset 0 mA;
 - duration 100 ns;
 - pause 100 ns.
- 2) Continuous spikes:
 - current 20 mA;
 - current offset 0 mA;
 - duration 400 ns;
 - pause 400 ns.
- 3) Continuous spikes:
 - current amplitude 15 mA;
 - current offset 5 mA;
 - (i.e. maximum amplitude = 5 mA + 15 mA = 20 mA);
 - duration 150 ns;
 - pause 300 ns.
- 4) Random spikes:
 - current amplitude 200 mA;
 - current offset 0 mA;
 - duration 200 ns;
 - pause between 0,1 ms and 500 ms, randomly varied.
- 5) Random spikes:
 - current amplitude 100 mA;
 - current offset 0 mA;
 - duration 400 ns;
 - pause between 0,1 ms and 500 ms, randomly varied.
- 6) Random spikes:
 - current amplitude 195 mA;
 - current offset 5mA;
 - (i.e. maximum amplitude = 5 mA + 195 mA = 200 mA);
 - Duration 200 ns;

- Pause between 0,1 ms and 500 ms, randomly varied.

In order to test the requirements 2), the voltage on contact C1 of the UICC-Terminal interface shall be monitored and the following current spikes shall be applied:

- 1) Continuous spikes:
 - current amplitude 12 mA;
 - current offset 0 mA;
 - duration 100 ns;
 - pause 100 ns.
- 2) Continuous spikes:
 - current 12 mA;
 - current offset 0 mA;
 - duration 400 ns;
 - pause 400 ns.
- 3) Continuous spikes:
 - current amplitude 9 mA;
 - current offset 3 mA;
 - (i.e. maximum amplitude = 3 mA + 9 mA = 12 mA);
 - duration 150 ns;
 - pause 300 ns.
- 4) Random spikes:
 - current amplitude 60 mA;
 - current offset 0 mA;
 - duration 200 ns;
 - pause between 0,1 ms and 500 ms, randomly varied.
- 5) Random spikes:
 - current amplitude 30 mA;
 - current offset 0 mA;
 - duration 400 ns;
 - pause between 0,1 ms and 500 ms, randomly varied.
- 6) Random spikes:
 - current amplitude 57 mA;
 - current offset 3 mA;
 - (i.e. maximum amplitude = 3 mA + 57 mA = 60 mA);
 - duration 200 ns;
 - pause between 0,1 ms and 500 ms, randomly varied.

The specified spike durations shall be measured at 50 % of the spike amplitude.

5.2.2.2.6 Acceptance criteria

The voltage on contact C1 of the UICC-Terminal interface shall be within the ranges specified in the conformance requirements.

5.2.2.3 Electrical tests on contact C1, Test 1: 1,8 V - 3 V

5.2.2.3.1 Definition and applicability

When the user equipment is activated, the supply voltage on the UICC -Terminal interface shall remain in the specified range in order to ensure correct operation and to prevent any damage to the UICC.

For applicability of this test case see clause 3.8.

5.2.2.3.2 Conformance requirement

RQ	REL	Description
RQ_1a	up to Rel-11	The voltage on contact C1 of the UICC-Terminal interface shall be $3\text{ V} \pm 10\%$ for I_{cc} up to 7.5 mA when the Terminal is in 3 V operation mode.
RQ_1b	Rel-12 upwards	The voltage on contact C1 of the UICC-Terminal interface shall be $3\text{ V} \pm 10\%$ for I_{cc} up to 10 mA when the Terminal is in 3 V operation mode.
RQ_2a	up to Rel 11	The voltage on contact C1 of the UICC-Terminal interface shall be $1,8\text{ V} \pm 10\%$ for I_{cc} up to 5 mA when the Terminal is in 1,8 V operation mode.
RQ_2b	Rel-12 upwards	The voltage on contact C1 of the UICC-Terminal interface shall be $1,8\text{ V} \pm 10\%$ for I_{cc} up to 10 mA when the Terminal is in 1,8 V operation mode.

5.2.2.3.3 Reference

- 1) ETSI TS 102 221 [1], clause 5.2.
- 2) ETSI TS 102 221 [1], clause 5.3.

5.2.2.3.4 Test purpose

To verify that the Terminal keeps the voltage on contact C1 of the UICC-Terminal interface within the ranges specified in the conformance requirements.

5.2.2.3.5 Method of test

5.2.2.3.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UE shall be activated.

The remaining contacts of the UICC-Terminal interface shall be in nominal test conditions:

- For an interface as defined for releases up to 11, operated in class B see clause 5.2.1, Table 5.2a of the present document.
- For an interface as defined for Release 12 and upwards, operated in class B see clause 5.2.1, Table 5.2b of the present document.
- For an interface as defined for releases up to 11, operated in class C see clause 5.2.1, Table 5.3a of the present document.
- For an interface as defined for Release 12 and upwards, operated in class C see clause 5.2.1, Table 5.3b of the present document.

5.2.2.3.5.2 Test Procedure

The voltage of contact C1 (V_{CC}) of the UICC-Terminal interface shall be measured.

5.2.2.3.6 Acceptance criteria

The voltage on contact C1 of the UICC-Terminal interface shall be within the ranges specified in the conformance requirements.

5.2.2.4 Electrical tests on contact C1, Test 2: 1,8 V - 3 V

5.2.2.4.1 Definition and applicability

When the user equipment is activated, the supply voltage on the UICC-Terminal interface shall be able to counteract spikes in the current consumption of the UICC up to the limits given in the conformance requirement, ensuring that the supply voltage stays in the specified range.

For applicability of this test case see clause 3.8.

5.2.2.4.2 Conformance requirement

- 1) The voltage on contact C1 of the UICC-Terminal interface shall be $3\text{ V} \pm 10\%$ for spikes in the current consumption with a maximum charge of 12 n. As with no more than 400 ns duration and an amplitude of at most 60 mA when the Terminal is in 3 V operation mode.
- 2) The voltage on contact C1 of the UICC-Terminal interface shall be $1,8\text{ V} \pm 10\%$ for spikes in the current consumption with a maximum charge of 12 n. As with no more than 400 ns duration and an amplitude of at most 60 mA when the Terminal is in 1,8 V operation mode.

NOTE: For compatibility reasons a maximum spike duration of 400 ns is kept also for terminals implemented in accordance to ETSI TS 102 221 [1] - Release 12 and upwards.

5.2.2.4.3 Reference

- 1) ETSI TS 102 221 [1], clause 5.2.
- 2) ETSI TS 102 221 [1], clause 5.3.

5.2.2.4.4 Test purpose

To verify that the Terminal keeps the voltage on contact C1 of the UICC-Terminal interface within the specified range for the conditions given in the UICC-Terminal conformance requirement.

5.2.2.4.5 Method of test

5.2.2.4.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UE shall be activated.

The remaining contacts of the interface shall held in nominal test condition (see clause 5.2.1).

5.2.2.4.5.2 Procedure

In order to test the requirements 1) and 2), the voltage on contact C1 of the UICC-Terminal interface shall be monitored and the following current spikes shall be applied:

- 1) Continuous spikes:
 - current amplitude 12 mA;

- current offset 0 mA;
 - duration 100 ns;
 - pause 100 ns.
- 2) Continuous spikes:
- current 12 mA;
 - current offset 0 mA;
 - duration 400 ns;
 - pause 400 ns.
- 3) Continuous spikes:
- current amplitude 9 mA;
 - current offset 3 mA;
 - (i.e. maximum amplitude = 3 mA + 9 mA = 12 mA);
 - duration 150 ns;
 - pause 300 ns.
- 4) Random spikes:
- current amplitude 60 mA;
 - current offset 0 mA;
 - duration 200 ns;
 - pause between 0,1 ms and 500 ms, randomly varied.
- 5) Random spikes:
- current amplitude 30 mA;
 - current offset 0 mA;
 - duration 400 ns;
 - pause between 0,1 ms and 500 ms, randomly varied.
- 6) Random spikes:
- current amplitude 57 mA;
 - current offset 3 mA;
 - (i.e. maximum amplitude = 3 mA + 57 mA = 60 mA);
 - duration 200 ns;
 - pause between 0,1 ms and 500 ms, randomly varied.

The specified spike durations shall be measured at 50 % of the spike amplitude.

5.2.2.4.6 Acceptance criteria

The voltage on contact C1 of the UICC-Terminal interface shall be within the ranges specified in the conformance requirements.

5.2.3 Electrical tests on contact C2 (Reset - RST)

5.2.3.1 Electrical tests on contact C2: 3 V - 5 V

5.2.3.1.1 Definition and applicability

When the user equipment is activated, the voltage on contact C2 of the UICC-Terminal interface shall remain in the specified range in order to ensure correct operation and to prevent any damage to the UICC.

For applicability of this test case see clause 3.8.

5.2.3.1.2 Conformance requirement

- 1) The voltage on contact C2 (RST) of the UICC-Terminal interface shall be between -0,3 V and +0,6 V for a current of -200 μ A in low state and between $V_{CC} - 0,7$ V and $V_{CC} + 0,3$ V for a current of +20 μ A in high state when the Terminal is in 5 V operation mode.
- 2) The voltage on contact C2 (RST) of the UICC-Terminal interface shall be between -0,3 V and $0,2 \times V_{CC}$ for a current of -200 μ A in low state and between $0,8 \times V_{CC}$ and $V_{CC} + 0,3$ V for a current of +20 μ A in high state when the Terminal is in 3 V operation mode.

5.2.3.1.3 Reference

- 1) ETSI TS 102 221 [1], clause 5.1.
- 2) ETSI TS 102 221 [1], clause 5.2.

5.2.3.1.4 Test purpose

To verify that the Terminal keeps the voltage on contact C2 (RST) of the UICC-Terminal interface within the specified range, as given in the conformance requirement.

5.2.3.1.5 Method of test

5.2.3.1.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UE shall be activated.

The remaining contacts of the UICC-Terminal interface shall be held in nominal test conditions (see clause 5.2.1).

5.2.3.1.5.2 Procedure

The voltage on contact C2 (RST) of the UICC-Terminal interface shall be measured.

5.2.3.1.6 Acceptance criteria

The voltage on contact C2 (RST) of the UICC-Terminal interface shall be within the range specified in the conformance requirement.

5.2.3.2 Electrical tests on contact C2: 1,8 V - 3 V

5.2.3.2.1 Definition and applicability

When the user equipment is activated, the voltage on contact C2 of the UICC-Terminal interface shall remain in the specified range in order to ensure correct operation and to prevent any damage to the UICC.

For applicability of this test case see clause 3.8.

5.2.3.2.2 Conformance requirement

- 1) The voltage on contact C2 (RST) of the UICC-Terminal interface shall be between $-0,3\text{ V}$ and $0,2 \times V_{CC}$ for a current of $-200\ \mu\text{A}$ in low state and between $0,8 \times V_{CC}$ and $V_{CC} + 0,3\text{ V}$ for a current of $+20\ \mu\text{A}$ in high state when the Terminal is in 3 V operation mode.
- 2) The voltage on contact C2 (RST) of the UICC-Terminal interface shall be between $-0,3\text{ V}$ and $0,2 \times V_{CC}$ for a current of $-200\ \mu\text{A}$ in low state and between $0,8 \times V_{CC}$ and $V_{CC} + 0,3\text{ V}$ for a current of $+20\ \mu\text{A}$ in high state when the Terminal is in 1,8 V operation mode.

5.2.3.2.3 Reference

- 1) ETSI TS 102 221 [1], clause 5.2.
- 2) ETSI TS 102 221 [1], clause 5.3.

5.2.3.2.4 Test purpose

To verify that the Terminal keeps the voltage on contact C2 (RST) of the UICC-Terminal interface within the specified range, as given in the conformance requirement.

5.2.3.2.5 Method of test

5.2.3.2.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UE shall be activated.

The remaining contacts of the UICC-Terminal interface shall be held in nominal test conditions (see clause 5.2.1).

5.2.3.2.5.2 Procedure

The voltage on contact C2 (RST) of the UICC-Terminal interface shall be measured.

5.2.3.2.6 Acceptance criteria

The voltage on contact C2 (RST) of the UICC-Terminal interface shall be within the range specified in the conformance requirement.

5.2.4 Electrical tests on contact C3 (Clock - CLK)

5.2.4.1 Electrical tests on contact C3: 3 V - 5 V

5.2.4.1.1 Definition and applicability

When the user equipment is activated, the voltage, the rise/fall time of the signal, the clock cycle ratio and the frequency on contact C3 of the UICC - Terminal interface shall remain in the specified range in order to ensure correct operation and to prevent any damage to the UICC.

For applicability of this test case see clause 3.8.

5.2.4.1.2 Conformance requirement

- 1) The voltage on contact C3 (CLK) of the UICC - Terminal interface shall be between $-0,3\text{ V}$ and $+0,5\text{ V}$ for a current of $-200\ \mu\text{A}$ in low state and between $0,7 \times V_{CC}$ and $V_{CC} + 0,3\text{ V}$ for a current of $+20\ \mu\text{A}$ in high state when the Terminal is in 5 V operation mode.
- 2) The rise and the fall time of the clock signal shall not exceed 9 % of the clock period with a maximum of $0,5\ \mu\text{s}$ when the Terminal is in 5 V operation mode.

- 3) The cycle ratio of the clock signal shall be between 40 % and 60 % of the period, in steady state when the Terminal is in 5 V operation mode.
- 4) The frequency of the clock signal shall be between 1 MHz and 5 MHz when the Terminal is in 5 V operation mode.
- 5) The voltage on contact C3 (CLK) of the UICC - Terminal interface shall be between -0,3 V and $0,2 \times V_{CC}$ for a current of -20 μ A in low state and between $0,7 \times V_{CC}$ and $V_{CC} + 0,3$ V for a current of +20 μ A in high state when the Terminal is in 3 V operation mode.
- 6) The rise and the fall time of the clock signal shall not exceed 50 ns when the Terminal is in 3 V operation mode.
- 7) The cycle ratio of the clock signal shall be between 40 % and 60 % of the period, in steady state when the Terminal is in 3 V operation mode.
- 8) The frequency of the clock signal shall be between 1 MHz and 5 MHz when the Terminal is in 3 V operation mode.

5.2.4.1.3 Reference

- 1 - 4) ETSI TS 102 221 [1], clause 5.1.
- 5 - 8) ETSI TS 102 221 [1], clause 5.2.

5.2.4.1.4 Test purpose

To verify that the Terminal keeps the voltage, the rise and fall time, the cycle ratio and the frequency on contact C3 (CLK) of the UICC - Terminal interface within the ranges specified in the conformance requirements.

5.2.4.1.5 Method of test

5.2.4.1.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UE shall be activated.

The remaining contacts of the UICC-Terminal interface shall be held in nominal test conditions (see clause 5.2.1).

5.2.4.1.5.2 Procedure

The voltage, the rise/fall time, the clock cycle ratio and the frequency on contact C3 (CLK) of the UICC-Terminal interface shall be measured.

5.2.4.1.6 Acceptance criteria

The voltage, the rise and fall time, the cycle ratio and the frequency on contact C3 (CLK) of the UICC-Terminal interface shall be within the ranges specified in the conformance requirements.

5.2.4.2 Electrical tests on contact C3: 1,8 V - 3 V

5.2.4.2.1 Definition and applicability

When the user equipment is activated, the voltage, the rise/fall time of the signal, the clock cycle ratio and the frequency on contact C3 of the UICC - Terminal interface shall remain in the specified range in order to ensure correct operation and to prevent any damage to the UICC.

For applicability of this test case see clause 3.8.

5.2.4.2.2 Conformance requirement

- 1) The voltage on contact C3 (CLK) of the UICC - Terminal interface shall be between $-0,3\text{ V}$ and $0,2 \times V_{CC}$ for a current of $-20\ \mu\text{A}$ in low state and between $0,7 \times V_{CC}$ and $V_{CC} + 0,3\text{ V}$ for a current of $+20\ \mu\text{A}$ in high state when the Terminal is in 3 V operation mode.
- 2) The rise and the fall time of the clock signal shall not exceed 50 ns when the Terminal is in 3 V operation mode.
- 3) The cycle ratio of the clock signal shall be between 40 % and 60 % of the period, in steady state when the Terminal is in 3 V operation mode.
- 4) The frequency of the clock signal shall be between 1 MHz and 5 MHz when the Terminal is in 3 V operation mode.
- 5) The voltage on contact C3 (CLK) of the UICC-Terminal interface shall be between $-0,3\text{ V}$ and $0,2 \times V_{CC}$ for a current of $-20\ \mu\text{A}$ in low state and between $0,7 \times V_{CC}$ and $V_{CC} + 0,3\text{ V}$ for a current of $+20\ \mu\text{A}$ in high state when the Terminal is in 1,8 V operation mode.
- 6) The rise and the fall time of the clock signal shall not exceed 50 ns when the Terminal is in 1,8 V operation mode.
- 7) The cycle ratio of the clock signal shall be between 40 % and 60 % of the period, in steady state when the Terminal is in 1,8 V operation mode.
- 8) The frequency of the clock signal shall be between 1 MHz and 5 MHz when the Terminal is in 1,8 V operation mode.

5.2.4.2.3 Reference

- 1 - 4) ETSI TS 102 221 [1], clause 5.2.
- 5 - 8) ETSI TS 102 221 [1], clause 5.3.

5.2.4.2.4 Test purpose

To verify that the Terminal keeps the voltage, the rise and fall time, the cycle ratio and the frequency on contact C3 (CLK) of the UICC - Terminal interface within the ranges specified in the conformance requirements.

5.2.4.2.5 Method of test

5.2.4.2.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UE shall be activated.

The remaining contacts of the UICC-Terminal interface shall be held in nominal test conditions (see clause 5.2.1).

5.2.4.2.5.2 Procedure

The voltage, the rise/fall time, the clock cycle ratio and the frequency on contact C3 (CLK) of the UICC-Terminal interface shall be measured.

5.2.4.2.6 Acceptance criteria

The voltage, the rise and fall time, the cycle ratio and the frequency on contact C3 (CLK) of the UICC-Terminal interface shall be within the ranges specified in the conformance requirements.

5.2.5 Electrical tests on contact C7 (Input/Output - I/O)

5.2.5.1 Electrical tests on contact C7, Test 1: 3 V - 5 V

5.2.5.1.1 Definition and applicability

When the user equipment is activated, the Terminal shall keep the voltage, the current and the rise/fall time of the signal on contact C7 of the UICC-Terminal interface within the specified range in order to ensure correct operation and to prevent any damage to the UICC.

For applicability of this test case see clause 3.8.

5.2.5.1.2 Conformance requirement

- 1) Terminal receiving state A (low state):
 - With an imposed voltage of 0 V the current flowing out of the Terminal shall not exceed 1 mA when the Terminal is in 5 V operation mode.
- 2) Terminal transmitting state A (low state):
 - The voltage shall be between -0,3 V and $0,15 \times V_{CC}$ when a current of 1 mA flowing into the Terminal is applied when the Terminal is in 5 V operation mode.
- 3) Terminal transmitting or receiving state Z (high state):
 - The voltage shall be between $+3,8 \text{ V} (V_{OH})/0,7 \times V_{CC} (V_{IH})$ respectively and $V_{CC} + 0,3 \text{ V}$ when a current of 20 μA flowing out of the Terminal is applied when the Terminal is in 5 V operation mode.
- 4) The rise time and the fall time of the I/O signal shall not exceed 1 μs when the Terminal is in 5 V operation mode.
- 5) Terminal receiving state A (low state):
 - With an imposed voltage of 0 V the current flowing out of the Terminal shall not exceed 1 mA when the Terminal is in 3 V operation mode.
- 6) Terminal transmitting state A (low state):
 - The voltage shall be between -0,3 V and $0,2 \times V_{CC}$ when a current of 1 mA flowing into the Terminal is applied when the Terminal is in 3 V operation mode.
- 7) Terminal transmitting or receiving state Z (high state):
 - The voltage shall be between $0,7 \times V_{CC}$ and $V_{CC} + 0,3 \text{ V}$ when a current of 20 μA flowing out of the Terminal is applied when the Terminal is in 3 V operation mode.
- 8) The rise time and the fall time of the I/O signal shall not exceed 1 μs when the Terminal is in 3 V operation mode.

5.2.5.1.3 Reference

- 1 - 4) ETSI TS 102 221 [1], clause 5.1.
- 5 - 8) ETSI TS 102 221 [1], clause 5.2.

5.2.5.1.4 Test purpose

To verify that the Terminal keeps the voltage, the current and the rise and fall times of the signal on contact C7 (I/O) of the UICC-Terminal interface within the ranges specified in the conformance requirements.

5.2.5.1.5 Method of test

5.2.5.1.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UE shall be activated.

The remaining contacts of the UICC-Terminal interface shall be held in nominal test conditions (see clause 5.2.1).

5.2.5.1.5.2 Procedure

The voltage, the current and the rise/fall time on contact C7 (I/O) of the UICC-Terminal interface shall be measured.

5.2.5.1.6 Acceptance criteria

The voltage, the current and the rise and fall times of the signal on contact C7 (I/O) of the UICC-Terminal interface shall be within the ranges specified in the conformance requirements.

5.2.5.2 Electrical tests on contact C7, Test 2: 3 V - 5 V

5.2.5.2.1 Definition and applicability

When the user equipment is activated, the Terminal shall keep the voltage, the current and the rise/fall time of the signal on contact C7 of the UICC-Terminal interface within the specified range in order to ensure correct operation and to prevent any damage to the UICC.

For applicability of this test case see clause 3.8.

5.2.5.2.2 Conformance requirement

- 1) Terminal receiving state A (low state):
 - With an imposed voltage of 0 V the current flowing out of the Terminal shall not exceed 1 mA when the Terminal is in 5 V operation mode.
- 2) Terminal transmitting state A (low state):
 - The voltage shall be between -0,3 V and $0,15 \times V_{CC}$ when a current of 1 mA flowing into the Terminal is applied when the Terminal is in 5 V operation mode.
- 3) Terminal transmitting or receiving state Z (high state):
 - The voltage shall be between $+3,8 \text{ V} (V_{OH})/0,7 \times V_{CC} (V_{IH})$ respectively and $V_{CC} + 0,3 \text{ V}$ when a current of 20 μA flowing out of the Terminal is applied when the Terminal is in 5 V operation mode.
- 4) The rise time and the fall time of the I/O signal shall not exceed 100 ns when the Terminal is in 5 V operation mode.
- 5) Terminal receiving state A (low state):
 - With an imposed voltage of 0 V the current flowing out of the Terminal shall not exceed 1 mA when the Terminal is in 3 V operation mode.
- 6) Terminal transmitting state A (low state):
 - The voltage shall be between -0,3 V and $0,2 \times V_{CC}$ when a current of 1 mA flowing into the Terminal is applied when the Terminal is in 3 V operation mode.
- 7) Terminal transmitting or receiving state Z (high state):
 - The voltage shall be between $0,7 \times V_{CC}$ and $V_{CC} + 0,3 \text{ V}$ when a current of 20 μA flowing out of the Terminal is applied when the Terminal is in 3 V operation mode.

- 8) When the low impedance buffer is selected, the rise time and the fall time of the I/O signal shall not exceed 100 ns when the Terminal is in 3 V operation mode.

5.2.5.2.3 Reference

- 1 - 4) ETSI TS 102 221 [1], clause 5.1.
5 - 8) ETSI TS 102 221 [1], clause 5.2.

5.2.5.2.4 Test purpose

To verify that the Terminal supporting low impedance buffer keeps the voltage, the current and the rise and fall times of the signal on contact C7 (I/O) of the UICC-Terminal interface within the ranges specified in the conformance requirements.

5.2.5.2.5 Method of test

5.2.5.2.5.1 Initial condition

The Terminal shall be connected to a UICC simulator.

The UE shall be activated.

The remaining contacts of the UICC-Terminal interface shall be held in nominal test conditions (see clause 5.2.1).

An ATR indicating the support of the low impedance buffer shall have been received and the PPS procedure selecting the low impedance buffer shall have been successfully completed.

5.2.5.2.5.2 Procedure

The voltage, the current and the rise/fall time on contact C7 (I/O) of the UICC-Terminal interface shall be measured.

5.2.5.2.6 Acceptance criteria

The voltage, the current and the rise and fall times of the signal on contact C7 (I/O) of the UICC-Terminal interface shall be within the ranges specified in the conformance requirements.

5.2.5.3 Electrical tests on contact C7, Test 1: 1,8 V - 3 V

5.2.5.3.1 Definition and applicability

When the user equipment is activated, the Terminal shall keep the voltage, the current and the rise/fall time of the signal on contact C7 of the UICC-Terminal interface within the specified range in order to ensure correct operation and to prevent any damage to the UICC.

For applicability of this test case see clause 3.8.

5.2.5.3.2 Conformance requirement

- 1) Terminal receiving state A (low state):
 - With an imposed voltage of 0 V the current flowing out of the Terminal shall not exceed 1 mA when the Terminal is in 3 V operation mode.
- 2) Terminal transmitting state A (low state):
 - The voltage shall be between -0,3 V and $0,2 \times V_{CC}$ when a current of 1 mA flowing into the Terminal is applied when the Terminal is in 3 V operation mode.

- 3) Terminal transmitting or receiving state Z (high state):
 - The voltage shall be between $0,7 \times V_{CC}$ and $V_{CC} + 0,3$ V when a current of 20 μ A flowing out of the Terminal is applied when the Terminal is in 3 V operation mode.
- 4) The rise time and the fall time of the I/O signal shall not exceed 1 μ s when the Terminal is in 3 V operation mode.
- 5) Terminal receiving state A (low state):
 - With an imposed voltage of 0 V the current flowing out of the Terminal shall not exceed 1 mA when the Terminal is in 1,8 V operation mode.
- 6) Terminal transmitting state A (low state):
 - The voltage shall be between -0,3 V and $0,2 \times V_{CC}$ when a current of 1 mA flowing into the Terminal is applied when the Terminal is in 1,8 V operation mode.
- 7) Terminal transmitting or receiving state Z (high state):
 - The voltage shall be between $0,7 \times V_{CC}$ and $V_{CC} + 0,3$ V when a current of 20 μ A flowing out of the Terminal is applied when the Terminal is in 1,8 V operation mode.
- 8) The rise time and the fall time of the I/O signal shall not exceed 1 μ s when the Terminal is in 1,8 V operation mode.

5.2.5.3.3 Reference

- 1 - 4) ETSI TS 102 221 [1], clause 5.2.
- 5 - 8) ETSI TS 102 221 [1], clause 5.3.

5.2.5.3.4 Test purpose

To verify that the Terminal keeps the voltage, the current and the rise and fall times of the signal on contact C7 (I/O) of the UICC-Terminal interface within the ranges specified in the conformance requirements.

5.2.5.3.5 Method of test

5.2.5.3.5.1 Initial condition

The Terminal shall be connected to an UICC simulator.

The UE shall be activated.

The remaining contacts of the UICC-Terminal interface shall be held in nominal test conditions (see clause 5.2.1).

5.2.5.3.5.2 Procedure

The voltage, the current and the rise/fall time on contact C7 (I/O) of the UICC-Terminal interface shall be measured.

5.2.5.3.6 Acceptance criteria

The voltage, the current and the rise and fall times of the signal on contact C7 (I/O) of the UICC-Terminal interface shall be within the ranges specified in the conformance requirements.

5.2.5.4 Electrical tests on contact C7, Test 2: 1,8 V - 3 V

5.2.5.4.1 Definition and applicability

When the user equipment is activated, the Terminal shall keep the voltage, the current and the rise/fall time of the signal on contact C7 of the UICC-Terminal interface within the specified range in order to ensure correct operation and to prevent any damage to the UICC.

For applicability of this test case see clause 3.8.

5.2.5.4.2 Conformance requirement

- 1) Terminal receiving state A (low state):
 - With an imposed voltage of 0 V the current flowing out of the Terminal shall not exceed 1 mA when the Terminal is in 3 V operation mode.
- 2) Terminal transmitting state A (low state):
 - The voltage shall be between -0,3 V and $0,2 \times V_{CC}$ when a current of 1 mA flowing into the Terminal is applied when the Terminal is in 3 V operation mode.
- 3) Terminal transmitting or receiving state Z (high state):
 - The voltage shall be between $0,7 \times V_{CC}$ and $V_{CC} + 0,3$ V when a current of 20 μ A flowing out of the Terminal is applied when the Terminal is in 3 V operation mode.
- 4) The rise time and the fall time of the I/O signal shall not exceed 100 ns when the Terminal is in 3 V operation mode.
- 5) Terminal receiving state A (low state):
 - With an imposed voltage of 0 V the current flowing out of the Terminal shall not exceed 1 mA when the Terminal is in 1,8 V operation mode.
- 6) Terminal transmitting state A (low state):
 - The voltage shall be between -0,3 V and $0,2 \times V_{CC}$ when a current of 1 mA flowing into the Terminal is applied when the Terminal is in 1,8 V operation mode.
- 7) Terminal transmitting or receiving state Z (high state):
 - The voltage shall be between $0,7 \times V_{CC}$ and $V_{CC} + 0,3$ V when a current of 20 μ A flowing out of the Terminal is applied when the Terminal is in 1,8 V operation mode.
- 8) When the low impedance buffer is selected, the rise time and the fall time of the I/O signal shall not exceed 100 ns when the Terminal is in 1,8 V operation mode.

5.2.5.4.3 Reference

- 1 - 4) ETSI TS 102 221 [1], clause 5.2.
- 5 - 8) ETSI TS 102 221 [1], clause 5.3.

5.2.5.4.4 Test purpose

To verify that the Terminal supporting low impedance buffer keeps the voltage, the current and the rise and fall times of the signal on contact C7 (I/O) of the UICC-Terminal interface within the ranges specified in the conformance requirements.

5.2.5.4.5 Method of test

5.2.5.4.5.1 Initial condition

The Terminal shall be connected to a UICC simulator.

The UE shall be activated.

The remaining contacts of the UICC-Terminal interface shall be held in nominal test conditions (see clause 5.2.1).

An ATR indicating the support of the low impedance buffer shall have been received and the PPS procedure selecting the low impedance buffer shall have been successfully completed.

5.2.5.4.5.2 Procedure

The voltage, the current and the rise/fall time on contact C7 (I/O) of the UICC-Terminal interface shall be measured.

5.2.5.4.6 Acceptance criteria

The voltage, the current and the rise and fall times of the signal on contact C7 (I/O) of the UICC-Terminal interface shall be within the ranges specified in the conformance requirements.

6 Initial communication tests

6.1 ATR

6.1.1 ATR characters

6.1.1.1 Definition and applicability

The ATR is the first string of bytes sent from the UICC to the Terminal after a reset has been performed.

The historical bytes indicate to the external world how to use the card.

Both protocols T=0 and T=1 are mandatory for the Terminal. The protocol starts after either the answer to reset or a successful PPS exchange.

For applicability of this test case see clause 3.8.

6.1.1.2 Conformance requirement

6.1.1.2.0 Description

- 1) The Terminal shall adopt the data encoding convention and initial etu time defined in the initial character TS of the ATR.
- 2) The Terminal shall be able to receive interface characters for transmission protocols other than T=0 and T=1, historical bytes and a check byte, even if only T=0 and T=1 are used by the Terminal.

6.1.1.2.1 Reference

ETSI TS 102 221 [1], clauses 6.3 and 7.

6.1.1.3 Test purpose

- 1) To verify that the Terminal adopts the data encoding convention and initial etu time defined in the initial character TS of the ATR.

- 2) To verify that the Terminal accepts interface characters for transmission protocols (T=0 and T=1), historical bytes and a check byte.

6.1.1.4 Method of test

6.1.1.4.1 Initial conditions

The Terminal shall be connected to the UICC (or UICC simulator).

6.1.1.4.2 Procedure

- a) The Terminal shall be powered on.
 b) The UICC (or UICC simulator) shall send an ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1 and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'80'	TD2 only is present Protocol T=0 supported by UICC
TD2	'1F'	TA3 only is present Global interface bytes following (T=15)
TA3	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'A2'	Check byte

- c) The Terminal shall be made to send further commands to the UICC (or UICC simulator) (e.g. by entering the PIN).
 d) The Terminal is switched off and on.
 e) The UICC (or UICC simulator) shall send an ATR as follows:

Character	Value	Description
TS	'3F'	Indicates inverse convention
T0	'97'	TA1 and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'80'	TD2 only is present Protocol T=0 supported by UICC
TD2	'1F'	TA3 only is present Global interface bytes following (T=15)
TA3	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported

Character	Value	Description
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'A2'	Check byte

- f) The Terminal shall be made to send further commands to the UICC (or UICC simulator) (e.g. by entering the PIN).
- g) The Terminal is switched off and on.
- h) The UICC (or UICC simulator) shall send an ATR as follows:

Character	Value	Description
TS	'3F'	Indicates inverse convention
T0	'97'	TA1, and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'80'	Only TD2 is present Protocol T=0 supported by UICC
TD2	'B1'	TA3, TB3 and TD3 are present Protocol T=1 supported by UICC
TA3	'FE'	IFSC is 254 bytes long
TB3	'00'	Block Waiting Integer=0 Character Waiting Integer=0
TD3	'1F'	Only TA4 is present Global interface bytes following (T=15)
TA4	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'ED'	Check byte

- i) The Terminal shall be made to send further commands to the UICC (or UICC simulator) (e.g. by entering the PIN).
- j) The Terminal is switched off and on.
- k) The UICC (or UICC simulator) shall send an ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1, and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'91'	TA2 and TD2 are present Protocol T=1 supported by UICC
TA2	'81'	Protocol T=1 used in specific mode Parameters indicated by the interface bytes, and card is not able to change mode
TD2	'B1'	TA3, TB3 and TD3 are present Protocol T=1 supported by UICC
TA3	'FE'	IFSC is 254 bytes long
TB3	'00'	Block Waiting Integer=0 Character Waiting Integer=0

Character	Value	Description
TD3	'0F'	Global interface bytes following (T=15)
TA4	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EF _{DIR} present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'7D'	Check byte

- l) The Terminal shall be made to send further commands to the UICC (or UICC simulator) (e.g. by entering the PIN).
- m) The Terminal is switched off and on.
- n) The UICC (or UICC simulator) shall send an ATR as follows:

Character	Value	Description
TS	'3F'	Indicates inverse convention
T0	'97'	TA1, and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'91'	TA2 and TD2 are present Protocol T=1 supported by UICC
TA2	'81'	Protocol T=1 used in specific mode Parameters indicated by the interface bytes, and card is not able to change mode
TD2	'B1'	TA3, TB3 and TD3 are present Protocol T=1 supported by UICC
TA3	'FE'	IFSC is 254 bytes long
TB3	'00'	Block Waiting Integer=0 Character Waiting Integer=0
TD3	'0F'	Global interface bytes following (T=15)
TA4	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EF _{DIR} present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'7D'	Check byte

- o) The Terminal shall be made to send further commands to the UICC (or UICC simulator) (e.g. by entering the PIN).

6.1.1.5 Acceptance criteria

In step c), the Terminal shall start a T=0 session in direct convention and work with the UICC (or UICC simulator).

In steps f) and i), the Terminal shall start a T=0 session in inverse convention and work with the UICC (or UICC simulator).

In step l), the Terminal shall start a T=1 session in direct convention and work with the UICC (or UICC simulator).

In step o), the Terminal shall start a T=1 session in inverse convention and work with the UICC (or UICC simulator).

6.2 Clock stop mode with 1,8 V technology UICC

6.2.1 Definition and applicability

The Terminal shall be able to receive interface characters, historical bytes and a check byte, even if only T=0 and T=1 are used by the Terminal.

T=15 global interface parameters shall be returned by the UICC.

The UICC shall support the clock stop procedure. The clock stop mode is indicated in TA_i (i > 2) in T=15 in the ATR.

For applicability of this test case see clause 3.8.

6.2.2 Conformance requirement

6.2.2.0 Description

If the UICC supports any other operating conditions even together with class A, clock stop mode shall be supported and the indication shall be set accordingly. The terminal shall follow this indication independently of operating conditions indicated by the card.

In case the UICC does not support any supply voltage indication, the UICC shall be treated as a 5 V only card by the Terminal.

The Terminal shall wait at least 1 860 clock cycles after having received the last character, including the guard time (2 etu), of the response before it switches off the clock. It shall wait at least 744 clock cycles before it sends the first command after having started the clock.

6.2.2.1 Reference

ETSI TS 102 221 [1], clauses 6.7, 6.10 and 11.1.1.4.6.1.

ISO/IEC 7816-3 [2], clauses 5.3.4 and 6.5.5.

6.2.3 Test purpose

- 1) To verify that the clock is only switched off as indicated in the ATR first global interface byte and file characteristics (byte 1 of the directory characteristics).
- 2) To verify that the timing of the clock switching is as specified.

6.2.4 Method of test

6.2.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator. PIN shall be enabled.

6.2.4.2 Procedure

- a) The Terminal shall be powered on and the UICC simulator shall send an ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1 and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)

Character	Value	Description
TD1	'80'	TD2 only is present Protocol T=0 supported by UICC
TD2	'1F'	TA3 only is present Global interface bytes following (T=15)
TA3	'C6'	Clock stop supported (no preferred state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'22'	Check byte

and be used with bits set as follows:

b8	b7	b6	b5	B4	b3	b2	b1	Meaning
0	1	1	0	0	0	0	1	Voltage classes BC and clock stop mode supported. No preferred level.

- b) When the Terminal is in mode PIN check, 10 seconds shall elapse before the PIN shall be entered.
- c) The Terminal shall be powered off and on. The UICC simulator shall send an ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1 and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI = 1 (F = 372) Baud rate adjustment factor DI = 1 (D = 1)
TD1	'80'	TD2 only is present Protocol T=0 supported by UICC
TD2	'1F'	TA3 only is present Global interface bytes following (T=15)
TA3	'86'	Clock stop supported (high electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'62'	Check byte

and be used with bits set as follows:

b8	b7	b6	b5	b4	b3	b2	b1	Meaning
0	1	1	0	0	1	0	1	Voltage classes BC and clock stop mode supported. High level preferred.

- d) When the Terminal is in mode PIN check, 10 seconds shall elapse before the PIN shall be entered.
- e) The Terminal shall be powered off and on. The UICC simulator shall send an ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1 and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'80'	TD2 only is present Protocol T=0 supported by UICC
TD2	'1F'	TA3 only is present Global interface bytes following (T=15)
TA3	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'A2'	Check byte

and be used with bits set as follows:

b8	b7	b6	b5	b4	b3	b2	b1	Meaning
0	1	1	0	1	0	0	1	Voltage classes BC and clock stop mode supported. Low level preferred.

- f) When the Terminal is in mode PIN check, 10 seconds shall elapse before the PIN shall be entered.

6.2.5 Acceptance criteria

- 1) During step b), the Terminal shall switch off the clock at either high or low level.
- 2) During step d), the Terminal shall switch off the clock at high level.
- 3) During step f), the Terminal shall switch off the clock at low level.
- 4) During steps b), d) and f), the Terminal shall not switch off the clock until at least 1 860 clock cycles after having received the last character of the response including the minimum guard time (2 etu).
- 5) During steps b), d) and f), the Terminal shall wait at least 744 clock cycles before it sends the first command after having restarted the clock.

NOTE: The Terminal will operate at either 1,8 V or 3 V and use the supply voltage procedure if it does not support the first value.

6.3 Clock stop mode with 3 V technology UICC

6.3.1 Definition and applicability

The Terminal shall be able to receive interface characters, historical bytes and a check byte, even if only T=0 and T=1 are used by the Terminal.

T=15 global interface parameters shall be returned by the UICC.

The UICC shall support the clock stop procedure. The clock stop mode is indicated in TA_i (i > 2) in T=15 in the ATR.

For applicability of this test case see clause 3.8.

6.3.2 Conformance requirement

6.3.2.0 Description

If the UICC supports any other operating conditions even together with class A, clock stop mode shall be supported and the indication shall be set accordingly. The terminal shall follow this indication independently of operating conditions indicated by the card.

In case the UICC does not support any supply voltage indication, the UICC shall be treated as a 5 V only card by the Terminal.

The Terminal shall wait at least 1 860 clock cycles after having received the last character, including the guard time (2 etu), of the response before it switches off the clock. It shall wait at least 744 clock cycles before it sends the first command after having started the clock.

6.3.2.1 Reference

ETSI TS 102 221 [1], clauses 6.7, 6.10 and 11.1.1.4.6.1.

ISO/IEC 7816-3 [2], clauses 5.3.4 and 6.5.5.

6.3.3 Test purpose

- 1) To verify that the clock is only switched off as indicated in the ATR first global interface byte and file characteristics (byte 1 of the directory characteristics).
- 2) To verify that the timing of the clock switching is as specified.

6.3.4 Method of test

6.3.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator. PIN shall be enabled.

6.3.4.2 Procedure

- a) The Terminal shall be powered on and the UICC simulator shall send an ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1 and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'80'	TD2 only is present Protocol T=0 supported by UICC
TD2	'1F'	TA3 only is present Global interface bytes following (T=15)
TA3	'C3'	Clock stop supported (no preferred state) 3 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'27'	Check byte

and be used with bits set as follows:

b8	b7	b6	b5	B4	b3	b2	b1	Meaning
0	0	1	1	0	0	0	1	Voltage classes AB and clock stop mode supported. No preferred level.

- b) When the Terminal is in mode PIN check, 10 seconds shall elapse before the PIN shall be entered.
- c) The Terminal shall be powered off and on. The UICC simulator shall send an ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1 and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'80'	TD2 only is present Protocol T=0 supported by UICC
TD2	'1F'	TA3 only is present Global interface bytes following (T=15)
TA3	'83'	Clock stop supported (high electrical state) 3 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'67'	Check byte

and be used with bits set as follows:

b8	b7	b6	b5	b4	b3	b2	b1	Meaning
0	0	1	1	0	1	0	1	Voltage classes AB and clock stop mode supported. High level preferred.

- d) When the Terminal is in mode PIN check, 10 seconds shall elapse before the PIN shall be entered.
- e) The Terminal shall be powered off and on. The UICC simulator shall send an ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1 and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'80'	TD2 only is present Protocol T=0 supported by UICC
TD2	'1F'	TA3 only is present Global interface bytes following (T=15)
TA3	'43'	Clock stop supported (low electrical state) 3 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte

Character	Value	Description
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'A7'	Check byte

and be used with bits set as follows:

b8	b7	b6	b5	b4	b3	b2	b1	Meaning
0	0	1	1	1	0	0	1	Voltage classes AB and clock stop mode supported. Low level preferred.

- f) When the Terminal is in mode PIN check, 10 seconds shall elapse before the PIN shall be entered.

6.3.5 Acceptance criteria

- 1) During step b), the Terminal shall switch off the clock at either high or low level.
- 2) During step d), the Terminal shall switch off the clock at high level.
- 3) During step f), the Terminal shall switch off the clock at low level.
- 4) During steps b), d) and f), the Terminal shall operate at 3 V and not switch off the clock until at least 1 860 clock cycles after having received the last character of the response including the minimum guard time (2 etu).
- 5) During steps b), d) and f), the Terminal shall wait at least 744 clock cycles before it sends the first command after having restarted the clock.

6.4 Void

6.5 Speed enhancement

6.5.1 Definition and applicability

The Terminal shall at least support speed enhancement using (F,D) = (512,8) and (512,16) in addition to (372,1), the default.

For applicability of this test case see clause 3.8.

6.5.2 Conformance requirement

For the Terminal, it is mandatory to support F = 512 and D = 8 as well as F = 512 and D = 16 (in addition to the default values F = 372 and D = 1).

6.5.3 Test purpose

To verify that the Terminal supports the transmission parameters F = 512 and D = 8 as well as F = 512 and D = 16.

6.5.4 Method of test

6.5.4.1 Initial conditions

The Terminal is connected to the UICC simulator.

6.5.4.2 Procedure

- a) The Terminal is powered on.
- b) The UICC simulator sends an ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1, TD1 are present 7 bytes of historical bytes
TA1	'94'	F=512, D=8
TD1	'80'	TD2 only is present T=0
TD2	'1F'	TA3 only is present Global interface bytes following
TA3	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC, supporting class B and class C
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'27'	Check byte

- c) After receipt of the PPS Request, the UICC simulator answers with the PPS Response "FF 10 94 7B" using a work waiting time of 9 600 etu (initial waiting time).
- d) The UICC simulator transmits with enhanced speed (F = 512, D = 8).
- e) The Terminal is switched off and on. The UICC simulator sends an ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1, TD1 are present 7 bytes of historical bytes
TA1	'95'	F=512, D=16
TD1	'80'	TD2 only is present T=0
TD2	'1F'	TA3 only is present Global interface bytes following
TA3	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC, supporting class B and class C
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'26'	Check byte

- f) After receipt of the PPS Request, the UICC simulator answers with the PPS Response "FF 10 95 7B" using a work waiting time of 9 600 etu (initial waiting time).
- g) The UICC simulator transmits with enhanced speed (F = 512, D = 16).

6.5.5 Acceptance criteria

After step b) the Terminal shall send to the UICC simulator the PPS Request "FF 10 94 7B".

After step c) the Terminal shall work with the UICC simulator.

After step e) the Terminal shall send to the UICC simulator the PPS Request "FF 10 95 7B".

After step f) the Terminal shall work with the UICC simulator.

7 Transmission protocol tests

7.1 Character transmission

7.1.1 Bit/character duration during the transmission from the Terminal to the UICC

7.1.1.1 Definition and applicability

A character consists of 10 consecutive bits:

- 1 start bit in state L;
- 8 bits, which comprise the data byte;
- 1 even parity checking bit.

For applicability of this test case see clause 3.8.

7.1.1.2 Conformance requirement

7.1.1.2.0 Description

The bit/character duration and the delay between two consecutive characters (between start leading edges) sent by the Terminal shall be in the range specified.

7.1.1.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.1.

7.1.1.3 Test purpose

To verify the timing during the transmission from the Terminal to the UICC.

7.1.1.4 Method of test

7.1.1.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

7.1.1.4.2 Procedure

A number of characters are transmitted from the Terminal to the UICC simulator. The UICC simulator shall measure the bit/character duration and the delay between two consecutive characters for all characters transmitted by the Terminal.

7.1.1.5 Acceptance criteria

The timing shall be in the specified range.

7.1.2 Bit/character duration during the transmission from the UICC to the Terminal

7.1.2.1 Definition and applicability

A character consists of 10 consecutive bits:

- 1 start bit in state L;
- 8 bits, which comprise the data byte;
- 1 even parity checking bit.

For applicability of this test case see clause 3.8.

7.1.2.2 Conformance requirement

7.1.2.2.0 Description

The bit/character duration and the delay between two consecutive characters (between start leading edges) sent by the Terminal shall be in the range specified.

7.1.2.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.1.

7.1.2.3 Test purpose

To verify the timing during the transmission from the UICC to the Terminal.

7.1.2.4 Method of test

7.1.2.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

7.1.2.4.2 Procedure

The UICC simulator shall send responses with the maximum and minimum bit/character duration specified in ETSI TS 102 221 [1].

7.1.2.5 Acceptance criteria

The Terminal shall accept the response and act accordingly.

7.2 T=0 protocol

7.2.1 Timing

7.2.1.1 Definition and applicability

The minimum interval between the leading edge of the start bits of two consecutive characters shall be at least 12 etu. The Work Waiting Time (WWT) is the maximum interval between the start leading edge of any character sent by the UICC and the start leading edge of the previous character sent by either by the UICC or the terminal.

The value of the WWT shall not exceed $960 \times WI \times Fi/f$. WI is an integer received in the specific interface byte TC2. The clock rate conversion factor, Fi, may be indicated in TA1.

For applicability of this test case see clause 3.8.

7.2.1.2 Conformance requirement

7.2.1.2.0 Description

- 1) If TA1 is absent the Terminal shall use the default value $Fi = 372$.
- 2) If no TC2 is available the Terminal shall use the default value of WI (10).
- 3) The Terminal shall accept characters sent by the UICC with the Work Waiting Time within the specified range.

7.2.1.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.2.1.

7.2.1.3 Test purpose

- 1) To verify the correct evaluation of the characters TA1 and TC2 indicated in the ATR.
- 2) To verify that the Terminal accepts the minimum and maximum Work Waiting Time during the transmission from the UICC to the Terminal.
- 3) To verify that the Terminal deactivates the UICC if WWT is exceeded.

7.2.1.4 Method of test

7.2.1.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

7.2.1.4.2 Procedure

- a) Upon reception of a reset the UICC simulator shall transmit the ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct or inverse convention
T0	'87'	TD1 only is present 7 bytes of historical bytes
TD1	'80'	TD2 only is present
TD2	'1F'	TA3 only is present Global interface bytes following
TA3	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services

Character	Value	Description
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'A3'	Check byte

b) Upon reception of a reset the UICC simulator shall transmit the ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct or inverse convention
T0	'97'	TA1 and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'C0'	TC2 and TD2 are present
TC2	'01'	WI=1 meaning WWT=960x(Fi/f)x1
TD2	'1F'	TA3 only is present Global interface bytes following
TA3	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'E3'	Check byte

c-1) The UICC simulator shall transmit with a WWT of 12 etu.

c-2) The UICC simulator shall transmit with the specified WWT ($960 \times (Fi/f) \times WI$).

c-3) The UICC simulator shall not transmit i.e. WWT exceeded.

7.2.1.5 Acceptance criteria

In step a), the Terminal shall work with the UICC simulator using the default values of TA1 and TC2.

In steps c-1) and c-2) the Terminal shall work with the UICC simulator.

In step c-3) the Terminal shall initiate a deactivation of the UICC within 960 etu following the excess of WWT.

7.2.2 Command processing, ACK, NACK, NULL procedure bytes

7.2.2.1 Definition and applicability

Procedure bytes are used to keep up the communication between the terminal and the UICC. They shall not be transmitted to the Application Layer.

The status bytes SW1 SW2 form an end sequence indicating the status of the UICC at the end of a command.

For applicability of this test case see clause 3.8.

7.2.2.2 Conformance requirement

7.2.2.2.0 Description

The Terminal shall correctly use the different modes of data transmission.

7.2.2.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.2.3.

ISO/IEC 7816-3 [2], clause 8.3.

7.2.2.3 Test purpose

To verify that the Terminal correctly uses the different modes of data transmission.

7.2.2.4 Method of test

7.2.2.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

T=0 ATR shall have been received and eventual PPS procedure successfully completed.

7.2.2.4.2 Procedure

- a) The Terminal shall be made to initiate a VERIFY PIN command with 8 bytes of data.
- b) The UICC simulator shall answer the first 5 bytes with ACK=INS complemented.
- c1) The UICC simulator shall answer the next data byte with NULL (NULL="60"). This byte is sent between 0,8 and 1,0 x Work Waiting Time after the previous procedure byte.
- c2) The UICC simulator shall send a second NULL (NULL="60"). This byte is sent between 0,8 and 1,0 x Work Waiting Time after the previous procedure byte.
- c3) The UICC simulator shall send a third NULL (NULL="60"). This byte is sent between 0,8 and 1,0 x Work Waiting Time after the previous procedure byte.
- d) The UICC simulator shall then send ACK=INS. This byte is sent between 0,8 and 1,0 x Work Waiting Time after the previous procedure byte.
- e) The UICC simulator shall answer the transmission of the rest of the data with NULL.
- f) The UICC simulator shall then send SW1 and SW2, indicating correct execution of the command ("90" and "00" for SW1 and SW2 respectively). These bytes are sent when the elapsed time since step d) is greater than the Work Waiting Time.

7.2.2.5 Acceptance criteria

The command shall be executed correctly.

7.2.3 Case 2 command, use of procedure bytes '61xx' and '6Cxx'

7.2.3.1 Definition and applicability

Procedure bytes '61XX' and '6CXX' are returned by the UICC to control exchanges between the Transport Layer of the Terminal and the UICC, and should never be returned to the Application Layer of the Terminal. Command processing in the UICC is not complete if it has returned procedure bytes '61XX' or '6CXX'.

For applicability of this test case see clause 3.8.

7.2.3.2 Conformance requirement

7.2.3.2.0 Description

The UICC returns procedure bytes '61xx' and '6Cxx' to the Transport Layer of the Terminal to indicate to it the manner in which it should retrieve the data requested by the command currently being processed. These procedure bytes are only used when processing case 2 and 4 commands using T=0.

7.2.3.2.1 Reference

ETSI TS 102 221 [1], clause 7.3.1.1.5.

ISO/IEC 7816-3 [2], clause 8.3.

7.2.3.3 Test purpose

To verify that the Terminal correctly handles the procedure bytes '61XX' and '6CXX' when processing a case 2 command.

7.2.3.4 Method of test

7.2.3.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

T=0 ATR shall have been received and eventual PPS procedure successfully completed.

7.2.3.4.2 Procedure

- a) The Terminal shall be made to initiate a case 2 command with $Le > Luicc$ (ex: READ RECORD command).
- b) The UICC simulator shall send '6CLuicc' procedure bytes.
- c) Following receipt of the command, the UICC simulator shall send '61xx' procedure bytes.
- d) Following receipt of the command, the UICC simulator shall send corresponding data + '61yy' procedure bytes.
- e) Following receipt of the command, the UICC simulator shall then send the rest of the data and SW1 and SW2, indicating correct execution of the command ("90" and "00" for SW1 and SW2 respectively).

7.2.3.5 Acceptance criteria

After step b) the Terminal shall send the previous command with $Le = Luicc$.

After step c) the Terminal shall send a GET RESPONSE command with $Le = 'xx'$.

After step f) the Terminal shall send a GET RESPONSE command with $Le = 'yy'$.

7.2.4 Case 4 command, use of procedure bytes '61xx'

7.2.4.1 Definition and applicability

Procedure bytes '61XX' and '6CXX' are returned by the UICC to control exchanges between the Transport Layer of the Terminal and the UICC, and should never be returned to the Application Layer of the Terminal. Command processing in the UICC is not complete if it has returned procedure bytes '61XX' or '6CXX'.

For applicability of this test case see clause 3.8.

7.2.4.2 Conformance requirement

7.2.4.2.0 Description

The UICC returns procedure bytes '61xx' and '6Cxx' to the Transport Layer of the Terminal to indicate to it the manner in which it should retrieve the data requested by the command currently being processed. These procedure bytes are only used when processing case 2 and 4 commands using T=0.

7.2.4.2.1 Reference

ETSI TS 102 221 [1], clause 7.3.1.1.5.

ISO/IEC 7816-3 [2], clause 8.3.

7.2.4.3 Test purpose

To verify that the Terminal correctly handles the procedure bytes '61XX' when processing a case 4 command.

7.2.4.4 Method of test

7.2.4.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

T=0 ATR shall have been received and eventual PPS procedure successfully completed.

7.2.4.4.2 Procedure

- a) The Terminal shall be made to initiate a case 4 command with Le > Luicc (ex: SELECT command).
- b) The UICC simulator shall answer the command header with INS and send '61xx' procedure bytes following reception of data.
- c) Following receipt of the command, the UICC simulator shall send corresponding data + '61yy' procedure bytes.
- d) Following receipt of the command, the UICC simulator shall then send the rest of the data and SW1 and SW2, indicating correct execution of the command ("90" and "00" for SW1 and SW2 respectively).

7.2.4.5 Acceptance criteria

After step b) the Terminal shall send a GET RESPONSE command with Le = 'xx'.

After step c) the Terminal shall send a GET RESPONSE command with Le = 'yy'.

7.2.5 Command processing, warning and error status bytes

7.2.5.1 Definition and applicability

The status bytes SW1 SW2 form an end sequence indicating the status of the UICC at the end of a command.

For applicability of this test case see clause 3.8.

7.2.5.2 Conformance requirement

7.2.5.2.0 Description

In the case of an error, the UICC may return status indicating error or warning conditions instead of the '61xx' or '6Cxx' response.

7.2.5.2.1 Reference

ETSI TS 102 221 [1], clauses 7.2.2.3 and 10.2.1.

7.2.5.3 Test purpose

To verify that the Terminal correctly handles status bytes different than '9000'.

7.2.5.4 Method of test

7.2.5.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

T=0 ATR shall have been received and eventual PPS procedure successfully completed.

7.2.5.4.2 Procedure

a) Warning:

- a-1) The Terminal shall be made to initiate a case 4 command except for SEARCH RECORD (ex: SELECT command).
- a-2) The UICC simulator shall send warning status bytes ('62xx' '63xx' or '9xxx').
- a-3) Following receipt of the command, the UICC simulator shall then send the rest of the data and SW1 and SW2, indicating correct execution of the command ("90" and "00" for SW1 and SW2 respectively).

b) Error:

- b-1) The Terminal shall be made to initiate a case 4 command (ex: SELECT command).
- b-2) The UICC simulator shall send error status bytes ('6xxx' except '6Cxx', '61xx', '62xx' and '63xx').

7.2.5.5 Acceptance criteria

After step a-2) the Terminal shall send a GET RESPONSE command with Le = '00'.

After step b-2) the Terminal shall discontinue processing of the command.

7.2.6 Error correction

7.2.6.1 Definition and applicability

If the UICC as receiver detects a parity error within $11 \text{ etu} \pm 0,2 \text{ etu}$ starting from the leading edge of the start bit, in a character just received, it shall set I/O to state L to indicate the error to the Terminal.

For applicability of this test case see clause 3.8.

7.2.6.2 Conformance requirement

7.2.6.2.0 Description

The error detection and correction procedure is mandatory for T=0 protocol except for the Terminal during the ATR-procedure.

7.2.6.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.2.4.

7.2.6.3 Test purpose

To verify the error handling during the transmission from the Terminal to the UICC.

7.2.6.4 Method of test

7.2.6.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

7.2.6.4.2 Procedure

The UICC simulator shall transmit an error signal in response to a received character by setting the I/O line to state L for a maximum of 2 etu and a minimum of 1 etu, $10,5 \text{ etu} \pm 0,2 \text{ etu}$ after the leading edge of the start bit of the received character.

7.2.6.5 Acceptance criteria

The Terminal shall repeat the disputed character after a minimum delay of 2 etu.

7.2.7 Error detection

7.2.7.1 Definition and applicability

If the Terminal as receiver detects a parity error within $11 \pm 0,2 \text{ etu}$ starting from the leading edge of the start bit, in a character just received, it shall set I/O to state L to indicate the error to the UICC.

For applicability of this test case see clause 3.8.

7.2.7.2 Conformance requirement

7.2.7.2.0 Description

The error detection and correction procedure is mandatory for T=0 protocol except for the Terminal during the ATR-procedure.

7.2.7.2.1 Reference

- ETSI TS 102 221 [1], clause 7.2.2.4.

7.2.7.3 Test purpose

To verify the error handling during the transmission from the UICC to the Terminal.

7.2.7.4 Method of test

7.2.7.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

7.2.7.4.2 Procedure

The UICC simulator shall send a response with a parity error and check that the terminals correctly handles it.

7.2.7.5 Acceptance criteria

The Terminal shall detect the parity error by setting the I/O line to state L for a maximum of 2 etu and a minimum of 1 etu, 10,5 etu \pm 0,2 etu after the leading edge of the start bit of the erroneous character and correctly evaluate the character when repeated by the UICC simulator.

7.3 T=1 protocol

7.3.1 Character Waiting Time

7.3.1.1 Definition and applicability

CWT is defined as the maximum delay between the leading edges of two consecutive characters in the block.

For applicability of this test case see clause 3.8.

7.3.1.2 Conformance requirement

7.3.1.2.0 Description

CWI is used to calculate CWT and shall be in the range from 0 to 5. The value is set in bits b4 to b1 in TB3. The value of CWT may be calculated from the following equation: $CWT = (11 + 2^{CWI})$ etu.

7.3.1.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.1.

ISO/IEC 7816-3 [2], clause 9.5.3.

7.3.1.3 Test purpose

To verify that the Terminal respects the CWT indicated by the UICC.

7.3.1.4 Method of test

7.3.1.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

7.3.1.4.2 Procedure

- a) Upon reception of a reset the UICC simulator shall transmit the ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1, and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'81'	Only TD2 is present Protocol T=1 supported by UICC
TD2	'A1'	TB3 and TD3 are present Protocol T=1 supported by UICC
TB3	'05'	Block Waiting Integer=0 Character Waiting Integer=5 indicating CWT=43 etu
TD3	'1F'	Only TA4 is present Global interface bytes following (T=15)
TA4	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC

Character	Value	Description
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'07'	Check byte

- b) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring reception of an I-Block.
- b-1) The UICC simulator shall send the I-Block (data + '9000' indicating correct execution of the command) using CWT=11 etu.
- b-2) The UICC simulator shall send the I-Block (data + '9000' indicating correct execution of the command) using CWT=43 etu.

7.3.1.5 Acceptance criteria

In step b.1) and b.2) the Terminal shall acknowledge the error free I-Block.

7.3.2 Block Timing

7.3.2.1 Definition and applicability

BWT is defined as the maximum delay between the leading edge of the last character of the block received by the card and the leading edge of the first character of the next block sent by the card.

BGT is defined as the minimum delay between the leading edge of two consecutive characters sent in opposite directions. The value of BGT shall be 22 etu.

For applicability of this test case see clause 3.8.

7.3.2.2 Conformance requirement

7.3.2.2.0 Description

BWI is used to calculate BWT and shall be in the range from 0 to 4. The value is set in bits b5 to b8 in TB3. The value of BWT may be calculated from the following equation: $BWT = 11 + (2^{BWI} \times 960 \times 372/f)$ etu.

The delay between the last character of a block received by the UICC and the first character of the next block sent from the UICC shall be in the interval: $BGT < \text{delay} < BWT$.

7.3.2.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.

ISO/IEC 7816-3 [2], clause 9.5.3.

7.3.2.3 Test purpose

To verify that the Terminal respects the BGT and BWT indicated by the UICC in the ATR and detects time-out.

7.3.2.4 Method of test

7.3.2.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

7.3.2.4.2 Procedure

- a) Upon reception of a reset the UICC simulator shall transmit the ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1, and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'81'	Only TD2 is present Protocol T=1 supported by UICC
TD2	'A1'	TB3 and TD3 are present Protocol T=1 supported by UICC
TB3	'31'	Block Waiting Integer=3 indicating BWT = 11 + (8 × 960 × 372 / f) etu Character Waiting Integer=1 indicating CWT=13 etu
TD3	'1F'	Only TA4 is present Global interface bytes following
TA4	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'33'	Check byte

- b) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring reception of chained I-Blocks.
- c) The UICC simulator shall measure the delay between the last character of each block sent by the UICC and the first character of each following block sent by the Terminal.
- d) BWT:
- d-1) The UICC simulator shall send the I-Blocks using $BGT = 22$ etu.
- d-2) The UICC simulator shall send each I-Block using $BWT = 11 + (2^{BWI} \times 960 \times 372 / f)$ etu.
- BWT excess:
- d-3) The UICC simulator shall not send an I-Block.

7.3.2.5 Acceptance criteria

In step c) the Terminal shall use a BGT of at least 22 etus.

In steps d-1) and d-2) the Terminal shall acknowledge reception of the I-Blocks without error.

In step d-3) the Terminal shall detect a time-out and send an R-Block requesting retransmission of the last block.

7.3.3 Block Waiting Time extension

7.3.3.1 Definition and applicability

WTX is a parameter used to ask for more time to process a command.

Supervisory blocks, S-block, are used to send control information.

S-blocks are always used in pairs. A S(request) is always followed by a S(response) block:

- S(WTX request), a request for an extension of the waiting time.
- S(WTX response), an acknowledge of the extension of the waiting time.

For applicability of this test case see clause 3.8.

7.3.3.2 Conformance requirement

7.3.3.2.0 Description

The UICC might need more than BWT to process the previously received block, a S(WTX request) is sent by the UICC. The terminal shall acknowledge with a S(WTX response).

When an S(... request) has been sent and either a BWT time-out occurs (with the terminal) or the received response is not a S(... response), the S(... request) shall be resent.

7.3.3.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.1.

ISO/IEC 7816-3 [2], clauses 9.5.3 and 9.7.3, scenarios 2, 14 and 15.

7.3.3.3 Test purpose

- 1) To verify that the Terminal respects the WTX procedure and applies the extended BWT.
- 2) To verify that the Terminal handles the different types of errors in S(... request).

7.3.3.4 Method of test

7.3.3.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

7.3.3.4.2 Procedure

- a) Upon reception of a reset the UICC simulator shall transmit the ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1, and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'81'	Only TD2 is present Protocol T=1 supported by UICC
TD2	'A1'	TB3 and TD3 are present Protocol T=1 supported by UICC
TB3	'21'	Block Waiting Integer=2 indicating BWT = 11 + (4 x 960 x 372/f) etu Character Waiting Integer=1 indicating CWT=13 etu
TD3	'1F'	Only TA4 is present Global interface bytes following

Character	Value	Description
TA4	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'23'	Check byte

- b) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring exchange of I-Blocks.
- c-1) Error free S(WTX request):
- c-1-1) Following receipt of the I-block, the UICC simulator shall send a S(WTX request) without error (BWT multiplied by 2).
 - c-1-2) The UICC simulator shall use the extended BWT when receiving the S(WTX response), then complete the command (data + '9000' indicating correct execution of the command).
- c-2) Error in S(WTX request):
- c-2-1) Following receipt of the I-block, the UICC simulator shall send a S(WTX request) and generate the following errors:
 - Parity error.
 - NAD ≠ '00'.
 - S(WTX response) instead of S(WTX request).
 - Other S(... response) instead of S(WTX request).
 - LEN error.
 - c-2-2) Following reception of the block sent by the Terminal (correct or with error assumed) the UICC simulator shall retransmit the S(WTX request) without error.
 - c-2-3) The UICC simulator shall use the extended BWT when receiving the S(WTX response), then complete the command (data + '9000' indicating correct execution of the command).

7.3.3.5 Acceptance criteria

After steps c-1-1) and c-2-2) the Terminal shall send a S(WTX response).

After step c-2-1) the Terminal shall send an R-Block requesting retransmission of the last block.

7.3.4 Chaining - Respect of IFSC by Terminal

7.3.4.1 Definition and applicability

Chaining allows the terminal or the UICC to transfer information, which is longer than IFSC or IFSD. If information longer than IFSC or IFSD is transferred, the information should be divided into pieces, each has a length \leq IFSC or IFSD. Each piece should be sent in an I-block using the chaining function.

The IFSC defines the maximum length of the information field of blocks that can be received by the UICC.

For applicability of this test case see clause 3.8.

7.3.4.2 Conformance requirement

7.3.4.2.0 Description

The default value of the IFSC is 32 bytes. Another value may be indicated in TA3 of the ATR.

When the terminal is the sender, all I-blocks of a chain shall have LEN = IFSC bytes except for the last, which could have a value in the range of 0 to IFSC.

When a receiver receives a more-data I-block, a R(N(R)) shall be sent. N(R) = N(S) of the expected I-block. At least one chained block should follow.

7.3.4.2.1 Reference

ETSI TS 102 221 [1], clauses 7.2.3.1.1 and 7.2.3.5.

ISO/IEC 7816-3 [2], clause 9.7.3, scenarios 5 and 6.

7.3.4.3 Test purpose

To verify that the Terminal respects the Information Field Size of the UICC in chaining mode.

7.3.4.4 Method of test

7.3.4.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

7.3.4.4.2 Procedure

a) No TA3:

a-1) Upon reception of a reset the UICC simulator shall transmit the ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1, and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'81'	Only TD2 is present Protocol T=1 supported by UICC
TD2	'A1'	TB3 and TD3 are present Protocol T=1 supported by UICC
TB3	'00'	Block Waiting Integer=0 Character Waiting Integer=0
TD3	'1F'	Only TA4 is present Global interface bytes following
TA4	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'02'	Check byte

- a-2) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring sending of chained I-Blocks.
- a-3) Following receipt of the command, the UICC simulator shall evaluate the length and acknowledge reception of the received I-Blocks without error.
- b) TA3='FE':
- b-1) Upon reception of a reset the UICC simulator shall transmit the ATR as follows:

Character	Value	Description
TS	'3B'	Indicates direct convention
T0	'97'	TA1, and TD1 are present 7 bytes of historical bytes
TA1	'11'	Clock rate conversion factor FI=1 (F=372) Baud rate adjustment factor DI=1 (D=1)
TD1	'81'	Only TD2 is present Protocol T=1 supported by UICC
TD2	'B1'	TA3, TB3 and TD3 are present Protocol T=1 supported by UICC
TA3	'FE'	IFSC is 254 bytes long
TB3	'00'	Block Waiting Integer=0 Character Waiting Integer=0
TD3	'1F'	Only TA4 is present Global interface bytes following
TA4	'46'	Clock stop supported (low electrical state) 1,8 V technology UICC
T1	'80'	
T2	'31'	Card data services
T3	'A0'	SELECT by AID supported EFDIR present
T4	'73'	Card capabilities
T5	'BE'	SFI supported
T6	'21'	Data Coding Byte
T7	'00'	No extended Lc and Le No Logical channels supported
TCK	'EC'	Check byte

- b-2) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring sending of chained I-Blocks.
- b-3) Following receipt of the command, the UICC simulator shall evaluate the length and acknowledge reception of the received I-Blocks without error.

7.3.4.5 Acceptance criteria

In step a-2) the Terminal shall send the chained I-Blocks, except the last one, using the default value of IFSC, i.e. 32 bytes long information field.

In step b-2) the Terminal shall send the chained I-Blocks, except the last one, using the specified value of IFSC, i.e. 254 bytes long information field.

7.3.5 Chaining - IFSD management

7.3.5.1 Definition and applicability

Chaining allows the Terminal or the UICC to transfer information, which is longer than IFSC or IFSD. If information longer than IFSC or IFSD is transferred, the information should be divided into pieces, each has a length \leq IFSC or IFSD. Each piece should be sent in an I-block using the chaining function.

When a receiver receives a more-data I-block, a R(N(R)) shall be sent. N(R) = N(S) of the expected I-block. At least one chained block should follow.

The IFSD defines the maximum length of the information field of blocks that the terminal can receive.

The default value of the IFSD is 32 bytes and may be adjusted during the card session. The maximum value of the IFSD is 254 bytes.

For applicability of this test case see clause 3.8.

7.3.5.2 Conformance requirement

7.3.5.2.0 Description

When the UICC is the sender, all I-blocks of a chain shall have $LEN \leq IFSD$ bytes per block.

7.3.5.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.

7.3.5.3 Test purpose

To verify that the Terminal correctly handles the Information Field Size in chaining mode.

7.3.5.4 Method of test

7.3.5.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

ATR shall have been received and eventual PPS procedure successfully completed.

7.3.5.4.2 Procedure

- a) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring reception of chained I-Blocks.
- b) The UICC simulator shall send an I-Block with $LEN > IFSD$.
- c) Following correct receipt of the next block the UICC simulator shall send the rest of I-Blocks (data + '9000' indicating correct execution of the command).

7.3.5.5 Acceptance criteria

In step b), the Terminal shall detect the incorrect LEN and send an R-Block requesting retransmission of the last block.

In step c) the Terminal shall acknowledge reception of the I-Blocks without error by sending R-Blocks with $N(R)=\text{sequence number of expected I-Block}$.

7.3.6 I-Block error correction

7.3.6.1 Definition and applicability

Information blocks are used to transfer command and response APDUs.

The I-blocks are denoted as follows: $I(N(S), M)$ where:

- $N(S)$ is the send-sequence number of the block.
- M is the more-data bit used in the chaining function.

For applicability of this test case see clause 3.8.

7.3.6.2 Conformance requirement

7.3.6.2.0 Description

When an I-block has been sent and a BWT time-out occurs or an invalid block has been received (with the terminal), an R-block is sent, which requests with its N(R) for the expected I-block with $N(S)=N(R)$.

7.3.6.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.4.

ISO/IEC 7816-3 [2], clause 9.7.3, scenario 8.

7.3.6.3 Test purpose

To verify that the Terminal sends an I-Block again when notified incorrect reception by the UICC (R-Block meaning error).

7.3.6.4 Method of test

7.3.6.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

ATR shall have been received and eventual PPS procedure successfully completed.

7.3.6.4.2 Procedure

- a) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring sending of chained I-Blocks.
- b) The UICC simulator shall assume each transmitted I-Block, including the last non-chained one, is invalid by sending an R-Block requesting retransmission.

7.3.6.5 Acceptance criteria

In step b), the Terminal shall resend each disputed I-Block.

7.3.7 I-Block error detection

7.3.7.1 Definition and applicability

Information blocks are used to transfer command and response APDUs.

The I-blocks are denoted as follows: $I(N(S), M)$ where:

- $N(S)$ is the send-sequence number of the block.
- M is the more-data bit used in the chaining function.

For applicability of this test case see clause 3.8.

7.3.7.2 Conformance requirement

7.3.7.2.0 Description

When an I-block has been sent and a BWT time-out occurs or an invalid block has been received (with the terminal), an R-block is sent, which requests with its N(R) for the expected I-block with $N(S)=N(R)$.

7.3.7.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.4.

ISO/IEC 7816-3 [2], clause 9.7.3, scenario 9.

7.3.7.3 Test purpose

To verify that the Terminal correctly handles the different types of invalid I-Blocks.

7.3.7.4 Method of test

7.3.7.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

ATR shall have been received and eventual PPS procedure successfully completed.

7.3.7.4.2 Procedure

- a) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring reception of I-Blocks.
- b) The UICC simulator shall send I-Blocks and generate the following errors:
 - Parity error.
 - NAD \neq '00'.
 - PCB with wrong sequence number.
 - PCB of an R-Block.
 - PCB of an S-Block.
 - LEN error (= 'FF').
 - EDC error.
- c) Following correct reception of the block sent by the Terminal, the UICC simulator shall retransmit the I-Block without error and complete the command (data + '9000' indicating correct execution of the command).

NOTE: Test can be achieved either by generating the errors in one session using chained blocks or through separate tests generating one error.

7.3.7.5 Acceptance criteria

In step b), the Terminal shall detect the invalid block and send an R-Block requesting retransmission of the last block (N(R)=sequence number of last I-Block).

In step c) the Terminal shall acknowledge reception of the I-Block without error.

7.3.8 R-Block error handling in non-chaining mode

7.3.8.1 Definition and applicability

Receive-ready blocks, R-blocks, are used to transfer acknowledgements.

The R-blocks are denoted as follows: R(N(R)), where:

- N(R) is the number of the expected I-block.

For applicability of this test case see clause 3.8.

7.3.8.2 Conformance requirement

7.3.8.2.0 Description

When an R-block was sent and an invalid block is received or BWT time-out, the R-block will be resent.

7.3.8.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.4.

ISO/IEC 7816-3 [2], clause 9.7.3, scenario 10.

7.3.8.3 Test purpose

To verify that the Terminal handles the different types of invalid R-Blocks and correctly recovers while sending non-chained data.

7.3.8.4 Method of test

7.3.8.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

ATR shall have been received and eventual PPS procedure successfully completed.

7.3.8.4.2 Procedure

- a) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring sending of a non-chained I-Block.
- b) The UICC simulator shall assume the received block is invalid by sending an R-Block and generate the following errors:
 - Parity error.
 - NAD \neq '00'.
 - PCB with wrong sequence number.
 - PCB with b6=1.
 - PCB of an S-Block.
 - LEN error.
 - EDC error.
- c) Following correct reception of the block sent by the Terminal, the UICC simulator shall retransmit the R-Block without error.

7.3.8.5 Acceptance criteria

In step b) the Terminal shall detect the invalid block and send an R-Block requesting retransmission of the last block (N(R)=sequence number of invalid R-Block).

After step c), the Terminal shall resend the first I-Block.

7.3.9 R-Block error handling in chaining mode

7.3.9.1 Definition and applicability

Receive-ready blocks, R-blocks, are used to transfer acknowledgements.

The R-blocks are denoted as follows: R(N(R)), where:

- N(R) is the number of the expected I-block.

For applicability of this test case see clause 3.8.

7.3.9.2 Conformance requirement

7.3.9.2.0 Description

When an R-block was sent and an invalid block is received or BWT time-out, the R-block will be resent.

7.3.9.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.4.

ISO/IEC 7816-3 [2], clause 9.7.3, scenario 21.

7.3.9.3 Test purpose

To verify that the Terminal handles the different types of invalid R-Blocks and correctly recovers while sending chained data.

7.3.9.4 Method of test

7.3.9.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

ATR shall have been received and eventual PPS procedure successfully completed.

7.3.9.4.2 Procedure

- a) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring sending of chained I-Blocks.
- b) The UICC simulator shall send an invalid R-Block and generate the following errors:
 - Parity error.
 - NAD \neq '00'.
 - PCB with b6=1.
 - PCB of an S-Block.
 - LEN error.
 - EDC error.
- c) Following correct reception of the block sent by the Terminal, the UICC simulator shall retransmit the R-Block without error.

7.3.9.5 Acceptance criteria

In step b) the Terminal shall detect the invalid block and send an R-Block requesting retransmission of the last block (N(R)=sequence number of invalid R-Block).

After step c), the Terminal shall send the rest of chained data (I-Block).

7.3.10 Successive errors in both directions

7.3.10.1 Definition and applicability

Receive-ready blocks, R-blocks, are used to transfer acknowledgements.

The R-blocks are denoted as follows: R(N(R)), where:

- N(R) is the number of the expected I-block.

For applicability of this test case see clause 3.8.

7.3.10.2 Conformance requirement

7.3.10.2.0 Description

When an R-block was sent and an invalid block is received or BWT time-out, the R-block will be resent.

7.3.10.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.4.

ISO/IEC 7816-3 [2], clause 9.7.3, scenarios 12 and 13.

7.3.10.3 Test purpose

To verify that the Terminal properly recovers after receiving and being notified errors successively.

7.3.10.4 Method of test

7.3.10.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

ATR shall have been received and eventual PPS procedure successfully completed.

7.3.10.4.2 Procedure

- Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring reception of I-Blocks.
- The UICC simulator shall send an invalid I-Block.
- Following correct reception of the block sent by the Terminal, the UICC simulator shall assume the received block is invalid by sending an R-Block, also invalid.
- Following correct reception of the block sent by the Terminal:

d-1) No error:

d-1-1) The UICC simulator shall retransmit the I-Block without error and complete the command (data + '9000' indicating correct execution of the command).

d-2) Error assumed:

d-2-1) The UICC simulator shall assume the received block is invalid by sending an R-Block requesting retransmission (N(R)= correct sequence number of step c)).

d-2-2) Following correct reception of the block sent by the Terminal, the UICC simulator shall complete the command (data + '9000' indicating correct execution of the command).

7.3.10.5 Acceptance criteria

After step b) and c), the Terminal shall detect the invalid block and send an R-Block requesting retransmission of the last block (N(R)=sequence number of invalid I-Block).

After step d-2-1), the Terminal shall resend the previous R-Block with N(R)=sequence number of invalid I-Block.

After step d-1) and d-2-2), the Terminal shall acknowledge the error free I-Block(s).

7.3.11 Chaining - Abortion

7.3.11.1 Definition and applicability

Supervisory blocks, S-block, are used to send control information.

S-blocks are always used in pairs. A S(request) is always followed by a S(response) block:

- S(ABORT request), a request to abort the chain function.
- S(ABORT response), an acknowledge of the abortion of the chain function.

For applicability of this test case see clause 3.8.

7.3.11.2 Conformance requirement

7.3.11.2.0 Description

When an S(... request) has been sent and either a BWT time-out occurs (with the terminal) or the received response is not a S(... response), the S(... request) shall be resent. But if an S(... response) has been sent and either an invalid block is received or a BWT time-out occurs (with the terminal), an R-block shall be sent.

7.3.11.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.4.

ISO/IEC 7816-3 [2], clause 9.7.3, scenarios 26 and 27.

7.3.11.3 Test purpose

To verify that the Terminal correctly handles the abortion procedure in chaining mode.

7.3.11.4 Method of test

7.3.11.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

ATR shall have been received and eventual PPS procedure successfully completed.

7.3.11.4.2 Procedure

- a) Terminal sends chained data:
 - a-1) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring sending of chained I-Blocks.
 - a-2) The UICC simulator shall acknowledge receipt of the first chained I-Block by sending an R-Block without error.
 - a-3) Following receipt of the second I-Block, the UICC simulator shall send an S(ABORT request).
 - a-4) The UICC simulator shall acknowledge receipt of the response and give back the Terminal the right to send (R-Block without error) and complete the next command.
- b) UICC sends chained data:
 - b-1) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring reception of chained I-Blocks.
 - b-2) The UICC simulator shall transmit the first chained I-Block without error.
 - b-3) Following correct reception of the block sent by the Terminal, the UICC simulator shall send an S(ABORT request).
 - b-4) The UICC simulator shall acknowledge receipt of the response without error.
 - b-5) The UICC simulator shall restart and complete the command (data + '9000' indicating correct execution of the command).

7.3.11.5 Acceptance criteria

After steps a-3) and b-3), the Terminal shall send an S(ABORT response).

In step b-5) the Terminal shall acknowledge reception of the I-Blocks without error by sending R-Blocks with N(R)=sequence number of expected I-Block.

7.3.12 Block repetition and resynchronization

7.3.12.1 Definition and applicability

Resynchronization of the protocol may be attempted at three consecutive levels. If one level is unsuccessful, then the next level is tried:

- For the terminal, the three levels are:
 - Retransmission of blocks.
 - Use of S(RESYNCH request).
 - Card reset or deactivation.

Supervisory blocks, S-block, are used to send control information.

S-blocks are always used in pairs. A S(request) is always followed by a S(response) block:

- S(RESYNCH request), a request of a resynchronization.
- S(RESYNCH response), an acknowledge of the resynchronization.

For applicability of this test case see clause 3.8.

7.3.12.2 Conformance requirement

7.3.12.2.0 Description

When an S(... request) has been sent and either a BWT time-out occurs (with the terminal) or the received response is not a S(... response), the S(... request) shall be resent. But if an S(... response) has been sent and either an invalid block is received or a BWT time-out occurs (with the terminal), an R-block shall be sent.

If the terminal fails to receive an error-free block during a card-session, a maximum of two further attempts is allowed before a S(RESYNCH request) is sent.

7.3.12.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.4.

ISO/IEC 7816-3 [2], clause 9.7.3, scenarios 29, 30, 31, 32 and 34.

7.3.12.3 Test purpose

- 1) To verify that the Terminal resynchronizes the UICC if block repetition is unsuccessful.
- 2) To verify that the Terminal correctly handles an invalid response to an S(... request).

7.3.12.4 Method of test

7.3.12.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

ATR shall have been received and eventual PPS procedure successfully completed.

7.3.12.4.2 Procedure

- a) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring sending of an I-Block.
- b) Following receipt of the first I-Block, the UICC simulator shall send an erroneous block or be unresponsive.
- c) Following correct reception of the block sent by the Terminal, the UICC simulator shall send two more erroneous blocks or remain unresponsive two more times:
 - c-1) No error:
 - c-1-1) Following correct reception of the block (S(RESYNCH request)) sent by the Terminal, the UICC simulator shall send a S(RESYNCH response), then complete the next command without error.
 - c-2) Error assumed:
 - c-2-1) Following correct reception of the block (S(RESYNCH request)) sent by the Terminal, the UICC simulator shall send a S(RESYNCH response) and generate the following errors:
 - Parity error.
 - NAD ≠ '00'.
 - LEN error (≠ '01').
 - S(RESYNCH request) instead of S(RESYNCH response).
 - Other S(... response).
 - EDC error.

c-2-2) Following correct reception of the block (S(RESYNCH request)) sent by the Terminal, the UICC simulator shall send a S(RESYNCH response), then complete the next command without error.

7.3.12.5 Acceptance criteria

After step b), the Terminal shall send an R-Block requesting retransmission.

In step c), the Terminal shall send the same R-Block as in b) two more times, then initiate an S(RESYNCH request).

After step c-2-1), the Terminal shall resend an S(RESYNCH request).

7.3.13 UICC is unresponsive

7.3.13.1 Definition and applicability

Resynchronization of the protocol may be attempted at three consecutive levels. If one level is unsuccessful, then the next level is tried:

- For the terminal, the three levels are:
 - Retransmission of blocks.
 - Use of S(RESYNCH request).
 - Card reset or deactivation.

For applicability of this test case see clause 3.8.

7.3.13.2 Conformance requirement

7.3.13.2.0 Description

After an ATR due to a Warm reset or successful PPS procedure, the communication between the terminal and the UICC can be initiated. But if the terminal fails to receive an error-free block, in the beginning of the protocol, a maximum of two more successive attempts to receive the block is allowed before resetting or a deactivation of the card takes place.

If the terminal fails to receive an error-free block during a card-session, a maximum of two further attempts is allowed before a S(RESYNCH request) is sent.

7.3.13.2.1 Reference

ETSI TS 102 221 [1], clause 7.2.3.4.

ISO/IEC 7816-3 [2], clause 9.7.3, scenarios 33 and 35.

7.3.13.3 Test purpose

To verify that the Terminal correctly resets or deactivates the UICC at the start of the protocol and during the protocol if resynchronization is unsuccessful.

7.3.13.4 Method of test

7.3.13.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, and powered on.

ATR shall have been received and eventual PPS procedure successfully completed.

7.3.13.4.2 Procedure

- a) At the start of the protocol:
 - a-1) Following receipt of the first block, the UICC simulator shall be unresponsive.
 - a-2) Following correct reception of the block sent by the Terminal, the UICC simulator shall remain unresponsive two more times.
- b) During the protocol:
 - b-1) Following receipt of the first block by the UICC simulator, the Terminal shall be made to initiate a command requiring sending of an I-Block.
 - b-2) Following receipt of the first I-Block, the UICC simulator shall be unresponsive.
 - b-3) Following correct reception of the block sent by the Terminal, the UICC simulator shall remain unresponsive two more times.
 - b-4) Following correct reception of the block (S(RESYNCH request)) sent by the Terminal, the UICC simulator shall remain unresponsive three more times.

7.3.13.5 Acceptance criteria

After step a-1), the Terminal shall:

- Send an R-Block if the first block it sent was an I-Block.
- Repeat the S-Block if the first block it sent was an S-Block.

In step a-2), the Terminal shall send the same block as in a-1) two more times, then reset or deactivate the UICC.

After step b-2), the Terminal shall send an R-Block with $N(R)=$ sequence number of previous I-Block.

In step b-3), the Terminal shall send the same R-Block as in b-2) two more times, then initiate an S(RESYNCH request).

In step b-4), the Terminal shall resend S(RESYNCH request) two more times, then reset or deactivate the UICC.

8 Application dependent procedures

8.1 UICC presence detection

8.1.1 Definition and applicability

To ensure that the UICC has not been removed during a card session, the Terminal sends, at frequent intervals, a STATUS command during each voice call.

This procedure shall be used in addition to a mechanical or other device used to detect the removal of a UICC.

8.1.2 Conformance requirement

8.1.2.0 Description

A STATUS command shall be issued within all 30 seconds periods of inactivity on the UICC-Terminal interface during a voice call. Inactivity in this case is defined as starting at the end of the last communication or the last issued STATUS command. If no response data is received to this STATUS command, then the voice call shall be terminated as soon as possible but at least within 5 seconds after the STATUS command has been sent. If the DF indicated in response to a STATUS command is not the same as that which was indicated in the previous response, or accessed by the previous command, then the voice call shall be terminated as soon as possible but at least within 5 seconds after the response data has been received.

8.1.2.1 Reference

ETSI TS 102 221 [1], clause 14.5.2.

8.1.3 Test purpose

To verify that:

- 1) There are no periods of inactivity on the UICC-Terminal interface greater than 30 seconds during a call.
- 2) The Terminal terminates a voice call within 5 seconds at the latest after having received an invalid response to the STATUS command.

8.1.4 Method of test

8.1.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator.

All elementary files shall be coded as default.

8.1.4.2 Procedure

- a) A call shall be set up using the generic voice call setup.
- b) The UICC simulator shall monitor the time of periods of inactivity on the UICC-Terminal interface.
- c) After 3 minutes, the voice call shall be cleared.
- d) A call shall be set up using the generic voice call setup.
- e) After one minute after the call was successfully set up, the UICC simulator shall respond to a STATUS command with the response data of the MF.

8.1.5 Acceptance criteria

- 1) During step b), the time of periods of inactivity on the UICC-Terminal interface shall not be longer than 30 seconds.
- 2) After step e), the Terminal shall terminate the voice call within 5 seconds at the latest after having received the wrong response to the STATUS command.

9 Commands

9.1 TERMINAL CAPABILITY

9.1.1 Additional interfaces support

9.1.1.1 Definition and applicability

Terminals supporting an interface in addition to the interface defined in ETSI TS 102 221 [1] shall indicate it to the UICC by issuing the TERMINAL CAPABILITY command with an additional interface support TLV object during a new card session before the first application selection.

For applicability of this test case see clause 3.8.

9.1.1.2 Conformance requirement

9.1.1.2.1 Description

Terminals supporting an interface in addition to the interface defined in the present document and present in the list below (e.g. the UICC-CLF interface as defined in ETSI TS 102 613 [6]) shall indicate it to the UICC by issuing the TERMINAL CAPABILITY command with an additional interface support TLV object during a new card session before the first application selection. The terminal supporting the SWP interface shall send a TLV object with tag '82' to indicate the support of the SWP interface before the first application selection.

The TERMINAL CAPABILITY command shall not be issued by the terminal if the Terminal capability mechanism is not indicated inside the supported system command field.

9.1.1.2.2 Reference

ETSI TS 102 221 [1], clauses 11.1.19.2.3 and 11.1.19.1.

9.1.1.3 Test purpose

To verify that the terminal which supports the SWP interface sends a TERMINAL CAPABILITY command indicating the interface supported before the first application selection.

9.1.1.4 Method of test

9.1.1.4.1 Initial conditions

The UICC simulator shall support the SWP interface.

The Terminal shall be connected to the UICC simulator.

The UICC simulator shall indicate support of the TERMINAL CAPABILITY command in the FCP for the MF.

9.1.1.4.2 Procedure

- a) Power on the Terminal.
- b) The UICC simulator shall send an ATR with a global interface byte tBi ($i > 2$) indicating the support of the SWP interface.
- c) The terminal shall retrieve the FCP of the MF of the UICC using a SELECT command or a STATUS command.
- d) The terminal sends a TERMINAL CAPABILITY command.

9.1.1.5 Acceptance criteria

In step d), the Terminal shall send TERMINAL CAPABILITY command indicating support of the SWP interface.

NOTE: Other commands may be sent by the terminal before the TERMINAL CAPABILITY command.

The terminal may send other TERMINAL CAPABILITY commands which do not include an Additional interfaces support TLV; such TERMINAL CAPABILITY commands shall be ignored for the purposes of this test case.

The terminal shall send the TERMINAL CAPABILITY command before the first application selection.

9.2 SUSPEND UICC

9.2.1 Support of the SUSPEND UICC command

9.2.1.1 SUSPEND UICC - Nominal Condition

9.2.1.1.1 Definition and applicability

A Terminal supporting the SUSPEND UICC command shall be capable of suspending and resuming the UICC as defined in ETSI TS 102 221 [1] if operated with a UICC indicating the support of the SUSPEND UICC command.

For applicability of the test case see clause 3.8.

9.2.1.1.2 Conformance requirement

9.2.1.1.2.1 Description

The Terminal can run a UICC suspension by issuing the SUSPEND UICC command.

Upon reception of the response indicating successful execution of the SUSPEND UICC command, the terminal shall deactivate the contacts of the UICC, storing the 8 byte Resume token sent by the UICC.

Within the maximum time duration for the suspension given by the UICC the Terminal resumes the UICC-Terminal interface. The Terminal performs the initial communication establishment procedures to allow the UICC to resume in the exact same condition it was in before the power supply was removed.

9.2.1.1.2.2 Reference

ETSI TS 102 221 [1], clauses 11.1.22 and 14.5.6.

9.2.1.1.3 Test purpose

- 1) To verify that the Terminal is issuing the SUSPEND UICC command correctly.
- 2) To verify that the Terminal is deactivating the contacts of the UICC-Terminal interface in the correct order (as defined in clause 5.1.3) after receiving the confirmation for the UICC suspension.
- 3) To verify that the Terminal is reactivating the UICC-Terminal interface within the maximum time frame negotiated with the UICC.
- 4) To verify that the Terminal is performing the initial communication establishment procedures as defined in ETSI TS 102 221 [1], clause 6:
 - a) During establishment of the initial communication the Terminal is not issuing commands other than:
 - SELECT with P1 ≠ '04';
 - READ BINARY;

- READ RECORD;
- TERMINAL CAPABILITY;

before a SUSPEND UICC command with P1 = 'Resume the UICC' and the Resume token is sent.

- b) If the Terminal has sent a TERMINAL CAPABILITY command before suspending the UICC, it is sending a TERMINAL CAPABILITY command with the same content as sent before when resuming the UICC.
- 5) To verify that the Terminal is sending the 8-byte Resume token provided by the UICC when it was suspended.
 - 6) To verify that the Terminal is maintaining the logical status of the UICC as before the suspension and is resuming the UICC for the events for which it had previously registered:
 - a) On request of the UICC a Terminal shall correctly indicate the status of a timer as defined in ETSI TS 102 223 [7] for a timer set using the TIMER MANAGEMENT command before the UICC was suspended.

9.2.1.1.4 Method of test

9.2.1.1.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, where the UICC simulator indicates support of the SUSPEND UICC command in EF_{UMPC}.

The UICC simulator shall indicate support of the TERMINAL CAPABILITY command in the FCP for the MF.

The PIN to verify the user at the NAA is disabled.

The Terminal shall be activated.

The test tool shall record any TERMINAL CAPABILITY command sent by the terminal.

The Terminal has selected an NAA present on the UICC. Any technology specific conditions for the Terminal to use the SUSPEND UICC command are met.

9.2.1.1.4.2 Procedure

- a) The UICC simulator shall send the proactive command TIMER MANAGEMENT to start a timer for 24 hours.
- b) The Terminal shall be made to suspend the UICC. Any conditions (for example: waiting for a timeout or suitable configuration of the Terminal) which would normally be required for the Terminal to suspend the UICC shall be satisfied (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).
- c) After reception of a SUSPEND UICC command with P1 = 'Suspend the UICC' the UICC simulator returns an 8 byte Resume token and the minimum time duration proposed by the terminal as the time duration for which it can be suspended.
- d) The Terminal shall deactivate the UICC-Terminal interface.
- e) The Terminal shall be made to resume the UICC (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).
- f) The Terminal shall activate the UICC-Terminal interface after the suspension.
- g) The Terminal is performing the communication establishment procedures.
- h) After reception of a SUSPEND UICC command with P1 = 'Resume the UICC' the UICC simulator shall restore the previous status and return '9000' (indicating correct execution of the command).
- i) The UICC simulator shall send the proactive command TIMER MANGEMENT to get the current value of the Timer.

NOTE: The maximum value (24 hours) for the timer set in the proactive command **TIMER MANAGEMENT** is used to ensure that the timer is still running after the resume. It is not intended that the test execution will last 24 hours.

9.2.1.1.5 Acceptance criteria

- 1) In step d) the Terminal shall deactivate the UICC-Terminal interface as defined in ETSI TS 102 221 [1], clause 4.5.2.
- 2) After step d) the Terminal shall keep the inactive contacts within the voltage range defined in ETSI TS 102 221 [1], clause 4.5.3.
- 3) In step e) the Terminal is activating the UICC-Terminal interface as defined in ETSI TS 102 221 [1], clause 4.5.2 within the time frame negotiated to be the time duration for the suspension in step c).
- 4) After step f), the terminal shall not re-select the network application.
- 5) During step g) The Terminal is successfully establishing the communication as defined in ETSI TS 102 221 [1] clause 6. Where the Terminal shall not issue commands other than:
 - SELECT with P1 ≠ '04'.
 - READ BINARY.
 - READ RECORD.
 - TERMINAL CAPABILITY:
 - Where the TERMINAL CAPABILITY, if sent, shall be identical to the one sent in the Initial conditions.
- 6) After step i) the Terminal shall send a TERMINAL RESPONSE providing the current value of the timer started before the resume. The timer value returned shall be 24 hours minus the test execution time elapsed after ending the proactive command "TIMER MANAGEMENT ± 1 minute.

9.2.1.2 SUSPEND UICC - Nominal Condition - Events

9.2.1.2.1 Definition and applicability

A Terminal supporting the SUSPEND UICC command shall be capable of suspending and resuming the UICC as defined in ETSI TS 102 221 [1] if operated with a UICC indicating the support of the SUSPEND UICC command.

For applicability of the test case see clause 3.8.

9.2.1.2.2 Conformance requirement

9.2.1.2.2.1 Description

The Terminal can run a UICC suspension by issuing the SUSPEND UICC command.

Upon reception of the response indicating successful execution of the SUSPEND UICC command, the terminal shall deactivate the contacts of the UICC, storing the 8 byte Resume token sent by the UICC.

Within the maximum time duration for the suspension given by the UICC the Terminal resumes the UICC-Terminal interface. The Terminal performs the initial communication establishment procedures to allow the UICC to resume in the exact same condition it was in before the power supply was removed.

9.2.1.2.2.2 Reference

ETSI TS 102 221 [1], clauses 11.1.22 and 14.5.6.

9.2.1.2.3 Test purpose

- 1) To verify that the Terminal is issuing the SUSPEND UICC command correctly.
- 2) To verify that the Terminal is deactivating the contacts of the UICC-Terminal interface in the correct order (as defined in clause 5.1.3) after receiving the confirmation for the UICC suspension.
- 3) To verify that the Terminal is reactivating the UICC-Terminal interface within the maximum time frame negotiated with the UICC
- 4) To verify that the Terminal is performing the initial communication establishment procedures as defined in ETSI TS 102 221 [1], clause 6:
 - During establishment of the initial communication the Terminal is not issuing commands other than:
 - SELECT with P1 ≠ '04';
 - READ BINARY;
 - READ RECORD;
 - TERMINAL CAPABILITY;before a SUSPEND UICC command with P1 = 'Resume the UICC' and the Resume token is sent.
- 5) To verify that the Terminal is sending the 8-byte Resume token provided by the UICC when it was suspended.
- 6) To verify that the Terminal is maintaining the logical status of the UICC as before the suspension and is resuming the UICC for the events for which it had previously registered:
 - a) The Terminal shall not ask for a PIN verification for applications already verified.
 - b) A Terminal supporting the SETUP EVENT LIST command shall provide information to the UICC as defined in ETSI TS 102 223 [7] at occurrence of a listed event.

9.2.1.2.4 Method of test

9.2.1.2.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, where the UICC simulator indicates support of the SUSPEND UICC command in EF_{UMPC}.

The UICC simulator shall indicate support of the TERMINAL CAPABILITY command in the FCP for the MF.

The PIN to verify the user at the NAA is enabled.

The Terminal shall be activated.

The Terminal has selected an NAA present on the UICC. Any technology specific conditions for the Terminal to use the SUSPEND UICC command are met.

9.2.1.2.4.2 Procedure

- a) When the Terminal is in mode PIN check, the valid PIN shall be entered.
- b) The UICC simulator shall send the proactive command SETUP EVENT LIST for the event: User activity.
- c) The Terminal shall be made to suspend the UICC. Any conditions (for example: waiting for a timeout or suitable configuration of the Terminal) which would normally be required for the Terminal to suspend the UICC shall be satisfied (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).
- d) After reception of a SUSPEND UICC command with P1 = 'Suspend the UICC' the UICC simulator returns an 8 byte Resume token and the minimum time duration proposed by the terminal as the time duration for which it can be suspended.
- e) The Terminal shall deactivate the UICC-Terminal interface.

- f) The Terminal shall be made to resume the UICC (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).

NOTE: No user activity should be performed before step j).

- g) The Terminal shall activate the UICC-Terminal interface after the suspension.
- h) The Terminal is performing the communication establishment procedures.
- i) After reception of a SUSPEND UICC command with P1 = 'Resume the UICC' the UICC simulator shall restore the previous status and return '9000' (indicating correct execution of the command).
- j) When there is a period of inactivity on the UICC-Terminal interface longer than 20 seconds, the user shall press any key.

9.2.1.2.5 Acceptance criteria

- 1) In step e) the Terminal shall deactivate the UICC-Terminal interface as defined in ETSI TS 102 221 [1], clause 4.5.2.
- 2) After step e) the Terminal shall keep the inactive contacts within the voltage range defined in ETSI TS 102 221 [1], clause 4.5.3.
- 3) In step f) the Terminal is activating the UICC-Terminal interface as defined in ETSI TS 102 221 [1], clause 4.5.2 within the time frame negotiated to be the time duration for the suspension in step c).
- 4) After step g), the terminal shall not re-select the network application and shall not ask the user to verify the PIN.
- 5) During step h) The Terminal is successfully establishing the communication as defined in ETSI TS 102 221 [1] clause 6. Where the Terminal shall not issue commands other than:
 - SELECT with P1 ≠ '04'.
 - READ BINARY.
 - READ RECORD.
 - TERMINAL CAPABILITY.
- 6) After step i) and before step j) the Terminal shall not send an ENVELOPE for the User activity event to the UICC simulator.
- 7) After step j) the Terminal shall send an ENVELOPE for the User activity event to the UICC simulator.

9.2.1.3 SUSPEND UICC - Suspension not supported by the UICC

9.2.1.3.1 Definition and applicability

A Terminal supporting the SUSPEND UICC command shall not cause the UICC suspension if the UICC is not indicating the support in EF_{UMPC}.

For applicability of the test case see clause 3.8.

9.2.1.3.2 Conformance requirement

9.2.1.3.2.1 Description

The Terminal does not issue the command if the UICC suspension mechanism is not indicated as supported by the UICC in the UICC Maximum Power Consumption file (EF_{UMPC}).

9.2.1.3.2.2 Reference

ETSI TS 102 221 [1], clause 11.1.22.

9.2.1.3.3 Test purpose

To verify that the Terminal is not issuing a SUSPEND UICC command if the support is not indicated in EF_{UMPC}.

9.2.1.3.4 Method of test

9.2.1.3.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, where the UICC simulator shall not indicate support of the SUSPEND UICC command in EF_{UMPC}.

The PIN to verify the user at the NAA is disabled.

The Terminal shall be activated.

The Terminal has selected an NAA present on the UICC.

Any technology specific conditions for the Terminal to use the SUSPEND UICC command are met.

9.2.1.3.4.2 Procedure

- a) The UICC simulator shall monitor the activity on the UICC-Terminal interface.
- b) After the conditions which would normally cause the Terminal to suspend the UICC are met, wait for 3 minutes.

9.2.1.3.5 Acceptance criteria

During step b) the Terminal shall not issue the SUSPEND UICC command or deactivate the UICC-Terminal interface.

9.2.1.4 SUSPEND UICC - Rejection of the UICC suspension with status word '6985'

9.2.1.4.1 Definition and applicability

A Terminal shall not deactivate the contacts of the UICC if the UICC has send status word '6985' in response to a SUSPEND UICC command with coding P1 = 'Suspend the UICC'.

For applicability of the test case see clause 3.8.

9.2.1.4.2 Conformance requirement

9.2.1.4.2.1 Description

The UICC can reject the SUSPEND UICC command with status word '6985' during an active proactive UICC session, or if there is any open BIP channel, or if a secure channel is in use, or due to internal reasons.

9.2.1.4.2.2 Reference

ETSI TS 102 221 [1], clause 11.1.22.

9.2.1.4.3 Test purpose

To verify that the Terminal is not deactivating the UICC-Terminal interface after receiving status word '6985' in response to a SUSPEND UICC command with coding P1 = 'Suspend the UICC'.

9.2.1.4.4 Method of test

9.2.1.4.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, where the UICC simulator indicates support of the SUSPEND UICC command in EF_{UMPC}.

The UICC simulator shall indicate support of the TERMINAL CAPABILITY command in the FCP for the MF.

The PIN to verify the user at the NAA is disabled.

The Terminal shall be activated.

The Terminal has selected an NAA present on the UICC.

Any technology specific conditions for the Terminal to use the SUSPEND UICC command are met.

9.2.1.4.4.2 Procedure

- a) The Terminal shall be made to suspend the UICC. Any conditions (for example: waiting for a timeout or suitable configuration of the Terminal) which would normally be required for the Terminal to suspend the UICC shall be satisfied (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).
- b) After reception of a SUSPEND UICC command with P1 = 'Suspend the UICC' the UICC simulator sends status word '6985' in response.
- c) Wait for 3 minutes.

9.2.1.4.5 Acceptance criteria

In step c) the Terminal shall not deactivate the UICC-Terminal interface.

9.2.1.5 SUSPEND UICC - Rejection of the UICC suspension with status word '9864'

9.2.1.5.1 Definition and applicability

A Terminal shall not deactivate the contacts of the UICC if the UICC has send status word '9864' in response to a SUSPEND UICC command.

For applicability of the test case see clause 3.8.

9.2.1.5.2 Conformance requirement

9.2.1.5.2.1 Description

The UICC can reject the SUSPEND UICC command with status word '9864' in response to a SUSPEND UICC command where the minimum duration requested by the terminal is too large to be accepted.

9.2.1.5.2.2 Reference

ETSI TS 102 221 [1], clause 11.1.22.

9.2.1.5.3 Test purpose

To verify that the Terminal is not deactivating the UICC-Terminal interface after receiving status word '9864' in response to a SUSPEND UICC command.

9.2.1.5.4 Method of test

9.2.1.5.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, where the UICC simulator indicates support of the SUSPEND UICC command in EF_{UMPC}.

The UICC simulator shall indicate support of the TERMINAL CAPABILITY command in the FCP for the MF.

The PIN to verify the user at the NAA is disabled.

The Terminal shall be activated.

The Terminal has selected an NAA present on the UICC.

Any technology specific conditions for the Terminal to use the SUSPEND UICC command are met.

9.2.1.5.4.2 Procedure

- a) The Terminal shall be made to suspend the UICC. Any conditions (for example: waiting for a timeout or suitable configuration of the Terminal) which would normally be required for the Terminal to suspend the UICC shall be satisfied (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).
- b) After reception of a SUSPEND UICC command with P1 = 'Suspend the UICC' the UICC simulator sends the status word '9864' in response.
- c) Wait for 3 minutes.

9.2.1.5.5 Acceptance criteria

In step c) the Terminal shall not deactivate the UICC-Terminal interface.

9.2.1.6 SUSPEND UICC - Rejection of the UICC resume with status word '6982'

9.2.1.6.1 Definition and applicability

A Terminal shall not try to restore the logical status as before the suspension or to resume the UICC for the events for which it had previously registered if the UICC sent status word '6982' in response to a SUSPEND UICC command with P1 = 'Resume the UICC'.

For applicability of the test case see clause 3.8.

9.2.1.6.2 Conformance requirement

9.2.1.6.2.1 Description

The UICC compares the Resume token passed by the Terminal with the token stored in its non-volatile memory. If the Resume token passed by the Terminal does not match the token stored the UICC will return status word '6982'.

9.2.1.6.2.2 Reference

ETSI TS 102 221 [1], clause 11.1.22.

9.2.1.6.3 Test purpose

To verify that the Terminal is not resuming the UICC for the file system state and for the events for which it had previously registered if the resume is rejected by the UICC.

9.2.1.6.4 Method of test

9.2.1.6.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, where the UICC simulator indicates support of the SUSPEND UICC command in EF_{UMPC}.

The UICC simulator shall indicate support of the TERMINAL CAPABILITY command in the FCP for the MF.

The PIN to verify the user at the NAA is disabled.

The Terminal shall be activated.

The Terminal has selected an NAA present on the UICC.

Any technology specific conditions for the Terminal to use the SUSPEND UICC command are met.

9.2.1.6.4.2 Procedure

- a) The UICC simulator shall send the proactive command TIMER MANAGEMENT to start a timer for 24 hours.
- b) The Terminal shall be made to suspend the UICC. Any conditions (for example: waiting for a timeout or suitable configuration of the Terminal) which would normally be required for the Terminal to suspend the UICC shall be satisfied (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).
- c) After reception of a SUSPEND UICC command with P1 = 'Suspend the UICC' the UICC simulator returns an 8 byte Resume token and the minimum time duration proposed by the terminal as the time duration for which it can be suspended.
- d) The Terminal shall deactivate the UICC-Terminal interface.
- e) The Terminal shall be made to resume the UICC (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7)
- f) The Terminal shall activate the UICC-Terminal interface.
- g) The Terminal is performing the communication establishment procedures.
- h) After reception of a SUSPEND UICC command with P1 = 'Resume the UICC' the UICC simulator sends status word '6982' in return.
- i) The Terminal shall send TERMINAL PROFILE.
- j) The Terminal shall select a network application present on the UICC.
- k) The UICC simulator shall send the proactive command TIMER MANGEMENT to get the current value of the Timer.

NOTE: The maximum value (24 hours) for the timer set in the proactive command TIMER MANAGEMENT is used to ensure that the timer is still running after the resume. It is not intended that the test execution will last 24 hours.

9.2.1.6.5 Acceptance criteria

- 1) After step k) the Terminal shall send a TERMINAL RESPONSE providing the message:
 - 'Action in contradiction with the current timer state'.

9.2.1.7 SUSPEND UICC - Rejection of the UICC resume with status word '6982' - Events

9.2.1.7.1 Definition and applicability

A Terminal shall not try to restore the logical status as before the suspension or to resume the UICC for the events for which it had previously registered if the UICC sent status word '6982' in response to a SUSPEND UICC command with P1 = 'Resume the UICC'.

For applicability of the test case see clause 3.8.

9.2.1.7.2 Conformance requirement

9.2.1.7.2.1 Description

The UICC compares the Resume token passed by the Terminal with the token stored in its non-volatile memory. If the Resume token passed by the Terminal does not match the token stored the UICC will return status word '6982'.

9.2.1.7.2.2 Reference

ETSI TS 102 221 [1], clause 11.1.22.

9.2.1.7.3 Test purpose

To verify that the Terminal is not resuming the UICC for the file system state and for the events for which it had previously registered if the resume is rejected by the UICC.

9.2.1.7.4 Method of test

9.2.1.7.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, where the UICC simulator indicates support of the SUSPEND UICC command in EF_{UMPC}.

The UICC simulator shall indicate support of the TERMINAL CAPABILITY command in the FCP for the MF.

The Terminal supports a keypad and the PIN to verify the user at the NAA is enabled.

The Terminal shall be activated.

The Terminal has selected an NAA present on the UICC.

Any technology specific conditions for the Terminal to use the SUSPEND UICC command are met.

9.2.1.7.4.2 Procedure

- a) When the Terminal is in mode PIN check, the valid PIN shall be entered.
- b) The UICC simulator shall send the proactive command SETUP EVENT LIST for the event: User activity.
- c) The Terminal shall be made to suspend the UICC. Any conditions (for example: waiting for a timeout or suitable configuration of the Terminal) which would normally be required for the Terminal to suspend the UICC shall be satisfied (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).
- d) After reception of a SUSPEND UICC command with P1 = 'Suspend the UICC' the UICC simulator returns an 8 byte Resume token and the minimum time duration proposed by the terminal as the time duration for which it can be suspended.
- e) The Terminal shall deactivate the UICC-Terminal interface.

- f) The Terminal shall be made to resume the UICC (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).

NOTE: No user activity should be performed before step k).

- g) The Terminal shall activate the UICC-Terminal interface.
- h) The Terminal is performing the communication establishment procedures.
- i) After reception of a SUSPEND UICC command with P1 = 'Resume the UICC' the UICC simulator sends status word '6982' in return.
- j) The Terminal shall send TERMINAL PROFILE.
- k) The Terminal shall select a network application present on the UICC.
- l) When the Terminal is in mode PIN check, the valid PIN shall be entered.
- m) Wait for at least 2 minutes.

9.2.1.7.5 Acceptance criteria

- 1) During step m) the Terminal shall not send an ENVELOPE for the User activity event to the UICC simulator.

9.2.1.8 SUSPEND UICC - Rejection of the UICC resume with status word '6985'

9.2.1.8.1 Definition and applicability

A Terminal shall not try to restore the logical status as before the suspension or to resume the UICC for the events for which it had previously registered if the UICC sent status word '6985' in response to a SUSPEND UICC command with P1 = 'Resume the UICC'.

For applicability of the test case see clause 3.8.

9.2.1.8.2 Conformance requirement

9.2.1.8.2.1 Description

The UICC rejects the RESUME UICC command if it does not have a valid status to resume. To indicate the rejection the UICC will return status word '6985'.

9.2.1.8.2.2 Reference

ETSI TS 102 221 [1], clause 11.1.22.

9.2.1.8.3 Test purpose

To verify that the Terminal is not resuming the UICC for the file system state and for the events for which it had previously registered if the resume is rejected by the UICC.

9.2.1.8.4 Method of test

9.2.1.8.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, where the UICC simulator indicates support of the SUSPEND UICC command in EF_{UMPC}.

The UICC simulator shall indicate support of the TERMINAL CAPABILITY command in the FCP for the MF.

The PIN is disabled.

The Terminal shall be activated.

The Terminal has selected an NAA present on the UICC.

Any technology specific conditions for the Terminal to use the SUSPEND UICC command are met.

9.2.1.8.4.2 Procedure

- a) The UICC simulator shall send the proactive command TIMER MANAGEMENT to start a timer for 24 hours.
- b) The Terminal shall be made to suspend the UICC. Any conditions (for example: waiting for a timeout or suitable configuration of the Terminal) which would normally be required for the Terminal to suspend the UICC shall be satisfied (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).
- c) After reception of a SUSPEND UICC command with P1 = 'Suspend the UICC' the UICC simulator returns an 8 byte Resume token and the minimum time duration proposed by the terminal as the time duration for which it can be suspended.
- d) The Terminal shall deactivate the UICC-Terminal interface.
- e) The Terminal shall be made to resume the UICC (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).
- f) The Terminal shall activate the UICC-Terminal interface.
- g) The Terminal is performing the communication establishment procedures.
- h) After reception of a SUSPEND UICC command with P1 = 'Resume the UICC' the UICC simulator sends status word '6985' in return.
- i) The Terminal shall send TERMINAL PROFILE.
- j) The Terminal shall select a network application present on the UICC.
- k) The UICC simulator shall send the proactive command TIMER MANGEMENT to get the current value of the Timer.

NOTE: The maximum value (24 hours) for the timer set in the proactive command TIMER MANAGEMENT is used to ensure that the timer is still running after the resume. It is not intended that the test execution will last 24 hours.

9.2.1.8.5 Acceptance criteria

- 1) After step k) the Terminal shall send a TERMINAL RESPONSE providing the message: 'Action in contradiction with the current timer state'.

9.2.1.9 SUSPEND UICC - Rejection of the UICC resume with status word '6985' - Events

9.2.1.9.1 Definition and applicability

A Terminal shall not try to restore the logical status as before the suspension or to resume the UICC for the events for which it had previously registered if the UICC sent status word '6985' in response to a SUSPEND UICC command with P1 = 'Resume the UICC'.

For applicability of the test case see clause 3.8.

9.2.1.9.2 Conformance requirement

9.2.1.9.2.1 Description

The UICC rejects the RESUME UICC command if it does not have a valid status to resume. To indicate the rejection the UICC will return status word '6985'.

9.2.1.9.2.2 Reference

ETSI TS 102 221 [1], clause 11.1.22.

9.2.1.9.3 Test purpose

To verify that the Terminal is not resuming the UICC for the file system state and for the events for which it had previously registered if the resume is rejected by the UICC.

9.2.1.9.4 Method of test

9.2.1.9.4.1 Initial conditions

The Terminal shall be connected to the UICC simulator, where the UICC simulator indicates support of the SUSPEND UICC command in EF_{UMPC}.

The UICC simulator shall indicate support of the TERMINAL CAPABILITY command in the FCP for the MF.

The Terminal supports a keypad and the PIN to verify the user at the NAA is enabled.

The Terminal shall be activated.

The Terminal has selected an NAA present on the UICC.

Any technology specific conditions for the Terminal to use the SUSPEND UICC command are met.

9.2.1.9.4.2 Procedure

- a) When the Terminal is in mode PIN check, the valid PIN shall be entered.
- b) The UICC simulator shall send the proactive command SETUP EVENT LIST for the event: User activity.
- c) The Terminal shall be made to suspend the UICC. Any conditions (for example: waiting for a timeout or suitable configuration of the Terminal) which would normally be required for the Terminal to suspend the UICC shall be satisfied (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).
- d) After reception of a SUSPEND UICC command with P1 = 'Suspend the UICC' the UICC simulator returns an 8 byte Resume token and the minimum time duration proposed by the terminal as the time duration for which it can be suspended.
- e) The Terminal shall deactivate the UICC-Terminal interface.
- f) The Terminal shall be made to resume the UICC (see note related to O_SUSPEND_UICC of table A.1 in clause 3.7).

NOTE: No user activity should be performed before step k).

- g) The Terminal shall activate the UICC-Terminal interface.
- h) The Terminal is performing the communication establishment procedures.
- i) After reception of a SUSPEND UICC command with P1 = 'Resume the UICC' the UICC simulator sends status word '6985' in return.
- j) The Terminal shall send TERMINAL PROFILE.
- k) The Terminal shall select a network application present on the UICC.
- l) When the Terminal is in mode PIN check, the valid PIN shall be entered.
- m) Wait for at least 2 minutes.

9.2.1.9.5 Acceptance criteria

- 1) During step m) the Terminal shall not send an ENVELOPE for the User activity event to the UICC simulator.

Annex A (normative): UICC simulator functional requirement

A.1 General

The UICC simulator shall implement the functions of an UICC as described in ETSI TS 102 221 [1].

A.2 Contacts C1, C3, C7

A.2.1 Default measurement/setting uncertainties

Unless stated otherwise below, the following uncertainties apply:

Voltage measurement uncertainty:	< ± 50 mV
Time measurement uncertainty:	< ± 100 ns

A.2.2 Contact C1

Continuous Spikes:

Voltage measurement uncertainty:	< ± 100 mV
Current Load Amplitude:	0 mA to 20 mA
Adjustable Step Size:	1 mA
Uncertainty:	< ± 1 mA
Additional Current Offset:	0 mA to 5 mA
Adjustable Step Size:	1 mA
Uncertainty:	< ± 1 mA
Pulse Width:	100 ns to 500 ns
Adjustable Step Size:	50 ns
Uncertainty:	< ± 25 ns
Rise and Fall Time:	≤ 50 ns
Pause Width:	100 ns to 500 ns
Adjustable Step Size:	50 ns
Uncertainty:	< ± 25 ns

Random Spikes:

Voltage measurement uncertainty:	< ± 100 mV
Current Load Amplitude:	50 mA to 200 mA
Adjustable Step Size:	1 mA
Uncertainty:	< ± 1 mA

Additional Current Offset:	0 mA to 5 mA
Adjustable Step Size:	1 mA
Uncertainty:	$< \pm 0,1$ mA
Pulse Width:	100 ns to 500 ns
Adjustable Step Size:	50 ns
Uncertainty:	$< \pm 25$ ns
Rise and Fall Time:	≤ 50 ns
Pause Width:	0,1 ms to 500 ms, randomly varied
Adjustable Step Size:	0,1 ms
Uncertainty:	$< \pm 0,1$ ms

A.2.3 Contact C7

The Elementary Time Unit (etu) used in the clauses below refer to the nominal bit duration on the I/O line, as defined in ISO/IEC 7816-3 [2]:

Voltage setting uncertainty:	$< \pm 25$ mV
Rise and fall Time setting uncertainty:	$< \pm 100$ ns
Jitter measurement uncertainty:	$< \pm 5 \times 10E-3$ etu
Jitter setting uncertainty:	$< \pm 5 \times 10E-3$ etu

A.2.4 Contact C3

Frequency measurement uncertainty:	$< \pm 0,5$ %
Voltage Measurement uncertainty:	$< \pm 50$ mV
Rise and fall time measurement uncertainty:	$< \pm 5$ ns
Duty cycle:	
Measurement range:	35 % to 65 %
Measurement uncertainty:	$< \pm 2,5$ %

A.3 Definition of timing

It shall be possible to define all timings relative to the clock. The UICC simulator shall be able to calculate and to use the absolute values automatically, even if the Terminal changes the frequency during the communication.

Annex B (informative): Change history

The table below indicates all change requests that have been incorporated into the present document since it was created by TC SET (formerly TC SCP).

Date	Meeting	Doc	CR	Rev	Cat	Subject/Comment	Old	New
2001-06	SCP-06	SCP-010156				TSG-T #11 agreed to transfer the contents of the test specification, 3GPP TS 31.120 to EP SCP. V1.0.0 is submitted to EP SCP for approval. It contains only editorial changes compared to 3GPP TS 31.120 V3.0.0		1.0.0
2001-06	SCP-06	SCP-010194				Undoing a change regarding the coding conventions in clause 3.4	1.0.0	1.0.1
2001-06	SCP-06	-				EP SCP agreed that V1.0.1 was ready to be put under change control. As a result, V3.0.0 was created.	1.0.1	3.0.0
2001-07	SCP-06	SCP-010193	001		B	Alignment with Rel-4 version of core specification (UICC current consumption values for 3 V and 1,8V)	3.0.0	4.0.0
		SCP-010200	002		F	Correction of ATR examples regarding DCB and T4		
2002-03	SCP-09	SCP-020052	003		F	Correction of Errors in UICC type recognition	4.0.0	4.1.0
2003-01	SCP-12	SCP-030013	005		F	Correction of test on processing of ACK, NACK, NULL procedure bytes and correction of CHV	4.1.0	4.2.0
		SCP-030062	006		D	Remove UICC as an abbreviation to align with 3GPP TR 21.905		
2003-09	SCP-14	SCP-030288	007		F	Upgrade to Rel-5 version of the specification	4.2.0	5.0.0
2004-05	SCP-17	SCP-040284	010		A	Removal of test 6.4 and modification of the numbering order of electrical tests in clause 5.2	5.0.0	5.1.0
2004-09	SCP#18	SCP-040376	015		A	Removal of transmit for WWT exceeded in test 7.2.1 Timing	5.1.0	5.2.0
2004-11	SCP#19	SCP-040489	020		A	Non-specific Referencing	5.2.0	5.3.0
		SCP-040492	023		A	Modification of test 7.3.2 Block Timing		
2005-06	SCP#21	SCP-050129	026		F	Correction of test case 7.3.9	5.3.0	5.4.0
		SCP-050131	029		F	Correction of test case 7.3.11		
		SCP-050186	032		F	Correction of references to ISO/IEC 7816		
2005-09	SCP#22	SCP-050297	035		A	Change of internal references	5.4.0	5.5.0
2006-03	SCP#25	SCP-060160	038		A	Removal of test case 5.1.5.5	5.5.0	5.6.0
2007-01	SCP#29	SCP-070062	041		A	Essential correction of "Chaining - IFSD management" test case	5.6.0	5.7.0
2007-10	SCP#33	SCP-070446	049		F	CR to ETSI TS 102 230, Rel-5: Adding an applicability table to generate a base for a combined Rel-5 to Rel-7 test specification Note: incorrect CR number renumbered from 42 to 49	5.7.0	5.8.0
2008-07	SCP#38	SCP-080337	047		A	CR 102 230 Rel-5 Essential correction of ATR coding	5.7.0	5.8.0
2008-10	SCP#39	SCP-080414	050		F	Correction of cl. 5.2 chapter numbering	5.8.0	5.9.0
2009-04	SCP#41	-----	----		-	Upgrade of the specification to Rel-7	5.9.0	7.0.0
2009-04	SCP#41	SCP-090180	053		B	Addition of a test case: analysing rise- and fall-time when a low impedance buffer is selected.	7.0.0	7.1.0
2010-03	SCP#44	SCP(10)0065	055		F	Creation of REL 8 of ETSI TS 102 230	7.1.0	8.0.0
2013-03	SCP#45	SCP(10)0116	059		F	Correction of maximum allowed rise/fall time on contact C7 in test 5.2.5.2	8.0.0	8.1.0
2013-03	SCP#58	SCP(13)000016	061		F	Enhancement of TC 7.2.2 with regards to NULL procedure byte	8.0.0	8.1.0
2013-03	SCP#57	SCP(12)000229	060		F	Creation of ETSI TS 102 230 REL-9	8.1.0	9.0.0
2013-04	SCP#59	SCP(13)000063	062		F	Creation of ETSI TS 102 230 REL-10	9.0.0	10.0.0
2014-02	SCP#62	SCP(14)000009	063		F	Modification of the electrical test cases	10.0.0	10.1.0
2014-04	-	-	-		-	Correction of clause numbering and related release information in applicability table	10.1.0	10.1.1
2014-04	SCP#63	SCP(14)000106r 1	064	1	F	Modification of test case 5.1.5.6	10.1.1	10.2.0
2015-10	SCP#70	SCP(15)000212	067		B	Creation of Rel-11 of the specification	10.2.0	11.0.0
2015-10	SCP#70	SCP(15)000213	068		B	Additional of TERMINAL CAPABILITY - Additional interfaces support test case	10.2.0	11.0.0
						Addition/modification of section headers to remove hanging paragraphs (as required by updated ETSI drafting rules)	10.2.0	11.0.0
2018-05	SCP#75	SCP(16)000167r 1	069	1	C	Update the applicability of test case 9.1.1	11.0.0	11.1.0
2018-05	SCP#75	SCP(16)000168	070		B	Creation of REL-12 of ETSI TS 102 230-1	11.1.0	12.0.0

Date	Meeting	Doc	CR	Rev	Cat	Subject/Comment	Old	New
2018-05	SCP#76	SCP(16)000244	071		B	Creation of REL-13 of ETSI TS 102 230-1	12.0.0	13.0.0
2018-05	SCP#76	SCP(16)000245	072	1	F	Test case 7.2.5: fix for unfair failure for '6282' after SEARCH RECORD	12.0.0	13.0.0
2018-05	SCP#79	SCP(17)000092r 1	073	1	C	Adding Nominal Test Conditions for Rel-12 implementations	13.0.0	13.1.0
2018-05	SCP#81	SCP(17)000166r 1	074	1	B	Adding tests for Terminals supporting one Voltage Class only	13.1.0	13.2.0
2018-05	SCP#81	SCP(17)000167r 1	075	1	F	Clarification on UICC Presence Detection Test Case	13.1.0	13.2.0
2018-05	SCP#81	SCP(17)000168r 1	076	1	B	Creation of REL-14 of ETSI TS 102 230-1	13.2.0	14.0.0
2018-07	SCP#85	SCP(18)000150	077	2	B	Adding new Rel-14 test cases for the UICC Suspension Mechanism	14.0.0	14.1.0
2018-07	SCP#85	SCP(18)000151	078	2	B	Additional Rel-14 test cases for the UICC Suspension Mechanism	14.0.0	14.1.0
2023-06	SET#110	SET(23)000054	086		F	Addition of test case 'Reaction of Terminals not supporting any voltage class indicated in the ATR'	14.1.0	14.2.0
2023-06	SET#110	SET(23)000055	087		F	Change of maximum current on C1 to allow for different releases	14.1.0	14.2.0
2023-06	SET#110	SET(23)000056	083		F	Update to Rel-15	14.2.0	15.0.0
2023-06	SET#110	SET(23)000057	084		F	Update to Rel-16	15.0.0	16.0.0

Annex C (informative): Core specification version information

Unless otherwise specified, the versions of ETSI TS 102 221 [1] which have been taken into consideration for the present document are as follows.

Release	ETSI TS 102 221 [1] version
Rel-9	V9.2.0
Rel-10	V10.0.0
Rel-11	V11.1.0
Rel-12	V12.1.0
Rel-13	V13.2.0
Rel-14	V14.2.0
Rel-15	V15.5.0
Rel-16	V16.6.0

History

Document history		
V16.0.0	August 2023	Publication