

# ETSI TS 149 008 V19.0.0 (2025-10)



**Digital cellular telecommunications system (Phase 2+) (GSM);  
Application of the Base Station System Application Part  
(BSSAP) on the E interface  
(3GPP TS 49.008 version 19.0.0 Release 19)**



---

**Reference**

---

RTS/TSGC-0149008vj00

---

---

**Keywords**

---

GSM

---

**ETSI**

650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

---

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° w061004871

---

**Important notice**

---

The present document can be downloaded from the  
[ETSI Search & Browse Standards application](#).

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on [ETSI deliver repository](#).

Users should be aware that the present document may be revised or have its status changed,  
this information is available in the [Milestones listing](#).

If you find errors in the present document, please send your comments to  
the relevant service listed under [Committee Support Staff](#).

If you find a security vulnerability in the present document, please report it through our  
[Coordinated Vulnerability Disclosure \(CVD\)](#) program.

---

**Notice of disclaimer & limitation of liability**

---

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

---

**Copyright Notification**

---

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2025.  
All rights reserved.

---

# Intellectual Property Rights

## Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the [ETSI IPR online database](#).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

## Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

**DECT™**, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™**, **LTE™** and **5G™** logo are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

---

# Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found at [3GPP to ETSI numbering cross-referencing](#).

---

# Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

# Contents

Intellectual Property Rights .....	2
Legal Notice .....	2
Modal verbs terminology.....	2
Foreword.....	4
1 Scope .....	5
2 References .....	5
3 Abbreviations .....	6
4 Principles for the use of BSSAP on the E-interface .....	6
4.1 General .....	6
4.2 Transfer of DTAP and BSSMAP layer 3 messages on the E-interface .....	6
4.3 Roles of MSC-A, MSC-I and MSC-T .....	7
5 Use of the BSSAP on the E-interface.....	7
5.1 DTAP .....	8
5.2 Assignment.....	8
5.3 Handover resource allocation.....	8
5.4 Handover execution.....	8
5.5 Internal handover indication.....	9
5.6 Release due to BSS generated reasons .....	9
5.7 Classmark handling .....	9
5.8 Cipher mode control.....	9
5.9 Trace invocation .....	9
5.10 Queuing indication .....	10
5.11 Data link control SAPI not equal to "0" .....	10
5.12 Location Acquisition .....	10
5.13 LSA handling .....	10
5.14 Common ID.....	10
6 BSSMAP messages transferred on the E-interface .....	11
7 Exceptions for BSSMAP message contents and information element coding when transferred on the E-interface .....	12
7.1 Message contents.....	12
7.2 Information element coding .....	14
8 BSSAP message error handling when transferred on the E-interface .....	14
<b>Annex A (informative): Change history .....</b>	<b>15</b>
History .....	18

---

# Foreword

This Technical Specification (TS) has been produced by the 3<sup>rd</sup> Generation Partnership Project (3GPP).

The present document provides a mechanism giving reliable transfer of signalling messages within the 3GPP system.

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

---

# 1 Scope

The present document describes the subset of Base Station System Application Part (BSSAP) messages and procedures, defined in 3GPP TS 48.006 and 3GPP TS 48.008, which is used on the E-interface. A general description can be found in 3GPP TS 23.002 and 3GPP TS 23.009.

For the initiation and execution of handover between MSCs a subset of BSSMAP procedures are used. For the subsequent control of resources allocated to the Mobile Station (MS) BSSMAP procedures are used. DTAP is used for the transfer of connection management and mobility management messages between the MS and the controlling MSC.

---

# 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

[1] Void.

[1a] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".

[2] 3GPP TS 23.009: "Handover procedures".

[2a] 3GPP TS 23.002: "Network Architecture".

[3] 3GPP TS 48.006: "Signalling transport mechanism specification for the Base Station System - Mobile-services Switching Centre (BSS - MSC) interface".

[4] 3GPP TS 48.008: "Mobile-services Switching Centre - Base Station System (MSC - BSS) interface; Layer 3 specification".

[5] 3GPP TS 29.002: "Mobile Application Part (MAP) specification".

[6] 3GPP TS 29.010: "Information element mapping between Mobile Station - Base Station System (MS - BSS) and Base Station System - Mobile-services Switching Centre (BSS - MSC); Signalling procedures and the Mobile Application Part (MAP)".

[7] 3GPP TS 23.172: "Technical realization of Circuit Switched (CS) multimedia service; UDI/RDI fallback and service modification; Stage 2)".

[8] 3GPP TS 25.413: "UTRAN Iu interface Radio Access Network Application Part (RANAP) signalling".

---

## 3 Abbreviations

For the purposes of the present document, the abbreviations defined in 3GPP TR 21.905 [1a] and the following apply:

BSS	Base Station System
BSSAP	Base Station System Application Part
BSSMAP	Base Station System Management Application Part
CCCH	Common Control CHannel
DLCI	Data Link Connection Identifier
DTAP	Direct Transfer Application Part
MSC	Mobile-services Switching Centre
MSC-A	Mobile-services Switching Centre, Anchor (Anchor MSC)
MSC-I	Mobile-services Switching Centre, Intermediate (Intermediate MSC)
MSC-T	Mobile-services Switching Centre, Target (Target MSC)
SAPI	Service Access Point Identifier
SCCP	Signalling Connection Control Part
TCAP	Transaction Capabilities Application Part

---

## 4 Principles for the use of BSSAP on the E-interface

### 4.1 General

The mechanisms for the transfer of the BSSAP messages on the E-interface is defined in 3GPP TS 29.002 [5]. The operation of the handover procedures between MSCs and the use of the BSSMAP messages for those procedures is described in 3GPP TS 23.009 [2] and 3GPP TS 29.010 [6].

In the same way as a SCCP signalling connection is used for the messages relating to one MS on the MSC-BSS interface a TCAP dialogue is used on the E-interface for messages relating to one MS. As no correspondence to the connectionless service on the MSC-BSS interface is used on the E-interface none of the global procedures (see 3GPP TS 48.008 [4] subclause 3.1) are applicable.

The management of the terrestrial circuits and IP connections between the MSCs is outside the scope of the E-interface (see 3GPP TS 23.009 [2]), therefore all procedures, messages and information elements relating to terrestrial circuits or IP connections are also excluded from the BSSMAP procedures and messages used on the E-interface.

### 4.2 Transfer of DTAP and BSSMAP layer 3 messages on the E-interface

The BSSAP data which on the MSC-BSS interface is contained in the user data field of the exchanged SCCP frames (see 3GPP TS 48.006) is on the E-interface transferred as the contents of the signalling info in a BSS-APDU parameter as described in 3GPP TS 29.002.

The BSSAP data consists of a BSSAP header and a DTAP or BSSMAP layer 3 message. The BSSAP header contains, as specified in 3GPP TS 48.006 (subclauses 6.3.1, 6.3.2 and 6.3.3), of a discrimination parameter, possibly a Data Link Connection Identification (DLCI) parameter, and a length indicator.

## 4.3 Roles of MSC-A, MSC-I and MSC-T

For the description in the present document, the MSC's functionality related to the handover between MSCs has been split into three logical parts, MSC-A, MSC-T and MSC-I. The different roles need not necessarily be performed by different MSCs.

MSC-A is the call/connection controlling part of the MSC where the call/connection was originally established and the switching point for handover between MSCs. (This corresponds to MSC-A as defined in 3GPP TS 23.009 and 3GPP TS 29.002). The MSC that is the MSC-A will not be changed during the duration of a call/connection.

MSC-T is the part relating to the transitory state during the handover for the MSC to which the MS is handed over when Basic handover or Subsequent handover (see 3GPP TS 23.009) take place. (This corresponds, depending on the type of handover to MSC-A, MSC-B or MSC-B' in 3GPP TS 23.009 and 3GPP TS 29.002).

MSC-I is the part of an MSC through which the MSC-A, via an E-interface (or an internal interface) is in contact with the MS. (This corresponds, depending on the type of handover to MSC-A, MSC-B or MSC-B' in 3GPP TS 23.009 and 3GPP TS 29.002).

The MSC that is the MSC-A can also have the role of either the MSC-I or the MSC-T during a period of the call/connection.

The following is applicable for the involved MSCs concerning the exchange of BSSAP data on an E-interface before and after a successful inter MSC handover:

- 1) At Basic handover, two MSCs are involved, one MSC being MSC-A and one being MSC-T. When this handover has been performed, the two MSCs interworking on the E-interface have the roles of MSC-A and MSC-I respectively, i.e. the MSC that is the MSC-T during the handover is now the MSC-I.
- 2) At Subsequent handover back to MSC-A, two MSCs are involved. The MSC having the role of MSC-A has also the role of MSC-T. The other MSC involved has the role of MSC-I. When this handover has been completed, there is no exchange of BSS data on the E-interface, i.e. the MSC being the MSC-I before and during the handover is now no longer taking part.
- 3) At subsequent handover to an MSC not being MSC-A, three MSCs are involved. The roles of these MSCs are MSC-A, MSC-I, and MSC-T respectively. When this handover has been performed, the two MSCs interworking on an E-interface have the roles of MSC-A and MSC-I respectively, i.e. the MSC that is the MSC-T during the handover is now the MSC-I and the MSC being MSC-I during the handover is now no longer taking part.

---

## 5 Use of the BSSAP on the E-interface

DTAP is used on the E-interface for the transfer of messages between the MSC-A and the MS.

The dedicated BSSMAP procedures (3GPP TS 48.008 subclause 3.1) used on the E-interface to some extent are:

- assignment;
- handover resource allocation;
- handover execution;
- internal handover indication;
- release due to BSS generated reasons;
- classmark handling;
- cipher mode control;
- trace invocation;
- queuing indication;
- data link control SAPI not equal to "0";



- Location Acquisition;
- LSA handling;
- Common ID.

One dedicated BSSMAP procedure is used only on the E-interface:

- Service Change (subclause 5.15).

## 5.1 DTAP

For the exchange of the DTAP messages (3GPP TS 48.008 subclause 2.2), the involved MSCs shall act according to the following:

- the MSC-A acts as the MSC;
- the MSC-I acts as the BSS.

## 5.2 Assignment

The Assignment procedure (3GPP TS 48.008 subclause 3.1.1) is applied on the E-interface with following conditions:

- the MSC-A acts as the MSC;
- the MSC-I acts as the BSS.

The handling of terrestrial resources is not applicable.

## 5.3 Handover resource allocation

At Basic Inter-MSC Handover (3GPP TS 23.009) the Handover resource allocation procedure (3GPP TS 48.008 subclause 3.1.5.2) is applied on the E-interface with the following conditions:

- the MSC-A acts as the MSC;
- the MSC-T acts as the target BSS.

At Subsequent Inter-MSC Handover (3GPP TS 23.009) the Handover resource allocation procedure (3GPP TS 48.008 subclause 3.1.5.2) is applied on the E-interface with the following conditions:

- the MSC-I acts as the MSC;
- the MSC-T acts as the target BSS;
- if the MSC that is the MSC-A is not also the MSC-T, then this MSC shall act as the target BSS towards the MSC-I and as the MSC towards the MSC-T.

The handling of terrestrial resources is not applicable.

## 5.4 Handover execution

For the Handover execution procedure (3GPP TS 48.008 subclause 3.1.5.3) the applicable parts on the E-interface are the transfer of HANDOVER DETECT, HANDOVER COMPLETE and HANDOVER FAILURE messages at inter MSC handover. For those parts, the involved MSCs shall act according to the following:

- the MSC that is the MSC-A, acts as the MSC;
- the MSC that is the MSC-I, if it is not also the MSC-A, acts as the serving BSS;

- the MSC that is the MSC-T, if it is not also the MSC-A, acts as the target BSS.

## 5.5 Internal handover indication

For the Internal handover indication (3GPP TS 48.008 subclauses 3.1.6 and 3.1.7), the involved MSCs shall act according to the following:

- the MSC-A acts as the MSC;
- the MSC-I acts as the BSS.

MSC internal handovers (inter-BSS and intra-BSS handover) at the MSC-I are decided and executed autonomously by that MSC together with the connected BSSs. At completion of the handover execution the MSC-I initiates the internal handover indication procedure.

## 5.6 Release due to BSS generated reasons

For the Release due to BSS generated reasons procedure (3GPP TS 48.008 subclause 3.1.9.2) the involved MSCs shall act according to the following:

- the MSC-I acts as the BSS;
- no further action is taken by the MSC-A.

Additionally, at Basic Inter-MSC Handover and at Subsequent Inter-MSC Handover (3GPP TS 23.009), if the MSC that is the MSC-A is not also the MSC-T, the Release due to BSS generated reasons procedure (3GPP TS 48.008 subclause 3.1.9.2) is applied on the E-interface with the following conditions:

- the MSC-T acts as the BSS;
- no further action is taken by the MSC-A.

## 5.7 Classmark handling

For the Classmark handling (3GPP TS 48.008 subclause 3.1.13), the involved MSCs shall act according to the following:

- the MSC-A acts as the MSC;
- the MSC-I acts as the BSS.

## 5.8 Cipher mode control

For the Cipher mode control (3GPP TS 48.008 subclause 3.1.14), the involved MSCs shall act according to the following:

- the MSC-A acts as the MSC;
- the MSC-I acts as the BSS.

## 5.9 Trace invocation

For the Trace invocation (3GPP TS 48.008 subclause 3.1.11), the involved MSCs shall act according to the following:

- the MSC-A acts as the MSC;
- the MSC-I acts as the BSS.

Additionally, at Basic Inter-MSD Handover and at Subsequent Inter-MSD Handover (3GPP TS 23.009), if the MSD that is the MSD-A is not also the MSD-T, the Trace invocation (3GPP TS 48.008 subclause 3.1.11) is applied on the E-interface with the following conditions:

- the MSD-A acts as the MSD;
- the MSD-T acts as the target BSS.

## 5.10 Queuing indication

For the Queuing Indication (3GPP TS 48.008 subclause 3.1.17), the involved MSDs shall act according to the following:

- at Assignment and at Basic Inter-MSD handover:
  - the MSD-A acts as the MSD;
  - the MSD-I acts as the BSS.
- at Subsequent Inter-MSD handover:
  - the MSD-I acts as the MSD;
  - the MSD-T acts as the BSS;
  - if the MSD that is the MSD-A is not also the MSD-T, then this MSD acts as the target BSS towards the MSD-I and as the MSD towards the MSD-T.

## 5.11 Data link control SAPI not equal to "0"

For the Data Link Control SAPI not Equal to "0" (3GPP TS 48.008 subclause 3.1.18), the involved MSDs shall act according to the following:

- the MSD-A acts as the MSD;
- the MSD-I acts as the BSS.

## 5.12 Location Acquisition

For the Location Acquisition procedure (3GPP TS 48.008 subclause 3.1.28), the involved MSDs shall act according to the following:

- the MSD-A acts as the MSD;
- the MSD-I acts as the BSS.

## 5.13 LSA handling

For the LSA handling (3GPP TS 48.008 subclause 3.1.27), the involved MSDs shall act according to the following:

- the MSD-A acts as the MSD;
- the MSD-I acts as the BSS.

## 5.14 Common ID

For the Common Id (3GPP TS 48.008), the involved MSDs shall act according to the following:

- the MSD-A acts as the MSD;

- the MSC-I acts as the BSS.

#### 5.15 Service Change procedure

In the Service Change procedure for network-initiated SCUDIF (see 3GPP TS 23.172), the MSC-I sends the CHANNEL MODIFY REQUEST message (see 3GPP TS 48.008) to the MSC-A. The request was originally sent by the RNC using RAB MODIFY REQUEST to trigger execution of the alternative RAB configuration (see 3GPP TS 25.413). For the CHANNEL MODIFY REQUEST message, the involved MSCs shall act according to the following:

- the MSC-A acts as the MSC;
- the MSC-I acts as the BSS.

---

## 6 BSSMAP messages transferred on the E-interface

The following BSSMAP messages, defined in 3GPP TS 48.008 [4] subclause 3.2.1, are transferred on the E-interface:

### ASSIGNMENT REQUEST (MSC-A -> MSC-I)

Excluded information elements: CIRCUIT IDENTITY CODE, AoIP Transport Layer Address (MGW), Call Identifier, Codec List (MSC Preferred)

### ASSIGNMENT COMPLETE (MSC-I -> MSC-A)

Excluded information elements: CIRCUIT POOL, CIRCUIT IDENTITY CODE, AoIP Transport Layer Address (BSS), Speech Codec (Chosen), Codec List (BSS Supported)

### ASSIGNMENT FAILURE (MSC-I -> MSC-A)

Excluded information elements: CIRCUIT POOL, CIRCUIT POOL LIST

### \* HANDOVER REQUEST (MSC-A -> MSC-T and MSC-I -> MSC-A)

Excluded information elements: CIRCUIT IDENTITY CODE, AoIP Transport Layer Address (MGW), Call Identifier, Codec List (MSC Preferred)

### \* HANDOVER REQUEST ACKNOWLEDGE (MSC-T -> MSC-A and MSC-A -> MSC-I)

Excluded information elements: CIRCUIT POOL, CIRCUIT IDENTITY CODE, AoIP Transport Layer Address (BSS), Speech Codec (Chosen), Codec List (BSS Supported)

### \* HANDOVER COMPLETE (MSC-T -> MSC-A)

### \* HANDOVER FAILURE (MSC-T -> MSC-A, MSC-A -> MSC-I and MSC-I -> MSC-A)

Excluded information elements: CIRCUIT POOL, CIRCUIT POOL LIST, Codec List (BSS Supported)

### HANDOVER PERFORMED (MSC-I -> MSC-A)

Excluded information elements: Speech Codec (Chosen), Codec List (BSS Supported)

### \* HANDOVER DETECT (MSC-T -> MSC-A)

### CLEAR REQUEST (MSC-I -> MSC-A and MSC-T -> MSC-A)

### SAPI "n" REJECT (MSC-I -> MSC-A)

### CONFUSION (MSC-T -> MSC-A, MSC-A -> MSC-T, MSC-I -> MSC-A and MSC-A -> MSC-I)

### # MSC INVOKE TRACE (MSC-A -> MSC-I and MSC-A -> MSC-T)

### # BSS INVOKE TRACE (MSC-I -> MSC-A and MSC-A -> MSC-T)

### CIPHER MODE COMMAND (MSC-A -> MSC-I)

CIPHER MODE COMPLETE (MSC-I -> MSC-A)

CIPHER MODE REJECT (MSC-I -> MSC-A)

\*\* QUEUING INDICATION (MSC-T -> MSC-A, MSC-I -> MSC-A, and MSC-A -> MSC-I)

CLASSMARK UPDATE (MSC-I -> MSC-A and MSC-A -> MSC-T)

CLASSMARK REQUEST (MSC-A -> MSC-I)

CONNECTION ORIENTED INFORMATION (MSC-I -> MSC-A, MSC-A->MSC-I)

LSA INFORMATION (MSC-A -> MSC-I)

PERFORM LOCATION REQUEST (MSC-I->MSC-A, MSC-A -> MSC-I)

PERFORM LOCATION ABORT (MSC-I->MSC-A, MSC-A -> MSC-I)

PERFORM LOCATION RESPONSE (MSC-I -> MSC-A, MSC-A->MSC-I)

COMMON ID (MSC-A -> MSC-I)

CHANNEL MODIFY REQUEST (MSC-I -> MSC-A)

All other BSSMAP messages shall be considered as non-existent on the E-interface.

NOTE: Segmentation procedures for LCS CONNECTION ORIENTED INFORMATION message in 3GPP TS 48.008 [4] apply to the corresponding message on the E-interface.

Some of the messages above are qualified by \*, \*\* or #. This signifies whether the message, when sent on the E-interface, is considered as:

- handover related message (\*);
- handover related when sent as a response to HANDOVER REQUEST (\*\*); or
- trace related message (#).

---

## 7 Exceptions for BSSMAP message contents and information element coding when transferred on the E-interface

### 7.1 Message contents

For the applicable BSSMAP messages transferred on the E-interface the following exceptions to the descriptions in 3GPP TS 48.008 [4] subclause 3.2.1 are valid:

Assignment request message:

- excluded information elements:
  - circuit identity code;
  - AoIP Transport Layer Address (MGW);
  - Call Identifier;
  - Codec List (MSC Preferred).
- if received, the information element shall be treated as an information element with an unrecognisable identifier.

Assignment complete message:

- excluded information element:
  - circuit pool;
  - circuit identity code;
  - AoIP Transport Layer Address (BSS);
  - Speech Codec (Chosen);
  - Codec List (BSS Supported).
- if received, the information element shall be treated as an information element with an unrecognisable identifier.

Assignment failure message:

- excluded information elements:
  - circuit pool;
  - circuit pool list;
  - Codec List (BSS Supported).
- if received, the information element shall be treated as an information element with an unrecognisable identifier.

Handover request message:

- excluded information element:
  - circuit identity code;
  - AoIP Transport Layer Address (MGW);
  - Call Identifier;
  - Codec List (MSC Preferred).
- if received, the information element shall be treated as an information element with an unrecognisable identifier.

Handover request acknowledge message:

- excluded information element:
  - circuit pool;
  - circuit identity code;
  - AoIP Transport Layer Address (BSS);
  - Speech Codec (Chosen);
  - Codec List (BSS Supported).
- if received, the information element shall be treated as an information element with an unrecognisable identifier.

Handover failure message:

- excluded information elements:
  - circuit pool;
  - circuit pool list;
  - Codec List (BSS Supported).
- if received, the information element shall be treated as an information element with an unrecognisable identifier.

Handover performed message:

- excluded information elements:
  - Speech Codec (Chosen);
  - Codec List (BSS Supported).
- if received, the information element shall be treated as an information element with an unrecognisable identifier.

## 7.2 Information element coding

For the applicable BSSMAP information elements transferred on the E-interface the following exceptions to the description in 3GPP TS 48.008 [4] subclause 3.2.2.5 are valid:

Cause information element:

- excluded causes:
  - call control;
  - CCCH overload;
  - handover successful;
  - requested terrestrial resource unavailable;
  - terrestrial circuit already allocated;
  - circuit pool mismatch;
  - switch circuit pool;
  - Call Identifier already allocated.

The corresponding cause values shall be considered as reserved for national use.

Cell identifier information element:

- excluded format:
  - Cell Identity.

The corresponding cell identification discriminator value shall be considered as reserved.

---

## 8 BSSAP message error handling when transferred on the E-interface

The handling of abnormal events related to the BSSAP header (3GPP TS 48.008 subclause 2.4) and the BSSMAP error handling (3GPP TS 48.008 subclause 3.1.19) are applicable with exception of the following:

- the handling of faults concerning the use of SCCP is not applicable.

The BSSMAP error messages sent on the E-interface shall only be sent as response to BSSAP messages received on the same interface.

---

## Annex A (informative): Change history



TSG N	TSGN-number	WG Number	Spec	CR	Rev	Rel	Cat	Old vers	New ver	Title	WI	Notes
s29	P-99-476		09.08	A133		R98	B	6.0.0	7.0.0	Application of the Base Station System Application Part (BSSAP) on the E-interface for LCS		
S30	P-99-617		09.08	A134		R98	B	7.0.0	7.1.0	Addition of LSA Information message		
NP-06	NP-99446		09.08	A137		R98	C	7.1.0	7.2.0	Changes due to LCS enhancements		
NP-06	NP-99446		09.08	A139		R98	C	7.1.0	7.2.0	LCS CR for GSM 09.08		
S31			09.08			R99		7.2.0	8.0.0	Version release upgrade 1999		
NP-10	NP-000673	N1-001319	09.08	A140		R99	F	8.0.0	8.1.0	Addition of Common Id procedure on the E-interface	TEI	Specification layout is changed to 3GPP
NP-11			49.008			Rel-4		8.1.0	4.0.0	Release 4 version after CN#11, 09.08 -> 49.008		
			49.008			Rel-4		4.0.0	4.0.1		03.05.2002	ETSI/MCC cleanup on references and editorials.
NP-16			49.008			Rel-5		4.0.1	5.0.0		06-2002	CN plenary decision to make this TS also for Release 5.
NP-19	NP-030040	N1-030086	49.008	002		Rel-5	A	5.0.0	5.1.0	Corrections to the list of BSSMAP messages transferred on the E-interface	GSM/UMTS interworking	
NP-26			49.008			Rel-5		5.1.0	6.0.0		12-2004	CN plenary decision to make this TS also for Release 6.
CP-28	CP-050180		49.008	03		Rel-6	F	6.0.0	6.1.0	Network-initiated SCUDIF on MAP/E-interface with BSSAP	06-2005	
						Rel-7		6.1.0	7.0.0		07-2007	CT plenary decision to make this TS also for Release 7
CP-42						Rel-8		7.0.0	8.0.0		12-2008	CT plenary decision to make this TS also for Release 8
CP-43	CP-090145	C1-090842	49.008	0004	1	Rel-8		8.0.0	8.1.0	Protocol Alignment for AoIP	03-2009	
								8.1.0	8.1.1	Correction to cover page	04-2009	
CP-46								8.1.1	9.0.0	Upgrade to Rel-9	12-2009	
CP-51								9.0.0	10.0.0	Upgrade to Rel-10	03-2011	
CP-57								10.0.0	11.0.0	Upgrade to Rel-11	09-2012	
CP-65	-	-	-	-	-	-	-	11.0.0	12.0.0	Upgrade to Rel-12	09-2014	12.0.0
CP-70								12.0.0	13.0.0	Upgrade to Rel-13	12-2015	13.0.0

Change history							
Date	Meeting	TDoc	CR	Rev	Cat	Subject/Comment	New version
2017-03	SA#75					Upgrade to Rel-14	14.0.0
2018-06	SA#80	-	-	-	-	Update to Rel-15 version (MCC)	15.0.0
2020-06	SA#88e					Update to Rel-16 version (MCC)	16.0.0
2022-04	SA#95e	-	-	-	-	Update to Rel-17 version (MCC)	17.0.0
2024-04	-	-	-	-	-	Update to Rel-18 version (MCC)	18.0.0
2025-10	-	-	-	-	-	Update to Rel-19 version (MCC)	19.0.0

---

# History

Document history		
V19.0.0	October 2025	Publication