

**Broadband Integrated Services Digital Network (B-ISDN);  
Digital Subscriber Signalling System No. two (DSS2) protocol;  
Quality of Service class and parameters indication  
at call/connection establishment;  
Part 3: Test Suite Structure and Test Purposes (TSS&TP)  
specification for the user**

---



---

Reference

DEN/SPAN-130251-3

---

Keywords

B-ISDN, DSS2, quality, TSS&TP, user

**ETSI**

650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° 7803/88

---

**Important notice**

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, send your comment to:

[editor@etsi.fr](mailto:editor@etsi.fr)

---

**Copyright Notification**

No part may be reproduced except as authorized by written permission.  
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2002.  
All rights reserved.

**DECT™**, **PLUGTESTS™** and **UMTS™** are Trade Marks of ETSI registered for the benefit of its Members.  
**TIPHON™** and the **TIPHON logo** are Trade Marks currently being registered by ETSI for the benefit of its Members.  
**3GPP™** is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

---

# Contents

Intellectual Property Rights .....	4
Foreword.....	4
1 Scope .....	5
2 References .....	5
3 Definitions and abbreviations.....	6
3.1 Definitions .....	6
3.1.1 Definitions related to conformance testing .....	6
3.1.2 Definitions related to EN 301 815-1 .....	6
3.2 Abbreviations .....	6
4 Test Suite Structure (TSS).....	7
5 Test Purposes (TP) .....	7
5.1 Introduction .....	7
5.1.1 TP naming convention .....	7
5.1.2 Source of TP definition .....	7
5.1.3 Test strategy .....	7
5.1.4 Test of call states .....	7
5.2 TPs for the Quality of Service Class and Parameters indication, user.....	8
5.2.1 Support of Quality of Service classes (01).....	8
5.2.2 Signalling of individual Quality of Service parameters .....	9
5.2.2.1 End-to-end transit delay procedures (02) .....	9
5.2.2.2 Extended QoS parameters procedures (03) .....	12
6 Compliance.....	13
7 Requirements for a comprehensive testing service .....	13
<b>Annex A (informative): Bibliography .....</b>	<b>14</b>
History .....	15

---

## Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://webapp.etsi.org/IPR/home.asp>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

---

## Foreword

This European Standard (Telecommunications series) has been produced by ETSI Technical Committee Services and Protocols for Advanced Networks (SPAN), and is now submitted for the Vote phase of the ETSI standards Two-step Approval Procedure.

The present document is part 3 of a multi-part deliverable covering the Digital Subscriber Signalling System No. two (DSS2) protocol specification for the Broadband Integrated Services Digital Network (B-ISDN) to support Quality of Service class and parameters indication at call/connection establishment, as identified below:

- Part 1: "Protocol specification [ITU-T Recommendations Q.2965.1 (1999) and Q.2965.2 (1999), modified]";
- Part 2: "Protocol Implementation Conformance Statement (PICS) proforma specification [ITU-T Recommendations Q.2965.1B (2000) and Q.2965.2B (2000), modified]";
- Part 3: "Test Suite Structure and Test Purposes (TSS&TP) specification for the user";**
- Part 4: "Abstract Test Suite (ATS) and partial Protocol Implementation eXtra Information for Testing (PIXIT) proforma specification for the user";
- Part 5: "Test Suite Structure and Test Purposes (TSS&TP) specification for the network";
- Part 6: "Abstract Test Suite (ATS) and partial Protocol Implementation eXtra Information for Testing (PIXIT) proforma specification for the network".

<b>Proposed national transposition dates</b>	
Date of latest announcement of this EN (doa):	3 months after ETSI publication
Date of latest publication of new National Standard or endorsement of this EN (dop/e):	6 months after doa
Date of withdrawal of any conflicting National Standard (dow):	6 months after doa

---

# 1 Scope

The present document specifies the user Test Suite Structure and Test Purposes (TSS&TP) for the  $T_B$  reference point or coincident  $S_B$  and  $T_B$  reference point (as defined in ITU-T Recommendation I.413 [5]) of implementations conforming to the standards for the Broadband Integrated Services Digital Network (B-ISDN) Digital Subscriber Signalling System No. two (DSS2) protocol specification for support of Quality of Service Class and parameters indication at call/connection establishment defined in EN 301 815-1 [1].

A further part of the present document specifies the Abstract Test Suite (ATS) and partial Protocol Implementation eXtra Information for Testing (PIXIT) proforma based on the present document.

---

# 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication and/or edition number or version number) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies.

- [1] ETSI EN 301 815-1: "Broadband Integrated Services Digital Network (B-ISDN); Digital Subscriber Signalling System No. two (DSS2) protocol; Quality of Service Class and parameters indication at call/connection establishment; Part 1: Protocol specification [ITU-T Recommendations Q.2965.1 (1999) and Q.2965.2 (1999), modified]".
- [2] ETSI EN 301 815-2: "Broadband Integrated Services Digital Network (B-ISDN); Digital Subscriber Signalling System No. two (DSS2) protocol; Quality of Service class and parameters indication at call/connection establishment; Part 2: Protocol Implementation Conformance Statement (PICS) proforma specification [ITU-T Recommendations Q.2965.1B (2000) and Q.2965.2B (2000), modified]".
- [3] ISO/IEC 9646-1 (1994): "Information technology - Open Systems Interconnection - Conformance testing methodology and framework - Part 1: General concepts".
- [4] ISO/IEC 9646-2 (1994): "Information technology - Open Systems Interconnection - Conformance testing methodology and framework - Part 2: Abstract Test Suite specification".
- [5] ITU-T Recommendation I.413 (1993): "B-ISDN user-network interface".
- [6] ETSI ETS 300 406: "Methods for Testing and Specification (MTS); Protocol and profile conformance testing specifications; Standardization methodology".
- [7] ETSI EN 300 443-1: "Broadband Integrated Services Digital Network (B-ISDN); Digital Subscriber Signalling System No. two (DSS2) protocol; B-ISDN user-network interface layer 3 specification for basic call/bearer control; Part 1: Protocol specification [ITU-T Recommendation Q.2931 (1995), modified]".
- [8] ITU-T Recommendation Q.2965.1: "Digital Subscriber Signalling System No. 2 - Support of Quality of Service classes".
- [9] ITU-T Recommendation Q.2965.2: "Digital Subscriber Signalling System No. 2 - Signalling of individual Quality of Service parameters".

## 3 Definitions and abbreviations

### 3.1 Definitions

For the purposes of the present document, the terms and definitions given in EN 301 815-1 [1], EN 300 443-1 [7] and the following apply.

#### 3.1.1 Definitions related to conformance testing

**abstract test case:** Refer to ISO/IEC 9646-1 [3].

**Abstract Test Method (ATM):** Refer to ISO/IEC 9646-1 [3].

**Abstract Test Suite (ATS):** Refer to ISO/IEC 9646-1 [3].

**Implementation Under Test (IUT):** Refer to ISO/IEC 9646-1 [3].

**Lower Tester (LT):** Refer to ISO/IEC 9646-1 [3].

**Protocol Implementation Conformance Statement (PICS):** Refer to ISO/IEC 9646-1 [3].

**PICS proforma:** Refer to ISO/IEC 9646-1 [3].

**Protocol Implementation eXtra Information for Testing (PIXIT):** Refer to ISO/IEC 9646-1 [3].

**PIXIT proforma:** Refer to ISO/IEC 9646-1 [3].

**Test Purpose (TP):** Refer to ISO/IEC 9646-1 [3].

#### 3.1.2 Definitions related to EN 301 815-1

**user:** DSS2 protocol entity at the User side of the user-network interface where a  $T_B$  reference point or coincident  $S_B$  and  $T_B$  reference point applies

**user ( $S_B/T_B$ ):** DSS2 protocol entity at the User side of the user-network interface where a coincident  $S_B$  and  $T_B$  reference point applies

**user ( $T_B$ ):** DSS2 protocol entity at the User side of the user-network interface where a  $T_B$  reference point applies (user is a private ISDN)

### 3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

ATM	Abstract Test Method
ATS	Abstract Test Suite
B-ISDN	Broadband Integrated Services Digital Network
DSS2	Digital Subscriber Signalling System No. two
IUT	Implementation Under Test
PICS	Protocol Implementation Conformance Statement
PIXIT	Protocol Implementation eXtra Information for Testing
QoS	Quality of Service
TP	Test Purpose
TSS	Test Suite Structure
U0	Null call/connection state
U1	Call Initiated call/connection state
U10	Active call/connection state
U11	Release Request call/connection state
U3	Outgoing Call Proceeding call/connection state

U4	Call Delivered call/connection state
U7	Call Received call/connection state
U8	Connect Request call/connection state
U9	Incoming Call Proceeding call/connection state

---

## 4 Test Suite Structure (TSS)

- Support of Quality of Service classes (01)
- Signalling of individual Quality of Service parameters
  - End-to-end transit delay procedures (02)
  - Extended QoS parameters procedures (03)

---

## 5 Test Purposes (TP)

### 5.1 Introduction

For each test requirement a TP is defined.

#### 5.1.1 TP naming convention

Tps are numbered, starting at 01, within each group. Groups are organized according to the TSS. Additional references are added to identify the actual test suite (see table 1).

**Table 1: TP identifier naming convention scheme**

Identifier:	<suite_id>_<group>_<nnn>
<suite_id>=	service + type of IUT: "QOSU" for Quality Of Service class and parameters indication, IUT = User
<group> =	group number: two character field representing the group reference according to TSS
<nn> =	sequential number: (01-99)

#### 5.1.2 Source of TP definition

The TPs are based on EN 301 815-1 [1].

#### 5.1.3 Test strategy

As the base standard EN 301 815-1 [1] contains no explicit requirements for testing, the TPs were generated as a result of an analysis of the base standard and the PICS specification EN 301 815-2 [2].

The TPs are only based on conformance requirements related to the externally observable behaviour of the IUT and are limited to conceivable situations to which a real implementation is likely to be faced (see ETS 300 406 [6]).

#### 5.1.4 Test of call states

Many TPs include a reference to the IUT's final call state after the realization of the TP. In these cases the TP includes the requirement to ensure that the IUT has entered this particular final call state. Ensuring that the IUT is in a particular call state shall be realized by following the procedures described in clause 5.6.11 of EN 300 443-1 [7]. According to these procedures, the IUT on receipt of a STATUS ENQUIRY message, shall respond with a STATUS message indicating, in the fifth octet of the Call state information element, the current call state of the IUT. This exchange of messages is not mentioned explicitly in each TP but is considered to be implicit in the reference to the final call state. This way of phrasing the TPs has been used to avoid over-complicating the text and structure of the TPs and to improve the readability.

## 5.2 TPs for the Quality of Service Class and Parameters indication, user

All PICS items referred to in this clause are as specified in EN 301 815-2 [2] unless indicated otherwise by another numbered reference.

Unless specified:

- the messages indicated are valid and contain at least the mandatory information elements and possibly optional information elements;
- the information elements indicated are valid and contain at least the mandatory parameters and possibly optional parameters.

### 5.2.1 Support of Quality of Service classes (01)

Test purposes for EN 301 815-1 [1] (ITU-T Recommendation Q.2965.1 [8], modified).

#### QOSU\_01\_01

Ensure that the IUT in U0, to initiate call establishment, sends a SETUP message (Quality of Service parameter indicating identical forward and backward QoS classes, Broadband bearer capability, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters) and enters U1.

**Selection:** Outgoing calls with QoS class indication supported. PICS: MCu 1

#### QOSU\_01\_02

Ensure that the IUT in U0, on receipt of a SETUP message (Valid combination of traffic parameters, Quality of Service parameter present, requesting a QOS class that is supported), sends any of a CALL PROCEEDING, ALERTING or CONNECT message and enters the relevant call state U9, U7 or U8.

**Selection:** Incoming calls with QoS class interpretation supported. PICS: MCu 2

#### QOSU\_01\_03

Ensure that the IUT in U0, on receipt of a SETUP message (Valid combination of traffic parameters, Quality of Service parameter present, requesting a QOS class that is not supported), sends a RELEASE COMPLETE message (Cause value = 49) and remains in U0.

**Selection:** Incoming calls with QoS class interpretation supported. PICS: MCu 2

#### QOSU\_01\_04

Ensure that the IUT in U0, on receipt of a SETUP message (Invalid combination of traffic parameters and QOS class), sends a RELEASE COMPLETE message (Cause value = 73) and remains in U0.

**Selection:** Incoming calls with QoS class interpretation supported. PICS: MCu 2



## 5.2.2 Signalling of individual Quality of Service parameters

Test purposes for EN 301 815-1 [1] (ITU-T Recommendation Q.2965.2 [9], modified).

### 5.2.2.1 End-to-end transit delay procedures (02)

#### QOSU\_02\_01

Ensure that the IUT in U0, to initiate call establishment,  
sends a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters) and enters U1.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

#### QOSU\_02\_02

Ensure that the IUT in U3, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay present),  
sends a CONNECT ACKNOWLEDGE message and enters U10.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

#### QOSU\_02\_03

Ensure that the IUT in U4, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay present),  
sends a CONNECT ACKNOWLEDGE message and enters U10.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

#### QOSU\_02\_04

Ensure that the IUT in U3, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element absent),  
sends a STATUS message (Cause value = 96, call state value = 3) and remains in U3.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

#### QOSU\_02\_05

Ensure that the IUT in U4, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element absent),  
sends a STATUS message (Cause value = 96, call state value = 4) and remains in U4.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

#### QOSU\_02\_06

Ensure that the IUT in U3, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = IE instruction field not significant),  
sends a STATUS message (Cause value = 100, call state value = 3) and remains in U3.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

#### QOSU\_02\_07

Ensure that the IUT in U3, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = clear call),  
sends a RELEASE message (Cause value = 100) and enters U11.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_08**

Ensure that the IUT in U3, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = discard message and report status), sends a STATUS message (Cause value = 100, call state value = 3) and remains in U3.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_09**

Ensure that the IUT in U3, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = discard message), sends no message and remains in U3.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_10**

Ensure that the IUT in U3, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = discard information element, proceed and report status),

sends a STATUS message (Cause value = 100, call state value = 10) followed by a CONNECT ACKNOWLEDGE message and enters U10.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_11**

Ensure that the IUT in U3, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = discard information element and proceed), sends a CONNECT ACKNOWLEDGE message and enters U10.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_12**

Ensure that the IUT in U3, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = reserved value),

sends a STATUS message (Cause value = 100, call state value = 10) followed by a CONNECT ACKNOWLEDGE message and enters U10.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_13**

Ensure that the IUT in U4, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = IE instruction field not significant),

sends a STATUS message (Cause value = 100, call state value = 4) and remains in U4.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_14**

Ensure that the IUT in U4, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = clear call),  
sends a RELEASE message (Cause value = 100) and enters U11.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_15**

Ensure that the IUT in U4, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = discard message and report status),  
sends a STATUS message (Cause value = 100, call state value = 4) and remains in U4.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_16**

Ensure that the IUT in U4, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = discard message),  
sends no message and remains in U4.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_17**

Ensure that the IUT in U4, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = discard information element, proceed and report status),  
sends a STATUS message (Cause value = 100, call state value = 10) followed by a CONNECT ACKNOWLEDGE message and enters U10.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_18**

Ensure that the IUT in U4, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = discard information element and proceed),  
sends a CONNECT ACKNOWLEDGE message and enters U10.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_19**

Ensure that the IUT in U4, having sent a SETUP message (End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (End-to-end transit delay information element with maximum end-to-end transit delay subfield present, IE instruction field flag = follow explicit instructions, IE action indicator = reserved value),  
sends a STATUS message (Cause value = 100, call state value = 10) followed by a CONNECT ACKNOWLEDGE message and enters U10.

**Selection:** Outgoing calls with End-to-end transfer delay indication in SETUP messages. PICS: MCu 1

**QOSU\_02\_20**

Ensure that the IUT in U0, on receipt of a SETUP message (End-to-end transit delay present, requesting a QOS class/maximum end-to-end transit delay combination that can be supported),  
sends any of a CALL PROCEEDING, ALERTING or CONNECT message and enters the relevant call state U9, U7 or U8.

**QOSU\_02\_21**

Ensure that the IUT in U7 or U9, having received a SETUP message (End-to-end transit delay present, requesting a QOS class/maximum end-to-end transit delay combination that can be supported), to accept the call, sends a CONNECT message (End-to-end transit delay present, maximum end-to-end transit delay absent) and enters U10.

**Selection:** Incoming calls with End-to-end transfer delay indication in CONNECT messages. PICS: MCu 3.2

**QOSU\_02\_22**

Ensure that the IUT in U0, on receipt of a SETUP message (End-to-end transit delay present, requesting a QOS class/maximum end-to-end transit delay combination that can not be supported), sends a RELEASE COMPLETE message (Cause value = 49) and remains in U0.

**QOSU\_02\_23**

Ensure that the IUT in U0, on receipt of a SETUP message (End-to-end transit delay present, invalid combination of transit delay, traffic parameters and QOS class), sends a RELEASE COMPLETE message (Cause value = 73) and remains in U0.

**5.2.2.2 Extended QoS parameters procedures (03)**

**Selection:**  $T_B$  reference point supported. PICS: R 1.2

**QOSU\_03\_01**

Ensure that the IUT in U0, to initiate call establishment, sends a SETUP message (Extended Quality of Service parameter, End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters) and enters U1.

**Selection:** Outgoing calls with Extended Quality of Service parameter indication in SETUP messages. PICS: MCu 2

**QOSU\_03\_02**

Ensure that the IUT in U3, having sent a SETUP message (Extended Quality of Service parameter, End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (Extended Quality of Service parameter present), sends a CONNECT ACKNOWLEDGE message and enters U10.

**Selection:** Outgoing calls with Extended Quality of Service parameter indication in SETUP messages. PICS: MCu 2

**QOSU\_03\_03**

Ensure that the IUT in U4, having sent a SETUP message (Extended Quality of Service parameter, End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (Extended Quality of Service parameter present), sends a CONNECT ACKNOWLEDGE message and enters U10.

**Selection:** Outgoing calls with Extended Quality of Service parameter indication in SETUP messages. PICS: MCu 2

**QOSU\_03\_04**

Ensure that the IUT in U3, having sent a SETUP message (Extended Quality of Service parameter, End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (Extended Quality of Service parameter absent), sends a STATUS message (Cause value = 96, call state value = 3) and remains U3.

**Selection:** Outgoing calls with Extended Quality of Service parameter indication in SETUP messages. PICS: MCu 2

**QOSU\_03\_05**

Ensure that the IUT in U4, having sent a SETUP message (Extended Quality of Service parameter, End-to-end transit delay, Quality of Service parameter, ATM traffic descriptor, Broadband bearer capability present, consistent set of parameters), on receipt of a CONNECT message (Extended Quality of Service parameter absent), sends a STATUS message (Cause value = 96, call state value = 4) and remains U4.

**Selection:** Outgoing calls with Extended Quality of Service parameter indication in SETUP messages.  
PICS: MCu 2

**QOSU\_03\_06**

Ensure that the IUT in U0, on receipt of a SETUP message (Extended Quality of Service parameter, End-to-end transit delay present, requesting a QOS class/maximum end-to-end transit delay combination that can be supported), sends any of a CALL PROCEEDING, ALERTING or CONNECT message and enters the relevant call state U9, U7 or U8.

**QOSU\_03\_07**

Ensure that the IUT in U7 or U9, having received a SETUP message (Extended Quality of Service parameter, End-to-end transit delay present, requesting a QOS class/maximum end-to-end transit delay combination that can be supported), to accept the call, sends a CONNECT message (Extended Quality of Service parameter present) and enters U10.

**Selection:** Incoming calls with Extended Quality of Service parameter indication in CONNECT messages.  
PICS: MCu 4.2

**QOSU\_03\_08**

Ensure that the IUT in U0, on receipt of a SETUP message (Extended Quality of Service parameter present, requesting an unacceptable 2-point cell delay variation), sends a RELEASE COMPLETE message (Cause value = 49) and remains in U0.

**QOSU\_03\_09**

Ensure that the IUT in U0, on receipt of a SETUP message (Extended Quality of Service parameter present, invalid combination of transit delay, traffic parameters and individual QOS parameters), sends a RELEASE COMPLETE message (Cause value = 73) and remains in U0.

## 6 Compliance

An ATS which complies with this TSS&TP specification shall:

- a) consist of a set of test cases corresponding to the set or to a subset of the TPs specified in clause 5;
- b) use a TSS which is an appropriate subset of the whole of the TSS specified in clause 4;
- c) use the same naming conventions for the test groups and test cases;
- d) maintain the relationship specified in clause 5 between the test groups and TPs and the entries in the PICS proforma to be used for test case deselection;
- e) comply with ISO/IEC 9646-2 [4].

In the case of a) or b) above, a subset shall be used only where a particular Abstract Test Method (ATM) makes some TPs untestable. All testable TPs from clause 5 shall be included in a compliant ATS.

## 7 Requirements for a comprehensive testing service

As a minimum the Remote test method, as specified in ISO/IEC 9646-2 [4], shall be used by any organization claiming to provide a comprehensive testing service for network equipment claiming conformance to EN 301 815-1 [1].

---

## Annex A (informative): Bibliography

ISO/IEC 9646-3 (1998): "Information technology - Open Systems Interconnection - Conformance testing methodology and framework - Part 3: The Tree and Tabular Combined Notation (TTCN)".

---

## History

<b>Document history</b>			
V1.1.1	April 2002	Public Enquiry	PE 20020802: 2002-04-03 to 2002-08-02
V1.1.1	August 2002	Vote	V 20021011: 2002-08-12 to 2002-10-11