

**Electromagnetic compatibility
and Radio spectrum Matters (ERM);
Wideband Transmission systems;
Data transmission equipment operating
in the 2,4 GHz ISM band
and using spread spectrum modulation techniques;
Specification of Reference Receiver Performance Parameters
for Spectrum Planning**



Reference

DES/ERM-TG11-002

Keywords

data, ISM, LAN, mobile, radio, spread spectrum,
SRD, testing, transmission, UHF

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, send your comment to:

editor@etsi.org

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2002.
All rights reserved.

DECT™, **PLUGTESTS™** and **UMTS™** are Trade Marks of ETSI registered for the benefit of its Members.
TIPHON™ and the **TIPHON logo** are Trade Marks currently being registered by ETSI for the benefit of its Members.
3GPP™ is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

Contents

Intellectual Property Rights	4
Foreword.....	4
1 Scope	5
2 References	5
3 Definitions and abbreviations.....	6
3.1 Definitions	6
3.2 Abbreviations	7
4 Receiver performance parameters	7
4.1 Introduction	7
4.2 Applicability overview	7
4.3 Receiver parameter definitions.....	7
4.3.1 Rx Sensitivity.....	7
4.3.2 Blocking or desensitization.....	8
4.3.3 Adjacent Channel Selectivity.....	8
4.4 Reference values.....	8
4.4.1 IEEE 802.11 - FH systems.....	8
4.4.2 IEEE 802.11 - DS and IEEE 802.11b systems.....	8
4.4.3 IEEE 802.11g systems - ERP OFDM operation	9
4.4.4 IEEE 802.11g systems - ERP PBCC operation	9
4.4.5 HomeRF systems	10
4.4.6 Bluetooth™ systems	10
5 Recommended methods of measurement.....	10
5.1 Test conditions	10
5.1.1 Normal test conditions	10
5.1.1.1 Normal temperature and humidity	10
5.1.1.2 Normal power source	11
5.1.1.2.1 Mains voltage	11
5.1.1.2.2 Lead-acid battery power sources used on vehicles	11
5.1.1.2.3 Other power sources	11
5.1.2 Normal modulation	11
5.2 Test arrangements.....	11
5.3 Minimum Rx Sensitivity	11
5.3.1 Method of measurement	11
5.4 Blocking or desensitization	12
5.5 Adjacent Channel Selectivity	12
5.5.1 General.....	12
5.5.2 Method of measurement	12
6 Interpretation of measurement results	13
Annex A (informative): Bibliography.....	14
History	15

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://webapp.etsi.org/IPR/home.asp>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This ETSI Standard (ES) has been produced by ETSI Technical Committee Electromagnetic compatibility and Radio spectrum Matters (ERM), and is now submitted for the ETSI standards Membership Approval Procedure.

1 Scope

The present document specifies the reference receiver performance parameters, not covered by the harmonized standard EN 300 328 [1], which are required for the purpose of spectrum planning and methods of investigation including resolving interference issues. These parameters play a fundamental role in the frequency planning and the respective compatibility analysis performed by responsible national administrations.

The present document applies to equipment utilizing wideband radio modulation techniques such as described in the IEEE 802.11 [3], [4] and [5], HomeRF (see bibliography) and Bluetooth™ [6] standards.

Fixed, mobile or portable applications, e.g.:

- stand-alone radio equipment with or without their own control provisions;
- plug-in radio devices intended for use with or within a variety of host systems, e.g. personal computers, hand-held terminals, etc.;
- plug-in radio devices intended for use within combined equipment, e.g. cable modems, set-top boxes, access points, etc.;
- combined equipment or a combination of a plug-in radio device and a specific type of host equipment.

This radio equipment is capable of operating in all or any part of the Industrial, Scientific and Medical (ISM) service frequency band shown in table 1.

Table 1: Industrial, Scientific and Medical (ISM) service frequency band

Direction of transmission	Industrial, Scientific and Medical (ISM) service frequency band
Transmit/Receive	2,4 GHz to 2,483 5 GHz

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication and/or edition number or version number) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies.

- [1] ETSI EN 300 328: "Electromagnetic compatibility and Radio spectrum Matters (ERM); Wideband Transmission systems; Data transmission equipment operating in the 2.4 GHz ISM band and using spread spectrum modulation techniques".
- [2] ETSI TR 100 028 (all parts): "Electromagnetic compatibility and Radio spectrum Matters (ERM); Uncertainties in the measurement of mobile radio equipment characteristics".
- [3] IEEE 802.11: "IEEE Standard for Information Technology - Telecommunications and information exchange between systems - Local and Metropolitan networks - Specific requirements - Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) specifications".
- [4] IEEE 802.11b: "IEEE Standard for Information Technology - Telecommunications and information exchange between systems - Local and Metropolitan networks - Specific requirements - Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) specifications: Higher speed Physical Layer (PHY) extension in the 2.4 Ghz band".

- [5] IEEE 802.11g: "Supplement to STANDARD [FOR] Information Technology - Telecommunications and information exchange between systems-Local and Metropolitan networks - Specific requirements - Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) specifications: Further Higher data rate extension in the 2.4GHz band".
- [6] "Bluetooth Specification Version 1.1"; February 22, 2001.

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the following terms and definitions apply:

Bluetooth™ system: Equipment in compliance with Bluetooth™ specification [6].

combined equipment: any combination of non-radio equipment that requires a plug-in radio device to offer full functionality

direct sequence spread spectrum: form of modulation where a combination of data to be transmitted and a known code sequence (chip sequence) is used to directly modulate a carrier, e.g. by phase shift keying

frequency hopping spread spectrum: spread spectrum technique in which the transmitter signal occupies a number of frequencies in time, each for some period of time, referred to as the dwell time

frequency range: range of operating frequencies over which the equipment can be adjusted

fixed station: equipment intended for use in a fixed location and fitted with one or more antennae

hand-portable station: equipment normally used on a stand-alone basis and to be carried by a person or held in the hand

HomeRF systems: Equipment in compliance with HomeRF specification (see bibliography).

host equipment: any equipment which has complete user functionality when not connected to the radio equipment part and to which the radio equipment part provides additional functionality and to which connection is necessary for the radio equipment part to offer functionality

integral antenna: antenna designed to be connected to the equipment without the use of a standard connector and considered to be part of the equipment

mobile station: equipment normally used in a vehicle or as a transportable station

operating frequency: nominal frequency at which the equipment can be operated; this is also referred to as the operating centre frequency

plug-in radio device: radio equipment module intended to be used with or within host, combined or multi-radio equipment, using their control functions and power supply

spread spectrum modulation: modulation technique in which the energy of a transmitted signal is spread throughout a relatively large portion of the frequency spectrum

stand-alone radio equipment: equipment that is intended primarily as communications equipment and that is normally used on a stand-alone basis

wide band modulation: wide band modulation is considered to include FHSS or DSSS modulation as well as other forms of modulation that meet the emission requirements as defined in ES 202 131

3.2 Abbreviations

For the purposes of the present document, the following symbols apply:

BER	Bit Error Rate
DS	Direct Sequence
DSSS	Direct Sequence Spread Spectrum
ERP	Extended Rate PHY
FER	Frame Error Rate
FH	Frequency Hopping
FHSS	Frequency Hopping Spread Spectrum
ISM	Industrial, Scientific and Medical
N.A.	Not applicable
OFDM	Orthogonal Frequency Division Multiplex
PBCC	Packet Binary Convolutional Coding
PLCP	PHY Layer Convergence Procedure
PSDU	PLCP Service Data Units
RF	Radio Frequency
Rx	Receiver
TDMA	Time-Division Multiple Access

4 Receiver performance parameters

4.1 Introduction

The purpose of the present document is to provide additional information on receiver performance parameters which are not included in a product harmonized standard. This additional information can be used for spectrum planning, methods of investigation and resolving interference issues.

4.2 Applicability overview

Table 2 indicates the parameters which are considered applicable for the various technologies that are covered by the present document.

Table 2: Applicability overview

System	Rx Sensitivity	Blocking or desensitization	Adjacent Channel Selectivity
IEEE 802.11 (FH)	Yes	Yes	No
IEEE 802.11 (DS) and IEEE 802.11b	Yes	Yes	Yes
IEEE 802.11g	Yes	Yes	Yes
HomeRF	Yes	Yes	No
Bluetooth	Yes	Yes	No

4.3 Receiver parameter definitions

4.3.1 Rx Sensitivity

The receiver sensitivity is the minimum power level at the receiver RF input produced by a carrier at the nominal frequency of the receiver, modulated with the normal modulation (clause 5.1.2) which will, without interference, produce after demodulation a data signal with either a specified Bit Error Rate (BER) or a Frame Error Rate (FER).

4.3.2 Blocking or desensitization

Blocking is a measure of the capability of the receiver to receive a wanted modulated signal without exceeding a given degradation due to the presence of an unwanted signal outside the 2 395 MHz to 2 488,5 MHz band at frequencies other than those of the spurious responses.

4.3.3 Adjacent Channel Selectivity

The adjacent channel selectivity is a measure of the capability of the receiver to receive a wanted modulated signal without exceeding a given degradation due to the presence of an unwanted signal that differs in frequency from the wanted signal by an amount equal to the adjacent channel separation for which the equipment is intended.

For IEEE 802.11 [3] systems using direct sequence spread spectrum, the adjacent channel is defined as the non-overlapping channel which is at least 30 MHz separated from the wanted signal.

For IEEE 802.11b [4] and IEEE 802.11g [5] systems, the adjacent channel is defined as the non-overlapping channel which is at least 25 MHz separated from the wanted signal.

4.4 Reference values

4.4.1 IEEE 802.11 - FH systems

The minimum receiver sensitivity shall not be less than the reference values as stated in table 3.

The blocking level, for any frequency within the specified ranges, shall not be less than the values given in table 3, except at frequencies on which spurious responses are found.

Table 3: Reference values for IEEE 802.11 - FH systems

Parameter	Data rate	Value for a FER \leq 3 % at a PSDU length of 400 bytes
Rx Sensitivity	1 Mbit/s	-80 dBm
	2 Mbit/s	-75 dBm
Blocking or desensitization	1 Mbit/s	40 dB
	2 Mbit/s	30 dB
Adjacent Channel Selectivity		N.A.

4.4.2 IEEE 802.11 - DS and IEEE 802.11b systems

The minimum receiver sensitivity shall not be less than the reference values as stated in table 4.

The blocking level, for any frequency within the specified ranges, shall not be less than the values given in table 4, except at frequencies on which spurious responses are found.

The adjacent channel selectivity shall not be less than the values as stated in table 4.

Table 4: Reference values for IEEE 802.11 - DS and IEEE 802.11b systems

Parameter	Data rate	Value for a FER \leq 8 % at a PSDU length of 1 024 bytes
Rx Sensitivity	2 Mbit/s	-80 dBm
	11 Mbit/s	-76 dBm
Blocking or desensitization	2 Mbit/s	50 dB
	11 Mbit/s	50 dB
Adjacent Channel Selectivity	2 Mbit/s	35 dB
	11 Mbit/s	35 dB

4.4.3 IEEE 802.11g systems - ERP OFDM operation

The minimum receiver sensitivity shall not be less than the reference values as stated in table 5.

The blocking level, for any frequency within the specified ranges, shall not be less than the values given in table 5, except at frequencies on which spurious responses are found.

The adjacent channel selectivity shall not be less than the values as stated in table 5.

Table 5: Reference values for IEEE 802.11g systems - ERP OFDM operation

Parameter	Data rate	Value for a FER \leq 10 % at a PSDU length of 1 000 bytes
Rx Sensitivity	6 Mbit/s	-82 dBm
	9 Mbit/s	-81 dBm
	12 Mbit/s	-79 dBm
	18 Mbit/s	-77 dBm
	24 Mbit/s	-74 dBm
	36 Mbit/s	-70 dBm
	48 Mbit/s	-66 dBm
	54 Mbit/s	-65 dBm
Blocking or desensitization	6 Mbit/s	47 dB
	54 Mbit/s	30 dB
Adjacent Channel Selectivity	6 Mbit/s	16 dB
	9 Mbit/s	15 dB
	12 Mbit/s	13 dB
	18 Mbit/s	11 dB
	24 Mbit/s	8 dB
	36 Mbit/s	4 dB
	48 Mbit/s	0 dB
	54 Mbit/s	-1 dB

4.4.4 IEEE 802.11g systems - ERP PBCC operation

The minimum receiver sensitivity shall not be less than the reference values as stated in table 6.

The blocking level, for any frequency within the specified ranges, shall not be less than the values given in table 6, except at frequencies on which spurious responses are found.

The adjacent channel selectivity shall not be less than the values as stated in table 6.

Table 6: Reference values for IEEE 802.11g systems - ERP PBCC operation

Parameter	Data rate	Value for a FER \leq 8 % at a PSDU length of 1 024 bytes
Rx Sensitivity	22 Mbit/s	-76 dBm
	33 Mbit/s	-74 dBm
Blocking or desensitization	22 Mbit/s	30 dB
	33 Mbit/s	30 dB
Adjacent Channel Selectivity	22 Mbit/s	35 dB
	33 Mbit/s	35 dB

4.4.5 HomeRF systems

The minimum receiver sensitivity shall not be less than the reference values as stated in table 7.

The blocking level, for any frequency within the specified ranges, shall not be less than the values given in table 7, except at frequencies on which spurious responses are found.

Table 7: Reference values for HomeRF

Parameter	Modulation	Value for a FER \leq 3 % for a standard TDMA PSDU
Rx Sensitivity	2-FSK	-75 dBm
	4-FSK	-65 dBm
Blocking or desensitization	2-FSK	35 dB
	4-FSK	25 dB
Adjacent Channel Selectivity		N.A.

4.4.6 Bluetooth™ systems

The minimum receiver sensitivity shall not be less than the reference values as stated in table 8.

The blocking level, for any frequency within the specified ranges, shall not be less than the values given in table 8, except at frequencies on which spurious responses are found.

Table 8: Reference values for Bluetooth™ systems

Parameter	Value for a BER \leq 0,1 %
Rx Sensitivity	-70 dBm
Blocking or desensitization	40 dB (see note)
Adjacent Channel Selectivity	N.A.
NOTE: The interference signal is within the range 2 000 MHz to 2 400 MHz and 2 483,5 MHz to 3 000 MHz except where spurious responses are found.	

5 Recommended methods of measurement

5.1 Test conditions

All tests described in the present document need only be performed under normal test conditions.

5.1.1 Normal test conditions

5.1.1.1 Normal temperature and humidity

The normal temperature and humidity conditions for tests shall be any convenient combination of temperature and humidity within the following ranges:

- temperature: +15°C to +35°C;
- relative humidity: 20 % to 75 %.

5.1.1.2 Normal power source

5.1.1.2.1 Mains voltage

The normal test voltage for equipment to be connected to the mains shall be the nominal mains voltage. For the purpose of the present document, the nominal voltage shall be the voltage(s) for which the equipment was designed.

The frequency of the test power source corresponding to the AC mains shall be between 49 Hz and 51 Hz.

5.1.1.2.2 Lead-acid battery power sources used on vehicles

When radio equipment is intended for operation from the usual, alternator fed lead-acid battery power source used on vehicles, then the normal test voltage shall be 1,1 times the nominal voltage of the battery (6 V, 12 V, etc.).

5.1.1.2.3 Other power sources

For operation from other power sources or types of battery (primary or secondary), the nominal test voltage shall be as stated by the equipment manufacturer.

5.1.2 Normal modulation

The manufacturer shall describe the modulation to be used by the signal generator(s) during the measurements described in the present document. This modulation should be representative of normal use of the equipment. The same modulation shall be used for all measurements on the same equipment.

5.2 Test arrangements

Radiated RF power measurements are imprecise and therefore conducted measurements are recommended.

Equipment used for testing may be provided with a suitable connector for conducted RF measurements. Where this is not possible, a suitable test fixture shall be used. Alternatively, radiated measurements shall be performed.

Plug-in radio devices may be tested together with a suitable test jig and/or typical host equipment.

5.3 Minimum Rx Sensitivity

5.3.1 Method of measurement

The measurement procedure shall be as follows:

- a) an input signal with a frequency equal to the nominal frequency (± 20 ppm) of the receiver, using normal modulation (clause 5.1.2), shall be applied to the receiver input;
- b) depending on the type of system, the bit pattern of the modulating signal or the frame packets shall be compared to those obtained from the receiver after demodulation to calculate the Bit Error Rate (BER), or the Frame Error Rate (FER) in case the frame packets contain means for detecting frame errors;
- c) the level of the input signal to the receiver is adjusted until the stated maximum Bit Error Ratio (BER) or Frame Error Rate (FER) is met;
- d) the maximum usable sensitivity is the mean level of the input signal to the receiver.

The minimum receiver sensitivity may vary with the datarate. Therefore the above procedure may need to be repeated for the different datarates of the equipment.

5.4 Blocking or desensitization

This measurement method can be used for all types of equipment specified in table 2.

Two signal generators A and B shall be connected to the receiver via a combining network, either:

- a) via a test fixture to the integrated or dedicated receiver antenna; or
- b) directly to the permanent or temporary receiver antenna connector.

Signal generator A shall be at the nominal frequency (middle frequency) of the receiver, with normal modulation (clause 5.1.2) of the wanted signal.

Signal generator B, except for HomeRF systems, shall be unmodulated and be adjusted to test frequencies above and below the band edges as specified below. In the case of HomeRF systems, signal generator B shall be adjusted and modulated in accordance with the HomeRF system specifications.

Initially signal generator B shall be switched off and using signal generator A the level which still gives sufficient response shall be established. The output level of generator A shall then be increased by 3 dB.

Signal generator B is then switched on and adjusted until the wanted criteria are met.

The frequency for signal generator B shall be at the following frequencies:

- The measurements shall be at approximately +5 MHz, +10 MHz, +20 MHz and +50 MHz from the upper band edge.
The tests shall be repeated at approximately -5 MHz, -10 MHz, -20 MHz and -50 MHz from the lower band edge.
- Frequencies at which spurious responses are found should be ignored.

The blocking or desensitization is the ratio in dB between the level of the unwanted signal (generator B) and the level of the wanted signal (generator A).

5.5 Adjacent Channel Selectivity

5.5.1 General

This parameter is applicable for equipment where specific carrier frequencies or a channelization is specified.

FH systems have inherent immunity to adjacent channel signals and therefore Adjacent Channel Selectivity is not applicable to HomeRF (see bibliography), Bluetooth™ [6] and IEEE 802.11 [3] FH systems.

5.5.2 Method of measurement

This measurement shall be conducted under normal conditions.

Two signal generators A and B shall be connected to the receiver via a combining network, either:

- a) via a test fixture to the integrated or dedicated receiver antenna; or
- b) directly to the permanent or temporary receiver antenna connector.

Signal generator A shall be at the nominal frequency of the receiver, with normal modulation (clause 5.1.2) of the wanted signal. Signal generator B shall be modulated using normal modulation (clause 5.1.2) and shall be adjusted to the adjacent channel frequency above that of the wanted signal.

Initially signal generator B shall be switched off and using signal generator A the level that still gives sufficient response shall be established. The output level of generator A, except for IEEE 802.11g systems operating in the ERP OFDM mode (clause 4.4.3), shall then be increased by 6 dB. In case of IEEE 802.11g systems operating in the ERP OFDM mode, the output level of generator A shall be increased by 3 dB.

Signal generator B is then switched on and adjusted until the wanted criteria are met.

The measurements shall be repeated for the adjacent channel below the wanted signal.

For IEEE 802.11 [3] systems using direct sequence spread spectrum, the adjacent channel is defined as the non-overlapping channel which is at least 30 MHz separated from the wanted signal.

For IEEE 802.11b [4] and IEEE 802.11g [5] systems, the adjacent channel is defined as the non-overlapping channel which is at least 25 MHz separated from the wanted signal.

The adjacent channel selectivity is the ratio in dB between the level of the unwanted signal (generator B) and the level of the wanted signal (generator A).

6 Interpretation of measurement results

The interpretation of the results for the measurements described in the present document shall be as follows:

- the measured value will be compared to the corresponding reference value;
- the measurement uncertainty value for the measurement of each parameter shall be noted;
- the recorded value of the measurement uncertainty shall be, for each measurement, equal to or lower than the figures in table 8.

For the test methods, according to the present document, the measurement uncertainty figures shall be calculated in accordance with TR 100 028 [2] and shall correspond to an expansion factor (coverage factor) $k = 1,96$ or $k = 2$ (which provide confidence levels of respectively 95 % and 95,45 % in the case where the distributions characterizing the actual measurement uncertainties are normal (Gaussian)).

Table 9 is based on such expansion factors.

Table 9: Maximum measurement uncertainty

Parameter	Uncertainty
radio frequency	$\pm 1 \times 10^{-5}$
RX sensitivity	± 3 dB
2-signal measurements	± 4 dB
temperature	$\pm 1^\circ\text{C}$
humidity	± 5 %
DC and low frequency voltages	± 3 %

Annex A (informative): Bibliography

ERC Report 109: "Compatibility of Bluetooth™ with other existing and proposed radiocommunication systems in the 2,45 GHz frequency band".

ECC/REC 02-01: "Specification of Reference Receiver Performance Parameters".

"HomeRF specification", HomeRF, Revision 2.0 Draft 20010507 <http://www.homerf.org/>.

History

Document history			
V1.1.1	November 2002	Membership Approval Procedure	MV 20030117: 2002-11-19 to 2003-01-17