



**E
UROPEAN
T
ELECOMMUNICATION
S
TANDARD**

FINAL DRAFT
pr ETS 300 476-3
May 1996

Source: ETSI TC-RES

Reference: DE/RES-03042-3

ICS: 33.020, 33.060.50

Key words: DECT, CI, PICS

**Radio Equipment and Systems (RES);
Digital Enhanced Cordless Telecommunications (DECT);
Common Interface (CI);
Protocol Implementation Conformance Statement (PICS)
proforma;
Part 3: Medium Access Control (MAC) layer -
Portable radio Termination (PT)**

ETSI

European Telecommunications Standards Institute

ETSI Secretariat

Postal address: F-06921 Sophia Antipolis CEDEX - FRANCE
Office address: 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE
X.400: c=fr, a=atlas, p=etsi, s=secretariat - **Internet:** secretariat@etsi.fr

*

Tel.: +33 92 94 42 00 - Fax: +33 93 65 47 16

Copyright Notification: No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1996. All rights reserved.

Contents

Foreword	13
1 Scope	15
2 Normative references.....	15
3 Definitions and abbreviations	16
3.1 Definitions	16
3.2 Abbreviations	16
4 Conformance requirement to this PICS proforma specification	16
Annex A (normative): PICS proforma for DECT MAC PT	17
A.1 Introduction for completing the PICS proforma.....	17
A.1.1 Purposes and structure.....	17
A.1.2 Symbols, abbreviations and conventions.....	17
A.1.3 Guidances for completing the PICS.....	18
A.2 Identification of the implementation.....	19
A.2.1 Date of statement	19
A.2.2 Implementation Under Test (IUT) identification	19
A.2.3 System Under Test (SUT) identification	19
A.2.4 Product supplier	19
A.2.5 Client identification	20
A.2.6 Contact person.....	20
A.3 Identification of the protocol	20
A.4 Global statement of conformance	20
A.5 Capabilities	21
A.5.1 Services	21
A.5.1.1 Connection oriented control services	21
A.5.1.2 Broadcast control services	22
A.5.1.3 Connectionless control services	22
A.5.1.3.1 Downlink connectionless services	22
A.5.1.3.2 Uplink connectionless services.....	23
A.5.1.4 Multiplexing services	23
A.5.1.5 Management services	24
A.5.2 Procedures.....	24
A.5.2.1 Connection procedures	25
A.5.2.1.1 Connection setup procedures.....	25
A.5.2.1.2 Connection modification procedures	26
A.5.2.1.3 Connection data transfer procedures	26
A.5.2.1.4 Handover procedures	26
A.5.2.1.5 Connection release procedures.....	27
A.5.2.2 Broadcast procedures	27
A.5.2.3 Connectionless procedures	27
A.5.2.3.1 Downlink connectionless procedures	27
A.5.2.3.2 Uplink connectionless procedures.....	27
A.5.2.4 CSF multiplexing procedures	28
A.5.2.5 Layer management procedures	28
A.5.3 Other capabilities	28
A.6 Protocol parameters.....	29

A.6.1	Timer support	29
A.6.2	Protocol constants.....	29
A.6.3	Channel selection parameters	29
A.6.4	Channels supported	30
A.6.5	Bearer types supported	30
A.6.6	Slot types supported.....	30
A.7	Messages	30
A.7.1	A - field header	31
A.7.1.1	A - field header - Tail Identification	31
A.7.1.2	A - field header - "Q1/BCK" bit.....	31
A.7.1.3	A - field header - B-field identification	32
A.7.1.4	A - field header - "Q2" bit	32
A.7.2	A - field identities information (N_T) message	32
A.7.3	A - field system information (Q_T) messages.....	33
A.7.4	A - field paging tail (P_T) messages	33
A.7.4.1	Paging tail messages supported.....	33
A.7.4.2	P_T messages information type	33
A.7.5	A - field MAC control (M_T) messages	34
A.7.5.1	Mac control messages supported.....	34
A.7.5.2	Basic connection control messages	35
A.7.5.3	MAC layer test messages.....	35
A.7.5.4	Advanced connection control messages	36
A.7.5.5	Quality control messages	37
A.7.5.6	Broadcast and connectionless (BCL) messages.....	37
A.7.5.7	Encryption control (EC) messages	38
A.7.6	B - Field Messages.....	39
A.7.6.1	B - Field Messages supported	39
A.7.6.2	B - Field Advanced connection control messages.....	39
A.7.6.3	B - Field - Null messages.....	40
A.7.6.4	B - Field - Quality control messages	41
A.7.6.5	B - Field - GF-channel data packet messages	42
A.8	MAC messages format and field value.....	43
A.8.1	A - field identities information (N_T) message	43
A.8.2	A - field system information (Q_T) messages.....	44
A.8.2.1	QT - Static system information	44
A.8.2.2	QT - Extended RF carrier information	44
A.8.2.3	QT - Fixed part capability.....	45
A.8.2.4	QT - Extended fixed part capabilities.....	45
A.8.2.5	QT - Secondary access rights identities	45
A.8.2.6	QT - Multi-frame number	46
A.8.2.7	QT - escape	46
A.8.3	A - field paging tail (P_T) messages	46
A.8.3.1	P_T message - Full page	46
A.8.3.2	P_T message - Long page	46
A.8.3.3	P_T message - Short page.....	47
A.8.3.4	P_T message - Zero length page	47
A.8.3.5	P_T messages - MAC info. element.....	47
A.8.3.5.1	MAC info. element - Fill bits	47
A.8.3.5.2	MAC info. element - Blind full slot	47
A.8.3.5.3	MAC info. element - Other bearer.....	48
A.8.3.5.4	MAC info. element - Recommended other bearer	48
A.8.3.5.5	MAC info. element - Good RFP bearer.....	48
A.8.3.5.6	MAC info. element - Dummy or C/L bearer position	48
A.8.3.5.7	MAC info. element - RFP identity.....	48
A.8.3.5.8	MAC info. element - Escape	49
A.8.3.5.9	MAC info. element - Dummy or C/L bearer marker	49
A.8.3.5.10	MAC info. element - Bearer handover information.....	49
A.8.3.5.11	MAC info. element - RFP status	49
A.8.4	A - field MAC control (M_T) messages	50
A.8.4.1	Basic connection control messages	50
A.8.4.1.1	Basic CC - access request.....	50

A.8.4.1.2	Basic CC - bearer handover request	50
A.8.4.1.3	Basic CC - connection handover request	50
A.8.4.1.4	Basic CC - unconfirmed access request	50
A.8.4.1.5	Basic CC - bearer confirm	51
A.8.4.1.6	Basic CC - wait	51
A.8.4.1.7	Basic CC - release.....	51
A.8.4.2	MAC layer test messages	52
A.8.4.2.1	MAC test - force transmit.....	52
A.8.4.2.2	MAC test - loopback data	53
A.8.4.2.3	MAC test - defeat antenna diversity.....	53
A.8.4.2.4	MAC test - force bearer handover	53
A.8.4.2.5	MAC test - escape	54
A.8.4.2.6	MAC test - network test	54
A.8.4.2.7	MAC test - clear test modes	55
A.8.4.3	Advanced connection control messages.....	55
A.8.4.3.1	Advanced CC - access request	55
A.8.4.3.2	Advanced CC - bearer handover request.....	56
A.8.4.3.3	Advanced CC - connection handover request.....	56
A.8.4.3.4	Advanced CC - unconfirmed access request	56
A.8.4.3.5	Advanced CC - bearer confirm	57
A.8.4.3.6	Advanced CC - wait	57
A.8.4.3.7	Advanced CC - Attributes_T request.....	58
A.8.4.3.8	Advanced CC - Attributes_T confirm	59
A.8.4.3.9	Advanced CC - Bandwidth_T request	59
A.8.4.3.10	Advanced CC - Bandwidth_T confirm	60
A.8.4.3.11	Advanced CC - Channel List	61
A.8.4.3.12	Advanced CC - Unconfirmed_dummy	61
A.8.4.3.13	Advanced CC - Unconfirmed_handover	62
A.8.4.3.14	Advanced CC - release.....	62
A.8.4.4	Quality control messages	63
A.8.4.4.1	QC - antenna switch single bearer request	63
A.8.4.4.2	QC - antenna switch all bearers request	63
A.8.4.4.3	QC - bearer handover request.....	64
A.8.4.4.4	QC - connection handover request.....	64
A.8.4.4.5	QC - frequency control single bearer request.....	65
A.8.4.4.6	QC - frequency control all bearers request.....	65
A.8.4.5	Broadcast and connectionless (BCL) messages	66
A.8.4.5.1	BCL - CLF, first of 2 transmissions, half slot	66
A.8.4.5.2	BCL - CLF, first of 2 transmissions, full slot	66
A.8.4.5.3	BCL - CLF, first of 2 transmissions, double slot	66
A.8.4.5.4	BCL - CLF, last transmissions, half slot.....	67
A.8.4.5.5	BCL - CLF, last transmissions, full slot.....	67
A.8.4.5.6	BCL - CLF, last transmissions, double slot.....	67
A.8.4.5.7	BCL - C/L single transmissions, no CF or CLS	67
A.8.4.5.8	BCL - CLS service, first transmissions	68
A.8.4.5.9	BCL - change dummy bearer position	68
A.8.4.5.10	BCL - extended system info., A-field procedure	68
A.8.4.5.11	BCL - extended system info., B-field procedure	69
A.8.4.6	Encryption control (EC) messages.....	69
A.8.4.6.1	EC - Encryption start.....	69
A.8.4.6.2	EC - Encryption stop.....	70
A.8.4.7	M _T message - B - field setup	72
A.8.4.8	M _T message - Escape	72
A.8.4.9	M _T message - TARI	72
A.8.5	B - Field Messages	73
A.8.5.1	B - Field - Advanced CC messages	73
A.8.5.1.1	B-field Advanced CC - Access request	73
A.8.5.1.2	B-field Advanced CC - Bearer handover request	74
A.8.5.1.3	B-field Advanced CC - Connection handover request.....	75
A.8.5.1.4	B-field Advanced CC - Unconfirmed access request	76
A.8.5.1.5	B-field Advanced CC - Bearer confirm	77
A.8.5.1.6	B-field Advanced CC - Wait.....	77
A.8.5.1.7	B-field Advanced CC - Attributes_B request	78

A.8.5.1.8	B-field Advanced CC - Attributes_B confirm	79
A.8.5.1.9	B-field Advanced CC - Bandwidth_B request	80
A.8.5.1.10	B-field Advanced CC - Bandwidth_B confirm	81
A.8.5.1.11	B-field Advanced CC - Channel List.....	82
A.8.5.1.12	B-field Advanced CC - Unconfirmed_Dummy	83
A.8.5.1.13	B-field Advanced CC - Unconfirmed_Handover	84
A.8.5.1.14	B-field Advanced CC - Release	85
A.8.5.2	B-field - Null Messages (NM)	85
A.8.5.2.1	B-field - NM No C _F or CL _F data in the B-field.....	85
A.8.5.2.2	B-field - NM One B-subfield contains C _F or CL _F data	86
A.8.5.2.3	B-field - NM Two B-subfield contain C _F or CL _F data.....	87
A.8.5.2.4	B-field - NM Three B-subfield contain C _F or CL _F data	87
A.8.5.2.5	B-field - NM Four B-subfield contain C _F or CL _F data	88
A.8.5.2.6	B-field - NM Five B-subfield contain C _F or CL _F data	89
A.8.5.2.7	B-field - NM Six B-subfield contain C _F or CL _F data	89
A.8.5.2.8	B-field - NM Seven B-subfield contain C _F or CL _F data	90
A.8.5.2.9	B-field - NM Eight B-subfield contain C _F or CL _F data	91
A.8.5.2.10	B-field - NM Nine B-subfield contain C _F or CL _F data	91
A.8.5.3	B - Field - Quality control (QC) messages	92
A.8.5.3.1	B - Field - QC Antenna switch single bearer	92
A.8.5.3.2	B - Field - QC Antenna switch all bearers	93
A.8.5.3.3	B - Field - QC Bearer handover	93
A.8.5.3.4	B - Field - QC Connection handover.....	94
A.8.5.3.5	B - Field - QC Frequency control single bearer.....	95
A.8.5.3.6	B - Field - QC Frequency control all bearers.....	95
A.8.5.3.7	B - Field - QC Reset request first TDMA half frame	96
A.8.5.3.8	B - Field - QC Reset request second TDMA half frame.....	97
A.8.5.3.9	B - Field - QC Reset request both TDMA half frames	97
A.8.5.3.10	B - Field - QC Reset confirm first TDMA half frame	98
A.8.5.3.11	B - Field - QC Reset confirm second TDMA half frame.....	99
A.8.5.3.12	B - Field - QC Reset confirm both TDMA half frames	99
A.8.5.3.13	B - Field - QC MOD2 ACK	100
A.8.5.4	B - Field - Extended system information (ES) messages	101
A.8.5.4.1	B - Field - ES TARI message.....	101
A.8.5.5	B - Field - GF-channel data packet messages	101
A.8.5.5.1	B - Field - GF-No C _F data in the B-field.....	101
A.8.5.5.2	B - Field - GF-One B-subfield contains C _F data	102
A.8.5.5.3	B - Field - GF-Two B-subfield contain C _F data	102
A.8.5.5.4	B - Field - GF-Three B-subfield contain C _F data	103
A.8.5.5.5	B - Field - GF-Four B-subfield contain C _F data	103
A.8.5.5.6	B - Field - GF-Five B-subfield contain C _F data	104
A.8.5.5.7	B - Field - GF-Six B-subfield contain C _F data	104
A.8.5.5.8	B - Field - GF-Seven B-subfield contain C _F data	105
A.8.5.5.9	B - Field - GF-Eight B-subfield contain C _F data.....	105
A.8.5.5.10	B - Field - GF-Nine B-subfield contain C _F data	106
A.8.5.6	B - Field - Escape message	106
History		107

Questions

Table A.1: Date of Statement.....	19
Table A.2: IUT identification	19
Table A.3: SUT identification.....	19
Table A.4: Product supplier	19
Table A.5: Client identification.....	20
Table A.6: Contact person identification.....	20
Table A.7: Identification of protocol	20
Table A.8: Global statement of conformance.....	20
Table A.9: Service groups supported	21
Table A.10: Connection oriented control services.....	21
Table A.11: Connection services.....	21
Table A.12: Symmetric connection oriented services	21
Table A.13: Asymmetric connection oriented services	22
Table A.14: C-plane connection services.....	22
Table A.15: Broadcast services	22
Table A.16: Connectionless control services	22
Table A.17: Downlink connectionless services	22
Table A.18: Uplink connectionless services	23
Table A.19: CSF multiplexing services	23
Table A.20: D-MAP services	23
Table A.21: B-MAP services	23
Table A.22: E/U mux services	24
Table A.23: C mux mapping services	24
Table A.24: Management services.....	24
Table A.25: Handover services management	24
Table A.26: C/O single bearer setup procedures	25
Table A.27: C/O multi-bearer symmetric setup procedures	25
Table A.28: C/O multi-bearer asymmetric setup procedures	25
Table A.29: C/O bearer setup procedures	26
Table A.30: C/O connection modification procedures.....	26
Table A.31: C/O data transfer procedures	26
Table A.32: Handover procedures	26
Table A.33: C/O connection release procedures	27
Table A.34: Broadcast procedures.....	27
Table A.35: Downlink connectionless procedures	27
Table A.36: Uplink connectionless procedures	27
Table A.37: CSF multiplexing procedures.....	28
Table A.38: Layer management procedures	28
Table A.39: Extended RF carriers supported	28
Table A.40: Operation modes in Idle_locked state supported	28
Table A.41: Timer supported.....	29
Table A.42: Protocol constants support	29
Table A.43: Channel selection parameters	30
Table A.44: Channels supported.....	30
Table A.45: Bearer types supported.....	30
Table A.46: Slot types supported	30
Table A.47: Tail Identification (Sending P to F).....	31
Table A.48: Tail Identification (Receipt F to P).....	31
Table A.49: Q1/BCK bit (Sending P to F).....	31
Table A.50: Q1/BCK bit (Receipt F to P).....	31
Table A.51: B-field identification (Sending P to F).....	32
Table A.52: B-field identification (Receipt F to P).....	32
Table A.53: Q2 bit (Sending P to F)	32
Table A.54: Q2 bit (Receipt F to P)	32
Table A.55: Identities information (N_T) message (Sending P to F)	33
Table A.56: Identities information (N_T) message (Receipt F to P)	33
Table A.57: System information (Q_T) message (Receipt F to P).....	33
Table A.58: Paging tail (P_T) messages (Receipt F to P)	33

Table A.59: P _T messages information supported (Receipt F to P)	34
Table A.60: MAC control (M _T) messages (Sending P to F)	34
Table A.61: MAC control (M _T) messages (Receipt F to P)	34
Table A.62: Basic connection control (Sending P to F)	35
Table A.63: Basic connection control (Receipt F to P)	35
Table A.64: MAC layer test messages (Sending P to F)	35
Table A.65: MAC layer test messages (Receipt F to P)	36
Table A.66: Advanced connection control messages (Sending P to F)	36
Table A.67: Advanced connection control messages (Receipt F to P)	37
Table A.68: Quality control (QC) messages (Sending P to F)	37
Table A.69: Quality control (QC) messages (Receipt F to P)	37
Table A.70: Broadcast and connectionless (BCL) messages (Sending P to F)	38
Table A.71: Broadcast and connectionless (BCL) messages (Receipt F to P)	38
Table A.72: Encryption control (EC) messages (Sending P to F)	38
Table A.73: Encryption control (EC) messages (Receipt F to P)	39
Table A.74: B - Field messages supported (Sending P to F)	39
Table A.75: B - Field messages supported (Receipt F to P)	39
Table A.76: B - Field Advanced connection control messages (Sending P to F)	40
Table A.77: B - Field Advanced connection control messages (Receipt F to P)	40
Table A.78: B - Field - Null messages (Sending P to F)	41
Table A.79: B - Field - Null messages (Receipt F to P)	41
Table A.80: B - Field - Quality control messages (Sending P to F)	42
Table A.81: B - Field - Quality control messages (Receipt F to P)	42
Table A.82: B - Field - GF-channel data packet messages (Sending P to F)	43
Table A.83: B - Field - GF-channel data packet messages (Receipt F to P)	43
Table A.84: NT - Identities Information (Sending P to F)	43
Table A.85: NT - Identities Information (Receipt F to P)	44
Table A.86: QT - Static system information (Receipt F to P)	44
Table A.87: QT - Extended RF carrier information (Receipt F to P)	44
Table A.88: QT - Fixed part capability (Receipt F to P)	45
Table A.89: QT - Extended fixed part capabilities (Receipt F to P)	45
Table A.90: QT - Secondary access rights identities (Receipt F to P)	45
Table A.91: QT - Multi-frame number (Receipt F to P)	46
Table A.92: QT - escape (Receipt F to P)	46
Table A.93: P _T message - Full page (Receipt F to P)	46
Table A.94: P _T message - Long page (Receipt F to P)	46
Table A.95: P _T message - Short page (Receipt F to P)	47
Table A.96.: P _T message - Zero length page (Receipt F to P)	47
Table A.97: MAC info. element - Fill bits (Receipt F to P)	47
Table A.98: MAC info. element - Blind full slot (Receipt F to P)	47
Table A.99.: MAC info. element - Other bearer (Receipt F to P)	48
Table A.100: MAC info. element - Recommended other bearer (Receipt F to P)	48
Table A.101: MAC info. element - Good RFP bearer (Receipt F to P)	48
Table A.102: MAC info. element - Dummy or C/L bearer position (Receipt F to P)	48
Table A.103.: MAC info. element - RFP identity (Receipt F to P)	48
Table A.104: MAC info. element - Escape (Receipt F to P)	49
Table A.105: MAC info. element - Dummy or C/L bearer marker (Receipt F to P)	49
Table A.106: MAC info. element - Bearer handover information (Receipt F to P)	49
Table A.107: MAC info. element - RFP status (Receipt F to P)	49
Table A.108: Basic CC - access request (Sending P to F)	50
Table A.109: Basic CC - bearer handover request (Sending P to F)	50
Table A.110: Basic CC - connection handover request (Sending P to F)	50
Table A.111: Basic CC - unconfirmed access request (Sending P to F)	50
Table A.112: Basic CC - bearer confirm (Receipt F to P)	51
Table A.113: Basic CC - wait (Sending P to F)	51
Table A.114: Basic CC - wait (Receipt F to P)	51
Table A.115: Basic CC - release (Sending P to F)	51
Table A.116: Basic CC - release (Receipt F to P)	52
Table A.117: MAC test - force transmit (Sending P to F)	52
Table A.118: MAC test - force transmit (Receipt F to P)	52
Table A.119: MAC test - loopback data (Sending P to F)	53
Table A.120: MAC test - loopback data (Receipt F to P)	53
Table A.121: MAC test - defeat antenna diversity (Sending P to F)	53

Table A.122.: MAC test - force bearer handover (Sending P to F)	53
Table A.123.: MAC test - force bearer handover (Receipt F to P)	54
Table A.124: MAC test - escape (Sending P to F)	54
Table A.125: MAC test - escape (Receipt F to P)	54
Table A.126: MAC test - network test (Sending P to F)	54
Table A.127: MAC test - network test (Receipt F to P)	54
Table A.128: MAC test - clear test modes (Sending P to F)	55
Table A.129: MAC test - clear test modes (Receipt F to P)	55
Table A.130: Advanced CC - access request (Sending P to F)	55
Table A.131: Advanced CC - access request (Receipt F to P)	55
Table A.132: Advanced CC - bearer handover request (Sending P to F)	56
Table A.133: Advanced CC - connection handover request (Sending P to F)	56
Table A.134: Advanced CC - connection handover request (Receipt F to P)	56
Table A.135: Advanced CC - unconfirmed access request (Sending P to F)	56
Table A.136: Advanced CC - unconfirmed access request (Receipt F to P)	57
Table A.137: Advanced CC - bearer confirm (Sending P to F)	57
Table A.138: Advanced CC - bearer confirm (Receipt F to P)	57
Table A.139: Advanced CC - wait (Sending P to F)	57
Table A.140: Advanced CC - wait (Receipt F to P)	58
Table A.141: Advanced CC - Attributes_T request (Sending P to F)	58
Table A.142: Advanced CC - Attributes_T request (Receipt F to P)	58
Table A.143: Advanced CC - Attributes_T confirm (Sending P to F)	59
Table A.144: Advanced CC - Attributes_T confirm (Receipt F to P)	59
Table A.145: Advanced CC - Bandwidth_T request (Sending P to F)	59
Table A.146: Advanced CC - Bandwidth_T request (Receipt F to P)	60
Table A.147: Advanced CC - Bandwidth_T confirm (Sending P to F)	60
Table A.148: Advanced CC - Bandwidth_T confirm (Receipt F to P)	60
Table A.149: Advanced CC - Channel List (Sending P to F)	61
Table A.150: Advanced CC - Channel List (Receipt F to P)	61
Table A.151: Advanced CC - Unconfirmed_dummy (Sending P to F)	61
Table A.152: Advanced CC - Unconfirmed_dummy (Receipt F to P)	61
Table A.153: Advanced CC - Unconfirmed_handover (Sending P to F)	62
Table A.154: Advanced CC - Unconfirmed_handover (Receipt F to P)	62
Table A.155: Advanced CC - release (Sending P to F)	62
Table A.156: Advanced CC - release (Receipt F to P)	62
Table A.157: QC - antenna switch single bearer request (Sending P to F)	63
Table A.158: QC - antenna switch single bearer request (Receipt F to P)	63
Table A.159: QC - antenna switch all bearers request (Sending P to F)	63
Table A.160: QC - antenna switch all bearers request (Receipt F to P)	64
Table A.161: QC - bearer handover request (Sending P to F)	64
Table A.162: QC - bearer handover request (Receipt F to P)	64
Table A.163: QC - connection handover request (Sending P to F)	64
Table A.164: QC - connection handover request (Receipt F to P)	65
Table A.165: QC - frequency control single bearer request (Sending P to F)	65
Table A.166: QC - frequency control single bearer request (Receipt F to P)	65
Table A.167: QC - frequency control all bearers request (Sending P to F)	65
Table A.168: QC - frequency control all bearers request (Receipt F to P)	66
Table A.169: BCL - CLF, first of 2 transmissions, half slot (Sending P to F)	66
Table A.170: BCL - CLF first of 2 transmissions, full slot (Sending P to F)	66
Table A.171: BCL - CLF first of 2 transmissions, double slot (Sending P to F)	66
Table A.172: BCL - CLF, last transmissions, half slot (Sending P to F)	67
Table A.173: BCL - CLF, last transmissions, full slot (Sending P to F)	67
Table A.174: BCL - CLF, last transmissions, double slot (Sending P to F)	67
Table A.175: BCL - C/L single transmissions, no CF or CLS (Sending P to F)	67
Table A.176: BCL - CLS service, first transmission (Sending P to F)	68
Table A.177: BCL - change dummy bearer position (Sending P to F)	68
Table A.178: BCL - extended system info., A-field procedure (Sending P to F)	68
Table A.179: BCL - extended system info., A-field procedure (Receipt F to P)	68
Table A.180: BCL - extended system info., B-field procedure (Sending P to F)	69
Table A.181: BCL - extended system info., B-field procedure (Receipt F to P)	69
Table A.182: EC - Encryption start request (Sending P to F)	69
Table A.183: EC - Encryption start request (Receipt F to P)	69
Table A.184: EC - Encryption start grant (Sending P to F)	70

Table A.185: EC - Encryption start grant (Receipt F to P).....	70
Table A.186: EC - Encryption start confirm (Sending P to F)	70
Table A.187: EC - Encryption start confirm (Receipt F to P)	70
Table A.188: EC - Encryption stop request (Sending P to F)	70
Table A.189: EC - Encryption stop request (Receipt F to P)	71
Table A.190: EC - Encryption stop grant (Sending P to F)	71
Table A.191: EC - Encryption stop grant (Receipt F to P)	71
Table A.192: EC - Encryption stop confim (Sending P to F)	71
Table A.193: EC - Encryption stop confim (Receipt F to P)	71
Table A.194: M _T message - B - field setup (Sending P to F)	72
Table A.195: M _T message - Escape (Sending P to F)	72
Table A.196: M _T message - Escape (Receipt F to P)	72
Table A.197: M _T message - TARI request (Sending P to F)	72
Table A.198: M _T message - TARI reply (Receipt F to P)	72
Table A.199: B-field Advanced CC - Access request (Sending P to F)	73
Table A.200: B-field Advanced CC - Access request (Receipt F to P)	73
Table A.201: B-field Advanced CC - Bearer handover request (Sending P to F)	74
Table A.202: B-field Advanced CC - Bearer handover request (Receipt F to P)	74
Table A.203: B-field Advanced CC - Connection handover request (Sending P to F)	75
Table A.204: B-field Advanced CC - Connection handover request (Receipt F to P)	75
Table A.205: B-field Advanced CC - Unconfirmed access request (Sending P to F)	76
Table A.206: B-field Advanced CC - Unconfirmed access request (Receipt F to P)	76
Table A.207: B-field Advanced CC - Bearer confirm (Sending P to F)	77
Table A.208: B-field Advanced CC - Bearer confirm (Receipt F to P)	77
Table A.209: B-field Advanced CC - Wait (Sending P to F)	77
Table A.210: B-field Advanced CC - Wait (Receipt F to P)	78
Table A.211: B-field Advanced CC - Attributes_B request (Sending P to F)	78
Table A.212: B-field Advanced CC - Attributes_B request (Receipt F to P)	78
Table A.213: B-field Advanced CC - Attributes_B confirm (Sending P to F)	79
Table A.214: B-field Advanced CC - Attributes_B confirm (Receipt F to P)	79
Table A.215: B-field Advanced CC - Bandwidth_B request (Sending P to F)	80
Table A.216: B-field Advanced CC - Bandwidth_B request (Receipt F to P)	80
Table A.217: B-field Advanced CC - Bandwidth_B confirm (Sending P to F)	81
Table A.218: B-field Advanced CC - Bandwidth_B confirm (Receipt F to P)	81
Table A.219: B-field Advanced CC - Channel List (Sending P to F)	82
Table A.220: B-field Advanced CC - Channel List (Receipt F to P)	82
Table A.221: B-field Advanced CC - Unconfirmed_Dummy (Sending P to F)	83
Table A.222: B-field Advanced CC - Unconfirmed_Dummy (Receipt F to P)	83
Table A.223: B-field Advanced CC - Unconfirmed_Handover (Sending P to F)	84
Table A.224: B-field Advanced CC - Unconfirmed_Handover (Receipt F to P)	84
Table A.225: B-field Advanced CC - Release (Sending P to F)	85
Table A.226: B-field Advanced CC - Release (Receipt F to P)	85
Table A.227: B-field - NM No C _F or CL _F data in the B-field (Sending P to F)	85
Table A.228: B-field - NM No C _F or CL _F data in the B-field (Receipt F to P)	86
Table A.229: B-field - NM One B-subfield contains C _F or CL _F data (Sending P to F)	86
Table A.230: B-field - NM One B-subfield contains C _F or CL _F data (Receipt F to P)	86
Table A.231: B-field - NM Two B-subfield contains C _F or CL _F data (Sending P to F)	87
Table A.232: B-field - NM Two B-subfield contains C _F or CL _F data (Receipt F to P)	87
Table A.233: B-field - NM Three B-subfield contains C _F or CL _F data (Sending P to F)	87
Table A.234: B-field - NM Three B-subfield contains C _F or CL _F data (Receipt F to P)	88
Table A.235: B-field - NM Four B-subfield contains C _F or CL _F data (Sending P to F)	88
Table A.236: B-field - NM Four B-subfield contains C _F or CL _F data (Receipt F to P)	88
Table A.237: B-field - NM Five B-subfield contains C _F or CL _F data (Sending P to F)	89
Table A.238: B-field - NM Five B-subfield contains C _F or CL _F data (Receipt F to P)	89
Table A.239: B-field - NM Six B-subfield contains C _F or CL _F data (Sending P to F)	89
Table A.240: B-field - NM Six B-subfield contains C _F or CL _F data (Receipt F to P)	90
Table A.241: B-field - NM Seven B-subfield contains C _F or CL _F data (Sending P to F)	90
Table A.242: B-field - NM Seven B-subfield contains C _F or CL _F data (Receipt F to P)	90
Table A.243: B-field - NM Eight B-subfield contains C _F or CL _F data (Sending P to F)	91
Table A.244: B-field - NM Eight B-subfield contains C _F or CL _F data (Receipt F to P)	91
Table A.245: B-field - NM Nine B-subfield contains C _F or CL _F data (Sending P to F)	91
Table A.246: B-field - NM Nine B-subfield contains C _F or CL _F data (Receipt F to P)	92
Table A.247 : B-field QC - Antenna switch single bearer (Sending P to F)	92

Table A.248 : B-field QC - Antenna switch single bearer (Receipt F to P).....	92
Table A.249: B-field QC - Antenna switch all bearers (Sending P to F).....	93
Table A.250: B-field QC - Antenna switch all bearers (Receipt F to P).....	93
Table A.251: B-field QC - Bearer handover (Sending P to F)	93
Table A.252: B-field QC - Bearer handover (Receipt F to P)	94
Table A.253: B - Field - QC Connection handover (Sending P to F).....	94
Table A.254: B - Field - QC Connection handover (Receipt F to P)	94
Table A.255: B-field QC - Frequency control single bearer (Sending P to F)	95
Table A.256: B-field QC - Frequency control single bearer (Receipt F to P)	95
Table A.257: B-field QC - Frequency control all bearers (Sending P to F)	95
Table A.258: B-field QC - Frequency control all bearers (Receipt F to P)	96
Table A.259: B - Field - QC Reset request first TDMA half frame (Sending P to F)	96
Table A.260: B - Field - QC Reset request first TDMA half frame (Receipt F to P)	96
Table A.261: B - Field - QC Reset request second TDMA half frame (Sending P to F)	97
Table A.262: B - Field - QC Reset request second TDMA half frame (Receipt F to P)	97
Table A.263: B - Field - QC Reset request both TDMA half frame (Sending P to F)	97
Table A.264: B - Field - QC Reset request both TDMA half frame (Receipt F to P)	98
Table A.265: B - Field - QC Reset confirm first TDMA half frame (Sending P to F)	98
Table A.266: B - Field - QC Reset confirm first TDMA half frame (Receipt F to P)	98
Table A.267: B - Field - QC Reset confirm second TDMA half frame (Sending P to F)	99
Table A.268: B - Field - QC Reset confirm second TDMA half frame (Receipt F to P)	99
Table A.269: B - Field - QC Reset confirm both TDMA half frame (Sending P to F)	99
Table A.270: B - Field - QC Reset confirm both TDMA half frame (Receipt F to P)	100
Table A.271: B - Field - QC MOD2 ACK (Sending P to F)	100
Table A.272: B - Field - QC MOD2 ACK (Receipt F to P)	100
Table A.273: B - Field - ES TARI message (Sending P to F)	101
Table A.274: B - Field - ES TARI message (Receipt F to P)	101
Table A.275: B - Field - GF-No C _F data in the B-field (Sending P to F)	101
Table A.276: B - Field - GF-No C _F data in the B-field (Receipt F to P)	101
Table A.277: B - Field - GF-One B-subfield contains C _F data (Sending P to F).....	102
Table A.278: B - Field - GF-One B-subfield contains C _F data (Receipt F to P).....	102
Table A.279: B - Field - GF-Two B-subfield contains C _F data (Sending P to F).....	102
Table A.280: B - Field - GF-Two B-subfield contains C _F data (Receipt F to P).....	102
Table A.281: B - Field - GF-Three B-subfield contains C _F data (Sending P to F)	103
Table A.282: B - Field - GF-Three B-subfield contains C _F data (Receipt F to P)	103
Table A.283: B - Field - GF-Four B-subfield contains C _F data (Sending P to F)	103
Table A.284: B - Field - GF-Four B-subfield contains C _F data (Receipt F to P)	103
Table A.285: B - Field - GF-Five B-subfield contains C _F data (Sending P to F).....	104
Table A.286: B - Field - GF-Five B-subfield contains C _F data (Receipt F to P)	104
Table A.287: B - Field - GF-Six B-subfield contains C _F data (Sending P to F).....	104
Table A.288: B - Field - GF-Six B-subfield contains C _F data (Receipt F to P)	104
Table A.289: B - Field - GF-Seven B-subfield contains C _F data (Sending P to F)	105
Table A.290: B - Field - GF-Seven B-subfield contains C _F data (Receipt F to P)	105
Table A.291: B - Field - GF-Eight B-subfield contains C _F data (Sending P to F)	105
Table A.292: B - Field - GF-Eight B-subfield contains C _F data (Receipt F to P)	105
Table A.293: B - Field - GF-Nine B-subfield contains C _F data (Sending P to F)	106
Table A.294: B - Field - GF-Nine B-subfield contains C _F data (Receipt F to P)	106
Table A.295: B - Field - GF-Nine B-subfield contains C _F data (Sending P to F)	106
Table A.296: B - Field - GF-Nine B-subfield contains C _F data (Receipt F to P)	106

Blank page

Foreword

This final draft European Telecommunication Standard (ETS) has been produced by the Radio Equipment and Systems (RES), Technical Committee of the European Telecommunications Standards Institute (ETSI), and is now submitted for the Voting phase of the ETSI standards approval procedure.

The DECT Common interface Protocol Implementation Conformance Statement (PICS) proforma standard comprises seven parts as follows:

- Part 1: "Network (NWK) layer - Portable radio Termination (PT)"
- Part 2: "Data Link Control (DLC) layer - Portable radio Termination (PT)"
- Part 3: "Medium Access Control (MAC) layer - Portable radio Termination (PT)"**
- Part 4: "Network (NWK) layer - Fixed radio Termination (FT)"
- Part 5: "Data Link Control (DLC) layer - Fixed radio Termination (FT)"
- Part 6: "Medium Access Control (MAC) layer - Fixed radio Termination (FT)"
- Part 7: "Physical layer"

Annex A of this specification contains the PICS proforma for the PT medium access control layer.

Blank page

1 Scope

This final draft European Telecommunication Standard (ETS) provides the Protocol Implementation Conformance Statement (PICS) proforma for the Digital Enhanced Cordless Telecommunications Medium Access Control layer at the Portable Termination as defined in ETS 300 175 Part 3 [3] in compliance with the relevant requirements and in accordance with the relevant guidance given in ISO/IEC 9646-7 [14].

2 Normative references

This ETS incorporates, by dated or undated reference, provisions from other publications. These normative references are cited at the appropriate places in the text and the publications are listed hereafter. For dated references, subsequent amendments to or revisions of any of these publications apply to this ETS only when incorporated in it by amendment or revision. For undated references the latest edition of the publication referred to applies.

- [1] ETS 300 175-1: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 1: Overview".
- [2] ETS 300 175-2: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 2: Physical Layer".
- [3] ETS 300 175-3: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 3: Medium Access Control (MAC) layer".
- [4] ETS 300 175-4: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 4: Data Link Control (DLC) layer".
- [5] ETS 300 175-5: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 5: Network (NWK) layer".
- [6] ETS 300 175-6: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 6: Identities and addressing".
- [7] ETS 300 175-7: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 7: Security features".
- [8] ETS 300 175-8: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 8: Speech coding and transmission".
- [9] ETS 300 175-9: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 9: Public Access Profile (PAP)".
- [10] ETS 300 406 (1995): "Methods for Testing and Specification (MTS); Protocol and profile conformance testing specifications; Standardization methodology".
- [11] ISO/IEC 9646-1 (1995): "Information technology - Open Systems Interconnection - Conformance testing methodology and framework - Part 1: General concepts".
- [12] ISO/IEC 9646-7 (1995): "Information technology - Open Systems Interconnection - Conformance testing methodology and framework - Part 7: Implementation Conformance Statements".

3 Definitions and abbreviations

3.1 Definitions

For the purposes of this ETS, the following terms and definitions apply:

- terms defined in ETS 300 175-1 [1]
- terms defined in ISO/IEC 9646-1 [11] and in ISO/IEC 9646-7 [12].

In particular, the following terms defined in ISO/IEC 9646-1 [11] apply:

Implementation Conformance Statement (ICS): A statement made by the supplier of an implementation or system claimed to conform to a given specification, stating which capabilities have been implemented. The ICS can take several forms: protocol ICS, profile ICS, profile specific ICS, information object ICS, etc.

ICS proforma: A document, in the form of a questionnaire, which when completed for an implementation or system becomes an ICS.

3.2 Abbreviations

For the purposes of this ETS, the abbreviations defined in ISO/IEC 9646-1 [11], the medium access control layer abbreviations defined in ETS 300 175-3 [3], and the following abbreviations apply.

ICS	Implementation Conformance Statement
IUT	Implementation Under Test
PICS	Protocol Implementation Conformance Statement
SCS	System Conformance Statement
SUT	System Under Test

4 Conformance requirement to this PICS proforma specification

The supplier of a protocol implementation which is claimed to conform to the portable termination specific requirements of ETS 300 175-3 [3] shall complete a copy of the PICS proforma provided in Annex A and shall provide the information necessary to identify both the supplier and the implementation.

An ICS which conforms to this ETS shall be a conforming PICS proforma completed in accordance with the guidances for completion given in clause A.1.

Annex A (normative): PICS proforma for DECT MAC PT

Notwithstanding the provisions of the copyright clause related to the text of the present ETS (see front page), ETSI grants users of this ETS to freely reproduce the PICS Proforma in this annex so that it can be used for its intended purposes and may further publish the completed PICS.

A.1 Introduction for completing the PICS proforma

A.1.1 Purposes and structure

The purpose of this PICS is to provide a mechanism whereby a supplier of an implementation of the portable termination specific medium access control layer requirements of ETS 300 175-3 [3]: DECT Medium Access Control Layer may provide information in a standard form.

The PICS proforma is subdivided into subclauses for the following categories of information:

- guidances for completing the PICS proforma;
- identification of the implementation;
- identification of the protocol;
- services, procedures and functions;
- timers and protocol parameters;
- messages;

A.1.2 Symbols, abbreviations and conventions

The PICS proforma contained in this annex is comprised of information in tabular form in accordance with the guidelines presented in ISO/IEC 9646-7 [12].

Item column

The item column contains a number which identifies the item in the table.

Item description column

The item description column describes in free text each respective item (e.g. parameters, timers, etc.). It implicitly means "is <item description> supported by the implementation?".

Status column

The following notations, defined in ISO/IEC 9646-7 [12], are used for the status column:

- | | |
|-----|---|
| m | mandatory - the capability is required to be supported. |
| o | optional - the capability may be supported or not (e.g. the capability is not allowed because the underlying DECT layers (service provider) cannot handle it or the requirement belongs to an application i.e. does not belong to the data link control layer) |
| n/a | not applicable - in the given context, it is impossible to use the capability. |
| x | prohibited (excluded) - there is a requirement not to use this capability in the given context. |
| o.i | qualified optional - for mutually exclusive or selectable options from a set. "i" is an integer which identifies an unique group of related optional items and the logic of their selection which is defined immediately following the table. |
| ci | conditional - the requirement on the capability ("m", "o", "x" or "n/a") depends on the support of other optional or conditional items. "i" is an integer identifying an unique conditional status expression which is defined immediately following the table. |

Reference column

The reference column gives reference to ETS 300 175-3 [3], except where explicitly stated otherwise.

Support column

The support column shall be filled in by the supplier of the implementation. The following common notations, defined in ISO/IEC 9646-7 [12], are used for the support column:

Y or y	supported by the implementation
N or n	not supported by the implementation
N/A, n/a or -	no answer required (allowed only if the status is n/a, directly or after evaluation of a conditional status)

In each context, the kind of "non-support" which is implemented at the receipt may be additionally indicated such as:

- Err the item is treated as a protocol error;
- Ig the item is received and ignored (i.e. processed syntactically, but not semantically);
- rj the item is received and rejected.

NOTE: As stated in ISO/IEC 9646-7 [12], support for a received PDU requires the ability to parse all valid parameters of that PDU. Supporting a PDU while having no ability to parse a valid parameter is non-conformant. Support for a parameter on a PDU means that the semantics of that parameter are supported.

Values allowed column

The values allowed column contains the values or the ranges of values allowed. The range of value is defined as follows: [min value] .. [max value]. Alternative values are defined as follows:

[value1], [value 2], ..., [value n].

EXAMPLE: '00110000'B .. '01001011'B is the value range
from '00110000'B to '01001011'B

'00110000'B, '01001011'B the value can be '00110000'B or '01001011'B.

Values supported column

The values supported column shall be filled in by the supplier of the implementation. In this column, the values or the ranges of values supported by the implementation shall be indicated.

Prerequisite line

A prerequisite line takes the form: Prerequisite: <predicate>.

A prerequisite line before a table title indicates that the whole table is not required to be completed if the predicate is FALSE.

A.1.3 Guidances for completing the PICS

The supplier of the implementation shall enter an explicit statement in each of the tables provided using the notation described in subclause A.1.2. If necessary, specific instruction is provided in the text which precedes each table.

A.2 Identification of the implementation

A.2.1 Date of statement

Identification of the Implementation Under Test (IUT) and the system in which it resides (the System Under Test (SUT)) should be filled in so as to provide as much detail as possible regarding version numbers and configuration options.

Table A.1: Date of statement

Date of statement		
Day	Month	Year

A.2.2 Implementation Under Test (IUT) identification

The supplier of the implementation shall enter information necessary to uniquely identify the IUT in the table below.

Table A.2: IUT identification

IUT identification	
IUT name	
IUT version	

A.2.3 System Under Test (SUT) identification

The supplier of the implementation shall enter information necessary to uniquely identify the SUT in the table below.

Table A.3: SUT identification

IUT identification	
SUT name	International Portable Equipment Identity (IPEI):
Hardware configuration	

A.2.4 Product supplier

Table A.4 : Product supplier

Product supplier	
Name	
Address	
Phone No.	
Fax No.	
E-mail address	
Additional information	

A.2.5 Client identification

The product supplier information and client information should both be filled in if they are different.

Table A.5: Client identification

Client	
Name	
Address	
Phone No.	
Fax No.	
E-mail address	
Additional information	

A.2.6 Contact person

A person who can answer queries regarding information supplied in the PICS should be named as the contact person.

Table A.6 : Contact person identification

Contact person	
Name	
Address	
Phone No.	
Fax No.	

A.3 Identification of the protocol

Table A.7: Identification of protocol

Identification of protocol	
Title of specification	Radio Equipment and Systems Digital Enhanced Cordless Telecommunications Common Interface Part 3: Medium Access Control Layer
Reference no.	ETS 300 175-3
Date of Publication	

A.4 Global statement of conformance

The supplier of the implementation shall state whether or not all mandatory capabilities are implemented for ETS 300 175-3 [3]: Medium Access Control Layer.

Table A.8: Global statement of conformance

Are all mandatory capabilities implemented?	
---	--

NOTE: Answering "No" to this question indicates non-conformance to the protocol specification. Non-supported mandatory capabilities are to be identified in the PICS, with an explanation of why the implementation is non-conforming.

A.5 Capabilities

A.5.1 Services

The supplier of the implementation shall state the support of the implementation for each of the following services, in the table below.

Table A.9: Service groups supported

Item	Name of service	Ref.	Status	Support
1	Connection oriented control	5.6	o.901	
2	Broadcast control	5.7.1	o.901	
3	Connectionless control	5.7.2	o.901	
4	Multiplexing	6	m	
5	Management	11	m	

o.901: It is mandatory to support at least one of this options

A.5.1.1 Connection oriented control services

Table A.10: Connection oriented control services

Prerequisite: A.9/1				
Item	Connection oriented control services	Ref.	Status	Supp.
1	Basic connections	5.6.1.1	o.1001	
2	Advanced symmetric connections	5.6.2.1	o.1001	
3	Advanced asymmetric connections	5.6.2.2	o.1001	

o.1001: It is mandatory to support at least one of this options

Table A.11: Connection services

Prerequisite: A.10/1 OR A.10/2 OR A.10/3				
Item	Connection services	Ref.	Status	Support
1	Connection setup	10.2	m	
2	Connection modification	10.3	c1101	
3	Connection data transfer	10.8	m	
4	Connection release	10.4	m	

c1101: IF A.9/2 OR A.9/3 THEN o ELSE n/a

Table A.12: Symmetric connection oriented services

Prerequisite: A.10/2				
Item	Symmetric connection oriented services	Ref.	Status	Support
1	Type 1 IN_minimum_delay	5.6.2.1	o.1201	
2	Type 2 IN_normal_delay	5.6.2.1	o.1201	
3	Type 3 IP_error_detection	5.6.2.1	o.1201	
4	Type 4 IP_error_correction	5.6.2.1	o.1201	

o.1201: It is mandatory to support at least one of this options

Table A.13: Asymmetric connection oriented services

Prerequisite: A.10/3				
Item	Asymmetric connection oriented services	Ref.	Status	Support
1	Type 5 IN_normal_delay	5.6.2.2	o.1301	
2	Type 6 IP_error_detection	5.6.2.2	o.1301	
3	Type 7 IP_error_correction	5.6.2.2	o.1301	

o.1301: It is mandatory to support at least one of this options

Table A.14: C-plane connection services

Prerequisite: A.10/1 OR A.10/2 OR A.10/3				
Item	C-plane connection services	Ref.	Status	Support
1	Only CS channel supported	10.8.1	o.1401	
2	CS and CF channels supported	10.8.1	o.1401	
3	Only CF channel supported	10.8.1	o.1401	

o.1401: It is mandatory to support at least one of this options

A.5.1.2 Broadcast control services

Table A.15: Broadcast services

Prerequisite: A.9/2				
Item	Broadcast services	Ref.	Status	Support
1	Continuous broadcast	5.7.1.1	m	
2	Non-continuous broadcast	5.7.1.2	o	
3	Paging broadcast	9.1.3	o	

A.5.1.3 Connectionless control services

Table A.16: Connectionless control services

Prerequisite: A.9/2				
Item	Broadcast services	Ref.	Status	Support
1	Downlink connectionless	5.7.2.1	o	
2	Uplink connectionless	5.7.2.2	o	

A.5.1.3.1 Downlink connectionless services

Table A.17: Downlink connectionles services

Prerequisite: A.16/1				
Item	Downlink connectionless services	Ref.	Status	Support
1	CLS channel only, short simplex bearer	5.7.2.1	o.1701	
2	CLS and CLF channels, long simplex bearer	5.7.2.1	o.1701	
3	CLS and SIN channels, long simplex bearer	5.7.2.1	o.1701	

o.1701: It is mandatory to support at least one of this options

A.5.1.3.2 Uplink connectionless services

Table A.18: Uplink connectionless services

Prerequisite: A.16/2				
Item	Uplink connectionless services	Ref.	Status	Support
1	CLS channel only, short simplex bearer	5.7.2.2	o.1801	
2	CLS channel only, long simplex bearer	5.7.2.2	o.1801	
3	CLF channel only, long simplex bearer	5.7.2.2	o.1801	
4	No SDU, PMID only, short simplex bearer	5.7.2.2	o.1801	
5	No SDU, PMID only, long simplex bearer	5.7.2.2	o.1801	

o.1801: It is mandatory to support at least one of this options

A.5.1.4 Multiplexing services

Table A.19: CSF multiplexing services

Prerequisite: A.9/4				
Item	CSF multiplexing services	Ref.	Status	Support
1	D-MAP	6.2.1.1	m	
2	A-MAP	6.2.1.2	m	
3	B-MAP	6.2.1.3	o	
4	T-MUX	6.2.2.1	m	
5	E/U-MUX	6.2.2.2	o	
6	C-MUX	6.2.2.3	o	
7	Encryption activation	6.2.3	o	
8	Encryption deactivation	6.2.3	o	
9	Scrambling	6.2.4	m	
10	Error control R-CRC	6.2.5.1	o	
11	Error control X-CRC	6.2.5.3	o	
12	Broadcast control	6.2.6	m	

Table A.20: D-MAP services

Prerequisite: A.19/1				
Item	D-MAP	Ref.	Status	Support
1	D-field MAP D80	6.2.1.1	o.2001	
2	D-field MAP D32	6.2.1.1	o.2001	
3	D-field MAP D08	6.2.1.1	o.2001	
4	D-field MAP D00	6.2.1.1	o.2001	

o.2001: It is mandatory to support at least one of this options

Table A.21: B-MAP services

Prerequisite: A.19/3				
Item	B-MAP	Ref.	Status	Support
1	B-field MAP unprotected format	6.2.1.3	o.2101	
2	B-field MAP protected format	6.2.1.3	o.2101	

o.2101: It is mandatory to support at least one of this options

Table A.22: E/U mux services

Prerequisite: A.19/5				
Item	E/U MUX	Ref.	Status	Support
1	E/U-mux E type	6.2.2.2	o.2201	
2	E/U-mux U type	6.2.2.2	o.2201	

o.2201: It is mandatory to support at least one of this options

Table A.23: C mux mapping services

Prerequisite: A.19/6				
Item	Time multiplexers - C mux	Ref.	Status	Support
1	C-mux double slot	6.2.2.3.1	o.2301	
2	C-mux full slot	6.2.2.3.1	o.2301	
3	C-mux half slot	6.2.2.3.2	o.2301	

o.2301: It is mandatory to support at least one of this options

A.5.1.5 Management services

Table A.24: Management services

Prerequisite: A.9/5				
Item	Management services	Ref.	Status	Support
1	Broadcasting	11.1	c2401	
2	Extended system information	11.2	o	
3	PP states and state transition	11.3	m	
4	Physical channel selection	11.4	m	
5	In-connection quality control	11.5	m	
6	RFP system load	11.6	m	
7	Receiver scan sequence	11.9	m	
8	Test messages	12	o	
9	SARI support	7.2.3.6.2	o	
10	TARI support	7.2.5.10	o	

c2401: IF A.15/1 THEN m ELSE n/a

Table A.25: Handover services management

Item	Name of service	Ref.	Status	Supp.
1	Connection handover	10.2.4.1	c2501	
2	Bearer handover	10.6	o	

c2501: IF A.9/1 THEN o ELSE n/a

A.5.2 Procedures

The supplier of the implementation shall state the support of the implementation for each of the following procedures, in the tables below.

A.5.2.1 Connection procedures

A.5.2.1.1 Connection setup procedures

Table A.26: C/O single bearer setup procedures

Prerequisite: A.10/1 AND A.11/1				
Item	Name of procedure	Ref.	Status	Supp.
1	Basic setup, single bearer basic connection of known service	10.2.4.2	o.2601	
2	Normal setup, single bearer duplex connection known service	10.2.4.2	o.2601	
3	Fast setup, single bearer duplex connection known service	10.2.4.2	o.2601	

o.2601: It is mandatory to support at least one of this options

Table A.27: C/O multi-bearer symmetric setup procedures

Prerequisite: A.10/2 AND A.11/1				
Item	Name of procedure	Ref.	Status	Supp.
1	Normal setup, multi-bearer symmetric connection	10.2.4.3.1	o.2701	
2	Fast setup, multi-bearer symmetric connection	10.2.4.3.1	o.2701	

o.2701: It is mandatory to support at least one of this options

Table A.28: C/O multi-bearer asymmetric setup procedures

Prerequisite: A.10/3 AND A.11/1				
Item	Name of procedure	Ref.	Status	Supp.
1	Normal setup, multi-bearer fully asymmetric UL connection	10.2.4.3.2	o.2801	
2	Fast setup, multi-bearer fully asymmetric UL connection	10.2.4.3.2	o.2801	
3	Normal setup, multi-bearer fully asymmetric DL connection	10.2.4.3.3	o.2801	
4	Fast setup, multi-bearer fully asymmetric DL connection	10.2.4.3.3	o.2801	

o.2801: It is mandatory to support at least one of this options

Table A.29: C/O bearer setup procedures

Prerequisite: A.11/1				
Item	Name of procedure	Ref.	Status	Supp.
1	Basic bearer setup	10.5.1.1	c2901	
2	PT initiated - A-field advanced single bearer setup	10.5.1.2.1	c2902	
3	PT initiated - B-field single bearer setup	10.5.1.3.1	c2902	
4	FT initiated - A-field advanced single bearer setup	10.5.1.2.2	c2903	
5	FT initiated - B-field single bearer setup	10.5.1.3.2	c2904	
6	Double simplex bearer setup, indirect	10.5.1.4	c2905	
7	Double simplex bearer setup, direct	10.5.1.4	c2905	
8	Channel list	10.5.2	c2906	

c2901: IF A.26/1 THEN m ELSE n/a

c2902: IF A.26/2 OR A.27/1 OR A.28/1 OR A.28/3 THEN o.2901 ELSE n/a

c2903: IF A.28/4 THEN o for additional duplex bearers ELSE n/a

c2904: IF A.26/3 OR A.27/2 OR A.28/2 OR A.28/4 THEN m ELSE n/a

c2905: IF A.27/1 OR A.27/2 OR A.28/1 OR A.28/2 OR A.28/3 OR A.28/4 THEN o.2901 ELSE n/a

c2906: IF A.29/6 OR A.29/7 THEN m ELSE o

o.2901: It is mandatory to support at least one of this options

A.5.2.1.2 Connection modification procedures**Table A.30: C/O connection modification procedures**

Prerequisite: A.11/2				
Item	Name of procedure	Ref.	Status	Supp.
1	Connection modification	10.3	m	

A.5.2.1.3 Connection data transfer procedures**Table A.31: C/O data transfer procedures**

Prerequisite: A.11/3				
Item	Name of procedure	Ref.	Status	Supp.
1	ARQ procedure, Q1 and Q2 bit setting, for C-channel	10.8.1	m	
2	Cs - channel data	10.8.1.1	o	
3	Q1/Q2 setting for sliding collision / A-,B-field check (FT to PT)	10.8.1.3	m	
4	Antenna diversity (React on Q1 bit in direction PT to FT)	10.8.1.3	o	
5	Q2 bit settings	10.8.1.3.1	o	
6	Q1 bit settings	10.8.1.3.2	o	
7	BCK/Q2 bit setting for IP channel flow control, duplex bearer	10.8.2.4	o	
8	ACK/BCK bit setting for IP flow control, double simplex	10.8.2.4	o	
9	Bearer replacement	10.8.2.5.1	o	
10	Unilateral jump	10.8.2.5.2	o	
11	IP bearer reset	10.8.2.5.3	o	

A.5.2.1.4 Handover procedures**Table A.32: Handover procedures**

Prerequisite: A.25				
Item	Name of procedure	Ref.	Status	Supp.
1	Connection handover	10.2.4.1	c3201	
2	Duplex bearer handover	10.6.2	c3202	
3	Double simplex bearer handover	10.6.3	c3203	

c3201: IF A.25/1 THEN m ELSE n/a

c3202: IF A.25/2 AND A.29/1 THEN m ELSE n/a
 c3203: IF A.25/2 AND (A.29/6 OR A.29/7) THEN m ELSE n/a

A.5.2.1.5 Connection release procedures

Table A.33: C/O connection release procedures

Prerequisite: A.11/5				
Item	Name of procedure	Ref.	Status	Supp.
1	Unacknowledge bearer release	10.7.2.1	m	
2	Acknowledge bearer release	10.7.2.2	o.3301	
3	Fast bearer release	10.7.2.3	c3301	

c3301: IF A.11/5 THEN m ELSE n/a
 o.3301: IF A.29/6 OR A.29/7 THEN m ELSE n/a

A.5.2.2 Broadcast procedures

Table A.34: Broadcast procedures

Prerequisite: A.15/3				
Item	Name of procedure	Ref.	Status	Supp.
1	Normal paging	9.1.3	o.3401	
2	Fast paging	9.1.3	o.3401	
3	Downlink broadcast	9.1.1.3	m	

o.3401: It is mandatory to support at least one of this options

A.5.2.3 Connectionless procedures

A.5.2.3.1 Downlink connectionless procedures

Table A.35: Downlink connectionless procedures

Prerequisite: A.16/1				
Item	Name of procedure	Ref.	Status	Supp.
1	Downlink C/L	9.1.2	m	

A.5.2.3.2 Uplink connectionless procedures

Table A.36: Uplink connectionless procedures

Prerequisite: A.16/2				
Item	Name of procedure	Ref.	Status	Supp.
1	Uplink C/L bearer selection	9.2.2	o	
2	Uplink C/L	9.2.3	o	
3	Request for specific Q-channel information, A-field procedure	9.3.1	c3601	
4	Request for specific Q-channel information, B-field procedure	9.3.1	c3601	
5	Request for new dummy bearer	9.3.2	o	

c3601: IF A.24/2 THEN o.3601 ELSE n/a
 o.3601: It is mandatory to support at least one of this options

A.5.2.4 CSF multiplexing procedures

Table A.37: CSF multiplexing procedures

Prerequisite: A.9/4				
Item	CSF multiplexing procedures	Ref.	Status	Support
1	Encryption	6.2.3	o	
2	Scrambling	6.2.4	m	
3	R-CRC generation	6.2.5.2	o	
4	R-CRC checking	6.2.5.2	o	
5	X-CRC generation	6.2.5.4	o	
6	X-CRC checking	6.2.5.4	o	
7	Broadcast control function	6.2.6	m	

A.5.2.5 Layer management procedures

Table A.38: Layer management procedures

Prerequisite: A.9/5				
Item	Name of procedure	Ref.	Status	Supp.
1	Extented system information PP request	11.2.1	o	
2	Duplex bearer physical channel selection	11.4.1	m	
3	Double simplex bearer physical channel selection	11.4.1	o	
4	Simplex bearer physical channel selection	11.4.1	m	
5	RFPI handshake	11.5.1	m	
6	RFP measurement of frequency error	11.5.2.1	o	
7	RFP idle receiver scan sequence	11.8	o	
8	Test message procedures	12	o	

A.5.3 Other capabilities

The supplier of the implementation shall state whether or not extended RF carriers are supported.

Table A.39: Extended RF carriers supported

Item	Extended RF Carriers	Ref.	Status	Support
1	Extended RF carriers	7.2.3	o	

The supplier of the implementation shall state which modes of operation are supported by the PT in the Idle_locked state.

Table A.40: Operation modes in Idle_locked state supported

Item	Operation mode	Ref.	Status	Support
1	Scanning mode	4.3.1, 11.3	m	
2	High duty cylce Idle_locked mode	4.3.1, 11.3	o.4001	
3	Normal cylce Idle_locked mode	4.3.1, 11.3	o.4001	
4	Low cylce Idle_locked mode	4.3.1, 11.3	o.4001	

o.4001: It is mandatory to support at least one of this options

A.6 Protocol parameters

A.6.1 Timer support

The supplier of the implementation shall provide information about the timers specified in the ETS 300 175-3 [3]: Medium Access Control Layer.

Table A.41: Timer supported

Item	Name of timer	Ref.	Status	Support	Value Allowed	Value Supported
1	T200	A.1	o		3 seconds	
2	T201	A.1	o		5 seconds	
3	T202	A.1	o		3 seconds	
4	T203	A.1	o		16 frames	
5	T204	A.1	x		6 multi-frames	
6	T205	A.1	x		10 seconds	
7	T206	A.1	x		10 frames	
8	T207	A.1	o		5 seconds	
9	T208	A.1	o		20 seconds	
10	T209	A.1	o		30 seconds	
11	T210	A.1	o		2 seconds	
12	T211	A.1	c4101		3 seconds	
13	T212	A.1	c4102		20 frames	
14	T213	A.1	c4103		20 frames	
15	T214	A.1	c4104		20 frames	
16	T215	A.1	c4104		6 multi-frames	

c4101: IF A.26/10 THEN m ELSE x

c4102: IF A.29/3 OR A.29/4 THEN m ELSE x

c4103: IF A.29/9 THEN m ELSE x

c4104: IF A.18/1..5 THEN m ELSE x

A.6.2 Protocol constants

The supplier of the implementation shall provide information about the protocol constants specified in the ETS 300 175-3 [3]: Medium Access Control Layer.

Table A.42: Protocol constants support

Item	Protocol Constants	Ref.	Status	Support	Value Allowed	Value Supported
1	N200	A.2	o		10	
2	N201	A.2	o		15	
3	N202	A.2	o		10	
4	N203	A.2	c4201		6	

c4201: IF A.18/1..5.THEN m ELSE x

A.6.3 Channel selection parameters

The supplier of the implementation shall state whether or not the following parameters specified by ETS 300 175-3 [3]: Medium Access Control Layer are supported and their type, value(s) and range(s), in the table below.

Table A.43: Channel selection parameters

Item	Parameter	Ref.	Status	Supp.	Value Allowed	Value Supported
1	Lowest boundary of channel list	11.4.1	m		<= -93 dBm	
2	Band resolution	11.4.1	m		<= 6 dB	
3	RSSI variation between checking	11.4.2	m		<= 12 dB	

A.6.4 Channels supported

Table A.44: Channels supported

Item	Channels supported	Ref.	Status	Support
1	B _S channel	5.3.3.1	o	
2	C _S channel	5.3.1.1	o	
3	C _F channel	5.3.1.1	o	
4	G _F channel	5.3.1.3	o	
5	SI _N channel	5.3.2.2	o	
6	CL _S channel	5.3.2.1	o	
7	CL _F channel	5.3.2.1	o	
8	I _N channel	5.3.1.2	o	
9	I _P channel	5.3.1.2	o	

A.6.5 Bearer types supported

Table A.45: Bearer types supported

Item	Bearer types supported	Ref.	Status	Support
1	Short simplex	5.5.1	o.4501	
2	Long simplex	5.5.1	o.4501	
3	Duplex	5.5.1	o.4501	
4	Double simplex	5.5.1	o.4501	

o.4501: It is mandatory to support at least one of this options

A.6.6 Slot types supported

Table A.46: Slot types supported

Item	Slot types supported	Ref.	Status	Support
1	Short slot	6.2.1	o.4601	
2	Half slot	6.2.1	o.4601	
3	Full slot	6.2.1	o.4601	
4	Double slot	6.2.1	o.4601	

o.4601: It is mandatory to support at least one of this options

A.7 Messages

The supplier of the implementation shall state whether or not the messages specified by ETS 300 175-3 [3]: Medium Access Control Layer are supported, in the tables below. The supplier shall indicate the status of support for sending and receiving each message.

A.7.1 A - field header

A.7.1.1 A - field header - Tail Identification

Table A.47: Tail Identification (Sending P to F)

Prerequisite: A.19/2				
Item	Tail Identification	Ref.	Status	Support
1	CT data packet number 0	7.1.2	m	
2	CT data packet number 1	7.1.2	m	
3	Identifies information on C/L bearer	7.1.2	x	
4	Identifies information	7.1.2	m	
5	Multiframe syncronisation - system info.	7.1.2	x	
6	Escape	7.1.2	o	
7	MAC layer control	7.1.2	m	
8	Paging tail	7.1.2	x	
9	First PP transmission	7.1.2	m	

Table A.48: Tail Identification (Receipt F to P)

Prerequisite: A.19/2				
Item	Tail Identification	Ref.	Status	Support
1	CT data packet number 0	7.1.2	m	
2	CT data packet number 1	7.1.2	m	
3	Identifies information on C/L bearer	7.1.2	o	
4	Identifies information	7.1.2	m	
5	Multiframe syncronisation - system info.	7.1.2	m	
6	Escape	7.1.2	o	
7	MAC layer control	7.1.2	m	
8	Paging tail	7.1.2	o	
9	First PP transmission	7.1.2	x	

A.7.1.2 A - field header - “Q1/BCK” bit

Table A.49: “Q1/BCK” bit (Sending P to F)

Prerequisite: A.19/2				
Item	“Q1/BCK” bit	Ref.	Status	Support
1	BCK IP flow control (sliding collision)	7.1.3	m	
2	Q1 bearer quality control	7.1.3	x	

Table A.50: “Q1/BCK” bit (Receipt F to P)

Prerequisite: A.19/2				
Item	“Q1/BCK” bit	Ref.	Status	Support
1	BCK IP flow control (sliding collision)	7.1.3	m	
2	Q1 bearer quality control	7.1.3	m	

A.7.1.3 A - field header - B-field identification

Table A.51: B-field identification (Sending P to F)

Prerequisite: A.19/2				
Item	B-field identification	Ref.	Status	Support
1	U-type, IN, SIN or IP packet number 0	7.1.4	c5101	
2	U-type, IP error detect or IP packet number 1	7.1.4	c5101	
3	E-type, all CF or CLF, packet number 0	7.1.4	c5102	
4	E-type, all CF, packet number 1	7.1.4	c5102	
5	E-type, not all CF or CLF; packet number 0	7.1.4	c5102	
6	E-type, not all CF; CF packet number 1	7.1.4	c5102	
7	E-type, all MAC control (unnumbered)	7.1.4	c5102	
8	No B-field	7.1.4	o	

c5101: IF 22/2 THEN o ELSE n/a

c5102: IF 22/1 THEN o ELSE n/a

Table A.52: B-field identification (Receipt F to P)

Prerequisite: A.19/2				
Item	B-field identification	Ref.	Status	Support
1	U-type, IN, SIN or IP packet number 0	7.1.4	c5201	
2	U-type, IP error detect or IP packet number 1	7.1.4	c5201	
3	E-type, all CF or CLF, packet number 0	7.1.4	c5202	
4	E-type, all CF, packet number 1	7.1.4	c5202	
5	E-type, not all CF or CLF; packet number 0	7.1.4	c5202	
6	E-type, not all CF; CF packet number 1	7.1.4	c5202	
7	E-type, all MAC control (unnumbered)	7.1.4	c5202	
8	No B-field	7.1.4	m	

c5201: IF 22/2 THEN o ELSE n/a

c5202: IF 22/1 THEN o ELSE n/a

A.7.1.4 A - field header - “Q2” bit

Table A.53: “Q2” bit (Sending P to F)

Prerequisite: A.19/2				
Item	“Q2” bit	Ref.	Status	Support
1	Q2 bearer quality & flow control	7.1.5	m	

Table A.54: “Q2” bit (Receipt F to P)

Prerequisite: A.19/2				
Item	“Q2” bit	Ref.	Status	Support
1	Q2 bearer quality & flow control	7.1.5	m	

A.7.2 A - field identities information (N_T) message

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.55: Identities information (N_T) message (Sending P to F)

Prerequisite: A.24/1				
Item	System information message	Ref.	Status	Support
1	NT - Identities Information	7.2.2	m	

Table A.56: Identities information (N_T) message (Receipt F to P)

Prerequisite: A.24/1				
Item	System information message	Ref.	Status	Support
1	NT - Identities Information	7.2.2	m	

A.7.3 A - field system information (Q_T) messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.57: System information (Q_T) message (Receipt F to P)

Prerequisite: A.24/1				
Item	System information message	Ref.	Status	Support
1	QT - Static system information	7.2.3.2	m	
2	QT - Extended RF carrier information	7.2.3.3	c5701	
3	QT - Fixed part capabilities	7.2.3.4	m	
4	QT - Extended fixed part capabilities	7.2.3.5	o	
5	QT - Secondary access rights identities	7.2.3.6	o	
6	QT - Multi-frame number	7.2.3.7	c5702	
7	QT - escape	7.2.3.8	o	

c5701: IF A.39/1 THEN m ELSE o

c5702: IF A.37/1 THEN m ELSE o

A.7.4 A - field paging tail (P_T) messages

A.7.4.1 Paging tail messages supported

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.58: Paging tail (P_T) messages (Receipt F to P)

Prerequisite: 15/3				
Item	Paging tail messages	Ref.	Status	Support
1	Full page format	7.2.4.1	o.5801	
2	Long page format	7.2.4.1	o.5801	
3	Short page format	7.2.4.1	o.5801	
4	Zero length page format	7.2.4.1	o.5801	

o.5801: It is mandatory to support at least one of this options

A.7.4.2 P_T messages information type

The support of a P_T message information element in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.59: P_T messages information supported (Receipt F to P)

Prerequisite: A.58/3 OR A.58/4				
Item	P _T messages information type	Ref.	Status	Support
1	0000 - fill bits	7.2.4.3.2	o	
2	0001 - blind full slot	7.2.4.3.3	o	
3	0010 - other bearer	7.2.4.3.4	o	
4	0011 - recommended other bearer	7.2.4.3.4	o	
5	0100 - good RFP bearer	7.2.4.3.4	o	
6	0101 - dummy or C/L bearer position	7.2.4.3.4	o	
7	0110 - RFP identity	7.2.4.3.5	o	
8	0111 - escape	7.2.4.3.6	o	
9	1000 - dummy or C/L bearer marker	7.2.4.3.7	c5901	
10	1001 - bearer handover information	7.2.4.3.8	o	
11	1010 - RFP status	7.2.4.3.9	o	

c5901: Only on dummy or connectionless downlink bearer

A.7.5 A - field MAC control (M_T) messages**A.7.5.1 Mac control messages supported**

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.60: MAC control (M_T) messages (Sending P to F)

Prerequisite: A.9/1 OR A.9/2 OR A.9/3 OR A.9/4 OR A.9/5				
Item	MAC control (M _T) messages	Ref.	Status	Supp.
1	Basic connection control	7.2.5.1	c6004	
2	MAC layer test messages	7.2.5.1	x	
3	Advanced connection control	7.2.5.1	c6002	
4	Quality control	7.2.5.1	o	
5	Broadcast and connectionless services	7.2.5.1	c6005	
6	Encryption control	7.2.5.1	c6003	
7	B-field setup, first PT transmission	7.2.5.1	o	
8	MAC control escape	7.2.5.1	o	
9	TARI	7.2.5.1	o	

c6001: IF A.38/8 THEN m ELSE n/a

c6002: IF A.29/2 OR A.29/4 THEN m ELSE n/a

c6003: IF A.37/1 THEN m ELSE n/a

c6004: IF A.9/1 THEN m ELSE o

c6005: IF A.9/2 OR A.9/3 THEN m ELSE o

Table A.61: MAC control (M_T) messages (Receipt F to P)

Prerequisite: A.9/1 OR A.9/2 OR A.9/3 OR A.9/4 OR A.9/5				
Item	MAC control (M _T) messages	Ref.	Status	Supp.
1	Basic connection control	7.2.5.1	c6104	
2	MAC layer test messages	7.2.5.1	c6101	
3	Advanced connection control	7.2.5.1	c6102	
4	Quality control	7.2.5.1	o	
5	Broadcast and connectionless services	7.2.5.1	c6105	
6	Encryption control	7.2.5.1	c6103	
7	B-field setup, first PT transmission	7.2.5.1	x	
8	MAC control escape	7.2.5.1	o	
9	TARI	7.2.5.1	o	

c6101: IF A.38/8 THEN m ELSE n/a

c6102: IF A.29/2 OR 29/4 THEN m ELSE n/a
 c6103: IF A.37/1 THEN m ELSE n/a
 c6104: IF A.9/1 THEN m ELSE o
 c6105: IF A.9/2 OR A.9/3 THEN m ELSE o

A.7.5.2 Basic connection control messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.62: Basic connection control (Sending P to F)

Prerequisite: A.60/1				
Item	MAC control (M_T) messages -Basic connection control	Ref.	Status	Supp.
1	Basic CC - access request	7.2.5.2.2	m	
2	Basic CC - bearer handover request	7.2.5.2.2	m	
3	Basic CC - connection handover request	7.2.5.2.2	m	
4	Basic CC - unconfirmed access request	7.2.5.2.2	c6201	
5	Basic CC - bearer confirm	7.2.5.2.2	x	
6	Basic CC - release	7.2.5.2.2	m	
7	Basic CC - wait	7.2.5.2.3	m	

c6201: IF A.29/7 THEN m ELSE o

Table A.63: Basic connection control (Receipt F to P)

Prerequisite: A.61/1				
Item	MAC control (M_T) messages -Basic connection control	Ref.	Status	Supp.
1	Basic CC - access request	7.2.5.2.2	x	
2	Basic CC - bearer handover request	7.2.5.2.2	x	
3	Basic CC - connection handover request	7.2.5.2.2	x	
4	Basic CC - unconfirmed access request	7.2.5.2.2	x	
5	Basic CC - bearer confirm	7.2.5.2.2	m	
6	Basic CC - release	7.2.5.2.2	m	
7	Basic CC - wait	7.2.5.2.3	m	

A.7.5.3 MAC layer test messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.64: MAC layer test messages (Sending P to F)

Item	MAC control (M_T) messages - MAC layer test messages	Ref.	Status	Supp.
1	MAC test - force transmit	7.2.5.4.2	x	
2	MAC test - loopback data	7.2.5.4.3	x	
3	MAC test - defeat antenna diversity	7.2.5.4.4	x	
4	MAC test - force bearer handover	7.2.5.4.5	x	
5	MAC test - escape	7.2.5.4.6	x	
6	MAC test - network test	7.2.5.4.7	x	
7	MAC test - clear test modes	7.2.5.4.8	x	

Table A.65: MAC layer test messages (Receipt F to P)

Prerequisite: A.61/2				
Item	MAC control (M_T) messages - MAC layer test messages	Ref.	Status	Supp.
1	MAC test - force transmit	7.2.5.4.2	m	
2	MAC test - loopback data	7.2.5.4.3	m	
3	MAC test - defeat antenna diversity	7.2.5.4.4	c6501	
4	MAC test - force bearer handover	7.2.5.4.5	o	
5	MAC test - escape	7.2.5.4.6	o	
6	MAC test - network test	7.2.5.4.7	o	
7	MAC test - clear test modes	7.2.5.4.8	m	

c6501: IF A.31/4 THEN m ELSE x

A.7.5.4 Advanced connection control messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.66: Advanced connection control messages (Sending P to F)

Prerequisite: A.60/3				
Item	MAC control (M_T) messages - Advanced connection control	Ref.	Status	Supp.
1	Advanced CC - access request	7.2.5.3.2	m	
2	Advanced CC - bearer handover request	7.2.5.3.3	m	
3	Advanced CC - connection handover request	7.2.5.3.4	m	
4	Advanced CC - unconfirmed access request	7.2.5.3.5	c6601	
5	Advanced CC - bearer confirm	7.2.5.3.6	m	
6	Advanced CC - wait	7.2.5.3.7	m	
7	Advanced CC - attributes_T.request	7.2.5.3.8	m	
8	Advanced CC - attributes_T.confirm	7.2.5.3.8	m	
9	Advanced CC - bandwidth_T.request	7.2.5.3.9	m	
10	Advanced CC - bandwidth_T.confirm	7.2.5.3.9	m	
11	Advanced CC - channel list	7.2.5.3.10	m	
12	Advanced CC - unconfirmed dummy	7.2.5.3.11	c6601	
13	Advanced CC - unconfirmed handover	7.2.5.3.12	c6601	
14	Advanced CC - release	7.2.5.3.13	m	

c6601: IF 29/6 OR 29/7 THEN m ELSE n/a

Table A.67: Advanced connection control messages (Receipt F to P)

Prerequisite: A.61/3				
Item	MAC control (M_T) messages - Advanced connection control	Ref.	Status	Supp.
1	Advanced CC - access request	7.2.5.3.2	m	
2	Advanced CC - bearer handover request	7.2.5.3.3	x	
3	Advanced CC - connection handover request	7.2.5.3.4	m	
4	Advanced CC - unconfirmed access request	7.2.5.3.5	c6701	
5	Advanced CC - bearer confirm	7.2.5.3.6	m	
6	Advanced CC - wait	7.2.5.3.7	m	
7	Advanced CC - attributes_T.request	7.2.5.3.8	m	
8	Advanced CC - attributes_T.confirm	7.2.5.3.8	m	
9	Advanced CC - bandwidth_T.request	7.2.5.3.9	m	
10	Advanced CC - bandwidth_T.confirm	7.2.5.3.9	m	
11	Advanced CC - channel list	7.2.5.3.10	m	
12	Advanced CC - unconfirmed dummy	7.2.5.3.11	c6701	
13	Advanced CC - unconfirmed handover	7.2.5.3.12	c6701	
14	Advanced CC - release	7.2.5.3.13	m	

c6701: IF 29/6 OR 29/7 THEN m ELSE n/a

A.7.5.5 Quality control messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.68: Quality control (QC) messages (Sending P to F)

Prerequisite: A.60/4				
Item	MAC control (M_T) messages - Quality control	Ref.	Status	Supp.
1	QC - antenna switch single bearer request	7.2.5.5	m	
2	QC - antenna switch all bearers request	7.2.5.5	m	
3	QC - bearer handover reject	7.2.5.5	m	
4	QC - connection handover reject	7.2.5.5	m	
5	QC - frequency control single bearer reject	7.2.5.5	m	
6	QC - frequency control all bearers reject	7.2.5.5	m	

Table A.69: Quality control (QC) messages (Receipt F to P)

Prerequisite: A.61/4				
Item	MAC control (M_T) messages - Quality control	Ref.	Status	Supp.
1	QC - antenna switch single bearer reject	7.2.5.5	m	
2	QC - antenna switch all bearers reject	7.2.5.5	m	
3	QC - bearer handover request	7.2.5.5	m	
4	QC - connection handover request	7.2.5.5	m	
5	QC - frequency control single bearer request	7.2.5.5	m	
6	QC - frequency control all bearers request	7.2.5.5	m	

A.7.5.6 Broadcast and connectionless (BCL) messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.70: Broadcast and connectionless (BCL) messages (Sending P to F)

Prerequisite: A.60/5				
Item	MAC control (M_T) messages - Broadcast and connectionless services	Ref.	Status	Supp.
1	CLF, first of 2 transmissions, half slot	7.2.5.6	o	
2	CLF first of 2 transmissions, full slot	7.2.5.6	o	
3	CLF first of 2 transmissions, double slot	7.2.5.6	o	
4	CLF, last transmissions, half slot	7.2.5.6	o	
5	CLF, last transmissions, full slot	7.2.5.6	o	
6	CLF, last transmissions, double slot	7.2.5.6	o	
7	C/L single transmissions, no CF or CLS	7.2.5.6	o	
8	CLS service, first transmissions	7.2.5.6	o	
9	change dummy bearer position	7.2.5.6	o	
10	extended system info., A-field procedure	7.2.5.6	c7001	
11	extended system info., B-field procedure	7.2.5.6	c7002	

c7001: IF 36/3 THEN m ELSE n/a

c7002: IF 36/4 THEN m ELSE n/a

Table A.71: Broadcast and connectionless (BCL) messages (Receipt F to P)

Prerequisite: A.61/5				
Item	MAC control (M_T) messages - Broadcast and connectionless services	Ref.	Status	Supp.
1	CLF, first of 2 transmissions, half slot	7.2.5.6	x	
2	CLF first of 2 transmissions, full slot	7.2.5.6	x	
3	CLF first of 2 transmissions, double slot	7.2.5.6	x	
4	CLF, last transmissions, half slot	7.2.5.6	x	
5	CLF, last transmissions, full slot	7.2.5.6	x	
6	CLF, last transmissions, double slot	7.2.5.6	x	
7	C/L single transmissions, no CF or CLS	7.2.5.6	x	
8	CLS service, first transmissions	7.2.5.6	x	
9	change dummy bearer position	7.2.5.6	x	
10	extended system info., A-field procedure	7.2.5.6	c7101	
11	extended system info., B-field procedure	7.2.5.6	c7102	

c7101: IF 36/3 THEN m ELSE n/a

c7102: IF 36/4 THEN m ELSE n/a

A.7.5.7 Encryption control (EC) messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.72: Encryption control (EC) messages (Sending P to F)

Prerequisite: A.60/6				
Item	MAC control (M_T) messages - Encryption control	Ref.	Status	Supp.
1	Encryption start request	7.2.5.7	m	
2	Encryption start confirm	7.2.5.7	m	
3	Encryption start grant	7.2.5.7	m	
4	Encryption stop request	7.2.5.7	o	
5	Encryption stop confirm	7.2.5.7	o	
6	Encryption stop grant	7.2.5.7	o	

Table A.73: Encryption control (EC) messages (Receipt F to P)

Prerequisite: A.61/6				
Item	MAC control (M _T) messages - Encryption control	Ref.	Status	Supp.
1	Encryption start request	7.2.5.7	m	
2	Encryption start confirm	7.2.5.7	m	
3	Encryption start grant	7.2.5.7	m	
4	Encryption stop request	7.2.5.7	o	
5	Encryption stop confirm	7.2.5.7	o	
6	Encryption stop grant	7.2.5.7	o	

A.7.6 B - Field Messages

A.7.6.1 B - Field Messages supported

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.74: B - Field messages supported (Sending P to F)

Prerequisite: A.9/5 OR A.10/2 OR A.10/3				
Item	B - Field messages	Ref.	Status	Support
1	X001 - Advanced connection control	7.3.1	m	
2	X010 - Null message	7.3.1	m	
3	X011 - Quality control	7.3.1	m	
4	X100 - Extended system information	7.3.1	m	
5	X101 - GF channel data packet	7.3.1	m	
6	X111 - B-field escape	7.3.1	m	

Table A.75: B - Field messages supported (Receipt F to P)

Prerequisite: A.9/5 OR A.10/2 OR A.10/3				
Item	B - Field messages	Ref.	Status	Support
1	X001 - Advanced connection control	7.3.1	m	
2	X010 - Null message	7.3.1	m	
3	X011 - Quality control	7.3.1	m	
4	X100 - Extended system information	7.3.1	m	
5	X101 - GF channel data packet	7.3.1	m	
6	X111 - B-field escape	7.3.1	m	

A.7.6.2 B - Field Advanced connection control messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.76: B - Field Advanced connection control messages (Sending P to F)

Prerequisite: A.74/1				
Item	B - Field Advanced CC messages	Ref.	Status	Support
1	Access request	7.3.3.2	m	
2	Bearer handover request	7.3.3.2	m	
3	Connection handover request	7.3.3.2	m	
4	Unconfirmed access request	7.3.3.2	o	
5	Bearer confirm	7.3.3.3	m	
6	Wait	7.3.3.4	m	
7	Attributes_B.request	7.3.3.5	m	
8	Attributes_B.confirm	7.3.3.5	m	
9	Bandwidth_B.request	7.3.3.6	m	
10	Bandwidth_B.confirm	7.3.3.6	m	
11	Channel list	7.3.3.7	m	
12	Unconfirmed dummy	7.3.3.8	o	
13	Unconfirmed handover	7.3.3.9	o	
14	Release	7.3.3.10	m	

Table A.77: B - Field Advanced connection control messages (Receipt F to P)

Prerequisite: A.75/1				
Item	B - Field Advanced CC messages	Ref.	Status	Support
1	Access request	7.3.3.2	m	
2	Bearer handover request	7.3.3.2	m	
3	Connection handover request	7.3.3.2	m	
4	Unconfirmed access request	7.3.3.2	o	
5	Bearer confirm	7.3.3.3	m	
6	Wait	7.3.3.4	m	
7	Attributes_B.request	7.3.3.5	m	
8	Attributes_B.confirm	7.3.3.5	m	
9	Bandwidth_B.request	7.3.3.6	m	
10	Bandwidth_B.confirm	7.3.3.6	m	
11	Channel list	7.3.3.7	m	
12	Unconfirmed dummy	7.3.3.8	o	
13	Unconfirmed handover	7.3.3.9	o	
14	Release	7.3.3.10	m	

A.7.6.3 B - Field - Null messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.78: B - Field - Null messages (Sending P to F)

Prerequisite: A.74/2				
Item	B - Field - Null messages	Ref.	Status	Support
1	No C _F or CL _F data in the B-field	7.3.4	m	
2	One B-subfield contains C _F or CL _F data	7.3.4	c7801	
3	Two B-subfield contain C _F or CL _F data	7.3.4	c7802	
4	Three B-subfield contain C _F or CL _F data	7.3.4	c7802	
5	Four B-subfield contain C _F or CL _F data	7.3.4	c7802	
6	Five B-subfield contain C _F or CL _F data	7.3.4	c7803	
7	Six B-subfield contain C _F or CL _F data	7.3.4	c7803	
8	Seven B-subfield contain C _F or CL _F data	7.3.4	c7803	
9	Eight B-subfield contain C _F or CL _F data	7.3.4	c7803	
10	Nine B-subfield contain C _F or CL _F data	7.3.4	c7803	

c7801: IF A.22/1 AND (A.23/1 OR A.23/2 OR A.23/3) THEN m ELSE n/a

c7802: IF A.22/1 AND (A.23/1 OR A.23/2) THEN m ELSE n/a

c7803: IF A.22/1 AND A.23/1 THEN m ELSE n/a

Table A.79: B - Field - Null messages (Receipt F to P)

Prerequisite: A.75/2				
Item	B - Field - Null messages	Ref.	Status	Support
1	No C _F or CL _F data in the B-field	7.3.4	m	
2	One B-subfield contains C _F or CL _F data	7.3.4	c7901	
3	Two B-subfield contain C _F or CL _F data	7.3.4	c7902	
4	Three B-subfield contain C _F or CL _F data	7.3.4	c7902	
5	Four B-subfield contain C _F or CL _F data	7.3.4	c7902	
6	Five B-subfield contain C _F or CL _F data	7.3.4	c7903	
7	Six B-subfield contain C _F or CL _F data	7.3.4	c7903	
8	Seven B-subfield contain C _F or CL _F data	7.3.4	c7903	
9	Eight B-subfield contain C _F or CL _F data	7.3.4	c7903	
10	Nine B-subfield contain C _F or CL _F data	7.3.4	c7903	

c7901: IF A.22/1 AND (A.23/1 OR A.23/2 OR A.23/3) THEN m ELSE n/a

c7902: IF A.22/1 AND (A.23/1 OR A.23/2) THEN m ELSE n/a

c7903: IF A.22/1 AND A.23/1 THEN m ELSE n/a

A.7.6.4 B - Field - Quality control messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.80: B - Field - Quality control messages (Sending P to F)

Prerequisite: A.74/3				
Item	Quality control message	Ref.	Status	Support
1	Antenna switch single bearer	7.3.5.2	m	
2	Antenna switch all bearers	7.3.5.2	m	
3	Bearer handover	7.3.5.2	m	
4	Connection handover	7.3.5.2	m	
5	Frequency control single bearer	7.3.5.2	m	
6	Frequency control all bearers	7.3.5.2	m	
7	Reset request first TDMA half frame	7.3.5.3	c8001	
8	Reset request second TDMA half frame	7.3.5.3	c8001	
9	Reset request both TDMA half frames	7.3.5.3	c8001	
10	Reset confirm first TDMA half frame	7.3.5.3	c8001	
11	Reset confirm second TDMA half frame	7.3.5.3	c8001	
12	Reset confirm both TDMA half frames	7.3.5.3	c8001	
13	MOD2 ACK	7.3.5.4	m	

c8001: IF A.12/4 OR A.13/3 THEN m ELSE x

Table A.81: B - Field - Quality control messages (Receipt F to P)

Prerequisite: A.75/3				
Item	Quality control message	Ref.	Status	Support
1	Antenna switch single bearer	7.3.5.2	m	
2	Antenna switch all bearers	7.3.5.2	m	
3	Bearer handover	7.3.5.2	m	
4	Connection handover	7.3.5.2	m	
5	Frequency control single bearer	7.3.5.2	m	
6	Frequency control all bearers	7.3.5.2	m	
7	Reset request first TDMA half frame	7.3.5.3	c8101	
8	Reset request second TDMA half frame	7.3.5.3	c8101	
9	Reset request both TDMA half frames	7.3.5.3	c8101	
10	Reset confirm first TDMA half frame	7.3.5.3	c8101	
11	Reset confirm second TDMA half frame	7.3.5.3	c8101	
12	Reset confirm both TDMA half frames	7.3.5.3	c8101	
13	MOD2 ACK	7.3.5.4	m	

c8101: IF A.12/4 OR A.13/3 THEN m ELSE x

A.7.6.5 B - Field - GF-channel data packet messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

Table A.82: B - Field - GF-channel data packet messages (Sending P to F)

Prerequisite: A.74/5				
Item	GF-channel data packet	Ref.	Status	Support
1	No C _F data in the B-field	7.3.7	m	
2	One B-subfield contains C _F data	7.3.7	c8201	
3	Two B-subfield contain C _F data	7.3.7	c8202	
4	Three B-subfield contain C _F data	7.3.7	c8202	
5	Four B-subfield contain C _F data	7.3.7	c8202	
6	Five B-subfield contain C _F data	7.3.7	c8203	
7	Six B-subfield contain C _F data	7.3.7	c8203	
8	Seven B-subfield contain C _F data	7.3.7	c8203	
9	Eight B-subfield contain C _F data	7.3.7	c8203	
10	Nine B-subfield contain C _F data	7.3.7	c8203	

c8201: IF A.22/1 AND (A.23/1 OR A.23/2 OR A.23/3) THEN m ELSE n/a

c8202: IF A.22/1 AND (A.23/1 OR A.23/2) THEN m ELSE n/a

c8203: IF A.22/1 AND A.23/1 THEN m ELSE n/a

Table A.83: B - Field - GF-channel data packet messages (Receipt F to P)

Prerequisite: A.75/5				
Item	GF-channel data packet	Ref.	Status	Support
1	No C _F data in the B-field	7.3.7	m	
2	One B-subfield contains C _F data	7.3.7	c8301	
3	Two B-subfield contain C _F data	7.3.7	c8302	
4	Three B-subfield contain C _F data	7.3.7	c8302	
5	Four B-subfield contain C _F data	7.3.7	c8302	
6	Five B-subfield contain C _F data	7.3.7	c8303	
7	Six B-subfield contain C _F data	7.3.7	c8303	
8	Seven B-subfield contain C _F data	7.3.7	c8303	
9	Eight B-subfield contain C _F data	7.3.7	c8303	
10	Nine B-subfield contain C _F data	7.3.7	c8303	

c8301: IF A.22/1 AND (A.23/1 OR A.23/2 OR A.23/3) THEN m ELSE n/a

c8302: IF A.22/1 AND (A.23/1 OR A.23/2) THEN m ELSE n/a

c8303: IF A.22/1 AND A.23/1 THEN m ELSE n/a

A.8 MAC messages format and field value

A.8.1 A - field identities information (N_T) message

Table A.84: NT - Identities Information (Sending P to F)

Prerequisite: 55/1						
Item	NT - Identities Information	Ref.	Status	Supp.	Value Allowed	Value Supported
1	E	7.2.2	m		'0'B, '1'B	
2	PARI	7.2.2	m		31 or 36 bits value	
3	RPN	7.2.2	m		3 or 8 bits value	

Table A.85: NT - Identities Information (Receipt F to P)

Prerequisite: 56/1						
Item	NT - Identities Information	Ref.	Status	Supp.	Value Allowed	Value Supported
1	E	7.2.2	m		'0'B, '1'B	
2	PARI	7.2.2	m		31 or 36 bits value	
3	RPN	7.2.2	m		3 or 8 bits value	

A.8.2 A - field system information (Q_T) messages

A.8.2.1 QT - Static system information

Table A.86: QT - Static system information (Receipt F to P)

Prerequisite: 57/1						
Item	QT - Static system information	Ref.	Status	Supp.	Value Allowed	Value Supported
1	Q_T header	7.2.3.2.1	m		'000'B	
2	Normal/reverse	7.2.3.2.2	m		'0'B, '1'B	
3	Slot number	7.2.3.2.3	m		0000'B .. '1011'B	
4	Start position	7.2.3.2.4	m		'00", '10'B	
5	Escape bit	7.2.3.2.5	m		'0'B, '1'B	
6	Number of tranceivers	7.2.3.2.6	m		'00'B .. '11'B	
7	Extended RF carrier	7.2.3.2.7	m		'0'B, '1'B	
8	RF carriers available	7.2.3.2.8	m		10 bits value	
9	Spr 1	7.2.3.2.9	m		'00'B	
10	Carrier number	7.2.3.2.10	m		000000'B .. '001001'B	
11	Spr 2	7.2.3.2.11	m		'00'B	
12	PSCN	7.2.3.2.12	m		'000000'B .. '001001'B	

A.8.2.2 QT - Extended RF carrier information

Table A.87: QT - Extended RF carrier information (Receipt F to P)

Prerequisite: 57/2						
Item	QT - Extended RF carrier information	Ref.	Status	Supp.	Value Allowed	Value Supported
1	Q_T header	7.2.3.3.1	m		'0010'B	
2	Reserved field	7.2.3.3.1	m		28 bits	
3	Spr	7.2.3.3.1	m		'00'B	
4	Number of RF carriers	7.2.3.3.1	m		6 bits value	

A.8.2.3 QT - Fixed part capability

Table A.88: QT - Fixed part capability (Receipt F to P)

Prerequisite: 57/3						
Item	QT - Fixed part capability	Ref.	Status	Supp.	Value Allowed	Value Supported
1	QT header	7.2.3.4.2	m		'0011'B	
2	Extended FP info.	7.2.3.4.2	m		'0'B, '1'B	
3	Reserved	7.2.3.4.2	m		1 bit	
4	Reserved	7.2.3.4.2	m		1 bit	
5	Double slot	7.2.3.4.2	m		'0'B, '1'B	
6	Half slot	7.2.3.4.2	m		'0'B, '1'B	
7	Full slot	7.2.3.4.2	m		'0'B, '1'B	
8	Frequency control	7.2.3.4.2	m		'0'B, '1'B	
9	Page repetition	7.2.3.4.2	m		'0'B, '1'B	
10	Dummy bearer setup	7.2.3.4.2	m		'0'B, '1'B	
11	C/L uplink	7.2.3.4.2	m		'0'B, '1'B	
12	C/L downlink	7.2.3.4.2	m		'0'B, '1'B	
13	Basic A-field setup	7.2.3.4.2	m		'0'B, '1'B	
14	Adv. A-field setup	7.2.3.4.2	m		'0'B, '1'B	
15	B-field setup	7.2.3.4.2	m		'0'B, '1'B	
16	CF messages	7.2.3.4.2	m		'0'B, '1'B	
17	IN minimum delay	7.2.3.4.2	m		'0'B, '1'B	
18	IN normal delay	7.2.3.4.2	m		'0'B, '1'B	
19	IP error detection	7.2.3.4.2	m		'0'B, '1'B	
20	IP error correction	7.2.3.4.2	m		'0'B, '1'B	
21	Multibearer connection	7.2.3.4.2	m		'0'B, '1'B	
22	Higher layer info.	7.2.3.4.2	m		16 bits value	

A.8.2.4 QT - Extended fixed part capabilities

Table A.89: QT - Extended fixed part capabilities (Receipt F to P)

Prerequisite: 57/4						
Item	QT - Extended fixed part capabilities	Ref.	Status	Supp.	Value Allowed	Value Supported
1	QT header	7.2.3.5.1	m		'0100'B	
2	Reserved field	7.2.3.5.2	m		36 bits value	

A.8.2.5 QT - Secondary access rights identities

Table A.90: QT - Secondary access rights identities (Receipt F to P)

Prerequisite: 57/5						
Item	QT - Secondary access rights identities	Ref.	Status	Supp.	Value	Value Supported
1	QT header	7.2.3.6.1			'0101'B	
2	SARI message	7.2.3.6.2			36 bits value	

A.8.2.6 QT - Multi-frame number

Table A.91: QT - Multi-frame number (Receipt F to P)

Prerequisite: 57/6						
Item	QT - Multi-frame number	Ref.	Status	Supp.	Value Allowed	Value Supported
1	QT header	7.2.3.7.1	m		'0110'B	
2	Spare	7.2.3.7.1	m		'1111 0000 1111'B	
3	Multiframe number	7.2.3.7.2	m		24 bits value	

A.8.2.7 QT - escape

Table A.92: QT - escape (Receipt F to P)

Prerequisite: 57/7						
Item	QT - escape	Ref.	Status	Supp.	Value Allowed	Value Supported
1	QT header	7.2.3.8.1	m		'0111'B	
2	Proprietary mess.	7.2.3.8.2	m		36 bits value	

A.8.3 A - field paging tail (P_T) messages

A.8.3.1 P_T message - Full page

Table A.93: P_T message - Full page (Receipt F to P)

Prerequisite: 58/1						
Item	P_T message - Full page	Ref.	Status	Supp.	Value Allowed	Value Supported
1	Extend flag	7.2.4.2.2	m		'0'B, '1'B	
2	B_S SDU length	7.2.4.2.3	m		'010'B	
3	36 bits B_S data	7.2.4.1.1	m		36 bits value	

A.8.3.2 P_T message - Long page

Table A.94: P_T message - Long page (Receipt F to P)

Prerequisite: 58/2						
Item	P_T message - Long page	Ref.	Status	Supp.	Value Allowed	Value Supported
1	Extend flag	7.2.4.2.2	m		'0'B, '1'B	
2	B_S SDU length	7.2.4.2.3	m		'100'B .. '111'B	
3	36 bits B_S data	7.2.4.1.1	m		36 bits value	

A.8.3.5.3 MAC info. element - Other bearer

Table A.99: MAC info. element - Other bearer (Receipt F to P)

Prerequisite: 59/3						
Item	MAC info. element - Other bearer	Ref.	Status	Supp.	Value Allowed	Value Supported
1	Slot number	7.2.3.2.3	m		'0000'B .. '1011'B	
2	Start position	7.2.3.2.4	m		'00'B, '10'B	
3	Carrier number	7.2.3.2.10	m		'000000'B .. '001001'B	

A.8.3.5.4 MAC info. element - Recommended other bearer

Table A.100: MAC info. element - Recommended other bearer (Receipt F to P)

Prerequisite: 59/4						
Item	MAC info. element - Recommended other bearer	Ref.	Status	Supp.	Value Allowed	Value Supported
1	Slot number	7.2.3.2.3	m		'0000'B .. '1011'B	
2	Start position	7.2.3.2.4	m		'00'B, '10'B	
3	Carrier number	7.2.3.2.10	m		'000000'B .. '001001'B	

A.8.3.5.5 MAC info. element - Good RFP bearer

Table A.101: MAC info. element - Good RFP bearer (Receipt F to P)

Prerequisite: 59/5						
Item	MAC info. element - Good RFP bearer	Ref.	Status	Supp.	Value Allowed	Value Supported
1	Slot number	7.2.3.2.3	m		'0000'B .. '1011'B	
2	Start position	7.2.3.2.4	m		'00'B, '10'B	
3	Carrier number	7.2.3.2.10	m		'000000'B .. '001001'B	

A.8.3.5.6 MAC info. element - Dummy or C/L bearer position

Table A.102: MAC info. element - Dummy or C/L bearer position (Receipt F to P)

Prerequisite: 59/6						
Item	MAC info. element - Dummy or C/L bearer position	Ref.	Status	Supp.	Value Allowed	Value Supported
1	Slot number	7.2.3.2.3	m		'0000'B .. '1011'B	
2	Start position	7.2.3.2.4	m		'00'B, '10'B	
3	Carrier number	7.2.3.2.10	m		'000000'B .. '001001'B	

A.8.3.5.7 MAC info. element - RFP identity

Table A.103: MAC info. element - RFP identity (Receipt F to P)

Prerequisite: 59/7						
Item	MAC info. element - RFP identity	Ref.	Status	Supp.	Value Allowed	Value Supported
1	12 LSB bits of RFPI	7.2.4.3.5	m		12 bits value	

A.8.3.5.8 MAC info. element - Escape

Table A.104: MAC info. element - Escape (Receipt F to P)

Prerequisite: 59/8						
Item	MAC info. element - Escape	Ref.	Status	Supp.	Value Allowed	Value Supported
1	12 bits proprietary	7.2.4.3.6	m		12 bits value	

A.8.3.5.9 MAC info. element - Dummy or C/L bearer marker

Table A.105: MAC info. element - Dummy or C/L bearer marker (Receipt F to P)

Prerequisite: 59/9						
Item	MAC info. element - Dummy or C/L bearer marker	Ref.	Status	Supp.	Value Allowed	Value Supported
1	Marker	7.2.4.3.7	m		'1111 0000 1111'B	

A.8.3.5.10 MAC info. element - Bearer handover information

Table A.106: MAC info. element - Bearer handover information (Receipt F to P)

Prerequisite: 59/10						
Item	MAC info. element - Bearer handover information	Ref.	Status	Supp.	Value Allowed	Value Supported
1	Info type	7.2.4.3.8	m		'0000'B .. '0011'B	
2	Parameter	7.2.4.3.8	m		'0000 1111'B or 12 bits 'bit mask'	

A.8.3.5.11 MAC info. element - RFP status

Table A.107: MAC info. element - RFP status (Receipt F to P)

Prerequisite: 59/11						
Item	MAC info. element - RFP status	Ref.	Status	Supp.	Value Allowed	Value Supported
1	RFP status	7.2.4.3.9	m		'0000'B .. '0011'B	
2	Spare	7.2.4.3.9	m		'0000 1111'B	

A.8.4 A - field MAC control (M_T) messages

A.8.4.1 Basic connection control messages

A.8.4.1.1 Basic CC - access request

Table A.108: Basic CC - access request (Sending P to F)

Prerequisite: 62/1						
Item	Basic CC access request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M_T header	7.2.5.2.2	m		'0000'B	
2	Command	7.2.5.2.2	m		'0000'B	
3	FMID	7.2.5.2.2	m		12 bits value	
4	PMID	7.2.5.2.2	m		20 bits value	

A.8.4.1.2 Basic CC - bearer handover request

Table A.109: Basic CC - bearer handover request (Sending P to F)

Prerequisite: 62/2						
Item	Basic CC bearer handover request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M_T header	7.2.5.2.2	m		'0000'B	
2	Command	7.2.5.2.2	m		'0001'B	
3	FMID	7.2.5.2.2	m		12 bits value	
4	PMID	7.2.5.2.2	m		20 bits value	

A.8.4.1.3 Basic CC - connection handover request

Table A.110: Basic CC - connection handover request (Sending P to F)

Prerequisite: 62/3						
Item	Basic CC connection handover request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M_T header	7.2.5.2.2	m		'0000'B	
2	Command	7.2.5.2.2	m		'0010'B	
3	FMID	7.2.5.2.2	m		12 bits value	
4	PMID	7.2.5.2.2	m		20 bits value	

A.8.4.1.4 Basic CC - unconfirmed access request

Table A.111: Basic CC - unconfirmed access request (Sending P to F)

Prerequisite: 62/4						
Item	Basic CC unconfirmed access request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M_T header	7.2.5.2.2	m		'0000'B	
2	Command	7.2.5.2.2	m		'0011'B	
3	FMID	7.2.5.2.2	m		12 bits value	
4	PMID	7.2.5.2.2	m		20 bits value	

A.8.4.1.5 Basic CC - bearer confirm

Table A.112: Basic CC - bearer confirm (Receipt F to P)

Prerequisite: 63/5						
Item	Basic CC bearer confirm	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.2.2	m		'0000'B	
2	Command	7.2.5.2.2	m		'0100'B	
3	FMID	7.2.5.2.2	m		12 bits value	
4	PMID	7.2.5.2.2	m		20 bits value	

A.8.4.1.6 Basic CC - wait

Table A.113: Basic CC - wait (Sending P to F)

Prerequisite: 62/6						
Item	Basic CC wait	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.2.2	m		'0000'B	
2	Command	7.2.5.2.2	m		'1111'B	
3	FMID	7.2.5.2.2	m		12 bits value	
4	PMID	7.2.5.2.3	m		20 bits value, '11110000 11110000 1111'B	

Table A.114: Basic CC - wait (Receipt F to P)

Prerequisite: 63/6						
Item	Basic CC wait	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.2.2	m		'0000'B	
2	Command	7.2.5.2.2	m		'1111'B	
3	FMID	7.2.5.2.2	m		12 bits value	
4	PMID	7.2.5.2.3	m		20 bits value, '11110000 11110000 1111'B	

A.8.4.1.7 Basic CC - release

Table A.115: Basic CC - release (Sending P to F)

Prerequisite: 62/7						
Item	Basic CC release	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.2.2	m		'0000'B	
2	Command	7.2.5.2.2	m		'1111'B	
3	FMID	7.2.5.2.2	m		12 bits value	
4	PMID	7.2.5.2.2	m		20 bits value	

Table A.116: Basic CC - release (Receipt F to P)

Prerequisite: 63/7						
Item	Basic CC release	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.2.2	m		'0000'B	
2	Command	7.2.5.2.2	m		'1111'B	
3	FMID	7.2.5.2.2	m		12 bits value	
4	PMID	7.2.5.2.2	m		20 bits value	

A.8.4.2 MAC layer test messages**A.8.4.2.1 MAC test - force transmit****Table A.117: MAC test - force transmit (Sending P to F)**

Prerequisite: 64/1						
Item	MAC test - force transmit	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.4.2	m		'0010'B	
2	Command	7.2.5.4.2	m		'0000'B	
3	Spr 1	7.2.5.4.2	m		'0101010'B	
4	KP	7.2.5.4.2	m		'0'B, '1'B	
5	Handover disable	7.2.5.4.2	m		'0'B, '1'B	
6	Spr2	7.2.5.4.2	m		'000'B	
7	Slot number	7.2.5.4.2	m		'0000'B .. '1011'B	
8	Start position	7.2.5.4.2	m		'0'B, '10'B	
9	Carrier number	7.2.5.4.2	m		'000000'B .. '001001'B	
10	Spare	7.2.5.4.2	m		'0000 1111"	

Table A.118: MAC test - force transmit (Receipt F to P)

Prerequisite: 65/1						
Item	MAC test - force transmit	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.4.2	m		'0010'B	
2	Command	7.2.5.4.2	m		'0000'B	
3	Spr 1	7.2.5.4.2	m		'0101010'B	
4	KP	7.2.5.4.2	m		'0'B, '1'B	
5	Handover disable	7.2.5.4.2	m		'0'B, '1'B	
6	Spr2	7.2.5.4.2	m		'000'B	
7	Slot number	7.2.5.4.2	m		'0000'B .. '1011'B	
8	Start position	7.2.5.4.2	m		'0'B, '10'B	
9	Carrier number	7.2.5.4.2	m		'000000'B .. '001001'B	
10	Spare	7.2.5.4.2	m		'0000 1111"	

A.8.4.2.2 MAC test - loopback data

Table A.119: MAC test - loopback data (Sending P to F)

Prerequisite: 64/2						
Item	MAC test - loopback data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.4.3	m		'0010'B	
2	Command	7.2.5.4.3	m		'0001'B	
3	Loopback data field	7.2.5.4.3	m		32 bits value	

Table A.120: MAC test - loopback data (Receipt F to P)

Prerequisite: 65/2						
Item	MAC test - loopback data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.4.3	m		'0010'B	
2	Command	7.2.5.4.3	m		'0001'B	
3	Loopback data field	7.2.5.4.3	m		32 bits value	

A.8.4.2.3 MAC test - defeat antenna diversity

Table A.121: MAC test - defeat antenna diversity (Sending P to F)

Prerequisite: 64/3						
Item	MAC test - defeat antenna diversity	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.4.4	m		'0010'B	
2	Command	7.2.5.4.4	m		'0010'B	
3	Defeat flag	7.2.5.4.4	m		'0'B, '1'B	
4	Antenna number	7.2.5.4.4	m		'000'B .. '111'B	
5	Spr	7.2.5.4.4	m		'1111'B	
6	Spare 1	7.2.5.4.4	m		'0000 1111"	
7	Spare 2	7.2.5.4.4	m		'0000 1111"	
8	Spare 3	7.2.5.4.4	m		'0000 1111"	

A.8.4.2.4 MAC test - force bearer handover

Table A.122.: MAC test - force bearer handover (Sending P to F)

Prerequisite: 64/4						
Item	MAC test - force bearer handover	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.4.5	m		'0010'B	
2	Command	7.2.5.4.5	m		'0011'B	
3	Spare 1	7.2.5.4.5	m		'0000 1111"	
4	Spare 2	7.2.5.4.5	m		'0000 1111"	
5	Spare 3	7.2.5.4.5	m		'0000 1111"	
6	Spare 4	7.2.5.4.5	m		'0000 1111"	

A.8.4.2.7 MAC test - clear test modes

Table A.128: MAC test - clear test modes (Sending P to F)

Prerequisite: 64/7						
Item	MAC test - clear test modes	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.4.8	m		'0010'B	
2	Command	7.2.5.4.8	m		'1111'B	
3	Spare 1	7.2.5.4.8	m		'0000 1111"	
4	Spare 2	7.2.5.4.8	m		'0000 1111"	
5	Spare 3	7.2.5.4.8	m		'0000 1111"	
6	Spare 4	7.2.5.4.8	m		'0000 1111"	

Table A.129: MAC test - clear test modes (Receipt F to P)

Prerequisite: 65/7						
Item	MAC test - clear test modes	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.4.8	m		'0010'B	
2	Command	7.2.5.4.8	m		'1111'B	
3	Spare 1	7.2.5.4.8	m		'0000 1111"	
4	Spare 2	7.2.5.4.8	m		'0000 1111"	
5	Spare 3	7.2.5.4.8	m		'0000 1111"	
6	Spare 4	7.2.5.4.8	m		'0000 1111"	

A.8.4.3 Advanced connection control messages

A.8.4.3.1 Advanced CC - access request

Table A.130: Advanced CC - access request (Sending P to F)

Prerequisite: 66/1						
Item	Advanced CC - access request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.2	m		'0001'B	
2	Command	7.2.5.3.2	m		'0000'B	
3	FMID	7.2.5.3.2	m		12 bits value	
4	PMID	7.2.5.3.2	m		20 bits value	

Table A.131: Advanced CC - access request (Receipt F to P)

Prerequisite: 67/1						
Item	Advanced CC - access request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.2	m		'0001'B	
2	Command	7.2.5.3.2	m		'0000'B	
3	FMID	7.2.5.3.2	m		12 bits value	
4	PMID	7.2.5.3.2	m		20 bits value	

A.8.4.3.2 Advanced CC - bearer handover request**Table A.132: Advanced CC - bearer handover request (Sending P to F)**

Prerequisite: 66/2						
Item	Advanced CC - bearer handover request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.3	m		'0001'B	
2	Command	7.2.5.3.3	m		'0001'B	
3	FMID	7.2.5.3.3	m		12 bits value	
4	PMID	7.2.5.3.3	m		20 bits value	

A.8.4.3.3 Advanced CC - connection handover request**Table A.133: Advanced CC - connection handover request (Sending P to F)**

Prerequisite: 66/3						
Item	Advanced CC - connection handover request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.4	m		'0001'B	
2	Command	7.2.5.3.4	m		'0010'B	
3	FMID	7.2.5.3.4	m		12 bits value	
4	PMID	7.2.5.3.4	m		20 bits value	

Table A.134: Advanced CC - connection handover request (Receipt F to P)

Prerequisite: 67/3						
Item	Advanced CC - connection handover request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.4	m		'0001'B	
2	Command	7.2.5.3.4	m		'0010'B	
3	FMID	7.2.5.3.4	m		12 bits value	
4	PMID	7.2.5.3.4	m		20 bits value	

A.8.4.3.4 Advanced CC - unconfirmed access request**Table A.135: Advanced CC - unconfirmed access request (Sending P to F)**

Prerequisite: 66/4						
Item	Advanced CC - unconfirmed access request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.5	m		'0001'B	
2	Command	7.2.5.3.5	m		'0011'B	
3	FMID	7.2.5.3.5	m		12 bits value	
4	PMID	7.2.5.3.5	m		20 bits value	

Table A.136: Advanced CC - unconfirmed access request (Receipt F to P)

Prerequisite: 67/4						
Item	Advanced CC - unconfirmed access request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.5	m		'0001'B	
2	Command	7.2.5.3.5	m		'0011'B	
3	FMID	7.2.5.3.5	m		12 bits value	
4	PMID	7.2.5.3.5	m		20 bits value	

A.8.4.3.5 Advanced CC - bearer confirm

Table A.137: Advanced CC - bearer confirm (Sending P to F)

Prerequisite: 66/5						
Item	Advanced CC - bearer confirm	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.6	m		'0001'B	
2	Command	7.2.5.3.6	m		'0100'B	
3	FMID	7.2.5.3.6	m		12 bits value	
4	PMID	7.2.5.3.6	m		20 bits value	

Table A.138: Advanced CC - bearer confirm (Receipt F to P)

Prerequisite: 67/5						
Item	Advanced CC - bearer confirm	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.6	m		'0001'B	
2	Command	7.2.5.3.6	m		'0100'B	
3	FMID	7.2.5.3.6	m		12 bits value	
4	PMID	7.2.5.3.6	m		20 bits value	

A.8.4.3.6 Advanced CC - wait

Table A.139: Advanced CC - wait (Sending P to F)

Prerequisite: 66/6						
Item	Advanced CC - wait	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.7	m		'0001'B	
2	Command	7.2.5.3.7	m		'1111'B	
3	FMID	7.2.5.3.7	m		12 bits value	
4	PMID	7.2.5.3.7	m		20 bits value, '11110000 1111'B	

Table A.140: Advanced CC - wait (Receipt F to P)

Prerequisite: 67/6						
Item	Advanced CC - wait	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.7	m		'0001'B	
2	Command	7.2.5.3.7	m		'1111'B	
3	FMID	7.2.5.3.7	m		12 bits value	
4	PMID	7.2.5.3.7	m		20 bits value, '11110000 11110000 1111'B	

A.8.4.3.7 Advanced CC - Attributes_T request**Table A.141: Advanced CC - Attributes_T request (Sending P to F)**

Prerequisite: 66/7						
Item	Advanced CC - Attributes_T request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.8	m		'0001'B	
2	Command	7.2.5.3.8	m		'0110'B	
3	ECN	7.2.5.3.8	m		4 bits value	
4	LBN	7.2.5.3.8	m		4 bits value	
5	Connection type	7.2.5.3.8	m		'00'B .. '11'B	
6	Service type	7.2.5.3.8	m		'000'B .. '100'B	
7	Maximum lifetime	7.2.5.3.8	m		3 bits value	
8	Slot type	7.2.5.3.8	m		'0000'B .. '0010'B	
9	CF support flag	7.2.5.3.8	m		'0B, '1B	
10	Spr	7.2.5.3.8	m		'111'B	
11	Spare	7.2.5.3.8	m		'0000 1111'B	

Note to item 7: Unless the service is Ip_error_correction, this parameter is set to '000'.

Table A.142: Advanced CC - Attributes_T request (Receipt F to P)

Prerequisite: 67/7						
Item	Advanced CC - Attributes_T request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.3.8	m		'0001'B	
2	Command	7.2.5.3.8	m		'0110'B	
3	ECN	7.2.5.3.8	m		4 bits value	
4	LBN	7.2.5.3.8	m		4 bits value	
5	Connection type	7.2.5.3.8	m		'00'B .. '11'B	
6	Service type	7.2.5.3.8	m		'000'B .. '100'B	
7	Maximum lifetime	7.2.5.3.8	m		3 bits value	
8	Slot type	7.2.5.3.8	m		'0000'B .. '0010'B	
9	CF support flag	7.2.5.3.8	m		'0B, '1B	
10	Spr	7.2.5.3.8	m		'111'B	
11	Spare	7.2.5.3.8	m		'0000 1111'B	

Note to item 7: Unless the service is Ip_error_correction, this parameter is set to '000'.

A.8.4.4 Quality control messages

A.8.4.4.1 QC - antenna switch single bearer request

Table A.157: QC - antenna switch single bearer request (Sending P to F)

Prerequisite: 68/1						
Item	QC - antenna switch single bearer request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.5	m		'0011'B	
2	Command	7.2.5.5	m		'0000'B	
3	spr	7.2.5.5	m		'0000'B	
4	LBN	7.2.5.5	m		4 bits value	
5	param_2	7.2.5.5	m		'0000 1111'B	
6	Spare 1	7.2.5.5	m		'0000 1111'B	
7	Spare 2	7.2.5.5	m		'0000 1111'B	

Table A.158: QC - antenna switch single bearer request (Receipt F to P)

Prerequisite: 69/1						
Item	QC - antenna switch single bearer request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.5	m		'0011'B	
2	Command	7.2.5.5	m		'0000'B	
3	spr	7.2.5.5	m		'0000'B	
4	LBN	7.2.5.5	m		4 bits value	
5	param_2	7.2.5.5	m		'0000 1111'B	
6	Spare 1	7.2.5.5	m		'0000 1111'B	
7	Spare 2	7.2.5.5	m		'0000 1111'B	

A.8.4.4.2 QC - antenna switch all bearers request

Table A.159: QC - antenna switch all bearers request (Sending P to F)

Prerequisite: 68/2						
Item	QC - antenna switch all bearers request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.5	m		'0011'B	
2	Command	7.2.5.5	m		'0001'B	
3	RPN	7.2.5.5	m		8 bits value	
4	param_2	7.2.5.5	m		'0000 1111'B	
5	Spare 1	7.2.5.5	m		'0000 1111'B	
6	Spare 2	7.2.5.5	m		'0000 1111'B	

A.8.4.5.4 BCL - CLF, last transmissions, half slot

Table A.172: BCL - CLF, last transmissions, half slot (Sending P to F)

Prerequisite: 70/4						
Item	BCL - CLF, last transmissions, half slot	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.6	m		'0100'B	
2	Command	7.2.5.6	m		'0100'B	
3	FMID	7.2.5.6	m		12 bits value	
4	PMID	7.2.5.6	m		20 bits value	

A.8.4.5.5 BCL - CLF, last transmissions, full slot

Table A.173: BCL - CLF, last transmissions, full slot (Sending P to F)

Prerequisite: 70/5						
Item	BCL - CLF, last transmissions, full slot	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.6	m		'0100'B	
2	Command	7.2.5.6	m		'0101'B	
3	FMID	7.2.5.6	m		12 bits value	
4	PMID	7.2.5.6	m		20 bits value	

A.8.4.5.6 BCL - CLF, last transmissions, double slot

Table A.174: BCL - CLF, last transmissions, double slot (Sending P to F)

Prerequisite: 70/6						
Item	BCL - CLF, last transmissions, double slot	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.6	m		'0100'B	
2	Command	7.2.5.6	m		'0110'B	
3	FMID	7.2.5.6	m		12 bits value	
4	PMID	7.2.5.6	m		20 bits value	

A.8.4.5.7 BCL - C/L single transmissions, no CF or CLS

Table A.175: BCL - C/L single transmissions, no CF or CLS (Sending P to F)

Prerequisite: 70/7						
Item	BCL - C/L single transmissions, no CF or CLS	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.6	m		'0100'B	
2	Command	7.2.5.6	m		'1000'B	
3	FMID	7.2.5.6	m		12 bits value	
4	PMID	7.2.5.6	m		20 bits value	

A.8.4.5.8 BCL - CLS service, first transmissions

Table A.176: BCL - CLS service, first transmission (Sending P to F)

Prerequisite: 70/8						
Item	BCL - CLS service, first transmissions	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.6	m		'0100'B	
2	Command	7.2.5.6	m		'1001'B	
3	FMID	7.2.5.6	m		12 bits value	
4	PMID	7.2.5.6	m		20 bits value	

A.8.4.5.9 BCL - change dummy bearer position

Table A.177: BCL - change dummy bearer position (Sending P to F)

Prerequisite: 70/9						
Item	BCL - change dummy bearer position	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.6	m		'0100'B	
2	Command	7.2.5.6	m		'1100'B	
3	FMID	7.2.5.6	m		12 bits value	
4	PMID	7.2.5.6	m		20 bits value	

A.8.4.5.10 BCL - extended system info., A-field procedure

Table A.178: BCL - extended system info., A-field procedure (Sending P to F)

Prerequisite: 70/10						
Item	BCL - extended system info., A-field procedure	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.6	m		'0100'B	
2	Command	7.2.5.6	m		'1110'B	
3	FMID	7.2.5.6	m		12 bits value	
4	PMID	7.2.5.6	m		20 bits value	

Table A.179: BCL - extended system info., A-field procedure (Receipt F to P)

Prerequisite: 71/10						
Item	BCL - extended system info., A-field procedure	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.6	m		'0100'B	
2	Command	7.2.5.6	m		'1110'B	
3	FMID	7.2.5.6	m		12 bits value	
4	PMID	7.2.5.6	m		20 bits value	

A.8.4.5.11 BCL - extended system info., B-field procedure

Table A.180: BCL - extended system info., B-field procedure (Sending P to F)

Prerequisite: 70/11						
Item	BCL - extended system info., B-field procedure	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.6	m		'0100'B	
2	Command	7.2.5.6	m		'1111'B	
3	FMID	7.2.5.6	m		12 bits value	
4	PMID	7.2.5.6	m		20 bits value	

Table A.181: BCL - extended system info., B-field procedure (Receipt F to P)

Prerequisite: 71/11						
Item	BCL - extended system info., B-field procedure	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.6	m		'0100'B	
2	Command	7.2.5.6	m		'1111'B	
3	FMID	7.2.5.6	m		12 bits value	
4	PMID	7.2.5.6	m		20 bits value	

A.8.4.6 Encryption control (EC) messages

A.8.4.6.1 EC - Encryption start

Table A.182: EC - Encryption start request (Sending P to F)

Prerequisite: 72/1						
Item	EC- Encryption start	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.7	m		'0101'B	
2	Command	7.2.5.7	m		'0000'B	
3	FMID	7.2.5.7	m		12 bits value	
4	PMID	7.2.5.7	m		20 bits value	

Table A.183: EC - Encryption start request (Receipt F to P)

Prerequisite: 73/1						
Item	EC- Encryption start	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.7	m		'0101'B	
2	Command	7.2.5.7	m		'0000'B	
3	FMID	7.2.5.7	m		12 bits value	
4	PMID	7.2.5.7	m		20 bits value	

A.8.4.7 M_T message - B - field setupTable A.194: M_T message - B - field setup (Sending P to F)

Prerequisite: 60/7						
Item	M _T message - B - field setup	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.8	m		'0110'B	
2	36 LSB bits of RFPI	7.2.5.8	m		36 bits value	

A.8.4.8 M_T message - EscapeTable A.195: M_T message - Escape (Sending P to F)

Prerequisite: 60/8						
Item	M _T message - Escape	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.9	m		'0111'B	
2	Proprietary info.	7.2.5.9	m		36 bits value	

Table A.196: M_T message - Escape (Receipt F to P)

Prerequisite: 61/8						
Item	M _T message - Escape	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.9	m		'0111'B	
2	Proprietary info.	7.2.5.9	m		36 bits value	

A.8.4.9 M_T message - TARITable A.197: M_T message - TARI request (Sending P to F)

Prerequisite: 60/9						
Item	M _T message - TARI	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.10	m		'1000'B	
2	36 bits field	7.2.5.10	m		TARI	

Table A.198: M_T message - TARI reply (Receipt F to P)

Prerequisite: 61/9						
Item	M _T message - TARI	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _T header	7.2.5.10	m		'1000'B	
2	36 bits field	7.2.5.10	m		TARI	

A.8.5 B - Field Messages

A.8.5.1 B - Field - Advanced CC messages

A.8.5.1.1 B-field Advanced CC - Access request

Table A.199: B-field Advanced CC - Access request (Sending P to F)

Prerequisite: 76/1						
Item	B-field Advanced CC - Access request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0000'B	
3	FMID	7.3.3.2	m		12 bits value	
4	PMID	7.3.3.2	m		20 bits value	
5	ECN	7.3.3.2	m		4 bits value	
6	LBN	7.3.3.2	m		4 bits value	
7	Connection type	7.3.3.2	m		'00'B .. '11'B	
8	Service type	7.3.3.2	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.2	m		3 bits value	
10	Slot type	7.3.3.2	m		'0000'B .. '0010'B	
11	Spr	7.3.3.2	m		'1111'B	

Note to item 9: Unless the service is l_P_error_correction, this parameter is set to '000'.

Table A.200: B-field Advanced CC - Access request (Receipt F to P)

Prerequisite: 77/1						
Item	B-field Advanced CC - Access request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0000'B	
3	FMID	7.3.3.2	m		12 bits value	
4	PMID	7.3.3.2	m		20 bits value	
5	ECN	7.3.3.2	m		4 bits value	
6	LBN	7.3.3.2	m		4 bits value	
7	Connection type	7.3.3.2	m		'00'B .. '11'B	
8	Service type	7.3.3.2	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.2	m		3 bits value	
10	Slot type	7.3.3.2	m		'0000'B .. '0010'B	
11	Spr	7.3.3.2	m		'1111'B	

Note to item 9: Unless the service is l_P_error_correction, this parameter is set to '000'.

A.8.5.1.2 B-field Advanced CC - Bearer handover request

Table A.201: B-field Advanced CC - Bearer handover request (Sending P to F)

Prerequisite: 76/2						
Item	B-field Advanced CC - Bearer handover request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0001'B	
3	FMID	7.3.3.2	m		12 bits value	
4	PMID	7.3.3.2	m		20 bits value	
5	ECN	7.3.3.2	m		4 bits value	
6	LBN	7.3.3.2	m		4 bits value	
7	Connection type	7.3.3.2	m		'00'B .. '11'B	
8	Service type	7.3.3.2	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.2	m		3 bits value	
10	Slot type	7.3.3.2	m		'0000'B .. '0010'B	
11	Spr	7.3.3.2	m		'1111'B	

Note to item 9: Unless the service is Ip_error_correction, this parameter is set to '000'.

Table A.202: B-field Advanced CC - Bearer handover request (Receipt F to P)

Prerequisite: 77/2						
Item	B-field Advanced CC - Bearer handover request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0001'B	
3	FMID	7.3.3.2	m		12 bits value	
4	PMID	7.3.3.2	m		20 bits value	
5	ECN	7.3.3.2	m		4 bits value	
6	LBN	7.3.3.2	m		4 bits value	
7	Connection type	7.3.3.2	m		'00'B .. '11'B	
8	Service type	7.3.3.2	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.2	m		3 bits value	
10	Slot type	7.3.3.2	m		'0000'B .. '0010'B	
11	Spr	7.3.3.2	m		'1111'B	

Note to item 9: Unless the service is Ip_error_correction, this parameter is set to '000'.

A.8.5.1.3 B-field Advanced CC - Connection handover request

Table A.203: B-field Advanced CC - Connection handover request (Sending P to F)

Prerequisite: 76/3						
Item	B-field Advanced CC - Connection handover request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0010'B	
3	FMID	7.3.3.2	m		12 bits value	
4	PMID	7.3.3.2	m		20 bits value	
5	ECN	7.3.3.2	m		4 bits value	
6	LBN	7.3.3.2	m		4 bits value	
7	Connection type	7.3.3.2	m		'00'B .. '11'B	
8	Service type	7.3.3.2	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.2	m		3 bits value	
10	Slot type	7.3.3.2	m		'0000'B .. '0010'B	
11	Spr	7.3.3.2	m		'1111'B	

Note to item 9: Unless the service is Ip_error_correction, this parameter is set to '000'.

Table A.204: B-field Advanced CC - Connection handover request (Receipt F to P)

Prerequisite: 77/3						
Item	B-field Advanced CC - Connection handover request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0010'B	
3	FMID	7.3.3.2	m		12 bits value	
4	PMID	7.3.3.2	m		20 bits value	
5	ECN	7.3.3.2	m		4 bits value	
6	LBN	7.3.3.2	m		4 bits value	
7	Connection type	7.3.3.2	m		'00'B .. '11'B	
8	Service type	7.3.3.2	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.2	m		3 bits value	
10	Slot type	7.3.3.2	m		'0000'B .. '0010'B	
11	Spr	7.3.3.2	m		'1111'B	

Note to item 9: Unless the service is Ip_error_correction, this parameter is set to '000'.

A.8.5.1.4 B-field Advanced CC - Unconfirmed access request

Table A.205: B-field Advanced CC - Unconfirmed access request (Sending P to F)

Prerequisite: 76/4						
Item	B-field Advanced CC - Unconfirmed access request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0011'B	
3	FMID	7.3.3.2	m		12 bits value	
4	PMID	7.3.3.2	m		20 bits value	
5	ECN	7.3.3.2	m		4 bits value	
6	LBN	7.3.3.2	m		4 bits value	
7	Connection type	7.3.3.2	m		'00'B .. '11'B	
8	Service type	7.3.3.2	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.2	m		3 bits value	
10	Slot type	7.3.3.2	m		'0000'B .. '0010'B	
11	Spr	7.3.3.2	m		'1111'B	

Note to item 9: Unless the service is Ip_error_correction, this parameter is set to '000'.

Table A.206: B-field Advanced CC - Unconfirmed access request (Receipt F to P)

Prerequisite: 77/4						
Item	B-field Advanced CC - Unconfirmed access request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0011'B	
3	FMID	7.3.3.2	m		12 bits value	
4	PMID	7.3.3.2	m		20 bits value	
5	ECN	7.3.3.2	m		4 bits value	
6	LBN	7.3.3.2	m		4 bits value	
7	Connection type	7.3.3.2	m		'00'B .. '11'B	
8	Service type	7.3.3.2	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.2	m		3 bits value	
10	Slot type	7.3.3.2	m		'0000'B .. '0010'B	
11	Spr	7.3.3.2	m		'1111'B	

Note to item 9: Unless the service is Ip_error_correction, this parameter is set to '000'.

A.8.5.1.5 B-field Advanced CC - Bearer confirm

Table A.207: B-field Advanced CC - Bearer confirm (Sending P to F)

Prerequisite: 76/5						
Item	B-field Advanced CC - Bearer confirm	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0100'B	
3	FMID	7.3.3.3	m		12 bits value	
4	PMID	7.3.3.3	m		20 bits value	
5	ECN	7.3.3.3	m		4 bits value	
6	LBN	7.3.3.3	m		4 bits value	
7	Connection type	7.3.3.3	m		'00'B .. '11'B	
8	Service type	7.3.3.3	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.3	m		3 bits value	
10	Slot type	7.3.3.3	m		'0000'B .. '0010'B	
11	Spr	7.3.3.3	m		'1111'B	

Note to item 9: Unless the service is Ip_error_correction, this parameter is set to '000'.

Table A.208: B-field Advanced CC - Bearer confirm (Receipt F to P)

Prerequisite: 77/5						
Item	B-field Advanced CC - Bearer confirm	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0100'B	
3	FMID	7.3.3.3	m		12 bits value	
4	PMID	7.3.3.3	m		20 bits value	
5	ECN	7.3.3.3	m		4 bits value	
6	LBN	7.3.3.3	m		4 bits value	
7	Connection type	7.3.3.3	m		'00'B .. '11'B	
8	Service type	7.3.3.3	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.3	m		3 bits value	
10	Slot type	7.3.3.3	m		'0000'B .. '0010'B	
11	Spr	7.3.3.3	m		'1111'B	

Note to item 9: Unless the service is Ip_error_correction, this parameter is set to '000'.

A.8.5.1.6 B-field Advanced CC - Wait

Table A.209: B-field Advanced CC - Wait (Sending P to F)

Prerequisite: 76/6						
Item	B-field Advanced CC - Wait	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0101'B	
3	FMID	7.3.3.4	m		12 bits value	
4	PMID	7.3.3.4	m		20 bits value or '1111 0000 1111 0000 1111'B	
5	Spare	7.3.3.4	m		'0000 1111 0000 1111 0000 1111'B	

Table A.210: B-field Advanced CC - Wait (Receipt F to P)

Prerequisite: 77/6						
Item	B-field Advanced CC - Wait	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0101'B	
3	FMID	7.3.3.4	m		12 bits value	
4	PMID	7.3.3.4	m		20 bits value or '1111 0000 1111 0000 1111'B	
5	Spare	7.3.3.4	m		'0000 1111 0000 1111 0000 1111'B	

A.8.5.1.7 B-field Advanced CC - Attributes_B request**Table A.211: B-field Advanced CC - Attributes_B request (Sending P to F)**

Prerequisite: 76/7						
Item	B-field Advanced CC - Attributes_B request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0110'B	
3	FMID	7.3.3.5	m		12 bits value	
4	PMID	7.3.3.5	m		20 bits value	
5	Spare	7.3.3.5	m		'0000 1111'B	
6	Connection type	7.3.3.5	m		'00'B .. '11'B	
7	Service type	7.3.3.5	m		'000'B .. '100'B	
8	Maximum lifetime	7.3.3.5	m		3 bits value	
9	Slot type	7.3.3.5	m		'0000'B .. '0010'B	
10	Spr	7.3.3.5	m		'1111'B	

Note to item 8: Unless the service is l_P_error_correction, this parameter is set to '000'.

Table A.212: B-field Advanced CC - Attributes_B request (Receipt F to P)

Prerequisite: 77/7						
Item	B-field Advanced CC - Attributes_B request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0110'B	
3	FMID	7.3.3.5	m		12 bits value	
4	PMID	7.3.3.5	m		20 bits value	
5	Spare	7.3.3.5	m		'0000 1111'B	
6	Connection type	7.3.3.5	m		'00'B .. '11'B	
7	Service type	7.3.3.5	m		'000'B .. '100'B	
8	Maximum lifetime	7.3.3.5	m		3 bits value	
9	Slot type	7.3.3.5	m		'0000'B .. '0010'B	
10	Spr	7.3.3.5	m		'1111'B	

Note to item 8: Unless the service is l_P_error_correction, this parameter is set to '000'.

A.8.5.1.8 B-field Advanced CC - Attributes_B confirm

Table A.213: B-field Advanced CC - Attributes_B confirm (Sending P to F)

Prerequisite: 76/8

Item	B-field Advanced CC - Attributes_B confirm	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0111'B	
3	FMID	7.3.3.5	m		12 bits value	
4	PMID	7.3.3.5	m		20 bits value	
5	Spare	7.3.3.5	m		'0000 1111'B	
6	Connection type	7.3.3.5	m		'00'B .. '11'B	
7	Service type	7.3.3.5	m		'000'B .. '100'B	
8	Maximum lifetime	7.3.3.5	m		3 bits value	
9	Slot type	7.3.3.5	m		'0000'B .. '0010'B	
10	Spr	7.3.3.5	m		'1111'B	

Note to item 8: Unless the service is I_P_error_correction, this parameter is set to '000'.

Table A.214: B-field Advanced CC - Attributes_B confirm (Receipt F to P)

Prerequisite: 77/8

Item	B-field Advanced CC - Attributes_B confirm	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'0111'B	
3	FMID	7.3.3.5	m		12 bits value	
4	PMID	7.3.3.5	m		20 bits value	
5	Spare	7.3.3.5	m		'0000 1111'B	
6	Connection type	7.3.3.5	m		'00'B .. '11'B	
7	Service type	7.3.3.5	m		'000'B .. '100'B	
8	Maximum lifetime	7.3.3.5	m		3 bits value	
9	Slot type	7.3.3.5	m		'0000'B .. '0010'B	
10	Spr	7.3.3.5	m		'1111'B	

Note to item 8: Unless the service is I_P_error_correction, this parameter is set to '000'.

A.8.5.1.9 B-field Advanced CC - Bandwidth_B request

Table A.215: B-field Advanced CC - Bandwidth_B request (Sending P to F)

Prerequisite: 76/9						
Item	B-field Advanced CC - Bandwidth_B request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'1000'B	
3	FMID	7.3.3.6	m		12 bits value	
4	Spr 1	7.3.3.6	m		'1111 0000 1111'B	
5	Spr 2	7.3.3.6	m		'000'B	
6	Minimum no. of uplink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
7	Spr 3	7.3.3.6	m		'000'B	
8	Taget no. of uplink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
9	Spr 4	7.3.3.6	m		'000'B	
10	Minimum no. of downlink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
11	Spr 5	7.3.3.6	m		'000'B	
12	Taget no. of downlink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	

Table A.216: B-field Advanced CC - Bandwidth_B request (Receipt F to P)

Prerequisite: 77/9						
Item	B-field Advanced CC - Bandwidth_B request	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'1000'B	
3	FMID	7.3.3.6	m		12 bits value	
4	Spr 1	7.3.3.6	m		'1111 0000 1111'B	
5	Spr 2	7.3.3.6	m		'000'B	
6	Minimum no. of uplink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
7	Spr 3	7.3.3.6	m		'000'B	
8	Taget no. of uplink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
9	Spr 4	7.3.3.6	m		'000'B	
10	Minimum no. of downlink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
11	Spr 5	7.3.3.6	m		'000'B	
12	Taget no. of downlink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	

A.8.5.1.10 B-field Advanced CC - Bandwidth_B confirm

Table A.217: B-field Advanced CC - Bandwidth_B confirm (Sending P to F)

Prerequisite: 76/10						
Item	B-field Advanced CC - Bandwidth_B confirm	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'1001'B	
3	FMID	7.3.3.6	m		12 bits value	
4	Spr 1	7.3.3.6	m		'1111 0000 1111'B	
5	Spr 2	7.3.3.6	m		'000'B	
6	Minimum no. of uplink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
7	Spr 3	7.3.3.6	m		'000'B	
8	Taget no. of uplink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
9	Spr 4	7.3.3.6	m		'000'B	
10	Minimum no. of downlink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
11	Spr 5	7.3.3.6	m		'000'B	
12	Taget no. of downlink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	

Table A.218: B-field Advanced CC - Bandwidth_B confirm (Receipt F to P)

Prerequisite: 77/10						
Item	B-field Advanced CC - Bandwidth_B confirm	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'1001'B	
3	FMID	7.3.3.6	m		12 bits value	
4	Spr 1	7.3.3.6	m		'1111 0000 1111'B	
5	Spr 2	7.3.3.6	m		'000'B	
6	Minimum no. of uplink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
7	Spr 3	7.3.3.6	m		'000'B	
8	Taget no. of uplink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
9	Spr 4	7.3.3.6	m		'000'B	
10	Minimum no. of downlink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	
11	Spr 5	7.3.3.6	m		'000'B	
12	Taget no. of downlink simplex bearers	7.3.3.6	m		'00000'B .. '11110'B	

A.8.5.1.12 B-field Advanced CC - Unconfirmed_Dummy

Table A.221: B-field Advanced CC - Unconfirmed_Dummy (Sending P to F)

Prerequisite: 76/12						
Item	B-field Advanced CC - Unconfirmed_Dummy	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'1011'B	
3	FMID	7.3.3.8	m		12 bits value	
4	PMID	7.3.3.8	m		20 bits value	
5	ECN	7.3.3.8	m		4 bits value	
6	LBN	7.3.3.8	m		4 bits value	
7	Connection type	7.3.3.8	m		'00'B .. '11'B	
8	Service type	7.3.3.8	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.8	m		3 bits value	
10	Slot type	7.3.3.8	m		'0000'B .. '0010'B	
11	Spr	7.3.3.8	m		'1111'B	

Note to item 9: Unless the service is l_P_error_correction, this parameter is set to '000'.

Table A.222: B-field Advanced CC - Unconfirmed_Dummy (Receipt F to P)

Prerequisite: 77/12						
Item	B-field Advanced CC - Unconfirmed_Dummy	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'1011'B	
3	FMID	7.3.3.8	m		12 bits value	
4	PMID	7.3.3.8	m		20 bits value	
5	ECN	7.3.3.8	m		4 bits value	
6	LBN	7.3.3.8	m		4 bits value	
7	Connection type	7.3.3.8	m		'00'B .. '11'B	
8	Service type	7.3.3.8	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.8	m		3 bits value	
10	Slot type	7.3.3.8	m		'0000'B .. '0010'B	
11	Spr	7.3.3.8	m		'1111'B	

Note to item 9: Unless the service is l_P_error_correction, this parameter is set to '000'.

A.8.5.1.13 B-field Advanced CC - Unconfirmed_Handover

Table A.223: B-field Advanced CC - Unconfirmed_Handover (Sending P to F)

Prerequisite: 76/13						
Item	B-field Advanced CC - Unconfirmed_Hando ver	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'1100'B	
3	FMID	7.3.3.9	m		12 bits value	
4	PMID	7.3.3.9	m		20 bits value	
5	ECN	7.3.3.9	m		4 bits value	
6	LBN	7.3.3.9	m		4 bits value	
7	Connection type	7.3.3.9	m		'00'B .. '11'B	
8	Service type	7.3.3.9	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.9	m		3 bits value	
10	Slot type	7.3.3.9	m		'0000'B .. '0010'B	
11	Spr	7.3.3.9	m		'1111'B	

Note to item 9: Unless the service is Ip_error_correction, this parameter is set to '000'.

Table A.224: B-field Advanced CC - Unconfirmed_Handover (Receipt F to P)

Prerequisite: 77/13						
Item	B-field Advanced CC - Unconfirmed_Hando ver	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'1100'B	
3	FMID	7.3.3.9	m		12 bits value	
4	PMID	7.3.3.9	m		20 bits value	
5	ECN	7.3.3.9	m		4 bits value	
6	LBN	7.3.3.9	m		4 bits value	
7	Connection type	7.3.3.9	m		'00'B .. '11'B	
8	Service type	7.3.3.9	m		'000'B .. '100'B	
9	Maximum lifetime	7.3.3.9	m		3 bits value	
10	Slot type	7.3.3.9	m		'0000'B .. '0010'B	
11	Spr	7.3.3.9	m		'1111'B	

Note to item 9: Unless the service is Ip_error_correction, this parameter is set to '000'.

A.8.5.1.14 B-field Advanced CC - Release

Table A.225: B-field Advanced CC - Release (Sending P to F)

Prerequisite: 76/14						
Item	B-field Advanced CC - Release	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'1111'B	
3	FMID	7.3.3.10	m		12 bits value	
4	PMID	7.3.3.10	m		20 bits value	
5	Spr	7.3.3.10	m		'0000'B	
6	LBN	7.3.3.10	m		4 bits value	
7	Spare	7.3.3.10	m		'0000 1111'B	
8	Reason	7.3.3.10	m		'0000 0000'B .. '0000 1101'B	

Table A.226: B-field Advanced CC - Release (Receipt F to P)

Prerequisite: 77/14						
Item	B-field Advanced CC - Release	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X001'B	
2	Command	7.3.3.1	m		'1111'B	
3	FMID	7.3.3.10	m		12 bits value	
4	PMID	7.3.3.10	m		20 bits value	
5	Spr	7.3.3.10	m		'0000'B	
6	LBN	7.3.3.10	m		4 bits value	
7	Spare	7.3.3.10	m		'0000 1111'B	
8	Reason	7.3.3.10	m		'0000 0000'B .. '0000 1101'B	

A.8.5.2 B-field - Null Messages (NM)

A.8.5.2.1 B-field - NM No C_F or CL_F data in the B-field

Table A.227: B-field - NM No C_F or CL_F data in the B-field (Sending P to F)

Prerequisite: 78/1						
Item	B-field - NM No C _F or CL _F data in the B-field	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'0000'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

Table A.228: B-field - NM No C_F or CL_F data in the B-field (Receipt F to P)

Prerequisite: 79/1						
Item	B-field - NM No C _F or CL _F data in the B-field	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'0000'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

A.8.5.2.2 B-field - NM One B-subfield contains C_F or CL_F data**Table A.229: B-field - NM One B-subfield contains C_F or CL_F data (Sending P to F)**

Prerequisite: 78/2						
Item	B-field - NM One B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'0001'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

Table A.230: B-field - NM One B-subfield contains C_F or CL_F data (Receipt F to P)

Prerequisite: 79/2						
Item	B-field - NM One B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'0001'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

A.8.5.2.6 B-field - NM Five B-subfield contain C_F or CL_F data

Table A.237: B-field - NM Five B-subfield contains C_F or CL_F data (Sending P to F)

Prerequisite: 78/6						
Item	B-field - NM Five B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'0101'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

Table A.238: B-field - NM Five B-subfield contains C_F or CL_F data (Receipt F to P)

Prerequisite: 79/6						
Item	B-field - NM Five B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'0101'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

A.8.5.2.7 B-field - NM Six B-subfield contain C_F or CL_F data

Table A.239: B-field - NM Six B-subfield contains C_F or CL_F data (Sending P to F)

Prerequisite: 78/7						
Item	B-field - NM Six B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'0110'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

Table A.240: B-field - NM Six B-subfield contains C_F or CL_F data (Receipt F to P)

Prerequisite: 79/7						
Item	B-field - NM Six B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'0110'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

A.8.5.2.8 B-field - NM Seven B-subfield contain C_F or CL_F data**Table A.241: B-field - NM Seven B-subfield contains C_F or CL_F data (Sending P to F)**

Prerequisite: 78/8						
Item	B-field - NM Seven B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'0111'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

Table A.242: B-field - NM Seven B-subfield contains C_F or CL_F data (Receipt F to P)

Prerequisite: 79/8						
Item	B-field - NM Seven B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'0111'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

A.8.5.2.9 B-field - NM Eight B-subfield contain C_F or CL_F data

Table A.243: B-field - NM Eight B-subfield contains C_F or CL_F data (Sending P to F)

Prerequisite: 78/9						
Item	B-field - NM Eight B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'1000'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

Table A.244: B-field - NM Eight B-subfield contains C_F or CL_F data (Receipt F to P)

Prerequisite: 79/9						
Item	B-field - NM Eight B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'1000'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

A.8.5.2.10 B-field - NM Nine B-subfield contain C_F or CL_F data

Table A.245: B-field - NM Nine B-subfield contains C_F or CL_F data (Sending P to F)

Prerequisite: 78/10						
Item	B-field - NM Nine B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'1000'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

Table A.246: B-field - NM Nine B-subfield contains C_F or CL_F data (Receipt F to P)

Prerequisite: 79/10						
Item	B-field - NM Nine B-subfield contains C _F or CL _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X010'B	
2	NCF	7.3.4	m		'1000'B	
3	Spare 1	7.3.4	m		'0000 1111 0000 1111'B	
4	Spare 2	7.3.4	m		'0000 1111 0000 1111'B	
5	Spare 3	7.3.4	m		'0000 1111 0000 1111'B	
6	Spare 4	7.3.4	m		'0000 1111'B	

A.8.5.3 B - Field - Quality control (QC) messages**A.8.5.3.1 B - Field - QC Antenna switch single bearer****Table A.247: B-field QC - Antenna switch single bearer (Sending P to F)**

Prerequisite: 80/1						
Item	B-field QC - Antenna switch single bearer	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0000'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	Spr	7.3.5.2	m		'0000'B	
6	LBN	7.3.5.2	m		4 bits value	
7	Param 2	7.3.5.2	m		'0000 1111'B	
8	Spare	7.3.5.2	m		'0000 1111'B	

Table A.248: B-field QC - Antenna switch single bearer (Receipt F to P)

Prerequisite: 81/1						
Item	B-field QC - Antenna switch single bearer	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0000'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	Spr	7.3.5.2	m		'0000'B	
6	LBN	7.3.5.2	m		4 bits value	
7	Param 2	7.3.5.2	m		'0000 1111'B	
8	Spare	7.3.5.2	m		'0000 1111'B	

A.8.5.3.2 B - Field - QC Antenna switch all bearers

Table A.249: B-field QC - Antenna switch all bearers (Sending P to F)

Prerequisite: 80/2						
Item	B-field QC - Antenna switch all bearers	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0001'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	RPN	7.3.5.2	m		8 bits value	
6	Param 2	7.3.5.2	m		'0000 1111'B	
7	Spare	7.3.5.2	m		'0000 1111'B	

Table A.250: B-field QC - Antenna switch all bearers (Receipt F to P)

Prerequisite: 81/2						
Item	B-field QC - Antenna switch all bearers	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0001'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	RPN	7.3.5.2	m		8 bits value	
6	Param 2	7.3.5.2	m		'0000 1111'B	
7	Spare	7.3.5.2	m		'0000 1111'B	

A.8.5.3.3 B - Field - QC Bearer handover

Table A.251: B-field QC - Bearer handover (Sending P to F)

Prerequisite: 80/3						
Item	B-field QC - Bearer handover	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0010'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	Spr	7.3.5.2	m		'0000'B	
6	LBN	7.3.5.2	m		4 bits value	
7	RPN	7.3.5.2	m		8 bits value or '0000 0000'B	
8	Spare	7.3.5.2	m		'0000 1111'B	

Table A.252: B-field QC - Bearer handover (Receipt F to P)

Prerequisite: 81/3						
Item	B-field QC - Bearer handover	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0010'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	Spr	7.3.5.2	m		'0000'B	
6	LBN	7.3.5.2	m		4 bits value	
7	RPN	7.3.5.2	m		8 bits value or '0000 0000'B	
8	Spare	7.3.5.2	m		'0000 1111'B	

A.8.5.3.4 B - Field - QC Connection handover**Table A.253: B - Field - QC Connection handover (Sending P to F)**

Prerequisite: 80/4						
Item	B - Field - QC Connection handover	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0011'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	Param 1	7.3.5.2	m		'0000 1111'B	
6	Param 2	7.3.5.2	m		'0000 1111'B	
7	Spare	7.3.5.2	m		'0000 1111'B	

Table A.254: B - Field - QC Connection handover (Receipt F to P)

Prerequisite: 81/4						
Item	B - Field - QC Connection handover	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0011'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	Param 1	7.3.5.2	m		'0000 1111'B	
6	Param 2	7.3.5.2	m		'0000 1111'B	
7	Spare	7.3.5.2	m		'0000 1111'B	

A.8.5.3.5 B - Field - QC Frequency control single bearer

Table A.255: B-field QC - Frequency control single bearer (Sending P to F)

Prerequisite: 80/5						
Item	B-field QC - Frequency control single bearer	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0100'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	Spr	7.3.5.2	m		'0000'B	
6	LBN	7.3.5.2	m		4 bits value	
7	Frequency error	7.3.5.2	m		8 bits signed value	
8	Spare	7.3.5.2	m		'0000 1111'B	

Table A.256: B-field QC - Frequency control single bearer (Receipt F to P)

Prerequisite: 81/5						
Item	B-field QC - Frequency control single bearer	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0100'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	Spr	7.3.5.2	m		'0000'B	
6	LBN	7.3.5.2	m		4 bits value	
7	Frequency error	7.3.5.2	m		8 bits signed value	
8	Spare	7.3.5.2	m		'0000 1111'B	

A.8.5.3.6 B - Field - QC Frequency control all bearers

Table A.257: B-field QC - Frequency control all bearers (Sending P to F)

Prerequisite: 80/6						
Item	B-field QC - Frequency control all bearers	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0101'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	RPN	7.3.5.2	m		8 bits value	
6	Frequency error	7.3.5.2	m		8 bits signed value	
7	Spare	7.3.5.2	m		'0000 1111'B	

Table A.258: B-field QC - Frequency control all bearers (Receipt F to P)

Prerequisite: 81/6						
Item	B-field QC - Frequency control all bearers	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'0101'B	
3	FMID	7.3.5.2	m		12 bits value	
4	PMID	7.3.5.2	m		20 bits value	
5	RPN	7.3.5.2	m		8 bits value	
6	Frequency error	7.3.5.2	m		8 bits signed value	
7	Spare	7.3.5.2	m		'0000 1111'B	

A.8.5.3.7 B - Field - QC Reset request first TDMA half frame**Table A.259: B - Field - QC Reset request first TDMA half frame (Sending P to F)**

Prerequisite: 80/7						
Item	B - Field - QC Reset request first TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0001'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

Table A.260: B - Field - QC Reset request first TDMA half frame (Receipt F to P)

Prerequisite: 81/7						
Item	B - Field - QC Reset request first TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0001'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

A.8.5.3.8 B - Field - QC Reset request second TDMA half frame

Table A.261: B - Field - QC Reset request second TDMA half frame (Sending P to F)

Prerequisite: 80/8						
Item	B - Field - QC Reset request second TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0010'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

Table A.262: B - Field - QC Reset request second TDMA half frame (Receipt F to P)

Prerequisite: 81/8						
Item	B - Field - QC Reset request second TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0010'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

A.8.5.3.9 B - Field - QC Reset request both TDMA half frames

Table A.263: B - Field - QC Reset request both TDMA half frame (Sending P to F)

Prerequisite: 80/9						
Item	B - Field - QC Reset request both TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0011'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

Table A.264: B - Field - QC Reset request both TDMA half frame (Receipt F to P)

Prerequisite: 81/9						
Item	B - Field - QC Reset request both TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0011'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

A.8.5.3.10 B - Field - QC Reset confirm first TDMA half frame

Table A.265: B - Field - QC Reset confirm first TDMA half frame (Sending P to F)

Prerequisite: 80/10						
Item	B - Field - QC Reset confirm first TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0101'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

Table A.266: B - Field - QC Reset confirm first TDMA half frame (Receipt F to P)

Prerequisite: 81/10						
Item	B - Field - QC Reset confirm first TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0101'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

A.8.5.3.11 B - Field - QC Reset confirm second TDMA half frame

Table A.267: B - Field - QC Resetconfirm second TDMA half frame (Sending P to F)

Prerequisite: 80/11						
Item	B - Field - QC Reset confirm second TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0110'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

Table A.268: B - Field - QC Resetconfirm second TDMA half frame (Receipt F to P)

Prerequisite: 81/11						
Item	B - Field - QC Reset confirm second TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0110'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

A.8.5.3.12 B - Field - QC Reset confirm both TDMA half frames

Table A.269: B - Field - QC Reset confirm both TDMA half frame (Sending P to F)

Prerequisite: 80/12						
Item	B - Field - QC Reset confirm both TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0111'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

Table A.270: B - Field - QC Reset confirm both TDMA half frame (Receipt F to P)

Prerequisite: 81/12						
Item	B - Field - QC Reset confirm both TDMA half frame	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1110'B	
3	FMID	7.3.5.3	m		12 bits value	
4	PMID	7.3.5.3	m		20 bits value	
5	Control	7.3.5.3	m		'0111'B	
6	LBN	7.3.5.3	m		4 bits value	
7	Spare 1	7.3.5.3	m		'0000 1111'B	
8	Spare 2	7.3.5.3	m		'0000 1111'B	

A.8.5.3.13 B - Field - QC MOD2 ACK

Table A.271: B - Field - QC MOD2 ACK (Sending P to F)

Prerequisite: 80/13						
Item	B - Field - QC MOD2 ACK	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1111'B	
3	First half of TDMA frame - LBN1 to LBN14 Q1/BCK and Q2/ACK	7.3.5.4	m		28 bits value	
4	Second half of TDMA frame - LBN1 to LBN14 Q1/BCK and Q2/ACK	7.3.5.4	m		28 bits value	

Table A.272: B - Field - QC MOD2 ACK (Receipt F to P)

Prerequisite: 81/13						
Item	B - Field - QC MOD2 ACK	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MBn header	7.3.1	m		'X011'B	
2	Command	7.3.3.1	m		'1111'B	
3	First half of TDMA frame - LBN1 to LBN14 Q1/BCK and Q2/ACK	7.3.5.4	m		28 bits value	
4	Second half of TDMA frame - LBN1 to LBN14 Q1/BCK and Q2/ACK	7.3.5.4	m		28 bits value	

A.8.5.4 B - Field - Extended system information (ES) messages

A.8.5.4.1 B - Field - ES TARI message

Table A.273: B - Field - ES TARI message (Sending P to F)

Prerequisite: 74/4						
Item	B - Field - ES TARI messagea	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X100'B	
2	Command	7.3.6.1	m		'0000'B	
3	TARI field	7.3.6.2	m		36 bits value	
4	Spr	7.3.6.2	m		'1111'B	
5	Spare	7.3.6.2	m		'0000 1111 0000 1111'B	

Table A.274: B - Field - ES TARI message (Receipt F to P)

Prerequisite: 75/4						
Item	B - Field - ES TARI messagea	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X100'B	
2	Command	7.3.6.1	m		'0000'B	
3	TARI field	7.3.6.2	m		36 bits value	
4	Spr	7.3.6.2	m		'1111'B	
5	Spare	7.3.6.2	m		'0000 1111 0000 1111'B	

A.8.5.5 B - Field - GF-channel data packet messages

A.8.5.5.1 B - Field - GF-No C_F data in the B-field

Table A.275: B - Field - GF-No C_F data in the B-field (Sending P to F)

Prerequisite: 82/1						
Item	B - Field - GF-No C _F data in the B-field	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0000'B	
3	GF channel SDU	7.3.7	m		56 bits value	

Table A.276: B - Field - GF-No C_F data in the B-field (Receipt F to P)

Prerequisite: 83/1						
Item	B - Field - GF-No C _F data in the B-field	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0000'B	
3	GF channel SDU	7.3.7	m		56 bits value	

A.8.5.5.2 B - Field - GF-One B-subfield contains C_F data**Table A.277: B - Field - GF-One B-subfield contains C_F data (Sending P to F)**

Prerequisite: 82/2						
Item	B - Field - GF-One B-subfield contains C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MB _n header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0001'B	
3	GF channel SDU	7.3.7	m		56 bits value	

Table A.278: B - Field - GF-One B-subfield contains C_F data (Receipt F to P)

Prerequisite: 83/2						
Item	B - Field - GF-One B-subfield contains C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MB _n header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0001'B	
3	GF channel SDU	7.3.7	m		56 bits value	

A.8.5.5.3 B - Field - GF-Two B-subfield contain C_F data**Table A.279: B - Field - GF-Two B-subfield contain C_F data (Sending P to F)**

Prerequisite: 82/3						
Item	B - Field - GF-Two B-subfield contain C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MB _n header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0010'B	
3	GF channel SDU	7.3.7	m		56 bits value	

Table A.280: B - Field - GF-Two B-subfield contain C_F data (Receipt F to P)

Prerequisite: 83/3						
Item	B - Field - GF-Two B-subfield contain C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MB _n header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0010'B	
3	GF channel SDU	7.3.7	m		56 bits value	

A.8.5.5.4 B - Field - GF-Three B-subfield contain C_F data

Table A.281: B - Field - GF-Three B-subfield contains C_F data (Sending P to F)

Prerequisite: 82/4						
Item	B - Field - GF-Three B-subfield contains C _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0011'B	
3	GF channel SDU	7.3.7	m		56 bits value	

Table A.282: B - Field - GF-Three B-subfield contains C_F data (Receipt F to P)

Prerequisite: 83/4						
Item	B - Field - GF-Three B-subfield contains C _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0011'B	
3	GF channel SDU	7.3.7	m		56 bits value	

A.8.5.5.5 B - Field - GF-Four B-subfield contain C_F data

Table A.283: B - Field - GF-Four B-subfield contains C_F data (Sending P to F)

Prerequisite: 82/5						
Item	B - Field - GF-Four B-subfield contains C _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0100'B	
3	GF channel SDU	7.3.7	m		56 bits value	

Table A.284: B - Field - GF-Four B-subfield contains C_F data (Receipt F to P)

Prerequisite: 83/5						
Item	B - Field - GF-Four B-subfield contains C _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0100'B	
3	GF channel SDU	7.3.7	m		56 bits value	

A.8.5.5.6 B - Field - GF-Five B-subfield contain C_F data

Table A.285: B - Field - GF-Five B-subfield contains C_F data (Sending P to F)

Prerequisite: 82/6						
Item	B - Field - GF-Five B-subfield contains C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MB _n header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0101'B	
3	GF channel SDU	7.3.7	m		56 bits value	

Table A.286: B - Field - GF-Five B-subfield contains C_F data (Receipt F to P)

Prerequisite: 83/6						
Item	B - Field - GF-Five B-subfield contains C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MB _n header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0101'B	
3	GF channel SDU	7.3.7	m		56 bits value	

A.8.5.5.7 B - Field - GF-Six B-subfield contain C_F data

Table A.287: B - Field - GF-Six B-subfield contains C_F data (Sending P to F)

Prerequisite: 82/7						
Item	B - Field - GF-Six B-subfield contains C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MB _n header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0110'B	
3	GF channel SDU	7.3.7	m		56 bits value	

Table A.288: B - Field - GF-Six B-subfield contains C_F data (Receipt F to P)

Prerequisite: 83/7						
Item	B - Field - GF-Six B-subfield contains C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	MB _n header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0110'B	
3	GF channel SDU	7.3.7	m		56 bits value	

A.8.5.5.8 B - Field - GF-Seven B-subfield contain C_F data

Table A.289: B - Field - GF-Seven B-subfield contains C_F data (Sending P to F)

Prerequisite: 82/8						
Item	B - Field - GF-Seven B-subfield contains C _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0111'B	
3	GF channel SDU	7.3.7	m		56 bits value	

Table A.290: B - Field - GF-Seven B-subfield contains C_F data (Receipt F to P)

Prerequisite: 83/8						
Item	B - Field - GF-Seven B-subfield contains C _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'0111'B	
3	GF channel SDU	7.3.7	m		56 bits value	

A.8.5.5.9 B - Field - GF-Eight B-subfield contain C_F data

Table A.291: B - Field - GF-Eight B-subfield contains C_F data (Sending P to F)

Prerequisite: 82/9						
Item	B - Field - GF-Eight B-subfield contains C _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'1000'B	
3	GF channel SDU	7.3.7	m		56 bits value	

Table A.292: B - Field - GF-Eight B-subfield contains C_F data (Receipt F to P)

Prerequisite: 83/9						
Item	B - Field - GF-Eight B-subfield contains C _F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M _{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'1000'B	
3	GF channel SDU	7.3.7	m		56 bits value	

A.8.5.5.10 B - Field - GF-Nine B-subfield contain C_F data

Table A.293: B - Field - GF-NineB-subfield contains C_F data (Sending P to F)

Prerequisite: 82/10						
Item	B - Field - GF-Nine B-subfield contains C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M_{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'1001'B	
3	GF channel SDU	7.3.7	m		56 bits value	

Table A.294: B - Field - GF-NineB-subfield contains C_F data (Receipt F to P)

Prerequisite: 83/10						
Item	B - Field - GF-Nine B-subfield contains C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M_{Bn} header	7.3.1	m		'X101'B	
2	NCF	7.3.7	m		'1001'B	
3	GF channel SDU	7.3.7	m		56 bits value	

A.8.5.6 B - Field - Escape message

Table A.295: B - Field - GF-NineB-subfield contains C_F data (Sending P to F)

Prerequisite: 74/6						
Item	B - Field - GF-Nine B-subfield contains C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M_{Bn} header	7.3.1	m		'X111'B	
2	Escape information	7.3.8	m		60 bits value	

Table A.296: B - Field - GF-NineB-subfield contains C_F data (Receipt F to P)

Prerequisite: 75/6						
Item	B - Field - GF-Nine B-subfield contains C_F data	Ref.	Status	Supp.	Value Allowed	Value Supported
1	M_{Bn} header	7.3.1	m		'X111'B	
2	Escape information	7.3.8	m		60 bits value	

History

Document history			
June 1995	Public Enquiry	PE 85:	1995-06-05 to 1995-09-29
May 1996	Vote	V 102:	1996-05-06 to 1996-08-09