



AMENDMENT

ETS 300 494-3
pr A1

January 1997

Source: ETSI EP-DECT

Reference: RE/DECT-040093-3

ICS: 33.020

Key words: DECT, GAP, testing

**This draft amendment A1, if approved, will modify
the European Telecommunication Standard ETS 300 494-3 (1996)**

**Radio Equipment and Systems (RES);
Digital Enhanced Cordless Telecommunications (DECT);
Generic Access Profile (GAP);
Profile Test Specification (PTS);
Part 3: Profile Specific Test Specification (PSTS)
- Fixed radio Termination (FT)**

ETSI

European Telecommunications Standards Institute

ETSI Secretariat

Postal address: F-06921 Sophia Antipolis CEDEX - FRANCE

Office address: 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE

X.400: c=fr, a=atlas, p=etsi, s=secretariat - **Internet:** secretariat@etsi.fr

Tel.: +33 4 92 94 42 00 - Fax: +33 4 93 65 47 16

Copyright Notification: No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1997. All rights reserved.

Foreword

This draft amendment to ETS 300 494-3 (1996) has been produced by the Digital Enhanced Cordless Telecommunications (DECT) Project of the European Telecommunications Standards Institute (ETSI), and is now submitted for the Public Enquiry phase of the ETSI standards Two-step Approval Procedure.

| Proposed transposition dates | |
|--|---------------------------------|
| Date of latest announcement of this amendment (doa): | 3 months after ETSI publication |
| Date of latest publication or endorsement of this amendment (dop/e): | 6 months after doa |
| Date of withdrawal of any conflicting National Standard (dow): | 6 months after doa |

Amendments

Subclause 4.1

Modify subclause 4.1 as follows:

This subclause includes lists of the test groups and abstract test cases relevant for GAP PTS - NWK layer Fixed Termination (FT) derived from ETS 300 497-9 [26].

~~The page number referenced is the relative page number in the corresponding ETS where the particular item can be found.~~

NOTE: ~~As ETS 300 497-1 [18] is draft, and some changes are likely due to the results of the Public Enquiry (PE) phase, page numbers reflecting the exact place in that ETS where a test case is to be found are not included in this ETS. They shall be added in a later stage. References when necessary shall be made based on the particular test case name unique through all test specification ETS 300 497-1 [18].~~

Subclause 4.1.1

Add the test group reference for "FT/CC/RS" in table 1, as follows:

| | |
|----------|--|
| FT/CC/RS | To check the IUT's behaviour during call related supplementary service procedures. |
|----------|--|

Subclause 4.1.2

Replace table 2 with the following table 2:

Table 2

| Test Case Index | | |
|----------------------|-------------------|--|
| Test Group Reference | Test Case Id | Description |
| FT/CC/BV/OC/ | TC_FT_CC_BV_OC_01 | Outgoing normal call; F-00 to F-10; piece-wise dialling |
| | TC_FT_CC_BV_OC_06 | Internal call. (There is no test case defined in ETS 300 497-9 [26] due to difficulties of predicting the IUT behaviour) |
| FT/CC/BV/IC/ | TC_FT_CC_BV_IC_01 | Incoming call; F-00, F-06, F-07 to F-10 |
| FT/CC/BV/CI/ | TC_FT_CC_BV_CI_01 | Incoming call; <<Signal>> either in {SS-SETUP}{CC-SETUP} or in {CC-INFO} |
| | TC_FT_CC_BV_CI_02 | Outgoing normal call; F-02; {CC-INFO}, <<Multi keypad>>, "Go to pulse" handling |
| | TC_FT_CC_BV_CI_03 | Outgoing normal call; F-10; {CC-INFO}, <<Multi keypad>>, 'dialling pause' handling. |
| | TC_FT_CC_BV_CI_04 | Outgoing normal call; F-02; {CC-INFO}, <<Multi keypad>>, "dialling pause" handling |
| | TC_FT_CC_BV_CI_05 | Outgoing normal call; F-10; {CC-INFO}, <<Multi keypad>>, "Dialling pause" handling |
| | TC_FT_CC_BV_CI_06 | Outgoing normal call; F-02; {CC-INFO}, <<Multi keypad>>, "Go to DTMF defined tone length" handling |
| | TC_FT_CC_BV_CI_07 | Outgoing normal call; F-10; {CC-INFO}, <<Multi keypad>>, "Go to DTMF defined tone length" handling |
| | TC_FT_CC_BV_CI_08 | Outgoing normal call; F-02; {CC-INFO}, <<Multi keypad>>, "Go to DTMF infinite tone length" handling |
| | TC_FT_CC_BV_CI_09 | Outgoing normal call; F-10; {CC-INFO}, <<Multi keypad>>, "Go to DTMF infinite tone length" handling |
| | TC_FT_CC_BV_CI_10 | Outgoing normal call; F-10; {CC-INFO}, <<Multi keypad>>, "0-9, star, hash mark" handling |
| | TC_FT_CC_BV_CI_11 | Internal call. (There is no test case defined in ETS 300 497-9 [26] due to difficulties of predicting the IUT behaviour) |
| | TC_FT_CC_BV_CI_12 | FT handling <<Terminal capability>>. (There is no test case defined in ETS 300 497-9 [26] due to difficulties of predicting the IUT behaviour) |
| FT/CC/BV/CR/ | TC_FT_CC_BV_CR_01 | Outgoing normal call; F-02; IUT initiated normal release |
| | TC_FT_CC_BV_CR_02 | F-10; IUT initiated normal release |
| | TC_FT_CC_BV_CR_03 | Incoming call; F-07; IUT initiated normal release |
| | TC_FT_CC_BV_CR_04 | Outgoing call; F-02; PT initiated normal release |
| | TC_FT_CC_BV_CR_05 | F-10; PT initiated normal release |
| | TC_FT_CC_BV_CR_06 | Incoming call; F-07; PT initiated normal release |
| | TC_FT_CC_BV_CR_07 | Incoming call; F-07; PT initiated abnormal release |
| | TC_FT_CC_BV_CR_08 | F-10; PT initiated abnormal release |
| | TC_FT_CC_BV_CR_09 | Incoming call; F-06; PT initiated abnormal release |
| | TC_FT_CC_BV_CR_10 | F-10; PT initiated partial release |
| | TC_FT_CC_BV_CR_11 | F-10; FT initiated partial release |
| FT/CC/RS/ | TC_FT_CC_RS_04 | Register recall. (There is no test case defined in ETS 300 497-9 [26] due to difficulties of predicting the IUT behaviour) |
| | TC_FT_CC_RS_07 | Incoming call; T-00; {CC-SETUP}, <<Calling party number>> provision (CLIP support) |

(continued)

Table 2 (continued)

| Test Case Index | | |
|----------------------|-------------------|---|
| Test Group Reference | Test Case Id | Description |
| FT/CC/BO/ | TC_FT_CC_BO_01 | F-10; unexpected {CC-ALERTING} F-02; unexpected {CC-SETUP} |
| | TC_FT_CC_BO_02 | F-19; receipt of {CC-RELEASE}; release collisions handling |
| FT/CC/BI/ | TC_FT_CC_BI_01 | F-00; {CC-SETUP} mandatory I.E. missing; answer upon with {CC-RELEASE-COM} |
| | TC_FT_CC_BI_02 | F-00; {CC-SETUP} wrong mandatory I.E.; answer upon with {CC-RELEASE-COM} |
| | TC_FT_CC_BI_03 | F-00; {CC-SETUP}-like message, non {CC-SETUP} unrecognised message type; ignore |
| | TC_FT_CC_BI_04 | F-00; to short message to contain the complete <<Message type>>; ignore |
| FT/CC/TI/ | TC_FT_CC_TI_01 | Outgoing call; F-02; timer F-<CC.01> expiry ($\pm 5\%$ margin); IUT sends {CC-RELEASE} |
| | TC_FT_CC_TI_02 | Outgoing call; F-02; restart of timer F-<CC.01> on receipt of {CC-INFO} |
| | TC_FT_CC_TI_03 | Outgoing call; F-19; timer F-<CC.02> expiry ($\pm 5\%$ margin); IUT sends {CC-RELEASE-COM} |
| | TC_FT_CC_TI_04 | Outgoing call; F-06; timer F-<CC.03> expiry ($\pm 5\%$ margin); IUT sends {CC-RELEASE-COM} |
| FT/MM/BV/ID/ | TC_FT_MM_BV_ID_01 | Identity request procedure; IUT initiated |
| FT/MM/BV/AU/ | TC_FT_MM_BV_AU_01 | Authentication of PT; PT has no stored ZAP value and service class info |
| | TC_FT_MM_BV_AU_02 | Authentication of PT; ZAP increment; PT has stored ZAP value and service class info; PT authenticates FT before answering |
| | TC_FT_MM_BV_AU_03 | Authentication of user; PT has no stored ZAP value and service class info |
| | TC_FT_MM_BV_AU_04 | Authentication of FT |
| | TC_FT_MM_BV_AU_05 | Authentication of FT; Unsupported key requested; IUT rejects |
| | TC_FT_MM_BV_AU_06 | Authentication of PT; store DCK ; PT has no stored ZAP value and service class info |
| FT/MM/BV/LO/ | TC_FT_MM_BV_LO_01 | Location registration; a38=1 at locking and at the beginning of the procedure; request with IPUI |
| | TC_FT_MM_BV_LO_02 | Location registration; a38=1 at locking and at the beginning of the procedure; request with unknown IPUI; reject |
| | TC_FT_MM_BV_LO_03 | Location registration; a38=1 at locking and at the beginning of the procedure; request with IPUI; IUT assigns TPUI |
| | TC_FT_MM_BV_LO_05 | Location update; a38=1 at locking; {MM-INFO-SUGGEST}; |
| | TC_FT_MM_BV_LO_06 | Location registration; a38=1 at locking; a38=0 at the beginning of the procedure; request with IPUI |
| FT/MM/BV/AR/ | TC_FT_MM_BV_AR_01 | Obtain access rights; both sides use AC indication; IUT sends the whole PARK |
| | TC_FT_MM_BV_AR_02 | Obtain access rights; service class assign |
| | TC_FT_MM_BV_AR_03 | Terminate access rights; IUT(FT) initiated; PT authenticates FT |
| | TC_FT_MM_BV_AR_06 | Obtain access rights; both sides use UAK indication; IUT sends the whole PARK |
| | TC_FT_MM_BV_AR_07 | Obtain access rights; ZAP value assign |
| FT/MM/BV/KA/ | TC_FT_MM_BV_KA_01 | Key allocate; IUT initiated |

(continued)

Table 2 (continued)

| Test Case Index | | |
|----------------------|-------------------|--|
| Test Group Reference | Test Case Id | Description |
| | TC_FT_MM_BV_KA_02 | Key allocate; IUT initiated; "implicit PT authentication" failure; IUT rejects |
| | TC_FT_MM_BV_KA_03 | Key allocate; IUT initiated; PT rejects; IUT keeps AG |
| FT/MM/BV/CH/ | TC_FT_MM_BV_CH_01 | Cipher switching; PT initiated; "cipher-off" to "cipher-on" |
| | TC_FT_MM_BV_CH_02 | Cipher switching; PT initiated; "cipher-on" to "cipher-off" |
| | TC_FT_MM_BV_CH_03 | Cipher switching; IUT(FT) initiated; "cipher-off" to "cipher-on" |
| | TC_FT_MM_BV_CH_04 | Cipher switching; IUT(FT) initiated; "cipher-on" to "cipher-off" |
| | TC_FT_MM_BV_CH_05 | Cipher switching; PT initiated with "unsupported cipher key"; IUT rejects |
| | TC_PT_MM_BV_CH_06 | Cipher switching; IUT(PT) initiated; "cipher-off" to "cipher-on"; successful intra-cell bearer handover |
| | TC_PT_MM_BV_CH_07 | Cipher switching; FT initiated; "cipher-off" to "cipher-on"; successful intra-cell bearer handover |
| | TC_PT_MM_BV_CH_08 | Cipher switching; IUT(PT) initiated; "cipher-off" to "cipher-on"; successful inter-cell bearer handover |
| | TC_PT_MM_BV_CH_09 | Cipher switching; FT initiated; "cipher-off" to "cipher-on"; successful inter-cell bearer handover |
| | TC_PT_MM_BV_CH_10 | Cipher switching; IUT(PT) initiated; "cipher-off" to "cipher-on" fails; release of link |
| | TC_PT_MM_BV_CH_11 | Cipher switching; FT initiated; "cipher-off" to "cipher-on" fails; release of link. |
| | TC_PT_MM_BV_CH_12 | Cipher switching; IUT(PT) initiated; "cipher-off" to "cipher-on"; "cipher-on" to "cipher-off" fails; release of link |
| | TC_PT_MM_BV_CH_13 | Cipher switching; FT initiated; "cipher-off" to "cipher-on"; "cipher-on" to "cipher-off" fails; release of link |
| FT/MM/BO/ | TC_FT_MM_BO_01 | Cipher switching; IUT(FT) initiated; ignoring unexpected {IDENTITY-REPLY} |
| FT/MM/BI/ | TC_FT_MM_BI_01 | Identity request; PT sends unrecognised message; IUT ignores |
| | TC_FT_MM_BI_02 | Obtain access rights; {ACCESS-RIGHTS-REQUEST} missing <<Auth type>>; IUT sends {ACCESS-RIGHTS-REJECT} |
| | TC_FT_MM_BI_03 | Obtain access rights; {ACCESS-RIGHTS-REQUEST} with <<Auth type>> exceeding the max. allowed length; IUT sends {ACCESS-RIGHTS-REJECT} |
| FT/MM/TI/ | TC_FT_MM_TI_01 | Identity request; timer F-<MM_ident.2> expiry ($\pm 5\%$ margin) (- 10% margin) |
| | TC_FT_MM_TI_02 | Authentication of PT; timer F-<MM_auth.1> expiry ($\pm 5\%$ margin) (- 10% margin) |
| | TC_FT_MM_TI_03 | Authentication of user; timer F-<MM_auth.2> expiry ($\pm 5\%$ margin) (- 10% margin) |
| | TC_FT_MM_TI_04 | Terminate access rights; IUT(FT) initiated; timer F-<MM_access.2> expiry ($\pm 5\%$ margin) (- 10% margin) |
| | TC_FT_MM_TI_05 | Key allocation; timer F-<MM_key.1> expiry ($\pm 5\%$ margin) (- 10% margin) |
| | TC_FT_MM_TI_06 | Cipher switching; IUT(FT) initiated; timer F-<MM_cipher.1> expiry ($\pm 5\%$ margin) |
| | TC_FT_MM_TI_07 | Location registration with TPUI assignment; timer F-<MM_ident.1> expiry ($\pm 5\%$ margin) |

(continued)

Table 2 (concluded)

| Test Case Index | | |
|---------------------------|-------------------|---|
| Test Group Reference | Test Case Id | Description |
| FT/ME/BV/ | TC_FT_ME_BV_01 | Incoming call and authentication of FT handled in parallel |
| | TC_FT_ME_BV_02 | Authentication of user interrupted by Authentication of FT |
| | TC_FT_ME_BV_03 | CC call and location registration in parallel |
| FT/ME/BO/ | TC_FT_ME_BO_01 | Authentication of PT; ignore of {LOCATE-REQUEST} (lower priority) |
| FT/LC/BV/LE/ | TC_FT_LC_BV_LE_01 | Indirect IUT(FT) link establishment procedure; correct PT answer |
| | TC_FT_LC_BV_LE_02 | Indirect IUT(FT) link establishment procedure; {LCE-PAGE-RESPONSE} with mismatching IPUI; IUT rejects and release the link |
| | TC_FT_LC_BV_LE_03 | Direct PT initiated link establishment procedure |
| FT/LC/BV/LR/ | TC_FT_LC_BV_LR_01 | Link exists; PT initiated "normal" link release |
| | TC_FT_LC_BV_LR_02 | Link exists; MM entity ceases to use the link; no other entity uses the link; IUT maintains the link <LCE.02> time |
| | TC_FT_LC_BV_LR_03 | Link exists; CC call is terminated; FT initiated link release |
| | TC_FT_LC_BV_LR_04 | Link exists; CC entity ceases to use the link partial release agreed; no other entity uses the link; IUT maintains the link <LCE.02> time |
| FT/LC/BI/ | TC_FT_LC_BI_01 | Protocol discriminator value error -unsupported service; IUT ignores |
| | TC_FT_LC_BI_04 | {AUTH-REQUEST} with illegal transaction id.; ignore |
| | TC_FT_LC_BI_05 | Identity request procedure; {IDENTITY-REPLY} with transaction id. flag='0'; ignore |
| | TC_FT_LC_BI_07 | F-10; link fails; IUT clears the call |
| FT/LC/TI/ | TC_FT_LC_TI_01 | Link exists; normal link release is requested; timer <LCE.01> expiry. (There is no test case defined in ETS 300 497-9 [26] due to difficulties of predicting the IUT behaviour) |
| | TC_FT_LC_TI_02 | MM ceases to use the link; no other entity uses the link; timer <LCE.02> expiry ($\pm 5\%$ margin) |
| | TC_FT_LC_TI_03 | Indirect IUT(FT) initiated link establishment; no answer; timer <LCE.03> expiry ($\pm 5\%$ margin) |
| Detailed Comments: | | |
| 1. The FT is the IUT. | | |

Subclause 4.2

Modify subclause 4.2 as follows:

This subclause includes list of the test groups and the abstract test cases relevant for GAP PTS - DLC layer FT derived from ETS 300 497-5 [22].

The page number referenced is the relative page number in the corresponding ETS where the particular item can be found.

Subclause 4.2.2

Delete the entry for "TC_A_BV_004" table 4, as follows:

| | | |
|--|-------------|--|
| | TC_A_BV_003 | I-Frame acknowledgement; accepting an I-Frame command with correct N(S) and N(R) values as an acknowledgement. |
| | TC_A_BV_004 | re-establishment request acceptance; Class A established state |
| | TC_A_BV_005 | timer re transmission phase; acceptance of a RR response frame with correct N(R) value as an acknowledgement |
| | | |

Subclause 4.3

Modify subclause 4.3 as follows:

This subclause includes list of the test groups and the abstract test cases relevant for GAP PTS - MAC FT layer derived from ETS 300 497-3 [20].

~~The page number referenced is the relative page number in the corresponding ETS where the particular item can be found.~~

Subclause 4.3.1

Replace table 5 with the following table 5:

Table 5

| Test Suite Structure | |
|---|--|
| Suite Name: mac_ft | |
| Standards Ref: ETS 300 444 [8]; ETS 300 497-3 [20] | |
| Profile ICS Ref: ETS 300 474 [27] | |
| Profile IXIT Ref: ETS 300 494-3 | |
| Test Method: remote (modified) | |
| Comments: | |
| Test Group Reference | Test Group Objective |
| FT/ | Verify the correct implementation of the FT (IUT) MAC layer |
| FT/DB/ | Verify the correct implementation of the Downlink broadcast services |
| FT/DB/CA/ | Limited testing that the observable capabilities of the IUT concerning the downlink broadcast service are in accordance with the static conformance requirements and the additional capabilities claimed in the PROFILE ICS/PROFILE IXIT |
| FT/DB/BV/ | To tests the behaviour of the IUT in relation to syntactically and contextual correct behaviour of the test system |
| FT/PG/ | Verify the correct implementation of the paging services |
| FT/PG/CA/ | Limited testing that the observable capabilities of the IUT concerning the paging services are in accordance with the static conformance requirements and the additional capabilities claimed in the PROFILE ICS/PROFILE IXIT |
| FT/PG/BV/ | To tests the behaviour of the IUT in relation to syntactically and contextual correct behaviour of the test system |
| FT/BS/ | Verify the correct implementation of connection oriented bearer setup procedures |
| FT/BS/CA/ | Limited testing that the observable capabilities of the IUT concerning the connection oriented bearer setup procedures are in accordance with the static conformance requirements and the additional capabilities claimed in the PROFILE ICS/PROFILE IXIT |
| FT/BS/BV/ | To tests the behaviour of the IUT in relation to syntactically and contextual correct behaviour of the test system |
| FT/BH/ | Verify the correct implementation of connection oriented bearer handover procedures |
| FT/BH/CA/ | Limited testing that the observable capabilities of the IUT concerning the connection oriented bearer handover procedures are in accordance with the static conformance requirements and the additional capabilities claimed in the PROFILE ICS/PROFILE IXIT |
| FT/BH/BV/ | To tests the behaviour of the IUT in relation to syntactically and contextual correct behaviour of the test system |
| FT/BR/ | Verify the correct implementation of connection oriented bearer release procedures |
| FT/BR/CA/ | Limited testing that the observable capabilities of the IUT concerning the connection oriented bearer release procedures are in accordance with the static conformance requirements and the additional capabilities claimed in the PROFILE ICS/PROFILE IXIT |
| FT/DT/ | Verify the correct implementation of connection oriented data transfer procedures |
| (continued) | |

Table 5 (concluded)

| Test Suite Structure | |
|-----------------------------|--|
| FT/DT/CA/ | Limited testing that the observable capabilities of the IUT concerning the connection oriented data transfer procedures are in accordance with the static conformance requirements and the additional capabilities claimed in the PROFILE ICS/PROFILE IXIT |
| FT/DT/BV/ | To tests the behaviour of the IUT in relation to syntactically and contextual correct behaviour of the test system |
| FT/DT/BI/ | To check the behaviour of the of the IUT in response to invalid messages |
| FT/LM/ | Verify the correct implementation of the LLME MAC layer management procedures |
| FT/LM/CA/ | Limited testing that the observable capabilities of the IUT concerning the LLME MAC layer management procedures are in accordance with the static conformance requirements and the additional capabilities claimed in the PROFILE ICS/PROFILE IXIT |
| Detailed Comments: | |

Subclause 4.3.2

Replace table 6 with the following table 6:

Table 6

| Test Case Index | | |
|----------------------|----------------|---|
| Test Group Reference | Test Case Id | Description |
| FT/DB/CA/ | TC_FT_DB_CA_00 | Active_idle; NT message in frame 14 |
| | TC_FT_DB_CA_01 | Active_idle; NT message in frame 0 every T205 seconds |
| | TC_FT_DB_CA_02 | Active_idle; QT message in frame 8; each multiframe |
| | TC_FT_DB_CA_03 | Active_idle; static system information in QT message in frame 8; each 8 multiframe |
| | TC_FT_DB_CA_04 | Active_idle; fixed part capabilities in QT message in frame 8; each 8 multiframe |
| | TC_FT_DB_CA_05 | Active_idle; multiframe number in QT message in frame 8; each 8 multiframe |
| | TC_FT_DB_CA_06 | Active_idle; SARI list in QT message in frame 8; each 4 multiframe |
| | TC_FT_DB_CA_07 | Active_idle; Extended carrier information in QT message in frame 8; multiframe after the one containing the Static system information |
| FT/DB/BV/ | TC_FT_DB_BV_03 | Active_idle; SARI exists; NT message; E-bit indicating SARI available |
| FT/PG/CA/ | TC_FT_PG_CA_00 | Active_idle; paging; short page message transmission |
| | TC_FT_PG_CA_01 | Active_idle; zero page message transmission |
| FT/PG/BV/ | TC_FT_PG_BV_01 | Active_idle; blind slot announcement every 10s |
| FT/BS/CA/ | TC_FT_BS_CA_00 | Active_idle; PT initiated single bearer setup |
| FT/BS/BV/ | TC_FT_BS_BV_00 | Active_traffic/Active_traffic_and_idle; duplex bearer; T201 expiry; bearer release |
| FT/BH/CA/ | TC_FT_BH_CA_00 | Active_traffic/Active_traffic_and_idle; PT initiated intracell bearer handover |
| | TC_FT_BH_CA_01 | Active_traffic/Active_traffic_and_idle; PT initiated intercell bearer handover |
| FT/BH/BV/ | TC_FT_BH_BV_00 | Active_traffic/Active_traffic_and_idle; encryption enabled; PT initiated intracell bearer handover |
| | TC_FT_BH_BV_01 | Active_traffic/Active_traffic_and_idle; encryption enabled; PT initiated intercell bearer handover |
| FT/BR/CA/ | TC_FT_BR_CA_00 | Active_traffic/Active_traffic_and_idle; unacknowledged release; release message received |
| FT/DT/CA/ | TC_FT_DT_CA_00 | Active_traffic/Active_traffic_and_idle; CS segment re-transmission till acknowledgement in the same ARQ window |
| | TC_FT_DT_CA_01 | Active_traffic/Active_traffic_and_idle; no transmission of new CS segment before acknowledgement |
| | TC_FT_DT_CA_02 | Active_traffic/Active_traffic_and_idle; numbering of the CS segments |
| | TC_FT_DT_CA_03 | Active_traffic/Active_traffic_and_idle; basic connection; switch on encryption mode |
| | TC_FT_DT_CA_04 | Active_traffic/Active_traffic_and_idle; basic connection; switch off encryption mode |
| | | (continued) |

Table 6 (concluded)

| Test Case Index | | |
|---------------------------|---|--|
| Test Group Reference | Test Case Id | Description |
| FT/DT/BV/ | TC_FT_DT_BV_00 | Active_traffic/Active_traffic_and_idle; basic connection; switch on encryption mode failure; connection release |
| | TC_FT_DT_BV_01 | Active_traffic/Active_traffic_and_idle; basic connection; switch off encryption mode failure; connection release |
| FT/DT/BI/ | TC_FT_DT_BI_00 TC_FT_DT_BI_00 | Active_traffic/Active_traffic_and_idle; IN_minimum_delay data, A-field R-CRC error handling; respond Q2=0 |
| | TC_FT_DT_BI_01 | Active_traffic/Active_traffic_and_idle; IN_minimum_delay data transfer; Z-field error; Q1&Q2 setting |
| | | |
| FT/LM/CA/ | TC_FT_LM_CA_05 | Active_traffic/Active_traffic_and_idle; bearer handover; bearer release within T203 sec |
| Detailed Comments: | | |
| 1. The FT is the IUT. | | |

Subclause B.6.1

replace the table given in subclause B.6.1 with the following table:

| TC Name | Selected [Yes/No] | Run [Yes/No] | Verdict [P/F/I] | Observation |
|-------------------|----------------------|-----------------|-----------------|-------------|
| TC_FT_CC_BV_OC_01 | | | | |
| TC_FT_CC_BV_OC_06 | | | | |
| TC_FT_CC_BV_IC_01 | | | | |
| TC_FT_CC_BV_CI_01 | | | | |
| TC_FT_CC_BV_CI_02 | | | | |
| TC_FT_CC_BV_CI_03 | | | | |
| TC_FT_CC_BV_CI_04 | | | | |
| TC_FT_CC_BV_CI_05 | | | | |
| TC_FT_CC_BV_CI_06 | | | | |
| TC_FT_CC_BV_CI_07 | | | | |
| TC_FT_CC_BV_CI_08 | | | | |
| TC_FT_CC_BV_CI_09 | | | | |
| TC_FT_CC_BV_CI_10 | | | | |
| TC_FT_CC_BV_CI_11 | | | | |
| TC_FT_CC_BV_CI_12 | | | | |
| TC_FT_CC_BV_CR_01 | | | | |
| TC_FT_CC_BV_CR_02 | | | | |
| TC_FT_CC_BV_CR_03 | | | | |
| TC_FT_CC_BV_CR_04 | | | | |
| TC_FT_CC_BV_CR_05 | | | | |
| TC_FT_CC_BV_CR_06 | | | | |
| TC_FT_CC_BV_CR_07 | | | | |
| TC_FT_CC_BV_CR_08 | | | | |
| TC_FT_CC_BV_CR_09 | | | | |
| TC_FT_CC_BV_CR_10 | | | | |
| TC_FT_CC_BV_CR_11 | | | | |
| TC_FT_CC_RS_01 | | | | |
| TC_FT_CC_RS_07 | | | | |
| TC_FT_CC_BO_01 | | | | |
| TC_FT_CC_BO_02 | | | | |
| TC_FT_CC_BI_01 | | | | |
| TC_FT_CC_BI_02 | | | | |
| TC_FT_CC_BI_03 | | | | |
| TC_FT_CC_BI_04 | | | | |
| TC_FT_CC_TI_01 | | | | |
| TC_FT_CC_TI_02 | | | | |
| TC_FT_CC_TI_03 | | | | |
| TC_FT_CC_TI_04 | | | | |
| TC_FT_MM_BV_ID_01 | | | | |
| TC_FT_MM_BV_AU_01 | | | | |
| TC_FT_MM_BV_AU_02 | | | | |
| TC_FT_MM_BV_AU_03 | | | | |
| TC_FT_MM_BV_AU_04 | | | | |
| TC_FT_MM_BV_AU_05 | | | | |
| TC_FT_MM_BV_AU_06 | | | | |
| TC_FT_MM_BV_LO_01 | | | | |
| TC_FT_MM_BV_LO_02 | | | | |
| TC_FT_MM_BV_LO_03 | | | | |
| TC_FT_MM_BV_LO_05 | | | | |
| TC_FT_MM_BV_LO_06 | | | | |
| TC_FT_MM_BV_AR_01 | | | | |
| TC_FT_MM_BV_AR_02 | | | | |
| TC_FT_MM_BV_AR_03 | | | | |

(continued)

(concluded)

| TC Name | Selected [Yes/No] | Run [Yes/No] | Verdict [P/F/I] | Observation |
|-------------------|-------------------|--------------|-----------------|-------------|
| TC_FT_MM_BV_AR_06 | | | | |
| TC_FT_MM_BV_AR_07 | | | | |
| TC_FT_MM_BV_KA_01 | | | | |
| TC_FT_MM_BV_KA_02 | | | | |
| TC_FT_MM_BV_KA_03 | | | | |
| TC_FT_MM_BV_CH_01 | | | | |
| TC_FT_MM_BV_CH_02 | | | | |
| TC_FT_MM_BV_CH_03 | | | | |
| TC_FT_MM_BV_CH_04 | | | | |
| TC_FT_MM_BV_CH_05 | | | | |
| TC_FT_MM_BV_CH_06 | | | | |
| TC_FT_MM_BV_CH_07 | | | | |
| TC_FT_MM_BV_CH_08 | | | | |
| TC_FT_MM_BV_CH_09 | | | | |
| TC_FT_MM_BV_CH_10 | | | | |
| TC_FT_MM_BV_CH_11 | | | | |
| TC_FT_MM_BV_CH_12 | | | | |
| TC_FT_MM_BV_CH_13 | | | | |
| TC_FT_MM_BO_01 | | | | |
| TC_FT_MM_BI_01 | | | | |
| TC_FT_MM_BI_02 | | | | |
| TC_FT_MM_BI_03 | | | | |
| TC_FT_MM_TI_01 | | | | |
| TC_FT_MM_TI_02 | | | | |
| TC_FT_MM_TI_03 | | | | |
| TC_FT_MM_TI_04 | | | | |
| TC_FT_MM_TI_05 | | | | |
| TC_FT_MM_TI_06 | | | | |
| TC_FT_MM_TI_07 | | | | |
| TC_FT_ME_BV_01 | | | | |
| TC_FT_ME_BV_02 | | | | |
| TC_FT_ME_BV_03 | | | | |
| TC_FT_ME_BO_04 | | | | |
| TC_FT_LC_BV_LE_01 | | | | |
| TC_FT_LC_BV_LE_02 | | | | |
| TC_FT_LC_BV_LE_03 | | | | |
| TC_FT_LC_BV_LR_01 | | | | |
| TC_FT_LC_BV_LR_02 | | | | |
| TC_FT_LC_BV_LR_03 | | | | |
| TC_FT_LC_BV_LR_04 | | | | |
| TC_FT_LC_BI_01 | | | | |
| TC_FT_LC_BI_04 | | | | |
| TC_FT_LC_BI_05 | | | | |
| TC_FT_LC_BI_07 | | | | |
| TC_FT_LC_TI_01 | | | | |
| TC_FT_LC_TI_02 | | | | |
| TC_FT_LC_TI_03 | | | | |

Subclause B.6.2

Delete the entry for "TC_A_BV_004" table 4, as follows:

| | | | | |
|-------------|--|--|--|--|
| TC_A_BV_003 | | | | |
| TC_A_BV_004 | | | | |
| TC_A_BV_005 | | | | |

Subclause B.6.3

Modify the line containing test group reference "TC_FT__DT_BI_00", as follows:

| | | | | |
|-----------------|--|--|--|--|
| TC_FT_DT_BV_01 | | | | |
| TC_FT__DT_BI_00 | | | | |
| TC_FT_DT_BI_00 | | | | |
| TC_FT_DT_BI_01 | | | | |

History

| Document history | |
|-------------------------|--|
| August 1996 | First Edition |
| January 1997 | Public Enquiry PE 9722: 1997-01-31 to 1997-05-30 |
| | |
| | |
| | |
| | |