

# ETSI TS 125 327 V11.1.0 (2014-07)



**Universal Mobile Telecommunications System (UMTS);  
High Speed Packet Access (HSPA);  
Requirements on User Equipments (UEs)  
supporting a release-independent frequency band  
and multi-carrier configuration  
(3GPP TS 25.327 version 11.1.0 Release 11)**



---

**Reference**

RTS/TSGR-0225327vb10

---

**Keywords**

UMTS

**ETSI**

---

650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° 7803/88

---

**Important notice**

The present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the only prevailing document is the print of the Portable Document Format (PDF) version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

[http://portal.etsi.org/chaicor/ETSI\\_support.asp](http://portal.etsi.org/chaicor/ETSI_support.asp)

---

**Copyright Notification**

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2014.

All rights reserved.

**DECT™**, **PLUGTESTS™**, **UMTS™** and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are Trade Marks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

**GSM®** and the GSM logo are Trade Marks registered and owned by the GSM Association.

---

## Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://ipr.etsi.org>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

---

## Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

---

## Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**may not**", "**need**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

---

# Contents

Intellectual Property Rights .....	2
Foreword.....	2
Modal verbs terminology.....	2
Foreword.....	4
1 Scope .....	5
2 References .....	5
3 Definitions, symbols and abbreviations .....	5
3.1 Definitions .....	5
3.2 Abbreviations .....	5
4 DB-DC-HSDPA configurations independent of release .....	6
4.1 Void.....	6
4.2 Void.....	6
4.3 DB-DC-HSDPA configuration 6.....	6
4.3.1 RF requirements.....	6
4.3.2 Signalling requirements .....	6
5 4C-HSDPA configurations independent of release .....	7
5.1 Single-band contiguous configurations .....	7
5.1.1 Void .....	7
5.1.2 Void .....	7
5.2 Dual-band configurations .....	7
5.2.1 Void .....	7
5.2.2 Void .....	7
5.2.3 Void .....	7
5.2.4 4C-HSDPA configuration I-1-XXXII-2 .....	7
5.2.4.1 RF requirements .....	7
5.2.4.2 Signalling requirements .....	7
5.2.5 4C-HSDPA configuration I-2-XXXII-1 .....	8
5.2.5.1 RF requirements .....	8
5.2.5.2 Signalling requirements .....	8
6 8C-HSDPA configurations independent of release .....	8
<b>Annex A (informative): Change history .....</b>	<b>9</b>
History .....	10

---

# Foreword

This Technical Specification has been produced by the 3<sup>rd</sup> Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

---

# 1 Scope

The present document specifies requirements on UEs supporting a DB-DC-HSDPA, 4C-HSDPA, and 8C-HSDPA configuration that is independent of release. TSG-RAN has agreed that the standardisation of new configurations may be independent of a release. However, in order to implement a UE that conforms to a particular release but supports a configuration that is specified in a later release, it is necessary to specify some extra requirements.

For example, Band I-XI combination for DB-DC-HSDPA (referred to as DB-DC-HSDPA configuration 4 in [2]) is contained in the Release 10 specifications. In order to implement a UE conforming to Release 9 but supporting this configuration, it is necessary for the UE to additionally conform to some parts of the Release 10 specifications, such as the radio frequency and radio resource management requirements for the configuration.

Similarly, 4C-HSDPA configuration I-3 is contained in the Release 11 specification [3]. In order to implement a UE conforming to Release 10, but supporting this configuration, it is necessary for the UE to additionally conform to some parts of the Release 11 specifications.

---

# 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] 3GPP TS 25.101 (Release 10): "User Equipment (UE) radio transmission and reception (FDD)".
- [3] 3GPP TS 25.101 (Release 11): "User Equipment (UE) radio transmission and reception (FDD)".
- [4] 3GPP TS 25.101 (Release 12): "User Equipment (UE) radio transmission and reception (FDD)".
- [5] 3GPP TS 25.331 (Release 12): "Radio Resource Control Protocol".

---

# 3 Definitions, symbols and abbreviations

## 3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

## 3.2 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

DB-DC-HSDPA	Dual Band Dual Cell HSDPA
4C-HSDPA	Four-carrier HSDPA
8C-HSDPA	Eight-carrier HSDPA

## 4 DB-DC-HSDPA configurations independent of release

4.1 Void

4.2 Void

### 4.3 DB-DC-HSDPA configuration 6

DB-DC-HSDPA Configuration 6, i.e. Band I-XXXII combination, is specified in Release 12 in [4] but is defined as a release-independent frequency band combination. This approach aligns DB-DC-HSDPA configuration 6 with other DB-DC-HSDPA configurations when considering features that have to be supported in different releases.

UEs that conform to Release 11 and support DB-DC-HSDPA configuration 6 shall support the following requirements of Release 12.

#### 4.3.1 RF requirements

The UE shall comply with the RF requirements for DB-DC-HSDPA configuration 6, as specified in [4]. These requirements are:

**Table 4.3.1-1: RF Requirements for DB-DC-HSDPA Configuration 6 UE**

Section / Clause	Description
5.2	Frequency bands
5.4	Channel arrangement
6.2.1	UE maximum output power
7.3	Reference sensitivity level
7.4	Maximum input level
7.5	Adjacent channel selectivity
7.6	Blocking characteristics
7.7	Spurious response
7.8	Intermodulation characteristics
7.9	Spurious emissions
7.10	Reference input power adjustment for a dual band device
B.2.2	Multi-path fading propagation conditions

All the receiver core requirements, which are defined relative to reference sensitivity level, shall consider the reference sensitivity as specified in TS 25.101 REL-12 [4].

#### 4.3.2 Signalling requirements

In order to signal its radio access capabilities, the UE shall support the DB-DC-HSDPA configuration index 6 for the IE "Band Combination" in the IE "Radio Access Capability Band Combination List".

In order to signal UE's measurement capabilities for band XXXII, the UE shall support the RRC extension for the parameter value "Band XXXII" for the IE "FDD frequency band 3" contained within the IE "Measurement capability extension" [5].

## 5 4C-HSDPA configurations independent of release

### 5.1 Single-band contiguous configurations

5.1.1 Void

5.1.2 Void

### 5.2 Dual-band configurations

5.2.1 Void

5.2.2 Void

5.2.3 Void

#### 5.2.4 4C-HSDPA configuration I-1-XXXII-2

4C-HSDPA configuration I-1-XXXII-2, i.e. 1+2 carriers in Band I-XXXII combination, is specified in Release 12 in [4] but is defined as a release-independent configuration. This approach aligns 4C-HSDPA configuration I-1-XXXII-2 with other 4C-HSDPA configurations when considering features that have to be supported in different releases.

UEs that conform to Release 11 and support 4C-HSDPA configuration I-1-XXXII-2 shall support the following requirements of Release 12.

##### 5.2.4.1 RF requirements

The UE shall comply with the RF requirements for 4C-HSDPA configuration I-1-XXXII-2, as specified in [4]. These requirements are:

**Table 5.2.4.1-1: RF Requirements for 4C-HSDPA Configuration I-1-XXXII-2 UE**

Section / Clause	Description
5.2	Frequency bands
5.4	Channel arrangement
6.2.1	UE maximum output power
7.3	Reference sensitivity level
7.4	Maximum input level
7.5	Adjacent channel selectivity
7.6	Blocking characteristics
7.7	Spurious response
7.8	Intermodulation characteristics
7.9	Spurious emissions
7.10	Reference input power adjustment for a dual band device
B.2.2	Multi-path fading propagation conditions

##### 5.2.4.2 Signalling requirements

In order to signal UE's measurement capabilities for band XXXII, the UE shall support the RRC extension for the parameter value "Band XXXII" for the IE "FDD frequency band 3" contained within the IE "Measurement capability extension" [5].



## 5.2.5 4C-HSDPA configuration I-2-XXXII-1

4C-HSDPA configuration I-2-XXXII-1, i.e. 2+1 carriers in Band I-XXXII combination, is specified in Release 12 in [4] but is defined as a release-independent configuration. This approach aligns 4C-HSDPA configuration I-2-XXXII-1 with other 4C-HSDPA configurations when considering features that have to be supported in different releases.

UEs that conform to Release 11 and support 4C-HSDPA configuration I-2-XXXII-1 shall support the following requirements of Release 12.

### 5.2.5.1 RF requirements

The UE shall comply with the RF requirements for 4C-HSDPA configuration I-2-XXXII-1, as specified in [4]. These requirements are:

**Table 5.2.5.1-1: RF Requirements for 4C-HSDPA Configuration I-2-XXXII-1 UE**

Section / Clause	Description
5.2	Frequency bands
5.4	Channel arrangement
6.2.1	UE maximum output power
7.3	Reference sensitivity level
7.4	Maximum input level
7.5	Adjacent channel selectivity
7.6	Blocking characteristics
7.7	Spurious response
7.8	Intermodulation characteristics
7.9	Spurious emissions
7.10	Reference input power adjustment for a dual band device
B.2.2	Multi-path fading propagation conditions

### 5.2.1.2 Signalling requirements

In order to signal UE's measurement capabilities for band XXXII, the UE shall support the RRC extension for the parameter value "Band XXXII" for the IE "FDD frequency band 3" contained within the IE "Measurement capability extension" [5].

---

## 6 8C-HSDPA configurations independent of release

---

## Annex A (informative): Change history

Change history							
Date	TSG #	TSG Doc.	CR	Rev	Subject/Comment	Old	New
2013-11					Skeleton report based on 25.317 contents	-	1.0.0
2013-12	RP-62	RP-131629			TS 25.327 approved by RAN #62	1.0.0	9.0.0
	RP-62	RP-131980	0002	1	Introduction of TS 25.327	9.0.0	11.0.0
2014-06	RP-64	RP-140872	0008	-	Introduction of the new Band combinations related to Band XXXII	11.0.0	11.1.0

---

# History

<b>Document history</b>		
V11.0.0	January 2014	Publication
V11.1.0	July 2014	Publication