

ETSI TS 126 103 V4.4.0 (2004-12)

Technical Specification

**Digital cellular telecommunications system (Phase 2+);
Universal Mobile Telecommunications System (UMTS);
Speech codec list for GSM and UMTS
(3GPP TS 26.103 version 4.4.0 Release 4)**



Reference

RTS/TSGS-0426103v440

Keywords

GSM, UMTS

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

http://portal.etsi.org/chaicor/ETSI_support.asp

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2004.
All rights reserved.

DECTTM, **PLUGTESTS**TM and **UMTS**TM are Trade Marks of ETSI registered for the benefit of its Members.
TIPHONTM and the **TIPHON logo** are Trade Marks currently being registered by ETSI for the benefit of its Members.
3GPPTM is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://webapp.etsi.org/IPR/home.asp>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Contents

Intellectual Property Rights	2
Foreword.....	2
Foreword.....	4
1 Scope	5
2 Normative references	5
3 Definitions and Abbreviations.....	5
3.1 Definitions	5
3.2 Abbreviations	6
4 General	6
5 3GPP Codec List for OoBTC.....	7
5.1 GSM Full Rate Codec Type (GSM FR)	7
5.2 GSM Half Rate Codec Type (GSM HR).....	7
5.3 GSM Enhanced Full Rate Codec Type (GSM EFR)	8
5.4 Four Adaptive Multi-Rate Codec Types (FR AMR, HR AMR, UMTS AMR, UMTS AMR2)	8
5.5 TDMA Enhanced Full Rate Codec Type (TDMA EFR).....	11
5.6 PDC Enhanced Full Rate Codec Type (PDC_EFR).....	11
6 Codec List for the Call Control Protocol.....	12
6.1 System Identifiers for GSM and UMTS.....	12
6.2 Codec Bitmap	12
6.3 Selected Codec Type.....	13
Annex A (informative): Example Codec List for UMTS	14
Annex B (informative) : Change history	15
History	16

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

1 Scope

The present Technical Specification outlines the Codec Lists in 3GPP including both systems, GSM and UMTS, to be used by the Out of Band Transcoder Control (OoBTC) protocol to set up a call or modify a call in **Transcoder Free Operation** (TrFO) and in "transcoder at the edge" scenarios.

The TS further specifies the coding of the Supported Codec List Information Elements for the UMTS radio access technology.

The Supported Codec List IE includes Codec_Types from the TDMA and PDC systems, to support TFO or TrFO between UMTS and TDMA, or UMTS and PDC.

2 Normative references

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3GPP TS 26.090: "Mandatory Speech Codec speech processing functions; AMR Speech Codec; Transcoding functions".
- [2] 3GPP TS 26.093: "Mandatory Speech Codec speech processing functions; AMR Speech Codec; Source Controlled Rate operation".
- [3] 3GPP TS 26.101: "Mandatory Speech Codec speech processing functions; AMR Speech Codec; Frame Structure".
- [4] 3GPP 46.0xx: "Enhanced Full Rate Codec Recommendations".
- [5] 3GPP 26.0xx: "Adaptive Multi-Rate Codec Recommendations".
- [6] ITU-T Recommendation Q.765.5: "Application transport mechanism - Bearer independent call control (BICC)".
- [7] 3GPP TS 28.062: "Inband Tandem Free Operation (TFO) of Speech Codecs; Service Description; Stage 3".
- [8] 3GPP TS 23.153: "Out of Band Transcoder Control; Stage 2".
- [9] 3GPP TS 24.008: "Mobile Radio Interface - Layer 3 MM/CC Specification".

3 Definitions and Abbreviations

3.1 Definitions

Codec Type: defines a specific type of speech Coding algorithms (e.g. GSM FR, GSM FR AMR)

Codec Mode: defines a specific mode of a Codec Type (e.g. 12,2 kBit/s Mode of the GSM FR AMR)

Organisation Identifier (OID): identifies the standard organisation (e.g. 3GPP) producing a specification for a Codec List. ITU-T is responsible for maintaining the list of Organisation Identifiers

System Identifier (SysID): identifies the radio access technology (e.g. GSM or UMTS) for which the supported Codec List is defined

Other definitions are given in TS 23.153 [8].

3.2 Abbreviations

For the purposes of the present document, the following abbreviations apply:

CoID	Codec IDentifier
DTX	Discontinuous Transmission
GSM	Global System for Mobile communication
OID	Organisation IDentifier (e.g. ITU-T, 3GPP)
OoBTC	Out of Band Transcoder Control
PDC	Personal Digital Communication (synonym for ...)
RX	Receive
SCR	Source Controlled Rate operation (synonym to DTX)
SID	Silence Descriptor
SysID	System Identifier
TDMA	Time Division Multiple Access (synonym for ...)
TFO	T andem F ree O peration (also sometimes called "Transcoder-Through" or "Codec-Bypass")
TrFO	T ranscoder F ree O peration
TX	Transmit
UMTS	Universal Mobile Telecommunications System

4 General

The present Technical Specification outlines the 3GPP internal Codec Lists for both, GSM and UMTS, to be used by the Out of Band Transcoder Control (OoBTC) protocol to set up a call or modify a call in Transcoder Free Operation (TrFO).

It further specifies the coding of the Supported Codec List Information Elements as defined in 3GPP TS 24.008 for the UMTS radio access technology.

Transcoder Free Operation allows the transport of speech signals in the coded domain from one user equipment (UE) to the other user equipment through the radio access network (RAN) and core network (CN), possibly through a transit network (TN). This enables high speech quality, low transmission costs and high flexibility.

The necessary Codec Type selection and resource allocation are negotiated out of band **before** and after call setup. Possible Codec (re-)configuration, Rate Control and DTX signalling may be performed after call setup by additional inband signalling or a combination of inband and out-of-band signalling.

Up to release '99 GSM does not support Transcoder Free Operation, but specifies the Tandem Free Operation (TFO). Tandem Free Operation enables similar advantages, but is based on pure inband signalling **after** call setup. The parameters defined in this Technical Specification allow interaction between TrFO and TFO. They further provide an evolutionary path for GSM towards Transcoder Free Operation.

The GSM and UMTS standards define currently nine different Codec Types: GSM Full Rate, GSM Half Rate, GSM Enhanced Full Rate, Full Rate Adaptive Multi-Rate, Half Rate Adaptive Multi-Rate, UMTS Adaptive Multi-Rate, UMTS Adaptive Multi-Rate 2, TDMA EFR and PDC EFR. Within each radio access technology the following Codec Types may be used, see table 4.1.

Table 4.1: Support of Codec Types in Radio Access Technologies

	TDMA EFR	UMTS AMR2	UMTS AMR	(GSM) HR AMR	(GSM) FR AMR	GSM EFR	GSM HR	GSM FR
CoID	0x07	0x06	0x05	0x04	0x03	0x02	0x01	0x00
GSM	not defined	not possible	not possible	yes, 4 modi	yes, 4 modi	yes	yes	yes
UMTS	yes	yes, 8 modi	R99, UTRAN-only UEs	not defined	not defined	yes	not defined	not defined

								PDC EFR
CoID	0x0F	0x0E	0x0D	0x0C	0x0B	0x0A	0x09	0x08
GSM								not defined
UMTS								yes

CoID is reprinted here in hexadecimal notation. It is defined in section 5.

5 3GPP Codec List for OoBTC

The definition of the common Codec List for Out of Band Transcoder Control (3GPP TS 23.153 [8]) in 3GPP for GSM and UMTS follows the specifications given in ITU Q.765.5 [6]: The most preferred Codec Type is listed first, followed by the second preferred one, and so on. An informative example for a codec list for UMTS can be found in Annex A.

5.1 GSM Full Rate Codec Type (GSM FR)

The Codec IDentification (CoID) code is defined to be: FR_CoID := 0x0000.0000.

The GSM Full Rate Codec Type has no additional parameters.

For information (for exact details see GSM Recommendations):

The GSM Full Rate Codec Type supports one fixed Codec Mode with 13.0 kBit/s.

DTX may be enabled in uplink and in downlink independently of each other. DTX on or off is defined by the network on a cell basis and can not be negotiated at call setup or during the call. The DTX scheme uses one SID frame to mark the end of a speech burst and to start Comfort Noise Generation. Identical SID frames for comfort noise updates are sent in speech pauses about every 480 ms, aligned with the cell's TDMA frame structure. The defined Tandem Free Operation allows the reception of GSM FR DTX information for the downlink direction in all cases. The TFO respectively TrFO partner is prepared to receive DTX information as well.

5.2 GSM Half Rate Codec Type (GSM HR)

The Codec IDentification (CoID) code is defined to be: HR_CoID := 0x0000.0001.

The GSM Half Rate Codec Type has no additional parameters.

For information (for exact details see GSM Recommendations):

The GSM Half Rate Codec Type supports one fixed Codec Mode with 5.60 kBit/s.

DTX may be enabled in uplink and in downlink independently of each other. DTX on or off is defined by the network on a cell basis and can not be negotiated at call setup or during the call. The DTX scheme uses one SID frame to mark the end of a speech burst and to start Comfort Noise Generation. Identical SID frames for comfort noise updates are sent in speech pauses about every 480 ms, aligned with the cell's TDMA frame structure. The defined Tandem Free Operation allows the reception of GSM HR DTX information for the downlink direction in all cases. The TFO respectively TrFO partner shall be prepared to receive DTX information as well.

5.3 GSM Enhanced Full Rate Codec Type (GSM EFR)

The Codec IDentification (CoID) code is defined to be: EFR_CoID := 0x0000.0010.

The GSM Enhanced Full Rate Codec Type has no additional parameters.

For information (for exact details see GSM Recommendations):

The GSM Enhanced Full Rate Codec Type supports one fixed Codec Mode with 12.2 kBit/s.

DTX may be enabled in uplink and in downlink independently of each other. DTX on or off is defined by the network on a cell basis and can not be negotiated at call setup or during the call. The DTX scheme uses one SID frame to mark the end of a speech burst and to start Comfort Noise Generation. It is important to note that the Comfort Noise parameters for this start of the comfort noise generation are calculated at transmitter side from the previous eight speech frames. A DTX hangover period needs to be applied therefore at transmitter side before sending the first SID frame. SID frames with incremental information for comfort noise updates are sent in speech pauses about every 480 ms, aligned with the cell's TDMA frame structure. The defined Tandem Free Operation allows the reception of GSM EFR DTX information for the downlink direction in all cases. The TFO respectively TrFO partner shall be prepared to receive DTX information as well.

5.4 Four Adaptive Multi-Rate Codec Types (FR AMR, HR AMR, UMTS AMR, UMTS AMR2)

The Adaptive Multi-Rate Codec algorithm is applied in GSM and UMTS in four different Codec Types.

The Codec IDentification (CoID) codes are defined to be:

FR_AMR_CoID := 0x0000.0011.
 HR_AMR_CoID := 0x0000.0100.
 UMTS_AMR_CoID := 0x0000.0101.
 UMTS_AMR_2_CoID := 0x0000.0110.

The Single Codec Information Element for AMR Codec Types may have several additional parameters. These parameters are optional in the Supported Codec List (BICC) and in the Available Codec List (BICC), but these parameters shall specify exactly one AMR Configuration for the Selected Codec (BICC), see [8].

Active Codec Set, ACS: eight bits.

Each bit corresponds to one AMR Mode. Setting the bit to '1' means the mode is included, setting the bit to '0' means the mode is not included in the ACS.

Note: Except for HR_AMR all eight AMR modes may be selected, for the HR_AMR only the six lower modes.

Supported Codec Set, SCS: eight bits.

Each bit corresponds to one AMR Mode, as in the ACS. Setting the bit to '1' means the mode is supported, setting the bit to '0' means the mode is not supported. The SCS shall at least contain all modes of the ACS.

Maximal number of codec modes in the ACS, MACS: three bits.

MACS shall be used in the Supported Codec List (BICC) and the Available Codec List (BICC), when it is necessary to restrict the maximum number of modes for the (future) Selected Codec (BICC).

For FR AMR, HR AMR and OHR AMR one up to four, for the UMTS AMR and UMTS AMR2 one up to eight Codec Modes are allowed.

Coding: '001': one, '010': two, ... '111': seven, '000': eight Codec Modes allowed.

Optimisation Mode for ACS, OM: one bit.

OM indicates, whether the sending side supports the modification (optimisation) of its offered ACS for the needs of the distant side.

Coding: "0": Optimisation of the ACS not supported, "1": Optimisation of the ACS supported.

If OM is specified as 'Optimisation of the ACS not supported', then SCS and MACS have no meaning for this Single Codec Information Element; then the SCS shall at least contain all modes of the offered ACS; MACS shall be equal to or larger than the number of modes in the offered ACS.

Usage of this Single Codec Information Element in OoBTC.

In the Single Codec Information Element for the Selected Codec (BICC) the ACS shall be specified exactly.

For FR AMR, HR_AMR and OHR AMR at least one, but not more than four modes shall be included.

For UMTS AMR and UMTS AMR2 at least one, but not more than four modes should be included.

OM shall be set to 'Optimisation of the ACS not supported'.

In the Single Codec Information Element for the Supported Codec List (BICC) and the Available Codec List (BICC) one of the following codings shall be used

- either all parameters (ACS, SCS, MACS and OM) are omitted.
Then per default all possible AMR modes shall be treated as included in ACS and SCS, MACS shall be treated as set to its allowed maximum and OM shall be treated as set to 'Optimisation of the ACS supported'.
- or only the ACS is specified:
Then per default all possible AMR modes shall be treated as included in the SCS, MACS shall be treated as set to its allowed maximum and OM shall be treated as set to 'Optimisation of the ACS supported'.
- or ACS and SCS are specified.
Then per default MACS shall be treated as set to its allowed maximum and OM shall be treated as set to 'Optimisation of the ACS supported'.
- or all parameters (ACS, SCS, MACS and OM) are specified.

Procedures in OoBTC

The procedures for handling of these Single Codec Information Element in the originating, intermediate and terminating nodes are specified in TS 23.153 [8].

The "Single Codec" information element consists of 5 to 8 octets in case of the AMR Codec Types (table 5.4):

Table 5.4: Coding of "Single Codec" for the Adaptive Multi-Rate Codec Types

Octet	Parameter	MSB 8	7	6	5	4	3	2	1 LSB
1 m	Single Codec	Single Codec (see ITU-T Q.765.5 [6])							
2 m	Length Indication	3, 4, 5, 6							
3 m	Compat. Info	Compatibility Information							
4 m	OID	ETSI OID (See ITU-T Q.765.5 [6])							
5 m	CoID	FR_AMR_CoID, HR_AMR_CoID, UMTS_AMR_CoID or UMTS_AMR_2_CoID							
6 o	ACS	12.2	10.2	7.95	7.40	6.70	5.90	5.15	4.75
7 o	SCS	12.2	10.2	7.95	7.40	6.70	5.90	5.15	4.75
8 o	OM, MACS	(spare)	(spare)	(spare)	(spare)	OM	MACS		

with "m" = mandatory and "o" = optional

For information on GSM procedures (for exact details see GSM Recommendations):

The GSM AMR Codec Types comprise eight (Full Rate), respectively six (Half Rate) different Codec Modes: 12,2 ... 4,75 kBit/s.

The active Codec Mode is selected from the Active Codec Set (ACS) by the network (Codec Mode Command) with assistance by the mobile station (Codec Mode Request). This Codec Mode Adaptation, also termed Rate Control, can be performed every 40 ms by going one Codec Mode up or down within the ACS. The Codec Modes in uplink and downlink at one radio leg may be different. In Tandem Free Operation both radio legs (A and B) are considered for the optimal selection of the active Codec Mode in each direction (uplink A and then downlink B, respectively vice versa) by the "Distributed Rate Decision" algorithm. The worst of both radio legs determines the highest allowed Codec Mode, respectively the maximally allowed rate ("Maximum Rate Control"). All rate control commands are transmitted inband: on the radio interface, the BTS-TRAU interface and the TRAU-TRAU interface.

The Active Codec Set is configured at call setup or reconfigured during the call. It consists of one up to maximally four Codec Modes (MACS) at a given time, selected from the Supported Codec Set. The maximal number of Codec Modes and the Supported Codec Set may be constrained by the network to consider resources and radio conditions.

The Active Codec Sets in uplink and downlink are identical.

First, at start up of Tandem Free Operation, Active Codec Sets, the Supported Codec Sets, the MACSs and the OMs are taken into account to determine the optimal common Active Codec Set. In a later phase the Codec Lists of both radio legs may be taken into account to find the optimum configuration. For exact details see 3GPP TS 28.062. All configuration data and update protocols are transmitted inband.

The DTX scheme of the Adaptive Multi-Rate Codec Type marks with a specific SID_FIRST frame the end of a speech burst. SID_FIRST does not contain Comfort Noise parameters. This SID_FIRST starts the comfort noise generation with parameters that are calculated at receiver side (!) from the latest received seven speech frames. A DTX hangover period needs to be applied therefore at transmitter side before sending of this SID_FIRST.

Absolutely coded SID_UPDATE frames follow about every eighth frame (160 ms) in speech pauses. SID_UPDATE frames are sent independently of the cell's TDMA frame structure and are related only to the source signal.

An ONSET frame (typically) precedes in uplink direction the beginning of a new speech burst. DTX on or off is defined by the network on a cell basis. The defined Tandem Free Operation allows the reception of GSM-AMR DTX information for the downlink direction in all cases.

Note: The DTX scheme of the Enhanced Full Rate Codec Type is not compatible with the DTX scheme of the Adaptive Multi-Rate Codec Type in Codec Mode 12.2 kBit/s, although the speech modes of these two Codec Types are bit exact identical.

Informative for terminals of R99 that support only UTRAN access ("UTRAN-only" terminals):

UTRAN-only terminals of R99 may either use UMTS AMR or UMTS AMR2 as default speech version in UTRAN access.

Normative for terminals that support GSM and UTRAN radio access ("dual-mode" terminals):

Dual-mode terminals of R99 and onwards shall use the UMTS AMR2 as the default speech version in UTRAN access. They need not to support the UMTS AMR, because the UMTS AMR2 in terminals is a fully compatible replacement.

Normative for all UMTS terminals of REL-4 and onwards: The UMTS AMR2 shall be the default speech version for UTRAN access in all terminals, UTRAN-only and dual-mode (GSM and UTRAN) of REL-4 and onwards.

For information on UMTS procedures (for exact details see 3GPP TS 28.062 (TFO) and 3GPP TS 23.153 (TrFO)):

The active Codec Mode is selected from the Active Codec Set (ACS) by the network. This Codec Mode Adaptation, also termed Rate Control, can be performed for the UMTS AMR every 20 ms by going to another Codec Mode within the ACS. For the UMTS AMR2 this Codec Mode Adaptation can be performed every 20ms for the downlink traffic channel, but only every 40ms for the uplink radio channel. The UE selects at call setup one of the two possible phases for Codec Mode Adaptation (odd or even frames). During the call changes of the Codec Mode in uplink direction are only allowed in this selected phase. Rate Control commands received in downlink direction are considered at the next possible phase.

By this definition the UMTS AMR2 Codec Type is TFO and TrFO compatible to the FR AMR, HR AMR and UMTS AMR2 Codec Types. In any multi-mode configuration the UMTS_AMR shall be regarded as only compatible to itself, not to any other AMR codec Type, to avoid incompatibilities in TFO-TrFO-TFO interworking scenarios. In single mode configuration, UMTS_AMR and UMTS_AMR_2 are compatible, when both codec types use the same single rate ACS.

The Codec Modes in uplink and downlink at one radio leg may be different. In Tandem Free Operation or Transcoder Free Operation both radio legs (A and B) are considered for the optimal selection of the active Codec Mode in each direction (uplink A and then downlink B, respectively vice versa) by a "Distributed Rate Decision" algorithm. The worst of both radio legs determine the highest allowed Codec Mode, respectively the maximally allowed rate. All rate control commands are transmitted inband on the Iu and Nb interfaces and out of band on the radio interface.

The Active Codec Set is configured at call setup or reconfigured during the call. It consists of one up to maximally eight Codec Modes (MACS) at a given time, selected from the Supported Codec Set. The maximal number of Codec Modes and the Supported Codec Set may be constrained by the network to consider resources and radio conditions.

The Active Codec Sets in uplink and downlink are typically identical.

At call setup the Originating Side sends the AMR parameter set (included in the Codec List). The Terminating side then selects a suitable ACS from the given information and sends it back. In case the terminating side does not support TrFO a transcoder is allocated in the path at a suitable position, preferably as close as possible to the terminating side. This transcoder may by inband signalling install a Tandem Free Operation after call setup. Then, at start up of Tandem Free Operation, both Active Codec Sets, the Supported Codec Sets, the MACSs and the OMs are taken into account to determine the optimal common Active Codec Set. In a later phase the Codec Lists of both radio legs may be taken into account to find the optimum configuration. All configuration data and update protocols are transmitted inband on the TFO interface, but out of band within the UMTS network. For information on Tandem Free Operation see 3GPP TS 28.062 and on Transcoder Free Operation see 3GPP TS 23.153.

The SCR scheme of the Adaptive Multi-Rate Codec Types mark with a specific SID_FIRST frame the end of a speech burst. SID_FIRST does not contain Comfort Noise parameters. This SID_FIRST starts the comfort noise generation with parameters that are calculated at receiver side (!) from the latest received seven speech frames. A DTX hangover period needs to be applied therefore at transmitter side before sending of this SID_FIRST.

Absolutely coded SID_UPDATE frames follow about every eighth frame (160 ms) in speech pauses. SID_UPDATE frames are sent independently of the cell's timing structure and are related only to the source signal.

An ONSET frame does (typically) not exist in UMTS networks, but may be received in TFO from the distant partner. It marks the beginning of a speech burst. "SCR on" is always defined by the network. The defined Tandem Free Operation and Transcoder Free Operation allows the reception of AMR SCR information for the downlink direction in all cases.

The SCR scheme of the UMTS AMR2 Codec Type in UMTS is fully compatible to the SCR scheme of the UMTS AMR in UMTS and the DTX schemes of FR AMR and HR AMR in GSM.

5.5 TDMA Enhanced Full Rate Codec Type (TDMA EFR)

The Codec IDentification (CoID) code is defined to be: TDMA_EFR_CoID := 0x0000.0111.

The TDMA Enhanced Full Rate Codec Type has no additional parameters.

For information (for exact details see TDMA Recommendations):

The TDMA Enhanced Full Rate Codec Type supports one fixed Codec Mode with 7.4 kBit/s. This codec mode is bit exact identical with AMR codec mode at 7.4 kBit/s.

In a TDMA system DTX may be enabled in uplink, but not in downlink. The DTX scheme uses one SID frame to mark the end of a speech burst and to start or continue Comfort Noise Generation.

The defined Tandem Free Operation allows the reception of TDMA EFR DTX information for the downlink direction in all cases. In TDMA systems the transcoder has to generate comfort noise in speech like frames to be sent downlink. In UMTS the downlink DTX shall always be supported and the transcoder can therefore stay transparently in TFO.

5.6 PDC Enhanced Full Rate Codec Type (PDC_EFR)

The Codec IDentification (CoID) code is defined to be: TDMA_EFR_CoID := 0x0000.1000.

The PDC Enhanced Full Rate Codec Type has no additional parameters.

For information (for exact details see PDC Recommendations):

The PDC Enhanced Full Rate Codec Type supports one fixed Codec Mode with 6.7 kBit/s. This codec mode is bit exact identical with AMR codec mode at 6.7 kBit/s.

In a PDC system DTX may be enabled in uplink, but not in downlink. The DTX scheme uses one SID frame to mark the end of a speech burst and to start or continue Comfort Noise Generation.

The Tandem Free Operation allows the reception of PDC EFR DTX information for the downlink direction in all cases. In PDC systems the transcoder has to generate comfort noise in speech like frames to be sent downlink. In UMTS the downlink DTX shall always be supported and the transcoder can therefore stay transparently in TFO.

6 Codec List for the Call Control Protocol

For call control on the air interface the Codec Lists need to be specified for each radio access technology separately, because it can not be expected that an UE supports the same Codec Types in different radio access technologies.

3GPP TS 24.008 [9] defines the call control signalling and how to use the "Supported Codec List Information Element" (IE). It contains Codec Lists (in form of Codec Bitmaps) for each supported radio access technology (identified by a SysID).

The coding of this IE is given here. It is also used for TFO in 3GPP TS 28.062 [7].

6.1 System Identifiers for GSM and UMTS

The system identifiers for the radio access technologies supported by this specification are:

SysID for GSM: 0x0000.0000 (bit 8 .. bit 1)

SysID for UMTS: 0x0000.0100 (bit 8 .. bit 1)

These values are selected in accordance with [7] (3GPP TS 28.062).

6.2 Codec Bitmap

The Codec Types are coded in the first and second octet of the Codec List Bitmap as follows:

8	7	6	5	4	3	2	bit 1	
TDMA EFR	UMTS AMR 2	UMTS AMR	HR AMR	FR AMR	GSM EFR	GSM HR	GSM FR	Octet 1
bit 16	15	14	13	12	11	10	bit 9	
(reserved)	(reserved)	(reserved)	(reserved)	(reserved)	(reserved)	(reserved)	PDC EFR	Octet 2

A Codec Type is supported, if the corresponding bit is set to "1". All reserved bits shall be set to "0".

6.3 Selected Codec Type

The Selected Codec Type is coded as shown in Table 6.3-1. The same coding is used also in 3GPP TS 28.062 [7].

Table 6.3-1: Coding of the selected Codec_Type (long form)

Bit 8...Bit 1 CoID	Codec_Type	Name
0000.0000	GSM Full Rate (13.0 kBit/s)	GSM FR
0000.0001	GSM Half Rate (5.6 kBit/s)	GSM HR
0000.0010	GSM Enhanced Full Rate (12.2 kBit/s)	GSM EFR
0000.0011	Full Rate Adaptive Multi-Rate	FR AMR
0000.0100	Half Rate Adaptive Multi-Rate	HR AMR
0000.0101	UMTS Adaptive Multi-Rate	UMTS AMR
0000.0110	UMTS Adaptive Multi-Rate 2	UMTS AMR 2
0000.0111	TDMA Enhanced Full Rate (7.4 kBit/s)	TDMA EFR
0000.1000	PDC Enhanced Full Rate (6.7 kBit/s)	PDC EFR
other codes	reserved for future use.	

Annex A (informative): Example Codec List for UMTS

This Annex gives some informative examples how the Codec List for UMTS may look like for the OoBTC protocol. UMTS does support: UMTS AMR, FR AMR and HR AMR. It may support also GSM EFR, TDMA EFR and PDC EFR.

One list (with arbitrarily selected Codec Type preference) could look at Originating side like:

Octet	Parameter	MSB 8	7	6	5	4	3	2	1 LSB
1	Codec List	Codec List (see ITU-T Q.765.5 [6])							
2	Length Indication (LI)	30							
3	Compat. Info	Compatibility Information							
4	Single Codec	Single Codec (see ITU-T Q.765.5 [6])							
5	LI	6							
6	Compat. Info	Compatibility Information							
7	OID	ETSI OID (See ITU-T Q.765.5 [6])							
8	CoID	UMTS_AMR_CoID							
9 o	ACS	12.2	10.2	7.95	7.40	6.70	5.90	5.15	4.75
10 o	SCS	12.2	10.2	7.95	7.40	6.70	5.90	5.15	4.75
11 o	MACS	(spare)	(spare)	(spare)	(spare)	OM	MACS		
12	Single Codec	Single Codec (see ITU-T Q.765.5 [6])							
13	LI	6							
14	Compat. Info	Compatibility Information							
15	OID	ETSI OID (See ITU-T Q.765.5 [6])							
16	CoID	FR_AMR_CoID							
17 o	ACS	12.2	10.2	7.95	7.40	6.70	5.90	5.15	4.75
18 o	SCS	12.2	10.2	7.95	7.40	6.70	5.90	5.15	4.75
19 o	MACS	(spare)	(spare)	(spare)	(spare)	OM	MACS		
20	Single Codec	Single Codec (see ITU-T Q.765.5 [6])							
21	LI	6							
22	Compat. Info	Compatibility Information							
23	OID	ETSI OID (See ITU-T Q.765.5 [6])							
24	CoID	HR_AMR_CoID							
25 o	ACS	(spare)	(spare)	7.95	7.40	6.70	5.90	5.15	4.75
26 o	SCS	(spare)	(spare)	7.95	7.40	6.70	5.90	5.15	4.75
27 o	MACS	(spare)	(spare)	(spare)	(spare)	OM	MACS		
28	Single Codec	Single Codec (see ITU-T Q.765.5 [6])							
29	LI	3							
30	Compat. Info	Compatibility Information							
31	OID	ETSI OID (See ITU-T Q.765.5 [6])							
32	CoID	EFR_CoID							

with "o" = optional octet

The Terminating Side selects one of the Codec Types and returns it, together with the selected codec attributes.

The AMR Codec Types may have very similar, if not identical codec attributes at Originating side. The UMTS as Originating side can, however, already decide, which configuration would be preferred in case the Terminating side is UMTS, or GSM FR or GSM HR. A GSM as Originating side can not offer UMTS AMR and the Codec attributes for FR AMR and HR AMR may be quite different.

Annex B (informative) : Change history

Change history							
Date	TSG SA#	TSG Doc.	CR	Rev	Subject/Comment	Old	New
12-2000	10	SP-000576	004		Introduction of Codec Type Bit-Map for Codec Negotiation	3.0.0	4.0.0
12-2000	10	SP-000576	005		Introduction of Selected Codec Type for Codec Negotiation	3.0.0	4.0.0
12-2000	10	SP-000576	006		Clarification for the use of the Codec List Information Element	3.0.0	4.0.0
03-2001	11	SP-010104	007		Simplification of the Optimisation Mode Field	4.0.0	4.1.0
03-2001	11	SP-010199	008	3	Introduction of UMTS_AMR_2	4.0.0	4.1.0
12-2001	14	SP-010698	010		Removal of AMR-WB codec type	4.1.0	4.2.0
06-2002	16	SP-020223	013	2	UMTS_AMR2 is default Codec Type in all terminals of REL-4 and onwards	4.2.0	4.3.0
12-2004	26	SP-040845	030		TFO/TrFO Compatibility of UMTS_AMR and UMTS_AMR2	4.3.0	4.4.0
12-2004	26	SP-040847	033	1	Clarifications for AMR, Alternative 1	4.3.0	4.4.0

History

Document history		
V4.1.0	March 2001	Publication
V4.2.0	December 2001	Publication
V4.3.0	June 2002	Publication
V4.4.0	December 2004	Publication