

# ETSI TS 129 108 V4.0.0 (2001-03)

---

*Technical Specification*

## **Universal Mobile Telecommunications System (UMTS); Application of the Radio Access Network Application Part (RANAP) on the E-interface (3GPP TS 29.108 version 4.0.0 Release 4)**



---

**Reference**

RTS/TSGN-0329108Uv4

---

**Keywords**

GSM, UMTS

**ETSI**

650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

---

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° 7803/88

---

**Important notice**

---

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at <http://www.etsi.org/tb/status/>

If you find errors in the present document, send your comment to:  
editor@etsi.fr

---

**Copyright Notification**

---

No part may be reproduced except as authorized by written permission.  
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2001.

All rights reserved.

---

## Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://www.etsi.org/ipr>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

---

## Foreword

This Technical Specification (TS) has been produced by the ETSI 3<sup>rd</sup> Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under [www.etsi.org/key](http://www.etsi.org/key).

---

# Contents

Foreword .....	4
1 Scope.....	5
2 References.....	5
3 Abbreviations.....	5
4 Principles for the use of RANAP on the E-interface .....	6
4.1 General.....	6
4.2 Transfer of RANAP layer 3 messages on the E-interface.....	6
4.3 Roles of 3G_MSC-A, 3G_MSC-I and 3G_MSC-T.....	6
5 Use of the RANAP on the E-interface.....	7
5.1 RAB Assignment .....	7
5.2 RAB Release Request.....	7
5.3 Iu Release Request.....	8
5.4 Relocation Resource Allocation .....	8
5.5 Relocation Cancel .....	8
5.6 Relocation Detect and Relocation Complete .....	8
5.7 CN Trace invocation.....	8
5.8 Security mode control.....	9
5.9 Location Reporting Control.....	9
5.10 Location Report .....	9
5.11 Direct Transfer.....	9
5.12 Error Indication.....	9
5.13 CN Deactivate Trace.....	9
5.14 Common ID .....	9
6 RANAP messages transferred on the E-interface.....	10
7 Exceptions for RANAP message contents and information element coding when transferred on the E-interface.....	11
7.1 Message Contents .....	11
8 RANAP message error handling when transferred on the E-interface .....	11
<b>Annex A (informative): Change history.....</b>	<b>12</b>

---

# Foreword

This Technical Specification has been produced by the 3GPP.

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of this TS, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version 3.y.z

where:

- 3 the first digit:
  - 3 Indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the specification.

---

# 1 Scope

The present document describes the subset of Radio Access Network Application Part (RANAP) messages and procedures, defined in 3GPP TS 25.413, which is used on the E-interface. A general description can be found in 3GPP TS 23.002 and 3GPP TS 23.009.

For the initiation and execution of relocation of SRNS (relocation for short, throughout the whole document) between MSCs a subset of RANAP procedures are used. For the subsequent control of resources allocated to the User Equipment (UE) RANAP procedures are used. The Direct Transfer Elementary Procedure (EP) of RANAP, is used for the transfer of connection management and mobility management messages between the UE and the controlling 3G\_MSC.

---

# 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] 3G TS 21.905: "3G Vocabulary".
- [2] 3G TS 23.009: "Handover procedures"
- [3] 3G TS 25.412: "UTRAN Iu Interface Signalling Transport".
- [4] 3G TS 25.413: " UTRAN Iu Interface RANAP Signalling"
- [5] 3G TS 29.002: " Mobile Application Part (MAP) specification"
- [6] 3G TS 29.010: "Signalling procedures and the Mobile Application Part (MAP)"
- [7] 3G TS 23.002: "Network architecture"
- [8] 3G TS 24.008: "Mobile radio interface layer 3 specification, Core Network Protocols - Stage 3"

---

# 3 Abbreviations

For the purpose of this specification, the following definitions and abbreviations apply:

3G_MSC	A third generation Mobile services Switching Centre that supports the Iu interface (and possibly also the A-interface)
3G_MSC-A	The controlling 3G_MSC on which the call was originally established
3G_MSC-B	The 3G_MSC to which the UE is handed over in a Basic Handover
3G_MSC-B'	The 3G_MSC to which the UE is handed over in a Subsequent Handover
3G_MSC-I	Interworking 3G_MSC
3G_MSC-T	Target 3G_MSC
EP	Elementary Procedure
RNC	Radio Network Controller

Other abbreviations used in this specification are listed in 3G TS 21.905 [1].

---

## 4 Principles for the use of RANAP on the E-interface

### 4.1 General

The mechanisms for the transfer of the RANAP messages on the E-interface is defined in TS 29.002. The operation of the relocation procedures between 3G\_MSCs and the use of the RANAP messages for those procedures is described in TS 23.009 and TS 29.010.

RANAP is defined to connect the RNS to both, the cs and ps domain of an UMTS CN. Procedures, messages and IEs, only defined for communication between the RNS and the ps domain of an UMTS CN will, of course, never appear on the E-interface.

In the same way as a the connection oriented service of SCCP is used for the messages relating to one UE on the 3G\_MSC-RNS interface a TCAP dialogue is used on the E-interface for messages relating to one UE. As no correspondence to the connectionless service on the 3G\_MSC-RNS interface is used on the E-interface none of the global procedures are applicable.

The management of the terrestrial circuits between the 3G\_MSCs is outside the scope of the E-interface (see TS 23.009), therefore all procedures, messages and information elements relating to terrestrial circuits are also excluded from the RANAP procedures and messages used on the E-interface.

### 4.2 Transfer of RANAP layer 3 messages on the E-interface

The RANAP data which on the 3G\_MSC-RNS interface is contained in the user data field of the exchanged SCCP frames is on the E-interface transferred as the contents of the access network signalling info in the AN-APDU parameter as described in TS 29.002, indicating the access network protocol identification "ts3G-25413".

### 4.3 Roles of 3G\_MSC-A, 3G\_MSC-I and 3G\_MSC-T

For the description in this TS, the 3G\_MSC's functionality related to the relocation between 3G\_MSCs has been split into three logical parts, 3G\_MSC-A, 3G\_MSC-T and 3G\_MSC-I. The different roles need not necessarily be performed by different 3G\_MSCs.

3G\_MSC-A is the call/connection controlling part of the 3G\_MSC where the call/connection was originally established and the switching point for relocation between 3G\_MSCs. (This corresponds to 3G\_MSC-A as defined in TS 23.009 and 29.002). The 3G\_MSC that is the 3G\_MSC-A will not be changed during the duration of a call/connection.

3G\_MSC-T is the part relating to the transitory state during the relocation for the 3G\_MSC controlling the RNS the serving RNS functionality is relocated to, when basic relocation or subsequent relocation (see TS 23.009) take place. (This corresponds, depending on the type of relocation to 3G\_MSC-A, 3G\_MSC-B or 3G\_MSC-B' in TS 23.009 and 29.002).

3G\_MSC-I is the part of an 3G\_MSC through which the 3G\_MSC-A, via an E-interface (or an internal interface) is in contact with the UE. (This corresponds, depending on the type of relocation to 3G\_MSC-A, 3G\_MSC-B or 3G\_MSC-B' in TS 23.009 and TS 29.002).

The 3G\_MSC that is the 3G\_MSC-A can also have the role of either the 3G\_MSC-I or the 3G\_MSC-T during a period of the call/connection.

The following is applicable for the involved 3G\_MSCs concerning the exchange of RANAP data on an E-interface before and after a successful inter 3G\_MSC relocation:

- 1) At basic relocation, two 3G\_MSCs are involved, one 3G\_MSC being 3G\_MSC-A and one being 3G\_MSC-T. When this relocation has been performed, the two 3G\_MSCs interworking on the E-interface have the roles of 3G\_MSC-A and 3G\_MSC-I respectively, i.e. the 3G\_MSC that is the 3G\_MSC-T during the relocation is now the 3G\_MSC-I.
- 2) At subsequent relocation back to 3G\_MSC-A, two 3G\_MSCs are involved. The 3G\_MSC having the role of 3G\_MSC-A has also the role of 3G\_MSC-T. The other 3G\_MSC involved has the role of 3G\_MSC-I. When this

relocation has been completed, there is no exchange of RANAP data on the E-interface, i.e. the 3G\_MSC being the 3G\_MSC-I before and during the relocation is now no longer taking part.

- 3) At subsequent relocation of SRNS to an 3G\_MSC not being 3G\_MSC-A, three 3G\_MSCs are involved. The roles of these 3G\_MSCs are 3G\_MSC-A, 3G\_MSC-I, and 3G\_MSC-T respectively. When this relocation has been performed, the two 3G\_MSCs interworking on an E-interface have the roles of 3G\_MSC-A and 3G\_MSC-I respectively, i.e. the 3G\_MSC that is the 3G\_MSC-T during the relocation is now the 3G\_MSC-I and the 3G\_MSC being 3G\_MSC-I during the relocation is now no longer taking part.

---

## 5 Use of the RANAP on the E-interface

The dedicated RANAP procedures used on the E-interface to some extent are:

- RAB assignment
- RAB Release Request
- Iu Release Request
- Relocation resource allocation
- Relocation Detect
- Relocation Complete
- Relocation Cancel
- CN Invoke Trace
- Security mode control
- Location Reporting Control
- Location Report
- Direct Transfer
- Error Indication
- Common ID

### 5.1 RAB Assignment

The RAB Assignment procedure (TS 25.413 subclause 8.2) is applied on the E-interface with following conditions:

- the 3G\_MSC-A acts as the 3G\_MSC;
- the 3G\_MSC-I acts as the RNS.

The handling of terrestrial resources is not applicable, i.e. the RANAP IEs *Transport Layer Address* and *Iu Transport Association* will be assigned by the 3G\_MSC-I.

### 5.2 RAB Release Request

For the RAB Release Request procedure (TS 25.413 subclauses 8.3) the involved 3G\_MSCs shall act according to the following:

- the 3G\_MSC-I acts as the RNS
- the 3G\_MSC-A acts as the 3G\_MSC

## 5.3 Iu Release Request

For the Iu Release Request procedure (TS 25.413 subclause 8.4) the involved 3G\_MSCs shall act according to the following:

- the 3G\_MSC-I acts as the RNS
- the 3G\_MSC-A acts as the 3G\_MSC

## 5.4 Relocation Resource Allocation

At basic Inter-3G\_MSC relocation (TS 23.009) the Relocation Resource Allocation procedure (TS25.413 subclause 8.7) is applied on the E-interface with the following conditions:

- the 3G\_MSC-A acts as the 3G\_MSC
- the 3G\_MSC-T acts as the target RNS

At subsequent Inter-3G\_MSC relocation the Relocation Resource Allocation procedure is applied on the E-interface with the following conditions:

- the 3G\_MSC-I acts as the 3G\_MSC
- the 3G\_MSC-T acts as the RNS
- if the 3G\_MSC that is the 3G\_MSC-A is not also the 3G\_MSC-T, then this 3G\_MSC shall act as the target RNS towards the 3G\_MSC-I and as the 3G\_MSC towards the 3G\_MSC-T.

The handling of terrestrial resources is not applicable, i.e. the RANAP IEs *Transport Layer Address* and *Iu Transport Association* will be assigned by the 3G\_MSC-T.

## 5.5 Relocation Cancel

For subsequent Inter-3G\_MSC relocation the Relocation Cancel procedure (TS 25.413 subclause 8.10) is applied on the E-interface with the following conditions.

- the 3G\_MSC-A, acts as the 3G\_MSC
- the 3G\_MSC-I, acts as the serving RNS

## 5.6 Relocation Detect and Relocation Complete

For the Relocation Detect and Relocation Complete procedure (TS 25.413 subclauses 8.8 and 8.9) the applicable parts on the E-interface are the transfer of RELOCATION DETECT, RELOCATION COMPLETE messages at inter 3G\_MSC relocation. For those parts, the involved 3G\_MSCs shall act according to the following:

- the 3G\_MSC-A acts as the 3G\_MSC;
- the 3G\_MSC-T acts as the target RNS.

## 5.7 CN Trace invocation

For the CN Trace invocation procedure (TS 25.413, subclause 8.17), the involved 3G\_MSCs shall act according to the following:

- the 3G\_MSC-A acts as the 3G\_MSC
- the 3G\_MSC-I acts as the RNS.

## 5.8 Security mode control

For the Security mode control procedure (TS 25.413, subclause 8.18), the involved 3G\_MSCs shall act according to the following:

- the 3G\_MSC-A acts as the 3G\_MSC
- the 3G\_MSC-I acts as the RNS.

## 5.9 Location Reporting Control

For the Location Reporting Control procedure (TS 25.413, subclause 8.19), the involved 3G\_MSCs shall act according to the following:

- the 3G\_MSC-A acts as the 3G\_MSC
- the 3G\_MSC-I acts as the RNS.

## 5.10 Location Report

For the Location Report procedure (TS 25.413, subclause 8.20), the involved 3G\_MSCs shall act according to the following:

- the 3G\_MSC-A acts as the 3G\_MSC
- the 3G\_MSC-I acts as the RNS.

## 5.11 Direct Transfer

For the Direct Transfer procedure (TS 25.413, subclause 8.23), the involved 3G\_MSCs shall act according to the following:

- the 3G\_MSC-A acts as the 3G\_MSC
- the 3G\_MSC-I acts as the RNS.

## 5.12 Error Indication

For the Error Indication procedure (TS 25.413, subclause 8.27), the involved 3G\_MSCs shall act according to the following:

- the 3G\_MSC-A acts as the 3G\_MSC
- the 3G\_MSC-I acts as the RNS.

## 5.13 CN Deactivate Trace

For the Error Indication procedure (TS 25.413, subclause 8.28), the involved 3G\_MSCs shall act according to the following:

- the 3G\_MSC-A acts as the 3G\_MSC
- the 3G\_MSC-I acts as the RNS.

## 5.14 Common ID

For the Common ID procedure (TS 25.413, subclause 8.16), the involved 3G MSCs shall act according to the following:

- the 3G\_MSC-A acts as the 3G\_MSC
- the 3G\_MSC-I acts as the RNS.

---

## 6 RANAP messages transferred on the E-interface

The list given below shows the RANAP messages, defined in TS 25.413 subclause 9.1 (tabular format) and 9.3 (ASN.1 notation), that are transferred on the E-interface.

RAB ASSIGNMENT REQUEST	(3G_MSC-A -> 3G_MSC-I)
RAB ASSIGNMENT RESPONSE	(3G_MSC-I -> 3G_MSC-A)
RAB RELEASE REQUEST	(3G_MSC-I -> 3G_MSC-A)
IU RELEASE REQUEST	(3G_MSC-I -> 3G_MSC-A)
RELOCATION REQUEST	(3G_MSC-A -> 3G_MSC-T and 3G_MSC-I -> 3G_MSC-A)
RELOCATION REQUEST ACKNOWLEDGE	(3G_MSC-T -> 3G_MSC-A and 3G_MSC-A -> 3G_MSC-I)
RELOCATION DETECT	(3G_MSC-T -> 3G_MSC-A)
RELOCATION COMPLETE	(3G_MSC-T -> 3G_MSC-A)
RELOCATION FAILURE	(3G_MSC-T -> 3G_MSC-A and 3G_MSC-I -> 3G_MSC-A)
RELOCATION CANCEL	(3G_MSC-I -> 3G_MSC-A)
RELOCATION CANCEL ACKNOWLEDGE	(3G_MSC-A -> 3G_MSC-I)
CN INVOKE TRACE	(3G_MSC-A -> 3G_MSC-I)
SECURITY MODE COMMAND	(3G_MSC-A -> 3G_MSC-I)
SECURITY MODE COMPLETE	(3G_MSC-I -> 3G_MSC-A)
SECURITY MODE REJECT	(3G_MSC-I -> 3G_MSC-A)
LOCATION REPORTING CONTROL	(3G_MSC-A -> 3G_MSC-I)
LOCATION REPORT	(3G_MSC-I -> 3G_MSC-A)
DIRECT TRANSFER	(3G_MSC-A -> 3G_MSC-I and 3G_MSC-I -> 3G_MSC-A)
ERROR INDICATION	(3G_MSC-A -> 3G_MSC-I and 3G_MSC-I -> 3G_MSC-A)
CN DEACTIVATE TRACE	(3G_MSC-A -> 3G_MSC-I)
COMMON ID	(3G_MSC-A->3G_MSC-I)

All other RANAP messages shall be considered as non-existent on the E-interface.

---

## 7 Exceptions for RANAP message contents and information element coding when transferred on the E-interface

### 7.1 Message Contents

For the applicable RANAP messages transferred on the E-interface the following exceptions to the descriptions in TS 25.413 are valid:

RAB ASSIGNMENT REQUEST message

- *Transport Layer Address IE*  
if received, this IE shall be ignored
- *Iu Transport Association IE*  
if received, this IE shall be ignored
- *UP Mode Versions IE*  
the information given within this IE is only useful in case of TrFO
- *Iu Signalling Connection Identifier IE*  
if received, this IE shall be ignored.

RELOCATION REQUEST message

- *Transport Layer Address IE*  
if received, this IE shall be ignored
- *Iu Transport Association IE*  
if received, this IE shall be ignored
- *UP Mode Versions IE*  
the information given within this IE is only useful in case of TrFO

---

## 8 RANAP message error handling when transferred on the E-interface

The RANAP error handling (TS 25.413 [4] chapter 10) is applicable. The handling of faults concerning the use of SCCP is not applicable.

The RANAP error messages sent on the E-interface shall only be sent as response to RANAP messages received on the same interface.

# Annex A (informative): Change history

Change history					
TSG RAN#	Version	CR	Tdoc RAN	New Version	Subject/Comment
RAN_08	2.0.0	-	RP-000258	3.0.0	Approved at TSG RAN #8 and placed under Change Control
RAN_10	3.0.0	001 002	RP-000634	3.1.0	Approved at TSG RAN #10

Change history							
Date	TSG #	TSG Doc.	CR	Rev	Subject/Comment	Old	New
March 01	11	-	-		Approved at TSG RAN #11 and placed under Change Control	-	4.0.0

---

## History

<b>Document history</b>		
V4.0.0	March 2001	Publication