

# ETSI TS 131 124 V6.6.0 (2006-09)

---

*Technical Specification*

**Universal Mobile Telecommunications System (UMTS);  
Mobile Equipment (ME) conformance test specification;  
Universal Subscriber Interface Module Application  
Toolkit (USAT) conformance test specification  
(3GPP TS 31.124 version 6.6.0 Release 6)**

---



---

**Reference**

RTS/TSGC-0631124v660

---

**Keywords**

UMTS

**ETSI**

650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

---

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° 7803/88

---

**Important notice**

---

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

[http://portal.etsi.org/chaicor/ETSI\\_support.asp](http://portal.etsi.org/chaicor/ETSI_support.asp)

---

**Copyright Notification**

---

No part may be reproduced except as authorized by written permission.  
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2006.  
All rights reserved.

**DECT**<sup>TM</sup>, **PLUGTESTS**<sup>TM</sup> and **UMTS**<sup>TM</sup> are Trade Marks of ETSI registered for the benefit of its Members.  
**TIPHON**<sup>TM</sup> and the **TIPHON logo** are Trade Marks currently being registered by ETSI for the benefit of its Members.  
**3GPP**<sup>TM</sup> is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

---

## Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "*Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards*", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://webapp.etsi.org/IPR/home.asp>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

---

## Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

# Contents

Intellectual Property Rights .....	2
Foreword.....	2
Foreword.....	9
1 Scope .....	10
2 References .....	10
3 Definitions and abbreviations.....	12
3.1 Mobile station definition and configurations.....	12
3.2 Applicability.....	12
3.2.1 Applicability of the present document .....	12
3.2.2 Applicability of the individual tests .....	12
3.2.3 Applicability to terminal equipment .....	12
3.2.4 Definitions .....	12
3.2.4.1 Format of the table of optional features .....	12
3.2.4.2 Format of the applicability table .....	12
3.2.4.3 Status and notations.....	13
3.3 Table of optional features.....	13
3.4 Applicability table .....	15
3.5 Conventions for mathematical notations .....	52
3.5.1 Mathematical signs .....	52
4 Test equipment .....	52
5 Testing methodology in general .....	52
5.1 Testing of optional functions and procedures.....	52
5.2 Test interfaces and facilities .....	52
5.3 Information to be provided by the apparatus supplier .....	52
6 Implicit testing.....	53
7 Measurement uncertainty .....	53
8 Format of tests .....	53
9 Generic call set up procedures.....	56
10 - 26 Not used.....	56
27 Testing of the UICC/ME interface .....	56
27.1 - 27.21 Void.....	56
27.22 USIM Application Toolkit .....	56
27.22.1A General Test purpose .....	56
27.22.2A Definition of default values for USIM Application Toolkit testing .....	56
27.22.1 Initialization of USIM Application Toolkit Enabled UICC by USIM Application Toolkit Enabled ME (Profile Download) .....	61
27.22.1.1 Definition and applicability.....	61
27.22.1.2 Conformance requirement.....	61
27.22.1.3 Test purpose .....	61
27.22.1.4 Method of test .....	61
27.22.1.4.1 Initial conditions .....	61
27.22.1.4.2 Procedure.....	61
27.22.1.5 Test requirement .....	62
27.22.2 Contents of the TERMINAL PROFILE command.....	62
27.22.2.1 Definition and applicability.....	62
27.22.2.2 Conformance requirement.....	62
27.22.2.3 Test purpose .....	62
27.22.2.4 Method of test .....	62
27.22.2.4.1 Initial conditions .....	62

27.22.1.4.2	Procedure .....	62
27.22.2.5	Test requirement .....	63
27.22.3	Servicing of proactive UICC commands .....	63
27.22.3.1	Definition and applicability.....	63
27.22.3.2	Conformance requirement.....	63
27.22.3.3	Test purpose .....	63
27.22.3.4	Method of test .....	63
27.22.3.4.1	Initial conditions .....	63
27.22.3.4.2	Procedure.....	63
27.22.3.5	Test requirement .....	63
27.22.4	Proactive UICC commands .....	64
27.22.4.1	DISPLAY TEXT.....	64
27.22.4.1.1	DISPLAY TEXT (Normal) .....	64
27.22.4.1.2	DISPLAY TEXT (Support of "No response from user") .....	65
27.22.4.1.3	DISPLAY TEXT (Display of extension text).....	66
27.22.4.1.4	DISPLAY TEXT (Sustained text).....	66
27.22.4.1.5	DISPLAY TEXT (Display of icons) .....	68
27.22.4.1.6	DISPLAY TEXT (UCS2 display in Cyrillic).....	69
27.22.4.1.7	DISPLAY TEXT (Variable Time out) .....	70
27.22.4.1.8	DISPLAY TEXT (Support of Text Attribute).....	70
27.22.4.1.9	DISPLAY TEXT (UCS2 display in Chinese) .....	78
27.22.4.1.10	DISPLAY TEXT (UCS2 display in Katakana) .....	78
27.22.4.2	GET INKEY .....	79
27.22.4.2.1	GET INKEY(normal).....	79
27.22.4.2.2	GET INKEY (No response from User) .....	80
27.22.4.2.3	GET INKEY (UCS2 display in Cyrillic).....	81
27.22.4.2.4	GET INKEY (UCS2 entry in Cyrillic) .....	82
27.22.4.2.5	GET INKEY ("Yes/No" Response).....	82
27.22.4.2.6	GET INKEY (display of Icon) .....	83
27.22.4.2.7	GET INKEY (Help Information).....	84
27.22.4.2.8	GET INKEY (Variable Time out) .....	85
27.22.4.2.9	GET INKEY (Support of Text Attribute).....	85
27.22.4.2.10	GET INKEY (UCS2 display in Chinese) .....	92
27.22.4.2.11	GET INKEY (UCS2 entry in Chinese) .....	93
27.22.4.2.12	GET INKEY (UCS2 display in Katakana) .....	93
27.22.4.2.13	GET INKEY (UCS2 entry in Katakana) .....	94
27.22.4.3	GET INPUT .....	95
27.22.4.3.1	GET INPUT (normal).....	95
27.22.4.3.2	GET INPUT (No response from User).....	96
27.22.4.3.3	GET INPUT (UCS2 display in Cyrillic) .....	97
27.22.4.3.4	GET INPUT (UCS2 entry in Cyrillic).....	98
27.22.4.3.5	GET INPUT (default text).....	99
27.22.4.3.6	GET INPUT (display of Icon).....	99
27.22.4.3.7	GET INPUT (Help Information) .....	101
27.22.4.3.8	GET INPUT (Support of Text Attribute) .....	101
27.22.4.3.9	GET INPUT (UCS2 display in Chinese).....	108
27.22.4.3.10	GET INPUT (UCS2 entry in Chinese) .....	109
27.22.4.3.11	GET INPUT (UCS2 display in Katakana).....	110
27.22.4.3.12	GET INPUT (UCS2 entry in Katakana).....	110
27.22.4.4	MORE TIME .....	111
27.22.4.4.1	Definition and applicability .....	111
27.22.4.4.2	Conformance requirement .....	111
27.22.4.4.3	Test purpose .....	111
27.22.4.4.4	Method of test.....	112
27.22.4.4.5	Test requirement .....	112
27.22.4.5	PLAY TONE.....	112
27.22.4.5.1	PLAY TONE (Normal) .....	112
27.22.4.5.2	PLAY TONE (UCS2 display in Cyrillic) .....	116
27.22.4.5.3	PLAY TONE (display of Icon) .....	117
27.22.4.5.4	PLAY TONE (Support of Text Attribute).....	118
27.22.4.5.5	PLAY TONE (UCS2 display in Chinese) .....	125
27.22.4.5.6	PLAY TONE (UCS2 display in Katakana).....	126

27.22.4.6	POLL INTERVAL.....	126
27.22.4.6.1	Definition and applicability .....	126
27.22.4.6.2	Conformance requirement .....	126
27.22.4.6.3	Test purpose .....	127
27.22.4.6.4	Method of test.....	127
27.22.4.6.5	Test requirement .....	127
27.22.4.7	REFRESH .....	127
27.22.4.7.1	REFRESH (normal).....	127
27.22.4.7.2	REFRESH (IMSI changing procedure).....	135
27.22.4.8	SET UP MENU and ENVELOPE MENU SELECTION .....	139
27.22.4.8.1	SET UP MENU (normal) and ENVELOPE MENU SELECTION.....	139
27.22.4.8.2	SET UP MENU (help request support) and ENVELOPE MENU SELECTION.....	140
27.22.4.8.3	SET UP MENU (next action support) and ENVELOPE MENU SELECTION .....	141
27.22.4.8.4	SET UP MENU (display of icons) and ENVELOPE MENU SELECTION.....	142
27.22.4.8.5	SET UP MENU (soft keys support) and ENVELOPE MENU SELECTION.....	143
27.22.4.8.6	SET UP MENU (support of Text Attribute) and ENVELOPE MENU SELECTION .....	143
27.22.4.8.7	SET UP MENU (UCS2 display in Cyrillic) and ENVELOPE MENU SELECTION.....	151
27.22.4.8.8	SET UP MENU (UCS2 display in Chinese) and ENVELOPE MENU SELECTION.....	152
27.22.4.8.9	SET UP MENU (UCS2 display in Katakana) and ENVELOPE MENU SELECTION.....	153
27.22.4.9	SELECT ITEM .....	154
27.22.4.9.1	SELECT ITEM (mandatory features for ME supporting SELECT ITEM).....	154
27.22.4.9.2	SELECT ITEM (next action support).....	155
27.22.4.9.3	SELECT ITEM (default item support).....	156
27.22.4.9.4	SELECT ITEM (help request support).....	156
27.22.4.9.5	SELECT ITEM (icons support).....	157
27.22.4.9.6	SELECT ITEM (presentation style) .....	158
27.22.4.9.7	SELECT ITEM (soft keys support).....	158
27.22.4.9.8	SELECT ITEM (Support of "No response from user").....	159
27.22.4.9.9	SELECT ITEM (Support of Text Attribute).....	160
27.22.4.9.10	SELECT ITEM (UCS2 display in Cyrillic).....	166
27.22.4.9.11	SELECT ITEM (UCS2 display in Chinese).....	167
27.22.4.9.12	SELECT ITEM (UCS2 display in Katakana).....	168
27.22.4.10	SEND SHORT MESSAGE.....	169
27.22.4.10.1	SEND SHORT MESSAGE (normal) .....	169
27.22.4.10.2	SEND SHORT MESSAGE (UCS2 display in Cyrillic).....	184
27.22.4.10.3	SEND SHORT MESSAGE (icon support).....	189
27.22.4.10.4	SEND SHORT MESSAGE (Support of Text Attribute) .....	195
27.22.4.10.5	SEND SHORT MESSAGE (UCS2 display in Chinese) .....	231
27.22.4.10.6	SEND SHORT MESSAGE (UCS2 display in Katakana).....	235
27.22.4.11	SEND SS.....	240
27.22.4.11.1	SEND SS (normal) .....	240
27.22.4.11.2	SEND SS (Icon support).....	252
27.22.4.11.3	SEND SS (UCS2 display in Cyrillic) .....	259
27.22.4.11.4	SEND SS (support of Text Attribute).....	260
27.22.4.11.5	SEND SS (UCS2 display in Chinese) .....	295
27.22.4.11.6	SEND SS (UCS2 display in Katakana) .....	297
27.22.4.12	SEND USSD .....	299
27.22.4.12.1	SEND USSD (normal) .....	299
27.22.4.12.2	SEND USSD (Icon support).....	309
27.22.4.12.3	SEND USSD (UCS2 display in Cyrillic) .....	315
27.22.4.12.4	SEND USSD (support of Text Attribute).....	317
27.22.4.12.5	SEND USSD (UCS2 display in Chinese).....	351
27.22.4.12.6	SEND USSD (UCS2 display in Katakana).....	353
27.22.4.13	SET UP CALL .....	356
27.22.4.13.1	SET UP CALL (normal).....	356
27.22.4.13.2	SET UP CALL (second alpha identifier).....	367
27.22.4.13.3	SET UP CALL (display of icons).....	369
27.22.4.13.4	SET UP CALL (support of Text Attribute) .....	378
27.22.4.13.5	SET UP CALL (UCS2 Display in <i>Cyrillic</i> ) .....	414
27.22.4.13.6	SET UP CALL (UCS2 Display in Chinese).....	417
27.22.4.13.7	SET UP CALL (UCS2 Display in Katakana).....	420
27.22.4.14	POLLING OFF .....	423

27.22.4.14.1	Definition and applicability .....	423
27.22.4.14.2	Conformance requirement .....	423
27.22.4.14.3	Test purpose .....	423
27.22.4.14.4	Method of test.....	423
27.22.4.14.5	Test requirement .....	426
27.22.4.15	PROVIDE LOCAL INFORMATION .....	426
27.22.4.15.1	Definition and applicability .....	426
27.22.4.15.2	Conformance requirement .....	426
27.22.4.15.3	Test purpose .....	426
27.22.4.15.4	Method of tests .....	426
27.22.4.15.5	Test requirement .....	433
27.22.4.16	SET UP EVENT LIST .....	433
27.22.4.16.1	SET UP EVENT LIST (normal) .....	433
27.22.4.17	PERFORM CARD APDU .....	441
27.22.4.17.1	PERFORM CARD APDU (normal).....	441
27.22.4.17.2	PERFORM CARD APDU (detachable card reader) .....	443
27.22.4.18	POWER OFF CARD .....	443
27.22.4.18.1	POWER OFF CARD (normal).....	443
27.22.4.18.2	POWER OFF CARD (detachable card reader) .....	444
27.22.4.19	POWER ON CARD .....	445
27.22.4.19.1	POWER ON CARD (normal) .....	445
27.22.4.19.2	POWER ON CARD (detachable card reader) .....	446
27.22.4.20	GET READER STATUS .....	446
27.22.4.20.1	GET READER STATUS (normal) .....	446
27.22.4.20.2	GET CARD READER STATUS (detachable card reader) .....	447
27.22.4.21	TIMER MANAGEMENT and ENVELOPE TIMER EXPIRATION .....	448
27.22.4.21.1	TIMER MANAGEMENT (normal).....	448
27.22.4.21.2	ENVELOPE TIMER EXPIRATION (normal) .....	449
27.22.4.22	SET UP IDLE MODE TEXT.....	450
27.22.4.22.1	SET UP IDLE MODE TEXT (normal) .....	450
27.22.4.22.2	SET UP IDLE MODE TEXT (Icon support) .....	455
27.22.4.22.3	SET UP IDLE MODE TEXT (UCS2 support).....	456
27.22.4.22.4	SET UP IDLE MODE TEXT (support of Text Attribute) .....	457
27.22.4.22.5	SET UP IDLE MODE TEXT (UCS2 display in Chinese) .....	463
27.22.4.22.6	SET UP IDLE MODE TEXT (UCS2 display in Katakana) .....	464
27.22.4.23	RUN AT COMMAND.....	464
27.22.4.23.1	RUN AT COMMAND (normal) .....	464
27.22.4.23.2	RUN AT COMMAND (Icon support) .....	467
27.22.4.23.3	RUN AT COMMAND (support of Text Attribute).....	473
27.22.4.23.4	RUN AT COMMAND (UCS2 display in Cyrillic) .....	504
27.22.4.23.5	RUN AT COMMAND (UCS2 display in Chinese) .....	504
27.22.4.23.6	RUN AT COMMAND (UCS2 display in Katakana) .....	505
27.22.4.24	SEND DTMF .....	506
27.22.4.24.1	SEND DTMF (Normal).....	506
27.22.4.24.2	SEND DTMF (Display of icons).....	511
27.22.4.24.3	SEND DTMF (UCS2 display in Cyrillic) .....	516
27.22.4.24.4	SEND DTMF (support of Text Attribute) .....	518
27.22.4.24.5	SEND DTMF (UCS2 Display in Chinese) .....	555
27.22.4.24.6	SEND DTMF (UCS2 Display in Katakana).....	556
27.22.4.25	LANGUAGE NOTIFICATION .....	558
27.22.4.25.1	Definition and applicability .....	558
27.22.4.25.2	Conformance Requirement.....	558
27.22.4.25.3	Test purpose .....	558
27.22.4.25.4	Method of Test .....	558
27.22.4.25.5	Test requirement .....	559
27.22.4.26	LAUNCH BROWSER.....	559
27.22.4.26.1	LAUNCH BROWSER (No session already launched) .....	559
27.22.4.26.2	LAUNCH BROWSER (Interaction with current session).....	564
27.22.4.26.3	LAUNCH BROWSER (UCS2 display in Cyrillic) .....	568
27.22.4.26.4	LAUNCH BROWSER (icons support) .....	570
27.22.4.26.5	LAUNCH BROWSER (support of Text Attribute).....	574
27.22.4.26.6	LAUNCH BROWSER (UCS2 Display in Chinese).....	606

27.22.4.26.7	LAUNCH BROWSER (UCS2 Display in Katakana) .....	608
27.22.4.27	OPEN CHANNEL .....	610
27.22.4.27.2	Open Channel (related to GPRS).....	610
27.22.4.27.3	Open Channel (default bearer) .....	621
27.22.4.27.4	Open Channel (Local Bearer).....	621
27.22.4.27.5	Open Channel (GPRS, support of Text Attribute).....	621
27.22.4.28	CLOSE CHANNEL .....	677
27.22.4.28.1	CLOSE CHANNEL(normal) .....	677
27.22.4.28.2	CLOSE CHANNEL (support of Text Attribute).....	683
27.22.4.29	RECEIVE DATA.....	721
27.22.4.29.1	RECEIVE DATA (NORMAL) .....	721
27.22.4.29.5	Test requirement .....	730
27.22.4.29.2	RECEIVE DATA (support of Text Attribute).....	730
27.22.4.30	SEND DATA .....	770
27.22.4.30.1	SEND DATA (normal).....	770
27.22.4.30.2	SEND DATA (support of Text Attribute) .....	783
27.22.4.31	GET CHANNEL STATUS .....	815
27.22.4.31.1	Definition and applicability .....	815
27.22.4.31.2	Conformance requirements.....	815
27.22.4.31.3	Test purpose .....	815
27.22.4.31.4	Method of test.....	815
27.22.4.31.5	Test requirement .....	824
27.22.5	Data Download to UICC.....	824
27.22.5.1	SMS-PP Data Download .....	824
27.22.5.1.1	Definition and applicability .....	824
27.22.5.1.2	Conformance requirement .....	825
27.22.5.1.3	Test purpose .....	825
27.22.5.1.4	Method of Test .....	825
27.22.5.1.5	Test requirement .....	830
27.22.5.2	SMS-CB Data Download.....	830
27.22.5.2.1	Definition and applicability .....	830
27.22.5.2.2	Conformance requirement .....	830
27.22.5.2.3	Test purpose .....	830
27.22.5.2.4	Method of Test .....	830
27.22.5.2.5	Test requirement .....	833
27.22.6	CALL CONTROL BY USIM.....	833
27.22.6.1	Procedure for Mobile Originated calls .....	833
27.22.6.1.1	Definition and applicability .....	833
27.22.6.1.2	Conformance requirement .....	833
27.22.6.1.3	Test purpose .....	834
27.22.6.1.4	Method of tests .....	834
27.22.6.1.5	Test requirement .....	854
27.22.6.2	Procedure for Supplementary (SS) Services .....	854
27.22.6.2.1	Definition and applicability .....	854
27.22.6.2.2	Conformance requirement .....	854
27.22.6.2.3	Test purpose .....	855
27.22.6.2.4	Method of tests .....	855
27.22.6.2.5	Test requirement .....	862
27.22.6.3	Interaction with Fixed Dialling Number (FDN).....	862
27.22.6.3.1	Definition and applicability .....	862
27.22.6.3.2	Conformance requirement .....	862
27.22.6.3.3	Test purpose .....	862
27.22.6.3.4	Method of tests .....	862
27.22.6.3.5	Test requirement .....	869
27.22.6.4	Support of Barred Dialling Number (BDN) service.....	869
27.22.6.4.1	Definition and applicability .....	869
27.22.6.4.2	Conformance requirement .....	869
27.22.6.4.3	Test purpose .....	869
27.22.6.4.4	Method of tests .....	870
27.22.6.4.5	Test requirement .....	876
27.22.6.5	Barred Dialling Number (BDN) service handling for terminals not supporting BDN.....	876
27.22.6.5.1	Definition and applicability .....	876

27.22.6.5.2	Conformance requirement .....	876
27.22.6.5.3	Test purpose .....	877
27.22.6.5.4	Method of tests .....	877
27.22.7	EVENT DOWNLOAD.....	877
27.22.7.1	MT Call Event.....	877
27.22.7.1.1	MT Call Event (normal) .....	877
27.22.7.2	Call Connected Event.....	879
27.22.7.2.1	Call Connected Event (MT and MO call).....	879
27.22.7.2.2	Call Connected Event (ME supporting SET UP CALL) .....	882
27.22.7.3	Call Disconnected Event .....	884
27.22.7.3.1	Call Disconnected Event .....	884
27.22.7.4	Location Status Event .....	888
27.22.7.4.1	Location Status Event (normal).....	888
27.22.7.5	User Activity Event.....	892
27.22.7.5.1	User Activity Event (normal) .....	892
27.22.7.6	Idle screen available event .....	892
27.22.7.6.1	Idle Screen Available (normal).....	892
27.22.7.7	Card reader status event .....	893
27.22.7.7.1	Card Reader Status (normal) .....	893
27.22.7.7.2	Card Reader Status(detachable card reader).....	894
27.22.7.8	Language selection event .....	894
27.22.7.8.1	Language selection event (normal).....	894
27.22.7.9	Browser termination event .....	895
27.22.7.9.1	Browser termination (normal) .....	895
27.22.7.10	Data available event .....	897
27.22.7.10.1	Definition and applicability .....	897
27.22.7.10.2	Conformance requirements.....	897
27.22.7.10.3	Test purpose .....	897
27.22.7.10.4	Method of test.....	897
27.22.7.11	Channel Status event .....	901
27.22.7.11.1	Definition and applicability .....	901
27.22.7.11.2	Conformance requirements.....	901
27.22.7.11.3	Test purpose .....	901
27.22.7.11.4	Method of test.....	901
27.22.7.12	Access Technology Change event.....	905
27.22.7.13	Local Connection event.....	905
27.22.7.14	Network search mode change event.....	905
27.22.7.15	Browsing status event .....	905
27.22.8	MO SHORT MESSAGE CONTROL BY USIM .....	905
27.22.8.1	Definition and applicability.....	905
27.22.8.2	Conformance requirement.....	905
27.22.8.3	Test purpose .....	905
27.22.8.4	Method of tests.....	906
27.22.8.4.1	Initial conditions .....	906
27.22.8.4.2	Procedure.....	907
27.22.8.5	Test requirement .....	915
27.22.9	Handling of command number .....	915
27.22.9.1	Definition and applicability.....	915
27.22.9.2	Conformance requirement.....	915
27.22.9.3	Test purpose .....	915
27.22.9.4	Method of tests.....	915
27.22.9.4.1	Initial conditions .....	915
27.22.9.4.2	Procedure.....	915
27.22.9.5	Test requirement .....	915
<b>Annex A (normative):</b>	<b>Details of Test-SIM (TestSIM).....</b>	<b>916</b>
<b>Annex B (normative):</b>	<b>Details of terminal profile support .....</b>	<b>918</b>
<b>Annex C (informative):</b>	<b>Change history .....</b>	<b>929</b>
History .....		931

---

# Foreword

This Technical Specification has been produced by the 3<sup>rd</sup> Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

---

# 1 Scope

The present document describes the technical characteristics and methods of test for testing the USIM Application Toolkit implemented in 3<sup>rd</sup> Generation Mobile Equipments (ME) or Mobile Station (MS) for the 3G and 2G digital cellular communications systems within the 3GPP digital cellular telecommunications system, in compliance with the relevant requirements, and in accordance with the relevant guidance given in ISO/IEC 9646-7 [19] and ETS 300 406 [20].

The present document is valid for ME implemented according to 3GPP Release 99, or Release 4, or Release 5 or Release 6

The present document covers the minimum characteristics considered necessary in order to provide sufficient performance for mobile equipment and to prevent interference to other services or to other users, and to the PLMNs.

It does not necessarily include all the characteristics which may be required by a user or subscriber, nor does it necessarily represent the optimum performance achievable.

The present document is part of the 3GPP-series of technical specifications. The present document neither replaces any of the other 3GPP technical specifications or 3GPP related ETSs or ENs, nor is it created to provide full understanding of (or parts of) the UMTS. The present document lists the requirements, and provides the methods of test for testing the USIM Application Toolkit implemented in a ME for conformance to the 3GPP standard.

For a full description of the system, reference should be made to all the 3GPP technical specifications or 3GPP related ETSIs, ETSs or ENs. Clause 2 provides a complete list of the 3GPP technical specifications, 3GPP related ETSIs, ETSs, ENs, and ETRs, on which this conformance test specifications is based.

If there is a difference between this present conformance document, and any other 3GPP technical specification or 3GPP related ETSI, ETS, EN, or 3GPP TS, then the other 3GPP technical specification or 3GPP related ETSI, ETS, EN or 3GPP TS shall prevail.

Within the context of this document, the term "terminal" used in ETSI TS 102 223 [16] refers to the Mobile Equipment (ME).

Within the context of this document, the term "UICC" used in ETSI TS 102 223 [16] refers to the USIM card.

Within the context of this document, the term "NAA" used in ETSI TS 102 223 [16] refers to the USIM application.

---

# 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the relevant Release*.
- References to 3GPP Technical Specifications and Technical Reports throughout the present document shall be interpreted according to the Release shown in the formal reference in this clause, based upon the Release of the implementation under test.

[1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".

[2] 3GPP TS 22.001: "Principles of circuit telecommunication services supported by a Public Land Mobile Network (PLMN)".

[3] 3GPP TS 22.003 "Circuit Teleservices supported by a Public Land Mobile Network (PLMN)".

- [4] 3GPP TS 22.004: "General on supplementary services".
- [5] ETSI TS 101 220: "ETSI numbering system for telecommunication application providers"
- [6] 3GPP TS 21.904: "UE capability requirements"
- [7] 3GPP TS 23.038: "Alphabets and language-specific information".
- [8] 3GPP TS 23.040: "Technical realization of the Short Message Service (SMS)".
- [9] 3GPP TS 23.041: "Technical realization of Cell Broadcast Service (CBS)".
- [10] 3GPP TS 24.008: "Mobile radio interface layer 3 specification; Core network protocols; Stage 3" (see note 1).
- [11] 3GPP TS 24.011: "Point-to-Point (PP) Short Message Service (SMS) Support on mobile radio interface".
- [12] 3GPP TS 34.108: "Common test environments for User Equipment (UE) conformance testing".
- [13] ETSI TS 102 221: "UICC-Terminal interface; Physical and logical characteristics".
- [14] 3GPP TS 31.102 : "Characteristics of the USIM application".
- [15] 3GPP TS 31.111 : "USIM Application Toolkit (USAT)"
- [16] ETSI TS 102 223: "Smart cards; Card Application Toolkit (CAT)"
- [17a] ISO/IEC 10646-1: "Information technology - Universal Multiple Octet Coded Character Set (UCS) - Part 1: Architecture and Basic Multilingual Plane".
- [17b] ISO/IEC 10646-2: "Information technology - Universal Multiple Octet Coded Character Set (UCS) - Part 2: Supplementary Planes".
- [18] 3GPP TS 27.007 : "AT command set for 3G User Equipment (UE)".
- [19] ISO/IEC 9646-7 (1995): "Information technology - Open Systems Interconnection - Conformance testing methodology and framework - Part 7: Implementation Conformance Statements".
- [20] ETSI ETS 300 406 (1995): "Methods for Testing and Specification (MTS); Protocol and profile conformance testing specifications; Standardization methodology".
- [21] 3GPP TS 31.121: "UICC-terminal interface; USIM application test specification"
- [22] 3GPP TS 22.101: "Service Aspects; Service principles"
- [23] 3GPP TS 51.010-1: "Mobile Station (MS) conformance specification; Part 1: Conformance specification"
- [24] ISO/IEC 7816-3: "Information technology - Identification cards - Integrated circuit(s) cards with contacts - Part 3: Electronic signals and transmission protocols".
- [25] TIA/IS-820-A: "Removable User Identity Module (R-UIM) for TIA/EIA Spread Spectrum System".
- [26] ETSI TS 102 384 "Smart cards; UICC-Terminal interface; Card Application Toolkit (CAT) conformance specification".
- [27] 3GPP TS 34.123-3: "User Equipment (UE) conformance specification; Part 3: Abstract test suites (ATSS)."

## 3 Definitions and abbreviations

### 3.1 Mobile station definition and configurations

The mobile station definition and configurations specified in 3GPP TS 34.108 [12] shall apply, unless otherwise specified in the present clause.

### 3.2 Applicability

#### 3.2.1 Applicability of the present document

The present specification applies to a terminal equipment that supports the USIM Application Toolkit optional feature.

#### 3.2.2 Applicability of the individual tests

Table A.1 lists the optional features for which the supplier of the implementation states the support.

#### 3.2.3 Applicability to terminal equipment

The applicability to terminal equipment specified in 3GPP TS 34.108 [12] shall apply, unless otherwise specified in the present clause.

Within the context of this document, the term "USS" refers to the 'UMTS System Simulator' when accessing a UTRAN and to the 'System Simulator' when accessing a GERAN.

See table B.1.

#### 3.2.4 Definitions

For the purposes of the present document, the terms and definitions given in 3GPP TS 34.108 [12], , apply.

##### 3.2.4.1 Format of the table of optional features

Option: The optional feature supported or not by the implementation.

Support Answer notation: The support columns shall be filled in by the supplier of the implementation. The following common notations, defined in ISO/IEC 9646-7 [19], are used for the support column in the tables below.

Y or y	supported by the implementation
N or n	not supported by the implementation
N/A, n/a or -	no answer required (allowed only if the status is N/A, directly or after evaluation of a conditional status)

Mnemonic column: The Mnemonic column contains mnemonic identifiers for each item.

##### 3.2.4.2 Format of the applicability table

The applicability of every test in table B.1 is formally expressed by the use of Boolean expression defined in the following clause.

The columns in table B.1 have the following meaning:

- In the "Item" column a local entry number for the requirement in the table is given.
- In the "Description" column a short non-exhaustive description of the requirement is found.

- The "Release" column gives the Release applicable and onwards, for the item in the "Description" column
- The "Test Sequence(s)" column gives a reference to the test sequence number(s) detailed in the present document and required to validate the implementation of the corresponding item in the "Description" column.
- For a given Release, the corresponding "Rel X ME" column lists the tests required for a Mobile Station to be declared compliant to this Release.
- The "Support" column is blank in the proforma, and shall be completed by the manufacturer in respect of each particular requirement to indicate the choices, which have been made in the implementation.
- The "Network Dependency" column indicates if a test depends on specific network access technology or requires network connection, but the status may not have an impact on references to ETSI TS 102 384[26].
- The "Terminal Profile" column gives a reference to the corresponding bit that needs to be present in the Terminal Profile.

### 3.2.4.3 Status and notations

"Release X ME" columns show the status of the entries as follows:

The following notations, defined in ISO/IEC 9646-7 [19], are used for the status column:

M	mandatory - the capability is required to be supported.
O	optional - the capability may be supported or not.
N/A	not applicable - in the given context, it is impossible to use the capability.
X	prohibited (excluded) - there is a requirement not to use this capability in the given context.
O.i	qualified optional - for mutually exclusive or selectable options from a set. "i" is an integer which identifies an unique group of related optional items and the logic of their selection which is defined immediately following the table.
Ci	conditional - the requirement on the capability ("M", "O", "X" or "N/A") depends on the support of other optional or conditional items. "i" is an integer identifying an unique conditional status expression which is defined immediately following the table. For nested conditional expressions, the syntax "IF ... THEN (IF ... THEN ... ELSE...) ELSE ..." shall be used to avoid ambiguities.

References to items: For each possible item answer (answer in the support column) there exists a unique reference, used, for example, in the conditional expressions. It is defined as the table identifier, followed by a solidus character "/", followed by the item number in the table. If there is more than one support column in a table, the columns shall be discriminated by letters (a, b, etc.), respectively.

EXAMPLE: A.1/4 is the reference to the answer of item 4 in table A.1.

## 3.3 Table of optional features

Support of USIM Application Toolkit is optional for Mobile Equipment. However, if an ME states conformance with a specific 3GPP release, it is mandatory for the ME to support all functions of that release, as stated in table B.1.

The support of letter classes, which specify mainly ME hardware dependent features, is optional for the ME and may supplement the USIM Application Toolkit functionality described in the present document. If an ME states conformance to a letter class, it is mandatory to support all functions within the respective letter class.

The supplier of the implementation shall state the support of possible options in table A.1.

**Table A.1: Options**

Item	Option	Status	Support	Mnemonic
1	Capability Configuration parameter	M		O_Cap_Conf
2	Sustained text	M		O_sust_text
3	UCS2 coding scheme for Entry	O		O_Ucs2_Entry
4	Extended Text String	M		O_Ext_Str
5	Help information	O		O_Help
6	Icons	O		O_Icons
7	Class A: Dual Slot	O		O_Dual_Slot
8	Detachable reader	O		O_Detach_Rdr
9	Class B: RUN AT	O		O_Run_At
10	Class C: LAUNCH BROWSER	O		O_LB
11	Class D: Soft keys	O		O_Soft_key
12	Class E: B.I.P related to CSD	O		O_BIP_CSD
13	Screen sizing parameters	O		O_Scr_Siz
14	Screen Resizing	O		O_Scr_Resiz
15	UCS2 coding scheme for Display	O		O_Ucs2_Disp
16	Mobile supporting GPRS	O		O_GPRS
17	Mobile supporting UDP	O		O_UDP
18	Mobile supporting TCP	O		O_TCP
19	Redial in Set Up Call	O		O_Redial
20	Mobile decision to respond with "No response from user" in finite time	O		O_D_NoResp
21	Class E: B.I.P related to GPRS	O		O_BIP_GPRS
22	Mobile supporting Called Party Subaddress	O		O_CP_Subaddr
23	Immediate response	O		O_Imm_Resp
24	Variable Timeout	O		O_Duration
25	void			
26	Class F: B.I.P related to local bearer	O		O_BIP_Local
27	BlueTooth Support	O		O_BT
28	IrDA Support	O		O_IrDA
29	RS232 Support	O		O_RS232
30	USB Support	O		O_USB
31	WML Browser Support	O		O_WML
32	XHTML Browser Support	O		O_XHTML
33	HTML Browser Support	O		O_HTML
34	CHTML Browser Support	O		O_CHTML
35	Class G: Battery Data	O		O_Batt
36	Class H: Multimedia Call Support	O		O_Xmedia_Call
37	Class I: Frame support	O		O_Frames
38	Class J: Multimedia Messaging Support	O		O_MMS
39	ME requesting for user confirmation before sending the Envelope Call Control command	O		O_UC_Before_EnvCC
40	ME requesting for user confirmation after sending the Envelope Call Control command	O		O_UC_After_EnvC C
41	UCS2 in Cyrillic	O		O_UCS2_Cyrillic
42	UCS2 in Chinese	O		O_UCS2_Chinese
43	UCS2 in Katakana	O		O_UCS2_Katakana

44	Mobile supporting Barred Dialling Numbers	O		O_BDN
45	Mobile supporting Fixed dialling numbers	O		O_FDN
46	Mobile supporting "+CIMI" in combination with Run AT Command	O		O_+CIMI
47	Mobile supporting "+CGMI" in combination with Run AT Command	O		O_+CGMI
48	Mobile supporting Open Channel (GPRS) not containing a Network Access Name TLV when no default Access Point Name is set in the terminal configuration	O		O_Open_Channel_GPRS_without_DefaultAPN
49	Preferred buffer size supported by the terminal for Open Channel command is greater than 0 byte and less than 65535 bytes	O		O_BUFFER_SIZE
50	Text attributes – Alignment left	O		O_TAT_AL
51	Text attributes – Alignment center	O		O_TAT_AC
52	Text attributes – Alignment right	O		O_TAT_AR
53	Text attributes – Font size normal	O		O_TAT_FSN
54	Text attributes – Font size large	O		O_TAT_FSL
55	Text attributes – Font size small	O		O_TAT_FSS
56	Text attributes – Style normal	O		O_TAT_SN
57	Text attributes – Style bold	O		O_TAT_SB
58	Text attributes – Style italic	O		O_TAT_SI
59	Text attributes – Style underlined	O		O_TAT_SU
60	Text attributes – Style strikethrough	O		O_TAT_SS
61	Text attributes – Style text foreground colour	O		O_TAT_STFC
62	Text attributes – Style text background colour	O		O_TAT_STFB
63	Terminal supports Long ForwardToNumber	O		O_longFTN
64	Mobile supporting GERAN	O		O_GERAN
65	Support of global phonebook	C001		O_Global_PB
C001 If terminal is implemented according to Rel-6 or later then M, else O				

### 3.4 Applicability table

Table B.1: Applicability of tests

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
1	PROFILE DOWNLOAD	R99	1	M	M	M	M	E.1/1	No	
2	Contents of the TERMINAL PROFILE command 27.22.2	R99		M	M	M	M	E.1/1	No	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
3	Servicing of Proactive UICC Commands	R99		M	M	M	M			
4	DISPLAY TEXT									
	Unpacked	R99	1.1	M	M	M	M	E.1/17	No	
	Screen busy	R99	1.2	M	M	M	M	E.1/17	No	
	high priority	R99	1.3	M	M	M	M	E.1/17	No	
	Packed	R99	1.4	M	M	M	M	E.1/17	No	
	clear after delay	R99	1.5	M	M	M	M	E.1/17	No	
	long text up to 160 bytes	R99	1.6	M	M	M	M	E.1/17	No	
	Backwards move in USIM session	R99	1.7	M	M	M	M	E.1/17	No	
	Session terminated by user	R99	1.8	M	M	M	M	E.1/17	No	
	Command not understood by ME	R99	1.9	M	M	M	M	E.1/17	No	
	no response from user	R99	2.1	C120	C120	C102	C120	E.1/17	No	
	Extension Text	R99	3.1	M	M	M	M	E.1/17 AND E.1/16	No	
	sustained text	R99	4.1, 4.2, 4.3, 4.4	M	M	M	M	E.1/17 AND E.1/65	No, except seq. 4.4	
	Icons	R99	5.1, 5.2, 5.3	C108	C108	C108	C108	E.1/17	No	
	UCS2 display in Cyrillic	R99	6.1	C118	C118	C118	C118	E.1/17 AND E.1/15	No	
	Variable Timeout	Rel-4	7.1	C126	C126	C126	C126	E.1/17 AND E.1/137	No	
	Text attribute – left alignment	Rel-5	8.1			C153	C153	E.1/17 AND E.1/124 AND E.1/217	No	
	Text attribute – center alignment	Rel-5	8.2			C154	C154	E.1/17 AND E.1/124 AND E.1/218	No	
	Text attribute – right alignment	Rel-5	8.3			C155	C155	E.1/17 AND E.1/124 AND E.1/219	No	
	Text attribute – large font size	Rel-5	8.4			C157 AND C156	C157 AND C156	E.1/17 AND E.1/124 AND E.1/221 AND E.1/220	No	
	Text attribute – small font size	Rel-5	8.5			C158 AND C156	C158 AND C156	E.1/17 AND E.1/124 AND E.1/222 AND E.1/220	No	
	Text attribute – bold on	Rel-5	8.6			C160 AND C159	C160 AND C159	E.1/17 AND E.1/124 AND E.1/225 AND E.1/226	No	

Item	Description	Release	Test sequence(s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – italic on	Rel-5	8.7			C161 AND C159	C161 AND C159	E.1/17 AND E.1/124 AND E.1/225 AND E.1/227	No	
	Text attribute – underlined on	Rel-5	8.8			C162 AND C159	C162 AND C159	E.1/17 AND E.1/124 AND E.1/225 AND E.1/228	No	
	Text attribute – strikethrough on	Rel-5	8.9			C163 AND C159	C163 AND C159	E.1/17 AND E.1/124 AND E.1/225 AND E.1/229	No	
	Text attribute – foreground and background colours	Rel-5	8.10			C164 AND C165	C164 AND C165	E.1/17 AND E.1/124 AND E.1/230 AND E.1/231	No	
	UCS2 display in Chinese	R99	9.1			C143	C143	E.1/17 AND E.1/15	No	
	UCS2 display in Katakana	R99	10.1			C145	C145	E.1/17 AND E.1/15	No	
	Frames	Rel-6	TBD				C133	E.1/17 AND E.1/177 AND E.1/178	TBD	
<b>5</b>	<b>GET INKEY</b>									
	prompt unpacked	R99	1.1	M	M	M	M	E.1/18	No	
	prompt packed	R99	1.2	M	M	M	M	E.1/18	No	
	digits only	R99	1.1	M	M	M	M	E.1/18	No	
	Backwards move in UICC session	R99	1.3	M	M	M	M	E.1/18	No	
	Session terminated by user	R99	1.4	M	M	M	M	E.1/18	No	
	SMS alphabet	R99	1.5	M	M	M	M	E.1/18	No	
	Long text up to 160 bytes	R99	1.6	M	M	M	M	E.1/18	No	
	no response from user	R99	2.1	C120	C120	C120	C120	E.1/18	No	
	UCS2 display in Cyrillic	R99	3.1	C118	C118	C118	C118	E.1/18 AND E.1/15	No	
	UCS2 display, Long text up to 70 chars in Cyrillic	R99	3.2	C118	C118	C118	C118	E.1/18 AND E.1/15	No	
	UCS2 entry in Cyrillic	R99	4.1	C105	C105	C105	C105	E.1/18 AND E.1/14	No	
	"Yes/No" response	R99	5.1	M	M	M	M	E.1/18 AND E.1/60	No	
	Icons	R99	6.1, 6.2, 6.3, 6.4	C108	C108	C108	C108	E.1/18	No	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Help information	R99	7.1	C107	C107	C107	C107	E.1/18	No	
	Variable Timeout	Rel-4	8.1	C126	C126	C126	C126	E.1/18 AND E.1/140	No	
	Text attribute – left alignment	Rel-5	9.1			C153	C153	E.1/18 AND E.1/124 AND E.1/217	No	
	Text attribute – center alignment	Rel-5	9.2			C154	C154	E.1/18 AND E.1/124 AND E.1/218	No	
	Text attribute – right alignment	Rel-5	9.3			C155	C156	E.1/18 AND E.1/124 AND E.1/219	No	
	Text attribute – large font size	Rel-5	9.4			C157 AND C156	C157 AND C156	E.1/18 AND E.1/124 AND E.1/221 AND E.1/220	No	
	Text attribute – small font size	Rel-5	9.5			C158 AND C156	C158 AND C156	E.1/18 AND E.1/124 AND E.1/222 AND E.1/220	No	
	Text attribute – bold on	Rel-5	9.6			C160 AND C159	C160 AND C159	E.1/18 AND E.1/124 E.1/221 AND E.1/220	No	
	Text attribute – italic on	Rel-5	9.7			C161 AND C159	C161 AND C159	E.1/18 AND E.1/124 E.1/225 AND E.1/227	No	
	Text attribute – underlined on	Rel-5	9.8			C162 AND C159	C162 AND C159	E.1/18 AND E.1/124 E.1/225 AND E.1/228	No	
	Text attribute – strikethrough on	Rel-5	9.9			C163 AND C159	C163 AND C159	E.1/18 AND E.1/124 E.1/225 AND E.1/229	No	
	Text attribute – foreground and background colours	Rel-5	9.10			C164 AND C165	C164 And C165	E.1/18 AND E.1/124 AND E.1/230 AND E.1/231	No	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	UCS2 display in Chinese	R99	10.1			C143	C143	E.1/18 AND E.1/15	No	
	UCS2 display in Chinese, Long text up to 70 chars	R99	10.2			C143	C143	E.1/18 AND E.1/15	No	
	UCS2 entry in Chinese	R99	11.1			C142	C142	E.1/18 AND E.1/14	No	
	UCS2 display in Katakana	R99	12.1			C145	C145	E.1/18 AND E.1/15	No	
	UCS2 display in Katakana, Long text up to 70 chars	R99	12.2			C145	C145	E.1/18 AND E.1/15	No	
	UCS2 entry in Katakana	R99	13.1			C144	C144	E.1/18 AND E.1/14	No	
	Frames	Rel-6	TBD				C133	E.1/18 AND E.1/177 AND E.1/178	TBD	
<b>6</b>	<b>GET INPUT</b>									
	input unpacked	R99	1.1	M	M	M	M	E.1/19	No	
	input packed	R99	1.2	M	M	M	M	E.1/19	No	
	digits only	R99	1.1	M	M	M	M	E.1/19	No	
	SMS alphabet	R99	1.3	M	M	M	M	E.1/19	No	
	hidden input	R99	1.4	M	M	M	M	E.1/19	No	
	min / max acceptable length	R99	1.5, 1.9	M	M	M	M	E.1/19	No	
	Backwards move in UICC session	R99	1.6	M	M	M	M	E.1/19	No	
	Session terminated by user	R99	1.7	M	M	M	M	E.1/19	No	
	Prompt text up to 160 bytes	R99	1.8	M	M	M	M	E.1/19	No	
	SMS default alphabet, ME to echo text, packing not required	R99	1.9	M	M	M	M	E.1/19	No	
	Null length for the text string	R99	1.10	M	M	M	M	E.1/19	No	
	no response from user	R99	2.1	C120	C120	C120	C120	E.1/19	No	
	UCS2 display in Cyrillic	R99	3.1, 3.2	C118	C118	C118	C118	E.1/19 AND E.1/15	No	
	UCS2 entry in Cyrillic	R99	4.1, 4.2	C105	C105	C105	C105	E.1/19 AND E.1/14	No	
	default text for the input	R99	5.1, 5.2	M	M	M	M	E.1/19	No	
	icons	R99	6.1, 6.2, 6.3, 6.4	C108	C108	C108	C108	E.1/19	No	
	help information	R99	7.1	C107	C107	C107	C107	E.1/19	No	
	Text attribute– left alignment	Rel-5	8.1			C153	C153	E.1/19 AND E.1/124 AND E.1/217	No	
	Text attribute – center alignment	Rel-5	8.2			C154	C145	E.1/19 AND E.1/124 AND E.1/218	No	
	Text attribute – right alignment	Rel-5	8.3			C155	C155	E.1/19 AND E.1/124 AND E.1/219	No	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – large font size	Rel-5	8.4			C157 AND C156	C157 AND C156	E.1/19 AND E.1/124 AND E.1/221 AND E.1/220	No	
	Text attribute – small font size	Rel-5	8.5			C158 AND C156	C158 AND C156	E.1/19 AND E.1/124 AND E.1/222 AND E.1/220	No	
	Text attribute – bold on	Rel-5	8.6			C160 AND C159	C160 AND C159	E.1/19 AND E.1/124 AND E.1/225 AND E.1/226	No	
	Text attribute – italic on	Rel-5	8.7			C161 AND C159	C161 AND C159	E.1/19 AND E.1/124 AND E.1/225 AND E.1/227	No	
	Text attribute – underlined on	Rel-5	8.8			C162 AND C159	C162 AND C159	E.1/19 AND E.1/124 AND E.1/225 AND E.1/228	No	
	Text attribute – strikethrough on	Rel-5	8.9			C163 AND C159	C163 AND C159	E.1/19 AND E.1/124 AND E.1/225 AND E.1/229	No	
	Text attribute – foreground and background colours	Rel-5	8.10			C164 AND C165	C164 AND C165	E.1/19 AND E.1/124 AND E.1/230 AND E.1/231	No	
	UCS2 display in Chinese	R99	9.1, 9.2			C143	C143	E.1/19 AND E.1/15	No	
	UCS2 entry in Chinese	R99	10.1, 10.2			C142	C142	E.1/19 AND E.1/14	No	
	UCS2 display in Katakana	R99	11.1, 11.2			C145	C145	E.1/19 AND E.1/15	No	
	UCS2 entry in Katakana	R99	12.1, 12.2			C144	C144	E.1/19 AND E.1/14	No	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Frames	Rel-6	TBD				C133	E.1/19 AND E.1/177 AND E.1/178	TBD	
7	MORE TIME	R99	1.1	M	M	M	M	E.1/20	No	
8	PLAY TONE									
	play all tones	R99	1.1	M	M	M	M	E.1/21	Yes	
	display alpha	R99	1.1	M	M	M	M	E.1/21	Yes	
	user termination	R99	1.1	M	M	M	M	E.1/21	Yes	
	superimpose	R99	1.1	M	M	M	M	E.1/21	Yes	
	UCS2 display in Cyrillic	R99	2.1	C118	C118	C118	C118	E.1/21 AND E.1/15	No	
	icons	R99	3.1, 3.2,3.3, 3.4	C108	C108	C108	C108	E.1/21	No	
	Text attribute – left alignment	Rel-5	4.1				C153 C153	E.1/21 AND E.1/124 AND E.1/217	No	
	Text attribute – center alignment	Rel-5	4.2				C154 C154	E.1/21 AND E.1/124 AND E.1/218	No	
	Text attribute – right alignment	Rel-5	4.3				C155 C155	E.1/21 AND E.1/124 AND E.1/219	No	
	Text attribute – large font size	Rel-5	4.4				C157 AND C156 C156	E.1/21 AND E.1/124 AND E.1/221 AND E.1/220	No	
	Text attribute – small font size	Rel-5	4.5				C158 AND C156 C156	E.1/21 AND E.1/124 AND E.1/222 AND E.1/220	No	
	Text attribute – bold on	Rel-5	4.6				C160 AND C159 C159	E.1/21 AND E.1/124 AND E.1/225 AND E.1/226	No	
	Text attribute – italic on	Rel-5	4.7				C161 AND C159 C159	E.1/21 AND E.1/124 AND E.1/225 AND E.1/227	No	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – underlined on	Rel-5	4.8			C162 AND C159	C162 AND C159	E.1/21 AND E.1/124 AND E.1/225 AND E.1/228	No	
	Text attribute – strikethrough on	Rel-5	4.9			C163 AND C159	C163 AND C159	E.1/21 AND E.1/124 AND E.1/225 AND E.1/229	No	
	Text attribute– foreground and background colours	Rel-5	4.10			C164 AND C165	C164 AND C165	E.1/21 AND E.1/124 AND E.1/230 AND E.1/231	No	
	UCS2 display in Chinese	R99	5.1			C143	C143	E.1/21 AND E.1/15	No	
	UCS2 display in Katakana	R99	6.1			C145	C145	E.1/21 AND E.1/15	No	
	Frames	Rel-6	TBD				C133	E.1/21 AND E.1/177 AND E.1/178	TBD	
	Themed and Melody tones	Rel-6	TBD				C138	E.1/21	TBD	
<b>9</b>	<b>POLL INTERVAL</b>									
	duration	R99	1.1	M	M	M	M	E.1/22	No	
<b>10</b>	<b>REFRESH</b>									
	USIM initialization, enabling FDN mode	R99	1.1	C146	C146	C146	C146	E.1/24	Yes	
	file change notification of FDN file	R99	1.2	C146	C146	C146	C146	E.1/24	Yes	
	USIM initialization and file change notification of ADN	R99	1.3	C168	C168	C168	M	E.1/24	No	
	USIM initialization and full file change notification, enabling FDN mode	R99	1.4	C146	C146	C146	C146	E.1/24	Yes	
	UICC reset	R99	1.5	M	M	M	M	E.1/24	TBD	
	USIM Initialization after SMS-PP data download	R99	1.6	C146	C146	C146	C146	E.1/24	Yes	
	UICC Reset for IMSI Changing procedure	R99	2.1						TBD	
	USIM Application Reset for IMSI Changing procedure	R99	2.2				M	E.1/24	Yes	
	3G Session Reset for IMSI Changing procedure	R99	2.3						TBD	
	reject 3G Session Reset for IMSI Changing procedure during call	R99	2.4				M	E.1/24	Yes	
<b>11</b>	<b>SET UP MENU</b>									
	Set up, menu selection, replace and remove menu	R99	1.1	M	M	M	M	E.1/30 AND E.1/4	No	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Large menu	R99	1.2	M	M	M	M	E.1/30 AND E.1/4	No	
	help information	R99	2.1	C107	C107	C107	C107	E.1/30 AND E.1/4	No	
	next action indicator	R99	3.1	M	M	M	M	E.1/30	No	
	Icons	R99	4.1, 4.2	C108	C108	C108	C108	E.1/30	No	
	soft key access	R99	5.1	C112	C112	C112	C112	E.1/30 AND E.1/74	No	
	Text attribute – left alignment	Rel-5	6.1			C153	C153	E.1/30 AND E.1/124 AND E.1/217	No	
	Text attribute – center alignment	Rel-5	6.2			C154	C154	E.1/30 AND E.1/124 AND E.1/218	No	
	Text attribute – right alignment	Rel-5	6.3			C155	C155	E.1/30 AND E.1/124 AND E.1/219	No	
	Text attribute – large font size	Rel-5	6.4			C157 AND C156	C157 AND C156	E.1/30 AND E.1/124 AND E.1/221 AND E.1/220	No	
	Text attribute – small font size	Rel-5	6.5			C158 AND C156	C158 AND C156	E.1/30 AND E.1/124 AND E.1/222 AND E.1/220	No	
	Text attribute – bold on	Rel-5	6.6			C160 AND C159	C160 AND C159	E.1/30 AND E.1/124 AND E.1/225 AND E.1/226	No	
	Text attribute – italic on	Rel-5	6.7			C161 AND C159	C161 AND C159	E.1/30 AND E.1/124 AND E.1/225 AND E.1/227	No	
	Text attribute – underlined on	Rel-5	6.8			C162 AND C159	C162 AND C159	E.1/30 AND E.1/124 AND E.1/225 AND E.1/228	No	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – strikethrough on	Rel-5	6.9			C163 AND C159	C163 AND C159	E.1/30 AND E.1/124 AND E.1/225 AND E.1/229	No	
	Text attribute – foreground and background colours	Rel-5	6.10			C164 AND C165	C164 AND C165	E.1/30 AND E.1/124 AND E.1/230 AND E.1/231	No	
	UCS2 display in Cyrillic	R99	7.1			C118	C118	E.1/39 AND E.1/15	No	
	UCS2 display in Chinese	R99	8.1			C143	C143	E.1/39 AND E.1/15	No	
	UCS2 display in Katakana	R99	9.1			C145	C145	E.1/39 AND E.1/15	No	
<b>12</b>	<b>SELECT ITEM</b>									
	Mandatory features	R99	1.1	M	M	M	M	E.1/25	No	
	Large menu	R99	1.2, 1.3, 1.5, 1.6	M	M	M	M	E.1/25	No	
	Backwards move	R99	1.4	M	M	M	M	E.1/25	No	
	user termination	R99	1.5	M	M	M	M	E.1/25	No	
	next action indicator	R99	2.1	M	M	M	M	E.1/25	No	
	default selected item	R99	3.1	M	M	M	M	E.1/25	No	
	help information	R99	4.1	C107	C107	C107	C107	E.1/25	No	
	icons	R99	5.1, 5.2	C108	C108	C108	C108	E.1/25	No	
	Presentation style	R99	6.1, 6.2	M	M	M	M	E.1/25	No	
	Soft keys	R99	7.1	C112	C112	C112	C112	E.1/25 AND E.1/73	No	
	No Response from user	R99	8.1	C120	C120	C120	C120	E.1/25	No	
	Text attribute – left alignment	Rel-5	9.1			C153	C153	E.1/25 AND E.1/124 AND E.1/217	No	
	Text attribute – center alignment	Rel-5	9.2			C154	C154	E.1/25 AND E.1/124 AND E.1/218	No	
	Text attribute – right alignment	Rel-5	9.3			C155	C155	E.1/25 AND E.1/124 AND E.1/219	No	
	Text attribute – large font size	Rel-5	9.4			C157 AND C156	C157 AND C156	E.1/25 AND E.1/124 AND E.1/221 AND E.1/220	No	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – small font size	Rel-5	9.5			C158 AND C156	C158 AND C156	E.1/25 AND E.1/124 AND E.1/222 AND E.1/220	No	
	Text attribute – bold on	Rel-5	9.6			C160 AND C159	C160 AND C159	E.1/25 AND E.1/124 AND E.1/225 AND E.1/226	No	
	Text attribute – italic on	Rel-5	9.7			C161 AND C159	C161 AND C159	E.1/25 AND E.1/124 AND E.1/225 AND E.1/227	No	
	Text attribute – underline on	Rel-5	9.8			C162 AND C159	C162 AND C159	E.1/25 AND E.1/124 AND E.1/225 AND E.1/228	No	
	Text attribute – strikethrough on	Rel-5	9.9			C163 AND C159	C163 AND C159	E.1/25 AND E.1/124 AND E.1/225 AND E.1/229	No	
	Text attribute – foreground and background colours	Rel-5	9.10			C164 AND C165	C164 AND C165	E.1/25 AND E.1/124 AND E.1/230 AND E.1/231	No	
	UCS2 display in Cyrillic	R99	10.1, 10.2, 10.3			C118	C118	E.1/39 AND E.1/15	No	
	UCS2 display in Chinese	R99	11.1			C143	C143	E.1/25 AND E.1/15	No	
	UCS2 display in Katakana	R99	12.1, 12.2, 12.3			C145	C145	E.1/25 AND E.1/15	No	
	Frames	Rel-6	TBD				C133	E.1/25 AND E.1/177 AND E.1/178	TBD	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
13	<b>SEND SMS</b>									
	Packing not required	R99	1.1, 1.3 1.5	M	M	M	M	E.1/26	Yes	
	Packing required	R99	1.2, 1.4	M	M	M	M	E.1/26	Yes	
	8 bit data	R99	1.1, 1.2	M	M	M	M	E.1/26	Yes	
	SMS default alphabet	R99	1.3, 1.4, 1.5	M	M	M	M	E.1/26	Yes	
	160 bytes length	R99	1.4, 1.5	M	M	M	M	E.1/26	Yes	
	Alpha identifier	R99	1.6, 1.7, 1.8	M	M	M	M	E.1/26	Yes	
	UCS2 SMS in Cyrillic	R99	2.1	C118	C118	C118	C118	E.1/26 AND E.1/15	Yes	
	icons	R99	3.1, 3.2	C108	C108	C108	C108	E.1/26	Yes	
	Text attribute– left alignment	Rel-5	4.1			C153	C153	E.1/26 AND E.1/124 AND E.1/217	Yes	
	Text attribute – center alignment	Rel-5	4.2			C154	C154	E.1/26 AND E.1/124 AND E.1/218	No	
	Text attribute – right alignment	Rel-5	4.3			C155	C155	E.1/26 AND E.1/124 AND E.1/219	No	
	Text attribute – large font size	Rel-5	4.4			C157 AND C156	C157 AND C156	E.1/26 AND E.1/124 AND E.1/221 AND E.1/220	No	
	Text attribute – small font size	Rel-5	4.5			C158 AND C156	C158 AND C156	E.1/26 AND E.1/124 AND E.1/222 AND E.1/220	No	
Text attribute – bold on	Rel-5	4.6			C160 AND C159	C160 AND C159	E.1/26 AND E.1/124 AND E.1/225 AND E.1/226	No		
Text attribute – italic on	Rel-5	4.7			C161 AND C159	C161 AND C159	E.1/26 AND E.1/124 AND E.1/225 AND E.1/227	No		
Text attribute – underline on	Rel-5	4.8			C162 AND C159	C162 AND C159	E.1/26 AND E.1/124 AND E.1/225 AND E.1/228	No		

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute– strikethrough on	Rel-5	4.9			C163 AND C159	C163 AND C159	E.1/26 AND E.1/124 AND E.1/225 AND E.1/229	No	
	Text attribute – foreground and background colours	Rel-5	4.10			C164 AND C165	C164 AND C165	E.1/26 AND E.1/124 AND E.1/230 AND E.1/231	No	
	UCS2 display in Chinese	R99	5.1			C143	C143	E.1/26 AND E.1/15	Yes	
	UCS2 display in Katakana	R99	6.1			C145	C145	E.1/26 AND E.1/15	Yes	
	Frames	Rel-6	TBD				C133	E.1/26 AND E.1/177 AND E.1/178	TBD	
<b>14</b>	<b>SEND SS</b>									
	call forward unconditional, all bearers, successful	R99	1.1	C166	C166	C166	C166	E.1/27	Yes	
	call forward unconditional, all bearers, Return Error	R99	1.2	M	M	M	M	E.1/27	Yes	
	call forward unconditional, all bearers, Reject	R99	1.3	M	M	M	M	E.1/27	Yes	
	call forward unconditional, all bearers, successful, SS request size limit	R99	1.4	C166	C166	C166	C166	E.1/27	Yes	
	interrogate CLIR status, successful, alpha identifier limits	R99	1.5	M	M	M	M	E.1/27	Yes	
	call forward unconditional, all bearers, successful, null data alpha identifier	R99	1.6	C166	C166	C166	C166	E.1/27	Yes	
	call forward unconditional, all bearers, successful, icon support	R99	2.1, 2.2, 2.3, 2.4	C108	C108	C108	C108	E.1/27	Yes	
	UCS2 display in Cyrillic	R99	3.1	C118	C118	C118	C118	E.1/27 AND E.1/15	Yes	
	Text attribute – left alignment	Rel-5	4.1			C153 AND C166	C153 AND C166	E.1/27 AND E.1/124 AND E.1/217	Yes	
	Text attribute – center alignment	Rel-5	4.2			C154 AND C166	C154 AND C166	E.1/27 AND E.1/124 AND E.1/218	Yes	
	Text attribute – right alignment	Rel-5	4.3			C155 AND C166	C155 AND C166	E.1/27 AND E.1/124 AND E.1/219	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – large font size	Rel-5	4.4			C157 AND C156 AND C166	C157 AND C156 AND C166	E.1/27 AND E.1/124 AND E.1/221 AND E.1/220	Yes	
	Text attribute – small font size	Rel-5	4.5			C158 AND C156 AND C166	C158 AND C156 AND C166	E.1/27 AND E.1/124 AND E.1/222 AND E.1/220	Yes	
	Text attribute – bold on	Rel-5	4.6			C160 AND C159 AND C166	C160 AND C159 AND C166	E.1/27 AND E.1/124 AND E.1/225 AND E.1/226	Yes	
	Text attribute – italic on	Rel-5	4.7			C161 AND C159 AND C166	C161 AND C159 AND C166	E.1/27 AND E.1/124 AND E.1/225 AND E.1/227	Yes	
	Text attribute – underline on	Rel-5	4.8			C162 AND C159 AND C166	C162 AND C159 AND C166	E.1/27 AND E.1/124 AND E.1/225 AND E.1/228	Yes	
	Text attribute – strikethrough on	Rel-5	4.9			C163 AND C159 AND C166	C163 AND C159 AND C166	E.1/27 AND E.1/124 AND E.1/225 AND E.1/229	Yes	
	Text attribute – foreground and background colours	Rel-5	4.10			C164 AND C165 AND C166	C164 AND C165 AND C166	E.1/27 AND E.1/124 AND E.1/230 AND E.1/231	Yes	
	UCS2 display in Chinese	R99	5.1			C143 AND C166	C143 AND C166	E.1/27 AND E.1/15	Yes	
	UCS2 display in Katakana	R99	6.1			C145 AND C166	C145 AND C166	E.1/27 AND E.1/15	Yes	
<b>15</b>	<b>SEND USSD</b>									
	7-bit data, successful	R99	1.1	M	M	M	M	E.1/28	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	8-bit data, successful	R99	1.2	M	M	M	M	E.1/28	Yes	
	UCS2 data, successful	R99	1.3	M	M	M	M	E.1/28	Yes	
	7-bit data, unsuccessful	R99	1.4	M	M	M	M	E.1/28	Yes	
	7-bit data, unsuccessful	R99	1.5	M	M	M	M	E.1/28	Yes	
	256 octets, 7-bit data, successful, long alpha identifier	R99	1.6	M	M	M	M	E.1/28	Yes	
	7-bit data, successful, no alpha identifier	R99	1.7	M	M	M	M	E.1/28	Yes	
	7-bit data, successful, null length alpha identifier	R99	1.8	M	M	M	M	E.1/28	Yes	
	icons	R99	2.1, 2.2, 2.3, 2.4	C108	C108	C108	C108	E.1/28	Yes	
	UCS2 in Cyrillic	R99	3.1	C118	C118	C118	C118	E.1/28 AND E.1/15	Yes	
	Text attribute – left alignment	Rel-5	4.1			C153	C153	E.1/28 AND E.1/124 AND E.1/217	Yes	
	Text attribute – center alignment	Rel-5	4.2			C154	C154	E.1/28 AND E.1/124 AND E.1/218	Yes	
	Text attribute – right alignment	Rel-5	4.3			C155	C155	E.1/28 AND E.1/124 AND E.1/219	Yes	
	Text attribute – large font size	Rel-5	4.4			C157 AND C156	C157 AND C156	E.1/28 AND E.1/124 AND E.1/221 AND E.1/220	Yes	
	Text attribute – small font size	Rel-5	4.5			C158 AND C156	C158 AND C156	E.1/28 AND E.1/124 AND E.1/222 AND E.1/220	Yes	
	Text attribute – bold on	Rel-5	4.6			C160 AND C159	C160 AND C159	E.1/28 AND E.1/124 AND E.1/225 AND E.1/226	Yes	
	Text attribute – italic on	Rel-5	4.7			C161 AND C159	C161 AND C159	E.1/28 AND E.1/124 AND E.1/225 AND E.1/227	Yes	
	Text attribute – underline on	Rel-5	4.8			C162 AND C159	C162 AND C159	E.1/28 AND E.1/124 AND E.1/225 AND E.1/228	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – strikethrough on	Rel-5	4.9			C163 AND C159	C163 AND C159	E.1/28 AND E.1/124 AND E.1/225 AND E.1/229	Yes	
	Text attribute – foreground and background colours	Rel-5	4.10			C164 AND C165	C164 AND C165	E.1/28 AND E.1/124 AND E.1/230 AND E.1/231	Yes	
	UCS2 in Chinese	R99	5.1			C143	C143	E.1/28 AND E.1/15	Yes	
	UCS2 in Katakana	R99	6.1			C145	C145	E.1/28 AND E.1/15	Yes	
<b>16</b>	<b>SET UP CALL</b>									
	Call confirmed by the user and connected	R99	1.1	M	M	M	M	E.1/29	Yes	
	call rejected by the user	R99	1.2	M	M	M	M	E.1/29	Yes	
	void							E.1/29		
	putting all other calls on hold, ME busy	R99	1.4	M	M	M	M	E.1/29	Yes	
	disconnecting all other calls, ME busy	R99	1.5	M	M	M	M	E.1/29	Yes	
	only if not currently busy on another call, ME busy	R99	1.6	M	M	M	M	E.1/29	Yes	
	putting all other calls on hold, call hold is not allowed	R99	1.7	M	M	M	M	E.1/29	Yes	
	Capability configuration	R99	1.8	C101	C101	C101	C101	E.1/29	Yes	
	long dialling number string	R99	1.9	M	M	M	M	E.1/29	Yes	
	long first alpha identifier	R99	1.10	M	M	M	M	E.1/29	Yes	
	Called party subaddress	R99	1.11	C124	C124	C124	C124	E.1/29	Yes	
	maximum duration for the redial mechanism	R99	1.12	C119	C119	C119	C119	E.1/29	Yes	
	second alpha identifier	R99	2.1	M	M	M	M	E.1/29 AND E.1/63	Yes	
	icons	R99	3.1,3.2, 3.3, 3.4	C108	C108	C108	C108	E.1/29	Yes	
	Text attribute – left alignment	Rel-5	4.1			C153	C153	E.1/29 AND E.1/124 AND E.1/217	Yes	
	Text attribute – center alignment	Rel-5	4.2			C154	C154	E.1/29 AND E.1/124 AND E.1/218	Yes	
	Text attribute – right alignment	Rel-5	4.3			C155	C155	E.1/29 AND E.1/124 AND E.1/219	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – large font size	Rel-5	4.4			C157 AND C156	C157 AND C156	E.1/29 AND E.1/124 AND E.1/221 AND E.1/220	Yes	
	Text attribute – small font size	Rel-5	4.5			C158 AND C156	C158 AND C156	E.1/29 AND E.1/124 AND E.1/222 AND E.1/220	Yes	
	Text attribute – bold on	Rel-5	4.6			C160 AND C159	C160 AND C159	E.1/29 AND E.1/124 AND E.1/225 AND E.1/226	Yes	
	Text attribute – italic on	Rel-5	4.7			C161 AND C159	C161 AND C159	E.1/29 AND E.1/124 AND E.1/225 AND E.1/227	Yes	
	Text attribute – underline on	Rel-5	4.8			C162 AND C159	C162 AND C159	E.1/29 AND E.1/124 AND E.1/225 AND E.1/228	Yes	
	Text attribute – strikethrough on	Rel-5	4.9			C163 AND C159	C163 AND C159	E.1/29 AND E.1/124 AND E.1/225 AND E.1/229	Yes	
	Text attribute – foreground and background colours	Rel-5	4.10			C164 AND C165	C164 AND C165	E.1/29 AND E.1/124 AND E.1/230 AND E.1/231	Yes	
	UCS2 Display in Cyrillic	R99	5.1, 5.2.			C118	C118	E.1/29 AND E.1/15	Yes	
	UCS2 display in Chinese	R99	6.1, 6.2			C143	C143	E.1/29 AND E.1/15	Yes	
	UCS2 display in Katakana	R99	7.1, 7.2			C145	C145	E.1/29 AND E.1/15	Yes	
	Frames	Rel-6	TBD				C133	E.1/29 AND E.1/177 AND E.1/178	TBD	
17	<b>POLLING OFF</b>	R996	1.1	M	M	M	M	E.1/23	Yes	
18	<b>PROVIDE LOCAL INFO</b>									

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	location information	R99	1.1	M	M	M	M	E.1/31	Yes	
	IMEI	R99	1.2	M	M	M	M	E.1/31	Yes	
	network measurement results and BCCH channel list	R99	1.3	C167	C167	C167	C167	E.1/32 AND E.1/67	Yes	
	Date, time and time zone	R99	1.4	M	M	M	M	E.1/59	No	
	language setting	R99	1.5	M	M	M	M	E.1/68	No	
	Timing advance	R99	1.6	C167	C167	C167	C167	E.1/69	Yes	
	Access Technology	Rel-4	1.7	M	M	M	M	E.1/72	Yes	
	Void									
	IMEISV	Rel-6	1.9				M	E.1/143	Yes	
	Search Mode Change	Rel-6	1.10				M	E.1/144	TBD	
	Charge State of the Battery	Rel-6	1.11				C139	E.1/170	No	
	UTRAN measurements	Rel-6	1.12				M	E.1/183	Yes	
<b>19</b>	<b>SET UP EVENT LIST</b>									
	Set up call connected event	R99	1.1	M	M	M	M	E.1/33 AND E.1/35	Yes	
	Replace by new event list	R99	1.2	M	M	M	M	E.1/33 AND E.1/35 AND E.1/36	Yes	
	Remove event	R99	1.3	M	M	M	M	E.1/33 AND E.1/35	Yes	
	Remove Event on ME Power Cycle	R99	1.4	M	M	M	M	E.1/33 AND E.1/35	Yes	
<b>20</b>	<b>PERFORM CARD APDU</b>									
	Additional card inserted, Select MF and Get Response	R99	1.1	C109	C109	C109	C109	E.1/51	No	
	Additional card inserted, Select DF GSM, Select EF PLMN , Update Binary, Read Binary on EF PLMN	R99	1.2	C109	C109	C109	C109	E.1/51	No	
	Additional card inserted, card powered off	R99	1.3	C109	C109	C109	C109	E.1/51	No	
	No card inserted, card powered off	R99	1.4	C109	C109	C109	C109	E.1/51	No	
	Invalid card reader identifier	R99	1.5	C109	C109	C109	C109	E.1/51	No	
	Detachable reader	R99	2.1	C116	C116	C116	C116	E.1/51	No	
<b>21</b>	<b>POWER OFF CARD</b>									
	Additional card inserted	R99	1.1	C109	C109	C109	C109	E.1/50	No	
	No card inserted	R99	1.2	C109	C109	C109	C109	E.1/50	No	
	Detachable reader	R99	2.1	C116	C109	C109	C109	E.1/50	No	
<b>22</b>	<b>POWER ON CARD</b>									
	Additional card inserted	R99	1.1	C109	C109	C109	C109	E.1/49	No	
	No ATR	R99	1.2	C109	C109	C109	C109	E.1/49	No	
	No card inserted	R99	1.3	C109	C109	C109	C109	E.1/49	No	
	Detachable reader	R99	2.1	C116	C116	C116	C116	E.1/49	No	
<b>23</b>	<b>GET READER STATUS</b>									
	Additional card inserted, card powered	R99	1.1	C109	C109	C109	C109	E.1/52	No	
	Additional card inserted, card not powered	R99	1.2	C109	C109	C109	C109	E.1/52	No	
	Additional card inserted, card not present	R99	1.3	C109	C109	C109	C109	E.1/52	No	
	Detachable reader	R99	2.1	C116	C116	C116	C116	E.1/52	No	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
24	<b>TIMER MANAGEMENT</b>									
	Start timer 1 several times, get the current value of the timer and deactivate the timer successfully	R99	1.1	M	M	M	M	E.1/57 AND E.1/58	No	
	Start timer 2 several times, get the current value of the timer and deactivate the timer successfully	R99	1.2	M	M	M	M	E.1/57 AND E.1/58	No	
	Start timer 8 several times, get the current value of the timer and deactivate the timer successfully	R99	1.3	M	M	M	M	E.1/57 AND E.1/58	No	
	Try to get the current value of a timer which is not started: action in contradiction with the current timer state	R99	1.4	M	M	M	M	E.1/57 AND E.1/58	No	
	Try to deactivate a timer which is not started: action in contradiction with the current timer state	R99	1.5	M	M	M	M	E.1/57 AND E.1/58	No	
	Start 8 timers successfully	R99	1.6	M	M	M	M	E.1/57 AND E.1/58	No	
25	<b>ENVELOPE TIMER EXPIRATION</b>									
	Pending proactive UICC command	R99	2.1	M	M	M	M	E.1/6 AND E.1/57	No	
	USIM application toolkit busy	R99	2.2	M	M	M	M	E.1/6 AND E.1/57 AND E.1/20	No	
26	<b>SET UP IDLE MODE TEXT</b>									
	Display idle mode text	R99	1.1	M	M	M	M	E.1/61 AND E.1/33 AND E.1/39	Yes	
	Replace idle mode text	R99	1.2	M	M	M	M	E.1/61 AND E.1/33 AND E.1/39	Yes	
	Remove idle mode test	R99	1.3	M	M	M	M	E.1/61 AND E.1/33 AND E.1/39	Yes	
	Competing information on ME display	R99	1.4	M	M	M	M	E.1/61 AND E.1/33 AND E.1/39	Yes	
	ME powered cycled	R99	1.5	M	M	M	M	E.1/61 AND E.1/33 AND E.1/39	Yes	
	Refresh with USIM initialization	R99	1.6	M	M	M	M	E.1/61 AND E.1/24 AND E.1/33 AND E.1/39	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Large text string	R99	1.7	M	M	M	M	E.1/61 AND E.1/33 AND E.1/39	Yes	
	Icons	R99	2.1, 2.2, 2.3, 2.4	C108	C108	C108	C108	E.1/61 AND E.1/39	Yes	
	UCS2 display in Cyrillic	R99	3.1	C118	C118	C118	C118	E.1/61 AND E.1/15 AND E.1/39	Yes	
	Text attribute – left alignment	Rel-5	4.1			C153	C153	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/217	Yes	
	Text attribute – center alignment	Rel-5	4.2			C154	C154	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/218	Yes	
	Text attribute – right alignment	Rel-5	4.3			C155	C155	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/219	Yes	
	Text attribute – large font size	Rel-5	4.4			C157 AND C156	C157 AND C156	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/221 AND E.1/220	Yes	
	Text attribute – small font size	Rel-5	4.5			C158 AND C156	C158 AND C156	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/222 AND E.1/220	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support	
	Text attribute – bold on	Rel-5	4.6				C160 AND C159	C160 AND C159	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/226	Yes	
	Text attribute – italic on	Rel-5	4.7				C161 AND C159	C161 AND C159	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/227	Yes	
	Text attribute – underline on	Rel-5	4.8				C162 AND C159	C162 AND C159	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/228	Yes	
	Text attribute – strikethrough on	Rel-5	4.9				C163 AND C159	C163 AND C159	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/229	Yes	
	Text attribute – foreground and background colours	Rel-5	4.10				C164 AND C165	C164 AND C165	E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/230 AND E.1/231	Yes	
	UCS2 display in Chinese	R99	5.1				C143	C143	E.1/61 AND E.1/15 AND E.1/39	Yes	
	UCS2 display in Katakana	R99	6.1				C145	C145	E.1/61 AND E.1/15 AND E.1/39	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Frames	Rel-6	TBD				C133	E.1/61 AND E.1/177 AND E.1/178	TBD	
<b>27</b>	<b>RUN AT COMMAND</b>									
	No alpha Identifier	R99	1.1	C110	C110	C110	C110	E.1/62	No	
	null data alpha identifier presented	R99	1.2	C110	C110	C110	C110	E.1/62	No	
	alpha identifier presented	R99	1.3	C110	C110	C110	C110	E.1/62	No	
	Icons	R99	2.1, 2.2, 2.3, 2.4, 2.5	C114	C114	C114	C114	E.1/62	No	
	Text attribute – left alignment	Rel-5	3.1			C110 AND C153	C110 AND C153	E.1/62 AND E.1/124 AND E.1/217	No	
	Text attribute – center alignment	Rel-5	3.2			C110 AND C154	C110 AND C154	E.1/62 AND E.1/124 AND E.1/218	No	
	Text attribute – right alignment	Rel-5	3.3			C110 AND C155	C110 AND C155	E.1/62 AND E.1/124 AND E.1/219	No	
	Text attribute – large font size	Rel-5	3.4			C110 AND C157 AND C156	C110 AND C157 AND C156	E.1/62 AND E.1/124 AND E.1/221 AND E.1/220	No	
	Text attribute – small font size	Rel-5	3.5			C110 AND C158 AND C156	C110 AND C158 AND C156	E.1/62 AND E.1/124 AND E.1/222 AND E.1/220	No	
	Text attribute – bold on	Rel-5	3.6			C110 AND C160 AND C159	C110 AND C160 AND C159	E.1/62 AND E.1/124 AND E.1/225 AND E.1/226	No	
	Text attribute – italic on	Rel-5	3.7			C110 AND C161 AND C159	C110 AND C161 AND C159	E.1/62 AND E.1/124 AND E.1/225 AND E.1/227	No	
	Text attribute – underline on	Rel-5	3.8			C110 AND C162 AND C159	C110 AND C162 AND C159	E.1/62 AND E.1/124 AND E.1/225 AND E.1/228	No	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – strikethrough on	Rel-5	3.9			C110 AND C163 AND C159	C110 AND C163 AND C159	E.1/62 AND E.1/124 AND E.1/225 AND E.1/229	No	
	Text attribute – foreground and background colours	Rel-5	3.10			C110 AND C164 AND C165	C110 AND C164 AND C165	E.1/62 AND E.1/124 AND E.1/230 AND E.1/231	No	
	UCS2 Display in Cyrillic	R99	4.1			C149	C149	E.1/62 AND E.1/15	No	
	UCS2 display in Chinese	R99	5.1			C150	C150	E.1/62 AND E.1/15	No	
	UCS2 display in Katakana	R99	6.1			C151	C151	E.1/62 AND E.1/15	No	
	Frames	Rel-6	TBD				C135	E.1/62 AND E.1/177 AND E.1/178	TBD	
<b>28</b>	<b>SEND DTMF</b>									
	Normal	R99	1.1	M	M	M	M	E.1/66	Yes	
	alpha identifier	R99	1.2, 1.3	M	M	M	M	E.1/66	Yes	
	Mobile is not in a speech call	R99	1.4	M	M	M	M	E.1/66	Yes	
	Icons	R99	2.1, 2.2, 2.3	C108	C108	C108	C108	E.1/66	Yes	
	UCS2 display in Cyrillic	R99	3.1	C118	C118	C118	C118	E.1/66 AND E.1/15	Yes	
	Text attribute – left alignment	Rel-5	4.1			C153	C153	E.1/66 AND E.1/124 AND E.1/217	Yes	
	Text attribute – center alignment	Rel-5	4.2			C154	C154	E.1/66 AND E.1/124 AND E.1/218	Yes	
	Text attribute – right alignment	Rel-5	4.3			C155	C155	E.1/66 AND E.1/124 AND E.1/219	Yes	
	Text attribute – large font size	Rel-5	4.4			C157 AND C156	C157 AND C156	E.1/66 AND E.1/124 AND E.1/221 AND E.1/220	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – small font size	Rel-5	4.5			C158 AND C156	C158 AND C156	E.1/66 AND E.1/124 AND E.1/222 AND E.1/220	Yes	
	Text attribute – bold on	Rel-5	4.6			C160 AND C159	C160 AND C159	E.1/66 AND E.1/124 AND E.1/225 AND E.1/226	Yes	
	Text attribute – italic on	Rel-5	4.7			C161 AND C159	C161 AND C159	E.1/66 AND E.1/124 AND E.1/225 AND E.1/227	Yes	
	Text attribute – underline on	Rel-5	4.8			C162 AND C159	C162 AND C159	E.1/66 AND E.1/124 AND E.1/225 AND E.1/228	Yes	
	Text attribute – strikethrough on	Rel-5	4.9			C163 AND C159	C163 AND C159	E.1/66 AND E.1/124 AND E.1/225 AND E.1/229	Yes	
	Text attribute – foreground and background colours	Rel-5	4.10			C164 AND C165	C164 AND C165	E.1/66 AND E.1/124 AND E.1/230 AND E.1/231	Yes	
	UCS2 display in Chinese	R99	5.1			C143	C143	E.1/66 AND E.1/15	Yes	
	UCS2 display in Katakana	R99	6.1			C145	C145	E.1/66 AND E.1/15	Yes	
	Frames	Rel-6	TBD				C133	E.1/66 AND E.1/177 AND E.1/178	TBD	
<b>29</b>	<b>LANGUAGE NOTIFICATION</b>									
	Specific language notification	R99	1.1	M	M	M	M	E.1/70	No	
	Non specific language notification	R99	1.2	M	M	M	M	E.1/70	No	
<b>30</b>	<b>LAUNCH BROWSER</b>									
	No session already launched: Connect to the default URL	R99	1.1	C111	C111	C111	C111	E.1/71	Yes	
	connect to the specified URL, alpha identifier length=0	R99	1.2	C111	C111	C111	C111	E.1/71	Yes	
	Browser identity, no alpha identifier	R99	1.3	C111	C111	C111	C111	E.1/71	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	one bearer specified and gateway/proxy identity	R99	1.4	C122	C122	C122	C122	E.1/71 AND E.1/98	Yes	
	void	R99	1.5	Void	void	void	void	void		
	Interaction with current session	R99	2.1, 2.2, 2.3	C111	C111	C111	C111	E.1/71	Yes	
	UCS2 display in Cyrillic	R99	3.1	C111 AND 118	C111 AND 118	C111 AND 118	C111 AND 118	E.1/71 AND E.1/15	Yes	
	Icons	R99	4.1, 4.2	C115	C115	C115	C115	E.1/71	Yes	
	Text attribute – left alignment	Rel-5	5.1			C111 AND C153	C111 AND C153	E.1/71 AND E.1/124 AND E.1/217	Yes	
	Text attribute – center alignment	Rel-5	5.2			C111 AND C154	C111 AND C154	E.1/71 AND E.1/124 AND E.1/218	Yes	
	Text attribute – right alignment	Rel-5	5.3			C111 AND C155	C111 AND C155	E.1/71 AND E.1/124 AND E.1/219	Yes	
	Text attribute – large font size	Rel-5	5.4			C111 AND C157 AND C156	C111 AND C157 AND C156	E.1/71 AND E.1/124 AND E.1/221 AND E.1/220	Yes	
	Text attribute – small font size	Rel-5	5.5			C111 AND C158 AND C156	C111 AND C158 AND C156	E.1/71 AND E.1/124 AND E.1/222 AND E.1/220	Yes	
	Text attribute – bold on	Rel-5	5.6			C111 AND C160 AND C159	C111 AND C160 AND C159	E.1/71 AND E.1/124 AND E.1/225 AND E.1/226	Yes	
	Text attribute – italic on	Rel-5	5.7			C111 AND C161 AND C159	C111 AND C161 AND C159	E.1/71 AND E.1/124 AND E.1/225 AND E.1/227	Yes	
	Text attribute – underline on	Rel-5	5.8			C111 AND C162 AND C159	C111 AND C162 AND C159	E.1/71 AND E.1/124 AND E.1/225 AND E.1/228	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – strikethrough on	Rel-5	5.9			C111 AND C163 AND C159	C111 AND C163 AND C159	E.1/71 AND E.1/124 AND E.1/225 AND E.1/229	Yes	
	Text attribute – foreground and background colours	Rel-5	5.10			C111 AND C164 AND C165	C111 AND C164 AND C165	E.1/71 AND E.1/124 AND E.1/230 AND E.1/231	Yes	
	UCS2 display in Chinese	R99	6.1			C111 AND C143	C111 AND C143	E.1/71 AND E.1/15	Yes	
	UCS2 display in Katakana	R99	7.1			C111 AND C145	C111 AND C145	E.1/71 AND E.1/15	Yes	
	Frames	Rel-6	TBD				C136	E.1/71 AND E.1/177 AND E.1/178	TBD	
<b>31</b>	<b>OPEN CHANNEL</b>									
	void	R99	void	Void	void	void	void	void		
	immediate link establishment, GPRS, no local address, no alpha identifier, no network access name	R99	2.1	C121	C121	C121	C121	E.1/89 AND E.1/98	Yes	
	immediate link establishment GPRS, no alpha identifier, with network access name	R99	2.2	C121	C121	C121	C121	E.1/89 AND E.1/98	Yes	
	immediate link establishment, GPRS, with alpha identifier	R99	2.3	C121	C121	C121	C121	E.1/89 AND E.1/98	Yes	
	immediate link establishment, GPRS, with null alpha identifier	R99	2.4	C121	C121	C121	C121	E.1/89 AND E.1/98	Yes	
	immediate link establishment, GPRS, command performed with modifications (buffer size)	R99	2.5	C152	C152	C152	C152	E.1/89 AND E.1/98	Yes	
	immediate link establishment, GPRS, open command with alpha identifier, User did not accept the proactive command	R99	2.7	C121	C121	C121	C121	E.1/89 AND E.1/98	Yes	
	void	void	2.8	Void	void	void	void	void		
	Default bearer	R99	TBD	C121	C121	C121	C121	E.1/89 AND E.1/98 AND C132	TBD	
	Local Bearer	Rel-4	TBD	C132	C132	C132	C132	E.1/89 AND E.1/98 AND C132	TBD	
	Text attribute – center alignment	Rel-5	5.1			C121 AND C153	C121 AND C153	E.1/89 AND E.1/98 AND E.1/124 AND E.1/217	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – center alignment	Rel-5	5.2			C121 AND C154	C121 AND C154	E.1/89 AND E.1/98 AND E.1/124 AND E.1/218	Yes	
	Text attribute – right alignment	Rel-5	5.3			C121 AND C155	C121 AND C155	E.1/89 AND E.1/98 AND E.1/124 AND E.1/219	Yes	
	Text attribute – large font size	Rel-5	5.4			C121 AND C157 AND C156	C121 AND C157 AND C156	E.1/89 AND E.1/98 AND E.1/124 AND E.1/221 AND E.1/220	Yes	
	Text attribute – small font size	Rel-5	5.5			C121 AND C158 AND C156	C121 AND C158 AND C156	E.1/89 AND E.1/98 AND E.1/124 AND E.1/222 AND E.1/220	Yes	
	Text attribute – bold on	Rel-5	5.6			C121 AND C160 AND C159	C121 AND C160 AND C159	E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/226	Yes	
	Text attribute – italic on	Rel-5	5.7			C121 AND C161 AND C159	C121 AND C161 AND C159	E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/227	Yes	
	Text attribute – underline on	Rel-5	5.8			C121 AND C162 AND C159	C121 AND C162 AND C159	E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/228	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – strikethrough on	Rel-5	5.9			C121 AND C163 AND C159	C121 AND C163 AND C159	E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/229	Yes	
	Text attribute – foreground and background colours	Rel-5	5.10			C121 AND C164 AND C165	C121 AND C164 AND C165	E.1/89 AND E.1/98 AND E.1/124 AND E.1/230 AND E.1/231	Yes	
	Frames	Rel-6	TBD				C137	E.1/89 AND E.1/98 AND E.1/177 AND E.1/178	TBD	
<b>32</b>	<b>CLOSE CHANNEL</b>									
	successful	R99	1.1	C121	C121	C121	C121	E.1/89 AND E.1/90	Yes	
	with an invalid channel identifier	R99	1.2	C121	C121	C121	C121	E.1/89 AND E.1/90	Yes	
	on an already closed channel	R99	1.3	C121	C121	C121	C121	E.1/90	Yes	
	Text attribute – left alignment	Rel-5	2.1			C121 AND C153	C121 AND C153	E.1/89 AND E.1/90 AND E.1/124 AND E.1/217	Yes	
	Text attribute – center alignment	Rel-5	2.2			C121 AND C154	C121 AND C154	E.1/89 AND E.1/90 AND E.1/124 AND E.1/218	Yes	
	Text attribute – right alignment	Rel-5	2.3			C121 AND C155	C121 AND C155	E.1/89 AND E.1/90 AND E.1/124 AND E.1/219	Yes	
	Text attribute – large font size	Rel-5	2.4			C121 AND C157 AND C156	C121 AND C157 AND C156	E.1/89 AND E.1/90 AND E.1/124 AND E.1/221 AND E.1/220	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – small font size	Rel-5	2.5			C121 AND C158 AND C156	C121 AND C158 AND C156	E.1/89 AND E.1/90 AND E.1/124 AND E.1/222 AND E.1/220	Yes	
	Text attribute – bold on	Rel-5	2.6			C121 AND C160 AND C159	C121 AND C160 AND C159	E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/226	Yes	
	Text attribute – italic on	Rel-5	2.7			C121 AND C161 AND C159	C121 AND C161 AND C159	E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/227	Yes	
	Text attribute – underline on	Rel-5	2.8			C121 AND C162 AND C159	C121 AND C162 AND C159	E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/228	Yes	
	Text attribute – strikethrough on	Rel-5	2.9			C121 AND C163 AND C159	C121 AND C163 AND C159	E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/229	Yes	
	Text attribute – foreground and background colours	Rel-5	2.10			C121 AND C164 AND C165	C121 AND C164 AND C165	E.1/89 AND E.1/90 AND E.1/124 AND E.1/230 AND E.1/231	Yes	
	Frames	Rel-6	TBD				C137	E.1/89 AND E.1/98 AND E.1/177 AND E.1/178	TBD	
33	RECEIVE DATA									

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	already opened channel	R99	1.1	C121	C121	C121	C121	E.1/89 AND E.1/91 AND E.1/92	Yes	
	Text attribute – center alignment	Rel-5	2.1			C121 AND C153	C121 AND C153	E.1/89 AND E.1/91 AND E.1/92 AND E.1/124 AND E.1/217	Yes	
	Text attribute – center alignment	Rel-5	2.2			C121 AND C154	C121 AND C154	E.1/89 AND E.1/91 AND E.1/124 AND E.1/218	Yes	
	Text attribute – right alignment	Rel-5	2.3			C121 AND C155	C121 AND C155	E.1/89 AND E.1/91 AND E.1/124 AND E.1/219	Yes	
	Text attribute – large font size	Rel-5	2.4			C121 AND C157 AND C156	C121 AND C157 AND C156	E.1/89 AND E.1/91 AND E.1/124 AND E.1/221 AND E.1/220	Yes	
	Text attribute – small font size	Rel-5	2.5			C121 AND C158 AND C156	C121 AND C158 AND C156	E.1/89 AND E.1/91 AND E.1/124 AND E.1/222 AND E.1/220	Yes	
	Text attribute – bold on	Rel-5	2.6			C121 AND C160 AND C159	C121 AND C160 AND C159	E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/226	Yes	
	Text attribute – italic on	Rel-5	2.7			C121 AND C161 AND C159	C121 AND C161 AND C159	E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/227	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – underline on	Rel-5	2.8			C121 AND C162 AND C159	C121 AND C162 AND C159	E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/228	Yes	
	Text attribute – strikethrough on	Rel-5	2.9			C121 AND C163 AND C159	C121 AND C163 AND C159	E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/229	Yes	
	Text attribute– foreground and background colours	Rel-5	2.10			C121 AND C164 AND C165	C121 AND C164 AND C165	E.1/89 AND E.1/91 AND E.1/124 AND E.1/230 AND E.1/231	Yes	
	Frames	Rel-6	TBD				C137	E.1/89 AND E.1/91 AND E.1/177 AND E.1/178	TBD	
<b>34</b>	<b>SEND DATA</b>									
	immediate mode	R99	1.1	C121	C121	C121	C121	E.1/89 AND E.1/92	Yes	
	Store mode	R99	1.2	C121	C121	C121	C121	E.1/89 AND E.1/92	Yes	
	Store mode, Tx buffer fully used	R99	1.3	C121	C121	C121	C121	E.1/89 AND E.1/92	Yes	
	2 consecutive SEND DATA Store mode	R99	1.4	C121	C121	C121	C121	E.1/89 AND E.1/92	Yes	
	immediate mode with a bad channel identifier	R99	1.5	C121	C121	C121	C121	E.1/89 AND E.1/92	Yes	
	void								Yes	
	Text attribute– left alignment	Rel-5	2.1			C121 AND C153	C121 AND C153	E.1/89 AND E.1/92 AND E.1/124 AND E.1/217	Yes	
	Text attribute – center alignment	Rel-5	2.2			C121 AND C154	C121 AND C154	E.1/89 AND E.1/92 AND E.1/124 AND E.1/218	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute – right alignment	Rel-5	2.3			C121 AND C155	C121 AND C155	E.1/89 AND E.1/92 AND E.1/124 AND E.1/219	Yes	
	Text attribute – large font size	Rel-5	2.4			C121 AND C157 AND C156	C121 AND C157 AND C156	E.1/89 AND E.1/92 AND E.1/124 AND E.1/221 AND E.1/220	Yes	
	Text attribute – small font size	Rel-5	2.5			C121 AND C158 AND C156	C121 AND C158 AND C156	E.1/89 AND E.1/92 AND E.1/124 AND E.1/222 AND E.1/220	Yes	
	Text attribute – bold on	Rel-5	2.6			C121 AND C160 AND C159	C121 AND C160 AND C159	E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/226	Yes	
	Text attribute – italic on	Rel-5	2.7			C121 AND C161 AND C159	C121 AND C161 AND C159	E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/227	Yes	
	Text attribute – underline on	Rel-5	2.8			C121 AND C162 AND C159	C121 AND C162 AND C159	E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/228	Yes	
	Text attribute – strikethrough on	Rel-5	2.9			C121 AND C163 AND C159	C121 AND C163 AND C159	E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/229	Yes	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Text attribute– foreground and background colours	Rel-5	2.10			C121 AND C164 AND C165	C121 AND C164 AND C165	E.1/89 AND E.1/92 AND E.1/124 AND E.1/230 AND E.1/231	Yes	
	Frames	Rel-6	TBD				C137	E.1/89 AND E.1/92 AND E.1/177 AND E.1/178	TBD	
<b>35</b>	<b>GET CHANNEL STATUS</b>									
	without any BIP channel opened	R99	1.1	C121	C121	C121	C121	E.1/93	Yes	
	with a BIP channel currently opened	R99	1.2	C121	C121	C121	C121	E.1/89 AND E.1/93	Yes	
	after a link dropped	R99	1.3	C121	C121	C121	C121	E.1/89 AND E.1/93	Yes	
<b>36</b>	<b>DATA DOWNLOAD TO UICC</b>									
<b>37</b>	<b>SMS-PP DATA DOWNLOAD</b>									
	void		1.1							
	UICC responds with '61 XX'	R99	1.2	M	M	M	M	E.1/2	Yes	
	More time	R99	1.3	M	M	M	M	E.1/2	Yes	
	8 bit alphabet	R99	1.4	M	M	M	M	E.1/2	Yes	
	Data coding / message class	R99	1.6	M	M	M	M	E.1/2	Yes	
	RP-ERROR Handling	R99	1.7				M	E 1/2	Yes	
<b>38</b>	<b>SMS-CB DATA DOWNLOAD</b>				M	M	M			
	ME does not display message	R99	1.1	M	M	M	M	E.1/3	Yes	
	More time	R99	1.2	M	M	M	M	E.1/3 AND E.1/20	Yes	
	ME displays message	R99	1.3	M	M	M	M	E.1/3	Yes	
<b>39</b>	<b>CALL CONTROL BY USIM</b>				M	M	M			
	Procedure for MO calls (Cell identity in envelope call control)	R99	1.1 to 1.14	M	M	M	M	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/29 AND E.1/64	Yes	
	Procedure for SS (Cell identity in envelope call control)	R99	2.1, 2.2, 2.3, 2.4	M	M	M	M	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64	Yes	

Item	Description	Release	Test sequence(s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	Interaction with FDN (Cell identity in envelope call control)	R99	3.1, 3.2, 3.3, 3.4, 3.5	C146	C146	C146	C146	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64	Yes	
	BDN service enabled	R99	4.1	C147	C147	C147	C147	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64	Yes	
	BDN service enabled, interaction with emergency call codes, R99 only	R99	4.2A	C147				E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64	Yes	
	BDN service enabled, interaction with emergency call codes, Rel-4+	Rel-4	4.2B		C147	C147	C147	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 ND E.1/64	Yes	
	FDN and BDN enabled, set up a call in EFDN, Allowed with modifications	R99	4.3	C146 AND C147	C146 AND C147	C146 AND C147	C146 AND C147	E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64	Yes	
	Call control on GPRS	Rel-5	TBD			C102	C102	E.1/98 AND E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13	TBD	

Item	Description	Release	Test sequence (s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	BDN service enabled, ME not supporting BDN	R99	5.1				C147 C147	N/A	Yes	
40	<b>EVENT DOWNLOAD</b>									
	27.22.7.1: MT call event	R99	1.1	M	M	M	M	E.1/34 AND E.1/33	Yes	
	27.22.7.2.1: call connected event	R99	1.1	M	M	M	M	E.1/35 AND E.1/33	Yes	
	27.22.7.2.2: ME supporting SET UP CALL	R99	2.1	M	M	M	M	E.1/35 AND E.1/29 AND E.1/33	Yes	
	27.22.7.3: call disconnected event	R99	1.1	M	M	M	M	E.1/36 AND E.1/33	Yes	
	27.22.7.4: location status event	R99	1.1	M	M	M	M	E.1/37 AND E.1/33	Yes	
	27.22.7.5: user activity event	R99	1.1	M	M	M	M	E.1/38 AND E.1/33	No	
	27.22.7.6: idle screen available event	R99	1.1	M	M	M	M	E.1/39 AND E.1/33	Yes	
	27.22.7.7.1: Card reader status normal	R99	1.1	C109	C109	C109	C109	E.1/40 AND E.1/33	No	
	27.22.7.7.2: Detachable card reader	R99	2.1	C116	C116	C116	C116	E.1/40 AND E.1/33	No	
	27.22.7.8: language selection event	R99	1.1	M	M	M	M	E.1/41 AND E.1/33	No	
	27.22.7.9: Browser termination event	R99	1.1	C111	C111	C111	C111	E.1/42 AND E.1/33	Yes	
	27.22.7.10: Data available event	R99	1.1	C121	C121	C121	C121	E.1/43 AND E.1/89 AND E.1/92 AND E.1/33	Yes	
	27.22.7.11: Channel status event	R99	1.1	C121	C121	C121	C121	E.1/44 AND E.1/89 AND E.1/33	Yes	
	27.22.7.12: Access Technology change event	Rel-4	TBD			M	M	M	E.1/45 AND E.1/33	TBD
27.22.7.13: Display parameter changed event	Rel-4	TBD			M	M	M	E.1/46 AND E.1/33	TBD	
27.22.7.14: Local connection event	Rel-4	TBD			M	M	M	E.1/47 AND E.1/33	TBD	
27.22.7.15: Network search mode change event	Rel-6	TBD					M	E.1/48 AND E.1/33	TBD	

Item	Description	Release	Test sequence(s)	Rel 99 ME	Rel-4 ME	Rel-5 ME	Rel-6 ME	Terminal Profile	Network Dependency	Support
	27.22.7.16: Browsing status event	Rel-6	TBD				M	E.1/193 AND E.1/33	TBD	
	Frame information changed event	Rel-6	TBD				C137	E.1/195 AND E.1/177 AND E.1/178	TBD	
<b>41</b>	<b>MO SMS Control by USIM</b>									
	With proactive command, Allowed , no modification	R99	1.1	M	M	M	M	E1/12 AND E.1/26	Yes	
	With user SMS, Allowed , no modification	R99	1.2	M	M	M	M	E1/12	Yes	
	With proactive command, Not allowed	R99	1.3	M	M	M	M	E1/12 AND E.1/26	Yes	
	With user SMS, Not allowed	R99	1.4	M	M	M	M	E1/12	Yes	
	With proactive command, Allowed, with modifications	R99	1.5	M	M	M	M	E1/12 AND E.1/26	Yes	
	With user SMS, Allowed, with modifications	R99	1.6	M	M	M	M	E1/12	Yes	
	With Proactive command, the USIM responds with '90 00', Allowed, no modification	R99	1.7	M	M	M	M	E1/12 AND E.1/26	Yes	
	Send Short Message attempt by user, the USIM responds with '90 00', Allowed, no modification	R99	1.8	M	M	M	M	E1/12	Yes	
	Void		1.9							
<b>42</b>	<b>SERVICE SEARCH</b>	Rel-4	TBD		M	M	M	E.1/94	TBD	
<b>43</b>	<b>GET SERVICE INFORMATION</b>	Rel-4	TBD		M	M	M	E.1/95	TBD	
<b>44</b>	<b>DECLARE SERVICE</b>	Rel-4	TBD		M	M	M	E.1/96	TBD	
<b>45</b>	<b>RETRIEVE MULTIMEDIA MESSAGE</b>	Rel-6	TBD				C134	E.1/173	TBD	
<b>46</b>	<b>SUBMIT MULTIMEDIA MESSAGE</b>	Rel-6	TBD				C134	E.1/173	TBD	
<b>47</b>	<b>DISPLAY MULTIMEDIA MESSAGE</b>	Rel-6	TBD				C134	E.1/173	TBD	
<b>48</b>	<b>SET FRAMES</b>	Rel-6	TBD				C133	E.1/177 AND E.1/178	TBD	
<b>49</b>	<b>GET FRAME STATUS</b>	Rel-6	TBD				C133	E.1/178 AND E.1/177	TBD	
<b>50</b>	<b>Handling of command number</b>									
	DISPLAY TEXT normal priority	R99	1.1	M	M	M	M	E.1/17	No	

C101	IF A.1/1 THEN M ELSE N/A	-- O_Cap_Conf
C102	IF A.1/16 THEN M ELSE N/Avoid	-- O_GPRS
C103	void	
C104	IF A.1/2 THEN M ELSE N/A	-- O_Sust_text
C105	IF A.1/3 AND A.1/41 THEN M ELSE N/A	-- O_Ucs2_Entry AND O_UCS2_Cyrillic
C106	IF A.1/4 THEN M ELSE N/A	-- O_Ext_Str
C107	IF A.1/5 THEN M ELSE N/A	-- O_Help
C108	IF A.1/6 THEN (O.1 OR O.2) ELSE N/A	-- O_Icons
C109	IF A.1/7 THEN M ELSE N/A	-- O_Dual_Slot
C110	IF A.1/9 AND A.1/46 THEN M ELSE N/A	-- O_Run_At AND O_+CIMI
C111	IF A.1/10 THEN M ELSE N/A	-- O_LB
C112	IF A.1/11 THEN M ELSE N/A	-- O_Soft_key
C113	void	
C114	IF C110 AND C108 THEN M ELSE N/A	-- O_Run_At AND O_+CIMI AND O_Icons
C115	IF C111 AND C108 THEN M ELSE N/A	-- O_LB AND O_Icons
C116	IF A.1/7 AND A.1/8 THEN M ELSE N/A	-- O_Dual_Slot AND O_Detach_Rdr
C117	void	
C118	IF A.1/15 AND A.1/41 THEN M ELSE N/A	-- O_Ucs2_Disp AND O_UCS2_Cyrillic
C119	IF A.1/19 THEN M ELSE N/A	-- O_Redial
C120	IF A.1/20 THEN M ELSE N/A	-- O_D_NoResp
C121	IF A.1/21 AND A.1/17 THEN M ELSE N/A	-- O_BIP_GPRS AND O_UDP
C122	IF C111 AND A.1/16 THEN M ELSE N/A	-- O_LB AND O_GPRS
C123	void	
C124	IF A.1/22, test x.A M ELSE x.B M (where x is the expected sequence number value)	-- O_CP_Subaddr
C125	IF A.1/23 THEN M ELSE N/A	-- O_Imm_Resp
C126	IF A.1/24 THEN M ELSE N/A	-- O_Duration
C127	void	
C128	void	
C129	void	
C130	void	
C131	void	
C132	IF A.1/27 THEN M ELSE N/A	-- O_BIP_Local
C133	IF A.1/37 THEN M ELSE N/A	-- O_Frames
C134	IF A.1/38 THEN M ELSE N/A	-- O_MMS
C135	IF C110 AND C133 THEN M ELSE N/A	-- O_Run_At AND O_Frames
C136	IF C111 AND C133 THEN M ELSE N/A	-- O_LB AND O_Frames
C137	IF A.1/12 AND C133 THEN M ELSE N/A	-- O_BIP AND O_Frames
C138	IF A.1/39 THEN M ELSE N/A	-- O_Tones
C139	IF A.1/35 THEN M ELSE N/A	-- O_Batt
C140	IF A.1/39 THEN M ELSE N/A	-- O_UC_Before_EnvCC
C141	IF A.1/40 THEN M ELSE N/A	-- O_UC_After_EnvCC
C142	IF A.1/3 AND A.1/42 THEN M ELSE N/A	-- O_UCS2_Entry AND O_UCS2_Chinese
C143	IF A.1/15 AND A.1/42 THEN M ELSE N/A	-- O_UCS2_Disp AND O_UCS2_Chinese
C144	IF A.1/3 AND A.1/43 THEN M ELSE N/A	-- O_UCS2_Entry AND O_UCS2_Katakana
C145	IF A.1/15 AND A.1/43 THEN M ELSE N/A	-- O_UCS2_Disp AND O_UCS2_Katakana
C146	IF A.1/45 THEN M ELSE N/A	-- O_FDN
C147	IF A.1/44 THEN M ELSE N/A	-- O_BDN
C148	IF (A.1/9 AND A.1/47) THEN M ELSE N/A	-- O_Run_At AND O_+CGMI
C149	IF C148 AND C118 THEN M ELSE N/A	-- O_Run_At AND O_+CGMI AND O_O_Ucs2_Disp AND O_Ucs2_Cyrillic
C150	IF C148 AND C143 THEN M ELSE N/A	-- O_Run_At AND O_+CGMI AND O_O_Ucs2_Disp AND O_Ucs2_Chinese
C151	IF C148 AND C145 THEN M ELSE N/A	-- O_Run_At AND O_+CGMI AND O_O_Ucs2_Disp AND O_Ucs2_Katakana
C152	IF C121 AND A.1/49 THEN M ELSE N/A	-- O_BIP_GPRS AND O_UDP AND O_BUFFER_SIZE
C153	IF A.1/50 THEN M ELSE N/A	-- O_TAT_AL
C154	IF A.1/51 THEN M ELSE N/A	-- O_TAT_AC
C155	IF A.1/52 THEN M ELSE N/A	-- O_TAT_AR
C156	IF A.1/53 THEN M ELSE N/A	-- O_TAT_FSN
C157	IF A.1/54 THEN M ELSE N/A	-- O_TAT_FSL
C158	IF A.1/55 THEN M ELSE N/A	-- O_TAT_FSS
C159	IF A.1/56 THEN M ELSE N/A	-- O_TAT_SN
C160	IF A.1/57 THEN M ELSE N/A	-- O_TAT_SB
C161	IF A.1/58 THEN M ELSE N/A	-- O_TAT_SI
C162	IF A.1/59 THEN M ELSE N/A	-- O_TAT_SU
C163	IF A.1/60 THEN M ELSE N/A	-- O_TAT_SS
C164	IF A.1/61 THEN M ELSE N/A	-- O_TAT_STFC
C165	IF A.1/62 THEN M ELSE N/A	-- O_TAT_STBC
C166	IF A.1/63 THEN test step option n.A M ELSE test step option n.B M	-- O_longFTN
C167	IF A.1/64 THEN M ELSE N/A	-- O_GERAN
C168	IF A.1/65 THEN M ELSE N/A	-- O_Global_PB

O.1 IF (the ME supports icons as defined in record 4.6.1 EF(IMG), tests x.1A M ELSE tests x.1B M (where x is

## 3.5 Conventions for mathematical notations

The conventions for mathematical notations specified below shall apply.

### 3.5.1 Mathematical signs

The "plus or minus" sign is expressed by " $\pm$ ".

The sign "multiplied by" is expressed by "\*".

The sign "divided by" is expressed by "/", or the common division bar.

The sign "greater than or equal to" is expressed by " $\geq$ ".

The sign "less than or equal to" is expressed by " $\leq$ ".

---

## 4 Test equipment

The test equipment is specified in 3GPP TS 34.108 [12] clause 4.

---

## 5 Testing methodology in general

When possible the present document refers to ETSI TS 102 384 [26] to describe generic aspects of application toolkit tests.

### 5.1 Testing of optional functions and procedures

Any function or procedure which is optional, as indicated in the present document, may be subject to a conformance test if it is implemented in the ME.

### 5.2 Test interfaces and facilities

The UICC, and (U)SS interfaces provides the main test interfaces for the purpose of performing conformance tests.

The tests which require a network simulator shall be carried out with using a Universal System Simulator when accessing a UTRAN, and if these tests have to be performed additionally when accessing a GERAN a System Simulator shall be used instead.

### 5.3 Information to be provided by the apparatus supplier

The information to be provided by the apparatus supplier specified in both 3GPP TS 34.108 [12] and 3GPP TS 51.010-1 [23] shall apply, unless otherwise specified in the present clause.

In addition, the apparatus supplier shall provide the information with respect to the Supported Option table A.1 and to ME's default configuration table A.2.

Table A.2: ME"s default configuration

Item	Description	Value	Status
1	DISPLAY TEXT: No Response from user timeout interval		C
2	GET INKEY: No response from user Timeout interval		C
3	GET INPUT: No response from user Timeout interval		C
4	SELECT ITEM: No response from user Timeout interval		C
5	DISPLAY TEXT Text Attributes Alignment [Left or Center or Right]		C
6	GET INKEY Text Attributes Alignment [Left or Center or Right]		C
7	GET IMPUT Text Attributes Alignment [Left or Center or Right]		C
8	PLAY TONE Text Attributes Alignment [Left or Center or Right]		C
9	SET UP MENU Text Attributes Alignment [Left or Center or Right]		C
10	SELECT ITEM Text Attributes Alignment [Left or Center or Right]		C
11	SEND SHORT MESSAGE Text Attributes Alignment [Left or Center or Right]		C
12	SEND SS Text Attributes Alignment [Left or Center or Right]		C
13	SEND USSD Text Attributes Alignment [Left or Center or Right]		C
14	SET UP CALL Text Attributes Alignment [Left or Center or Right]		C
15	SET UP IDLE MODE TEXT Text Attributes Alignment [Left or Center or Right]		C
16	RUN AT Text Attributes Alignment [Left or Center or Right]		C
17	SEND DTMF Text Attributes Alignment [Left or Center or Right]		C
18	LAUNCH BROWSER Text Attributes Alignment [Left or Center or Right]		C
19	OPEN CHANNEL Text Attributes Alignment [Left or Center or Right]		C
20	CLOSE CHANNEL Text Attributes Alignment [Left or Center or Right]		C
21	RECEIVE DATA Text Attributes Alignment [Left or Center or Right]		C
22	SEND DATA Text Attributes Alignment [Left or Center or Right]		C
23	IMEI		M
24	IMEISV		C
25	[Reserved]		
26	Additional Card Reader Id		C
27	Channel Id		C
28	Manufacturer identification as implemented according to TS 27.007, cl. 5.1		C
29	Preferred buffer size supported by the terminal for Open Channel command		C
NOTE : Conditional values shall be provided if the corresponding option is supported in the table A.1			

---

## 6 Implicit testing

For some 3GPP features conformance is not verified explicitly in the present document. This does not imply that correct functioning of these features is not essential, but that these are implicitly tested to a sufficient degree in other tests.

It should be noted that for these features some aspects have to be and are explicitly tested, e.g. the ability to switch between 1.8v and 3v operation.

Some UICC features will be explicitly tested as result of other tests. These should be identified for the following reason:

- To identify the areas of overlap and thus provide a more efficient testing.

---

## 7 Measurement uncertainty

The measured value relating to the corresponding limit shall be used to determine whether or not a terminal equipment meets the requirement. (ETR 028, annex B).

This process is often referred to as "shared risk".

---

## 8 Format of tests

In general the following basic format for tests is used:

**27.22.X.X. Tested command**

**27.22.X.X.1 Command tested in «environment #1" (NORMAL, ICONS, UCS2 ...)**

**27.22.X.X.1.1 Definition and applicability**

This clause refers back to clause 3.2.2.

**27.22.X.X.1.2 Conformance requirement**

Only if required, this clause details the necessary core specification references.

**27.22.X.X.1.3 Test purpose**

This clause details the purpose of the test.

**27.22.X.X.1.4 Method of test**

**27.22.X.X.1.4.1 Initial conditions**

If present this clause defines the initial conditions to be established before running each test sequence.

**27.22.X.X.1.4.2 Procedure**

This clause details the test procedure. Each test sequence shall be carried out independently unless otherwise stated.

- Sequence 1.1 (further initial conditions, added here)

Command 1.1.1
TERMINAL RESPONSE1.1.1A or 1.1.1B
Command 1.1.2
TERMINAL RESPONSE1.1.2

PROACTIVE COMMAND 1.1.1

TERMINAL RESPONSE 1.1.1A

TERMINAL RESPONSE 1.1.1B

PROACTIVE COMMAND 1.1.2

TERMINAL RESPONSE 1.1.2

- Sequence 1.2

Command 1.2.1
TERMINAL RESPONSE 1.2.1
Command 1.2.2
TERMINAL RESPONSE1.2.2 (same as TERMINAL RESPONSE 1.2.1)
Command 1.2.3
TERMINAL RESPONSE 1.2.3

PROACTIVE COMMAND 1.2.1

PROACTIVE COMMAND 1.2.2

PROACTIVE COMMAND 1.2.3

TERMINAL RESPONSE 1.2.1

TERMINAL RESPONSE 1.2.2

TERMINAL RESPONSE 1.2.3

- Sequence 1.3

Command 1.3.1
TERMINAL RESPONSE1.3.1

PROACTIVE COMMAND 1.3.1

TERMINAL RESPONSE 1.3.1

**27.22.X.X.1.5 Test requirement**

This clause details the conditions to be met for successful completion of the test.

**27.22.X.X.2 Command tested in "environment #2" (NORMAL, ICONS, UCS2 ...)**

**27.22.X.X. 2.1 Definition and applicability**

**27.22.X.X. 2.2 Conformance requirement**

**27.22.X.X. 2.3 Test purpose**

**27.22.X.X. 2.4 Method of test**

**27.22.X.X. 2.4.1.1 Initial conditions**

**27.22.X.X. 2.4.1.2 Procedure**

- Sequence 2.1

Command 2.1.1
TERMINAL RESPONSE2.1.1A or 2.1.1B
Command 2.1.2
TERMINAL RESPONSE2.1.2

PROACTIVE COMMAND 2.1.1

TERMINAL RESPONSE 2.1.1A

TERMINAL RESPONSE 2.1.1B

PROACTIVE COMMAND 2.1.2

TERMINAL RESPONSE 2.1.2

- Sequence 2.2

Command 2.2.1
TERMINAL RESPONSE 2.2.1
Command 2.2.2
TERMINAL RESPONSE 2.2.2 (same as TERMINAL RESPONSE 2.2.1)
Command 2.2.3
TERMINAL RESPONSE 2.2.3

PROACTIVE COMMAND 2.2.1

PROACTIVE COMMAND 2.2.2

PROACTIVE COMMAND 2.2.3

Coding TERMINAL RESPONSE 2.2.1

Coding TERMINAL RESPONSE 2.2.2

Coding TERMINAL RESPONSE 2.2.3

**27.22.X.X.2.5 Test requirement**

---

## 9 Generic call set up procedures

The generic call set up procedure for PS and CS calls specified for GERAN and UTRAN shall apply.

For a ME accessing UTRAN the call set up procedures specified in 3GPP TS 34.108 [12] subclause 7.2.3.1.3 and 7.2.3.2.3 shall apply, for session setup the ones defined in 7.2.4.1.3 and 7.2.4.2.3, unless otherwise specified in the present clause.

For a ME accessing GERAN the call set up procedures specified in 3GPP TS 51.010-1 [23] subclause 26.9 shall apply, for session setup the ones defined in 45.2 and 45.4, unless otherwise specified in the present clause.

---

## 10 - 26 Not used

## 27 Testing of the UICC/ME interface

This clause is an addition to 3GPP TS 31.121 [21] to confirm the correct interpretation of the USIM Application Toolkit commands and the correct operation of the Toolkit facilities.

The definitions, declarations and default values specified in 3GPP TS 31.121 [21] clause 4.1 shall apply, unless otherwise specified in the present clause.

A USIM Simulator with the appropriate USIM Application Toolkit functionality will be required. The USIM data defined below shall be used for all test cases unless otherwise specified within the test case.

The comprehension required flags in SIMPLE-TLV objects that are included in a TERMINAL RESPONSE or an ENVELOPE shall be set as described in TS 31.111 [15]. This means that in cases where it is up to the ME to decide if this flag is used or not, the corresponding Tag coding in the TERMINAL RESPONSEs and ENVELOPEs in this document represents only one of the two valid possibilities.

### 27.1 - 27.21 Void

### 27.22 USIM Application Toolkit

#### 27.22.1A General Test purpose

Testing of functional conformance to USIM Application Toolkit commands, including proactive UICC commands.

All facilities given by the TERMINAL PROFILE as supported, for which tests exist in the present document, shall be tested.

Many of the proactive UICC commands include an alpha identifier data object. This is intended to be a short one or two word identifier for the ME to optionally display on the screen along with any other indications, at the same time as the ME performs the UICC command.

**NOTE:** The sequence of USIM Application Toolkit commands are specific to the Toolkit Application being executed within the UICC, hence sequential testing of commands is not possible. The testing will therefore have to be performed on a command by command basis.

#### 27.22.2A Definition of default values for USIM Application Toolkit testing

A UICC containing the following default values is used for all tests of this clause unless otherwise stated.

For each item, the logical default values and the coding within the Elementary Files (EF) of the USIM follow, as defined in:

- 3GPP TS 31.121 [21], clause 4.1.

- ETSI TS 102 384 [26], clause 27.22.1B.

NOTE 1: Bx represents byte x of the coding.

NOTE 2: Unless otherwise defined, the coding values in binary.

### EF<sub>UST</sub> (USIM Service Table)

Logically:

(Service 01)	Local Phone Book available
(Service 02)	Fixed dialling numbers available
(Service 06)	Barred dialling numbers available
(Service 10)	Short Message Storage available
(Service 11)	Short Message Status Reports available
(Service 12)	Short Message Service Parameters available
(Service 15)	Cell Broadcast Message Identifier available
(Services 17, 18)	The Group Identifier level 1 and level 2 not available
(Service 20)	User controlled PLMN selector available
(Service 22)	Image (IMG) available
(Service 27)	The GSM Access available
(Service 28)	Data download via SMS-PP available
(Service 29)	Data download via SMS-CB available
(Service 30)	Call Control by USIM not available
(Service 31)	MO-SMS Control by USIM not available
(Service 32)	RUN AT COMMAND available
(Service 33)	(Packed Switched Domain) shall be set to '1'
(Service 34)	Enabled Services Table available

Coding:	B1	B2	B3	B4	B5
binary	xx1x xx11	x1xx 111x	xx1x 1x00	1001 11xx	xxx xx11

The coding of EF<sub>UST</sub> shall conform with the capabilities of the USIM used.

### EF<sub>EST</sub> (Enabled Services Table)

Logically:

(Service 1)	Fixed Dialling number deactivated
(Service 2)	Barred Dialling number deactivated
(Service 3)	APN Control List deactivated

Coding:	B1
binary	00

### EF<sub>IMSI</sub> (International Mobile Subscriber Identity)

Logically:

Length:	8 bytes
IMSI:	001 01 0123456789

Coding:	'08 09 10 10 10 32 54 76 98'
---------	------------------------------

### EF<sub>AD</sub> (Administrative Data)

Logically: Type approval operations  
OFM to be deactivated by the Terminal  
MNC: 2 digit

Coding:	B1	B2	B3	B4
Hex	80	00	00	02

**EF<sub>LOCI</sub> (Location Information)**

Logically:

LAI-MCC: 001  
 LAI-MNC: 01  
 LAI-LAC: 0001  
 TMSI: "FF .. FF"

Coding:	B1	B2	B3	B4	B5	B6	B7	B8	B9	B10	B11
Hex	FF	FF	FF	FF	00	F1	10	00	01	FF	00

**EF<sub>PSLOCI</sub> (Packet Switch Location Information)**

Logically:

RAI-MCC: 001  
 RAI-MNC: 01  
 RAI-LAC: 0001  
 RAI-RAC: 05  
 P-TMSI: "FF....FF"  
 P-TMSI signature value: "FF...FF"

Coding:	B1	B2	B3	B4	B5	B6	B7
Hex	FF						

Coding:	B8	B9	B10	B11	B12	B13	B14
Hex	00	F1	10	00	01	05	00

**EF<sub>CBMI</sub> (Cell Broadcast Message Identifier)**

Logically:

Cell Broadcast Message Identifier 1: '03 E7'

Coding:	03	E7	FF	..	FF						
---------	----	----	----	----	----	--	--	--	--	--	--

**EF<sub>CBMID</sub> (Cell Broadcast Message Identifier for Data Download)**

Logically:

Cell Broadcast Message Identifier 1: '10 01'

Coding:	10	01	FF	..	FF						
---------	----	----	----	----	----	--	--	--	--	--	--

**EF<sub>FDN</sub> (Fixed Dialling Numbers)**

Logically:

Record 1: Length of alpha identifier: 6 characters;  
 Alpha identifier: "FDN111";  
 Length of BCD number: "03";  
 TON and NPI: Telephony and unknown;  
 Dialed number: 123;  
 CCI: None;  
 Ext2: None.

Coding for record 1:

Hex	B1 46	B2 44	B3 4E	B4 31	B5 31	B6 31	B7 03	B8 81	B9 21	B10 F3	B11 FF	B12 FF	B13 FF
	B14 FF	B15 FF	B16 FF	B17 FF	B18 FF	B19 FF	B20 FF						

Record 2: Length of alpha identifier: 6 characters;  
 Alpha identifier: "FDN222";  
 Length of BCD number: "03";  
 TON and NPI: Telephony and Unknown;  
 Dialed number: 9876;  
 CCI: None;  
 Ext2: None.

Coding for record 2:

Hex	B1 46	B2 44	B3 4E	B4 32	B5 32	B6 32	B7 03	B8 81	B9 89	B10 67	B11 FF	B12 FF	B13 FF
	B14 FF	B15 FF	B16 FF	B17 FF	B18 FF	B19 FF	B20 FF						

Record 3: Length of alpha identifier: 6 characters;  
 Alpha identifier: "FDN333";  
 Length of BCD number: "0B";  
 TON and NPI: Telephony and International;  
 Dialed number: +12345678901234567890;  
 CCI: None;  
 Ext2: None.

Coding for record 3:

Hex	B1 46	B2 44	B3 4E	B4 33	B5 33	B6 33	B7 0B	B8 91	B9 21	B10 43	B11 65	B12 87	B13 09
	B14 21	B15 43	B16 65	B17 87	B18 09	B19 FF	B20 FF						

### EF<sub>BDN</sub> (Barred Dialling Numbers)

Logically:

Record 1: Length of alpha identifier: 6 characters;  
 Alpha identifier: "BDN111";  
 Length of BCD number: "06";  
 TON and NPI: Telephony and International;  
 Dialed number: +1357924680;  
 CCI: None;  
 Ext4: None  
 Comprehension method pointer: None.

Coding for record 1:

Hex	B1 42	B2 44	B3 4E	B4 31	B5 31	B6 31	B7 06	B8 91	B9 31	B10 75	B11 29	B12 64	B13 08
	B14 FF	B15 FF	B16 FF	B17 FF	B18 FF	B19 FF	B20 FF	B21 FF					

Record 2: Length of alpha identifier: 6 characters;  
 Alpha identifier: "BDN222";

Length of BCD number: "03";  
 TON and NPI: Telephony and Unknown;  
 Dialed number: 122;  
 CCI: None;  
 Ext4: None  
 Comprehension method pointer: None.

Coding for record 2:

Hex	B1	B2	B3	B4	B5	B6	B7	B8	B9	B10	B11	B12	B13
	42	44	4E	32	32	32	04	81	21	F2	FF	FF	FF
	B14	B15	B16	B17	B18	B19	B20	B21					
	FF												

Record 3: Length of alpha identifier: 6 characters;  
 Alpha identifier: "BDN333";  
 Length of BCD number: "03";  
 TON and NPI: Telephony and Unknown;  
 Dialed number: 112;  
 CCI: None;  
 Ext4: None.  
 Comprehension method pointer: None

Coding for record 3:

Hex	B1	B2	B3	B4	B5	B6	B7	B8	B9	B10	B11	B12	B13
	42	44	4E	33	33	33	03	81	11	F2	FF	FF	FF
	B14	B15	B16	B17	B18	B19	B20	B21					
	FF												

#### EF<sub>ECC</sub> (Emergency Call Codes)

Logically: Emergency call code: "122";  
 Emergency call code alpha identifier: "TEST";  
 Emergency call Service Category: RFU

Coding:	B1	B2	B3	B4	B5	B6	B7	B8
Hex	21	F2	FF	54	45	53	54	00

#### EF<sub>SMSS</sub> (SMS Status)

Logically: Last used TP-MR set to "00".  
 Memory capacity available (flag unset b1="1").

Coding:	B1	B2
Hex	00	FF

#### EF<sub>SMSP</sub> (Short message service parameters)

Logically:

Record 1:  
 Record length: 28 bytes  
 Parameter Indicators:  
 TP-Destination Address: Parameter absent  
 TS-Service Centre Address: Parameter present  
 TP-Protocol Identifier: Parameter absent  
 TP-Data Coding Scheme: Parameter absent

TP-Validity Period: Parameter absent  
 TS-Service Centre Address:  
 TON: International Number  
 NPI: "ISDN / telephone numbering plan"  
 Dialed number string: "112233445566778"

Coding:	B1	B2	B3	...	B13	B14	B15	B16	B17	B18	B19	B20	B21	B22	B23
Record 1:	FD	FF	FF	...	FF	09	91	11	22	33	44	55	66	77	F8

B24	B25	B26	B27	B28
FF	FF	FF	FF	FF

For the display of icon: See ETSI TS 102 384 [26] subclause 27.22.1B.

## 27.22.1 Initialization of USIM Application Toolkit Enabled UICC by USIM Application Toolkit Enabled ME (Profile Download)

### 27.22.1.1 Definition and applicability

See clause 3.2.2.

### 27.22.1.2 Conformance requirement

The ME shall support the PROFILE DOWNLOAD command as defined in:

- 3GPP TS 31.111 [15] clause 5.2.

### 27.22.1.3 Test purpose

To verify that the ME sends a TERMINAL PROFILE command in accordance with the above requirements.

### 27.22.1.4 Method of test

#### 27.22.1.4.1 Initial conditions

The ME is connected to the USIM Simulator. All elementary files are coded as the default Toolkit personalization..

#### 27.22.1.4.2 Procedure

#### Expected Sequence 1 (PROFILE DOWNLOAD)

Step	Direction	Message / Action	Comments
1	USER → ME	Power on ME	[UICC Activation]
2	ME → UICC	Select EF PL	
3	UICC → ME	Read EF PL	
4	ME → UICC	TERMINAL PROFILE 1.1	PROFILE DOWNLOAD
5	UICC → ME	NORMAL ENDING OF COMMAND 1.1	
6	ME → UICC	Select USIM Application	

### TERMINAL PROFILE: 1.1

Logically:

Coding:

APDU:	CLA=80	INS=10	P1=00	P2=00	P3=XX
-------	--------	--------	-------	-------	-------

DATA IN:	YY	ZZ	...
----------	----	----	-----

With XX representing the length of the following DATA IN depending on the USIM Toolkit commands supported by the ME, and with YY, ZZ, ... representing here the bytes of the TERMINAL PROFILE data, as specified in 3GPP TS 31.111 [15], clause 5.2.

#### **NORMAL ENDING OF COMMAND: 1.1**

Logically:

Coding:

SW1=90	SW2=00
--------	--------

### 27.22.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.

## 27.22.2 Contents of the TERMINAL PROFILE command

### 27.22.2.1 Definition and applicability

See table E.1 in annex B.

### 27.22.2.2 Conformance requirement

The ME shall support the PROFILE DOWNLOAD command as defined in:

- 3GPP TS 31.111 [15] clause 5.2.

### 27.22.2.3 Test purpose

1. Verify that the TERMINAL PROFILE indicates that Profile Download facility is supported.
2. Record which USIM Application Toolkit facilities are supported by the ME, to determine which subsequent tests are required.

### 27.22.2.4 Method of test

#### 27.22.2.4.1 Initial conditions

The ME is connected to the USIM Simulator. All elementary files are coded as the default USIM Application Toolkit personalization.

#### 27.22.1.4.2 Procedure

- a) The ME is powered on.
- b) After the ME sends the TERMINAL PROFILE command to the USIM Simulator, the USIM Simulator shall record the content of the TERMINAL PROFILE.
- c) The USIM Simulator shall return SW1 / SW2 of '90 00'.
- d) The contents of the TERMINAL PROFILE is recorded and compared to the corresponding table E.1 "status" column.

The test is terminated upon the ME sending the TERMINAL PROFILE command to the USIM Simulator.

### 27.22.2.5 Test requirement

- 1) After step a) the ME shall send the TERMINAL PROFILE command to the USIM Simulator with bit 1 of the first byte set to 1 (facility supported by ME).
- 2) In table E.1 for the corresponding ME USIM Toolkit Release and Options, The TERMINAL PROFILE information "support" recorded must be in accordance with the "Status" column. Support of features defined only in releases later than currently tested release shall be ignored.

## 27.22.3 Servicing of proactive UICC commands

### 27.22.3.1 Definition and applicability

See clause 3.2.2.

### 27.22.3.2 Conformance requirement

On detection of a pending USIM Application Toolkit command from the UICC the ME shall perform the FETCH command to retrieve the proactive UICC command. The result of the executed command shall be transmitted from the ME to the UICC within a TERMINAL RESPONSE command.

The MORE TIME proactive command is used in this test. The ME shall have knowledge of this command, but may not support this USIM Application Toolkit facility.

- 3GPP TS 31.111 [15] clause 6.3.

### 27.22.3.3 Test purpose

To verify that the ME uses the FETCH command to obtain the proactive UICC command, after detection of a pending proactive UICC command. The pending proactive UICC command is indicated by the response parameters '91 xx' from the UICC.

To verify that the ME transmits the result of execution of the proactive UICC command to the UICC in the TERMINAL RESPONSE command.

### 27.22.3.4 Method of test

#### 27.22.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as the USIM Application Toolkit default.

The USIM Simulator is configured to indicate that a proactive UICC command is pending.

The USIM Simulator is configured to monitor the UICC - ME interface.

#### 27.22.3.4.2 Procedure

- a) The ME is powered on.
- b) After the ME has performed the PROFILE DOWNLOAD procedure, the USIM Simulator indicates that a Proactive UICC Command is pending with SW1 / SW2 of '91 0B'.
- c) After the ME sends the FETCH command to the USIM Simulator, the USIM Simulator returns Proactive UICC Command 2.1: MORE TIME.

### 27.22.3.5 Test requirement

- 1) After step b) the ME shall send the FETCH command to the UICC.

- 2) After step c) the ME shall send the TERMINAL REPONSE command with command number "01", type of command "02" and command qualifier "00".

## 27.22.4 Proactive UICC commands

### 27.22.4.1 DISPLAY TEXT

#### 27.22.4.1.1 DISPLAY TEXT (Normal)

##### 27.22.4.1.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.1.1.2 Conformance requirements

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

3GPP TS 31.111 [15], clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

##### 27.22.4.1.1.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.1.1.4 Method of test

###### 27.22.4.1.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.1.1.4.2 Procedure

#### **Expected Sequence 1.1 (DISPLAY TEXT normal priority, Unpacked 8 bit data for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.1.

#### **Expected Sequence 1.2 (DISPLAY TEXT normal priority, Unpacked 8 bit data for Text String, screen busy)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.2.

#### **Expected Sequence 1.3 (DISPLAY TEXT, high priority, Unpacked 8 bit data for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.3.

#### **Expected Sequence 1.4 (DISPLAY TEXT, Packed, SMS default alphabet, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.4.

#### **Expected Sequence 1.5 (DISPLAY TEXT, Clear message after delay, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.5.

**Expected Sequence 1.6 (DISPLAY TEXT, Text string with 160 bytes, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.6.

**Expected Sequence 1.7 (DISPLAY TEXT, Backward move in UICC session, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.7.

**Expected Sequence 1.8 (DISPLAY TEXT, session terminated by user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.8.

**Expected Sequence 1.9 (DISPLAY TEXT, icon and text to be displayed, no text string given, not understood by ME)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.9.

**27.22.4.1.1.5 Test requirement**

The ME shall operate in the manner defined in expected sequences 1.1 to 1.9.

**27.22.4.1.2 DISPLAY TEXT (Support of "No response from user")****27.22.4.1.2.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.1.2.2 Conformance requirement**

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

**27.22.4.1.2.3 Test purpose**

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a "No response from user" result value in the TERMINAL RESPONSE command send to the UICC.

**27.22.4.1.2.4 Method of test****27.22.4.1.2.4.1 Initial conditions**

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

ME Manufacturers shall set the "no response from user" period of time as declared in table A.2/1..

The USIM simulator shall be set to that period of time.

**27.22.4.1.2.4.2 Procedure****Expected Sequence 2.1 (DISPLAY TEXT, no response from user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.2.4.2, Expected Sequence.

## 2.1.27.22.4.1.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

## 27.22.4.1.3 DISPLAY TEXT (Display of extension text)

## 27.22.4.1.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.1.3.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.15.

## 27.22.4.1.3.3 Test purpose

To verify that the ME displays the extension text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.1.3.4 Method of test

## 27.22.4.1.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.1.3.4.2 Procedure

**Expected Sequence 3.1 (DISPLAY TEXT, display of the extension text)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.3.4.2, Expected Sequence 3.1.

## 27.22.4.1.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

## 27.22.4.1.4 DISPLAY TEXT (Sustained text)

## 27.22.4.1.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.1.4.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.15, clause 8.15..

## 27.22.4.1.4.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, returns a successful result in the TERMINAL RESPONSE command send to the UICC and sustain the display beyond sending the TERMINAL response.

27.22.4.1.4.4 Method of test

27.22.4.1.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.4.4.2 Procedure

**Expected Sequence 4.1 (DISPLAY TEXT, sustained text, unpacked data 8 bits, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.4.4.2, Expected Sequence 4.1.

**Expected Sequence 4.2 (DISPLAY TEXT, sustained text, clear message after delay, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.4.4.2, Expected Sequence 4.2.

**Expected Sequence 4.3 (DISPLAY TEXT, sustained text, wait for user MMI to clear, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.4.4.2, Expected Sequence 4.3.

**Expected Sequence 4.4 (DISPLAY TEXT, sustained text, wait for high priority event to clear, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: DISPLAY TEXT 4.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: DISPLAY TEXT 4.4.1	[wait for user to clear message]
4	ME → USER	Display "Toolkit Test 4"	
5	ME → UICC	TERMINAL RESPONSE: DISPLAY TEXT 4.4.1	[Command performed successfully]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	ME → USER	Display of "Toolkit Test 4"	Text shall sustain until - a higher priority event occurs.
8	USS → ME	INCOMING MOBILE TERMINATED CALL	

PROACTIVE COMMAND: DISPLAY TEXT 4.4.1

Logically:

Command details

Command number: 1  
 Command type: DISPLAY TEXT  
 Command qualifier: normal priority, wait for user to clear message

Device identities

Source device: UICC  
 Destination device: Display

Text String

Data coding scheme: unpacked, 8 bit data  
 Text: "Toolkit Test 4"

Immediate Response

Coding:

BER-TLV:	D0	1C	81	03	01	21	80	82	02	81	02	8D
	0F	04	54	6F	6F	6C	6B	69	74	20	54	65
	73	74	20	34	AB	00						

#### TERMINAL RESPONSE: DISPLAY TEXT 4.4.1

Logically:

##### Command details

Command number: 1  
 Command type: DISPLAY TEXT  
 Command qualifier: normal priority, wait for user to clear message

##### Device identities

Source device: ME  
 Destination device: UICC

##### Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	21	80	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.1.4.5 Test requirement

The ME shall operate in the manner defined in expected sequences 4.1 to 4.4.

#### 27.22.4.1.5 DISPLAY TEXT (Display of icons)

##### 27.22.4.1.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.1.5.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

##### 27.22.4.1.5.3 Test purpose

To verify that the ME displays the icons which are referred to in the contents of the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.1.5.4 Method of test

###### 27.22.4.1.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.1.5.4.2 Procedure

#### **Expected Sequence 5.1A (DISPLAY TEXT, display of basic icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.1A.

**Expected Sequence 5.1B (DISPLAY TEXT, display of basic icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.1B.

**Expected Sequence 5.2A (DISPLAY TEXT, display of colour icon, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.2A.

**Expected Sequence 5.2B (DISPLAY TEXT, display of colour icon, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.2B.

**Expected Sequence 5.3A (DISPLAY TEXT, display of basic icon, not self explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.3A.

**Expected Sequence 5.3B (DISPLAY TEXT, display of basic icon, not self explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.3B. 27.22.4.1.5.5 Test requirement

The ME shall operate in the manner defined in expected sequences 5.1A to 5.3B.

**27.22.4.1.6 DISPLAY TEXT (UCS2 display in Cyrillic)****27.22.4.1.6.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.1.6.2 Conformance requirement**

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

The ME shall support the UCS2 alphabet for the coding of the Cyrillic alphabet, as defined in the following technical specification: ISO/IEC 10646 [17].

**27.22.4.1.6.3 Test purpose**

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

**27.22.4.1.6.4 Method of test****27.22.4.1.6.4.1 Initial conditions**

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.6.4.2 Procedure

**Expected Sequence 6.1 (DISPLAY TEXT, UCS2 coded in Cyrillic)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.6.4.2, Expected Sequence 6.1.

27.22.4.1.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

27.22.4.1.7 DISPLAY TEXT (Variable Time out)

27.22.4.1.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.7.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31 and clause 8.43.

The ME shall support the variable time out for the display text.

27.22.4.1.7.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.7.4 Method of test

27.22.4.1.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.7.4.2 Procedure

**Expected Sequence 7.1 (DISPLAY TEXT, variable timeout of 10 seconds)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.7.4.2, Expected Sequence 7.1.

27.22.4.1.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

27.22.4.1.8 DISPLAY TEXT (Support of Text Attribute)

27.22.4.1.8.1 DISPLAY TEXT (Support of Text Attribute – Left Alignment)

27.22.4.1.8.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.8.1.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with Left Alignment for the display text.

#### 27.22.4.1.8.1.3 Test purpose

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.8.1.4 Method of test

##### 27.22.4.1.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.8.1.4.2 Procedure

#### **Expected Sequence 8.1 (DISPLAY TEXT, Text Attribute with Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.1.4.2, Expected Sequence 8.1.

##### 27.22.4.1.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

#### 27.22.4.1.8.2 DISPLAY TEXT (Support of Text Attribute – Center Alignment)

##### 27.22.4.1.8.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.1.8.2.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with Centre Alignment for the display text.

##### 27.22.4.1.8.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.2.4 Method of test

27.22.4.1.8.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.2.4.2 Procedure

### **Expected Sequence 8.2 (DISPLAY TEXT, Text Attribute with Center Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.2.4.2, Expected Sequence 8.2.

27.22.4.1.8.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.2.

27.22.4.1.8.3 DISPLAY TEXT (Support of Text Attribute – Right Alignment)

27.22.4.1.8.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.3.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with Right Alignment for the display text.

27.22.4.1.8.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.3.4 Method of test

27.22.4.1.8.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.3.4.2 Procedure

### **Expected Sequence 8.3 (DISPLAY TEXT, Text Attribute with Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.3.4.2, Expected Sequence 8.3.

**27.22.4.1.8.3.5 Test requirement**

The ME shall operate in the manner defined in expected sequence 8.3.

**27.22.4.1.8.4 DISPLAY TEXT (Support of Text Attribute – Large Font Size)****27.22.4.1.8.4.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.1.8.4.2 Conformance requirement**

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with large font size for the display text.

**27.22.4.1.8.4.3 Test purpose**

To verify that the ME displays the text formatted according to the large size font text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

**27.22.4.1.8.4.4 Method of test****27.22.4.1.8.4.4.1 Initial conditions**

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

**27.22.4.1.8.4.4.2 Procedure****Expected Sequence 8.4 (DISPLAY TEXT, Text Attribute with Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.4.4.2, Expected Sequence 8.4.

**27.22.4.1.8.4.5 Test requirement**

The ME shall operate in the manner defined in expected sequence 8.4.

**27.22.4.1.8.5 DISPLAY TEXT (Support of Text Attribute – Small Font Size)****27.22.4.1.8.5.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.1.8.5.2 Conformance requirement**

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with small font size for the display text.

#### 27.22.4.1.8.5.3 Test purpose

To verify that the ME displays the text formatted according to the small size font text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.8.5.4 Method of test

##### 27.22.4.1.8.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.8.5.4.2 Procedure

### **Expected Sequence 8.5 (DISPLAY TEXT, Text Attribute with Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.5.4.2, Expected Sequence 8.5.

#### 27.22.4.1.8.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.5.

#### 27.22.4.1.8.6 DISPLAY TEXT (Support of Text Attribute – Bold On)

##### 27.22.4.1.8.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.1.8.6.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with bold on for the display text.

#### 27.22.4.1.8.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.8.6.4 Method of test

##### 27.22.4.1.8.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.6.4.2 Procedure

**Expected Sequence 8.6 (DISPLAY TEXT, Text Attribute with Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.6.4.2, Expected Sequence 8.6.

27.22.4.1.8.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.6.

27.22.4.1.8.7 DISPLAY TEXT (Support of Text Attribute – Italic On)

27.22.4.1.8.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.7.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with italic on for the display text.

27.22.4.1.8.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.7.4 Method of test

27.22.4.1.8.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.7.4.2 Procedure

**Expected Sequence 8.7 (DISPLAY TEXT, Text Attribute with Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.7.4.2, Expected Sequence 8.7.

27.22.4.1.8.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.7.

27.22.4.1.8.8 DISPLAY TEXT (Support of Text Attribute – Underline On)

27.22.4.1.8.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.8.8.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with underline on for the display text.

#### 27.22.4.1.8.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.8.8.4 Method of test

##### 27.22.4.1.8.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.8.8.4.2 Procedure

#### **Expected Sequence 8.8 (DISPLAY TEXT, Text Attribute with Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.8.4.2, Expected Sequence 8.8.

##### 27.22.4.1.8.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.8.

#### 27.22.4.1.8.9 DISPLAY TEXT (Support of Text Attribute – Strikethrough On)

##### 27.22.4.1.8.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.1.8.9.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with underline on for the display text.

##### 27.22.4.1.8.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.9.4 Method of test

27.22.4.1.8.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.9.4.2 Procedure

#### **Expected Sequence 8.9 (DISPLAY TEXT, Text Attribute with Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.9.4.2, Expected Sequence 8.9.

27.22.4.1.8.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.9.

27.22.4.1.8.10 DISPLAY TEXT (Support of Text Attribute – Foreground and Background Colours)

27.22.4.1.8.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.10.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with different foreground and background colours for the display text.

27.22.4.1.8.10.3 Test purpose

To verify that the ME displays the text formatted according to the foreground and background colour text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.10.4 Method of test

27.22.4.1.8.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.10.4.2 Procedure

#### **Expected Sequence 8.10 (DISPLAY TEXT, Text Attribute with Foreground and Background Colours)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.10.4.2, Expected Sequence 8.10.

## 27.22.4.1.8.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.10.

## 27.22.4.1.9 DISPLAY TEXT (UCS2 display in Chinese)

## 27.22.4.1.9.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.1.9.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

The ME shall support the UCS2 alphabet for the coding of the Chinese characters, as defined in the following technical specification: ISO/IEC 10646 [17].

## 27.22.4.1.9.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.1.9.4 Method of test

## 27.22.4.1.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.1.9.4.2 Procedure

**Expected Sequence 9.1 (DISPLAY TEXT, UCS2 coded – Chinese characters)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.9.4.2, Expected Sequence 9.1.

## 27.22.4.1.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

## 27.22.4.1.10 DISPLAY TEXT (UCS2 display in Katakana)

## 27.22.4.1.10.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.1.10.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

The ME shall support the UCS2 alphabet for the coding of the Katakana characters, as defined in the following technical specification: ISO/IEC 10646 [17].

#### 27.22.4.1.10.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.10.4 Method of test

##### 27.22.4.1.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.10.4.2 Procedure

#### **Expected Sequence 10.1 (DISPLAY TEXT, UCS2 coded – Katakana characters)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.10.4.2, Expected Sequence 10.1.

##### 27.22.4.1.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 10.1.

### 27.22.4.2 GET INKEY

#### 27.22.4.2.1 GET INKEY(normal)

##### 27.22.4.2.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.1.2 Conformance Requirement

The ME shall support the GET INKEY command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

##### 27.22.4.2.1.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the single character entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.2.1.4 Method of test

##### 27.22.4.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be set to a display other than the idle display.

## 27.22.4.2.1.4.2 Procedure

**Expected Sequence 1.1 (GET INKEY, digits only for character, Unpacked 8 bit data for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (GET INKEY, digits only for character set, SMS default Alphabet for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (GET INKEY, backward move)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.3.

**Expected Sequence 1.4 (GET INKEY, abort)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.4.

**Expected Sequence 1.5 (GET INKEY, SMS default alphabet for character set, Unpacked 8 bit data for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.5.

**Expected Sequence 1.6 (GET INKEY, Max length for the Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.6.

## 27.22.4.2.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.6.

## 27.22.4.2.2 GET INKEY (No response from User)

## 27.22.4.2.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.2.2.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

## 27.22.4.2.2.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns a "No response from user" result value in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.2.2.4 Method of test

## 27.22.4.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

ME Manufacturers shall set the "no response from user" period of time as declared in table A.2/2.

The USIM Simulator shall be set to that period of time.

#### 27.22.4.2.2.4.2 Procedure

##### **Expected Sequence 2.1 (GET INKEY, no response from the user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.2.4.2, Expected Sequence 2.1.

#### 27.22.4.2.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

#### 27.22.4.2.3 GET INKEY (UCS2 display in Cyrillic)

##### 27.22.4.2.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.3.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

##### 27.22.4.2.3.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.2.3.4 Method of test

###### 27.22.4.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.2.3.4.2 Procedure

##### **Expected Sequence 3.1 (GET INKEY, Text String coding in UCS2 Alphabet in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.3.4.2, Expected Sequence 3.1.

##### **Expected Sequence 3.2 (GET INKEY, max length for the Text String coding in UCS2 Alphabet in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.3.4.2, Expected Sequence 3.2.

#### 27.22.4.2.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1 to 3.2.

#### 27.22.4.2.4 GET INKEY (UCS2 entry in Cyrillic)

##### 27.22.4.2.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.4.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

##### 27.22.4.2.4.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.2.4.4 Method of test

###### 27.22.4.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.2.4.4.2 Procedure

#### **Expected Sequence 4.1 (GET INKEY, characters from UCS2 alphabet in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.4.4.2, Expected Sequence 4.1.

##### 27.22.4.2.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

#### 27.22.4.2.5 GET INKEY ("Yes/No" Response)

##### 27.22.4.2.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.5.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

##### 27.22.4.2.5.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

## 27.22.4.2.5.4 Method of test

## 27.22.4.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.2.5.4.2 Procedure

**Expected Sequence 5.1(GET INKEY, "Yes/No" Response for the input, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.5.4.2, Expected Sequence 5.1.

## 27.22.4.2.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

## 27.22.4.2.6 GET INKEY (display of Icon)

## 27.22.4.2.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.2.6.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

## 27.22.4.2.6.3 Test purpose

To verify that the ME displays the Icon contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

## 27.22.4.2.6.4 Method of test

## 27.22.4.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

## 27.22.4.2.6.4.2 Procedure

**Expected Sequence 6.1A (GET INKEY, Basic icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.1A.

**Expected Sequence 6.1B (GET INKEY, Basic icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.1B.

**Expected Sequence 6.2A (GET INKEY, Basic icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.2A.

**Expected Sequence 6.2B (GET INKEY, Basic icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.2B.

**Expected Sequence 6.3A (GET INKEY, Colour icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.3A.

**Expected Sequence 6.3B (GET INKEY, Colour icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.3B.

**Expected Sequence 6.4A (GET INKEY, Colour icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.4A.

**Expected Sequence 6.4B (GET INKEY, Colour icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.4B.

**27.22.4.2.6.5 Test requirement**

The ME shall operate in the manner defined in expected sequence 6.1A to 6.4B.

**27.22.4.2.7 GET INKEY (Help Information)****27.22.4.2.7.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.2.7.2 Conformance requirement**

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

**27.22.4.2.7.3 Test purpose**

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

**27.22.4.2.7.4 Method of test****27.22.4.2.7.4.1 Initial conditions**

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.7.4.2 Procedure

**Expected Sequence 7.1 (GET INKEY, help information available)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.7.4.2, Expected Sequence 7.1.

27.22.4.2.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

27.22.4.2.8 GET INKEY (Variable Time out)

27.22.4.2.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.8.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

27.22.4.2.8.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.8.4 Method of test

27.22.4.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.8.4.2 Procedure

**Expected Sequence 8.1 (GET INKEY, variable time out of 10 seconds)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.8.4.2, Expected Sequence 8.1.

27.22.4.2.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

27.22.4.2.9 GET INKEY (Support of Text Attribute)

27.22.4.2.9.1 GET INKEY (Support of Text Attribute – Left Alignment)

27.22.4.2.9.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.1.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

#### 27.22.4.2.9.1.3 Test purpose

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.9.1.4 Method of test

##### 27.22.4.2.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.2.9.1.4.2 Procedure

#### **Expected Sequence 9.1 (GET INKEY, Text attribute with Left Alignment )**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.1.4.2, Expected Sequence 9.1.

##### 27.22.4.2.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

#### 27.22.4.2.9.2 GET INKEY (Support of Text Attribute – Center Alignment)

##### 27.22.4.2.9.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.2.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.2.9.2.4 Method of test

##### 27.22.4.2.9.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.2.9.2.4.2 Procedure

**Expected Sequence 9.2 (GET INKEY, Text attribute with Center Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.2.4.2, Expected Sequence 9.2.

## 27.22.4.2.9.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.2.

## 27.22.4.2.9.3 GET INKEY (Support of Text Attribute – Right Alignment)

## 27.22.4.2.9.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.2.9.3.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

## 27.22.4.2.9.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

## 27.22.4.2.9.3.4 Method of test

## 27.22.4.2.9.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.2.9.3.4.2 Procedure

**Expected Sequence 9.3 (GET INKEY, Text attribute with Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.3.4.2, Expected Sequence 9.3.

## 27.22.4.2.9.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.3.

## 27.22.4.2.9.4 GET INKEY (Support of Text Attribute – Large Font Size)

## 27.22.4.2.9.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.2.9.4.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

#### 27.22.4.2.9.4.3 Test purpose

To verify that the ME displays the text formatted according to the large font size text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.9.4.4 Method of test

##### 27.22.4.2.9.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.2.9.4.4.2 Procedure

#### **Expected Sequence 9.4 (GET INKEY, Text attribute with Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.4.4.2, Expected Sequence 9.4.

##### 27.22.4.2.9.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.4.

#### 27.22.4.2.9.5 GET INKEY (Support of Text Attribute – Small Font Size)

##### 27.22.4.2.9.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.5.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.5.3 Test purpose

To verify that the ME displays the text formatted according to the small font size text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.2.9.5.4 Method of test

##### 27.22.4.2.9.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.2.9.5.4.2 Procedure

#### **Expected Sequence 9.5 (GET INKEY, Text attribute with Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.5.4.2, Expected Sequence 9.5.

#### 27.22.4.2.9.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.5.

#### 27.22.4.2.9.6 GET INKEY (Support of Text Attribute – Bold On)

##### 27.22.4.2.9.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.6.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.2.9.6.4 Method of test

###### 27.22.4.2.9.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.2.9.6.4.2 Procedure

#### **Expected Sequence 9.6 (GET INKEY, Text attribute with Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.6.4.2, Expected Sequence 9.6.

##### 27.22.4.2.9.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.6.

#### 27.22.4.2.9.7 GET INKEY (Support of Text Attribute – Italic On)

##### 27.22.4.2.9.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.7.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.7.4 Method of test

27.22.4.2.9.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.7.4.2 Procedure

#### **Expected Sequence 9.7 (GET INKEY, Text attribute with Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.7.4.2, Expected Sequence 9.7.

27.22.4.2.9.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.7.

27.22.4.2.9.8 GET INKEY (Support of Text Attribute – Underline On)

27.22.4.2.9.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.8.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

27.22.4.2.9.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.8.4 Method of test

27.22.4.2.9.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.8.4.2 Procedure

#### **Expected Sequence 9.8 (GET INKEY, Text attribute with Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.8.4.2, Expected Sequence 9.8.

27.22.4.2.9.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.8.

#### 27.22.4.2.9.9 GET INKEY (Support of Text Attribute – Strikethrough On)

##### 27.22.4.2.9.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.9.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.2.9.9.4 Method of test

###### 27.22.4.2.9.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.2.9.9.4.2 Procedure

#### **Expected Sequence 9.9 (GET INKEY, Text attribute with Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.9.4.2, Expected Sequence 9.9.

##### 27.22.4.2.9.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.9.

#### 27.22.4.2.9.10 GET INKEY (Support of Text Attribute – Foreground and Background Colour)

##### 27.22.4.2.9.10.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.10.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.10.3 Test purpose

To verify that the ME displays the text formatted according to the foreground and background colour text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.10.4 Method of test

27.22.4.2.9.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.10.4.2 Procedure

**Expected Sequence 9.10 (GET INKEY, Text attribute with Foreground and Background Colour)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.10.4.2, Expected Sequence 9.10.

27.22.4.2.9.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.10.

27.22.4.2.10 GET INKEY (UCS2 display in Chinese)

27.22.4.2.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.10.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

27.22.4.2.10.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.10.4 Method of test

27.22.4.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.2.10.4.2 Procedure

**Expected Sequence 10.1 (GET INKEY, Text String coding in UCS2 Alphabet - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.10.4.2, Expected Sequence 10.1.

**Expected Sequence 10.2 (GET INKEY, max length for the Text String coding in UCS2 Alphabet - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.10.4.2, Expected Sequence 10.2.

**27.22.4.2.10.5 Test requirement**

The ME shall operate in the manner defined in expected sequence 10.1 to 10.2.

**27.22.4.2.11 GET INKEY (UCS2 entry in Chinese)****27.22.4.2.11.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.2.11.2 Conformance requirement**

The ME shall support the GET INKEY command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in the following technical specifications: ISO/IEC 10646 [17].

**27.22.4.2.11.3 Test purpose**

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

**27.22.4.2.11.4 Method of test****27.22.4.2.11.4.1 Initial conditions**

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

**27.22.4.2.11.4.2 Procedure****Expected Sequence 11.1 (GET INKEY, characters from UCS2 alphabet - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.11.4.2, Expected Sequence 11.1.

**27.22.4.2.11.5 Test requirement**

The ME shall operate in the manner defined in expected sequence 11.1

**27.22.4.2.12 GET INKEY (UCS2 display in Katakana)****27.22.4.2.12.1 Definition and applicability**

See clause 3.2.2.

#### 27.22.4.2.12.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.2.12.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.12.4 Method of test

##### 27.22.4.2.12.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.2.12.4.2 Procedure

#### **Expected Sequence 12.1 (GET INKEY, Text String coding in UCS2 Alphabet - Katakana characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.12.4.2, Expected Sequence 12.1.

#### **Expected Sequence 12.2 (GET INKEY, max length for the Text String coding in UCS2 Alphabet - Katakana characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.12.4.2, Expected Sequence 12.2.

#### 27.22.4.2.12.5 Test requirement

The ME shall operate in the manner defined in expected sequence 12.1 to 12.2.

#### 27.22.4.2.13 GET INKEY (UCS2 entry in Katakana)

##### 27.22.4.2.13.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.13.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.2.13.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.13.4 Method of test

##### 27.22.4.2.13.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.2.13.4.2 Procedure

#### **Expected Sequence 13.1 (GET INKEY, characters from UCS2 alphabet - Katakana characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.13.4.2, Expected Sequence 13.1.

#### 27.22.4.2.13.5 Test requirement

The ME shall operate in the manner defined in expected sequence 13.1

### 27.22.4.3. GET INPUT

#### 27.22.4.3.1 GET INPUT (normal)

##### 27.22.4.3.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.3.1.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

##### 27.22.4.3.1.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.3.1.4 Method of test

###### 27.22.4.3.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.3.1.4.2 Procedure

**Expected Sequence 1.1 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (GET INPUT, digits only, SMS default alphabet, ME to echo text, packing SMS Point-to-point required by ME)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (GET INPUT, character set, SMS Default Alphabet, ME to echo text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.3.

**Expected Sequence 1.4 (GET INPUT, digits only, SMS default alphabet, ME to hide text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.4.

**Expected Sequence 1.5 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.5.

**Expected Sequence 1.6 (GET INPUT, backwards move)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.6.

**Expected Sequence 1.7 (GET INPUT, abort)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.7.

**Expected Sequence 1.8 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.8.

**Expected Sequence 1.9 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.9.

**Expected Sequence 1.10 (GET INPUT, null length for the text string, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.10.

## 27.22.4.3.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.10.

## 27.22.4.3.2 GET INPUT (No response from User)

## 27.22.4.3.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.3.2.2 Conformance requirement

The ME shall support the GET INPUT command as defined in the following technical specifications :

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

#### 27.22.4.3.2.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns a "No response from user" result value in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.3.2.4 Method of test

##### 27.22.4.3.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

ME Manufacturers shall set the "no response from user" period of time as declared in table A.2/3.

The USIM Simulator shall be set to that period of time.

##### 27.22.4.3.2.4.2 Procedure

#### **Expected Sequence 2.1 (GET INPUT, no response from the user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.2.4.2, Expected Sequence 2.1.

##### 27.22.4.3.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

#### 27.22.4.3.3 GET INPUT (UCS2 display in Cyrillic)

##### 27.22.4.3.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.3.3.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

##### 27.22.4.3.3.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.3.3.4 Method of test

##### 27.22.4.3.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.3.3.4.2 Procedure

##### **Expected Sequence 3.1 (GET INPUT, text string coding in UCS2 in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.3.4.2, Expected Sequence 3.1.

##### **Expected Sequence 3.2 (GET INPUT, max length for the text string coding in UCS2 in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.3.4.2, Expected Sequence 3.2.

#### 27.22.4.3.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1 to 3.2.

#### 27.22.4.3.4 GET INPUT (UCS2 entry in Cyrillic)

##### 27.22.4.3.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.3.4.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in ISO/IEC 10646 [17].

##### 27.22.4.3.4.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.3.4.4 Method of test

###### 27.22.4.3.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.3.4.4.2 Procedure

##### **Expected Sequence 4.1 (GET INPUT, character set from UCS2 alphabet in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.4.4.2, Expected Sequence 4.1.

**Expected Sequence 4.2 (GET INPUT, character set from UCS2 alphabet in Cyrillic, Max length for the input, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.4.4.2, Expected Sequence 4.2.

**27.22.4.3.4.5 Test requirement**

The ME shall operate in the manner defined in expected sequences 4.1 to 4.2.

**27.22.4.3.5 GET INPUT (default text)****27.22.4.3.5.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.3.5.2 Conformance requirement**

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.23.

**27.22.4.3.5.3 Test purpose**

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

**27.22.4.3.5.4 Method of test****27.22.4.3.5.4.1 Initial conditions**

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

**27.22.4.3.5.4.2 Procedure****Expected Sequence 5.1 (GET INPUT, default text for the input, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.5.4.2, Expected Sequence 5.1.

**Expected Sequence 5.2 (GET INPUT, default text for the input with max length, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.5.4.2, Expected Sequence 5.2.

**27.22.4.3.5.5 Test requirement**

The ME shall operate in the manner defined in expected sequences 5.1 to 5.2.

**27.22.4.3.6 GET INPUT (display of Icon)****27.22.4.3.6.1 Definition and applicability**

See clause 3.2.2.

#### 27.22.4.3.6.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.5.4, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 12.31.

#### 27.22.4.3.6.3 Test purpose

To verify that the ME displays the Icon contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.6.4 Method of test

##### 27.22.4.3.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.3.6.4.2 Procedure

#### **Expected Sequence 6.1A (GET INPUT, Basic icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.1A.

#### **Expected Sequence 6.1B (GET INPUT, Basic icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.1B.

#### **Expected Sequence 6.2A (GET INPUT, Basic icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.2A.

#### **Expected Sequence 6.2B (GET INPUT, Basic icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.2B.

#### **Expected Sequence 6.3A (GET INPUT, Colour icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.3A.

#### **Expected Sequence 6.3B (GET INPUT, Colour icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.3B.

#### **Expected Sequence 6.4A (GET INPUT, Colour icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.4A.

#### **Expected Sequence 6.4B (GET INPUT, Colour icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.4B.

#### 27.22.4.3.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 6.1A to 6.4B.

### 27.22.4.3.7 GET INPUT (Help Information)

#### 27.22.4.3.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.7.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

#### 27.22.4.3.7.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns a 'help information required by the user' result value in the TERMINAL RESPONSE command sent to the UICC if the user has indicated the need to get help information.

#### 27.22.4.3.7.4 Method of test

##### 27.22.4.3.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.3.7.4.2 Procedure

#### **Expected Sequence 7.1 (GET INPUT, digits only, ME to echo text, ME supporting 8 bit data Message, help information available)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.7.4.2, Expected Sequence 7.1.

##### 27.22.4.3.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

### 27.22.4.3.8 GET INPUT (Support of Text Attribute)

#### 27.22.4.3.8.1 GET INPUT (Support of Text Attribute – Left Alignment)

##### 27.22.4.3.8.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.3.8.1.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

##### 27.22.4.3.8.1.3 Test purpose

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.1.4 Method of test

27.22.4.3.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.1.4.2 Procedure

#### **Expected Sequence 8.1 (GET INPUT, Text attribute – Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.1.4.2, Expected Sequence 8.1.

27.22.4.3.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

27.22.4.3.8.2 GET INPUT (Support of Text Attribute – Center Alignment)

27.22.4.3.8.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.2.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.2.4 Method of test

27.22.4.3.8.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.2.4.2 Procedure

#### **Expected Sequence 8.2 (GET INPUT, Text attribute – Center Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.2.4.2, Expected Sequence 8.2.

27.22.4.3.8.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.2.

### 27.22.4.3.8.3 GET INPUT (Support of Text Attribute – Right Alignment)

#### 27.22.4.3.8.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.8.3.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

#### 27.22.4.3.8.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.8.3.4 Method of test

##### 27.22.4.3.8.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.3.8.3.4.2 Procedure

#### **Expected Sequence 8.3 (GET INPUT, Text attribute – Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.3.4.2, Expected Sequence 8.3.

##### 27.22.4.3.8.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.3.

### 27.22.4.3.8.4 GET INPUT (Support of Text Attribute – Large Font Size)

#### 27.22.4.3.8.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.8.4.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

#### 27.22.4.3.8.4.3 Test purpose

To verify that the ME displays the text formatted according to the large font size text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.4.4 Method of test

27.22.4.3.8.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.4.4.2 Procedure

#### **Expected Sequence 8.4 (GET INPUT, Text attribute – Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.4.4.2, Expected Sequence 8.4.

27.22.4.3.8.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.4.

27.22.4.3.8.5 GET INPUT (Support of Text Attribute – Small Font Size)

27.22.4.3.8.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.5.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.5.3 Test purpose

To verify that the ME displays the text formatted according to the small font size text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.5.4 Method of test

27.22.4.3.8.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.5.4.2 Procedure

#### **Expected Sequence 8.5 (GET INPUT, Text attribute – Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.5.4.2, Expected Sequence 8.5.

27.22.4.3.8.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.5.

#### 27.22.4.3.8.6 GET INPUT (Support of Text Attribute – Bold On)

##### 27.22.4.3.8.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.3.8.6.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

##### 27.22.4.3.8.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.3.8.6.4 Method of test

###### 27.22.4.3.8.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.3.8.6.4.2 Procedure

#### **Expected Sequence 8.6 (GET INPUT, Text attribute – Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.6.4.2, Expected Sequence 8.6.

###### 27.22.4.3.8.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.6.

#### 27.22.4.3.8.7 GET INPUT (Support of Text Attribute – Italic On)

##### 27.22.4.3.8.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.3.8.7.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

##### 27.22.4.3.8.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.7.4 Method of test

27.22.4.3.8.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.7.4.2 Procedure

**Expected Sequence 8.7 (GET INPUT, Text attribute – Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.7.4.2, Expected Sequence 8.7.

27.22.4.3.8.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.7.

27.22.4.3.8.8 GET INPUT (Support of Text Attribute – Underline On)

27.22.4.3.8.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.8.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.8.4 Method of test

27.22.4.3.8.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.8.4.2 Procedure

**Expected Sequence 8.8 (GET INPUT, Text attribute – Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.8.4.2, Expected Sequence 8.8.

27.22.4.3.8.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.8.

#### 27.22.4.3.8.9 GET INPUT (Support of Text Attribute – Strikethrough On)

##### 27.22.4.3.8.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.3.8.9.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

##### 27.22.4.3.8.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.3.8.9.4 Method of test

###### 27.22.4.3.8.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.3.8.9.4.2 Procedure

#### **Expected Sequence 8.9 (GET INPUT, Text attribute – Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.9.4.2, Expected Sequence 8.9.

###### 27.22.4.3.8.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.9.

#### 27.22.4.3.8.10 GET INPUT (Support of Text Attribute – Foreground and Background Colour)

##### 27.22.4.3.8.10.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.3.8.10.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

##### 27.22.4.3.8.10.3 Test purpose

To verify that the ME displays the text formatted according to the fore- and background colour text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

## 27.22.4.3.8.10.4 Method of test

## 27.22.4.3.8.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.3.8.10.4.2 Procedure

**Expected Sequence 8.10 (GET INPUT, Text attribute – Foreground and Background Colour)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.10.4.2, Expected Sequence 8.10.

## 27.22.4.3.8.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.10.

## 27.22.4.3.9 GET INPUT (UCS2 display in Chinese)

## 27.22.4.3.9.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.3.9.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in the following technical specifications: ISO/IEC 10646 [17].

## 27.22.4.3.9.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

## 27.22.4.3.9.4 Method of test

## 27.22.4.3.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.3.9.4.2 Procedure

**Expected Sequence 9.1 (GET INPUT, text string coding in UCS2 - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.9.4.2, Expected Sequence 9.1.

**Expected Sequence 9.2 (GET INPUT, max length for the text string coding in UCS2 - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.9.4.2, Expected Sequence 9.2.

**27.22.4.3.9.5 Test requirement**

The ME shall operate in the manner defined in expected sequences 9.1 to 9.2

**27.22.4.3.10 GET INPUT (UCS2 entry in Chinese)****27.22.4.3.10.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.3.10.2 Conformance requirement**

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in ISO/IEC 10646 [17].

**27.22.4.3.10.3 Test purpose**

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

**27.22.4.3.10.4 Method of test****27.22.4.3.10.4.1 Initial conditions**

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

**27.22.4.3.10.4.2 Procedure****Expected Sequence 10.1 (GET INPUT, character set from UCS2 alphabet - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.10.4.2, Expected Sequence 10.1.

**Expected Sequence 10.2 (GET INPUT, character set from UCS2 alphabet - Chinese characters, Max length for the input, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.10.4.2, Expected Sequence 10.2.

**27.22.4.3.10.5 Test requirement**

The ME shall operate in the manner defined in expected sequences 10.1 to 10.2

### 27.22.4.3.11 GET INPUT (UCS2 display in Katakana)

#### 27.22.4.3.11.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.11.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.3.11.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.11.4 Method of test

##### 27.22.4.3.11.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.3.11.4.2 Procedure

#### **Expected Sequence 11.1 (GET INPUT, text string coding in UCS2 in Katakana, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.11.4.2, Expected Sequence 11.1.

#### **Expected Sequence 11.2 (GET INPUT, max length for the text string coding in UCS2 in Katakana, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.11.4.2, Expected Sequence 11.2.

#### 27.22.4.3.11.5 Test requirement

The ME shall operate in the manner defined in expected sequences 11.1 to 11.2

### 27.22.4.3.12 GET INPUT (UCS2 entry in Katakana)

#### 27.22.4.3.12.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.12.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in ISO/IEC 10646 [17].

#### 27.22.4.3.12.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.12.4 Method of test

##### 27.22.4.3.12.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.3.12.4.2 Procedure

#### **Expected Sequence 12.1 (GET INPUT, character set from UCS2 alphabet in Katakana, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.12.4.2, Expected Sequence 12.1.

#### **Expected Sequence 12.2 (GET INPUT, character set from UCS2 alphabet in Katakana, Max length for the input, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.12.4.2, Expected Sequence 12.2.

#### 27.22.4.3.12.5 Test requirement

The ME shall operate in the manner defined in expected sequences 12.1 to 12.2.

### 27.22.4.4 MORE TIME

#### 27.22.4.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.4.2 Conformance requirement

The ME shall support the MORE TIME command as defined in:

- 3GPP TS 31.111 [15] clause 6.4.4, clause 6.6.4, clause 5.2, clause 8.6 and clause 8.7.

#### 27.22.4.4.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (OK) to the UICC after the ME receives the MORE TIME proactive UICC command.

## 27.22.4.4.4 Method of test

## 27.22.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.4.4.2 Procedure

**Expected Sequence 1.1 (MORE TIME)**

See ETSI TS 102 384 [26] in subclause 27.22.4.4.4.2, Expected Sequence 1.1.

## 27.22.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.4.5 PLAY TONE

## 27.22.4.5.1 PLAY TONE (Normal)

## 27.22.4.5.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.5.1.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16 and clause 8.8.

## 27.22.4.5.1.3 Test purpose

To verify that the ME plays an audio tone of a type and duration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece whilst not in call and shall superimpose the tone on top of the downlink audio whilst in call.

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command.

## 27.22.4.5.1.4 Method of test

## 27.22.4.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.5.1.4.2 Procedure

**Expected Sequence 1.1 (PLAY TONE)**

Step	Direction	MESSAGE / Action	Comments
------	-----------	------------------	----------

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.1	
4	ME → USER	Display "Dial Tone" Play a standard supervisory dial tone through the external ringer for a duration of 5 s	
5	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.1	[Command performed successfully]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.2	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.2	
10	ME → USER	Display "Sub. Busy" Play a standard supervisory called subscriber busy tone for a duration of 5 s	
11	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.2	[Command performed successfully]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.3	
14	ME → UICC	FETCH	
15	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.3	
16	ME → USER	Display "Congestion" Play a standard supervisory congestion tone for a duration of 5 s	
17	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.3	[Command performed successfully]
18	UICC → ME	PROACTIVE UICC SESSION ENDED	
19	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.4	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.4	
22	ME → USER	Display "RP Ack" Play a standard supervisory radio path acknowledgement tone	
23	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.4	[Command performed successfully]
24	UICC → ME	PROACTIVE UICC SESSION ENDED	
25	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.5	
26	ME → UICC	FETCH	
27	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.5	
28	ME → USER	Display "No RP" Play a standard supervisory radio path not available / call dropped tone for a duration of 5 s	
29	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.5	[Command performed successfully]
30	UICC → ME	PROACTIVE UICC SESSION ENDED	
31	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.6	
32	ME → UICC	FETCH	

Step	Direction	MESSAGE / Action	Comments
33	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.6	
34	ME → USER	Display "Spec Info" Play a standard supervisory error / special information tone for a duration of 5 s	
35	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.6	[Command performed successfully]
36	UICC → ME	PROACTIVE UICC SESSION ENDED	
37	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.7	
38	ME → UICC	FETCH	
39	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.7	
40	ME → USER	Display "Call Wait" Play a standard supervisory call waiting tone for a duration of 5 s	
41	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.7	[Command performed successfully]
42	UICC → ME	PROACTIVE UICC SESSION ENDED	
43	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.8	
44	ME → UICC	FETCH	
45	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.8	
46	ME → USER	Display "Ring Tone" Play a standard supervisory ringing tone for duration of 5 s	
47	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.8	[Command performed successfully]
48	UICC → ME	PROACTIVE UICC SESSION ENDED	
49	USER → ME	Set up a voice call	[ User dials 123456789 to connect to the network manually]
50	ME → USS	Establish voice call	[Voice call is established]
51	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.9	
52	ME → UICC	FETCH	
53	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.9	
54	ME → USER	Display "Dial Tone" Superimpose the standard supervisory dial tone on the audio downlink for the duration of 5 s	
55	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.9	[Command performed successfully]
56	UICC → ME	PROACTIVE UICC SESSION ENDED	
57	USER → ME	The user ends the call	
58	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.10	
59	ME → UICC	FETCH	
60	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.10	
61	ME → USER	Display "This command instructs the ME to play an audio tone. Upon receiving this command, the ME shall check if it is currently in, or in the process of setting up (SET-UP message sent to the network, see GSM"04.08"(8)), a speech call. - If the ME I" Play a general beep	

Step	Direction	MESSAGE / Action	Comments
62	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.10a or TERMINAL RESPONSE: PLAY TONE 1.1.10b	[Command performed successfully] or [Command beyond ME's capabilities]
63	UICC → ME	PROACTIVE UICC SESSION ENDED	
64	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.11	
65	ME → UICC	FETCH	
66	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.11	
67	ME → USER	Display "Beep" Play a ME proprietary general beep	
68	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.11a Or TERMINAL RESPONSE: PLAY TONE 1.1.11b	[Command performed successfully] or [Command beyond ME's capabilities]
69	UICC → ME	PROACTIVE UICC SESSION ENDED	
70	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.12	
71	ME → UICC	FETCH	
72	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.12	
73	ME → USER	Display "Positive" Play a ME proprietary positive acknowledgement tone	
74	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.12a or TERMINAL RESPONSE: PLAY TONE 1.1.12b	[Command performed successfully] or [Command beyond ME's capabilities]
75	UICC → ME	PROACTIVE UICC SESSION ENDED	
76	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.13	
77	ME → UICC	FETCH	
78	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.13	
79	ME → USER	Display "Negative" Play a ME proprietary negative acknowledgement tone	
80	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.13a or TERMINAL RESPONSE: PLAY TONE 1.1.13b	[Command performed successfully] or [Command beyond ME's capabilities]
81	UICC → ME	PROACTIVE UICC SESSION ENDED	
82	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.14	
83	ME → UICC	FETCH	
84	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.14	
85	ME → USER	Display "Quick" Play a ME proprietary general beep	
86	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.14a or TERMINAL RESPONSE: PLAY TONE 1.1.14b	[Command performed successfully] or [Command beyond ME's capabilities]
87	UICC → ME	PROACTIVE UICC SESSION ENDED	

Step	Direction	MESSAGE / Action	Comments
88	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.15	
89	ME → UICC	FETCH	
90	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.15	
91	ME → USER	Display "<ABORT>" Play an ME Error / Special information tone until user aborts this command (the command shall be aborted by the user within 1 minute)	
92	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.15	[Proactive UICC session terminated by the user]
93	UICC → ME	PROACTIVE UICC SESSION ENDED	
94	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.1.16	
95	ME → UICC	FETCH	
96	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.1.16	[No alpha identifier, no tone tag, no duration tag]
97	ME → User	ME plays general beep, or if not supported any (defined by ME- manufacturer) other supported tone	[ME uses default duration defined by ME-manufacturer]
98	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.1.16	[Command performed successfully], [ME uses general beep, or if not supported any (defined by ME-manufacturer) other supported tone, uses default duration defined by ME-manufacturer]
99	UICC → ME	PROACTIVE UICC SESSION ENDED	

For coding, see ETSI TS 102 384 [26] in subclause 27.22.4.5.1.4.2, Expected Sequence 1.1.

#### 27.22.4.5.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

#### 27.22.4.5.2 PLAY TONE (UCS2 display in Cyrillic)

##### 27.22.4.5.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.2.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.16 and clause 8.8.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in ISO/IEC 10646 [17].

##### 27.22.4.5.2.3 Test purpose

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

#### 27.22.4.5.2.4 Method of test

##### 7.22.4.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.5.2.4.2 Procedure

#### **Expected Sequence 2.1 (PLAY TONE, character set from UCS2 alphabet in Russian, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.2.4.2, Expected Sequence 2.1.

##### 27.22.4.5.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

#### 27.22.4.5.3 PLAY TONE (display of Icon)

##### 27.22.4.5.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.3.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8 and clause 8.31.

##### 27.22.4.5.3.3 Test purpose

To verify that the ME plays an audio tone of a type and duration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

To verify that the ME displays the icon contained in the PLAY TONE proactive UICC command.

##### 27.22.4.5.3.4 Method of test

##### 27.22.4.5.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.5.3.4.2 Procedure

#### **Expected Sequence 3.1A (PLAY TONE, Basic icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.1A.

**Expected Sequence 3.1B (PLAY TONE, Basic icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.1B.

**Expected Sequence 3.2A (PLAY TONE, Basic icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.2A.

**Expected Sequence 3.2B (PLAY TONE, Basic icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.2B.

**Expected Sequence 3.3A (PLAY TONE, Colour icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.3A.

**Expected Sequence 3.3B (PLAY TONE, Colour icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.3B.

**Expected Sequence 3.4A (PLAY TONE, Colour icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.4A.

**Expected Sequence 3.4B (PLAY TONE, Colour icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.4B.

**27.22.4.5.3.5 Test Requirement**

The ME shall operate in the manner defined in expected sequences 3.1A to 3.4B.

**27.22.4.5.4 PLAY TONE (Support of Text Attribute)****27.22.4.5.4.1 PLAY TONE (Support of Text Attribute – Left Alignment)****27.22.4.5.4.1.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.5.4.1.2 Conformance requirement**

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

**27.22.4.5.4.1.3 Test purpose**

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

**27.22.4.5.4.1.4 Method of test****27.22.4.5.4.1.4.1 Initial conditions**

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.5.4.1.4.2 Procedure

##### **Expected Sequence 4.1 (PLAY TONE, Text Attribute – Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.1.4.2, Expected Sequence 4.1.

#### 27.22.4.5.4.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.1.

#### 27.22.4.5.4.2 PLAY TONE (Support of Text Attribute – Center Alignment)

##### 27.22.4.5.4.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.2.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.5.4.2.4 Method of test

###### 27.22.4.5.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.5.4.2.4.2 Procedure

##### **Expected Sequence 4.2 (PLAY TONE, Text Attribute – Centre Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.2.4.2, Expected Sequence 4.2.

#### 27.22.4.5.4.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.2.

#### 27.22.4.5.4.3 PLAY TONE (Support of Text Attribute – Right Alignment)

##### 27.22.4.5.4.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.3.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.5.4.3.4 Method of test

###### 27.22.4.5.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.5.4.3.4.2 Procedure

#### **Expected Sequence 4.3 (PLAY TONE, Text Attribute – Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.3.4.2, Expected Sequence 4.3.

##### 27.22.4.5.4.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.3.

#### 27.22.4.5.4.4 PLAY TONE (Support of Text Attribute – Large Font Size)

##### 27.22.4.5.4.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.4.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.4.3 Test purpose

To verify that the ME displays the text formatted according to the large font size text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.4.4 Method of test

27.22.4.5.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.4.4.2 Procedure

#### **Expected Sequence 4.4 (PLAY TONE, Text Attribute – Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.4.4.2, Expected Sequence 4.4.

27.22.4.5.4.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.4.

27.22.4.5.4.5 PLAY TONE (Support of Text Attribute – Small Font Size)

27.22.4.5.4.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.5.4.5.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

27.22.4.5.4.5.3 Test purpose

To verify that the ME displays the text formatted according to the small font size text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.5.4 Method of test

27.22.4.5.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.5.4.2 Procedure

#### **Expected Sequence 4.5 (PLAY TONE, Text Attribute – Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.5.4.2, Expected Sequence 4.5.

27.22.4.5.4.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.5.

#### 27.22.4.5.4.6 PLAY TONE (Support of Text Attribute – Bold On)

##### 27.22.4.5.4.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.6.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.5.4.6.4 Method of test

###### 27.22.4.5.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.5.4.6.4.2 Procedure

#### **Expected Sequence 4.6 (PLAY TONE, Text Attribute – Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.6.4.2, Expected Sequence 4.6.

##### 27.22.4.5.4.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.6.

#### 27.22.4.5.4.7 PLAY TONE (Support of Text Attribute – Italic On)

##### 27.22.4.5.4.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.7.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.7.4 Method of test

27.22.4.5.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.7.4.2 Procedure

#### **Expected Sequence 4.7 (PLAY TONE, Text Attribute – Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.7.4.2, Expected Sequence 4.7.

27.22.4.5.4.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.7.

27.22.4.5.4.8 PLAY TONE (Support of Text Attribute – Underline On)

27.22.4.5.4.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.5.4.8.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

27.22.4.5.4.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.8.4 Method of test

27.22.4.5.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.8.4.2 Procedure

#### **Expected Sequence 4.8 (PLAY TONE, Text Attribute – Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.8.4.2, Expected Sequence 4.8.

27.22.4.5.4.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.8.

#### 27.22.4.5.4.9 PLAY TONE (Support of Text Attribute – Strikethrough On)

##### 27.22.4.5.4.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.9.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.5.4.9.4 Method of test

###### 27.22.4.5.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.5.4.9.4.2 Procedure

#### **Expected Sequence 4.9 (PLAY TONE, Text Attribute – Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.9.4.2, Expected Sequence 4.9.

##### 27.22.4.5.4.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.9.

#### 27.22.4.5.4.10 PLAY TONE (Support of Text Attribute – Foreground and Background Colour)

##### 27.22.4.5.4.10.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.10.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.10.3 Test purpose

To verify that the ME displays the text formatted according to the foreground and background colour text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

## 27.22.4.5.4.10.4 Method of test

## 27.22.4.5.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.5.4.10.4.2 Procedure

**Expected Sequence 4.10 (PLAY TONE, Text Attribute – Foreground and Background Colour)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.10.4.2, Expected Sequence 4.10.

## 27.22.4.5.4.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.10.

## 27.22.4.5.5 PLAY TONE (UCS2 display in Chinese)

## 27.22.4.5.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.5.5.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.16 and clause 8.8.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in ISO/IEC 10646 [17].

## 27.22.4.5.5.3 Test purpose

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

## 27.22.4.5.5.4 Method of test

## 27.22.4.5.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.5.5.4.2 Procedure

**Expected Sequence 5.1 (PLAY TONE, character set from UCS2 alphabet in Chinese, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.5.4.2, Expected Sequence 5.1.

#### 27.22.4.5.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

#### 27.22.4.5.6 PLAY TONE (UCS2 display in Katakana)

##### 27.22.4.5.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.6.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.16 and clause 8.8.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in ISO/IEC 10646 [17].

##### 27.22.4.5.6.3 Test purpose

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

##### 27.22.4.5.6.4 Method of test

###### 27.22.4.5.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.5.6.4.2 Procedure

#### **Expected Sequence 6.1 (PLAY TONE, with UCS2 in Katakana, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.6.4.2, Expected Sequence 6.1.

##### 27.22.4.5.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

#### 27.22.4.6 POLL INTERVAL

##### 27.22.4.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.6.2 Conformance requirement

The ME shall support the POLL INTERVAL command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.6, clause 6.6.6, clause 5.2, clause 8.6, clause 8.7 and clause 8.8.

### 27.22.4.6.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (OK) to the UICC after the ME receives the POLL INTERVAL proactive UICC command.

To verify that the ME gives a valid response to the polling interval requested by the UICC.

To verify that the ME sends STATUS commands to the UICC at an interval no longer than the interval negotiated by the UICC.

### 27.22.4.6.4 Method of test

#### 27.22.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.6.4.2 Procedure

See ETSI TS 102 384 [26] in subclause 27.22.4.6.4.2, Expected Sequence 1.1.

NOTE: If the requested poll interval is not supported by the ME, the ME is allowed to use a different one as stated in 3GPP TS 31.111 [15], subclause 6.4.6.

### 27.22.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.4.7 REFRESH

### 27.22.4.7.1 REFRESH (normal)

#### 27.22.4.7.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.7.1.2 Conformance requirement

The ME shall support the REFRESH command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.7, clause 6.6.13, clause 5.2, clause 8.6, clause 8.7 and clause 8.18.

Consequently the ME shall support the USIM Initialization procedure as defined in:

- 3GPP TS 31.102 [14] clause 5.1.1.2 and ETSI TS 102 221[13] clause 11.1.2

#### 27.22.4.7.1.3 Test purpose

To verify that the ME performs the Proactive Command – REFRESH in accordance with the Command Qualifier. This shall require the ME to perform:

- the UICC and USIM initialization,
- a re-read of the contents and structure of the EFs on the UICC that have been notified as changed and are either part of initialization or used during the test,
- a restart of the card session,
- a successful return of the result of the execution of the command in the TERMINAL RESPONSE command send to the UICC.

27.22.4.7.1.4 Method of test

27.22.4.7.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table..

The elementary files are coded as Toolkit default except for expected sequence 1.3.

For expected sequence 1.3 the global phonebook shall be present.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

These values might be overwritten with values defined in the expected sequences itself.

Prior to the execution of expected sequence 1.2 the FDN service shall be enabled.

27.22.4.7.1.4.2 Procedure

### Expected Sequence 1.1 (REFRESH, USIM Initialization)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: REFRESH 1.1.1	[To inform the ME that FDN becomes enabled]
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: REFRESH 1.1.1	
4	UICC	EF EST contents states FDN enabled	[New EF EST value: 01]
5	ME → UICC	USIM Initialization including send STATUS[P1='01']	[ME performs USIM initialization in accordance with 3GPP TS 31.111 [15] clause 6.4.7]
6	ME → UICC	TERMINAL RESPONSE: REFRESH 1.1.1A Or TERMINAL RESPONSE: REFRESH 1.1.1B	[normal ending]  [additional EFs read]
7	UICC → ME	PROACTIVE UICC SESSION ENDED	
8	USER → ME	Call setup to "321"	
9	ME → USER	Call set up not allowed	
10	USER → ME	Call setup to "123"	
11	ME → USS	Setup	Called party BCD number shall be "123"

PROACTIVE COMMAND: REFRESH 1.1.1

Logically:

Command details

Command number: 1  
Command type: REFRESH  
Command qualifier: USIM Initialization

Device identities

Source device: UICC  
Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	01	03	82	02	81	82	
----------	----	----	----	----	----	----	----	----	----	----	----	--

TERMINAL RESPONSE: REFRESH 1.1.1A

Logically:

## Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Initialization

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	01	03	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## TERMINAL RESPONSE: REFRESH 1.1.1B

## Logically:

## Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Initialization

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: REFRESH performed with additional EFs read

## Coding:

BER-TLV:	81	03	01	01	03	82	02	82	81	83	01	03
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.2 (REFRESH, File Change Notification)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: REFRESH 1.2.1	[To inform the ME that EF FDN will be in an updated state, FDN service already enabled]
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: REFRESH 1.2.1	
4	UICC	Update EF FDN RECORD 1	[EF FDN record 1 updated to contain the dialling string "0123456789"]
5	ME → UICC	TERMINAL RESPONSE: REFRESH 1.2.1A Or TERMINAL RESPONSE: REFRESH 1.2.1B	[normal ending] [additional EFs read]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	USER → ME	Call setup to "123"	
8	ME → USER	Call set up not allowed	
9	USER → ME	Call setup to "0123456789"	
10	ME → USS	Setup	Called party BCD number shall be "0123456789"

## PROACTIVE COMMAND: REFRESH 1.2.1

## Logically:

## Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: File Change Notification

## Device identities

Source device: UICC  
 Destination device: ME  
 File List: EF FDN

## Coding:

BER-TLV:	D0	12	81	03	01	01	01	82	02	81	82	92
	07	01	3F	00	7F	FF	6F	3B				

## TERMINAL RESPONSE: REFRESH 1.2.1A

## Logically:

## Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: File Change Notification

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	01	01	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## TERMINAL RESPONSE: REFRESH 1.2.1B

## Logically:

## Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: File Change Notification

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: REFRESH performed with additional EFs read

## Coding:

BER-TLV:	81	03	01	01	01	82	02	82	81	83	01	03
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.3 (REFRESH, USIM Initialization and File Change Notification)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: REFRESH 1.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: REFRESH 1.3.1	
4	UICC	Update EF ADN in the global phonebook	[EF ADN entry 1 of the global phonebook to contain the the new and previously unused alpha identifier "Changed"]
5	ME → UICC	USIM Initialization including sending STATUS [P1='01']	[ME performs USIM initialization in accordance with 3GPP TS 31.111 [15] clause 6.4.7]
6	ME → UICC	TERMINAL RESPONSE: REFRESH 1.3.1A Or TERMINAL RESPONSE: REFRESH 1.3.1B	[normal ending]  [additional EFs read]
7	UICC → ME	PROACTIVE UICC SESSION ENDED	
8	USER → ME	Use an MMI dependent procedure to display the entry with the alpha identifier "Changed" stored in record 1 of EF ADN in the global phonebook	[To ensure that EF ADN in the global phonebook has been read after issuing the Refresh command]
9	ME → USER	The ME shall display the alpha identifier "Changed" for record 1 of EF ADN in the global phonebook	

**PROACTIVE COMMAND: REFRESH 1.3.1**

Logically:

Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Initialization and File Change Notification

Device identities

Source device: UICC  
 Destination device: ME  
 File List: ADN in the global phonebook

Coding:

BER-TLV:	D0	12	81	03	01	01	02	82	02	81	82	92
	Note 1											

Note 1: Length and data of the file list TLV depend on the card configuration used in this test. The global phonebook shall be used. The number of changed files shall be set to '01'.

**TERMINAL RESPONSE: REFRESH 1.3.1A**

Logically:

Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Initialization and File Change Notification

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	01	02	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: REFRESH 1.3.1B

Logically:

Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Initialization and File Change Notification

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: REFRESH performed with additional EFs read

Coding:

BER-TLV:	81	03	01	01	02	82	02	82	81	83	01	03
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.4 (REFRESH, USIM Initialization and Full File Change Notification)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: REFRESH 1.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: REFRESH 1.4.1	
4	UICC	EF EST contents states FDN enabled	[New EF EST value: 01]
5	UICC	Update EF FDN	[EF FDN record 1 updated to contain the dialling string "0123456789"]
6	ME → UICC	USIM Initialization including send STATUS[P1='01']	[ME performs USIM initialization in accordance with 3GPP TS 31.111 [15] clause 6.4.7]
7	ME → UICC	TERMINAL RESPONSE: REFRESH 1.4.1A Or TERMINAL RESPONSE: REFRESH 1.4.1B	[normal ending]  [additional EFs read]
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	Call setup to "321"	
10	ME → USER	Call set up not allowed	
11	USER → ME	Call setup to "0123456789"	
12	ME → USS	Setup	Called party BCD number shall be "0123456789"

PROACTIVE COMMAND: REFRESH 1.4.1

Logically:

Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Initialization and Full File Change Notification

Device identities

Source device: UICC

Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	01	00	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: REFRESH 1.4.1A

Logically:

Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Initialization and Full file Change Notification

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	01	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: REFRESH 1.4.1B

Logically:

Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Initialization and full File change Notification

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: REFRESH performed with additional EFs read

Coding:

BER-TLV:	81	03	01	01	00	82	02	82	81	83	01	03
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.5 (REFRESH, UICC Reset)**

TBD

**Expected Sequence 1.6 (REFRESH, USIM Initialization after SMS-PP data download)**

Step	Direction	MESSAGE / Action	Comments	
1	ME	The ME shall be in its normal idle mode	[Start a sequence to verify that the ME returns the RP-ACK message back to the USS, if the UICC responds with '90 00']	
2	USS → ME	SMS-PP Data Download Message 1.6.1		
3	ME → USER	The ME shall not display the message or alert the user of a short message waiting		
4	ME → USS	ENVELOPE: SMS-PP DOWNLOAD 1.6.1		
5	UICC → ME	PROACTIVE COMMAND PENDING: REFRESH 1.1.1		
6	ME → USS	RP-ACK		
7	ME → UICC	FETCH		
8	UICC → ME	PROACTIVE COMMAND: REFRESH 1.1.1		
9	UICC	EF EST contents states FDN enabled		[New EF EST value: 01]
10	ME → UICC	USIM Initialization including send STATUS[P1='01']		[ME performs USIM initialization in accordance with 3GPP TS 31.111 [15] clause 6.4.7]
11	ME → UICC	TERMINAL RESPONSE: REFRESH 1.1.1A Or TERMINAL RESPONSE: REFRESH 1.1.1B		[normal ending]  [additional EFs read]
12	UICC → ME	PROACTIVE UICC SESSION ENDED		
13	USER → ME	Call setup to "321"		
14	ME → USER	Call set up not allowed		
15	USER → ME	Call setup to "123"		
16	ME → USS	Setup		Called party BCD number shall be "123"

## SMS-PP (Data Download) Message 1.6.1

Logically:

## SMS TPDU

TP-MTI	SMS-DELIVER
TP-MMS	No more messages waiting for the MS in this SC
TP-RP	TP-Reply-Path is not set in this SMS-DELIVER
TP-UDHI	TP-UD field contains only the short message
TP-SRI	A status report will not be returned to the SME
TP-OA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"1234"
TP-PID	(U)SIM Data download
TP-DCS	
Coding Group	General Data Coding
Compression	Text is uncompressed
Message Class	Class 2 (U)SIM Specific Message
Alphabet	8 bit data
TP-SCTS:	01/01/98 00:00:00 +0
TP-UDL	13
TP-UD	"Short Message"

Coding:

Coding	04	04	91	21	43	7F	16	89	10	10	00	00
	00	00	0D	53	68	6F	72	74	20	4D	65	73
	73	61	67	65								

ENVELOPE: SMS-PP DOWNLOAD 1.6.1

Logically:

SMS-PP Download

Device identities  
Source device: Network  
Destination device: UICC  
Address  
TON International number  
NPI "ISDN / telephone numbering plan"  
Dialling number string "112233445566778"  
SMS TPDU  
TP-MTI SMS-DELIVER  
TP-MMS No more messages waiting for the MS in this SC  
TP-RP TP-Reply-Path is not set in this SMS-DELIVER  
TP-UDHI TP-UD field contains only the short message  
TP-SRI A status report will not be returned to the SME  
TP-OA  
TON International number  
NPI "ISDN / telephone numbering plan"  
Address value "1234"  
TP-PID (U)SIM Data download  
TP-DCS  
Coding Group General Data Coding  
Compression Text is uncompressed  
Message Class Class 2 (U)SIM Specific Message  
Alphabet 8 bit data  
TP-SCTS: 01/01/98 00:00:00 +0  
TP-UDL 13  
TP-UD "Short Message"

Coding:

BER-TLV:	D1	2D	82	02	83	81	06	09	91	11	22	33
	44	55	66	77	F8	8B	1C	04	04	91	21	43
	7F	16	89	10	10	00	00	00	00	0D	53	68
	6F	72	74	20	4D	65	73	73	61	67	65	

27.22.4.7.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.6.

27.22.4.7.2 REFRESH (IMSI changing procedure)

27.22.4.7.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.7.2.2 Conformance requirement

The ME shall support the REFRESH command as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.7, clause 6.4.7.1, clause 6, clause 6.6.13, clause 5.2, clause 8.6, clause 8.7 and clause 8.18.

Additionally the ME shall support the USIM Initialization and USIM application closure procedure as defined in:

- 3GPP TS 31.102 [14] clause 5.1.2 and Annex I.

#### 27.22.4.7.2.3 Test purpose

To verify that the ME performs the Proactive Command – REFRESH in accordance with the Command Qualifier and the IMSI changing procedure. This may require the ME to perform:

- the USIM initialization
- a re-read of the contents and structure of the IMSI on the USIM
- a restart of the card session
- a successful return of the result of the execution of the command in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.7.2.4 Method of test

##### 27.22.4.7.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table..

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ATT flag broadcast in the SYSTEM INFORMATION BLOCK TYPE 1 on the BCCH is set to "UEs shall apply IMSI attach and detach procedure" for Expected Sequences 2.2.

##### 27.22.4.7.2.4.2 Procedure

#### Expected Sequence 2.1 (REFRESH, UICC Reset for IMSI Changing procedure)

TBD

#### Expected Sequence 2.2 (REFRESH, USIM Application Reset for IMSI Changing procedure )

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: REFRESH 2.2.1	[To inform the ME that IMSI has changed]
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: REFRESH 2.2.1	
4	ME → UICC	STATUS[P1='02']	ME indicates to USIM that the termination procedure is starting Application termination
5	ME → UICC		
6	ME → USS	IMSI DETACH	
7	UICC	Update EF IMSI and EF LOCI	[Update the content of EF IMSI to "001010123456786", Temporary Mobile Subscriber Identity (TMSI) in EF LOCI be set to "FF FF FF FF"]
8	ME → UICC	SELECT AID=USIM (P2='0x')	Application selection
9	ME → UICC	USIM Initialization, including send STATUS[P1='01']	[ME performs USIM initialization]
10	ME → UICC	TERMINAL RESPONSE: REFRESH 2.2.1	[normal ending]
11	UICC → ME	PROACTIVE UICC SESSION ENDED	

## PROACTIVE COMMAND: REFRESH 2.2.1

Logically:

## Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Application Reset

## Device identities

Source device: UICC  
 Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	01	05	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

## TERMINAL RESPONSE: REFRESH 2.2.1

Logically:

## Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Application Reset

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	01	05	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 2.3 (REFRESH, 3G Session Reset for IMSI Changing procedure)**

TBD

**Expected Sequence 2.4 (REFRESH, reject 3G Session Reset for IMSI Changing procedure during call)**

Step	Direction	MESSAGE / Action	Comments
1	USER → ME	MO Call setup	
2	ME → USS	Call established and maintained	
3	UICC → ME	PROACTIVE COMMAND PENDING: REFRESH 2.4.1	
4	ME → UICC	FETCH	
5	UICC → ME	PROACTIVE COMMAND: REFRESH 2.4.1	
6	ME → UICC	TERMINAL RESPONSE: REFRESH 2.4.1A Or TERMINAL RESPONSE: REFRESH 2.4.1B	ME rejects REFRESH proactive command
7	UICC → ME	PROACTIVE UICC SESSION ENDED	Note: EF IMSI and EF LOCI are not updated by the UICC, see TS 31.111[15], cl. 6.4.7.1
8	USER → ME	The MO call is terminated	

## PROACTIVE COMMAND: REFRESH 2.4.1

Logically:

## Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: 3G Session Reset

## Device identities

Source device: UICC  
 Destination device: ME

## File list

Number of files: 2  
 File: EF IMSI  
 File: EF LOCI

## Coding:

BER-TLV:	D0	18	81	03	01	01	06	82	02	81	82	92
	0D	02	3F	00	7F	FF	6F	07	3F	00	7F	FF
	6F	7E										

## TERMINAL RESPONSE: REFRESH 2.4.1A

## Logically:

## Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: 3G Session Reset

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: ME currently unable to process command  
 Additional information on result: ME currently busy on call

## Coding:

BER-TLV:	81	03	01	01	06	82	02	82	81	83	02	20
	02											

## TERMINAL RESPONSE: REFRESH 2.4.1B

## Logically:

## Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: 3G Session Reset

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: ME currently unable to process command  
 Additional information on result: Screen is busy

## Coding:

BER-TLV:	81	03	01	01	06	82	02	82	81	83	02	20
	01											

#### 27.22.4.7.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.3.

### 27.22.4.8 SET UP MENU and ENVELOPE MENU SELECTION

#### 27.22.4.8.1 SET UP MENU (normal) and ENVELOPE MENU SELECTION

##### 27.22.4.8.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.1.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- 3GPP TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4.

The ME shall support MENU SELECTION as defined in:

- 3GPP TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.

##### 27.22.4.8.1.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user has indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

##### 27.22.4.8.1.4 Method of test

###### 27.22.4.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.8.1.4.2 Procedure

#### **Expected Sequence 1.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.1.4.2, Expected Sequence 1.1.

### Expected Sequence 1.2 (SET UP MENU, Large Menu with many items or with large items or with Large Alpha Identifier)

See ETSI TS 102 384 [26] in subclause 27.22.4.8.1.4.2, Expected Sequence 1.2.

The following table details the test requirements with relation to the tested features:

Proactive UICC Command Number	Proactive UICC Command Facilities		
	Alpha Identifier Length	Number of items	Maximum length of item
1.1.1	12	4	6
1.1.2	12	2	3
1.1.3	10	0	-
1.2.1	10	30	8
1.2.2	10	7	37
1.2.3	235	1	1

#### 27.22.4.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1 and in expected sequence 1.2.

#### 27.22.4.8.2 SET UP MENU (help request support) and ENVELOPE MENU SELECTION

##### 27.22.4.8.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.2.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP TS 31.111 [15] clause 8.21.

##### 27.22.4.8.2.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that when the help is available for the command and the user has indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

##### 27.22.4.8.2.4 Method of test

###### 27.22.4.8.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.8.2.4.2 Procedure

**Expected Sequence 2.1 (SET UP MENU and MENU SELECTION, with Help Request, Replace and Remove a Toolkit Menu)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.2.4.2, Expected Sequence 2.1.

## 27.22.4.8.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

## 27.22.4.8.3 SET UP MENU (next action support) and ENVELOPE MENU SELECTION

## 27.22.4.8.3.1 Definition and applicability

See clause 3.2.2.

If the UICC provides an Items Next Action Indicator data object, the comprehension required flag shall be set to '0'.

## 27.22.4.8.3.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP TS 31.111 [15] clause 8.24.

## 27.22.4.8.3.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the next action indicator is supported.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

## 27.22.4.8.3.4 Method of test

## 27.22.4.8.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.8.3.4.2 Procedure

**Expected Sequence 3.1 (SET UP MENU, next action indicator "Send SM", "Set Up Call", "Launch Browser", "Provide Local Information", successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.3.4.2, Expected Sequence 3.1.

## 27.22.4.8.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

#### 27.22.4.8.4 SET UP MENU (display of icons) and ENVELOPE MENU SELECTION

##### 27.22.4.8.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.4.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clause 6.5.4, 8.31 and 8.32.

##### 27.22.4.8.4.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that icons are displayed with the command Set Up Menu in the Alpha Identifier and Items Data Objects. To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

##### 27.22.4.8.4.4 Method of test

###### 27.22.4.8.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.8.4.4.2 Procedure

#### **Expected Sequence 4.1A (SET UP MENU, BASIC ICON NOT SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.1A.

#### **Expected Sequence 4.1B (SET UP MENU, BASIC ICON NOT SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.1B.

#### **Expected Sequence 4.2A (SET UP MENU, BASIC ICON SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.2A.

#### **Expected Sequence 4.2B (SET UP MENU, BASIC ICON SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.2B.

##### 27.22.4.8.4.5 Test requirement

The ME shall operate in the manner defined in expected sequences 4.1A to 4.2B.

#### 27.22.4.8.5 SET UP MENU (soft keys support) and ENVELOPE MENU SELECTION

##### 27.22.4.8.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.5.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1.

##### 27.22.4.8.5.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that if soft key preferred is indicated in the command details and soft key for SET UP MENU is supported by the ME and the number of icon items does not exceed the number of soft keys available, then the ME displays those icons as soft key.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

##### 27.22.4.8.5.4 Method of test

###### 27.22.4.8.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.8.5.4.2 Procedure

#### **Expected Sequence 5.1 (SET UP MENU, SOFT KEY PREFERRED, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.5.4.2, Expected Sequence 5.1.

##### 27.22.4.8.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

#### 27.22.4.8.6 SET UP MENU (support of Text Attribute) and ENVELOPE MENU SELECTION

##### 27.22.4.8.6.1 SET UP MENU (support of Text Attribute – Left Alignment) and ENVELOPE MENU SELECTION

###### 27.22.4.8.6.1.1 Definition and applicability

See clause 3.2.2.

###### 27.22.4.8.6.1.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.8.6.1.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the left alignment text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.1.4 Method of test

##### 27.22.4.8.6.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.6.1.4.2 Procedure

#### **Expected Sequence 6.1 (SET UP MENU, Text Attribute – Left Alignment, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.1.4.2, Expected Sequence 6.1.

##### 27.22.4.8.6.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

#### 27.22.4.8.6.2 SET UP MENU (support of Text Attribute – Center Alignment) and ENVELOPE MENU SELECTION

##### 27.22.4.8.6.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.6.2.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.8.6.2.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the center alignment text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

##### 27.22.4.8.6.2.4 Method of test

##### 27.22.4.8.6.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.8.6.2.4.2 Procedure

##### **Expected Sequence 6.2 (SET UP MENU, Text Attribute – Center Alignment, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.2.4.2, Expected Sequence 6.2.

#### 27.22.4.8.6.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.2.

#### 27.22.4.8.6.3 SET UP MENU (support of Text Attribute – Right Alignment) and ENVELOPE MENU SELECTION

##### 27.22.4.8.6.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.6.3.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.8.6.3.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the right alignment text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

##### 27.22.4.8.6.3.4 Method of test

###### 27.22.4.8.6.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.8.6.3.4.2 Procedure

##### **Expected Sequence 6.3 (SET UP MENU, Text Attribute – Right Alignment, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.3.4.2, Expected Sequence 6.3.

#### 27.22.4.8.6.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.3.

#### 27.22.4.8.6.4 SET UP MENU (support of Text Attribute – Large Font Size) and ENVELOPE MENU SELECTION

##### 27.22.4.8.6.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.6.4.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.8.6.4.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the large font size text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

##### 27.22.4.8.6.4.4 Method of test

###### 27.22.4.8.6.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.8.6.4.4.2 Procedure

#### **Expected Sequence 6.4 (SET UP MENU, Text Attribute – Large Font Size, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.4.4.2, Expected Sequence 6.4.

##### 27.22.4.8.6.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.4.

#### 27.22.4.8.6.5 SET UP MENU (support of Text Attribute – Small Font Size) and ENVELOPE MENU SELECTION

##### 27.22.4.8.6.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.6.5.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.8.6.5.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the with small font size text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.5.4 Method of test

##### 27.22.4.8.6.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.6.5.4.2 Procedure

#### **Expected Sequence 6.5 (SET UP MENU, Text Attribute – Small Font Size, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.5.4.2, Expected Sequence 6.5.

##### 27.22.4.8.6.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.5.

#### 27.22.4.8.6.6 SET UP MENU (support of Text Attribute – Bold On) and ENVELOPE MENU SELECTION

##### 27.22.4.8.6.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.6.6.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.8.6.6.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.6.4 Method of test

##### 27.22.4.8.6.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.8.6.6.4.2 Procedure

**Expected Sequence 6.6 (SET UP MENU, Text Attribute – Bold On, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.6.4.2, Expected Sequence 6.6.

## 27.22.4.8.6.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.6.

## 27.22.4.8.6.7 SET UP MENU (support of Text Attribute – Italic On) and ENVELOPE MENU SELECTION

## 27.22.4.8.6.7.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.8.6.7.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

## 27.22.4.8.6.7.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

## 27.22.4.8.6.7.4 Method of test

## 27.22.4.8.6.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.8.6.7.4.2 Procedure

**Expected Sequence 6.7 (SET UP MENU, Text Attribute – Italic On, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.7.4.2, Expected Sequence 6.7.

## 27.22.4.8.6.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.7.

## 27.22.4.8.6.8 SET UP MENU (support of Text Attribute – Underline On) and ENVELOPE MENU SELECTION

## 27.22.4.8.6.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.6.8.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.8.6.8.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.8.4 Method of test

##### 27.22.4.8.6.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.6.8.4.2 Procedure

#### **Expected Sequence 6.8 (SET UP MENU, Text Attribute – Underline On, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.8.4.2, Expected Sequence 6.8.

##### 27.22.4.8.6.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.8.

#### 27.22.4.8.6.9 SET UP MENU (support of Text Attribute – Strikethrough On) and ENVELOPE MENU SELECTION

##### 27.22.4.8.6.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.6.9.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.8.6.9.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.9.4 Method of test

27.22.4.8.6.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.6.9.4.2 Procedure

**Expected Sequence 6.9 (SET UP MENU, Text Attribute – Strikethrough On, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.9.4.2, Expected Sequence 6.9.

27.22.4.8.6.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.9.

27.22.4.8.6.10 SET UP MENU (support of Text Attribute – Foreground and Background Colour) and ENVELOPE MENU SELECTION

27.22.4.8.6.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.8.6.10.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.8.6.10.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.10.4 Method of test

27.22.4.8.6.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.6.10.4.2 Procedure

**Expected Sequence 6.10 (SET UP MENU, Text Attribute – Foreground and Background Colour, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.10.4.2, Expected Sequence 6.10.

## 27.22.4.8.6.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.10.

## 27.22.4.8.7 SET UP MENU (UCS2 display in Cyrillic) and ENVELOPE MENU SELECTION

## 27.22.4.8.7.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.8.7.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- 3GPP TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4.

The ME shall support MENU SELECTION as defined in:

- 3GPP TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.
- Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in ISO/IEC 10646 [17].

## 27.22.4.8.7.3 Test purpose

To verify that the ME correctly integrates the menu items in UCS2 coding contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user has indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

## 27.22.4.8.7.4 Method of test

## 27.22.4.8.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.8.7.4.2 Procedure

**Expected Sequence 7.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu, with UCS2 in Cyrillic Characters)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.7.4.2, Expected Sequence 7.1.

## 27.22.4.8.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

## 27.22.4.8.8 SET UP MENU (UCS2 display in Chinese) and ENVELOPE MENU SELECTION

## 27.22.4.8.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.8.8.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- 3GPP TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4

The ME shall support MENU SELECTION as defined in:

- 3GPP TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.
- Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in ISO/IEC 10646 [17].

## 27.22.4.8.8.3 Test purpose

To verify that the ME correctly integrates the menu items in UCS2 coding contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user has indicated the need to get help information on one of the items, the ME informs properly the UICC about a HELP REQUEST, using the MENU SELECTION mechanism.

## 27.22.4.8.8.4 Method of test

## 27.22.4.8.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.8.8.4.2 Procedure

**Expected Sequence 8.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu, with UCS2 – Chinese characters)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.8.4.2, Expected Sequence 8.1.

## 27.22.4.8.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

## 27.22.4.8.9 SET UP MENU (UCS2 display in Katakana) and ENVELOPE MENU SELECTION

## 27.22.4.8.9.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.8.9.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- 3GPP TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4.

The ME shall support MENU SELECTION as defined in:

- 3GPP TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.
- Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in ISO/IEC 10646 [17].

## 27.22.4.8.9.3 Test purpose

To verify that the ME correctly integrates the menu items in UCS2 coding contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user has indicated the need to get help information on one of the items, the ME informs properly the UICC about a HELP REQUEST, using the MENU SELECTION mechanism.

## 27.22.4.8.9.4 Method of test

## 27.22.4.8.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.8.9.4.2 Procedure

**Expected Sequence 9.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu, with UCS2 in Katakana Characters)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.9.4.2, Expected Sequence 9.1.

## 27.22.4.8.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

## 27.22.4.9 SELECT ITEM

## 27.22.4.9.1 SELECT ITEM (mandatory features for ME supporting SELECT ITEM)

## 27.22.4.9.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.9.1.2 Conformance requirement

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.

## 27.22.4.9.1.3 Test purpose

To verify that the ME correctly presents the set of items contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

## 27.22.4.9.1.4 Method of test

## 27.22.4.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.9.1.4.2 Procedure

**Expected Sequence 1.1 (SELECT ITEM, mandatory features, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (SELECT ITEM, large menu, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (SELECT ITEM, call options, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.3.

**Expected Sequence 1.4 (SELECT ITEM, backward move by user, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.4.

**Expected Sequence 1.5 (SELECT ITEM, "Y", successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.5.

**Expected Sequence 1.6 (SELECT ITEM, Large menu, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.6.

The following table details the test commands with relation to the tested features:

Proactive UICC Command SELECT ITEM Number	Proactive UICC Command Facilities		
	Alpha Identifier Length	Number of items	Maximum length of item
1.1	14	4	6
1.2	10	30	8
1.3	10	7	43
1.4	11	2	3
1.5	236	1	1
1.6	10	7	37

## 27.22.4.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1, 1.2, 1.3, 1.4, 1.5 and 1.6 (SELECT ITEM, mandatory features).

## 27.22.4.9.2 SELECT ITEM (next action support)

## 27.22.4.9.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.9.2.2 Conformance Requirement

Same as clause 27.22.4.9.1.2.

## 27.22.4.9.2.3 Test purpose

To verify that the mobile supports next action indicator mode.

## 27.22.4.9.2.4 Method of test

## 27.22.4.9.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.9.2.4.2 Procedure

**Expected Sequence 2.1 (SELECT ITEM, next action indicator, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.2.4.2, Expected Sequence 2.1.

## 27.22.4.9.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1

**27.22.4.9.3 SELECT ITEM (default item support)****27.22.4.9.3.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.9.3.2 Conformance requirement**

Same as clause 27.22.4.9.1.2.

**27.22.4.9.3.3 Test purpose**

To verify that the mobile supports "default item" mode.

**27.22.4.9.3.4 Method of test****27.22.4.9.3.4.1 Initial conditions**

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

**27.22.4.9.3.4.2 Procedure****Expected Sequence 3.1 (SELECT ITEM, default item, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.3.4.2, Expected Sequence 3.1.

**27.22.4.9.3.5 Test requirement**

The ME shall operate in the manner defined in expected sequence 3.1

**27.22.4.9.4 SELECT ITEM (help request support)****27.22.4.9.4.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.9.4.2 Conformance requirement**

Same as clause 27.22.4.9.1.2.

**27.22.4.9.4.3 Test purpose**

To verify that the mobile supports "help request" for the command Select Item.

**27.22.4.9.4.4 Method of test****27.22.4.9.4.4.1 Initial conditions**

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.4.4.2 Procedure

**Expected Sequence 4.1 (SELECT ITEM, help request, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.4.4.2, Expected Sequence 4.1.

27.22.4.9.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1

27.22.4.9.5 SELECT ITEM (icons support)

27.22.4.9.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.5.2 Conformance requirement

Same as clause 27.22.4.9.1.2 and 3GPP TS 31.111 [15] clause 8.31 and clause 8.32.

27.22.4.9.5.3 Test purpose

To verify that the mobile displays icons with the command Select Item.

27.22.4.9.5.4 Method of test

27.22.4.9.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.5.4.2 Procedure

**Expected Sequence 5.1A (SELECT ITEM, BASIC ICON NOT SELF EXPLANATORY, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.1A.

**Expected Sequence 5.1B (SELECT ITEM, BASIC ICON NOT SELF EXPLANATORY, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.1B.

**Expected Sequence 5.2A (SELECT ITEM, BASIC ICON SELF EXPLANATORY, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.2A.

**Expected Sequence 5.2B (SELECT ITEM, BASIC ICON SELF EXPLANATORY, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.2B.

27.22.4.9.5.5 Test requirement

The ME shall operate in the manner defined in expected sequences 5.1A to 5.2B.

#### 27.22.4.9.6 SELECT ITEM (presentation style)

##### 27.22.4.9.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.6.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

##### 27.22.4.9.6.3 Test purpose

To verify that the mobile supports the "presentation style" with the command Select Item.

##### 27.22.4.9.6.4 Method of test

###### 27.22.4.9.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.9.6.4.2 Procedure

#### **Expected Sequence 6.1 (SELECT ITEM, PRESENTATION AS A CHOICE OF NAVIGATION OPTIONS, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.6.4.2, Expected Sequence 6.1.

#### **Expected Sequence 6.2 (SELECT ITEM, PRESENTATION AS A CHOICE OF DATA VALUES, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.6.4.2, Expected Sequence 6.2.

##### 27.22.4.9.6.5 Test requirement

The ME shall operate in the manner defined in expected sequences 6.1 and 6.2.

#### 27.22.4.9.7 SELECT ITEM (soft keys support)

##### 27.22.4.9.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.7.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

##### 27.22.4.9.7.3 Test purpose

To verify that the mobile supports the "soft keys" with the command Select Item.

##### 27.22.4.9.7.4 Method of test

###### 27.22.4.9.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.7.4.2 Procedure

##### **Expected Sequence 7.1 (SELECT ITEM, SELECTING USING SOFT KEYS PREFERRED, successful, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.7.4.2, Expected Sequence 7.1.

#### 27.22.4.9.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

#### 27.22.4.9.8 SELECT ITEM (Support of "No response from user")

##### 27.22.4.9.8.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.8.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

##### 27.22.4.9.8.3 Test purpose

To verify that after a period of user inactivity the ME returns a "No response from user" result value in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.9.8.4 Method of test

###### 27.22.4.9.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME Manufacturer shall have defined the "no response from user" period of time as declared in table A.2/4.

The USIM Simulator shall be set to that period of time.

###### 27.22.4.9.8.4.2 Procedure

##### **Expected Sequence 8.1 (SELECT ITEM, no response from user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.8.4.2, Expected Sequence 8.1.

###### 27.22.4.9.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

#### 27.22.4.9.9 SELECT ITEM (Support of Text Attribute)

##### 27.22.4.9.9.1 SELECT ITEM (Support of Text Attribute – Left Alignment)

###### 27.22.4.9.9.1.1 Definition and applicability

See clause 3.2.2.

###### 27.22.4.9.9.1.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

###### 27.22.4.9.9.1.3 Test purpose

To verify that the ME displays text formatted according to the left alignment text attribute configuration within the command Select Item.

###### 27.22.4.9.9.1.4 Method of test

###### 27.22.4.9.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.9.9.1.4.2 Procedure

#### **Expected Sequence 9.1 (SELECT ITEM, Text Attribute – Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.1.4.2, Expected Sequence 9.1.

###### 27.22.4.9.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

#### 27.22.4.9.9.2 SELECT ITEM (Support of Text Attribute – Center Alignment)

##### 27.22.4.9.9.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.9.2.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.9.9.2.3 Test purpose

To verify that the ME displays text formatted according to the center alignment text attribute configuration within the command Select Item.

27.22.4.9.9.2.4 Method of test

27.22.4.9.9.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.2.4.2 Procedure

#### **Expected Sequence 9.2 (SELECT ITEM, Text Attribute – Center Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.2.4.2, Expected Sequence 9.2.

27.22.4.9.9.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.2.

27.22.4.9.9.3 SELECT ITEM (Support of Text Attribute – Right Alignment)

27.22.4.9.9.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.3.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.3.3 Test purpose

To verify that the ME displays text formatted according to the right alignment text attribute configuration within the command Select Item.

27.22.4.9.9.3.4 Method of test

27.22.4.9.9.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.3.4.2 Procedure

#### **Expected Sequence 9.3 (SELECT ITEM, Text Attribute – Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.3.4.2, Expected Sequence 9.3.

27.22.4.9.9.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.3.

#### 27.22.4.9.9.4 SELECT ITEM (Support of Text Attribute – Large Font Size)

##### 27.22.4.9.9.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.9.4.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.9.9.4.3 Test purpose

To verify that the ME displays text formatted according to the large font size text attribute configuration within the command Select Item.

##### 27.22.4.9.9.4.4 Method of test

###### 27.22.4.9.9.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.9.9.4.4.2 Procedure

#### **Expected Sequence 9.4 (SELECT ITEM, Text Attribute – Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.4.4.2, Expected Sequence 9.4.

##### 27.22.4.9.9.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.4.

#### 27.22.4.9.9.5 SELECT ITEM (Support of Text Attribute – Small Font Size)

##### 27.22.4.9.9.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.9.5.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.9.9.5.3 Test purpose

To verify that the ME displays text formatted according to the small font size text attribute configuration within the command Select Item.

##### 27.22.4.9.9.5.4 Method of test

###### 27.22.4.9.9.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.9.5.4.2 Procedure

##### **Expected Sequence 9.5 (SELECT ITEM, Text Attribute – Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.5.4.2, Expected Sequence 9.5.

#### 27.22.4.9.9.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.5.

#### 27.22.4.9.9.6 SELECT ITEM (Support of Text Attribute – Bold On)

##### 27.22.4.9.9.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.9.6.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.9.9.6.3 Test purpose

To verify that the ME displays text formatted according to the bold text attribute configuration within the command Select Item.

##### 27.22.4.9.9.6.4 Method of test

###### 27.22.4.9.9.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.9.6.4.2 Procedure

##### **Expected Sequence 9.6 (SELECT ITEM, Text Attribute – Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.6.4.2, Expected Sequence 9.6.

#### 27.22.4.9.9.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.6.

#### 27.22.4.9.9.7 SELECT ITEM (Support of Text Attribute – Italic On)

##### 27.22.4.9.9.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.9.7.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.9.9.7.3 Test purpose

To verify that the ME displays text formatted according to the italic text attribute configuration within the command Select Item.

#### 27.22.4.9.9.7.4 Method of test

##### 27.22.4.9.9.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.9.9.7.4.2 Procedure

#### **Expected Sequence 9.7 (SELECT ITEM, Text Attribute – Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.7.4.2, Expected Sequence 9.7.

##### 27.22.4.9.9.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.7.

#### 27.22.4.9.9.8 SELECT ITEM (Support of Text Attribute – Underline On)

##### 27.22.4.9.9.8.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.9.8.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.9.9.8.3 Test purpose

To verify that the ME displays text formatted according to the underline text attribute configuration within the command Select Item.

##### 27.22.4.9.9.8.4 Method of test

##### 27.22.4.9.9.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.9.9.8.4.2 Procedure

#### **Expected Sequence 9.8 (SELECT ITEM, Text Attribute – Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.8.4.2, Expected Sequence 9.8.

##### 27.22.4.9.9.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.8.

27.22.4.9.9.9           SELECT ITEM (Support of Text Attribute – Strikethrough On)

27.22.4.9.9.9.1       Definition and applicability

See clause 3.2.2.

27.22.4.9.9.9.2       Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.9.3       Test purpose

To verify that the ME displays text formatted according to the strikethrough text attribute configuration within the command Select Item.

27.22.4.9.9.9.4       Method of test

27.22.4.9.9.9.4.1     Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.9.4.2     Procedure

#### **Expected Sequence 9.9 (SELECT ITEM, Text Attribute – Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.4.2, Expected Sequence 9.9.

27.22.4.9.9.9.5       Test requirement

The ME shall operate in the manner defined in expected sequence 9.9.

27.22.4.9.9.10        SELECT ITEM (Support of Text Attribute – Foreground and Background Colour)

27.22.4.9.9.10.1     Definition and applicability

See clause 3.2.2.

27.22.4.9.9.10.2     Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.10.3     Test purpose

To verify that the ME displays text formatted according to the foreground and background colour text attribute configuration within the command Select Item.

27.22.4.9.9.10.4     Method of test

27.22.4.9.9.10.4.1   Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.9.10.4.2 Procedure

##### **Expected Sequence 9.10 (SELECT ITEM, Text Attribute – Foreground and Background Colour)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.10.4.2, Expected Sequence 9.10.

#### 27.22.4.9.9.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.10.

#### 27.22.4.9.10 SELECT ITEM (UCS2 display in Cyrillic)

##### 27.22.4.9.10.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.10.2 Conformance requirement

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.
- Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic characters, as defined in ISO/IEC 10646 [17].

##### 27.22.4.9.10.3 Test purpose

To verify that the ME correctly presents the set of items in UCS2 coding contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

##### 27.22.4.9.10.4 Method of test

###### 27.22.4.9.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.10.4.2 Procedure

##### **Expected Sequence 10.1 (SELECT ITEM with UCS2 in Cyrillic characters, 0x80 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.10.4.2, Expected Sequence 10.1.

**Expected Sequence 10.2 (SELECT ITEM with UCS2 in Cyrillic characters, 0x81 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.10.4.2, Expected Sequence 10.2.

**Expected Sequence 10.3 (SELECT ITEM with UCS2 in Cyrillic characters, 0x82 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.10.4.2, Expected Sequence 10.3.

**27.22.4.9.10.5 Test requirement**

The ME shall operate in the manner defined in expected sequences 10.1 to 10.3.

**27.22.4.9.11 SELECT ITEM (UCS2 display in Chinese)****27.22.4.9.11.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.9.11.2 Conformance requirement**

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.
- Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in ISO/IEC 10646 [17].

**27.22.4.9.11.3 Test purpose**

To verify that the ME correctly presents the set of items in UCS2 coding contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

**27.22.4.9.11.4 Method of test****27.22.4.9.11.4.1 Initial conditions**

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

**27.22.4.9.11.4.2 Procedure****Expected Sequence 11.1 (SELECT ITEM with UCS2 in Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.11.4.2, Expected Sequence 11.1.

## 27.22.4.9.11.5 Test requirement

The ME shall operate in the manner defined in expected sequence 11.1.

## 27.22.4.9.12 SELECT ITEM (UCS2 display in Katakana)

## 27.22.4.9.12.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.9.12.2 Conformance requirement

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.
- Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in ISO/IEC 10646 [17].

## 27.22.4.9.12.3 Test purpose

To verify that the ME correctly presents the set of items in UCS2 coding contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

## 27.22.4.9.12.4 Method of test

## 27.22.4.9.12.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.9.12.4.2 Procedure

**Expected Sequence 12.1 (SELECT ITEM with UCS2 in Katakana characters, 0x80 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.12.4.2, Expected Sequence 12.1.

**Expected Sequence 12.2 (SELECT ITEM with UCS2 - Katakana characters, 0x81 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.12.4.2, Expected Sequence 12.2.

**Expected Sequence 12.3 (SELECT ITEM with UCS2 - Katakana characters, 0x82 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.12.4.2, Expected Sequence 12.3.

## 27.22.4.9.12.5 Test requirement

The ME shall operate in the manner defined in expected sequences 12.1 to 12.3.

## 27.22.4.10 SEND SHORT MESSAGE

## 27.22.4.10.1 SEND SHORT MESSAGE (normal)

## 27.22.4.10.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.10.1.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

## 27.22.4.10.1.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

## 27.22.4.10.1.4 Method of test

## 27.22.4.10.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.1.4.2 Procedure

**Expected Sequence 1.1 (SEND SHORT MESSAGE, packing not required, 8-bit data, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1	[packing not required, 8-bit data]
4	ME → USER	Display "Send SM"	[Alpha Identifier]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 1.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send SM"

Address

TON: International number

NPI: "ISDN / telephone numbering plan"

Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8-bit data

Message class class 0

TP-UDL 12

TP-UD "Test Message"

Coding:

BER-TLV:	D0	37	81	03	01	13	00	82	02	81	83	85
	07	53	65	6E	64	20	53	4D	86	09	91	11
	22	33	44	55	66	77	F8	8B	18	01	00	09
	91	10	32	54	76	F8	40	F4	0C	54	65	73
	74	20	4D	65	73	73	61	67	65			

SMS-PP (SEND SHORT MESSAGE) Message 1.1

Logically:

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345678"

TP-PID Short message type 0

TP-DCS

Message coding 8-bit data

Message class class 0

TP-UDL 12

TP-UD "Test Message"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.2 (SEND SHORT MESSAGE, packing required, 8-bit data, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.2.1	[packing required, 8-bit data]
4	ME → USER	Display "Send SM"	[Alpha Identifier]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 1.2	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.2.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.2.1

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing required

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Send SM"

Address

TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS

Message coding 8-bit data  
 Message class class 0  
 TP-UDL 7  
 TP-UD "Send SM"

Coding:

BER-TLV:	D0	32	81	03	01	13	01	82	02	81	83	85
	07	53	65	6E	64	20	53	4D	86	09	91	11
	22	33	44	55	66	77	F8	8B	13	01	00	09
	91	10	32	54	76	F8	40	F4	07	53	65	6E
	64	20	53	4D								

SMS-PP (SEND SHORT MESSAGE) Message 1.2

Logically:

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "01"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 7  
 TP-UD "Send SM"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F0	07
	D3	B2	9B	0C	9A	36	01					

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.2.1

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing required

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	01	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.3 (SEND SHORT MESSAGE, packing not required, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.3.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Short Message"	[Alpha Identifier]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 1.3	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.3.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.3.1

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Short Message"

Address

TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 13  
 TP-UD "Short Message"

Coding:

BER-TLV:	D0	3D	81	03	01	13	00	82	02	81	83	85
	0D	53	68	6F	72	74	20	4D	65	73	73	61
	67	65	86	09	91	11	22	33	44	55	66	77
	F8	8B	18	01	00	09	91	10	32	54	76	F8
	40	F0	0D	53	F4	5B	4E	07	35	CB	F3	79
	F8	5C	06									

SMS-PP (SEND SHORT MESSAGE) Message 1.3

Logically:

SMS TPDU

TP-MTI	SMS-SUBMIT
TP-RD	Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF	TP-VP field not present
TP-RP	TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI	The TP-UD field contains only the short message
TP-SRR	A status report is not requested
TP-MR	"01"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"012345678"
TP-PID	Short message type 0
TP-DCS	
Message coding	SMS default alphabet
Message class	class 0
TP-UDL	13
TP-UD	"Short Message"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F0	0D
	53	F4	5B	4E	07	35	CB	F3	79	F8	5C	06

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.3.1

Logically:

Command details

Command number:	1
Command type:	SEND SHORT MESSAGE
Command qualifier:	packing not required

Device identities

Source device:	ME
Destination device:	UICC

Result

General Result:	Command performed successfully
-----------------	--------------------------------

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.4 (SEND SHORT MESSAGE, packing required, 8 bit data, message of 160 characters user data, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.4. 1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.4.1	[packing required, 8 bit data]
4	ME → USER	Display "The address data object holds the RP_Destination_Address "	[Alpha Identifier]
5	ME → USS	Send SMS-PP(SEND SHORT MESSAGE) Message 1.4	[message of 140 bytes user data]
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.4.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND SHORT MESSAGE 1.4.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing required

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "The address data object holds the RP\_Destination\_Address"

## Address

TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

## SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 8 bit data  
 Message class class 0  
 TP-UDL 160  
 TP-UD "Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transp"

Coding:

BER-TLV:	D0	81	FD	81	03	01	13	01	82	02	81	83
	85	38	54	68	65	20	61	64	64	72	65	73
	73	20	64	61	74	61	20	6F	62	6A	65	63
	74	20	68	6F	6C	64	73	20	74	68	65	20
	52	50	11	44	65	73	74	69	6E	61	74	69
	6F	6E	11	41	64	64	72	65	73	73	86	09
	91	11	22	33	44	55	66	77	F8	8B	81	AC
	01	00	09	91	10	32	54	76	F8	40	F4	A0
	54	77	6F	20	74	79	70	65	73	20	61	72
	65	20	64	65	66	69	6E	65	64	3A	20	2D
	20	41	20	73	68	6F	72	74	20	6D	65	73
	73	61	67	65	20	74	6F	20	62	65	20	73
	65	6E	74	20	74	6F	20	74	68	65	20	6E
	65	74	77	6F	72	6B	20	69	6E	20	61	6E
	20	53	4D	53	2D	53	55	42	4D	49	54	20
	6D	65	73	73	61	67	65	2C	20	6F	72	20
	61	6E	20	53	4D	53	2D	43	4F	4D	4D	41
	4E	44	20	6D	65	73	73	61	67	65	2C	20
	77	68	65	72	65	20	74	68	65	20	75	73
	65	72	20	64	61	74	61	20	63	61	6E	20
	62	65	20	70	61	73	73	65	64	20	74	72
	61	6E	73	70								

SMS-PP (SEND SHORT MESSAGE) Message 1.4

Logically:

SMS TPDU

TP-MTI	SMS-SUBMIT
TP-RD	Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF	TP-VP field not present
TP-RP	TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI	The TP-UD field contains only the short message
TP-SRR	A status report is not requested
TP-MR	"01"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"012345678"
TP-PID	Short message type 0
TP-DCS	
Message coding	SMS default alphabet
Message class	class 0
TP-UDL	160
TP-UD	"Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transp"

Coding:

Coding		01	01	09	91	10	32	54	76	F8	40	F0
	A0	D4	FB	1B	44	CF	C3	CB	73	50	58	5E
	06	91	CB	E6	B4	BB	4C	D6	81	5A	A0	20
	68	8E	7E	CB	E9	A0	76	79	3E	0F	9F	CB
	20	FA	1B	24	2E	83	E6	65	37	1D	44	7F
	83	E8	E8	32	C8	5D	A6	DF	DF	F2	35	28
	ED	06	85	DD	A0	69	73	DA	9A	56	85	CD
	24	15	D4	2E	CF	E7	E1	73	99	05	7A	CB
	41	61	37	68	DA	9C	B6	86	CF	66	33	E8
	24	82	DA	E5	F9	3C	7C	2E	B3	40	77	74
	59	5E	06	D1	D1	65	50	7D	5E	96	83	C8
	61	7A	18	34	0E	BB	41	E2	32	08	1E	9E
	CF	CB	64	10	5D	1E	76	CF	E1			

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.4.1

Logically:

Command details

Command number:	1
Command type:	SEND SHORT MESSAGE
Command qualifier:	packing required

Device identities

Source device:	ME
Destination device:	UICC

Result

General Result:	Command performed successfully
-----------------	--------------------------------

Coding:

BER-TLV:	81	03	01	13	01	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.5 (SEND SHORT MESSAGE, packing not required, SMS default alphabet, message of 160 characters user data, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.5.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "The address data object holds the RP Destination Address "	[Alpha Identifier]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 1.5	[message of 140 bytes user data]
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.5.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.5.1

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "The address data object holds the RP Destination Address"

Address

TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 160  
 TP-UD "Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transp"

Coding:

BER-TLV:	D0	81	E9	81	03	01	13	00	82	02	81	83
	85	38	54	68	65	20	61	64	64	72	65	73
	73	20	64	61	74	61	20	6F	62	6A	65	63
	74	20	68	6F	6C	64	73	20	74	68	65	20
	52	50	20	44	65	73	74	69	6E	61	74	69
	6F	6E	20	41	64	64	72	65	73	73	86	09
	91	11	22	33	44	55	66	77	F8	8B	81	98
	01	00	09	91	10	32	54	76	F8	40	F0	A0
	D4	FB	1B	44	CF	C3	CB	73	50	58	5E	06
	91	CB	E6	B4	BB	4C	D6	81	5A	A0	20	68
	8E	7E	CB	E9	A0	76	79	3E	0F	9F	CB	20
	FA	1B	24	2E	83	E6	65	37	1D	44	7F	83
	E8	E8	32	C8	5D	A6	DF	DF	F2	35	28	ED
	06	85	DD	A0	69	73	DA	9A	56	85	CD	24
	15	D4	2E	CF	E7	E1	73	99	05	7A	CB	41
	61	37	68	DA	9C	B6	86	CF	66	33	E8	24
	82	DA	E5	F9	3C	7C	2E	B3	40	77	74	59
	5E	06	D1	D1	65	50	7D	5E	96	83	C8	61
	7A	18	34	0E	BB	41	E2	32	08	1E	9E	CF
	CB	64	10	5D	1E	76	CF	E1				

## SMS-PP (SEND SHORT MESSAGE) Message 1.5

Logically:

## SMS TPDU

TP-MTI	SMS-SUBMIT
TP-RD	Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF	TP-VP field not present
TP-RP	TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI	The TP-UD field contains only the short message
TP-SRR	A status report is not requested
TP-MR	"01"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"012345678"
TP-PID	Short message type 0
TP-DCS	
Message coding	SMS default alphabet
Message class	class 0
TP-UDL	160
TP-UD	"Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transp"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F0	A0
	D4	FB	1B	44	CF	C3	CB	73	50	58	5E	06
	91	CB	E6	B4	BB	4C	D6	81	5A	A0	20	68
	8E	7E	CB	E9	A0	76	79	3E	0F	9F	CB	20
	FA	1B	24	2E	83	E6	65	37	1D	44	7F	83
	E8	E8	32	C8	5D	A6	DF	DF	F2	35	28	ED
	06	85	DD	A0	69	73	DA	9A	56	85	CD	24
	15	D4	2E	CF	E7	E1	73	99	05	7A	CB	41
	61	37	68	DA	9C	B6	86	CF	66	33	E8	24
	82	DA	E5	F9	3C	7C	2E	B3	40	77	74	59
	5E	06	D1	D1	65	50	7D	5E	96	83	C8	61
	7A	18	34	0E	BB	41	E2	32	08	1E	9E	CF
	CB	64	10	5D	1E	76	CF	E1				

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.5.1

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.6 (SEND SHORT MESSAGE, alpha identifier 160 bytes long, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.6.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transparently; - A short message to be sent to the network in an SMS-SUBMIT "	[Alpha Identifier of 160 bytes]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 1.6	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.6.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.6.1

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transparently; - A short message to be sent to the network in an SMS-SUBMIT"

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"

TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "

Coding:

BER-TLV:	D0	81	FD	81	03	01	13	00	82	02	81	83
	85	81	E6	54	77	6F	20	74	79	70	65	73
	20	61	72	65	20	64	65	66	69	6E	65	64
	3A	20	2D	20	41	20	73	68	6F	72	74	20
	6D	65	73	73	61	67	65	20	74	6F	20	62
	65	20	73	65	6E	74	20	74	6F	20	74	68
	65	20	6E	65	74	77	6F	72	6B	20	69	6E
	20	61	6E	20	53	4D	53	2D	53	55	42	4D
	49	54	20	6D	65	73	73	61	67	65	2C	20
	6F	72	20	61	6E	20	53	4D	53	2D	43	4F
	4D	4D	41	4E	44	20	6D	65	73	73	61	67
	65	2C	20	77	68	65	72	65	20	74	68	65
	20	75	73	65	72	20	64	61	74	61	20	63
	61	6 <sup>E</sup>	20	62	65	20	70	61	73	73	65	64
	20	74	72	61	6E	73	70	61	72	65	6E	74
	6C	79	3B	20	2D	20	41	20	73	68	6F	72
	74	20	6D	65	73	73	61	67	65	20	74	6F
	20	62	65	20	73	65	6E	74	20	74	6F	20
	74	68	65	20	6E	65	74	77	6F	72	6B	20
	69	6E	20	61	6E	20	53	4D	53	2D	53	55
	42	4D	49	54	20	8B	09	01	00	02	91	10
	40	F0	01	20								

SMS-PP (SEND SHORT MESSAGE) Message 1.6

Logically:

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "01"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "

Coding:

Coding	01	01	02	91	10	40	F0	01	20
--------	----	----	----	----	----	----	----	----	----

## TERMINAL RESPONSE: SEND SHORT MESSAGE 1.6.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.7(SEND SHORT MESSAGE, alpha identifier length '00', packing not required, 8-bit data, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.7.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.7.1	[packing not required, 8-bit data]
4	ME	No information to user	[Alpha identifier length '00']
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 1.7	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.7.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND SHORT MESSAGE 1.7.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier:

## Address

TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

## SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number

NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 8-bit data  
 Message class class 0  
 TP-UDL 12  
 TP-UD "Test Message"

Coding:

BER-TLV:	D0	30	81	03	01	13	00	82	02	81	83	85
	00	86	09	91	11	22	33	44	55	66	77	F8
	8B	18	01	00	09	91	10	32	54	76	F8	40
	F4	0C	54	65	73	74	20	4D	65	73	73	61
	67	65										

SMS-PP (SEND SHORT MESSAGE) Message 1.7

Logically:

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "01"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 8-bit data  
 Message class class 0  
 TP-UDL 12  
 TP-UD "Test Message"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.7.1

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.8 (SEND SHORT MESSAGE, packing not required, 8-bit data, no alpha identifier, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.8.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.8.1	[packing not required, 8-bit data]
4	ME → USER	May give information to user concerning what is happening	[No Alpha Identifier]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 1.8	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.8.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.8.1

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: UICC  
 Destination device: Network

Address

TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 8-bit data  
 Message class class 0  
 TP-UDL 12  
 TP-UD "Test Message"

Coding:

BER-TLV:	D0	2E	81	03	01	13	00	82	02	81	83	86
	09	91	11	22	33	44	55	66	77	F8	8B	18
	01	00	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

SMS-PP (SEND SHORT MESSAGE) Message 1.8

Logically:

SMS TPDU	
TP-MTI	SMS-SUBMIT
TP-RD	Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF	TP-VP field not present
TP-RP	TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI	The TP-UD field contains only the short message
TP-SRR	A status report is not requested
TP-MR	"01"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"012345678"
TP-PID	Short message type 0
TP-DCS	
Message coding	8-bit data
Message class	class 0
TP-UDL	12
TP-UD	"Test Message"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.8.1

Logically:

Command details	
Command number:	1
Command type:	SEND SHORT MESSAGE
Command qualifier:	packing not required
Device identities	
Source device:	ME
Destination device:	UICC
Result	
General Result:	Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.10.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.8.

27.22.4.10.2 SEND SHORT MESSAGE (UCS2 display in Cyrillic)

27.22.4.10.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.10.2.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

Additionally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

## 27.22.4.10.2.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

## 27.22.4.10.2.4 Method of test

## 27.22.4.10.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.2.4.2 Procedure

**Expected Sequence 2.1 (SEND SHORT MESSAGE, packing not required, UCS2 (16-bit data in Cyrillic))**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 2.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 2.1.1	[packing not required, 16-bit data]
4	ME → USER	Display "ЗДРАВСТВУЙТЕ"	[Alpha Identifier] "Hello" in Russian, 0x80 coding of UCS2 format Cyrillic
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 2.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 2.1.1	[Command performed successfully]
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 2.1.2	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND SEND SHORT MESSAGE 2.1.2	
12	ME → USER	Display "ЗДРАВСТВУЙТЕ"	[Alpha Identifier] "Hello" in Russian, 0x81 coding of UCS2 format
13	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 2.1	
14	USS → ME	SMS RP-ACK	

15	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 2.1.1	[Command performed successfully]
16	UICC → ME	PROACTIVE UICC SESSION ENDED	
17	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 2.1.3	
18	ME → UICC	FETCH	
19	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 2.1.3	[UCS2 alphabet]
20	ME → USER	Display "ЗДРАВСТВУЙТЕ"	[Alpha Identifier] "Hello" in Russian, 0x82 coding of UCS2 format
21	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 2.1	
22	USS → ME	SMS RP-ACK	
23	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 2.1.1	[Command performed successfully]
24	UICC → ME	PROACTIVE UICC SESSION ENDED	

#### PROACTIVE COMMAND: SEND SHORT MESSAGE: 2.1.1

Logically:

##### Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

##### Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ"

##### Address

TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

##### SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 16-bit data  
 Message class class 0  
 TP-UDL 24  
 TP-UD "ЗДРАВСТВУЙТЕ"

Coding:

BER-TLV:	D0	55	81	03	01	13	00	82	02	81	83	85
	19	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	86	09	91	11	22	33	44	55	66	77
	F8	8B	24	01	00	09	91	10	32	54	76	F8
	40	08	18	04	17	04	14	04	20	04	10	04
	12	04	21	04	22	04	12	04	23	04	19	04
	22	04	15									

## SMS-PP (SEND SHORT MESSAGE) Message 2.1

Logically:

## SMS TPDU

TP-MTI	SMS-SUBMIT
TP-RD	Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF	TP-VP field not present
TP-RP	TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI	The TP-UD field contains only the short message
TP-SRR	A status report is not requested
TP-MR	"01"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"012345678"
TP-PID	Short message type 0
TP-DCS	
Message coding	UCS2 (16-bit data)
Message class	class 0
TP-UDL	24
TP-UD	"ЗДРАВСТВУЙТЕ"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	08	18
	04	17	04	14	04	20	04	10	04	12	04	21
	04	22	04	12	04	23	04	19	04	22	04	15

## PROACTIVE COMMAND: SEND SHORT MESSAGE: 2.1.2

Logically:

## Command details

Command number:	1
Command type:	SEND SHORT MESSAGE
Command qualifier:	packing not required

## Device identities

Source device:	UICC
Destination device:	Network

Alpha identifier: "ЗДРАВСТВУЙТЕ"

## Address

TON:	International number
NPI:	"ISDN / telephone numbering plan"
Dialling number string	"112233445566778"

## SMS TPDU

TP-MTI	SMS-SUBMIT
TP-RD	Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF	TP-VP field not present
TP-RP	TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI	The TP-UD field contains only the short message

TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 16-bit data  
 Message class class 0  
 TP-UDL 24  
 TP-UD "ЗДРАВСТВУЙТЕ"

Coding:

BER-TLV:	D0	4B	81	03	01	13	00	82	02	81	83	85
	0F	81	0C	08	97	94	A0	90	92	A1	A2	92
	A3	99	A2	95	86	09	91	11	22	33	44	55
	66	77	F8	8B	24	01	00	09	91	10	32	54
	76	F8	40	08	18	04	17	04	14	04	20	04
	10	04	12	04	21	04	22	04	12	04	23	04
	19	04	22	04	15							

PROACTIVE COMMAND: SEND SHORT MESSAGE: 2.1.3

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ"

Address

TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 16-bit data  
 Message class class 0  
 TP-UDL 24  
 TP-UD "ЗДРАВСТВУЙТЕ"

Coding:

BER-TLV:	D0	4C	81	03	01	13	00	82	02	81	83	85
	10	82	0C	04	10	87	84	90	80	82	91	92
	82	93	89	92	85	86	09	91	11	22	33	44
	55	66	77	F8	8B	24	01	00	09	91	10	32
	54	76	F8	40	08	18	04	17	04	14	04	20
	04	10	04	12	04	21	04	22	04	12	04	23
	04	19	04	22	04	15						

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 2.1.1

Logically:

##### Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

##### Device identities

Source device: ME  
 Destination device: UICC

##### Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.10.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

#### 27.22.4.10.3 SEND SHORT MESSAGE (icon support)

##### 27.22.4.10.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.10.3.2 Conformance requirement

##### 27.22.4.10.3.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

##### 27.22.4.10.3.4 Method of test

##### 27.22.4.10.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

## 27.22.4.10.3.4.2 Procedure

**Expected Sequence 3.1A (SEND SHORT MESSAGE, basic icon self-explanatory, packing not required, 8-bit data, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 3.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 3.1.1	[packing not required, 8-bit data]
4	ME → USER	Displays the icon and not the alpha identifier	[basic icon self-explanatory]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 3.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 3.1.1A	[Command performed successfully]

## PROACTIVE COMMAND: SEND SHORT MESSAGE 3.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "NO ICON"

## Address

TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

## SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 8bit-data  
 Message class class 0  
 TP-UDL 12  
 TP-UD "Test Message"

## Icon Identifier

Icon Qualifier self-explanatory  
 Icon Identifier 1 (number of record in EF IMG)

Coding:

BER-TLV:	D0	3B	81	03	01	13	00	82	02	81	83	85
	07	4E	4F	20	49	43	4F	4E	86	09	91	11
	22	33	44	55	66	77	F8	8B	18	01	00	09
	91	10	32	54	76	F8	40	F4	0C	54	65	73
	74	20	4D	65	73	73	61	67	65	9E	02	00
	01											

## SMS-PP (SEND SHORT MESSAGE) Message 3.1

Logically:

## SMS TPDU

TP-MTI	SMS-SUBMIT
TP-RD	Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF	TP-VP field not present
TP-RP	TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI	The TP-UD field contains only the short message
TP-SRR	A status report is not requested
TP-MR	"01"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"012345678"
TP-PID	Short message type 0
TP-DCS	
Message coding	8-bit data
Message class	class 0
TP-UDL	12
TP-UD	"Test Message"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

## TERMINAL RESPONSE: SEND SHORT MESSAGE 3.1.1A

Logically:

## Command details

Command number:	1
Command type:	SEND SHORT MESSAGE
Command qualifier:	packing not required

## Device identities

Source device:	ME
Destination device:	UICC

## Result

General Result:	Command performed successfully
-----------------	--------------------------------

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 3.1B (SEND SHORT MESSAGE, basic icon self-explanatory, packing not required, 8-bit data, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 3.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 3.1.1	[packing not required, 8-bit data, basic icon self-explanatory]]
4	ME → USER	Displays the alpha identifier without the icon	
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 3.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 3.1.1B	[Command performed successfully, but requested icon could not be displayed]

TERMINAL RESPONSE: SEND SHORT MESSAGE 3.1.1B

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	04
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 3.2A (SEND SHORT MESSAGE, basic icon non-self-explanatory, packing not required, 8-bit data, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 3.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 3.2.1	[packing not required, 8-bit data]
4	ME → USER	display the icon and "Send SM"	[basic icon non-self-explanatory]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 3.2	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 3.2.1A	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 3.2.1

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network  
 Alpha Identifier "Send SM"  
 Address  
 TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"  
 SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 8bit-data  
 Message class class 0  
 TP-UDL 12  
 TP-UD "Test Message"  
 Icon Identifier  
 Icon Qualifier non-self-explanatory  
 Icon Identifier 1 (number of record in EF IMG)

Coding:

BER-TLV:	D0	3B	81	03	01	13	00	82	02	81	83	85
	07	53	65	6E	64	20	53	4D	86	09	91	11
	22	33	44	55	66	77	F8	8B	18	01	00	09
	91	10	32	54	76	F8	40	F4	0C	54	65	73
	74	20	4D	65	73	73	61	67	65	1E	02	01
	01											

SMS-PP (SEND SHORT MESSAGE) Message 3.2

Logically:

SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "01"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 8-bit data  
 Message class class 0  
 TP-UDL 12  
 TP-UD "Test Message"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

TERMINAL RESPONSE: SEND SHORT MESSAGE 3.2.1A

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 3.2B (SEND SHORT MESSAGE, basic icon non-self-explanatory, packing not required, 8-bit data, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 3.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 3.2.1	[packing not required, 8-bit data, basic icon non-self-explanatory ]
4	ME → USER	display "Send SM" without the icon	
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 3.2	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 3.2.1B	[Command performed successfully, but requested icon could not be displayed]

TERMINAL RESPONSE: SEND SHORT MESSAGE 3.2.1B

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed;

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	04
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.10.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1A to 3.2B.

#### 27.22.4.10.4 SEND SHORT MESSAGE (Support of Text Attribute)

##### 27.22.4.10.4.1 SEND SHORT MESSAGE (Support of Text Attribute – Left Alignment)

###### 27.22.4.10.4.1.1 Definition and applicability

See clause 3.2.2.

###### 27.22.4.10.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

###### 27.22.4.10.4.1.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the left alignment text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

###### 27.22.4.10.4.1.4 Method of test

###### 27.22.4.10.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.4.1.4.2 Procedure

**Expected Sequence 4.1 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Left Alignment, packing not required, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with left alignment]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.1.1	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.1.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.2	[packing not required, SMS default alphabet]
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/11, no alignment change will take place]
12	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.1.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

## SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1

TP-UD " "

Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.2

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier:

"Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class class 0

TP-UDL 1

TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20								

SMS-PP (SEND SHORT MESSAGE) Message 4.1

Logically:

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR	A status report is not requested
TP-MR	"01"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"01"
TP-PID	Short message type 0
TP-DCS	
Message coding	SMS default alphabet
Message class	class 0
TP-UDL	1
TP-UD	" "

Coding:

Coding	01	01	02	91	10	40	F0	01	20
--------	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.1.1

Logically:

Command details

Command number:	1
Command type:	SEND SHORT MESSAGE
Command qualifier:	packing not required

Device identities

Source device:	ME
Destination device:	UICC

Result

General Result:	Command performed successfully
-----------------	--------------------------------

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.10.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

27.22.4.10.4.2 SEND SHORT MESSAGE (Support of Text Attribute – Center Alignment)

27.22.4.10.4.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.10.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

27.22.4.10.4.2.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the center alignment text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.4.2.4 Method of test

27.22.4.10.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.2.4.2 Procedure

**Expected Sequence 4.2 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Center Alignment, packing not required, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.2.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with center alignment]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.2.1	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.2.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.2.2	[packing not required, SMS default alphabet]
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/11, no alignment change will take place]
12	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.2.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.2.1

Logically:

Command details

Command number: 1  
Command type: SEND SHORT MESSAGE  
Command qualifier: packing not required

Device identities

Source device: UICC  
Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT  
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
TP-VPF TP-VP field not present  
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
TP-UDHI The TP-UD field contains only the short message  
TP-SRR A status report is not requested  
TP-MR "00"

TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	01	B4		

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.2.2

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20								

## TERMINAL RESPONSE: SEND SHORT MESSAGE 4.2.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.10.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

## 27.22.4.10.4.3 SEND SHORT MESSAGE (Support of Text Attribute – Right Alignment)

## 27.22.4.10.4.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.10.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

## 27.22.4.10.4.3.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the right alignment text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

## 27.22.4.10.4.3.4 Method of test

## 27.22.4.10.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.4.3.4.2 Procedure

**Expected Sequence 4.3 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Right Alignment, packing not required, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.3.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with right alignment]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.3.1	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.3.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.3.2	[packing not required, SMS default alphabet]
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/11, no alignment change will take place]
12	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.3.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.3.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

## SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1

TP-UD " "

Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	02	B4		

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.3.2

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier:

"Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class class 0

TP-UDL 1

TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20								

## TERMINAL RESPONSE: SEND SHORT MESSAGE 4.3.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.10.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

## 27.22.4.10.4.4 SEND SHORT MESSAGE (Support of Text Attribute – Large Font Size)

## 27.22.4.10.4.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.10.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

## 27.22.4.10.4.4.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the large font size text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

## 27.22.4.10.4.4.4 Method of test

## 27.22.4.10.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.4.4.2 Procedure

**Expected Sequence 4.4 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Large Font Size, packing not required, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with large font size]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.4.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.2	[packing not required, SMS default alphabet]
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with normal font size]
12	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.4.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.1	[packing not required, SMS default alphabet]
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with large font size]
19	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
20	USS → ME	SMS RP-ACK	
21	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1	[Command performed successfully]
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.4.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.3	[packing not required, SMS default alphabet]
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with normal font size]
26	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
27	USS → ME	SMS RP-ACK	
28	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.1

Logically:

Command details

Command number: 1  
Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities  
 Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1

TP-UD " "  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	04	B4		

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.2

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities  
 Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS

Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.3

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Text Attribute 3"  
 SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE

Command qualifier:    packing not required  
 Device identities  
   Source device:        ME  
   Destination device:  UICC  
 Result  
   General Result:      Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.10.4.4.5    Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

#### 27.22.4.10.4.5    SEND SHORT MESSAGE (Support of Text Attribute – Small Font Size)

##### 27.22.4.10.4.5.1    Definition and applicability

See clause 3.2.2.

##### 27.22.4.10.4.5.2    Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

##### 27.22.4.10.4.5.3    Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the small font size text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

##### 27.22.4.10.4.5.4    Method of test

###### 27.22.4.10.4.5.4.1    Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.4.5.4.2 Procedure

**Expected Sequence 4.5 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Small Font Size, packing not required, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with small font size]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.5.1	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.5.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.2	[packing not required, SMS default alphabet]
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with normal font size]
12	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.5.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.5.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.1	[packing not required, SMS default alphabet]
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with small font size]
19	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
20	USS → ME	SMS RP-ACK	
21	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.5.1	[Command performed successfully]
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.5.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.3	[packing not required, SMS default alphabet]
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with normal font size]
26	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
27	USS → ME	SMS RP-ACK	
28	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.5.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.1

Logically:

Command details

Command number: 1  
Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class class 0

TP-UDL 1

TP-UD " "

Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	08	B4		

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.2

## Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.3

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Text Attribute 3"  
 SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.5.1

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE

Command qualifier:    packing not required  
 Device identities  
   Source device:        ME  
   Destination device:  UICC  
 Result  
   General Result:      Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.10.4.5.5      Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

#### 27.22.4.10.4.6        SEND SHORT MESSAGE (Support of Text Attribute – Bold On)

##### 27.22.4.10.4.6.1      Definition and applicability

See clause 3.2.2.

##### 27.22.4.10.4.6.2      Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

##### 27.22.4.10.4.6.3      Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the bold text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

##### 27.22.4.10.4.6.4      Method of test

###### 27.22.4.10.4.6.4.1    Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.4.6.4.2 Procedure

**Expected Sequence 4.6 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Bold On, packing not required, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with bold on]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.6.1	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.6.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.2	[packing not required, SMS default alphabet]
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with bold off]
12	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.6.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.6.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.1	[packing not required, SMS default alphabet]
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with bold on]
19	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
20	USS → ME	SMS RP-ACK	
21	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.6.1	[Command performed successfully]
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.6.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.3	[packing not required, SMS default alphabet]
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with bold off]
26	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
27	USS → ME	SMS RP-ACK	
28	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.6.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.1

Logically:

Command details

Command number: 1  
Command type: SEND SHORT MESSAGE  
Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network  
 Alpha identifier: "Text Attribute 1"  
 SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	10	B4		

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.2

## Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Text Attribute 2"  
 SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1

TP-UD " "

Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

### PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.3

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier: "Text Attribute 3"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class class 0

TP-UDL 1

TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

### TERMINAL RESPONSE: SEND SHORT MESSAGE 4.6.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: ME

Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.10.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

## 27.22.4.10.4.7 SEND SHORT MESSAGE (Support of Text Attribute – Italic On)

## 27.22.4.10.4.7.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.10.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

## 27.22.4.10.4.7.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the italic text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

## 27.22.4.10.4.7.4 Method of test

## 27.22.4.10.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.4.7.4.2 Procedure

**Expected Sequence 4.7 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Italic On, packing not required, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.7.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with italic on]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.7.1	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.7.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.2	[packing not required, SMS default alphabet]
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with italic off]
12	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.7.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.7.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.1	[packing not required, SMS default alphabet]
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with italic on]
19	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
20	USS → ME	SMS RP-ACK	
21	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.7.1	[Command performed successfully]
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.7.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.3	[packing not required, SMS default alphabet]
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with italic off]
26	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
27	USS → ME	SMS RP-ACK	
28	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.7.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: UICC

Destination device: Network  
Alpha identifier: "Text Attribute 1"  
SMS TPDU  
TP-MTI SMS-SUBMIT  
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
TP-VPF TP-VP field not present  
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
TP-UDHI The TP-UD field contains only the short message  
TP-SRR A status report is not requested  
TP-MR "00"  
TP-DA  
TON International number  
NPI "ISDN / telephone numbering plan"  
Address value "01"  
TP-PID Short message type 0  
TP-DCS  
Message coding SMS default alphabet  
Message class class 0  
TP-UDL 1  
TP-UD " "  
Text Attribute  
Formatting position: 0  
Formatting length: 16  
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off  
Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	20	B4		

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.2

## Logically:

Command details  
Command number: 1  
Command type: SEND SHORT MESSAGE  
Command qualifier: packing not required  
Device identities  
Source device: UICC  
Destination device: Network  
Alpha identifier: "Text Attribute 2"  
SMS TPDU  
TP-MTI SMS-SUBMIT  
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
TP-VPF TP-VP field not present  
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
TP-UDHI The TP-UD field contains only the short message  
TP-SRR A status report is not requested  
TP-MR "00"  
TP-DA  
TON International number  
NPI "ISDN / telephone numbering plan"  
Address value "01"  
TP-PID Short message type 0  
TP-DCS  
Message coding SMS default alphabet  
Message class class 0  
TP-UDL 1

TP-UD " "

Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.3

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier: "Text Attribute 3"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class class 0

TP-UDL 1

TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.7.1

Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.10.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

## 27.22.4.10.4.8 SEND SHORT MESSAGE (Support of Text Attribute – Underline On)

## 27.22.4.10.4.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.10.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

## 27.22.4.10.4.8.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the underline text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

## 27.22.4.10.4.8.4 Method of test

## 27.22.4.10.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.4.8.4.2 Procedure

**Expected Sequence 4.8 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Underline On, packing not required, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.8.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with underline on]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.8.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.2	[packing not required, SMS default alphabet]
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with underline off]
12	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.8.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.1	[packing not required, SMS default alphabet]
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with underline on]
19	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
20	USS → ME	SMS RP-ACK	
21	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1	[Command performed successfully]
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.8.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.3	[packing not required, SMS default alphabet]
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with underline off]
26	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
27	USS → ME	SMS RP-ACK	
28	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.1

Logically:

Command details

Command number: 1  
Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet

Message class class 0

TP-UDL 1

TP-UD " "

Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	40	B4		

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.2

## Logically:

Command details

Command number: 1

Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities

Source device: UICC

Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "00"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "01"

TP-PID Short message type 0

TP-DCS

Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.3

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Text Attribute 3"  
 SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE

Command qualifier:    packing not required  
 Device identities  
   Source device:        ME  
   Destination device:  UICC  
 Result  
   General Result:      Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.10.4.8.5      Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

#### 27.22.4.10.4.9        SEND SHORT MESSAGE (Support of Text Attribute – Strikethrough On)

##### 27.22.4.10.4.9.1      Definition and applicability

See clause 3.2.2.

##### 27.22.4.10.4.9.2      Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

##### 27.22.4.10.4.9.3      Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the strikethrough text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

##### 27.22.4.10.4.9.4      Method of test

###### 27.22.4.10.4.9.4.1    Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.4.9.4.2 Procedure

**Expected Sequence 4.9 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Strikethrough On, packing not required, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.9.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with striketrough on]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.9.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.2	[packing not required, SMS default alphabet]
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with striketrough off]
12	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.9.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.1	[packing not required, SMS default alphabet]
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with striketrough on]
19	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
20	USS → ME	SMS RP-ACK	
21	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1	[Command performed successfully]
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.9.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.3	[packing not required, SMS default alphabet]
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with striketrough off]
26	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
27	USS → ME	SMS RP-ACK	
28	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1	[Command performed successfully]

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.1

Logically:

Command details

Command number: 1  
Command type: SEND SHORT MESSAGE

Command qualifier: packing not required

Device identities  
 Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "

Text Attribute  
 Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	80	B4		

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.2

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities  
 Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS

Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.3

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Text Attribute 3"  
 SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "

Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8B	09	01	00	02	91	10
	40	F0	01	20								

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE

Command qualifier:    packing not required  
 Device identities  
   Source device:        ME  
   Destination device:  UICC  
 Result  
   General Result:      Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.10.4.9.5      Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

#### 27.22.4.10.4.10      SEND SHORT MESSAGE (Support of Text Attribute – Foreground and Background Colour)

##### 27.22.4.10.4.10.1      Definition and applicability

See clause 3.2.2.

##### 27.22.4.10.4.10.2      Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

##### 27.22.4.10.4.10.3      Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the foreground and background colour text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

##### 27.22.4.10.4.10.4      Method of test

###### 27.22.4.10.4.10.4.1      Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.4.10.4.2 Procedure

**Expected Sequence 4.10 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Foreground and Background Colour, packing not required, SMS default alphabet, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.10.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.1	[packing not required, SMS default alphabet]
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with foreground and background colour according to text attribute configuration]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.10.1	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.10.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.2	[packing not required, SMS default alphabet]
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with ME's default foreground and background colour]
12	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 4.1	
13	USS → ME	SMS RP-ACK	
14	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 4.10.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

## SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2C	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8B	09	01	00	02	91	10
	40	F0	01	20	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: UICC  
 Destination device: Network

## Alpha identifier:

"Text Attribute 2"

## SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "01"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding SMS default alphabet  
 Message class class 0  
 TP-UDL 1  
 TP-UD " "

## Coding:

BER-TLV:	D0	26	81	03	01	13	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8B	09	01	00	02	91	10
	40	F0	01	20								

## TERMINAL RESPONSE: SEND SHORT MESSAGE 4.10.1

## Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.10.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

27.22.4.10.5 SEND SHORT MESSAGE (UCS2 display in Chinese)

27.22.4.10.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.10.5.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

Additionally, the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

27.22.4.10.5.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.5.4 Method of test

27.22.4.10.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.5.4.2 Procedure

**Expected Sequence 5.1 (SEND SHORT MESSAGE, packing not required, UCS2 (16-bit data in Chinese))**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 5.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 5.1.1	[packing not required, 16-bit data]
4	ME → USER	Display "中—"	[Alpha Identifier] "Middle 1" in Chinese, 0x80 coding of UCS2 format
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 5.1	
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 5.1.1	[Command performed successfully]
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 5.1.2	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND SEND SHORT MESSAGE 5.1.2	
12	ME → USER	Display "中—"	[Alpha Identifier] "Middle 1" in Chinese, 0x81 coding of UCS2 format
13	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 5.1	
14	USS → ME	SMS RP-ACK	
15	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 5.1.1	[Command performed successfully]
16	UICC → ME	PROACTIVE UICC SESSION ENDED	
17	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 5.1.3	
18	ME → UICC	FETCH	
19	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 5.1.3	[UCS2 alphabet]
20	ME → USER	Display "中—"	[Alpha Identifier] "Middle 1" in Chinese, 0x82 coding of UCS2 format
21	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 5.1	
22	USS → ME	SMS RP-ACK	
23	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 5.1.1	[Command performed successfully]
24	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE COMMAND: SEND SHORT MESSAGE: 5.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "中—"

Address  
 TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 16-bit data  
 Message class class 0  
 TP-UDL 24  
 TP-UD "中—"

Coding:

BER-TLV:	D0	2D	81	03	01	13	00	82	02	81	83	85
	05	80	4E	2D	4E	00	86	09	91	11	22	33
	44	55	66	77	F8	8B	10	01	00	09	91	10
	32	54	76	F8	40	08	04	4E	2D	4E	00	

SMS-PP (SEND SHORT MESSAGE) Message 5.1

Logically:

SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "01"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding UCS2 (16-bit data)  
 Message class class 0  
 TP-UDL 24  
 TP-UD "中—"

Coding:

BER-TLV:	01	01	09	91	10	32	54	76	F8	40	08	04
	4E	2D	4E	00								

PROACTIVE COMMAND: SEND SHORT MESSAGE: 5.1.2

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities  
 Source device: UICC  
 Destination device: Network

Alpha identifier: "中—"

Address  
 TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 16-bit data  
 Message class class 0  
 TP-UDL 24  
 TP-UD "中—"

Coding:

BER-TLV:	D0	2D	81	03	01	13	00	82	02	81	83	85
	05	81	02	9C	AD	80	86	09	91	11	22	33
	44	55	66	77	F8	8B	10	01	00	09	91	10
	32	54	76	F8	40	08	04	4E	2D	4E	00	

PROACTIVE COMMAND: SEND SHORT MESSAGE: 5.1.3

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities  
 Source device: UICC  
 Destination device: Network

Alpha identifier: "中—"

Address  
 TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI	The TP-UD field contains only the short message
TP-SRR	A status report is not requested
TP-MR	"00"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"012345678"
TP-PID	Short message type 0
TP-DCS	
Message coding	16-bit data
Message class	class 0
TP-UDL	24
TP-UD	"中—"

Coding:

BER-TLV:	D0	2E	81	03	01	13	00	82	02	81	83	85
	06	82	02	4E	00	AD	80	86	09	91	11	22
	33	44	55	66	77	F8	8B	10	01	00	09	91
	10	32	54	76	F8	40	08	04	4E	2D	4E	00

TERMINAL RESPONSE: SEND SHORT MESSAGE 5.1.1

Logically:

Command details

Command number:	1
Command type:	SEND SHORT MESSAGE
Command qualifier:	packing not required

Device identities

Source device:	ME
Destination device:	UICC

Result

General Result:	Command performed successfully
-----------------	--------------------------------

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.10.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

#### 27.22.4.10.6 SEND SHORT MESSAGE (UCS2 display in Katakana)

##### 27.22.4.10.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.10.6.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

Additionally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

## 27.22.4.10.6.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

## 27.22.4.10.6.4 Method of test

## 27.22.4.10.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.10.6.4.2 Procedure

**Expected Sequence 6.1 (SEND SHORT MESSAGE, packing not required, UCS2 (16-bit data, in Katakana))**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 6.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 6.1.1	[packing not required, 16-bit data]
4	ME → USER	Display "80ル0"	[Alpha Identifier]
5	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 6.1	["80ル1" = "80Test1" in Katakana]
6	USS → ME	SMS RP-ACK	
7	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1	[Command performed successfully]
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 6.1.2	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 6.1.2	[packing not required, 16-bit data]
12	ME → USER	Display "81ル1"	[Alpha Identifier]
13	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 6.2	["80ル2" = "80Test2" in Katakana]
14	USS → ME	SMS RP-ACK	
15	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1	[Command performed successfully]
16	UICC → ME	PROACTIVE UICC SESSION ENDED	
17	UICC → ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 6.1.3	
18	ME → UICC	FETCH	
19	UICC → ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 6.1.3	[packing not required, 16-bit data]
20	ME → USER	Display "82ル2"	[Alpha Identifier]
21	ME → USS	Send SMS-PP (SEND SHORT MESSAGE) Message 6.3	["80ル3" = "80Test3" in Katakana]
22	USS → ME	SMS RP-ACK	
23	ME → UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1	[Command performed successfully]
24	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE COMMAND: SEND SHORT MESSAGE: 6.1.1

Logically:

Command details  
 Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities  
 Source device: UICC  
 Destination device: Network

Alpha identifier: "80ル0"

Address  
 TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept a SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 16-bit data  
 Message class class 0  
 TP-UDL 10  
 TP-UD "80ル1"

Coding:

BER-TLV:	D0	35	81	03	01	13	00	82	02	81	83	85
	09	80	00	38	00	30	30	EB	00	30	86	09
	91	11	22	33	44	55	66	77	F8	8B	14	01
	00	09	91	10	32	54	76	F8	40	08	08	00
	38	00	30	30	EB	00	31					

SMS-PP (SEND SHORT MESSAGE) Message 6.1

Logically:

SMS TPDU  
 TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "01"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding UCS2 (16-bit data)  
 Message class class 0  
 TP-UDL 10

TP-UD "80ル1"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	08	08
	00	38	00	30	30	EB	00	31				

TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

PROACTIVE COMMAND: SEND SHORT MESSAGE: 6.1.2

Logically:

Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "81ル1"

Address

TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept a SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 16-bit data  
 Message class class 0  
 TP-UDL 10  
 TP-UD "80ル2"

Coding:

BER-TLV:	D0	33	81	03	01	13	00	82	02	81	83	85
	07	81	04	61	38	31	EB	31	86	09	91	11
	22	33	44	55	66	77	F8	8B	14	01	00	09
	91	10	32	54	76	F8	40	08	08	00	38	00
	30	30	EB	00	32							

## SMS-PP (SEND SHORT MESSAGE) Message 6.2

Logically:

## SMS TPDU

TP-MTI	SMS-SUBMIT
TP-RD	Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF	TP-VP field not present
TP-RP	TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI	The TP-UD field contains only the short message
TP-SRR	A status report is not requested
TP-MR	"01"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"012345678"
TP-PID	Short message type 0
TP-DCS	
Message coding	UCS2 (16-bit data)
Message class	class 0
TP-UDL	10
TP-UD	"80ル2"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	08	08
	00	38	00	30	30	EB	00	32				

## PROACTIVE COMMAND: SEND SHORT MESSAGE: 6.1.3

Logically:

## Command details

Command number:	1
Command type:	SEND SHORT MESSAGE
Command qualifier:	packing not required

## Device identities

Source device:	UICC
Destination device:	Network

Alpha identifier: "82ル2"

## Address

TON:	International number
NPI:	"ISDN / telephone numbering plan"
Dialling number string	"112233445566778"

## SMS TPDU

TP-MTI	SMS-SUBMIT
TP-RD	Instruct the SC to accept a SMS-SUBMIT for a SM
TP-VPF	TP-VP field not present
TP-RP	TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI	The TP-UD field contains only the short message
TP-SRR	A status report is not requested
TP-MR	"00"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"

Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 16-bit data  
 Message class class 0  
 TP-UDL 10  
 TP-UD "80ル3"

Coding:

BER-TLV:	D0	34	81	03	01	13	00	82	02	81	83	85
	08	82	04	30	A0	38	32	CB	32	86	09	91
	11	22	33	44	55	66	77	F8	8B	14	01	00
	09	91	10	32	54	76	F8	40	08	08	00	38
	00	30	30	EB	00	33						

SMS-PP (SEND SHORT MESSAGE) Message 6.3

Logically:

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "01"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding UCS2 (16-bit data)  
 Message class class 0  
 TP-UDL 10  
 TP-UD "80ル3"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	08	08
	00	38	00	30	30	EB	00	33				

#### 27.22.4.10.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

#### 27.22.4.11 SEND SS

##### 27.22.4.11.1 SEND SS (normal)

###### 27.22.4.11.1.1 Definition and applicability

See clause 3.2.2.

###### 27.22.4.11.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

### 27.22.4.11.1.3 Test purpose

To verify that the ME correctly translates and sends the supplementary service request indicated in the SEND SS proactive UICC command to the USS.

To verify that the ME returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the SS and any contents of the SS result as additional data.

### 27.22.4.11.1.4 Method of test

#### 27.22.4.11.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.11.1.4.2 Procedure

#### Expected Sequence 1.1A (SEND SS, call forward unconditional, all bearers, successful)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 1.1.1	
4	ME → USER	Display "Call Forward"	
5	ME → USS	REGISTER 1.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 1.1.1A	

#### Expected Sequence 1.1B (SEND SS, call forward unconditional, all bearers, successful)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 1.1.1	
4	ME → USER	Display "Call Forward"	
5	ME → USS	REGISTER 1.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 1.1.1B	

PROACTIVE COMMAND: SEND SS 1.1.1

Logically:

#### Command details

Command number: 1  
Command type: SEND SS  
Command qualifier: "00"

#### Device identities

Source device: UICC  
Destination device: Network

Alpha identifier: "Call Forward"  
 SS String  
 TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	29	81	03	01	11	00	82	02	81	83	85
	0C	43	61	6C	6C	20	46	6F	72	77	61	72
	64	89	10	91	AA	12	0A	21	43	65	87	09
	21	43	65	87	A9	01	FB					

#### REGISTER 1.1A

Logically (only SS argument):

##### REGISTER SS ARGUMENT

SS-Code:  
 - Call Forwarding Unconditional  
 TeleserviceCode  
 - All Tele Services  
 ForwardedToNumber  
 - nature of address ind.: international  
 - numbering plan ind.: ISDN/Telephony (E.164)  
 - TBCD String: 01234567890123456789  
 - longFTN-Supported

Coding:

BER-TLV	30	15	04	01	21	83	01	00	84	0B	91	10
	32	54	76	98	10	32	54	76	98	89	00	

#### REGISTER 1.1B

Logically (only SS argument):

##### REGISTER SS ARGUMENT

SS-Code:  
 - Call Forwarding Unconditional  
 TeleserviceCode  
 - All Tele Services  
 ForwardedToNumber  
 - nature of address ind.: international  
 - numbering plan ind.: ISDN/Telephony (E.164)  
 - TBCD String: 01234567890123456789

Coding:

BER-TLV	30	13	04	01	21	83	01	00	84	0B	91	10
	32	54	76	98	10	32	54	76	98			

#### RELEASE COMPLETE (SS RETURN RESULT) 1.1A

Logically (only from operation code):

##### REGISTER SS RETURN RESULT

ForwardingInfo  
 SS-Code  
 - Call Forwarding Unconditional  
 ForwardFeatureList  
 ForwardingFeature  
 TeleserviceCode

- All Tele Services
- SS-Status
  - state ind.: operative
  - provision ind.: provisioned
  - registration ind.: registered
  - activation ind.: active
- longForwardedToNumber
  - nature of address ind.: international
  - numbering plan ind.: ISDN/Telephony (E.164)
  - TBCD String: 01234567890123456789

Coding:

Coding	0A	A0	1A	04	01	21	30	15	30	13	83	01
	00	84	01	07	89	0B	91	10	32	54	76	98
	10	32	54	76	98							

## RELEASE COMPLETE (SS RETURN RESULT) 1.1A

Logically (only from operation code):

## REGISTER SS RETURN RESULT

- ForwardingInfo
- SS-Code
  - Call Forwarding Unconditional
- ForwardFeatureList
  - ForwardingFeature
  - TeleserviceCode
    - All Tele Services
- SS-Status
  - state ind.: operative
  - provision ind.: provisioned
  - registration ind.: registered
  - activation ind.: active

Coding:

Coding	0A	A0	0D	04	01	21	30	08	30	06	83	01
	00	84	01	07								

## TERMINAL RESPONSE: SEND SS 1.1.1A

Logically:

## Command details

- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

## Device identities

- Source device: ME
- Destination device: UICC

## Result

- General Result: Command performed successfully
- Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	1E
	00	0A	A0	1A	04	01	21	30	15	30	13
	83	01	00	84	01	07	89	0B	91	10	32
	54	76	98	10	32	54	76	98			

## TERMINAL RESPONSE: SEND SS 1.1.1B

Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	11
	00	0A	A0	0D	04	01	21	30	08	30	06
	83	01	00	84	01	07					

**Expected Sequence 1.2 (SEND SS, call forward unconditional, all bearers, Return Error)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 1.1.1	
4	ME → USER	Display "Call Forward"	
5	ME → USS	REGISTER 1.1A Or REGISTER 1.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN ERROR) 1.1	[Return Error]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 1.2.1	

## RELEASE COMPLETE (SS RETURN ERROR) 1.1

Logically (only from error code):

Error Code: Facility not supported

Coding:

Coding	02	01	15
--------	----	----	----

## TERMINAL RESPONSE: SEND SS 1.2.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: SS Return Error  
 Additional information: Error Code

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	02
	34	15									

**Expected Sequence 1.3 (SEND SS, call forward unconditional, all bearers, Reject)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 1.1.1	
4	ME → USER	Display "Call Forward"	
5	ME → USS	REGISTER 1.1A Or REGISTER 1.1B	
6	USS → ME	RELEASE COMPLETE (SS REJECT) 1.1.	[Reject]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 1.3.1	

**RELEASE COMPLETE (SS REJECT) 1.1**

Logically (only from problem code):

Problem Code:

- General problem
- Unrecognized component

Coding:

Coding	80	01	00
--------	----	----	----

**TERMINAL RESPONSE: SEND SS 1.3.1**

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: SS Return Error  
 Additional information: No specific cause can be given

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	02
	34	00									

**Expected Sequence 1.4A (SEND SS, call forward unconditional, all bearers, successful, SS request size limit)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 1.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 1.4.1	
4	ME → USER	Display "Call Forward"	
5	ME → USS	REGISTER 1.2	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.2A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 1.4.1A	

**Expected Sequence 1.4B (SEND SS, call forward unconditional, all bearers, successful, SS request size limit)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 1.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 1.4.1	
4	ME → USER	Display "Call Forward"	
5	ME → USS	REGISTER 1.2B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.2B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 1.4.1B	

PROACTIVE COMMAND: SEND SS 1.4.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Call Forward"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*0123456789012345678901234567\*11#"

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	0C	43	61	6C	6C	20	46	6F	72	77	61	72
	64	89	14	91	AA	12	0A	21	43	65	87	09
	21	43	65	87	09	21	43	65	A7	11	FB	

REGISTER 1.2A

Logically (only SS argument):

REGISTER SS ARGUMENT

RegisterSSArg  
 SS-Code  
     Call Forwarding Unconditional  
 TeleserviceCode  
     See Note 1  
 ForwardedToNumber  
     nature of address ind.: international  
     numbering plan ind.: ISDN/Telephony (E.164)  
 TBCD String: 0123456789012345678901234567  
 longFTN-Supported

Coding:

BER-TLV	30	19	04	01	21	83	01	Note 1	84	0F	91	10
	32	54	76	98	10	32	54	76	98	10	32	54
	76	89	00									

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

REGISTER 1.2B

Logically (only SS argument):

REGISTER SS ARGUMENT

RegisterSSArg

SS-Code

Call Forwarding Unconditional

TeleserviceCode

See Note 1

ForwardedToNumber

nature of address ind.: international

numbering plan ind.: ISDN/Telephony (E.164)

TBCD String: 0123456789012345678901234567

Coding:

BER-TLV	30	17	04	01	21	83	01	Note 1	84	0F	91	10
	32	54	76	98	10	32	54	76	98	10	32	54
	76											

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

Logically (only from operation code):

REGISTER SS RETURN RESULT

ForwardingInfo

SS-Code

- Call Forwarding Unconditional

ForwardFeatureList

ForwardingFeature

TeleserviceCode

- See Note 1

SS-Status

- state ind.: operative

- provision ind.: provisioned

- registration ind.: registered

- activation ind.: active

longForwardedToNumber

- nature of address ind.: international

- numbering plan ind.: ISDN/Telephony (E.164)

- TBCD String: 0123456789012345678901234567

Coding:

Coding	0A	A0	1E	04	01	21	30	19	30	17	83	01
	Note 1	84	01	07	89	0F	91	10	32	54	76	98
	10	32	54	76	98	10	32	54	76			

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

RELEASE COMPLETE (SS RETURN RESULT) 1.2B

Logically (only from operation code):

REGISTER SS RETURN RESULT

ForwardingInfo

SS-Code

- Call Forwarding Unconditional

ForwardFeatureList

ForwardingFeature

TeleserviceCode

- See Note 1

SS-Status

- state ind.: operative

- provision ind.: provisioned
- registration ind.: registered
- activation ind.: active

Coding:

Coding	0A	A0	1E	04	01	21	30	19	30	17	83	01
	Note 1	84	01	07								

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

TERMINAL RESPONSE: SEND SS 1.4.1A

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	22
	00	0A	A0	1E	04	01	21	30	19	30	17
	83	01	Note 1	84	01	07	89	0F	91	10	32
	54	76	98	10	32	54	76	98	10	32	54
	76										

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

TERMINAL RESPONSE: SEND SS 1.4.1B

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	22
	00	0A	A0	1E	04	01	21	30	19	30	17
	83	01	Note 1	84	01	07					

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

**Expected Sequence 1.5 (SEND SS, interrogate CLIR status, successful, alpha identifier limits)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 1.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 1.5.1	
4	ME → USER	Display "Even if the Fixed Dialling Number service is enabled, the supplementary service control string included in the SEND SS proactive command shall not be checked against those of the FDN list. Upon receiving this command, the ME shall deci"	
5	ME → USS	REGISTER 1.3	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.3	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 1.5.1	

PROACTIVE COMMAND: SEND SS 1.5.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Even if the Fixed Dialling Number service is enabled, the supplementary service control string included in the SEND SS proactive command shall not be checked against those of the FDN list. Upon receiving this command, the ME shall deci"

## SS String

TON: Undefined  
 NPI: Undefined  
 SS string: "\*#31#"

Coding:

BER-TLV:	D0	81	FD	81	03	01	11	00	82	02	81	83
	85	81	EB	45	76	65	6E	20	69	66	20	74
	68	65	20	46	69	78	65	64	20	44	69	61
	6C	6C	69	6E	67	20	4E	75	6D	62	65	72
	20	73	65	72	76	69	63	65	20	69	73	20
	65	6E	61	62	6C	65	64	2C	20	74	68	65
	20	73	75	70	70	6C	65	6D	65	6E	74	61
	72	79	20	73	65	72	76	69	63	65	20	63
	6F	6E	74	72	6F	6C	20	73	74	72	69	6E
	67	20	69	6E	63	6C	75	64	65	64	20	69
	6E	20	74	68	65	20	53	45	4E	44	20	53
	53	20	70	72	6F	61	63	74	69	76	65	20
	63	6F	6D	6D	61	6E	64	20	73	68	61	6C
	6C	20	6E	6F	74	20	62	65	20	63	68	65
	63	6B	65	64	20	61	67	61	69	6E	73	74
	20	74	68	6F	73	65	20	6F	66	20	74	68
	65	20	46	44	4E	20	6C	69	73	74	2E	20
	55	70	6F	6E	20	72	65	63	65	69	76	69
	6E	67	20	74	68	69	73	20	63	6F	6D	6D
	61	6E	64	2C	20	74	68	65	20	4D	45	20
	73	68	61	6C	6C	20	64	65	63	69	89	04
	FF	BA	13	FB								

REGISTER 1.3

Logically (only SS argument):

INTERROGATE SS ARGUMENT

- SS-Code
- Calling Line Id Restriction

Coding:

BER-TLV	30	03	04	01	12
---------	----	----	----	----	----

RELEASE COMPLETE (SS RETURN RESULT) 1.3

Logically (only from operation code):

INTERROGATE SS RESULT

- CliRestrictionInfo
- SS-Status
  - state ind.: operative
  - provision ind.: provisioned
  - registration ind.: registered
  - activation ind.: not active
- CliRestrictionOption
  - Temporary Def Allowed

Coding:

Coding	0E	A4	06	04	01	06	0A	01	02
--------	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: SEND SS 1.5.1

Logically:

Command details

- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities

- Source device: ME
- Destination device: UICC

Result

- General Result: Command performed successfully

Additional information

- Operation Code: SS Code
- Parameters: SS Return Result

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	0A
	00	0E	A4	06	04	01	06	0A	01	02	

**Expected Sequence 1.6A (SEND SS, call forward unconditional, all bearers, successful, null data alpha identifier)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 1.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 1.6.1	
4	ME	Should not give any information to the user on the fact that the ME is sending an SS request	
5	ME → USS	REGISTER 1.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 1.1.1A	

**Expected Sequence 1.6B (SEND SS, call forward unconditional, all bearers, successful, null data alpha identifier)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 1.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 1.6.1	
4	ME	Should not give any information to the user on the fact that the ME is sending an SS request	
5	ME → USS	REGISTER 1.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 1.1.1B	

PROACTIVE COMMAND: SEND SS 1.6.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: null data object

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	1D	81	03	01	11	00	82	02	81	83	85
	00	89	10	91	AA	12	0A	21	43	65	87	09
	21	43	65	87	A9	01	FB					

27.22.4.11.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1 to 1.6.

## 27.22.4.11.2 SEND SS (Icon support)

## 27.22.4.11.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.11.2.2 Conformance requirement

## 27.22.4.11.2.3 Test purpose

To verify that the ME displays the text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

In addition to verify that if an icon is provided by the UICC, the icon indicated in the command may be used by the ME to inform the user, in addition to, or instead of the alpha identifier, as indicated with the icon qualifier.

## 27.22.4.11.2.4 Method of test

## 27.22.4.11.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

The elementary files are coded as Toolkit default.

## 27.22.4.11.2.4.2 Procedure

**Expected Sequence 2.1A (SEND SS, call forward unconditional, all bearers, successful, basic icon self explanatory, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 2.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 2.1.1	[BASIC-ICON, self-explanatory]
4	ME → USER	Display the basic icon without the alpha identifier	
5	ME → USS	REGISTER 1.1A Or REGISTER 1.1B	Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1A or RELEASE COMPLETE (SS RETURN RESULT) 1.1B	[Successful] Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
7	ME → UICC	TERMINAL RESPONSE: SEND SS 2.1.1AA or TERMINAL RESPONSE: SEND SS 2.1.1AB	[Command performed successfully] Option AA applies if A.1/63 is supported, Option AB applies if A.1/63 is not supported

## PROACTIVE COMMAND: SEND SS 2.1.1

Logically:

## Command details

Command number: 1  
Command type: SEND SS  
Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Basic Icon"  
 SS String  
 TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"  
 Icon Identifier:  
 Icon qualifier: icon is self-explanatory  
 Icon Identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	2B	81	03	01	11	00	82	02	81	83	85
	0A	42	61	73	69	63	20	49	63	6F	6E	89
	10	91	AA	12	0A	21	43	65	87	09	21	43
	65	87	A9	01	FB	9E	02	00	01			

TERMINAL RESPONSE: SEND SS 2.1.1AA

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	1E
	00	0A	A0	1A	04	01	21	30	15	30	13
	83	01	00	84	01	07	89	0B	91	10	32
	54	76	98	10	32	54	76	98			

TERMINAL RESPONSE: SEND SS 2.1.1AB

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	03	11
	00	0A	A0	0D	04	01	21	30	08	30	06
	83	01	00	84	01	07					

**Expected Sequence 2.1B (SEND SS, call forward unconditional, all bearers, successful, basic icon self explanatory, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 2.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 2.1.1	[BASIC-ICON, self-explanatory]
4	ME → USER	Display "Basic Icon" without the icon	
5	ME → USS	REGISTER 1.1A Or REGISTER 1.1B	Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1A or RELEASE COMPLETE (SS RETURN RESULT) 1.1B	[Successful] Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
7	ME → UICC	TERMINAL RESPONSE: SEND SS 2.1.1BA or TERMINAL RESPONSE: SEND SS 2.1.1BB	[Command performed successfully, but requested icon could not be displayed] Option BA applies if A.1/63 is supported, Option BB applies if A.1/63 is not supported

TERMINAL RESPONSE: SEND SS 2.1.1BA

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed  
 Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:

81	03	01	11	00	82	02	82	81	03	1E
04	0A	A0	1A	04	01	21	30	15	30	13
83	01	00	84	01	07	89	0B	91	10	32
54	76	98	10	32	54	76	98			

TERMINAL RESPONSE: SEND SS 2.1.1BB

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed  
 Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:

81	03	01	11	00	82	02	82	81	03	11
----	----	----	----	----	----	----	----	----	----	----

04	0A	A0	0D	04	01	21	30	08	30	06
83	01	00	84	01	07					

**Expected Sequence 2.2A (SEND SS, call forward unconditional, all bearers, successful, colour icon self explanatory, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 2.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 2.2.1	[COLOUR-ICON, self-explanatory]
4	ME → USER	Display the colour icon without the alpha identifier	
5	ME → USS	REGISTER 1.1A Or REGISTER 1.1B	Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1A or RELEASE COMPLETE (SS RETURN RESULT) 1.1B	[Successful] Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
7	ME → UICC	TERMINAL RESPONSE: SEND SS 2.1.1AA or TERMINAL RESPONSE: SEND SS 2.1.1AB	[Command performed successfully] Option AA applies if A.1/63 is supported, Option AB applies if A.1/63 is not supported

**PROACTIVE COMMAND: SEND SS 2.2.1**

Logically:

Command details

Command number: 1  
Command type: SEND SS  
Command qualifier: "00"

Device identities

Source device: UICC  
Destination device: Network  
Alpha identifier: "Colour Icon"

SS String

TON: International  
NPI: "ISDN / telephone numbering plan"  
SS string: "\*\*\*21\*01234567890123456789\*10#"

Icon Identifier:

Icon qualifier: icon is self-explanatory  
Icon Identifier: record 2 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	2C	81	03	01	11	00	82	02	81	83	85
	0B	43	6F	6C	6F	75	72	20	49	63	6F	6E
	89	10	91	AA	12	0A	21	43	65	87	09	21
	43	65	87	A9	01	FB	9E	02	00	02		

**Expected Sequence 2.2B (SEND SS, call forward unconditional, all bearers, successful, colour icon self explanatory, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 2.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 2.2.1	[COLOUR-ICON, self-explanatory]
4	ME → USER	Display "Colour Icon" without the icon	
5	ME → USS	REGISTER 1.1A Or REGISTER 1.1B	Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1A or RELEASE COMPLETE (SS RETURN RESULT) 1.1B	[Successful] Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
7	ME → UICC	TERMINAL RESPONSE: SEND SS 2.1.1BA or TERMINAL RESPONSE: SEND SS 2.1.1BB	[Command performed but requested icon could not be displayed] Option BA applies if A.1/63 is supported, Option BB applies if A.1/63 is not supported

**Expected Sequence 2.3A (SEND SS, call forward unconditional, all bearers, successful, basic icon non self-explanatory, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 2.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 2.3.1	[BASIC-ICON, non self-explanatory]
4	ME → USER	Display "Basic Icon" and the basic icon	
5	ME → USS	REGISTER 1.1A Or REGISTER 1.1B	Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1A or RELEASE COMPLETE (SS RETURN RESULT) 1.1B	[Successful] Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
7	ME → UICC	TERMINAL RESPONSE: SEND SS 2.1.1AA or TERMINAL RESPONSE: SEND SS 2.1.1AB	[Command performed successfully] Option AA applies if A.1/63 is supported, Option AB applies if A.1/63 is not supported

PROACTIVE COMMAND: SEND SS 2.3.1

Logically:

Command details

Command number: 1  
Command type: SEND SS  
Command qualifier: "00"

Device identities

Source device: UICC  
Destination device: Network

Alpha Identifier

Text: "Basic Icon"

SS String

TON: International  
NPI: "ISDN / telephone numbering plan"  
SS string: "\*\*\*21\*01234567890123456789\*10#"

Icon Identifier

Icon qualifier: icon is non self-explanatory  
 Icon Identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	2B	81	03	01	11	00	82	02	81	83	85
	0A	42	61	73	69	63	20	49	63	6F	6E	89
	10	91	AA	12	0A	21	43	65	87	09	21	43
	65	87	A9	01	FB	9E	02	01	01			

**Expected Sequence 2.3B (SEND SS, call forward unconditional, all bearers, successful, basic icon non self-explanatory)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 2.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 2.3.1	[BASIC-ICON, non self-explanatory]
4	ME → USER	Display "Basic Icon" without the icon	
5	ME → USS	REGISTER 1.1A Or REGISTER 1.1B	Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1A or RELEASE COMPLETE (SS RETURN RESULT) 1.1B	[Successful] Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
7	ME → UICC	TERMINAL RESPONSE: SEND SS 2.1.1BA or TERMINAL RESPONSE: SEND SS 2.1.1BB	[Command performed but requested icon could not be displayed] Option BA applies if A.1/63 is supported, Option BB applies if A.1/63 is not supported

**Expected Sequence 2.4 (SEND SS, call forward unconditional, all bearers, successful, basic icon non self-explanatory, no alpha identifier presented)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 2.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 2.4.1	[BASIC-ICON, non self-explanatory]
4	ME → UICC	TERMINAL RESPONSE: SEND SS 2.4.1	[Command data not understood by ME]

PROACTIVE COMMAND: SEND SS 2.4.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789#"

Icon Identifier

Icon qualifier: icon is non self-explanatory  
 Icon Identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	1D	81	03	01	11	00	82	02	81	83	89
	0E	91	AA	12	0A	21	43	65	87	09	21	43
	65	87	B9	9E	02	01	01					

TERMINAL RESPONSE: SEND SS 2.4.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command data not understood by ME

Coding:

BER-TLV:	81	03	01	11	00	82	02	82	81	83	01	32
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.11.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1A to 2.4.

#### 27.22.4.11.3 SEND SS (UCS2 display in Cyrillic)

##### 27.22.4.11.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.11.3.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5

Additionally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in: ISO/IEC 10646 [17].

##### 27.22.4.11.3.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.11.3.4 Method of test

###### 27.22.4.11.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.3.4.2 Procedure

**Expected Sequence 3.1 (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Cyrillic)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 3.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 3.1.1	
4	ME → USER	Display "ЗДРАВСТВУЙТЕ"	["Hello" in Russian]
5	ME → USS	REGISTER 1.1A Or REGISTER 1.1B	Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1A or RELEASE COMPLETE (SS RETURN RESULT) 1.1B	[Successful] Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported
7	ME → UICC	TERMINAL RESPONSE: SEND SS 1.1.1A or TERMINAL RESPONSE: SEND SS 1.1.1B	[Command performed successfully] Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported

PROACTIVE COMMAND: SEND SS 3.1.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha Identifier  
 Data coding scheme: UCS2 (16bit)  
 Text: "ЗДРАВСТВУЙТЕ"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	36	81	03	01	11	00	82	02	81	83	85
	19	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	89	10	91	AA	12	0A	21	43	65	87
	09	21	43	65	87	A9	01	FB				

27.22.4.11.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

27.22.4.11.4 SEND SS (support of Text Attribute)

27.22.4.11.4.1 SEND SS (support of Text Attribute – Left Alignment)

27.22.4.11.4.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.11.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

## 27.22.4.11.4.1.3 Test purpose

To verify that the ME displays the alpha identifier according to the left alignment text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.11.4.1.4 Method of test

## 27.22.4.11.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.4.1.4.2 Procedure

**Expected Sequence 4.1A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Left Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.1.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with left alignment]
5	ME → USS	REGISTER 4.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.1.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.1.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place]
12	ME → USS	REGISTER 4.1A	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	

**Expected Sequence 4.1B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Left Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.1.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with left alignment]
5	ME → USS	REGISTER 4.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.1.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.1.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place]
12	ME → USS	REGISTER 4.1B	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	

**PROACTIVE COMMAND: SEND SS 4.1.1**

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"

SS string: "\*\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

**PROACTIVE COMMAND: SEND SS 4.1.2**

Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

## REGISTER 4.1A

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1A

## REGISTER 4.1B

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1B

## RELEASE COMPLETE (SS RETURN RESULT) 4.1A

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1A

## RELEASE COMPLETE (SS RETURN RESULT) 4.1B

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1B

## TERMINAL RESPONSE: SEND SS 4.1.1A

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1A

## TERMINAL RESPONSE: SEND SS 4.1.1B

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1B

## 27.22.4.11.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

## 27.22.4.11.4.2 SEND SS (support of Text Attribute – Center Alignment)

## 27.22.4.11.4.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.11.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

## 27.22.4.11.4.2.3 Test purpose

To verify that the ME displays the alpha identifier according to the center alignment text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.11.4.2.4 Method of test

## 27.22.4.11.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.4.2.4.2 Procedure

**Expected Sequence 4.2A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Center Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.2.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with center alignment]
5	ME → USS	REGISTER 4.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.2.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.2.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with center alignment. Remark: If center alignment is the ME's default alignment as declared in table A.2/12, no alignment change will take place]
12	ME → USS	REGISTER 4.1A	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	

**Expected Sequence 4.2B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Center Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.2.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with center alignment]
5	ME → USS	REGISTER 4.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.2.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.2.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place]
12	ME → USS	REGISTER 4.1B	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	

**PROACTIVE COMMAND: SEND SS 4.2.1**

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	01	B4							

**PROACTIVE COMMAND: SEND SS 4.2.2**

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

27.22.4.11.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

27.22.4.11.4.3 SEND SS (support of Text Attribute – Right Alignment)

27.22.4.11.4.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.11.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

27.22.4.11.4.3.3 Test purpose

To verify that the ME displays the alpha identifier according to the right alignment text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.11.4.3.4 Method of test

27.22.4.11.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.4.3.4.2 Procedure

**Expected Sequence 4.3A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Right Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.3.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with right alignment]
5	ME → USS	REGISTER 4.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.3.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.3.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place]
12	ME → USS	REGISTER 4.1A	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	

**Expected Sequence 4.3B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Right Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.3.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with right alignment]
5	ME → USS	REGISTER 4.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.3.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.3.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place]
12	ME → USS	REGISTER 4.1B	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.3.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	02	B4							

PROACTIVE COMMAND: SEND SS 4.3.2

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

#### 27.22.4.11.4.4 SEND SS (support of Text Attribute – Large Font Size)

##### 27.22.4.11.4.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.11.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

##### 27.22.4.11.4.4.3 Test purpose

To verify that the ME displays the alpha identifier according to the large font size text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.11.4.4.4 Method of test

###### 27.22.4.11.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.4.4.2 Procedure

**Expected Sequence 4.4A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Large Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.4.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with large font size]
5	ME → USS	REGISTER 4.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.4.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.4.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with normal font size]
12	ME → USS	REGISTER 4.1A	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.4.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.4.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with large font size]
19	ME → USS	REGISTER 4.1A	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.4.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.4.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with normal font size]
26	ME → USS	REGISTER 4.1A	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	

**Expected Sequence 4.4B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Large Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.4.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with large font size]
5	ME → USS	REGISTER 4.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.4.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.4.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with normal font size]
12	ME → USS	REGISTER 4.1B	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.4.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.4.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with large font size]
19	ME → USS	REGISTER 4.1B	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.4.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.4.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with normal font size]
26	ME → USS	REGISTER 4.1B	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.4.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	04	B4							

## PROACTIVE COMMAND: SEND SS 4.4.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

## PROACTIVE COMMAND: SEND SS 4.4.3

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 3"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"

SS string:                    "\*\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.4.5      Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

#### 27.22.4.11.4.5      SEND SS (support of Text Attribute – Small Font Size)

##### 27.22.4.11.4.5.1      Definition and applicability

See clause 3.2.2.

##### 27.22.4.11.4.5.2      Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

##### 27.22.4.11.4.5.3      Test purpose

To verify that the ME displays the alpha identifier according to the small font size text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.11.4.5.4      Method of test

###### 27.22.4.11.4.5.4.1    Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.4.5.4.2 Procedure

**Expected Sequence 4.5A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Small Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.5.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with small font size]
5	ME → USS	REGISTER 4.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.5.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.5.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with normal font size]
12	ME → USS	REGISTER 4.1A	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.5.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.5.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with small font size]
19	ME → USS	REGISTER 4.1A	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.5.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.5.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with normal font size]
26	ME → USS	REGISTER 4.1A	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	

**Expected Sequence 4.5B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Small Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.5.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with small font size]
5	ME → USS	REGISTER 4.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.5.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.5.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with normal font size]
12	ME → USS	REGISTER 4.1B	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.5.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.5.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with small font size]
19	ME → USS	REGISTER 4.1B	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.5.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.5.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with normal font size]
26	ME → USS	REGISTER 4.1B	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.5.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	08	B4							

## PROACTIVE COMMAND: SEND SS 4.5.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

## PROACTIVE COMMAND: SEND SS 4.5.3

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 3"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"

SS string:                    "\*\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.5.5        Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

#### 27.22.4.11.4.6        SEND SS (support of Text Attribute – Bold On)

##### 27.22.4.11.4.6.1        Definition and applicability

See clause 3.2.2.

##### 27.22.4.11.4.6.2        Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

##### 27.22.4.11.4.6.3        Test purpose

To verify that the ME displays the alpha identifier according to the bold text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.11.4.6.4        Method of test

###### 27.22.4.11.4.6.4.1        Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.4.6.4.2 Procedure

**Expected Sequence 4.6A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Bold On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.6.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with bold on]
5	ME → USS	REGISTER 4.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.6.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.6.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with bold off]
12	ME → USS	REGISTER 4.1A	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.6.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.6.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with bold on]
19	ME → USS	REGISTER 4.1A	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.6.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.6.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with bold off]
26	ME → USS	REGISTER 4.1A	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	

**Expected Sequence 4.6B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Bold On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.6.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with bold on]
5	ME → USS	REGISTER 4.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.6.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.6.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with bold off]
12	ME → USS	REGISTER 4.1B	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.6.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.6.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with bold on]
19	ME → USS	REGISTER 4.1B	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.6.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.6.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with bold off]
26	ME → USS	REGISTER 4.1B	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.6.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	10	B4							

## PROACTIVE COMMAND: SEND SS 4.6.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

## PROACTIVE COMMAND: SEND SS 4.6.3

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 3"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

#### 27.22.4.11.4.7 SEND SS (support of Text Attribute – Italic On)

##### 27.22.4.11.4.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.11.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

##### 27.22.4.11.4.7.3 Test purpose

To verify that the ME displays the alpha identifier according to the italic text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.11.4.7.4 Method of test

###### 27.22.4.11.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.4.7.4.2 Procedure

**Expected Sequence 4.7A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Italic On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.7.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.7.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with italic on]
5	ME → USS	REGISTER 4.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.7.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.7.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with italic off]
12	ME → USS	REGISTER 4.1A	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.7.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.7.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with italic on]
19	ME → USS	REGISTER 4.1A	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.7.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.7.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with italic off]
26	ME → USS	REGISTER 4.1A	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	

**Expected Sequence 4.7B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Italic On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.7.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.7.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with italic on]
5	ME → USS	REGISTER 4.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.7.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.7.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with italic off]
12	ME → USS	REGISTER 4.1B	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.7.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.7.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with italic on]
19	ME → USS	REGISTER 4.1B	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.7.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.7.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with italic off]
26	ME → USS	REGISTER 4.1B	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.7.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	20	B4							

## PROACTIVE COMMAND: SEND SS 4.7.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

## PROACTIVE COMMAND: SEND SS 4.7.3

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 3"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

#### 27.22.4.11.4.8 SEND SS (support of Text Attribute – Underline On)

##### 27.22.4.11.4.8.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.11.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

##### 27.22.4.11.4.8.3 Test purpose

To verify that the ME displays the alpha identifier according to the underline text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.11.4.8.4 Method of test

###### 27.22.4.11.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.4.8.4.2 Procedure

**Expected Sequence 4.8A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Underline On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.8.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.8.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with underline on]
5	ME → USS	REGISTER 4.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.8.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.8.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with underline off]
12	ME → USS	REGISTER 4.1A	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.8.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.8.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with underline on]
19	ME → USS	REGISTER 4.1A	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.8.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.8.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with underline off]
26	ME → USS	REGISTER 4.1A	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	

**Expected Sequence 4.8B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Underline On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.8.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.8.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with underline on]
5	ME → USS	REGISTER 4.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.8.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.8.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with underline off]
12	ME → USS	REGISTER 4.1B	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.8.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.8.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with underline on]
19	ME → USS	REGISTER 4.1B	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.8.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.8.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with underline off]
26	ME → USS	REGISTER 4.1B	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.8.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	40	B4							

## PROACTIVE COMMAND: SEND SS 4.8.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

## PROACTIVE COMMAND: SEND SS 4.8.3

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 3"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"

SS string:                    `***21*01234567890123456789*10#`

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.8.5      Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

#### 27.22.4.11.4.9      SEND SS (support of Text Attribute – Strikethrough On)

##### 27.22.4.11.4.9.1      Definition and applicability

See clause 3.2.2.

##### 27.22.4.11.4.9.2      Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

##### 27.22.4.11.4.9.3      Test purpose

To verify that the ME displays the alpha identifier according to the strikethrough text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.11.4.9.4      Method of test

###### 27.22.4.11.4.9.4.1      Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.4.9.4.2 Procedure

**Expected Sequence 4.9A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Strikethrough On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.9.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.9.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with strikethrough on]
5	ME → USS	REGISTER 4.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.9.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.9.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with strikethrough off]
12	ME → USS	REGISTER 4.1A	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.9.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.9.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with strikethrough on]
19	ME → USS	REGISTER 4.1A	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.9.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.9.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with strikethrough off]
26	ME → USS	REGISTER 4.1A	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	

**Expected Sequence 4.9B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Strikethrough On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.9.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.9.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with striketrough on]
5	ME → USS	REGISTER 4.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.9.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.9.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with striketrough off]
12	ME → USS	REGISTER 4.1B	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.9.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND SS 4.9.1	
18	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with striketrough on]
19	ME → USS	REGISTER 4.1B	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
21	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.9.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND SS 4.9.3	
25	ME → USER	Display "Text Attribute 3"	[Message shall be formatted with striketrough off]
26	ME → USS	REGISTER 4.1B	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
28	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.9.1

Logically:

Command details

Command number: 1  
Command type: SEND SS  
Command qualifier: "00"

Device identities

Source device: UICC  
Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	80	B4							

## PROACTIVE COMMAND: SEND SS 4.9.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

## PROACTIVE COMMAND: SEND SS 4.9.3

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 3"

## SS String

TON: International

NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

#### 27.22.4.11.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

#### 27.22.4.11.4.10 SEND SS (support of Text Attribute – Foreground and Background Colour)

##### 27.22.4.11.4.10.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.11.4.10.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

##### 27.22.4.11.4.10.3 Test purpose

To verify that the ME displays the alpha identifier according to the foreground and background colour text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.11.4.10.4 Method of test

###### 27.22.4.11.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.4.10.4.2 Procedure

**Expected Sequence 4.10A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Foreground and Background Colour)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.10.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.10.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with foreground and background colour according to text attribute configuration]
5	ME → USS	REGISTER 4.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.10.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.10.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with ME"s default foreground and background colour]
12	ME → USS	REGISTER 4.1A	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1A	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1A	

**Expected Sequence 4.10B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Foreground and Background Colour)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.10.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 4.10.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with foreground and background colour according to text attribute configuration]
5	ME → USS	REGISTER 4.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 4.10.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND SS 4.10.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with ME"s default foreground and background colour]
12	ME → USS	REGISTER 4.1B	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1B	[Successful]
14	ME → UICC	TERMINAL RESPONSE: SEND SS 4.1.1B	

PROACTIVE COMMAND: SEND SS 4.10.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	33	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	D0
	04	00	10	00	B4							

## PROACTIVE COMMAND: SEND SS 4.10.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Coding:

BER-TLV:	D0	2D	81	03	01	11	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	89	10	91	AA	12	0A	21
	43	65	87	09	21	43	65	87	A9	01	FB	

## 27.22.4.11.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

## 27.22.4.11.5 SEND SS (UCS2 display in Chinese)

## 27.22.4.11.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.11.5.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5

Additionally, the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in: ISO/IEC 10646 [17].

## 27.22.4.11.5.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.11.5.4 Method of test

## 27.22.4.11.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.5.4.2 Procedure

#### Expected Sequence 5.1A (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Chinese)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 5.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 5.1.1	
4	ME → USER	Display "你好"	["Hello" in Chinese]
5	ME → USS	REGISTER 5.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 5.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 5.1.1A	[Command performed successfully]

#### Expected Sequence 5.1B (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Chinese)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 5.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 5.1.1	
4	ME → USER	Display "你好"	["Hello" in Chinese]
5	ME → USS	REGISTER 5.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 5.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 5.1.1B	[Command performed successfully]

PROACTIVE COMMAND: SEND SS 5.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha Identifier  
 Data coding scheme: UCS2 (16bit)  
 Text: "你好"

## SS String

TON: International  
 NPI: "ISDN / telephone numbering plan"  
 SS string: "\*\*\*21\*01234567890123456789\*10#"

## Coding:

BER-TLV:	D0	22	81	03	01	11	00	82	02	81	83	85
	05	80	4F	60	59	7D	89	10	91	AA	12	0A
	21	43	65	87	09	21	43	65	87	A9	01	FB

## REGISTER 5.1A

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1A

## REGISTER 5.1B

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1A

## RELEASE COMPLETE (SS RETURN RESULT) 5.1A

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1A

## RELEASE COMPLETE (SS RETURN RESULT) 5.1B

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1B

## TERMINAL RESPONSE: SEND SS 5.1.1A

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1A

## TERMINAL RESPONSE: SEND SS 5.1.1B

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1B

## 27.22.4.11.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

## 27.22.4.11.6 SEND SS (UCS2 display in Katakana)

## 27.22.4.11.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.11.6.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5

Additionally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in: ISO/IEC 10646 [17].

## 27.22.4.11.6.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.11.6.4 Method of test

## 27.22.4.11.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.11.6.4.2 Procedure

**Expected Sequence 6.1A (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Katakana)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 6.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 6.1.1	
4	ME → USER	Display "ル"	["Test" in Katakana]
5	ME → USS	REGISTER 6.1A	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 6.1A	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 6.1.1A	[Command performed successfully]

**Expected Sequence 6.1B (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Katakana)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND SS 6.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND SS 6.1.1	
4	ME → USER	Display "ル"	["Test" in Katakana]
5	ME → USS	REGISTER 6.1B	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 6.1B	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND SS 6.1.1B	[Command performed successfully]

PROACTIVE COMMAND: SEND SS 6.1.1

Logically:

Command details

Command number: 1  
 Command type: SEND SS  
 Command qualifier: "00"  
 Device identities  
   Source device: UICC  
   Destination device: Network  
   Alpha Identifier  
   Data coding scheme: UCS2 (16bit)  
   Text: "ル"  
 SS String  
   TON: International  
   NPI: "ISDN / telephone numbering plan"  
   SS string: "\*\*\*21\*01234567890123456789\*10#"

Coding:

BER-TLV:	D0	20	81	03	01	11	00	82	02	81	83	85
	03	80	30	EB	89	10	91	AA	12	0A	21	43
	65	87	09	21	43	65	87	A9	01	FB		

#### REGISTER 6.1A

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1A

#### REGISTER 6.1B

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1A

#### RELEASE COMPLETE (SS RETURN RESULT) 6.1A

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1A

#### RELEASE COMPLETE (SS RETURN RESULT) 6.1B

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1B

#### TERMINAL RESPONSE: SEND SS 6.1.1A

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1A

#### TERMINAL RESPONSE: SEND SS 6.1.1B

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1B

#### 27.22.4.11.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

### 27.22.4.12 SEND USSD

#### 27.22.4.12.1 SEND USSD (normal)

##### 27.22.4.12.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.12.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.
- ETSI TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in: ISO/IEC 10646 [17].

## 27.22.4.12.1.3 Test purpose

To verify that the ME correctly translates and sends the unstructured supplementary service request indicated in the SEND USSD proactive UICC command to the USS.

To verify that the ME returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the USSD request and including a USSD result as a text string in the TERMINAL RESPONSE.

## 27.22.4.12.1.4 Method of test

## 27.22.4.12.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.1.4.2 Procedure

**Expected Sequence 1.1 (SEND USSD, 7-bit data, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 1.1.1	
4	ME → USER	Display "7-bit USSD"	
5	ME → USS	REGISTER 1.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 1.1.1	

## PROACTIVE COMMAND: SEND USSD 1.1.1

Logically:

## Command details

Command number: 1  
Command type: SEND USSD  
Command qualifier: "00"

## Device identities

Source device: UICC  
Destination device: Network  
Alpha identifier: "7-bit USSD"

## USSD String

Data coding scheme: 7-bit default, no message class  
USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-  
1234567890"

Coding:

BER-TLV:	D0	50	81	03	01	12	00	82	02	81	83	85
	0A	37	2D	62	69	74	20	55	53	53	44	8A
	39	F0	41	E1	90	58	34	1E	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	CB	E6	33	3A	AD	5E	B3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60		

## REGISTER 1.1

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD string:

- "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

BER-TLV	30	3D	04	01	F0	04	38	41	E1	90	58	34
	1E	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

## RELEASE COMPLETE (SS RETURN RESULT) 1.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD string:

- "USSD string received from SS"

Coding:

BER-TLV	30	1E	04	01	F0	04	19	D5	E9	94	08	9A
	D3	E5	69	F7	19	24	2F	8F	CB	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

## TERMINAL RESPONSE: SEND USSD 1.1.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class

String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

**Expected Sequence 1.2 (SEND USSD, 8-bit data, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND	
2	ME → UICC	PENDING: SEND USSD 1.2.1	
3	UICC → ME	FETCH	
4	UICC → ME	PROACTIVE COMMAND: SEND USSD 1.2.1	
5	ME → USER	Display "8-bit USSD"	
6	ME → USS	REGISTER 1.2	
7	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.2	["USSD string received from SS"]
8	ME → UICC	TERMINAL RESPONSE: SEND USSD 1.2.1	

PROACTIVE COMMAND: SEND USSD 1.2.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "8-bit USSD"

USSD String

Data coding scheme: Uncompressed, no message class meaning, 8-bit data  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

BER-TLV:	D0	58	81	03	01	12	00	82	02	81	83	85
	0A	38	2D	62	69	74	20	55	53	53	44	8A
	41	44	41	42	43	44	45	46	47	48	49	4A
	4B	4C	4D	4E	4F	50	51	52	53	54	55	56
	57	58	59	5A	2D	61	62	63	64	65	66	67
	68	69	6A	6B	6C	6D	6E	6F	70	71	72	73
	74	75	76	77	78	79	7A	2D	31	32	33	34
	35	36	37	38	39	30						

REGISTER 1.2

Logically (only USSD argument):

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:  
 - Uncompressed, no message class meaning, 8-bit data  
 USSD string:  
 - "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

BER-TLV	30	45	04	01	44	04	40	41	42	43	44	45
	46	47	48	49	4A	4B	4C	4D	4E	4F	50	51
	52	53	54	55	56	57	58	59	5A	2D	61	62
	63	64	65	66	67	68	69	6A	6B	6C	6D	6E
	6F	70	71	72	73	74	75	76	77	78	79	7A
	2D	31	32	33	34	35	36	37	38	39	30	

## RELEASE COMPLETE (SS RETURN RESULT) 1.2

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- Uncompressed, no message class meaning, 8-bit data

USSD string:

- "USSD string received from SS"

Coding:

BER-TLV	30	21	04	01	44	04	1C	55	53	53	44	20
	73	74	72	69	6E	67	20	72	65	63	65	69
	76	65	64	20	66	72	6F	6D	20	53	53	

## TERMINAL RESPONSE: SEND USSD 1.2.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: Uncompressed, no message class meaning, 8-bit data

String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1D	04	55	53	53	44	20	73	74
	72	69	6E	67	20	72	65	63	65	69	76
	65	64	20	66	72	6F	6D	20	53	53	

## Expected Sequence 1.3 (SEND USSD, UCS2 data, successful)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 1.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 1.3.1	
4	ME → USER	Display "UCS2 USSD"	
5	ME → USS	REGISTER 1.3	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.3	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 1.3.1	

## PROACTIVE COMMAND: SEND USSD 1.3.1

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "UCS2 USSD"

## USSD String

Data coding scheme: Uncompressed, no message class meaning, UCS2 (16 bit)  
 USSD string: "ЗДРАВСТВУЙТЕ" ("Hello" in Russian)

Coding:

BER-TLV:	D0	2F	81	03	01	12	00	82	02	81	83	85
	09	55	43	53	32	20	55	53	53	44	8A	19
	48	04	17	04	14	04	20	04	10	04	12	04
	21	04	22	04	12	04	23	04	19	04	22	04
	15											

## REGISTER 1.3

Logically (only USSD argument):

## ProcessUnstructuredSS-Request ARGUMENT

## USSD-DataCodingScheme:

- Uncompressed, no message class meaning, UCS2 (16 bit)

## USSD string:

- "ЗДРАВСТВУЙТЕ" ("Hello" in Russian)

Coding:

BER-TLV	30	1D	04	01	48	04	18	04	17	04	14	04
	20	04	10	04	12	04	21	04	22	04	12	04
	23	04	19	04	22	04	15					

## RELEASE COMPLETE (SS RETURN RESULT) 1.3

Logically (only from USSD result):

## ProcessUnstructuredSS-Request RETURN RESULT

## USSD-DataCodingScheme:

- Uncompressed, no message class meaning, UCS2 (16 bit)

## USSD string:

- "USSD string received from SS"

Coding:

BER-TLV	30	3D	04	01	48	04	38	00	55	00	53	00
	53	00	44	00	20	00	73	00	74	00	72	00
	69	00	6E	00	67	00	20	00	72	00	65	00
	63	00	65	00	69	00	76	00	65	00	64	00
	20	00	66	00	72	00	6F	00	6D	00	20	00
	53	00	53									

## TERMINAL RESPONSE: SEND USSD 1.3.1

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Text String

Data coding scheme: Uncompressed, no message class meaning, UCS2 (16 bit)  
 String: "USSD string received from SS"

## Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	39	08	00	55	00	53	00	53	00
	44	00	20	00	73	00	74	00	72	00	69
	00	6E	00	67	00	20	00	72	00	65	00
	63	00	65	00	69	00	76	00	65	00	64
	00	20	00	66	00	72	00	6F	00	6D	00
	20	00	53	00	53						

**Expected Sequence 1.4 (SEND USSD, 7-bit data, unsuccessful (Return Error))**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 1.1.1	
4	ME → USER	Display "7-bit USSD"	
5	ME → USS	REGISTER 1.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN ERROR) 1.1	Return Error
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 1.4.1	

## RELEASE COMPLETE (SS RETURN ERROR) 1.1

Logically (only from Return Error code):

ProcessUnstructuredSS-Request RETURN ERROR  
 Return Error code:  
 - Unknown alphabet

## Coding:

Coding	02	01	47
--------	----	----	----

## TERMINAL RESPONSE: SEND USSD 1.4.1

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: USSD Return Error  
 Additional information: "Unknown alphabet"

## Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	02
	37	47									

**Expected Sequence 1.5 (SEND USSD, 7-bit data, unsuccessful (Reject))**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 1.1.1	
4	ME → USER	Display "7-bit USSD"	
5	ME → USS	REGISTER 1.1	
6	USS → ME	RELEASE COMPLETE (SS REJECT) 1.1	Reject
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 1.5.1	

RELEASE COMPLETE (SS REJECT) 1.1

Logically (only from Problem code):

ProcessUnstructuredSS-Request REJECT  
 Invoke Problem code:  
 - Mistyped parameter

Coding:

Coding	81	01	02
--------	----	----	----

TERMINAL RESPONSE: SEND USSD 1.5.1

Logically:

Command details  
 Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: USSD Return Error  
 Additional information: "No specific cause can be given"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	02
	37	00									

**Expected Sequence 1.6 (SEND USSD, 256 octets, 7-bit data, successful, long alpha identifier)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 1.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 1.6.1	
4	ME → USER	Display "once a RELEASE COMPLETE message containing the USSD Return Result message not containing an error has been received from the network, the ME shall inform the UICC that the command has"	
5	ME → USS	REGISTER 1.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 1.1.1	

PROACTIVE COMMAND: SEND USSD 1.6.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "once a RELEASE COMPLETE message containing the USSD Return Result message not containing an error has been received from the network, the ME shall inform the UICC that the command has"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

BER-TLV:	D0	81	FD	81	03	01	12	00	82	02	81	83
	85	81	B6	6F	6E	63	65	20	61	20	52	45
	4C	45	41	53	45	20	43	4F	4D	50	4C	45
	54	45	20	6D	65	73	73	61	67	65	20	63
	6F	6E	74	61	69	6E	69	6E	67	20	74	68
	65	20	55	53	44	20	52	65	74	75	72	
	6E	20	52	65	73	75	6C	74	20	6D	65	73
	73	61	67	65	20	6E	6F	74	20	63	6F	6E
	74	61	69	6E	69	6E	67	20	61	6E	20	65
	72	72	6F	72	20	68	61	73	20	62	65	65
	6E	20	72	65	63	65	69	76	65	64	20	66
	72	6F	6D	20	74	68	65	20	6E	65	74	77
	6F	72	6B	2C	20	74	68	65	20	4D	45	20
	73	68	61	6C	6C	20	69	6E	66	6F	72	6D
	20	74	68	65	20	53	49	4D	20	74	68	61
	74	20	74	68	65	20	63	6F	6D	6D	61	6E
	64	20	68	61	73	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

**Expected Sequence 1.7 (SEND USSD, 7-bit data, successful, no alpha identifier)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 1.7.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 1.7.1	
4	ME → USER	Optionally display an informative message	
5	ME → USS	REGISTER 1.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 1.1.1	

PROACTIVE COMMAND: SEND USSD 1.7.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

BER-TLV:	D0	44	81	03	01	12	00	82	02	81	83	8A
	39	F0	41	E1	90	58	34	1E	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	CB	E6	33	3A	AD	5E	B3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60		

**Expected Sequence 1.8 (SEND USSD, 7-bit data, successful, null length alpha identifier)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 1.8.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 1.8.1	
4	ME → USER	the ME should not give any information to the user on the fact that the ME is sending a USSD request	
5	ME → USS	REGISTER 1.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 1.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 1.1.1	

PROACTIVE COMMAND: SEND USSD 1.8.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: ""  
 USSD String  
 Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-  
 1234567890"

Coding:

BER-TLV:	D0	46	81	03	01	12	00	82	02	81	83	85
	00	8A	39	F0	41	E1	90	58	34	1E	91	49
	E5	92	D9	74	3E	A1	51	E9	94	5A	B5	5E
	B1	59	6D	2B	2C	1E	93	CB	E6	33	3A	AD
	5E	B3	DB	EE	37	3C	2E	9F	D3	EB	F6	3B
	3E	AF	6F	C5	64	33	5A	CD	76	C3	E5	60

#### 27.22.4.12.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 - 1.8.

#### 27.22.4.12.2 SEND USSD (Icon support)

##### 27.22.4.12.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.12.2.2 Conformance requirement

##### 27.22.4.12.2.3 Test purpose

To verify that the ME displays the text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

In addition to verify that if an icon is provided by the UICC, the icon indicated in the command may be used by the ME to inform the user, in addition to, or instead of the alpha identifier, as indicated with the icon qualifier.

##### 27.22.4.12.2.4 Method of test

###### 27.22.4.12.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS

The elementary files are coded as Toolkit default.

27.22.4.12.2.4.2 Procedure

**Expected Sequence 2.1A (SEND USSD, 7-bit data, successful, basic icon self explanatory, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 2.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 2.1.1	[BASIC-ICON, self-explanatory]
4	ME → USER	Display BASIC ICON	
5	ME → USS	REGISTER 2.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 2.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 2.1.1A	[Command performed successfully]

PROACTIVE COMMAND: SEND USSD 2.1.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Basic Icon"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Icon Identifier:

Icon qualifier: icon is self-explanatory  
 Icon Identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	54	81	03	01	12	00	82	02	81	83	85
	0A	42	61	73	69	63	20	49	63	6F	6E	8A
	39	F0	41	E1	90	58	34	1E	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	CB	E6	33	3A	AD	5E	B3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60	9E	02
	00	01										

REGISTER 2.1

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:  
 - 7-bit default, no message class  
 USSD string:  
 - "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

BER-TLV	30	3D	04	01	F0	04	38	41	E1	90	58	34
	1E	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

## RELEASE COMPLETE (SS RETURN RESULT) 2.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD string:

- "USSD string received from SS"

Coding:

BER-TLV	30	1E	04	01	F0	04	19	D5	E9	94	08	9A
	D3	E5	69	F7	19	24	2F	8F	CB	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

## TERMINAL RESPONSE: SEND USSD 2.1.1A

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class

String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

**Expected Sequence 2.1B (SEND USSD, 7-bit data, successful, basic icon self explanatory, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 2.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 2.1.1	[BASIC-ICON, self-explanatory]
4	ME → USER	Display "Basic Icon" without the icon	
5	ME → USS	REGISTER 2.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 2.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 2.1.1B	[Command performed but requested icon could not be displayed]

TERMINAL RESPONSE: SEND USSD 2.1.1B

Logically:

Command details

Command number: 1  
Command type: SEND USSD  
Command qualifier: "00"

Device identities

Source device: ME  
Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Text String

Data coding scheme: 7-bit default, no message class  
String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	04	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

**Expected Sequence 2.2 (SEND USSD, 7-bit data, successful, colour icon self explanatory)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 2.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 2.2.1	[COLOUR-ICON, self-explanatory]
4	ME → USER	Display COLOUR-ICON or May give information to user concerning what is happening	
5	ME → USS	REGISTER 2.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 2.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 2.1.1A or TERMINAL RESPONSE: SEND USSD 2.1.1B	[Command performed successfully] or [Command performed but requested icon could not be displayed]

PROACTIVE COMMAND: SEND USSD 2.2.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Color Icon"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Icon Identifier:

Icon qualifier: icon is self-explanatory  
 Icon Identifier: record 2 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	54	81	03	01	12	00	82	02	81	83	85
	0A	43	6F	6C	6F	72	20	49	63	6F	6E	8A
	39	F0	41	E1	90	58	34	1E	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	CB	E6	33	3A	AD	5E	B3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60	9E	02
	00	02										

**Expected Sequence 2.3A (SEND USSD, 7-bit data, successful, basic icon non self-explanatory, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 2.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 2.3.1	[BASIC-ICON, non self-explanatory]
4	ME → USER	Display "Basic Icon" and BASIC-ICON	
5	ME → USS	REGISTER 2.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 2.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 2.1.1A	[Command performed successfully]

PROACTIVE COMMAND: SEND USSD 2.3.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Basic Icon"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Icon Identifier

Icon qualifier: icon is non self-explanatory  
 Icon Identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	54	81	03	01	12	00	82	02	81	83	85
	0A	42	61	73	69	63	20	49	63	6F	6E	8A
	39	F0	41	E1	90	58	34	1E	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	CB	E6	33	3A	AD	5E	B3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60	9E	02
	01	01										

**Expected Sequence 2.3B (SEND USSD, 7-bit data, successful, basic icon non self-explanatory, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 2.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 2.3.1	[BASIC-ICON, non self-explanatory]
4	ME → USER	Display "Basic Icon" without the icon	
5	ME → USS	REGISTER 2.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 2.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 2.1.1B	[Command performed but requested icon could not be displayed]

**Expected Sequence 2.4 (SEND USSD, 7-bit data, basic icon non self-explanatory, no alpha identifier presented)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 2.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 2.4.1	[BASIC-ICON, non self-explanatory]
4	ME → UICC	TERMINAL RESPONSE: SEND USSD 2.4.1	[Command data not understood by ME]

PROACTIVE COMMAND: SEND USSD 2.4.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

Icon Identifier

Icon qualifier: icon is non self-explanatory

Icon Identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	48	81	03	01	12	00	82	02	81	83	8A
	39	F0	41	E1	90	58	34	1E	91	49	E5	92
	D9	74	3E	A1	51	E9	94	5A	B5	5E	B1	59
	6D	2B	2C	1E	93	CB	E6	33	3A	AD	5E	B3
	DB	EE	37	3C	2E	9F	D3	EB	F6	3B	3E	AF
	6F	C5	64	33	5A	CD	76	C3	E5	60	9E	02
	01	01										

TERMINAL RESPONSE: SEND USSD 2.4.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command data not understood by ME

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01	32
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.12.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 - 2.4.

#### 27.22.4.12.3 SEND USSD (UCS2 display in Cyrillic)

##### 27.22.4.12.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.12.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.
- ETSI TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in: ISO/IEC 10646 [17].

##### 27.22.4.12.3.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.12.3.4 Method of test

27.22.4.12.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.3.4.2 Procedure

**Expected Sequence 3.1 (SEND USSD, 7-bit data, successful, UCS2 text in Cyrillic)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 3.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 3.1.1	
4	ME → USER	Display "ЗДРАВСТВУЙТЕ"	["Hello" in Russian]
5	ME → USS	REGISTER 3.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 3.1	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 3.1.1	[Command performed successfully]

PROACTIVE COMMAND: SEND USSD 3.1.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha Identifier

Data coding scheme: UCS2 (16bit)  
 Text: "ЗДРАВСТВУЙТЕ"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD String: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

Coding:

BER-TLV:	D0	5F	81	03	01	12	00	82	02	81	83	85
	19	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	8A	39	F0	41	E1	90	58	34	1E	91
	49	E5	92	D9	74	3E	A1	51	E9	94	5A	B5
	5E	B1	59	6D	2B	2C	1E	93	CB	E6	33	3A
	AD	5E	B3	DB	EE	37	3C	2E	9F	D3	EB	F6
	3B	3E	AF	6F	C5	64	33	5A	CD	76	C3	E5
	60											

REGISTER 3.1

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:  
 - 7-bit default, no message class  
 USSD String:  
 - "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

BER-TLV	30	3D	04	01	F0	04	38	41	E1	90	58	34
	1E	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

RELEASE COMPLETE (SS RETURN RESULT) 3.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD String:

- "USSD string received from SS"

Coding:

BER-TLV	30	1E	04	01	F0	04	19	D5	E9	94	08	9A
	D3	E5	69	F7	19	24	2F	8F	CB	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

TERMINAL RESPONSE: SEND USSD 3.1.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class

String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

27.22.4.12.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

27.22.4.12.4 SEND USSD (support of Text Attribute)

27.22.4.12.4.1 SEND USSD (support of Text Attribute – Left Alignment)

27.22.4.12.4.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.12.4.1.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

## 27.22.4.12.4.1.3 Test purpose

To verify that the ME displays the alpha identifier according to the left alignment text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.12.4.1.4 Method of test

## 27.22.4.12.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.1.4.2 Procedure

**Expected Sequence 4.1 (SEND USSD, 7-bit data, successful, with Text Attribute – Left Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.1.1	
4	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with left alignment]
5	ME → USS	REGISTER 4.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.1.1	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.1.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.1.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed without left alignment. Remark: If left alignment is the ME's default alignment as declared in table A.2/13, no alignment change will take place]
12	ME → USS	REGISTER 4.1	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.1.1	

PROACTIVE COMMAND: SEND USSD 4.1.1

Logically:

Command details

Command number: 1  
Command type: SEND USSD  
Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Text Attribute 1"  
 USSD String  
 Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	00	B4		

PROACTIVE COMMAND: SEND USSD 4.1.2

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

REGISTER 4.1

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:  
 - 7-bit default, no message class  
 USSD string:  
 - "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

Coding	30	3D	04	01	F0	04	40	41	E1	90	58	34
	1E	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

RELEASE COMPLETE (SS RETURN RESULT) 4.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD string:

- "USSD string received from SS"

Coding:

BER-TLV	30	1E	04	01	F0	04	19	D5	E9	94	08	9A
	D3	E5	69	F7	19	24	2F	8F	CB	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

TERMINAL RESPONSE: SEND USSD 4.1.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class

String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

27.22.4.12.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

27.22.4.12.4.2 SEND USSD (support of Text Attribute – Center Alignment)

27.22.4.12.4.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.12.4.2.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

## 27.22.4.12.4.2.3 Test purpose

To verify that the ME displays the alpha identifier according to the center alignment text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.12.4.2.4 Method of test

## 27.22.4.12.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.2.4.2 Procedure

**Expected Sequence 4.2 (SEND USSD, 7-bit data, successful, with Text Attribute – Center Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.2.1	
4	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with center alignment]
5	ME → USS	REGISTER 4.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.2.1	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.2.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.2.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed without center alignment. Remark: If center alignment is the ME's default alignment as declared in table A.2/13, no alignment change will take place]
12	ME → USS	REGISTER 4.1	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.2.1	

PROACTIVE COMMAND: SEND USSD 4.2.1

Logically:

Command details

Command number: 1  
Command type: SEND USSD  
Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Text Attribute 1"  
 USSD String  
 Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	01	B4		

PROACTIVE COMMAND: SEND USSD 4.2.2

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.2.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Text String  
 Data coding scheme: 7-bit default, no message class  
 String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

#### 27.22.4.12.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

#### 27.22.4.12.4.3 SEND USSD (support of Text Attribute – Right Alignment)

##### 27.22.4.12.4.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.12.4.3.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

##### 27.22.4.12.4.3.3 Test purpose

To verify that the ME displays the alpha identifier according to the right alignment text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.12.4.3.4 Method of test

###### 27.22.4.12.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.3.4.2 Procedure

**Expected Sequence 4.3 (SEND USSD, 7-bit data, successful, with Text Attribute – Right Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.3.1	
4	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with right alignment]
5	ME → USS	REGISTER 4.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.3.1	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.3.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.3.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed without right alignment. Remark: If right alignment is the ME's default alignment as declared in table A.2/13, no alignment change will take place]
12	ME → USS	REGISTER 4.1	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.3.1	

PROACTIVE COMMAND: SEND USSD 4.3.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-  
 1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	02	B4		

## PROACTIVE COMMAND: SEND USSD 4.3.2

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-  
 1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

## TERMINAL RESPONSE: SEND USSD 4.3.1

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Text String

Data coding scheme: 7-bit default, no message class  
 String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

#### 27.22.4.12.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

#### 27.22.4.12.4.4 SEND USSD (support of Text Attribute – Large Font Size)

##### 27.22.4.12.4.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.12.4.4.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

##### 27.22.4.12.4.4.3 Test purpose

To verify that the ME displays the alpha identifier according to the large font size text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.12.4.4.4 Method of test

###### 27.22.4.12.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.4.2 Procedure

**Expected Sequence 4.4 (SEND USSD, 7-bit data, successful, with Text Attribute – Large Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.4.1	
4	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with large font size]
5	ME → USS	REGISTER 4.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.4.1	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.4.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.4.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed with normal font size]
12	ME → USS	REGISTER 4.1	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.4.1	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.4.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.4.1	
18	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with large font size]
19	ME → USS	REGISTER 4.1	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
21	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.4.1	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.4.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.4.3	
25	ME → USER	Display "Text Attribute 3"	[Alpha identifier is displayed with normal font size]
26	ME → USS	REGISTER 4.1	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
28	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.4.1	

PROACTIVE COMMAND: SEND USSD 4.4.1

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

## USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	04	B4		

## PROACTIVE COMMAND: SEND USSD 4.4.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND USSD 4.4.3

## Logically:

## Command details

Command number: 1  
 Command type: SEND USSD

Command qualifier: "00"  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Text Attribute 3"  
 USSD String  
 Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.4.1

Logically:

Command details  
 Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Text String  
 Data coding scheme: 7-bit default, no message class  
 String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

27.22.4.12.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

27.22.4.12.4.5 SEND USSD (support of Text Attribute – Small Font Size)

27.22.4.12.4.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.4.5.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

#### 27.22.4.12.4.5.3 Test purpose

To verify that the ME displays the alpha identifier according to the small font size text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.5.4 Method of test

##### 27.22.4.12.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.5.4.2 Procedure

**Expected Sequence 4.5 (SEND USSD, 7-bit data, successful, with Text Attribute – Small Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.5.1	
4	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with small font size]
5	ME → USS	REGISTER 4.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.5.1	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.5.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.5.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed with normal font size]
12	ME → USS	REGISTER 4.1	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.5.1	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.5.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.5.1	
18	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with small font size]
19	ME → USS	REGISTER 4.1	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
21	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.5.1	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.5.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.5.3	
25	ME → USER	Display "Text Attribute 3"	[Alpha identifier is displayed with normal font size]
26	ME → USS	REGISTER 4.1	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
28	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.5.1	

PROACTIVE COMMAND: SEND USSD 4.5.1

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	08	B4		

PROACTIVE COMMAND: SEND USSD 4.5.2

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	00	B4		

PROACTIVE COMMAND: SEND USSD 4.5.3

Logically:

Command details

Command number: 1  
 Command type: SEND USSD

Command qualifier: "00"  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Text Attribute 3"  
 USSD String  
 Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-  
 1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.5.1

Logically:

Command details  
 Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Text String  
 Data coding scheme: 7-bit default, no message class  
 String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

#### 27.22.4.12.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

#### 27.22.4.12.4.6 SEND USSD (support of Text Attribute – Bold On)

##### 27.22.4.12.4.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.12.4.6.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

## 27.22.4.12.4.6.3 Test purpose

To verify that the ME displays the alpha identifier according to the bold text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.12.4.6.4 Method of test

## 27.22.4.12.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.6.4.2 Procedure

**Expected Sequence 4.6 (SEND USSD, 7-bit data, successful, with Text Attribute – Bold On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.6.1	
4	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with bold on]
5	ME → USS	REGISTER 4.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.6.1	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.6.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.6.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed with bold off]
12	ME → USS	REGISTER 4.1	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.6.1	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.6.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.6.1	
18	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with bold on]
19	ME → USS	REGISTER 4.1	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
21	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.6.1	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.6.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.6.3	
25	ME → USER	Display "Text Attribute 3"	[Alpha identifier is displayed with bold off]
26	ME → USS	REGISTER 4.1	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
28	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.6.1	

PROACTIVE COMMAND: SEND USSD 4.6.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	10	B4		

PROACTIVE COMMAND: SEND USSD 4.6.2

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND USSD 4.6.3

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 3"

## USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

## TERMINAL RESPONSE: SEND USSD 4.6.1

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Text String

Data coding scheme: 7-bit default, no message class  
 String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

#### 27.22.4.12.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

#### 27.22.4.12.4.7 SEND USSD (support of Text Attribute – Italic On)

##### 27.22.4.12.4.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.12.4.7.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

##### 27.22.4.12.4.7.3 Test purpose

To verify that the ME displays the alpha identifier according to the italic text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.12.4.7.4 Method of test

###### 27.22.4.12.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.7.4.2 Procedure

**Expected Sequence 4.7 (SEND USSD, 7-bit data, successful, with Text Attribute – Italic On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.7.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.7.1	
4	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with italic on]
5	ME → USS	REGISTER 4.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.7.1	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.7.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.7.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed with italic off]
12	ME → USS	REGISTER 4.1	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.7.1	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.7.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.7.1	
18	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with italic on]
19	ME → USS	REGISTER 4.1	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
21	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.7.1	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.7.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.7.3	
25	ME → USER	Display "Text Attribute 3"	[Alpha identifier is displayed with italic off]
26	ME → USS	REGISTER 4.1	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
28	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.7.1	

PROACTIVE COMMAND: SEND USSD 4.7.1

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

## USSD String

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	20	B4		

## PROACTIVE COMMAND: SEND USSD 4.7.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND USSD 4.7.3

## Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Text Attribute 3"  
 USSD String  
 Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-  
 1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.7.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class  
 String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

27.22.4.12.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

27.22.4.12.4.8 SEND USSD (support of Text Attribute – Underline On)

27.22.4.12.4.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.4.8.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

#### 27.22.4.12.4.8.3 Test purpose

To verify that the ME displays the alpha identifier according to the underline text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.8.4 Method of test

##### 27.22.4.12.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.8.4.2 Procedure

**Expected Sequence 4.8 (SEND USSD, 7-bit data, successful, with Text Attribute – Underline On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.8.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.8.1	
4	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with underline on]
5	ME → USS	REGISTER 4.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.8.1	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.8.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.8.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed with underline off]
12	ME → USS	REGISTER 4.1	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.8.1	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.8.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.8.1	
18	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with underline on]
19	ME → USS	REGISTER 4.1	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
21	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.8.1	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.8.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.8.3	
25	ME → USER	Display "Text Attribute 3"	[Alpha identifier is displayed with underline off]
26	ME → USS	REGISTER 4.1	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
28	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.8.1	

PROACTIVE COMMAND: SEND USSD 4.8.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	40	B4		

PROACTIVE COMMAND: SEND USSD 4.8.2

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	00	B4		

PROACTIVE COMMAND: SEND USSD 4.8.3

Logically:

Command details

Command number: 1  
 Command type: SEND USSD

Command qualifier: "00"  
 Device identities  
   Source device: UICC  
   Destination device: Network  
 Alpha identifier: "Text Attribute 3"  
 USSD String  
   Data coding scheme: 7-bit default, no message class  
   USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-  
 1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.8.1

Logically:

Command details  
   Command number: 1  
   Command type: SEND USSD  
   Command qualifier: "00"  
 Device identities  
   Source device: ME  
   Destination device: UICC  
 Result  
   General Result: Command performed successfully  
 Text String  
   Data coding scheme: 7-bit default, no message class  
   String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

#### 27.22.4.12.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

#### 27.22.4.12.4.9 SEND USSD (support of Text Attribute – Strikethrough On)

##### 27.22.4.12.4.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.12.4.9.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

#### 27.22.4.12.4.9.3 Test purpose

To verify that the ME displays the alpha identifier according to the strikethrough text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.9.4 Method of test

##### 27.22.4.12.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.9.4.2 Procedure

**Expected Sequence 4.9 (SEND USSD, 7-bit data, successful, with Text Attribute – Strikethrough On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.9.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.9.1	
4	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with strikethrough on]
5	ME → USS	REGISTER 4.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.9.1	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.9.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.9.2	
11	ME → USER	Display "Text Attribute 2"	[Alpha identifier is displayed with strikethrough off]
12	ME → USS	REGISTER 4.1	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.9.1	
15	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.9.1	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.9.1	
18	ME → USER	Display "Text Attribute 1"	[Alpha identifier is displayed with strikethrough on]
19	ME → USS	REGISTER 4.1	
20	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
21	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.9.1	
22	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.9.3	
23	ME → UICC	FETCH	
24	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.9.3	
25	ME → USER	Display "Text Attribute 3"	[Alpha identifier is displayed with strikethrough off]
26	ME → USS	REGISTER 4.1	
27	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
28	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.9.1	

PROACTIVE COMMAND: SEND USSD 4.9.1

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 1"

## USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	80	B4		

## PROACTIVE COMMAND: SEND USSD 4.9.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

## USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	00	B4		

## PROACTIVE COMMAND: SEND USSD 4.9.3

## Logically:

## Command details

Command number: 1  
 Command type: SEND USSD

Command qualifier: "00"  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Text Attribute 3"  
 USSD String  
 Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	33	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.9.1

Logically:

Command details  
 Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Text String  
 Data coding scheme: 7-bit default, no message class  
 String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

#### 27.22.4.12.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

#### 27.22.4.12.4.10 SEND USSD (support of Text Attribute – Foreground and Background Colour)

##### 27.22.4.12.4.10.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.12.4.10.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

## 27.22.4.12.4.10.3 Test purpose

To verify that the ME displays the alpha identifier according to the foreground and background colour text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.12.4.10.4 Method of test

## 27.22.4.12.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.4.10.4.2 Procedure

**Expected Sequence 4.10 (SEND USSD, 7-bit data, successful, with Text Attribute – Foreground and Background Colour)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.10.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.10.1	
4	ME → USER	Display "Text Attribute 1"	[Message shall be formatted with foreground and background colour according to text attribute configuration]
5	ME → USS	REGISTER 4.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.10.1	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 4.10.2	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND USSD 4.10.2	
11	ME → USER	Display "Text Attribute 2"	[Message shall be formatted with ME's default foreground and background colour]
12	ME → USS	REGISTER 4.1	
13	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 4.1	["USSD string received from SS"]
14	ME → UICC	TERMINAL RESPONSE: SEND USSD 4.10.1	

PROACTIVE COMMAND: SEND USSD 4.10.1

Logically:

## Command details

Command number: 1  
Command type: SEND USSD  
Command qualifier: "00"

## Device identities

Source device: UICC  
Destination device: Network

Alpha identifier: "Text Attribute 1"

## USSD String

Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	5C	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	31	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60	D0	04	00	10	00	B4		

PROACTIVE COMMAND: SEND USSD 4.10.2

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Text Attribute 2"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD string: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

BER-TLV:	D0	56	81	03	01	12	00	82	02	81	83	85
	10	54	65	78	74	20	41	74	74	72	69	62
	75	74	65	20	32	8A	39	F0	41	E1	90	58
	34	1E	91	49	E5	92	D9	74	3E	A1	51	E9
	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB
	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F
	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD
	76	C3	E5	60								

TERMINAL RESPONSE: SEND USSD 4.10.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class

String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

#### 27.22.4.12.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

#### 27.22.4.12.5 SEND USSD (UCS2 display in Chinese)

##### 27.22.4.12.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.12.5.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.
- ETSI TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in: ISO/IEC 10646 [17].

##### 27.22.4.12.5.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.12.5.4 Method of test

###### 27.22.4.12.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

###### 27.22.4.12.5.4.2 Procedure

#### Expected Sequence 5.1 (SEND USSD, 7-bit data, successful, UCS2 text in Chinese)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 5.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 5.1.1	
4	ME → USER	Display "你好"	["Hello" in Chinese]
5	ME → USS	REGISTER 5.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 5.1	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 5.1.1	[Command performed successfully]

PROACTIVE COMMAND: SEND USSD 5.1.1

Logically:

Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha Identifier

Data coding scheme: UCS2 (16bit)  
 Text: "你好"

USSD String

Data coding scheme: 7-bit default, no message class  
 USSD String: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

BER-TLV:	D0	4B	81	03	01	12	00	82	02	81	83	85
	05	80	4F	60	59	7D	8A	39	F0	41	E1	90
	58	34	1E	91	49	E5	92	D9	74	3E	A1	51
	E9	94	5A	B5	5E	B1	59	6D	2B	2C	1E	93
	CB	E6	33	3A	AD	5E	B3	DB	EE	37	3C	2E
	9F	D3	EB	F6	3B	3E	AF	6F	C5	64	33	5A
	CD	76	C3	E5	60							

REGISTER 5.1

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:  
 - 7-bit default, no message class  
 USSD String:  
 - "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

Coding	30	3D	04	01	F0	04	38	41	E1	90	58	34
	1E	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

RELEASE COMPLETE (SS RETURN RESULT) 5.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:  
 - 7-bit default, no message class  
 USSD String:  
 - "USSD string received from SS"

Coding:

Coding	30	1E	04	01	00	04	19	D5	E9	94	08	9A
	D3	E5	69	F7	19	24	2F	8F	CB	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

## TERMINAL RESPONSE: SEND USSD 5.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Text String

Data coding scheme: 7-bit default, no message class  
 String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

## 27.22.4.12.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

## 27.22.4.12.6 SEND USSD (UCS2 display in Katakana)

## 27.22.4.12.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.12.6.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.
- ETSI TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in: ISO/IEC 10646 [17].

## 27.22.4.12.6.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.12.6.4 Method of test

## 27.22.4.12.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.12.6.4.2 Procedure

**Expected Sequence 6.1 (SEND USSD, 7-bit data, successful, UCS2 text in Katakana)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SEND USSD 6.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SEND USSD 6.1.1	
4	ME → USER	Display "ル"	["Test" in Katakana]
5	ME → USS	REGISTER 6.1	
6	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 6.1	[Successful]
7	ME → UICC	TERMINAL RESPONSE: SEND USSD 6.1.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND USSD 6.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND USSD  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

## Alpha Identifier

Data coding scheme: UCS2 (16bit)  
 Text: "ル"

## USSD String

Data coding scheme: 7-bit default, no message class  
 USSD String: "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

BER-TLV:	D0	49	81	03	01	12	00	82	02	81	83	85
	03	80	30	EB	8A	39	F0	41	E1	90	58	34
	1E	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

## REGISTER 6.1

Logically (only USSD argument)

## ProcessUnstructuredSS-Request ARGUMENT

USSD-DataCodingScheme:  
 - 7-bit default, no message class

USSD String:  
 - "ABCDEFGHJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxy-1234567890"

Coding:

Coding	30	3D	04	01	F0	04	38	41	E1	90	58	34
	1E	91	49	E5	92	D9	74	3E	A1	51	E9	94
	5A	B5	5E	B1	59	6D	2B	2C	1E	93	CB	E6
	33	3A	AD	5E	B3	DB	EE	37	3C	2E	9F	D3
	EB	F6	3B	3E	AF	6F	C5	64	33	5A	CD	76
	C3	E5	60									

RELEASE COMPLETE (SS RETURN RESULT) 6.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT

USSD-DataCodingScheme:

- 7-bit default, no message class

USSD String:

- "USSD string received from SS"

Coding:

Coding	30	1E	04	01	00	04	19	D5	E9	94	08	9A
	D3	E5	69	F7	19	24	2F	8F	CB	69	7B	99
	0C	32	CB	DF	6D	D0	74	0A				

TERMINAL RESPONSE: SEND USSD 6.1.1

Logically:

Command details

Command number: 1

Command type: SEND USSD

Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Text String

Data coding scheme: 7-bit default, no message class

String: "USSD string received from SS"

Coding:

BER-TLV:	81	03	01	12	00	82	02	82	81	83	01
	00	8D	1A	00	D5	E9	94	08	9A	D3	E5
	69	F7	19	24	2F	8F	CB	69	7B	99	0C
	32	CB	DF	6D	D0	74	0A				

27.22.4.12.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

## 27.22.4.13 SET UP CALL

### 27.22.4.13.1 SET UP CALL (normal)

#### 27.22.4.13.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.1.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

#### 27.22.4.13.1.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.1.4 Method of test

##### 27.22.4.13.1.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.13.1.4.2 Procedure

#### Expected Sequence 1.1 (SET UP CALL, call confirmed by the user and connected)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.1.1	
4	ME → USER	ME displays "Not busy" during user confirmation phase.	
5	USER → ME	The user confirms the call set up	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456"	
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 1.1.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns to idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 1.1.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Not busy"  
 Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"

Coding:

BER-TLV:	D0	1E	81	03	01	10	00	82	02	81	83	85
	08	4E	6F	74	20	62	75	73	79	86	09	91
	10	32	04	21	43	65	1C	2C				

TERMINAL RESPONSE: SET UP CALL 1.1.1

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### Expected Sequence 1.2 (SET UP CALL, call rejected by the user)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.1.1	
4	ME → USER	ME displays "Not busy" during the user confirmation phase	
5	USER → ME	The user rejects the set up call	[user rejects the call]
6	ME → UICC	TERMINAL RESPONSE 1.2.1	[User did not accept call set-up request]
7	ME → USER	The ME returns in idle mode.	

TERMINAL RESPONSE: SET UP CALL 1.2.1

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result

General Result: User did not accept the proactive command  
 Additional Information: This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	Note 1	22	Note 2
----------	----	----	----	----	----	----	----	----	----	----	--------	----	--------

Note 1: Length of BER-TLV is '01' plus length of the optional Additional Information parameter.

Note 2: Additional Information parameter may be present at this place.

Expected Sequence 1.3void

**Expected Sequence 1.4 (SET UP CALL, putting all other calls on hold, ME busy)**

ME is busy on a call

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.4.1	[putting all other calls on hold]
4	ME → USER	ME displays "On hold" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirms the call]
6	ME → USS	The active call is put on hold	
7	ME → USS	The ME attempts to set up a call to "+012340123456"	
8	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
9	ME → UICC	TERMINAL RESPONSE 1.4.1	[Command performed successfully]
10	USER → ME	The user ends the call after 10 s. The ME retrieves the previous call automatically or on request of the user.	

**PROACTIVE COMMAND: SET UP CALL 1.4.1**

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: putting all other calls on hold

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "On hold"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"

Coding:

BER-TLV:	D0	1D	81	03	01	10	02	82	02	81	83	85
	07	4F	6E	20	68	6F	6C	64	86	09	91	10
	32	04	21	43	65	1C	2C					

**TERMINAL RESPONSE: SET UP CALL 1.4.1**

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: putting all other calls on hold

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	02	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.5 (SET UP CALL, disconnecting all other calls, ME busy)**

ME is busy on a call

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.5.1	[disconnecting all other calls]
4	ME → USER	ME displays "Disconnect" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirms the call]
6	ME → USS	The ME disconnects the active call	
7	ME → USS	The ME attempts to set up a call to "+012340123456"	
8	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
9	ME → UICC	TERMINAL RESPONSE 1.5.1	[Command performed successfully]
10	USER → ME	The user ends the call after 10 s.	

**PROACTIVE COMMAND: SET UP CALL 1.5.1**

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: disconnecting all other calls

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Disconnect"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"

Coding:

BER-TLV:	D0	20	81	03	01	10	04	82	02	81	83	85
	0A	44	69	73	63	6F	6E	6E	65	63	74	86
	09	91	10	32	04	21	43	65	1C	2C		

TERMINAL RESPONSE: SET UP CALL 1.5.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: putting all other calls on hold

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	04	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.6 (SET UP CALL, only if not currently busy on another call, ME busy)**

ME is busy on a call

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.1.1	[only if not currently busy on another call]
4	ME → UICC	TERMINAL RESPONSE 1.6.1	[ME currently unable to process command]

TERMINAL RESPONSE: SET UP CALL 1.6.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: ME currently unable to process command  
 Additional Information: ME currently busy on call

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	02	20
	02											

**Expected Sequence 1.7 (SET UP CALL, putting all other calls on hold, call hold is not allowed)**

ME is busy on a call. The USS shall be configured to not allow Call Hold.

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.4.1	[putting all other calls on hold]
4	ME → USER	ME displays "On hold" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirms the call]
6	ME → USS	The ME attempts to put the active call on hold.	
7	USS → ME	The ME receives the HOLD REJECT message from the USS.	
8	ME → UICC	TERMINAL RESPONSE 1.7.1	[Network currently unable to process command]

## TERMINAL RESPONSE: SET UP CALL 1.7.1

Logically:

## Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: putting all other calls on hold

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Network currently unable to process command  
 Additional Information: No specific cause can be given

Coding:

BER-TLV:	81	03	01	10	02	82	02	82	81	83	02	21
	00											

## Expected Sequence 1.8 (SET UP CALL, Capability configuration)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.8.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.8.1	[Capability configuration parameters: full rate support]
4	ME → USER	ME displays "Capability config" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456" using the capability configuration parameters supplied by UICC	
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 1.8.1	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s The ME returns in idle mode.	

## PROACTIVE COMMAND: SET UP CALL 1.8.1

Logically:

## Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: if not busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Capability config"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"

Capability configuration parameters  
 Information transfer cap: full rate support only MS

Coding:

BER-TLV:	D0	2B	81	03	01	10	00	82	02	81	83	85
	11	43	61	70	61	62	69	6C	69	74	79	20
	63	6F	6E	66	69	67	86	09	91	10	32	04
	21	43	65	1C	2C	87	02	01	A0			

TERMINAL RESPONSE: SET UP CALL 1.8.1

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: if not busy on another call

Device identities  
 Source device: ME  
 Destination device: UICC

Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.9 (SET UP CALL, max dialling number string, no alpha identifier)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.9.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND SET UP CALL 1.9.1	[dialling number string, no alpha identifier]
4	USER → ME	The user confirms the set up call	[user confirmation]
5	ME→USS	The ME attempts to set up a call to "01234567890123456789012345678901"	
6	USS → ME	The ME receives the CONNECT message from the USS.	
7	ME → UICC	TERMINAL RESPONSE 1.9.1	[Command performed successfully]
8	USER → ME	The user ends the call The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 1.9.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call with redial  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "01234567890123456789012345678901"

Coding:

BER-TLV:	D0	1C	81	03	01	10	01	82	02	81	83	86
	11	91	10	32	54	76	98	10	32	54	76	98
	10	32	54	76	98	10						

TERMINAL RESPONSE: SET UP CALL 1.9.1

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call with redial  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	01	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.10 (SET UP CALL,256 octets length, long first alpha identifier)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.10.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.10.1	[ alpha identifier]
4	ME → USER	ME displays "Three types are defined: - set up a call, but only if not currently busy on another call; - set up a call, putting all other calls (if any) on hold; - set up a call, disconnecting all other calls (if any) first. For each of these types, " during the user confirmation phase.	
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME→USS	The ME attempts to set up a call to "+01"	
7	USS → ME	The ME receives the CONNECT message from the USS.	
8	ME → UICC	TERMINAL RESPONSE 1.10.1	[Command performed successfully]
9	USER → ME	The user ends the call The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 1.10.1

Logically:

Command details  
 Command number: 1

Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call with redial

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Three types are defined: - set up a call, but only if not currently busy on another call; - set up a call, putting all other calls (if any) on hold; - set up a call, disconnecting all other calls (if any) first. For each of these types, "

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "01"

Coding:

BER-TLV:	D0	81	FD	81	03	01	10	01	82	02	81	83
	85	81	ED	54	68	72	65	65	20	74	79	70
	65	73	20	61	72	65	20	64	65	66	69	6E
	65	64	3A	20	2D	20	73	65	74	20	75	70
	20	61	20	63	61	6C	6C	2C	20	62	75	74
	20	6F	6E	6C	79	20	69	66	20	6E	6F	74
	20	63	75	72	72	65	6E	74	6C	79	20	62
	75	73	79	20	6F	6E	20	61	6E	6F	74	68
	65	72	20	63	61	6C	6C	3B	20	2D	20	73
	65	74	20	75	70	20	61	20	63	61	6C	6C
	2C	20	70	75	74	74	69	6E	67	20	61	6C
	6C	20	6F	74	68	65	72	20	63	61	6C	6C
	73	20	28	69	66	20	61	6E	79	29	20	6F
	6E	20	68	6F	6C	64	3B	20	2D	20	73	65
	74	20	75	70	20	61	20	63	61	6C	6C	2C
	20	64	69	73	63	6F	6E	6E	65	63	74	69
	6E	67	20	61	6C	6C	20	6F	74	68	65	72
	20	63	61	6C	6C	73	20	28	69	66	20	61
	6E	79	29	20	66	69	72	73	74	2E	20	46
	6F	72	20	65	61	63	68	20	6F	66	20	74
	68	65	73	65	20	74	79	70	65	73	2C	20
	86	02	91	10								

TERMINAL RESPONSE: SET UP CALL 1.10.1

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call with redial

Device identities  
 Source device: ME  
 Destination device: UICC

Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	01	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.11A (SET UP CALL, Called party subaddress, command performed successfully)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.11.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.11.1	[set up a call with called party subaddress]
4	ME → USER	ME displays "Called party" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456" with the called party subaddress information	
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 1.11.1A	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s The ME returns in idle mode.	

**Expected Sequence 1.11B (SET UP CALL, Called party subaddress, ME not supporting the called party subaddress)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.11.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.11.1	[set up a call with called party subaddress]
4	ME → UICC	TERMINAL RESPONSE 1.11.1B	[beyond ME's capabilities]

PROACTIVE COMMAND: SET UP CALL 1.11.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: if not busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Called party"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"

Called party subaddress

Type of subaddress: NSAP (X.213 / ISO 8348 AD2)  
 Odd / even indicator: even number of address signals  
 Subaddress information: AFI, 95, 95, 95, 95, 95

Coding:

BER-TLV:	D0	2B	81	03	01	10	00	82	02	81	83	85
	0C	43	61	6C	6C	65	64	20	70	61	72	74
	79	86	09	91	10	32	04	21	43	65	1C	2C
	88	07	80	50	95	95	95	95	95			

TERMINAL RESPONSE: SET UP CALL 1.11.1A

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: if not busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: SET UP CALL 1.11.1B

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: if not busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Beyond ME's capabilities  
 Additional Information: This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	Note 1	30	Note 2
----------	----	----	----	----	----	----	----	----	----	----	--------	----	--------

Note 1: Length of BER-TLV is '01' plus length of the optional Additional Information parameter.

Note 2: Additional Information parameter may be present at this place.

### Expected Sequence 1.12 (SET UP CALL, maximum duration for the redial mechanism)

The USS shall be configured such that call set up requests will be rejected with cause "User Busy".

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 1.12.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.12.1	[only if not currently busy on another call with redial]
4	ME → USER	ME displays "Duration" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirms the call]
6	ME → USS	ME attempts to set up a call to "+012340123456" . It stops its attempts after 10 seconds.	[redial mechanism with maximum duration of 10 seconds]]
7	ME → UICC	TERMINAL RESPONSE 1.12.1	[network currently unable to process command]
8	ME → USER	The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 1.12.1

Logically:

## Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call with redial

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Duration"

## Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"

## Duration

Unit: Seconds  
 Interval: 10

## Coding:

BER-TLV:	D0	22	81	03	01	10	01	82	02	81	83	85
	08	44	75	72	61	74	69	6F	6E	86	09	91
	10	32	04	21	43	65	1C	2C	84	02	01	0A

## TERMINAL RESPONSE: SET UP CALL 1.12.1

## Logically:

## Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call with redial

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: network currently unable to process command  
 Additional Information: User Busy

## Coding:

BER-TLV:	81	03	01	10	01	82	02	82	81	83	02	21
	91											

## 27.22.4.13.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.12.

## 27.22.4.13.2 SET UP CALL (second alpha identifier)

## 27.22.4.13.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.13.2.2 Conformance requirement

Same as clause 27.22.4.13.2.1.

## 27.22.4.13.2.3 Test purpose

To verify that the ME accepts a Proactive Command - Set Up Call, displays the alpha identifiers to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.2.4 Method of test

27.22.4.13.2.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and is in updated idle mode on the USS.

27.22.4.13.2.4.2 Procedure

#### Expected Sequence 2.1 (SET UP CALL, two alpha identifiers)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 2.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 2.1.1	
4	ME → USER	ME displays "CONFIRMATION" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL"	[second alpha identifier]
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 2.1.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 2.1.1

Logically:

##### Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

##### Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION"

##### Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL"

Coding:

BER-TLV:	D0	28	81	03	01	10	00	82	02	81	83	85
	0C	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	86	09	91	10	32	04	21	43	65	1C	2C
	85	04	43	41	4C	4C						

#### TERMINAL RESPONSE: SET UP CALL 2.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.13.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

27.22.4.13.3 SET UP CALL (display of icons)

27.22.4.13.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.13.3.2 Conformance requirement

27.22.4.13.3.3 Test purpose

To verify that the ME accepts a Proactive Set Up Call , displays the message or icon to the user ,attempts to set up a call to the address, returns the result in the TERMINAL response.

27.22.4.13.3.4 Method of test

27.22.4.13.3.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and is in updated idle mode on the USS.

27.22.4.13.3.4.2 Procedure

**Expected Sequence 3.1A (SET UP CALL, display of basic icon during confirmation phase, not self-explanatory, successful )**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND	Including icon identifier, icon shall be displayed in addition of the first alpha identifier  [user confirmation]  [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] [Command performed successfully]
2	ME → UICC	PENDING: SET UP CALL 3.1.1	
3	UICC → ME	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 3.1.1	
4	ME → USER	ME displays "Set up call Icon 3.1.1" and the basic icon during a user confirmation phase.	
5	USER → ME	The user confirms the set up call	
6	ME → USS	The ME attempts to set up a call to "+012340123456"	
7	USS → ME	The ME receives the CONNECT message from the USS.	
8	ME → UICC	TERMINAL RESPONSE 3.1.1A	
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 3.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Set up call Icon 3.1.1"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"

Icon identifier

Icon qualifier: icon is not self-explanatory  
 Icon identifier: <record 1 in EF IMG>

Coding:

BER-TLV:	D0	30	81	03	01	10	00	82	02	81	83	85
	16	53	65	74	20	75	70	20	63	61	6C	6C
	20	49	63	6F	6E	20	33	2E	31	2E	31	86
	09	91	10	32	04	21	43	65	1C	2C	9E	02
	01	01										

TERMINAL RESPONSE: SET UP CALL 3.1.1A

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 3.1B (SET UP CALL, display of basic icon during confirmation phase, not self-explanatory, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 3.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 3.1.1	Including icon identifier, icon shall be displayed in addition of the first alpha identifier
4	ME → USER	ME displays "Set up call Icon 3.1.1" without the basic icon during a user confirmation phase.	
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME→USS	The ME attempts to set up a call to "+012340123456"	
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 3.1.1B	[Command performed successfully, but requested icon could not be displayed].
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

**TERMINAL RESPONSE: SET UP CALL 3.1.1B**

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	04
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 3.2A (SET UP CALL, display of basic icon during confirmation phase, self-explanatory, successful )**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 3.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 3.2.1	Including icon identifier, icon shall be displayed instead of the first alpha identifier
4	ME → USER	ME displays the basic icon during a user confirmation phase.	
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456"	
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 3.2.1A	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

**PROACTIVE COMMAND: SET UP CALL 3.2.1**

Logically:

Command details

- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities

- Source device: UICC
- Destination device: Network
- Alpha identifier: "Set up call Icon 3.2.1"

Address

- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"

Icon identifier

- Icon qualifier: icon is self-explanatory
- Icon identifier: <record 1 in EF IMG>

Coding:

BER-TLV:	D0	30	81	03	01	10	00	82	02	81	83	85
	16	53	65	74	20	75	70	20	63	61	6C	6C
	20	49	63	6F	6E	20	33	2E	32	2E	31	86
	09	91	10	32	04	21	43	65	1C	2C	9E	02
	00	01										

**TERMINAL RESPONSE: SET UP CALL 3.2.1A**

Logically:

Command details

- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities

- Source device: ME
- Destination device: UICC

Result

- General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 3.2B (SET UP CALL, display of basic icon during confirmation phase, self-explanatory, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 3.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 3.2.1	Including icon identifier, icon shall be displayed instead of the first alpha identifier
4	ME → USER	ME display "Set up call Icon 3.2.1" without the icon	
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456"	
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 3.2.1B	[Command performed successfully, but requested icon could not be displayed].
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

**TERMINAL RESPONSE: SET UP CALL 3.2.1B**

Logically:

Command details

- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities

- Source device: ME
- Destination device: UICC

Result

- General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	04
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 3.3A (SET UP CALL, display of colour icon during confirmation phase, not self-explanatory, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND	Including icon identifier, icon shall be displayed in addition of the first alpha identifier  [user confirmation]  [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] [Command performed successfully]
2	ME → UICC	PENDING: SET UP CALL 3.3.1	
3	UICC → ME	FETCH	
4	ME → USER	PROACTIVE COMMAND: SET UP CALL 3.3.1 ME displays "Set up call Icon 3.3.1" and the colour icon during a user confirmation phase.	
5	USER → ME	The user confirms the set up call	
6	ME → USS	The ME attempts to set up a call to "+012340123456"	
7	USS → ME	The ME receives the CONNECT message from the USS.	
8	ME → UICC	TERMINAL RESPONSE 3.3.1A	
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

**PROACTIVE COMMAND: SET UP CALL 3.3.1**

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Set up call Icon 3.3.1"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"

Icon identifier

Icon qualifier: icon is not self-explanatory  
 Icon identifier: <record 2 in EF IMG>

Coding:

BER-TLV:	D0	30	81	03	01	10	00	82	02	81	83	85
	16	53	65	74	20	75	70	20	63	61	6C	6C
	20	49	63	6F	6E	20	33	2E	33	2E	31	86
	09	91	10	32	04	21	43	65	1C	2C	9E	02
	01	02										

**TERMINAL RESPONSE: SET UP CALL 3.3.1A**

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 3.3B (SET UP CALL, display of colour icon during confirmation phase, not self-explanatory, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 3.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 3.3.1	Including icon identifier, icon shall be displayed in addition of the first alpha identifier
4	ME → USER	ME only display alpha string: " Set up call Icon 3.3.1"	
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456"	
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 3.3.1B	[Command performed successfully, but requested icon could not be displayed].
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

TERMINAL RESPONSE: SET UP CALL 3.3.1B

Logically:

Command details

- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities

- Source device: ME
- Destination device: UICC

Result

- General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	04
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 3.4A (SET UP CALL, display of self explanatory basic icon during set up call, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 3.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 3.4.1	Including a second alpha identifier and two icons
4	ME → USER	ME displays the basic icon during a user confirmation phase.	
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays the basic icon without the text during the set up call.	
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 3.4.1A	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 3.4.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Set up call Icon 3.4.1"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"

Icon identifier

Icon qualifier: icon is self-explanatory  
 Icon identifier: <record 1 in EF IMG>

Alpha identifier: "Set up call Icon 3.4.2"

Icon identifier

Icon qualifier: icon is self-explanatory  
 Icon identifier: <record 1 in EF IMG>

Coding:

BER-TLV:	D0	4C	81	03	01	10	00	82	02	81	83	85
	16	53	65	74	20	75	70	20	63	61	6C	6C
	20	49	63	6F	6E	20	33	2E	34	2E	31	86
	09	91	10	32	04	21	43	65	1C	2C	9E	02
	00	01	85	16	53	65	74	20	75	70	20	63
	61	6C	6C	20	49	63	6F	6E	20	33	2E	34
	2E	32	9E	02	00	01						

TERMINAL RESPONSE: SET UP CALL 3.4.1A

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 3.4B (SET UP CALL, display of self explanatory basic icon during set up call, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 3.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 3.4.1	Including a second alpha identifier and two icons
4	ME → USER	ME displays "Set up call Icon 3.4.1" without the icon	
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "Set up call Icon 3.4.2" without the icon during the set up call.	
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 3.4.1B	[Command performed successfully, but requested icon could not be displayed].
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

TERMINAL RESPONSE: SET UP CALL 3.4.1B

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	04
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.13.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1A to 3.4B.

#### 27.22.4.13.4 SET UP CALL (support of Text Attribute)

##### 27.22.4.13.4.1 SET UP CALL (support of Text Attribute – Left Alignment)

###### 27.22.4.13.4.1.1 Definition and applicability

See clause 3.2.2.

###### 27.22.4.13.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

###### 27.22.4.13.4.1.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the left alignment text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

###### 27.22.4.13.4.1.4 Method of test

###### 27.22.4.13.4.1.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.1.4.2 Procedure

**Expected Sequence 4.1 (SET UP CALL, Text Attribute – Left Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.1.1	
4	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with left alignment]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with left alignment]
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 4.1.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.1.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.1.2	
13	ME → USER	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	USER → ME	The user confirms the set up call	[User confirmation shall be formatted without left alignment. Remark: If left alignment is the ME's default alignment as declared in table A.2/14, no alignment change will take place]
15	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2"	[Second alpha identifier shall be formatted without left alignment. Remark: If left alignment is the ME's default alignment as declared in table A.2/14, no alignment change will take place]
16	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.1.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	USER → ME	The user ends the call after 18 s. The ME returns in idle mode.	

## PROACTIVE COMMAND: SET UP CALL 4.1.1

## Logically:

## Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 1"

## Address

TON: International

NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 1"  
 Text Attribute (user confirmation phase)  
 Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background  
 Text Attribute (call set up phase)  
 Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0E	00	B4	D0	04	00	06	00	B4		

PROACTIVE COMMAND: SET UP CALL 4.1.2

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 2"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 2"

Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32		

TERMINAL RESPONSE: SET UP CALL 4.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

#### 27.22.4.13.4.2 SET UP CALL (support of Text Attribute – Center Alignment)

##### 27.22.4.13.4.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

##### 27.22.4.13.4.2.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the center alignment text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.4.2.4 Method of test

###### 27.22.4.13.4.2.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.2.4.2 Procedure

**Expected Sequence 4.2 (SET UP CALL, Text Attribute – Center Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.2.1	
4	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with center alignment]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with center alignment]
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 4.2.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.2.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.2.2	
13	ME → USER	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	USER → ME	The user confirms the set up call	[User confirmation shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/14, no alignment change will take place]
15	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2"	[Second alpha identifier shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/14, no alignment change will take place]
16	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.2.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

## PROACTIVE COMMAND: SET UP CALL 4.2.1

Logically:

## Command details

Command number: 1  
Command type: SET UP CALL  
Command qualifier: only if not currently busy on another call

## Device identities

Source device: UICC  
Destination device: Network  
Alpha identifier: "CONFIRMATION 1"

## Address

TON: International

NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 1"  
 Text Attribute (user confirmation phase)  
   Formatting position: 0  
   Formatting length: 14  
   Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
   Colour: Dark Green Foreground, Bright Yellow Background  
 Text Attribute (call set up phase)  
   Formatting position: 0  
   Formatting length: 6  
   Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
   Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0E	01	B4	D0	04	00	06	01	B4		

PROACTIVE COMMAND: SET UP CALL 4.2.2

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 2"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 2"

Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32		

TERMINAL RESPONSE: SET UP CALL 4.2.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

#### 27.22.4.13.4.3 SET UP CALL (support of Text Attribute – Right Alignment)

##### 27.22.4.13.4.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

##### 27.22.4.13.4.3.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the right alignment text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.4.3.4 Method of test

###### 27.22.4.13.4.3.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.3.4.2 Procedure

**Expected Sequence 4.3 (SET UP CALL, Text Attribute – Right Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.3.1	
4	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with right alignment]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with right alignment]
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 4.3.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.3.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.3.2	
13	ME → USER	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	USER → ME	The user confirms the set up call	[User confirmation shall be formatted without right alignment. Remark: If right alignment is the ME's default alignment as declared in table A.2/14, no alignment change will take place]
15	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2"	[Second alpha identifier shall be formatted without right alignment. Remark: If right alignment is the ME's default alignment as declared in table A.2/14, no alignment change will take place]
16	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.3.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

## PROACTIVE COMMAND: SET UP CALL 4.3.1

## Logically:

## Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 1"

## Address

TON: International

NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 1"  
 Text Attribute (user confirmation phase)  
 Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background  
 Text Attribute (call set up phase)  
 Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0E	02	B4	D0	04	00	06	02	B4		

PROACTIVE COMMAND: SET UP CALL 4.3.2

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 2"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 2"

Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32		

TERMINAL RESPONSE: SET UP CALL 4.3.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

#### 27.22.4.13.4.4 SET UP CALL (support of Text Attribute – Large Font Size)

##### 27.22.4.13.4.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

##### 27.22.4.13.4.4.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the large font size text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.4.4.4 Method of test

###### 27.22.4.13.4.4.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.4.2 Procedure

**Expected Sequence 4.4 (SET UP CALL, Text Attribute – Large Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.4.1	
4	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with large font size]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with large font size]
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 4.4.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.4.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.4.2	
13	ME → USER	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	USER → ME	The user confirms the set up call	[user confirmation is displayed with normal font size]
15	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2"	[second alpha identifier is displayed with normal font size]
16	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.4.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
19	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.4.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.4.1	
22	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
23	USER → ME	The user confirms the set up call	[user confirmation is displayed with large font size]
24	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with large font size]
25	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
26	ME → UICC	TERMINAL RESPONSE 4.4.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
27	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
28	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.4.3	
29	ME → UICC	FETCH	

30	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.4.3	
31	ME → USER	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	USER → ME	The user confirms the set up call	[user confirmation is displayed with normal font size]
33	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3"	[second alpha identifier is displayed with normal font size]
34	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	ME → UICC	TERMINAL RESPONSE 4.4.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
36	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 4.4.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 1"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0E	04	B4	D0	04	00	06	04	B4		

PROACTIVE COMMAND: SET UP CALL 4.4.2

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 2"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)  
 Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)  
 Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0E	00	B4	D0	04	00	06	00	B4		

PROACTIVE COMMAND: SET UP CALL 4.4.3

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 3"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 3"

Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

TERMINAL RESPONSE: SET UP CALL 4.4.1

Logically:

Command details  
 Command number: 1

Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

#### 27.22.4.13.4.5 SET UP CALL (support of Text Attribute – Small Font Size)

##### 27.22.4.13.4.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.4.5.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

##### 27.22.4.13.4.5.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the small font size text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.4.4.5 Method of test

##### 27.22.4.13.4.4.5.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.4.5.2 Procedure

**Expected Sequence 4.5 (SET UP CALL, Text Attribute – Small Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.5.1	
4	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with small font size]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with small font size]
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 4.5.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.5.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.5.2	
13	ME → USER	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	USER → ME	The user confirms the set up call	[user confirmation is displayed with normal font size]
15	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2"	[second alpha identifier is displayed with normal font size]
16	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.5.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
19	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.5.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.5.1	
22	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
23	USER → ME	The user confirms the set up call	[user confirmation is displayed with small font size]
24	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with small font size]
25	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
26	ME → UICC	TERMINAL RESPONSE 4.5.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
27	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
28	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.5.3	
29	ME → UICC	FETCH	

30	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.5.3	
31	ME → USER	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	USER → ME	The user confirms the set up call	[user confirmation is displayed with normal font size]
33	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3"	[second alpha identifier is displayed with normal font size]
34	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	ME → UICC	TERMINAL RESPONSE 4.5.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
36	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 4.5.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 1"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0E	08	B4	D0	04	00	06	08	B4		

PROACTIVE COMMAND: SET UP CALL 4.5.2

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 2"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)  
 Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)  
 Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0E	00	B4	D0	04	00	06	00	B4		

PROACTIVE COMMAND: SET UP CALL 4.5.3

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 3"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 3"

Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

TERMINAL RESPONSE: SET UP CALL 4.5.1

Logically:

Command details  
 Command number: 1

Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

#### 27.22.4.13.4.6 SET UP CALL (support of Text Attribute – Bold On)

##### 27.22.4.13.4.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.4.6.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

##### 27.22.4.13.4.6.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the bold text attribute configuration to the user, attempts to set up a call to the address and returns the result in the **TERMINAL RESPONSE**.

##### 27.22.4.13.4.6.4 Method of test

###### 27.22.4.13.4.6.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.6.4.2 Procedure

**Expected Sequence 4.6 (SET UP CALL, Text Attribute – Bold On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.6.1	
4	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with bold on]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with bold on]
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 4.6.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.6.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.6.2	
13	ME → USER	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	USER → ME	The user confirms the set up call	[user confirmation is displayed with bold off]
15	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2"	[second alpha identifier is displayed with bold off]
16	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.6.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
19	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.6.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.6.1	
22	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
23	USER → ME	The user confirms the set up call	[user confirmation is displayed with bold on]
24	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with bold on]
25	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
26	ME → UICC	TERMINAL RESPONSE 4.6.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
27	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
28	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.6.3	
29	ME → UICC	FETCH	

30	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.6.3	
31	ME → USER	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	USER → ME	The user confirms the set up call	[user confirmation is displayed with bold off]
33	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3"	[second alpha identifier is displayed with bold off]
34	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	ME → UICC	TERMINAL RESPONSE 4.6.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
36	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 4.6.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 1"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0E	10	B4	D0	04	00	06	10	B4		

PROACTIVE COMMAND: SET UP CALL 4.6.2

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 2"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)  
 Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)  
 Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0E	00	B4	D0	04	00	06	00	B4		

PROACTIVE COMMAND: SET UP CALL 4.6.3

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 3"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 3"

Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

TERMINAL RESPONSE: SET UP CALL 4.6.1

Logically:

Command details  
 Command number: 1

Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

#### 27.22.4.13.4.7 SET UP CALL (support of Text Attribute – Italic On)

##### 27.22.4.13.4.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

##### 27.22.4.13.4.7.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the italic text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.4.7.4 Method of test

###### 27.22.4.13.4.7.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.7.4.2 Procedure

**Expected Sequence 4.7 (SET UP CALL, Text Attribute – *Italic On*)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.7.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.7.1	
4	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with italic on]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with italic on]
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.7.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.7.2	
13	ME → USER	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	USER → ME	The user confirms the set up call	[user confirmation is displayed with italic off]
15	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2"	[second alpha identifier is displayed with italic off]
16	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
19	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.7.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.7.1	
22	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
23	USER → ME	The user confirms the set up call	[user confirmation is displayed with italic on]
24	ME , USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with italic on]
25	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
26	ME → UICC	TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
27	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
28	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.7.3	
29	ME → UICC	FETCH	

30	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.7.3	
31	ME → USER	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	USER → ME	The user confirms the set up call	[user confirmation is displayed with italic off]
33	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3"	[second alpha identifier is displayed with italic off]
34	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	ME → UICC	TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
36	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 4.7.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 1"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0E	20	B4	D0	04	00	06	20	B4		

PROACTIVE COMMAND: SET UP CALL 4.7.2

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 2"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)  
 Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)  
 Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0E	00	B4	D0	04	00	06	00	B4		

## PROACTIVE COMMAND: SET UP CALL 4.7.3

## Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 3"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 3"

## Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

## TERMINAL RESPONSE: SET UP CALL 4.7.1

## Logically:

Command details  
 Command number: 1

Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

#### 27.22.4.13.4.8 SET UP CALL (support of Text Attribute – Underline On)

##### 27.22.4.13.4.8.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

##### 27.22.4.13.4.8.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the underline text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.4.8.4 Method of test

###### 27.22.4.13.4.8.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.8.4.2 Procedure

**Expected Sequence 4.8 (SET UP CALL, Text Attribute – Underline On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.8.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.8.1	
4	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with underline on]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with underline on]
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 4.8.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.8.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.8.2	
13	ME → USER	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	USER → ME	The user confirms the set up call	[user confirmation is displayed with underline off]
15	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2"	[second alpha identifier is displayed with underline off]
16	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.8.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
19	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.8.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.8.1	
22	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
23	USER → ME	The user confirms the set up call	[user confirmation is displayed with underline on]
24	ME , USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with underline on]
25	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
26	ME → UICC	TERMINAL RESPONSE 4.8.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
27	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
28	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.8.3	
29	ME → UICC	FETCH	

30	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.8.3	
31	ME → USER	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	USER → ME	The user confirms the set up call	[user confirmation is displayed with underline off]
33	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3"	[second alpha identifier is displayed with Undeline off]
34	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	ME → UICC	TERMINAL RESPONSE 4.8.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
36	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 4.8.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 1"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0E	40	B4	D0	04	00	06	40	B4		

PROACTIVE COMMAND: SET UP CALL 4.8.2

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 2"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)  
 Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)  
 Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0E	00	B4	D0	04	00	06	00	B4		

PROACTIVE COMMAND: SET UP CALL 4.8.3

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 3"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 3"

Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

TERMINAL RESPONSE: SET UP CALL 4.8.1

Logically:

Command details  
 Command number: 1

Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

#### 27.22.4.13.4.9 SET UP CALL (support of Text Attribute – Strikethrough On)

##### 27.22.4.13.4.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.4.9.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

##### 27.22.4.13.4.9.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the strikethrough text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.4.9.4 Method of test

###### 27.22.4.13.4.9.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.9.4.2 Procedure

**Expected Sequence 4.9 (SET UP CALL, Text Attribute – Strikethrough On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.9.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.9.1	
4	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with strikethrough on]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with strikethrough on]
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.9.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.9.2	
13	ME → USER	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	USER → ME	The user confirms the set up call	[user confirmation is displayed with strikethrough off]
15	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2"	[second alpha identifier is displayed with strikethrough off]
16	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
19	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.9.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.9.1	
22	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
23	USER → ME	The user confirms the set up call	[user confirmation is displayed with strikethrough on]
24	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with strikethrough on]
25	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
26	ME → UICC	TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
27	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
28	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.9.3	
29	ME → UICC	FETCH	

30	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.9.3	
31	ME → USER	ME displays "CONFIRMATION 3" during the user confirmation phase	
32	USER → ME	The user confirms the set up call	[user confirmation is displayed with strikethrough off]
33	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3"	[second alpha identifier is displayed with strikethrough off]
34	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
35	ME → UICC	TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
36	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

PROACTIVE COMMAND: SET UP CALL 4.9.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 1"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0E	80	B4	D0	04	00	06	80	B4		

PROACTIVE COMMAND: SET UP CALL 4.9.2

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 2"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)  
 Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)  
 Formatting position: 0  
 Formatting length: 6  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32	D0	04
	00	0E	00	B4	D0	04	00	06	00	B4		

PROACTIVE COMMAND: SET UP CALL 4.9.3

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 3"

Address  
 TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 3"

Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	33	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	33		

TERMINAL RESPONSE: SET UP CALL 4.9.1

Logically:

Command details  
 Command number: 1

Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

#### 27.22.4.13.4.10 SET UP CALL (support of Text Attribute – Foreground and Background Colour)

##### 27.22.4.13.4.10.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.4.10.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

##### 27.22.4.13.4.10.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the foreground and background colour text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.4.10.4 Method of test

###### 27.22.4.13.4.10.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

## 27.22.4.13.4.10.4.2 Procedure

**Expected Sequence 4.10 (SET UP CALL, Text Attribute – Foreground and Background Colour)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.10.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.10.1	
4	ME → USER	ME displays "CONFIRMATION 1" during the user confirmation phase	
5	USER → ME	The user confirms the set up call	[user confirmation is displayed with foreground and background colour according to Text Attribute configuration]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1"	[second alpha identifier is displayed with foreground and background colour according to Text Attribute configuration]
7	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
8	ME → UICC	TERMINAL RESPONSE 4.10.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 4.10.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: SET UP CALL 4.10.2	
13	ME → USER	ME displays "CONFIRMATION 2" during the user confirmation phase	
14	USER → ME	The user confirms the set up call	[user confirmation is displayed with ME's default foreground and background colour]
15	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2"	[second alpha identifier is displayed with ME's default foreground and background colour]
16	USS → ME	The ME receives the CONNECT message from the USS.	[The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way]
17	ME → UICC	TERMINAL RESPONSE 4.10.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
18	USER → ME	The user ends the call after 10 s. The ME returns in idle mode.	

## PROACTIVE COMMAND: SET UP CALL 4.10.1

## Logically:

## Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "CONFIRMATION 1"

## Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456p1p2"  
 Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)

Formatting position: 0

Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)

Formatting position: 0

Formatting length: 6

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Bright Yellow Foreground, Dark Green Background

Coding:

BER-TLV:	D0	38	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	31	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	31	D0	04
	00	0E	00	B4	D0	04	00	06	00	4B		

PROACTIVE COMMAND: SET UP CALL 4.10.2

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC

Destination device: Network

Alpha identifier: "CONFIRMATION 2"

Address

TON: International

NPI: ISDN / telephone numbering plan

Dialling number string: "012340123456p1p2"

Alpha Identifier (call set up phase): "CALL 2"

Coding:

BER-TLV:	D0	2C	81	03	01	10	00	82	02	81	83	85
	0E	43	4F	4E	46	49	52	4D	41	54	49	4F
	4E	20	32	86	09	91	10	32	04	21	43	65
	1C	2C	85	06	43	41	4C	4C	20	32		

TERMINAL RESPONSE: SET UP CALL 4.10.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL

Command qualifier: only if not currently busy on another call

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

#### 27.22.4.13.5 SET UP CALL (UCS2 Display in **Cyrillic**)

##### 27.22.4.13.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.5.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

The ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646 [17].

##### 27.22.4.13.5.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier with UCS2 coding to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.5.4 Method of test

###### 27.22.4.13.5.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.13.5.4.2 Procedure

**Expected Sequence 5.1 (SET UP CALL with UCS2 – Cyrillic Characters, call confirmed by the user and connected)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 5.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 5.1.1	
4	ME → USER	ME displays "ЗДРАВСТВУЙТЕ" during user confirmation phase.	["ЗДРАВСТВУЙТЕ": 'Hello' in Russian]
5	USER → ME	The user confirms the call set up	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456"	
7	USS → ME	The ME receives the CONNECT message from the USS.	
8	ME → UICC	TERMINAL RESPONSE 5.1.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 5 s. The ME returns to idle mode.	

PROACTIVE COMMAND: SET UP CALL 5.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456"

Coding:

BER-TLV:	D0	2D	81	03	01	10	00	82	02	81	83	85
	19	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	86	07	91	10	32	04	21	43	65	

TERMINAL RESPONSE: SET UP CALL 5.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 5.2 (SET UP CALL, two alpha identifiers coded in UCS2 – Cyrillic Characters)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 5.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 5.2.1	
4	ME → USER	ME displays "ЗДРАВСТВУЙТЕ1" during the user confirmation phase	[ЗДРАВСТВУЙТЕ1: 'Hello1' in Russian]
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456".	[second alpha identifier] [ЗДРАВСТВУЙТЕ2: 'Hello2' in Russian]
7	USS → ME	The ME displays "ЗДРАВСТВУЙТЕ2" The ME receives the CONNECT message from the USS.	
8	ME → UICC	TERMINAL RESPONSE 5.2.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 5 s. The ME returns in idle mode.	

**PROACTIVE COMMAND: SET UP CALL 5.2.1**

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ1"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456"  
 Alpha Identifier (call set up phase): "ЗДРАВСТВУЙТЕ2"

Coding:

BER-TLV:	D0	4C	81	03	01	10	00	82	02	81	83	85
	1B	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	00	31	86	09	91	0E	32	04	21	43
	65	85	1B	80	04	17	04	14	04	20	04	10
	04	12	04	21	04	22	04	12	04	23	04	19
	04	22	04	15	00							

**TERMINAL RESPONSE: SET UP CALL 5.2.1**

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 5.1 to 5.2.

#### 27.22.4.13.6 SET UP CALL (UCS2 Display in Chinese)

##### 27.22.4.13.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.6.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

The ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in:

- ISO/IEC 10646 [17].

##### 27.22.4.13.6.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier with UCS2 coding to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.6.4 Method of test

###### 27.22.4.13.6.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.13.6.4.2 Procedure

**Expected Sequence 6.1 (SET UP CALL with UCS2 – Chinese characters, call confirmed by the user and connected)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 6.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 6.1.1	
4	ME → USER	ME displays "不忙" during user confirmation phase.	['不忙' : 'Not Busy' in Chinese]
5	USER → ME	The user confirms the call set up	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456"	
7	USS → ME	The ME receives the CONNECT message from the USS.	
8	ME → UICC	TERMINAL RESPONSE 6.1.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 5 s. The ME returns to idle mode.	

PROACTIVE COMMAND: SET UP CALL 6.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "不忙"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456"

Coding:

BER-TLV:	D0	19	81	03	01	10	00	82	02	81	83	85
	05	80	4E	0D	5F	D9	86	07	91	10	32	04
	21	43	65									

TERMINAL RESPONSE: SET UP CALL 6.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

### Expected Sequence 6.2 (SET UP CALL, two alpha identifiers coded in UCS2 – Chinese characters)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 6.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 6.2.1	
4	ME → USER	ME displays "确定" during the user confirmation phase	["确定": 'Confirmation' in Chinese]
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456".	[second alpha identifier] ["打电话": 'CALL' in Chinese]
7	USS → ME	The ME displays "打电话" The ME receives the CONNECT message from the USS.	
8	ME → UICC	TERMINAL RESPONSE 6.2.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 5 s. The ME returns in idle mode.	

#### PROACTIVE COMMAND: SET UP CALL 6.2.1

Logically:

##### Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

##### Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "确定"

##### Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456p1p2"

Alpha Identifier (call set up phase): "打电话"

Coding:

BER-TLV:	D0	22	81	03	01	10	00	82	02	81	83	85
	05	80	78	6E	5B	9A	86	09	91	0E	32	04
	21	43	65	85	07	80	62	53	75	35	8B	DD

#### TERMINAL RESPONSE: SET UP CALL 6.2.1

Logically:

##### Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

##### Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 6.1 to 6.2.

#### 27.22.4.13.7 SET UP CALL (UCS2 Display in Katakana)

##### 27.22.4.13.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.7.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

The ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in:

- ISO/IEC 10646 [17].

##### 27.22.4.13.7.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier with UCS2 coding to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.7.4 Method of test

###### 27.22.4.13.7.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.13.7.4.2 Procedure

**Expected Sequence 7.1 (SET UP CALL with UCS2 – Katakana characters, call confirmed by the user and connected)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 7.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 7.1.1	
4	ME → USER	ME displays "ル" during user confirmation phase.	['ル' : 'Test' in Katakana]
5	USER → ME	The user confirms the call set up	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456"	
7	USS → ME	The ME receives the CONNECT message from the USS.	
8	ME → UICC	TERMINAL RESPONSE 7.1.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 5 s. The ME returns to idle mode.	

PROACTIVE COMMAND: SET UP CALL 7.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier:

"ル"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string "012340123456"

Coding:

BER-TLV:	D0	17	81	03	01	10	00	82	02	81	83	85
	03	80	30	EB	86	07	91	10	32	04	21	43
	65											

TERMINAL RESPONSE: SET UP CALL 7.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 7.2 (SET UP CALL, two alpha identifiers coded in UCS2 – Katakana characters)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 7.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 7.2.1	
4	ME → USER	ME displays "ル1" during the user confirmation phase	['ル1': 'Test1' in Katakana]
5	USER → ME	The user confirms the set up call	[user confirmation]
6	ME → USS	The ME attempts to set up a call to "+012340123456". The ME displays "ル2".	[second alpha identifier] ['ル2': 'Test2' in Katakana]
7	USS → ME	The ME receives the CONNECT message from the USS.	
8	ME → UICC	TERMINAL RESPONSE 7.2.1 The ME shall not update EF LND with the called party address.	[Command performed successfully]
9	USER → ME	The user ends the call after 5 s. The ME returns in idle mode.	

**PROACTIVE COMMAND: SET UP CALL 7.2.1**

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "ル1"

Address

TON: International  
 NPI: ISDN / telephone numbering plan  
 Dialling number string: "012340123456"

Alpha Identifier (call set up phase): "ル2"

Coding:

BER-TLV:	D0	20	81	03	01	10	00	82	02	81	83	85
	05	80	30	EB	00	31	86	07	91	10	32	04
	21	43	65	85	05	80	30	EB	00	32		

**TERMINAL RESPONSE: SET UP CALL 7.2.1**

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.13.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 7.1 to 7.2.

### 27.22.4.14 POLLING OFF

#### 27.22.4.14.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.14.2 Conformance requirement

The ME shall support the POLLING OFF as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.14, clause 6.6.14, clause 6.8, clause 6.11, clause 8.6 and clause 8.7.

#### 27.22.4.14.3 Test purpose

To verify that the ME cancels the effect of any previous POLL INTERVAL commands and does not effect UICC presence detection.

#### 27.22.4.14.4 Method of test

##### 27.22.4.14.4.1 Initial conditions

The ME is connected to the USIM Simulator and to the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.14.4.2 Procedure

**Expected Sequence 1.1 (POLLING OFF)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: POLL INTERVAL 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: POLL INTERVAL 1.1.1	Interval = 1 min
4	ME → UICC	TERMINAL RESPONSE: POLL INTERVAL 1.1.1 A or TERMINAL RESPONSE: POLL INTERVAL 1.1.1B	[command performed successfully, duration depends on the ME"s capabilities]
5	UICC → ME	PROACTIVE COMMAND PENDING: POLLING OFF 1.1.2	
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: POLLING OFF 1.1.2	
8	ME → UICC	TERMINAL RESPONSE: POLLING OFF 1.1.2	[command performed successfully]
9	USER → ME	Call to be set up	
10	ME → UICC	Periods of inactivity on the UICC-ME interfaceshall not exceed 30 seconds	
11	USER → ME	Call to be terminated 3 minutes after call setup	

PROACTIVE COMMAND: POLL INTERVAL 1.1.1

Logically:

Command details

Command number: 1  
 Command type: POLL INTERVAL  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Duration

Time unit: Minutes  
 Time interval: 1

Coding:

BER-TLV:	D0	0D	81	03	01	03	00	82	02	81	82	84
	02	00	01									

TERMINAL RESPONSE: POLL INTERVAL 1.1.1A

Logically:

Command details

Command number: 1  
 Command type: POLL INTERVAL  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Duration

Time unit: Minutes  
Time interval: 1

Coding:

BER-TLV:	81	03	01	03	00	82	02	82	81	83	01	00
	84	02	00	01								

TERMINAL RESPONSE: POLL INTERVAL 1.1.1B

Logically:

Command details

Command number: 1  
Command type: POLL INTERVAL  
Command qualifier: "00"

Device identities

Source device: ME  
Destination device: UICC

Result

General Result: Command performed successfully

Duration

Time unit: Seconds  
Time interval: 60

Coding:

BER-TLV:	81	03	01	03	00	82	02	82	81	83	01	00
	84	02	01	3C								

NOTE: If the requested poll interval is not supported by the ME, the ME is allowed to use a different one as stated in 3GPP TS 31.111 [15], subclause 6.4.6.

PROACTIVE COMMAND: POLLING OFF 1.1.2

Logically:

Command details

Command number: 1  
Command type: POLLING OFF  
Command qualifier: "00"

Device identities

Source device: UICC  
Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	04	00	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: POLLING OFF 1.1.2

Logically:

Command details

Command number: 1  
Command type: POLLING OFF  
Command qualifier: "00"

Device identities

Source device: ME  
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	04	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.14.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

#### 27.22.4.15 PROVIDE LOCAL INFORMATION

##### 27.22.4.15.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.15.2 Conformance requirement

The ME shall support the PROVIDE LOCAL INFORMATION facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.15.

##### 27.22.4.15.3 Test purpose

To verify that the ME returns the following requested local information within a TERMINAL RESPONSE:

- location information:
  - Mobile Country Code (MCC);
  - Mobile Network Code (MNC);
  - Location Area Code (LAC); and
  - cell ID of the current serving cell;
- the IMEI of the ME;
- the Network Measurement Results and the BCCH channel list;
- the current date, time and time zone;
- the current ME language setting;
- the Timing Advance;
- the Access Technology;
- the IMEISV
- the Search Mode change
- the Battery charge State
- the UTRAN measurements.

if the local information is stored in the ME; otherwise, sends the correct error code to the UICC in the TERMINAL RESPONSE.

##### 27.22.4.15.4 Method of tests

###### 27.22.4.15.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME is connected to the USS and has performed the location update procedure.

The UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;

The GERAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;
- Timing advance = 0;
- Neighbour allocations = 561, 565, 568, 569, 573, 575, 577, 581, 582 and 585.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;
- Timing advance = 0;
- Neighbour allocations = 561, 565, 568, 569, 573, 575, 577, 581, 582 and 585.

The elementary files are coded as the USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Expected sequence 1.3 and 1.6 shall be used on a USS setting up only a GERAN or PCS 1900 cell and expected sequence 1.12 shall be used on a USS setting up only a UTRAN cell.

#### 27.22.4.15.4.2 Procedure

##### Expected Sequence 1.1 (PROVIDE LOCAL INFORMATION, Local Info (MCC, MNC, LAC & Cell ID))

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.1.1A or TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.1.1B	[Command performed successfully, MCC MNC LAC and Cell Identity as USS, option A shall apply for 3GPP parameters] [Command performed successfully, MCC MNC LAC and Cell Identity as USS, option B shall apply for PCS1900 parameters]

## PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: PROVIDE LOCAL INFORMATION  
 Qualifier: "00" Location information (MCC MNC LAC and Cell Identity)

## Device identities

Source device: UICC  
 Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	26	00	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

## TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.1.1A

Logically:

## Command details

Command number: 1  
 Command type: PROVIDE LOCAL INFORMATION  
 Qualifier: "00" Location information (MCC MNC LAC and Cell Identity)

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Location Information  
 MCC & MNC: MCC = 001, MNC = 01  
 Location Area Code: 0001  
 Cell Identity Value: 0001  
 Extended Cell Identity Value: RNC-id value (for Rel-4 onwards), see also Note 2

Coding:

BER-TLV:	81	03	01	26	00	82	02	82	81	83	01	00
	93	Note 1	00	F1	10	00	01	00	01	Note 2		

Note 1: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 2: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

## TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.1.1B

Logically:

## Command details

Command number: 1  
 Command type: PROVIDE LOCAL INFORMATION  
 Qualifier: "00" Location information (MCC MNC LAC and Cell Identity)

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Location Information  
 MCC & MNC: MCC = 001, MNC = 011  
 Location Area Code: 0001  
 Cell Identity Value: 0001

Coding:

BER-TLV:	81	03	01	26	00	82	02	82	81	83	01	00
	93	07	00	11	10	00	01	00	01			

**Expected Sequence 1.2 (PROVIDE LOCAL INFORMATION, IMEI of the ME)**

Step	Direction	MESSAGE / Action	Comments
1	USS → ME	Identity request	[Identity type = IMEI]
2	ME → USS	Identity response	[Mobile identity = IMEI]
3	UICC → ME	PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.2.1	
4	ME → UICC	FETCH	
5	UICC → ME	PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.2.1	
6	ME → UICC	TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.2.1	[Command performed successfully, IMEI as USS, but spare digit shall be zero when transmitted by the ME]

PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.2.1

Logically:

Command details

Command number: 1  
 Command type: PROVIDE LOCAL INFORMATION  
 Qualifier: "01" IMEI of the ME

Device identities

Source device: UICC  
 Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	26	01	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.2.1

Logically:

Command details

Command number: 1  
 Command type: PROVIDE LOCAL INFORMATION  
 Qualifier: "01" IMEI of the ME

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

IMEI

IMEI of the ME: The IMEI of the ME

The result coding depends on the Mobile IMEI value as declared in table A.2/23.

Coding:

BER-TLV:	81	03	01	26	01	82	02	82	81	83	01	00
	94	08	XX									

As an example, if the IMEI of the mobile is "123456789012345" then XX XX XX XX XX XX XX XX = 1A 32 54 76 98 10 32 04. For further details see also 3GPP TS 24.008 [10], clause 10.5.1.

**Expected Sequence 1.3 (PROVIDE LOCAL INFORMATION, Network Measurement Results (NMR))**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.3.1	
4	ME → UICC	TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.3.1	[Command performed successfully, NMR as USS ]

**PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.3.1**

Logically:

## Command details

Command number: 1  
 Command type: PROVIDE LOCAL INFORMATION  
 Qualifier: "02" Network Measurement Results

## Device identities

Source device: UICC  
 Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	26	02	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

**TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.3.1**

The actual values of the measurements are not tested.

Logically:

## Command details

Command number: 1  
 Command type: PROVIDE LOCAL INFORMATION  
 Qualifier: "02" Network Measurement Results

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Network Measurement Results RXLEV-FULL-SERVING-CELL=52, BA not used, DTX not used, as an example in the BER-TLV)  
 BCCH channel list 561, 565, 568, 569, 573, 575, 577, 581, 582 and 585

Coding:

BER-TLV:	81	03	01	26	02	82	02	82	81	83	01	00
	96	10	34	34	00	00	00	00	00	00	00	00
	00	00	00	00	00	00	9D	0D	8C	63	58	E2
	39	8F	63	F9	06	45	91	A4	90			

**Expected Sequence 1.4 (PROVIDE LOCAL INFORMATION, Date, Time, Time Zone)**

See ETSI TS 102 384 [26] in subclause 27.22.4.15.4.2, Expected Sequence 1.4.

**Expected Sequence 1.5 (PROVIDE LOCAL INFORMATION, Language setting)**

See ETSI TS 102 384 [26] in subclause 27.22.4.15.4.2, Expected Sequence 1.5.

**Expected Sequence 1.6 (PROVIDE LOCAL INFORMATION, Timing advance)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.6.1	
4	ME → UICC	TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.6.1	[Command performed successfully]

**PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.6.1**

Logically:

## Command details

Command number: 1  
 Command type: PROVIDE LOCAL INFORMATION  
 Qualifier: "05" Timing Advance

## Device identities

Source device: UICC  
 Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	26	05	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

**TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.6.1**

Logically:

## Command details

Command number: 1  
 Command type: PROVIDE LOCAL INFORMATION  
 Qualifier: "05" Timing Advance

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Timing Advance

2 bytes  
 ME status: "00" ME is in idle state  
 Timing Advance: 0

Coding:

BER-TLV:	81	03	01	26	05	82	02	82	81	83	01	00
	AE	02	00	00								

**Expected Sequence 1.7 (PROVIDE LOCAL INFORMATION, Access Technology**

TBD

**Expected Sequence 1.8 (Void)****Expected Sequence 1.9 (PROVIDE LOCAL INFORMATION, IMEISV of the terminal)**

Step	Direction	MESSAGE / Action	Comments
1	USS → ME	Identity request	[Identity type = IMEISV]
2	ME → USS	Identity response	[Mobile identity = IMEISV]

3	UICC → ME	PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.9.1	
4	ME → UICC	FETCH	
5	UICC → ME	PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.9.1	
6	ME → UICC	TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.9.1	[Command performed successfully, IMEISV] as USS

PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.9.1

Logically:

Command details

Command number: 1  
 Command type: PROVIDE LOCAL INFORMATION  
 Qualifier: "08" IMEISV of the ME

Device identities

Source device: UICC  
 Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	26	08	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.9.1

Logically:

Command details

Command number: 1  
 Command type: PROVIDE LOCAL INFORMATION  
 Qualifier: "08" IMEISV of the ME

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

IMEISV

IMEISV of the ME: The IMEISV of the ME

The result coding depends on the ME IMEISV value as declared in table A.2/24.

Coding:

BER-TLV:	81	03	01	26	08	82	02	82	81	83	01	00
	E2	09	XX									

As an example, if the IMEISV of the ME is "1234567890123456" then XX XX XX XX XX XX XX XX XX= 13 32 54 76 98 10 32 54 F6. For further details see also ETSI TS 124.008 [7].

**Expected Sequence 1.10 (PROVIDE LOCAL INFORMATION, Search Mode Change)**

TBD

**Expected Sequence 1.11 (PROVIDE LOCAL INFORMATION, charge state of the battery)**

See ETSI TS 102 384 [26] in subclause 27.22.4.15.4.2, Expected Sequence 1.11.

**Expected Sequence 1.12 (PROVIDE LOCAL INFORMATION, UTRAN Measurements)**

TBD

**27.22.4.15.5 Test requirement**

The ME shall operate in the manner defined in expected sequences 1.1 to 1.12.

**27.22.4.16 SET UP EVENT LIST****27.22.4.16.1 SET UP EVENT LIST (normal)****27.22.4.16.1.1 Definition and applicability**

See clause 3.2.2.

**27.22.4.16.1.2 Conformance requirement**

The ME shall support the Proactive UICC: Set Up Event List facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.16 and clause 6.6.16.

Additionally the ME shall support the Event Download: Call Connect and the Event Download: Call Disconnected mechanism as defined in:

- 3GPP TS 31.111 [15] clause 11.2, clause 11.2.1, clause 11.2.2, clause 11.3, clause 11.3.1 and clause 11.3.2.

**27.22.4.16.1.3 Test purpose**

To verify that the ME accepts a list of events that it shall monitor the current list of events supplied by the UICC, is able to have this current list of events replaced and is able to have the list of events removed.

To verify that when the ME has successfully accepted or removed the list of events, it shall send TERMINAL RESPONSE (OK) to the UICC and when the ME is not able to successfully accept or remove the list of events, it shall send TERMINAL RESPONSE (Command beyond ME's capabilities).

**27.22.4.16.1.4 Method of test****27.22.4.16.1.4.1 Initial conditions**

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.16.1.4.2 Procedure

**Expected Sequence 1.1 (SET UP EVENT LIST, Set Up Call Connect Event)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE UICC SESSION ENDED	
6	USS → ME	SETUP 1.1.1	[Incoming call alert]
7	USER → ME	User shall accept the incoming call	
8	ME → USS	CONNECT 1.1.1	
9	ME → UICC	ENVELOPE: EVENT DOWNLOAD CALL CONNECTED 1.1.1	[Call Connected Event]
10	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

Device identities

Source device: UICC  
 Destination device: ME

Event list

Event 1: Call Connected

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	01										

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

SET UP 1.1.1

Logically:

Transaction identifier

Ti value: 0 (bit 5-7)

Address

TON: "Unknown"  
 NPI: "ISDN/ telephone numbering plan"  
 Dialling number string: "9876"

CONNECT 1.1.1

Logically:

Transaction identifier

Ti value: 0 (bit 5-7)  
 Ti flag: 1 (bit 8)

ENVELOPE: EVENT DOWNLOAD CALL CONNECTED 1.1.1

Logically

Event list

Event 1: Call Connected

Device identities

Source device: ME  
 Destination device: UICC

Transaction identifier

Ti value: 0 (bit 5-7)  
 Ti flag: 1 (bit 8)

Coding:

BER-TLV:	D6	0A	99	01	01	82	02	82	81	9C	01	80
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.2 (SET UP EVENT LIST, Replace Event)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.2.1	[Call Connected and Call Disconnected Events]
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.2.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.2.2	
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.2.2	[Call Disconnected Event]
8	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.2.2	
9	UICC → ME	PROACTIVE UICC SESSION ENDED	
10	USS → ME	SETUP 1.2.2	[Incoming call alert]
11	USER → ME	User shall accept the incoming call	
12	ME → USS	CONNECT 1.2.2	
13	USS → ME	DISCONNECT 1.2.2	
14	ME → UICC	ENVELOPE: EVENT DOWNLOAD CALL DISCONNECT 1.2.2A or ENVELOPE: EVENT DOWNLOAD CALL DISCONNECT 1.2.2B	[Call Disconnect Event]
15	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE COMMAND: SET UP EVENT LIST 1.2.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

Device identities

Source device: UICC  
 Destination device: ME

Event list

Event 1: Call Connected  
 Event 2: Call Disconnected

Coding:

BER-TLV:	D0	0D	81	03	01	05	00	82	02	81	82	99
	02	01	02									

TERMINAL RESPONSE: SET UP EVENT LIST 1.2.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

PROACTIVE COMMAND: SET UP EVENT LIST 1.2.2

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

Device identities

Source device: UICC  
 Destination device: ME

Event list

Event 1: Call Disconnected

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	02										

TERMINAL RESPONSE: SET UP EVENT LIST 1.2.2

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST

Command qualifier: '00'  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

### SET UP 1.2.2

Logically:

Transaction identifier  
 Ti value: 0 (bit 5-7)  
 Ti flag: 0 (bit 8)  
 Address  
 TON: "Unknown"  
 NPI: "ISDN/ telephone numbering plan"  
 Dialling number string: "9876"

### CONNECT 1.2.2

Logically:

Transaction identifier  
 Ti value: 0 (bit 5-7)  
 Ti flag: 1 (bit 8)

### DISCONNECT 1.2.2

Logically:

Transaction identifier  
 Ti value: 0 (bit 5-7)  
 Ti flag: 0 (bit 8)  
 Cause  
 Value: Normal call clearing

### ENVELOPE: EVENT DOWNLOAD CALL DISCONNECTED 1.2.2A

Logically:

Event list  
 Event 1: Call Disconnected  
 Device identities  
 Source device: Network  
 Destination device: UICC  
 Transaction identifier  
 Ti value: 0 (bit 5-7)  
 Ti flag: 0 (bit 8)  
 Cause  
 Value: Normal call clearing

Coding:

BER-TLV:	D6	0E	99	01	02	82	02	83	81	9C	01	00
	9A	02	60	90								

### ENVELOPE: EVENT DOWNLOAD CALL DISCONNECTED 1.2.2B

Logically:

Event list  
 Event 1: Call Disconnected  
 Device identities  
 Source device: Network  
 Destination device: UICC  
 Transaction identifier  
 Ti value: 0 (bit 5-7)  
 Ti flag: 0 (bit 8)  
 Cause  
 Value: Normal call clearing

Coding:

BER-TLV:	D6	0E	99	01	02	82	02	83	81	9C	01	00
	9A	02	E0	90								

**Expected Sequence 1.3 (SET UP EVENT LIST, Remove Event)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.3.1	[Call Connected Event]
	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.3.1	
4	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.3.2	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.3.2	[Remove Event]
7	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.3.2	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
10	USS → ME	SETUP 1.3.2	[Incoming call alert]
11	USER → ME	User shall accept the incoming call	
12	ME → USS	CONNECT 1.3.2	
13	ME → UICC	No ENVELOPE: EVENT DOWNLOAD (call connected) sent	
14	USS → ME	DISCONNECT 1.3.2	

PROACTIVE COMMAND: SET UP EVENT LIST 1.3.1

Logically:

Command details  
 Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'  
 Device identities  
 Source device: UICC  
 Destination device: ME  
 Event list  
 Event 1: Call Connected

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	01										

## TERMINAL RESPONSE: SET UP EVENT LIST 1.3.1

Logically:

## Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## PROACTIVE COMMAND: SET UP EVENT LIST 1.3.2

Logically:

## Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

## Device identities

Source device: UICC  
 Destination device: ME  
 Event list: Empty

Coding:

BER-TLV:	D0	0B	81	03	01	05	00	82	02	81	82	99
	00											

## TERMINAL RESPONSE: SET UP EVENT LIST 1.3.2

Logically:

## Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## SET UP 1.3.2

Logically:

## Transaction identifier

Ti value: 0 (bit 5-7)  
 Ti flag: 0 (bit 8)

## Address

TON: "Unknown"  
 NPI: "ISDN/ telephone numbering plan"  
 Dialling number string: "9876"

CONNECT 1.3.2

Logically:

Transaction identifier  
 Ti value: 0 (bit 5-7)  
 Ti flag: 1 (bit 8)

DISCONNECT 1.3.2

Logically:

Transaction identifier  
 Ti value: 0 (bit 5-7)  
 Ti flag: 0 (bit 8)  
 Cause  
 Value: Normal call clearing

**Expected Sequence 1.4 (SET UP EVENT LIST, Remove Event on ME Power Cycle)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.4.1	[Call Connected Event]
	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.4.1	
4	UICC → ME	PROACTIVE UICC SESSION ENDED	
5	User → ME	Power off ME	
6	User → ME	Power on ME	
7	USS → ME	SETUP 1.4.1	[Incoming call alert]
8	USER → ME	User shall accept the incoming call	
9	ME → USS	CONNECT 1.4.1	
10	ME → UICC	No ENVELOPE: EVENT DOWNLOAD (call connected) sent	
11	USS → ME	DISCONNECT 1.4.1	

PROACTIVE COMMAND: SET UP EVENT LIST 1.4.1

Logically:

Command details  
 Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'  
 Device identities  
 Source device: UICC  
 Destination device: ME  
 Event list  
 Event 1: Call Connected

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	01										

TERMINAL RESPONSE: SET UP EVENT LIST 1.4.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

### SET UP 1.4.1

Logically:

Transaction identifier

Ti value: 0 (bit 5-7)  
 Ti flag: 0 (bit 8)

Address

TON: "Unknown"  
 NPI: "ISDN/ telephone numbering plan"  
 Dialling number string: "9876"

### CONNECT 1.4.1

Logically:

Transaction identifier

Ti value: 0 (bit 5-7)  
 Ti flag: 1 (bit 8)

### DISCONNECT 1.4.1

Logically:

Transaction identifier

Ti value: 0 (bit 5-7)  
 Ti flag: 0 (bit 8)

Cause

Value: Normal call clearing

### 27.22.4.16.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.4.

### 27.22.4.17 PERFORM CARD APDU

#### 27.22.4.17.1 PERFORM CARD APDU (normal)

##### 27.22.4.17.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.17.1.2 Conformance requirement

The ME shall support the Proactive UICC: Perform Card APDU facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 5.2, clause 6.4.17, clause 6.6.17, clause 6.8, clause 8.6, clause 8.7, clause 8.35, clause 8.36 and clause 8.12.9.

Additionally the ME shall support multiple card operation as defined in:

- 3GPP TS 31.111 [15] clause 6.4.19, clause 6.6.19, clause 6.4.18 and clause 6.6.18.

#### 27.22.4.17.1.3 Test purpose

To verify that the ME sends an APDU command to the additional card identified in the PERFORM CARD APDU proactive UICC command, and successfully returns the result of the execution of the command in the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

In this particular case a special Test-SIM (TestSIM) with T=0 protocol is chosen as additional card for the additional ME card reader (for coding of the TestSIM see annex A).

#### 27.22.4.17.1.4 Method of test

##### 27.22.4.17.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The TestSIM is inserted in the additional ME card reader.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

The elementary files of the TestSIM are coded as defined in annex A. Another card with different parameters may be used as TestSIM to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

##### 27.22.4.17.1.4.2 Procedure

#### **Expected Sequence 1.1 (PERFORM CARD APDU, card reader 1, additional card inserted, Select MF and Get Response)**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.1.

#### **Expected Sequence 1.2 (PERFORM CARD APDU, card reader 1, additional card inserted, Select DF GSM, Select EF PLMN , Update Binary, Read Binary on EF PLMN)**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.2.

#### **Expected Sequence 1.3 (PERFORM CARD APDU, card reader 1, card inserted, card powered off)**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.3.

#### **Expected Sequence 1.4 (PERFORM CARD APDU, card reader 1, no card inserted)**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.4.

#### **Expected Sequence 1.5 (PERFORM CARD APDU, card reader 7 (which is not the valid card reader identifier of the additional ME card reader))**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.5.

#### 27.22.4.17.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.5.

#### 27.22.4.17.2 PERFORM CARD APDU (detachable card reader)

##### 27.22.4.17.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.17.2.2 Conformance requirement

##### 27.22.4.17.2.3 Test purpose

To verify that the ME sends an APDU command to the additional card identified in the PERFORM CARD APDU proactive UICC command, and successfully returns the result of the execution of the command in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.17.2.4 Method of test

###### 27.22.4.17.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The card reader shall be detached from the ME.

###### 27.22.4.17.2.4.2 Procedure

#### **Expected Sequence 2.1 (PERFORM CARD APDU, card reader 1, card reader detached)**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.2.4.2, Expected Sequence 2.1.

##### 27.22.4.17.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

#### 27.22.4.18 POWER OFF CARD

##### 27.22.4.18.1 POWER OFF CARD (normal)

###### 27.22.4.18.1.1 Definition and applicability

See clause 3.2.2.

###### 27.22.4.18.1.2 Conformance requirement

The ME shall support the Proactive UICC: Power Off Card facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.18, clause 6.6.18, clause 8.6, clause 8.7, clause 8.12, clause 8.12.9, clause 5.2 and annex H.

###### 27.22.4.18.1.3 Test purpose

To verify that the ME closes a session with the additional card identified in the POWER OFF CARD proactive UICC command, and successfully returns result in the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

#### 27.22.4.18.1.4 Method of test

##### 27.22.4.18.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME card reader is connected to aSIM Simulator (SIM2). Instead of a SIM Simulator a card with different parameters may be used as SIM2 to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

##### 27.22.4.18.1.4.2 Procedure

#### **Expected Sequence 1.1 (POWER OFF CARD, card reader 1)**

See ETSI TS 102 384 [26] in subclause 27.22.4.18.1.4.2, Expected Sequence 1.1.

#### **Expected Sequence 1.2 (POWER OFF CARD, card reader 1, no card inserted)**

See ETSI TS 102 384 [26] in subclause 27.22.4.18.1.4.2, Expected Sequence 1.2.

##### 27.22.4.18.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.2.

#### 27.22.4.18.2 POWER OFF CARD (detachable card reader)

##### 27.22.4.18.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.18.2.2 Conformance requirement

Void.

##### 27.22.4.18.2.3 Test purpose

To verify that the ME closes a session with the additional card identified in the POWER OFF CARD proactive UICC command, and successfully returns result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.18.2.4 Method of test

###### 27.22.4.18.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME card reader is connected to a SIM Simulator (SIM2).

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

The card reader shall be detached from the ME.

## 27.22.4.18.2.4.2 Procedure

**Expected Sequence 2.1 (POWER OFF CARD, card reader 1, no card reader attached)**

See ETSI TS 102 384 [26] in subclause 27.22.4.18.2.4.2, Expected Sequence 2.1.

## 27.22.4.18.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

## 27.22.4.19 POWER ON CARD

## 27.22.4.19.1 POWER ON CARD (normal)

## 27.22.4.19.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.19.1.2 Conformance requirement

The ME shall support the Proactive UICC: Power On Card facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.19, clause 6.6.19, clause 8.6, clause 8.7, clause 8.12, clause 8.12.9, clause 8.34, clause 5.2 and annex H.
- ISO /IEC 7816-3 [24].

## 27.22.4.19.1.3 Test purpose

To verify that the ME starts a session with the additional card identified in the POWER ON CARD proactive UICC command, and successfully returns the Answer To Reset within the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

## 27.22.4.19.1.4 Method of test

## 27.22.4.19.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME card reader is connected to a SIM Simulator (SIM2). Instead of the SIM Simulator a card with different parameters may be used as SIM2 to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

## 27.22.4.19.1.4.2 Procedure

**Expected Sequence 1.1 (POWER ON CARD, card reader 1)**

See ETSI TS 102 384 [26] in subclause 27.22.4.19.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (POWER ON CARD, card reader 1, no ATR)**

See ETSI TS 102 384 [26] in subclause 27.22.4.19.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (POWER ON CARD, card reader 1, no card inserted)**

See ETSI TS 102 384 [26] in subclause 27.22.4.19.1.4.2, Expected Sequence 1.3.

## 27.22.4.19.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

## 27.22.4.19.2 POWER ON CARD (detachable card reader)

## 27.22.4.19.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.19.2.2 Conformance requirement

## 27.22.4.19.2.3 Test purpose

To verify that the ME starts a session with the additional card identified in the POWER ON CARD proactive UICC command, and successfully returns the Answer To Reset within the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.19.2.4 Method of test

## 27.22.4.19.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The card reader shall be detached from the ME.

## 27.22.4.19.2.4.2 Procedure

**Expected Sequence 2.1 (POWER ON CARD, card reader 1, no card reader attached)**

See ETSI TS 102 384 [26] in subclause 27.22.4.19.2.4.2, Expected Sequence 2.1.

## 27.22.4.19.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

## 27.22.4.20 GET READER STATUS

## 27.22.4.20.1 GET READER STATUS (normal)

## 27.22.4.20.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.20.1.2 Conformance requirement

The ME shall support the Proactive UICC: Get Card Reader Status facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 5.2, clause 6.4.20, clause 6.6.20, clause 6.8, clause 8.6, clause 8.7, clause 8.33, clause 8.57 and annex H.

Additionally the ME shall support multiple card operation as defined in:

- 3GPP TS 31.111 [15] clause 6.4.19, clause 6.6.19, clause 6.4.18 and clause 6.6.18.

#### 27.22.4.20.1.3 Test purpose

To verify that the ME sends starts a session with the additional card identified in the GET CARD READER STATUS proactive UICC command, and successfully returns information about all interfaces to additional card reader(s) in the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

In this test case the SIM-Simulator (SIM2) shall response with the ATR "3B 00".

#### 27.22.4.20.1.4 Method of test

##### 27.22.4.20.1.4.1 Initial conditions

The ME shall support the Proactive UICC: Get Card Reader Status (Card Reader Status) facility. The ME is connected to the USIM Simulator.

The ME card reader is connected to a SIM Simulator (SIM2). Instead of the SIM Simulator a card with different parameters may be used as SIM2 to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

##### 27.22.4.20.1.4.2 Procedure

#### **Expected Sequence 1.1 (GET CARD READER STATUS, card reader 1, card inserted, card powered)**

See ETSI TS 102 384 [26] in subclause 27.22.4.20.1.4.2, Expected Sequence 1.1.

#### **Expected Sequence 1.2 (GET CARD READER STATUS, card reader 1, card inserted, card not powered)**

See ETSI TS 102 384 [26] in subclause 27.22.4.20.1.4.2, Expected Sequence 1.2.

#### **Expected Sequence 1.3 (GET CARD READER STATUS, card reader 1, card not present)**

See ETSI TS 102 384 [26] in subclause 27.22.4.20.1.4.2, Expected Sequence 1.3.

##### 27.22.4.20.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

#### 27.22.4.20.2 GET CARD READER STATUS (detachable card reader)

##### 27.22.4.20.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.20.2.2 Conformance requirement

Void.

#### 27.22.4.20.2.3 Test purpose

To verify that the ME closes a session with the additional card identified in the GET CARD READER STATUS proactive UICC command, and successfully returns result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.20.2.4 Method of test

##### 27.22.4.20.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

The card reader shall be detached from the ME.

##### 27.22.4.20.2.4.2 Procedure

#### **Expected Sequence 2.1 (GET CARD READER STATUS, no card reader attached)**

See ETSI TS 102 384 [26] in subclause 27.22.4.20.2.4.2, Expected Sequence 2.1.

#### 27.22.4.20.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

### 27.22.4.21 TIMER MANAGEMENT and ENVELOPE TIMER EXPIRATION

#### 27.22.4.21.1 TIMER MANAGEMENT (normal)

##### 27.22.4.21.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.21.1.2 Conformance Requirement

The ME shall support the TIMER MANAGEMENT as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.21, clause 6.8, clause 8.6, clause 8.7, clause 8.37 and clause 8.38.

##### 27.22.4.21.1.3 Test purpose

To verify that the ME manages correctly its internal timers, start a timer, deactivate a timer or return the current value of a timer according to the Timer Identifier defined in the TIMER MANAGEMENT proactive UICC command.

##### 27.22.4.21.1.4 Method of Test

###### 27.22.4.21.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

## 27.22.4.21.1.4.2 Procedure

**Expected Sequence 1.1 (TIMER MANAGEMENT, start timer 1 several times, get the current value of the timer and deactivate the timer successfully)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (TIMER MANAGEMENT, start timer 2 several times, get the current value of the timer and deactivate the timer successfully)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (TIMER MANAGEMENT, start timer 8 several times, get the current value of the timer and deactivate the timer successfully)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.3.

**Expected Sequence 1.4 (TIMER MANAGEMENT, try to get the current value of a timer which is not started: action in contradiction with the current timer state)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.4.

**Expected Sequence 1.5 (TIMER MANAGEMENT, try to deactivate a timer which is not started: action in contradiction with the current timer state)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.5.

**Expected Sequence 1.6 (TIMER MANAGEMENT, start 8 timers successfully)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.6.

## 27.22.4.21.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.6.

## 27.22.4.21.2 ENVELOPE TIMER EXPIRATION (normal)

## 27.22.4.21.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.21.2.2 Conformance requirement

The ME shall support the ENVELOPE (TIMER EXPIRATION) command as defined in the following technical specifications:

- 3GPP TS 31.111 clause 4.10, clause 7.4.1 and clause 7.4.2.

The ME shall support the TIMER MANAGEMENT as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.21, clause 6.8, clause 8.6, clause 8.7, clause 8.37 and clause 8.38.

## 27.22.4.21.2.3 Test purpose

To verify that the ME shall pass the identifier of the timer that has expired and its value using the ENVELOPE (TIMER EXPIRATION) command, when a timer previously started in a TIMER MANAGEMENT proactive command expires.

## 27.22.4.21.2.4 Method of test

## 27.22.4.21.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The timer 1 is not started.

When the UICC is busy when the envelope TIMER EXPIRATION is sent, either the ME retries periodically to send the envelope or it waits for a status not indicating busy.

#### 27.22.4.21.2.4.2 Procedure

##### **Expected Sequence 2.1 (TIMER EXPIRATION, pending proactive UICC command)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.2.4.2, Expected Sequence 2.1.

##### **Expected Sequence 2.2 (TIMER EXPIRATION, UICC application toolkit busy)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.2.4.2, Expected Sequence 2.2.

#### 27.22.4.21.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.2.

### 27.22.4.22 SET UP IDLE MODE TEXT

#### 27.22.4.22.1 SET UP IDLE MODE TEXT (normal)

##### 27.22.4.22.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.22.1.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 6.4.7 and clause 6.6.13.

Additionally the ME shall support the REFRESH proactive UICC facility as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.1, clause 6.4.7, clause 6.6.13, clause 6.11, clause 8.6, clause 8.7, clause 8.12, clause 9.4 and clause 10.

##### 27.22.4.22.1.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text.

##### 27.22.4.22.1.4 Method of test

###### 27.22.4.22.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

###### 27.22.4.22.1.4.2 Procedure

##### **Expected Sequence 1.1 (SET UP IDLE MODE TEXT, display idle mode text)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (SET UP IDLE MODE TEXT, replace idle mode text)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (SET UP IDLE MODE TEXT, remove idle mode text)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.3.

**Expected Sequence 1.4 (SET UP IDLE MODE TEXT, competing information on ME display)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP IDLE MODE TEXT 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP IDLE MODE TEXT 1.1.1	["Idle Mode Text"]
4	ME → UICC	TERMINAL RESPONSE: SET UP IDLE MODE TEXT 1.1.1	[Command performed successfully]
5	USER → ME	Select idle screen	Only if idle screen not already available
6	ME → USER	Display "Idle Mode Text"	
7	USS → ME	SMS PP 1.4.1	[Display immediate SMS]
8	ME → USER	Display "Test Message"	
9	USER → ME	Clear display and select idle screen	
10	ME → USER	Display "Idle Mode Text"	
11	UICC → ME	PROACTIVE COMMAND PENDING: DISPLAY TEXT 1.4.1	
12	ME → UICC	FETCH	
13	UICC → ME	PROACTIVE COMMAND: DISPLAY TEXT 1.4.1	[Normal priority, wait for user to clear message, unpacked, 8 bit data]
14	ME → USER	Display "Toolkit Test 1"	
15	USER → ME	Clear Message	
16	ME → UICC	TERMINAL RESPONSE: DISPLAY TEXT 1.4.1	[Command performed successfully]
17	ME → USER	Display "Idle Mode Text"	
18	UICC → ME	PROACTIVE COMMAND PENDING: PLAY TONE 1.4.1	
19	ME → UICC	FETCH	
20	UICC → ME	PROACTIVE COMMAND: PLAY TONE 1.4.1	
21	ME → USER	Display "Dial Tone" Play a standard supervisory dial tone through the external ringer for a duration of 5 s	
22	ME → UICC	TERMINAL RESPONSE: PLAY TONE 1.4.1	[Command performed successfully]
23	UICC → ME	PROACTIVE UICC SESSION ENDED	
24	ME → USER	Display "Idle Mode Text"	

## SMS-PP 1.4.1

Logically:

## SMS TPDU

TP-MTI	SMS-DELIVER
TP-MMS	No more messages waiting for the MS in this SC
TP-RP	TP-Reply-Path is not set in this SMS-DELIVER
TP-UDHI	TP-UD field contains only the short message
TP-SRI	A status report will not be returned to the ME
TP-OA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"1234"

TP-PID "00"  
 TP-DCS  
     Coding Group General Data Coding  
     Compression Text is uncompressed  
     Message Class Class 0  
     Alphabet GSM 7 bit default alphabet  
 TP-SCTS: 01/01/98 00:00:00 +0  
 TP-UDL 12  
 TP-UD "Test Message"

Coding:

Coding	04	04	91	21	43	00	10	89	10	10	00	00
	00	00	0C	D4	F2	9C	0E	6A	96	E7	F3	F0
	B9	0C										

#### PROACTIVE COMMAND: DISPLAY TEXT 1.4.1

Logically:

##### Command details

Command number: 1  
 Command type: DISPLAY TEXT  
 Command qualifier: normal priority, wait for user to clear message

##### Device identities

Source device: UICC  
 Destination device: Display

##### Text String

Data coding scheme: unpacked, 8 bit data  
 Text: "Toolkit Test 1"

Coding:

BER-TLV:	D0	1A	81	03	01	21	80	82	02	81	02	8D
	0F	04	54	6F	6F	6C	6B	69	74	20	54	65
	73	74	20	31								

#### TERMINAL RESPONSE: DISPLAY TEXT 1.4.1

Logically:

##### Command details

Command number: 1  
 Command type: DISPLAY TEXT  
 Command qualifier: normal priority, wait for user to clear message

##### Device identities

Source device: ME  
 Destination device: UICC

##### Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	21	80	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### PROACTIVE COMMAND: PLAY TONE 1.4.1

Logically:

##### Command details

Command number: 1  
 Command type: PLAY TONE

Command qualifier: "00"  
 Device identities  
 Source device: UICC  
 Destination device: Earpiece  
 Alpha identifier: "Dial Tone"  
 TONe: Standard supervisory tones: dial tone  
 Duration  
 Time unit: Seconds  
 Time interval: 5

Coding:

BER-TLV:	D0	1B	81	03	01	20	00	82	02	81	03	85
	09	44	69	61	6C	20	54	6F	6E	65	8E	01
	01	84	02	01	05							

TERMINAL RESPONSE: PLAY TONE 1.4.1

Logically:

Command details  
 Command number: 1  
 Command type: PLAY TONE  
 Command qualifier: "00"  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	20	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.5 (SET UP IDLE MODE TEXT, ME power cycled)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP IDLE MODE TEXT 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP IDLE MODE TEXT 1.1.1	["Idle Mode Text"]
4	ME → UICC	TERMINAL RESPONSE: SET UP IDLE MODE TEXT 1.1.1	[command performed successfully]
5	USER → ME	Select idle screen	Only if idle screen not already available
6	ME → USER	Display "Idle Mode Text"	
7	USER → ME	Power off ME	
8	ME ↔ UICC	3G Session TERMINATION PROCEDURE	
9	USER → ME	Power on ME	
10	ME ↔ UICC	3G Session ACTIVATION PROCEDURE	
11	ME ↔ UICC	USIM INITIALIZATION	
12	USER → ME	Select idle screen	Only if idle screen not already available
13	ME → USER	Display idle screen / "Idle Mode Text" not to be displayed	

**Expected Sequence 1.6 (SET UP IDLE MODE TEXT, REFRESH with USIM Initialization)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP IDLE MODE TEXT 1.1.1	[Idle Mode Text]
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP IDLE MODE TEXT 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP IDLE MODE TEXT 1.1.1	
5	USER → ME	Select idle screen	Only if idle screen not already available
6	ME → USER	Display "Idle Mode Text"	
7	UICC → ME	PROACTIVE COMMAND PENDING: REFRESH 1.6.1	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: REFRESH 1.6.1	[USIM Initialization]
10	ME ↔ UICC	USIM INITIALIZATION	
11	USER → ME	Select idle screen	Only if idle screen not already available
12	ME → USER	Display idle screen / "Idle Mode Text" not to be displayed	
13	ME → UICC	TERMINAL RESPONSE: REFRESH 1.6.1A or TERMINAL RESPONSE: REFRESH 1.6.1B	[Command performed successfully] [Command performed successfully with additional files read]
14	UICC → ME	PROACTIVE UICC SESSION ENDED	

**PROACTIVE COMMAND: REFRESH 1.6.1**

Logically:

Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Initialization

Device identities

Source device: UICC  
 Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	01	03	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

**TERMINAL RESPONSE: REFRESH 1.6.1A**

Logically:

Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Initialization

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	01	03	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: REFRESH 1.6.1B

Logically:

Command details

Command number: 1  
 Command type: REFRESH  
 Command qualifier: USIM Initialization

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: REFRESH performed with additional EFs read

Coding:

BER-TLV:	81	03	01	01	03	82	02	82	81	83	01	03
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.7 (SET UP IDLE MODE TEXT, large text string)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.7.

27.22.4.22.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.7.

27.22.4.22.2 SET UP IDLE MODE TEXT (Icon support)

27.22.4.22.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.22.2.2 Conformance requirement

27.22.4.22.2.3 Test purpose

To verify that the ME text and / or icon passed to the ME is displayed by the ME as an idle mode text.

To verify that the icon identifier provided with the text string can replace the text string or accompany it.

To verify that if both an alpha identifier or text string, and an icon are provided with a proactive command, and both are requested to be displayed, but the ME is not able to display both together on the screen, then the alpha identifier or text string takes precedence over the icon.

To verify that if the UICC provides an icon identifier with a proactive command, then the ME shall inform the UICC if the icon could not be displayed by sending the general result "Command performed successfully, but requested icon could not be displayed".

To verify that if the ME receives an icon identifier with a proactive command, and either an empty, or no alpha identifier / text string is given by the UICC, then the ME shall reject the command with general result "Command data not understood by ME".

27.22.4.22.2.4 Method of test

27.22.4.22.2.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in update idle mode on the System Simulator.

## 27.22.4.22.2.4.2 Procedure

**Expected Sequence 2.1A (SET UP IDLE MODE TEXT, Icon is self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.1A.

**Expected Sequence 2.1B (SET UP IDLE MODE TEXT, Icon is self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.1B.

**Expected Sequence 2.2A (SET UP IDLE MODE TEXT, Icon is not self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.2A.

**Expected Sequence 2.2B (SET UP IDLE MODE TEXT, Icon is not self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.2B.

**Expected Sequence 2.3A (SET UP IDLE MODE TEXT, Icon is self-explanatory, colour icon, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.3A.

**Expected Sequence 2.3B (SET UP IDLE MODE TEXT, Icon is self-explanatory, colour icon, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.3B.

**Expected Sequence 2.4 (SET UP IDLE MODE TEXT, Icon is not self-explanatory, empty text string)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.4.

## 27.22.4.22.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1A to 2.4.

## 27.22.4.22.3 SET UP IDLE MODE TEXT (UCS2 support)

## 27.22.4.22.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.22.3.2 Conformance requirement

The ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646 [17].

## 27.22.4.22.3.3 Test purpose

To verify that the UCS2 coded text string is displayed by the ME as an idle mode text.

## 27.22.4.22.3.4 Method of test

## 27.22.4.22.3.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in update idle mode on the System Simulator..

#### 27.22.4.22.3.4.2 Procedure

##### **Expected Sequence 3.1 (SET UP IDLE MODE TEXT, UCS2 alphabet text)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.3.4.2, Expected Sequence 3.1.

#### 27.22.4.22.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

#### 27.22.4.22.4 SET UP IDLE MODE TEXT (support of Text Attribute)

##### 27.22.4.22.4.1 SET UP IDLE MODE TEXT (support of Text Attribute – Left Alignment)

###### 27.22.4.22.4.1.1 Definition and applicability

See clause 3.2.2.

###### 27.22.4.22.4.1.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

###### 27.22.4.22.4.1.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the left alignment text attribute configuration.

###### 27.22.4.22.4.1.4 Method of test

###### 27.22.4.22.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.22.4.1.4.2 Procedure

##### **Expected Sequence 4.1 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.1.4.2, Expected Sequence 4.1.

###### 27.22.4.22.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

##### 27.22.4.22.4.2 SET UP IDLE MODE TEXT (support of Text Attribute – Center Alignment)

###### 27.22.4.22.4.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.22.4.2.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

#### 27.22.4.22.4.2.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the center alignment text attribute configuration.

#### 27.22.4.22.4.2.4 Method of test

##### 27.22.4.22.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.22.4.2.4.2 Procedure

Expected Sequence 4.2 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Center Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.2.4.2, Expected Sequence 4.2.

##### 27.22.4.22.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

#### 27.22.4.22.4.3 SET UP IDLE MODE TEXT (support of Text Attribute – Right Alignment)

##### 27.22.4.22.4.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.22.4.3.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

##### 27.22.4.22.4.3.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the right alignment text attribute configuration.

##### 27.22.4.22.4.3.4 Method of test

###### 27.22.4.22.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.22.4.3.4.2 Procedure

**Expected Sequence 4.3 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.3.4.2, Expected Sequence 4.3.

## 27.22.4.22.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

## 27.22.4.22.4.4 SET UP IDLE MODE TEXT (support of Text Attribute – Large Font Size)

## 27.22.4.22.4.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.22.4.4.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

## 27.22.4.22.4.4.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the large font size text attribute configuration.

## 27.22.4.22.4.4.4 Method of test

## 27.22.4.22.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.22.4.4.4.2 Procedure

**Expected Sequence 4.4 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.4.4.2, Expected Sequence 4.4.

## 27.22.4.22.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

## 27.22.4.22.4.5 SET UP IDLE MODE TEXT (support of Text Attribute – Small Font Size)

## 27.22.4.22.4.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.22.4.5.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

#### 27.22.4.22.4.5.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the small font size text attribute configuration.

#### 27.22.4.22.4.5.4 Method of test

##### 27.22.4.22.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.22.4.5.4.2 Procedure

#### **Expected Sequence 4.5 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.5.4.2, Expected Sequence 4.5.

##### 27.22.4.22.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

#### 27.22.4.22.4.6 SET UP IDLE MODE TEXT (support of Text Attribute – Bold On)

##### 27.22.4.22.4.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.22.4.6.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

##### 27.22.4.22.4.6.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the bold text attribute configuration.

##### 27.22.4.22.4.6.4 Method of test

##### 27.22.4.22.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.22.4.6.4.2 Procedure

#### **Expected Sequence 4.6 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.6.4.2, Expected Sequence 4.6.

##### 27.22.4.22.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

#### 27.22.4.22.4.7 SET UP IDLE MODE TEXT (support of Text Attribute – Italic On)

##### 27.22.4.22.4.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.22.4.7.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

##### 27.22.4.22.4.7.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the italic text attribute configuration.

##### 27.22.4.22.4.7.4 Method of test

###### 27.22.4.22.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.22.4.7.4.2 Procedure

#### **Expected Sequence 4.7 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.7.4.2, Expected Sequence 4.7.

##### 27.22.4.22.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

#### 27.22.4.22.4.8 SET UP IDLE MODE TEXT (support of Text Attribute – Underline On)

##### 27.22.4.22.4.8.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.22.4.8.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

##### 27.22.4.22.4.8.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the underline text attribute configuration.

##### 27.22.4.22.4.8.4 Method of test

###### 27.22.4.22.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.22.4.8.4.2 Procedure

**Expected Sequence 4.8 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.8.4.2, Expected Sequence 4.8.

## 27.22.4.22.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

## 27.22.4.22.4.9 SET UP IDLE MODE TEXT (support of Text Attribute – Strikethrough On)

## 27.22.4.22.4.9.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.22.4.9.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

## 27.22.4.22.4.9.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the strikethrough text attribute configuration.

## 27.22.4.22.4.9.4 Method of test

## 27.22.4.22.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.22.4.9.4.2 Procedure

**Expected Sequence 4.9 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.9.4.2, Expected Sequence 4.9.

## 27.22.4.22.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

## 27.22.4.22.4.10 SET UP IDLE MODE TEXT (support of Text Attribute – Foreground and Background Colour)

## 27.22.4.22.4.10.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.22.4.10.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

#### 27.22.4.22.4.10.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the foreground and background colour text attribute configuration.

#### 27.22.4.22.4.10.4 Method of test

##### 27.22.4.22.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.22.4.10.4.2 Procedure

#### **Expected Sequence 4.10 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Foreground and Background Colour)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.10.4.2, Expected Sequence 4.10.

##### 27.22.4.22.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

#### 27.22.4.22.5 SET UP IDLE MODE TEXT (UCS2 display in Chinese)

##### 27.22.4.22.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.22.5.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

The Terminal shall additionally support the UCS2 facility for the coding of the Chinese character, as defined in: ISO/IEC 10646 [17a/17b].

##### 27.22.4.22.5.3 Test purpose

To verify that the UCS2 coded text string is displayed by the ME as an idle mode text.

##### 27.22.4.22.5.4 Method of test

##### 27.22.4.22.5.4.1 Initial conditions

The Terminal is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the Terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.22.5.4.2 Procedure

#### **Expected Sequence 5.1 (SET UP IDLE MODE TEXT, UCS2 alphabet text in Chinese)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.5.4.2, Expected Sequence 5.1.

## 27.22.4.22.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

## 27.22.4.22.6 SET UP IDLE MODE TEXT (UCS2 display in Katakana)

## 27.22.4.22.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.22.6.2 Conformance requirement

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

The ME shall additionally support the UCS2 facility for the coding of the Katakana character, as defined in:

ISO/IEC 10646 [17a/17b].

## 27.22.4.22.6.3 Test purpose

To verify that the UCS2 coded text string is displayed by the ME as an idle mode text.

## 27.22.4.22.6.4 Method of test

## 27.22.4.22.6.4.1 Initial conditions

The ME is connected to both the UICC Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.22.6.4.2 Procedure

**Expected Sequence 6.1 (SET UP IDLE MODE TEXT, UCS2 alphabet text in Katakana)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.6.4.2, Expected Sequence 6.1.

## 27.22.4.22.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

## 27.22.4.23 RUN AT COMMAND

## 27.22.4.23.1 RUN AT COMMAND (normal)

## 27.22.4.23.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.23.1.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31 and clause 8.41.
- 3GPP TS 27.007 [18].

27.22.4.23.1.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.1.4 Method of test

27.22.4.23.1.4.1 Initial conditions

The ME is connected to the USIM Simulator. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.1.4.2 Procedure

**Expected Sequence 1.1(RUN AT COMMAND, no alpha identifier presented, request IMSI)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 1.1.1	[no alpha identifier, request IMSI]
4	ME (→ User)	The ME may give information to the user concerning what is happening	
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 1.1.1	[Command performed successfully, AT Response containing IMSI]

PROACTIVE UICC COMMAND: RUN AT COMMAND 1.1.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	12	81	03	01	34	00	82	02	81	82	A8
	07	41	54	2B	43	49	4D	49				

TERMINAL RESPONSE: RUN AT COMMAND 1.1.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 AT Response  
 AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

**Expected Sequence 1.2 (RUN AT COMMAND, null data alpha identifier presented, request IMSI)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 1.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 1.2.1	[null data alpha identifier, request IMSI]
4	ME	The ME should not give any information to user on the fact that the ME is performing an AT command	
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 1.1.1	[Command performed successfully, AT Response containing IMSI]

PROACTIVE UICC COMMAND: RUN AT COMMAND 1.2.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier null data object

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	14	81	03	01	34	00	82	02	81	82	85
	00	A8	07	41	54	2B	43	49	4D	49		

**Expected Sequence 1.3 (RUN AT COMMAND, alpha identifier presented, request IMSI)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 1.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 1.3.1	[alpha identifier, request IMSI]
4	ME → USER	Display "Run AT Command"	
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 1.1.1	[Command performed successfully, AT Response containing IMSI]

PROACTIVE UICC COMMAND: RUN AT COMMAND 1.3.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	22	81	03	01	34	00	82	02	81	82	85
	0E	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	A8	07	41	54	2B	43	49	4D	49

#### 27.22.4.23.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

#### 27.22.4.23.2 RUN AT COMMAND (Icon support)

##### 27.22.4.23.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.23.2.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31 and clause 8.41.
- 3GPP TS 27.007 [18].

##### 27.22.4.23.2.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

In addition to verify that if an icon is provided by the UICC, the icon indicated in the command may be used by the ME to inform the user, in addition to, or instead of the alpha identifier, as indicated with the icon qualifier.

##### 27.22.4.23.2.4 Method of test

###### 27.22.4.23.2.4.1 Initial conditions

The ME is connected to the USIM Simulator. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

The ME screen shall be in its normal stand-by display.

27.22.4.23.2.4.2 Procedure

**Expected Sequence 2.1A (RUN AT COMMAND, basic icon self explanatory, request IMSI, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 2.1.1	[BASIC-ICON, self-explanatory, request IMSI]
4	ME → USER	Display BASIC ICON without the alpha identifier	
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 2.1.1A	[Command performed successfully, AT response containing IMSI]

PROACTIVE COMMAND: RUN AT COMMAND 2.1.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier

Alpha identifier: "Basic Icon"

AT Command

AT Command string: "AT+CIMI"

Icon identifier:

Icon qualifier: icon is self-explanatory  
 Icon identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	22	81	03	01	34	00	82	02	81	82	85
	0A	42	61	73	69	63	20	49	63	6F	6E	A8
	07	41	54	2B	43	49	4D	49	9E	02	00	01

TERMINAL RESPONSE: RUN AT COMMAND 2.1.1A

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

**Expected Sequence 2.1B (RUN AT COMMAND, basic icon self explanatory, request IMSI, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 2.1.1	[BASIC-ICON, self-explanatory, request IMSI]
4	ME → USER	Display 'Basic Icon' without the BASIC-ICON	
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 2.1.1B	[Command performed but requested icon could not be displayed, AT response containing IMSI]

TERMINAL RESPONSE: RUN AT COMMAND 2.1.1B

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	04
	A9	08	09	10	10	10	32	54	76	98		

**Expected Sequence 2.2A (RUN AT COMMAND, colour icon self explanatory, request IMSI, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 2.2.1	[COLOUR-ICON, self-explanatory, request IMSI]
4	ME → USER	Display COLOUR-ICON without the alpha identifier	
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 2.1.1A	[Command performed successfully, AT response containing IMSI]

PROACTIVE COMMAND: RUN AT COMMAND 2.2.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC

Destination device: ME  
 Alpha Identifier  
 Alpha identifier: "Colour Icon"  
 AT Command  
 AT Command string: "AT+CIMI"  
 Icon identifier:  
 Icon qualifier: icon is self-explanatory  
 Icon identifier: record 2 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	23	81	03	01	34	00	82	02	81	82	A8
	0B	43	6F	6C	6F	75	72	20	49	63	6F	6E
	A8	07	41	54	2B	43	49	4D	49	9E	02	00
	02											

**Expected Sequence 2.2B (RUN AT COMMAND, colour icon self explanatory, request IMSI, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 2.2.1	[COLOUR-ICON, self-explanatory, request IMSI]
4	ME → USER	Display 'Colour Icon' without the COLOUR-ICON	
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 2.1.1B	[Command performed but requested icon could not be displayed, AT response containing IMSI]

**Expected Sequence 2.3A (RUN AT COMMAND, basic icon non self-explanatory, request IMSI, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 2.3.1	[BASIC-ICON, non self-explanatory, request IMSI]
4	ME → USER	Display "Basic Icon" and BASIC- ICON	
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 2.1.1A	[Command performed successfully, AT response containing IMSI]

PROACTIVE COMMAND: RUN AT COMMAND 2.3.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier

Alpha identifier: "Basic Icon"

## AT Command

AT Command string: "AT+CIMI"

## Icon identifier

Icon qualifier: icon is non self-explanatory

Icon identifier: record 1 in EF<sub>(IMG)</sub>

## Coding:

BER-TLV:	D0	22	81	03	01	34	00	82	02	81	82	85
	0A	42	61	73	69	63	20	49	63	6F	6E	A8
	07	41	54	2B	43	49	4D	49	9E	02	01	01

**Expected Sequence 2.3B (RUN AT COMMAND, basic icon non self-explanatory, request IMSI, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 2.3.1	[BASIC-ICON, non self-explanatory, request IMSI]
4	ME → USER	Display "Basic Icon" without BASIC-ICON	
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 2.1.1B	[Command performed but requested icon could not be displayed, AT response containing IMSI]

**Expected Sequence 2.4A (RUN AT COMMAND, colour icon non self-explanatory, request IMSI, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 2.4.1	[COLOUR-ICON, non self-explanatory, request IMSI]
4	ME → USER	Display "Colour Icon" and COLOUR-ICON	
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 2.1.1A	[Command performed successfully, AT response containing IMSI]

PROACTIVE COMMAND: RUN AT COMMAND 2.4.1

## Logically:

## Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: ME

## Alpha Identifier

Alpha identifier: "Colour Icon"

## AT Command

AT Command string: "AT+CIMI"

## Icon identifier:

Icon qualifier: icon is self-explanatory  
 Icon identifier: record 2 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	23	81	03	01	34	00	82	02	81	82	85
	0B	43	6F	6C	6F	75	72	20	49	63	6F	6E
	A8	07	41	54	2B	43	49	4D	49	9E	02	01
	02											

**Expected Sequence 2.4B (RUN AT COMMAND, colour icon non self-explanatory, request IMSI, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 2.4.1	[COLOUR-ICON, non self-explanatory, request IMSI]
4	ME → USER	Display "Colour Icon" without COLOUR-ICON	
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 2.1.1B	[Command performed but requested icon could not be displayed, AT response containing IMSI]

**Expected Sequence 2.5 (RUN AT COMMAND, basic icon non self-explanatory, no alpha identifier presented)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 2.5.1	[BASIC-ICON, non self-explanatory]
4	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 2.5.1	[Command data not understood by ME]

PROACTIVE COMMAND: RUN AT COMMAND 2.5.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

AT Command

AT Command string: "AT+CIMI"

Icon identifier

Icon qualifier: icon is non self-explanatory  
 Icon identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	16	81	03	01	34	00	82	02	81	82	A8
	07	41	54	2B	43	49	4D	49	9E	02	01	01

TERMINAL RESPONSE: RUN AT COMMAND 2.5.1

Logically:

## Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: ME

## Result

General Result: Command data not understood by ME

## Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	32
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.23.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.5.

## 27.22.4.23.3 RUN AT COMMAND (support of Text Attribute)

## 27.22.4.23.3.1 RUN AT COMMAND (support of Text Attribute – Left Alignment)

## 27.22.4.23.3.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.23.3.1.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

## 27.22.4.23.3.1.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with left alignment text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

## 27.22.4.23.3.1.4 Method of test

## 27.22.4.23.3.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.1.4.2 Procedure

**Expected Sequence 3.1(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Left Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.1.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with left alignment, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.1.1	[Command performed successfully, AT Response containing IMSI]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.1.2	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.1.2	
10	ME (→ USER)	Display "Run AT Command 2"	[Message shall be formatted without left alignment, request IMSI. Remark: If left alignment is the ME"s default alignment as declared in table A.2/16, no alignment change will take place]
11	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.1.1	[Command performed successfully, AT Response containing IMSI]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.1.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.1.2

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.1.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

#### 27.22.4.23.3.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

#### 27.22.4.23.3.2 RUN AT COMMAND (support of Text Attribute – Center Alignment)

##### 27.22.4.23.3.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.23.3.2.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

## 27.22.4.23.3.2.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with center alignment text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

## 27.22.4.23.3.2.4 Method of test

## 27.22.4.23.3.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

## 27.22.4.23.3.2.4.2 Procedure

**Expected Sequence 3.2(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Center Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.2.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with center alignment, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.2.1	[Command performed successfully, AT Response containing IMSI]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.2.2	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.2.2	
10	ME (→ USER)	Display "Run AT Command 2"	[Message shall be formatted without center alignment, request IMSI. Remark: If center alignment is the ME's default alignment as declared in table A.2/16, no alignment change will take place]
11	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.2.1	[Command performed successfully, AT Response containing IMSI]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.2.1

Logically:

## Command details

Command number: 1  
Command type: RUN AT COMMAND  
Command qualifier: "00"

## Device identities

Source device: UICC

Destination device: ME  
 Alpha Identifier  
 Alpha Identifier "Run AT Command 1"  
 AT Command  
 AT Command string: "AT+CIMI"  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	01	B4				

#### PROACTIVE UICC COMMAND: RUN AT COMMAND 3.2.2

Logically:

Command details  
 Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"  
 Device identities  
 Source device: UICC  
 Destination device: ME  
 Alpha Identifier  
 Alpha Identifier "Run AT Command 2"  
 AT Command  
 AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49										

#### TERMINAL RESPONSE: RUN AT COMMAND 3.2.1

Logically:

Command details  
 Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 AT Response  
 AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

#### 27.22.4.23.3.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.2.

#### 27.22.4.23.3.3 RUN AT COMMAND (support of Text Attribute – Right Alignment)

##### 27.22.4.23.3.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.23.3.3.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

##### 27.22.4.23.3.3.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with right alignment text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

##### 27.22.4.23.3.3.4 Method of test

###### 27.22.4.23.3.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.3.4.2 Procedure

**Expected Sequence 3.3(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Right Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.3.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with right alignment, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.3.1	[Command performed successfully, AT Response containing IMSI]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.3.2	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.3.2	
10	ME (→ USER)	Display "Run AT Command 2"	[Message shall be formatted without right alignment, request IMSI. Remark: If right alignment is the ME"s default alignment as declared in table A.2/16, no alignment change will take place]
11	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.3.1	[Command performed successfully, AT Response containing IMSI]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.3.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	02	B4				

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.3.2

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.3.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

#### 27.22.4.23.3.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.3.

#### 27.22.4.23.3.4 RUN AT COMMAND (support of Text Attribute – Large Font Size)

##### 27.22.4.23.3.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.23.3.4.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.3.4.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with large font size as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.3.4.4 Method of test

##### 27.22.4.23.3.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

## 27.22.4.23.3.4.4.2 Procedure

**Expected Sequence 3.4(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Large Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.4.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with large font size, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.4.1	[Command performed successfully, AT Response containing IMSI]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.4.2	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.4.2	
10	ME (→ USER)	Display "Run AT Command 2"	[alpha identifier is displayed with normal font size, request IMSI]
11	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.4.1	[Command performed successfully, AT Response containing IMSI]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.4.1	
14	ME → UICC	FETCH	
15	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.4.1	
16	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with large font size, request IMSI]
17	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.4.1	[Command performed successfully, AT Response containing IMSI]
18	UICC → ME	PROACTIVE UICC SESSION ENDED	
19	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.4.3	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.4.3	
22	ME (→ USER)	Display "Run AT Command 3"	[alpha identifier is displayed with normal font size, request IMSI]
23	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.4.1	[Command performed successfully, AT Response containing IMSI]
24	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.4.1

Logically:

## Command details

Command number: 1  
Command type: RUN AT COMMAND  
Command qualifier: "00"

## Device identities

Source device: UICC  
Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 1"

## AT Command

AT Command string: "AT+CIMI"

## Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	04	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.4.2

## Logically:

## Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

## Device identities

Source device: UICC

Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 2"

## AT Command

AT Command string: "AT+CIMI"

## Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,

Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.4.3

## Logically:

## Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

## Device identities

Source device: UICC

Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 3"

## AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.4.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

27.22.4.23.3.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.4.

27.22.4.23.3.5 RUN AT COMMAND (support of Text Attribute – Small Font Size)

27.22.4.23.3.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.23.3.5.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.3.5.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with small font size as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.5.4 Method of test

27.22.4.23.3.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

#### 27.22.4.23.3.5.4.2 Procedure

### Expected Sequence 3.5(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.5.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with small font size, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.5.1	[Command performed successfully, AT Response containing IMSI]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.5.2	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.5.2	
10	ME (→ USER)	Display "Run AT Command 2"	[alpha identifier is displayed with normal font size, request IMSI]
11	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.5.1	[Command performed successfully, AT Response containing IMSI]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.5.1	
14	ME → UICC	FETCH	
15	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.5.1	
16	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with small font size, request IMSI]
17	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.5.1	[Command performed successfully, AT Response containing IMSI]
18	UICC → ME	PROACTIVE UICC SESSION ENDED	
19	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.5.3	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.5.3	
22	ME (→ USER)	Display "Run AT Command 3"	[alpha identifier is displayed with normal font size, request IMSI]
23	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.5.1	[Command performed successfully, AT Response containing IMSI]
24	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.5.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"  
 Device identities  
   Source device: UICC  
   Destination device: ME  
 Alpha Identifier  
   Alpha Identifier "Run AT Command 1"  
 AT Command  
   AT Command string: "AT+CIMI"  
 Text Attribute  
   Formatting position: 0  
   Formatting length: 16  
   Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,  
   Strikethrough Off  
   Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	08	B4				

#### PROACTIVE UICC COMMAND: RUN AT COMMAND 3.5.2

Logically:

Command details  
   Command number: 1  
   Command type: RUN AT COMMAND  
   Command qualifier: "00"  
 Device identities  
   Source device: UICC  
   Destination device: ME  
 Alpha Identifier  
   Alpha Identifier "Run AT Command 2"  
 AT Command  
   AT Command string: "AT+CIMI"  
 Text Attribute  
   Formatting position: 0  
   Formatting length: 16  
   Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
   Strikethrough Off  
   Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

#### PROACTIVE UICC COMMAND: RUN AT COMMAND 3.5.3

Logically:

Command details  
   Command number: 1  
   Command type: RUN AT COMMAND  
   Command qualifier: "00"  
 Device identities

Source device: UICC  
 Destination device: ME  
 Alpha Identifier  
 Alpha Identifier "Run AT Command 3"  
 AT Command  
 AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.5.1

Logically:

Command details  
 Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 AT Response  
 AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

#### 27.22.4.23.3.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.5.

#### 27.22.4.23.3.6 RUN AT COMMAND (support of Text Attribute – Bold On)

##### 27.22.4.23.3.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.23.3.6.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

##### 27.22.4.23.3.6.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with bold text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.6.4 Method of test

27.22.4.23.3.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

## 27.22.4.23.3.6.4.2 Procedure

**Expected Sequence 3.6(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Bold On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.6.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with bold on, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.6.1	[Command performed successfully, AT Response containing IMSI]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.6.2	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.6.2	
10	ME (→ USER)	Display "Run AT Command 2"	[alpha identifier is displayed with bold off, request IMSI]
11	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.6.1	[Command performed successfully, AT Response containing IMSI]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.6.1	
14	ME → UICC	FETCH	
15	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.6.1	
16	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with bold on, request IMSI]
17	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.6.1	[Command performed successfully, AT Response containing IMSI]
18	UICC → ME	PROACTIVE UICC SESSION ENDED	
19	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.6.3	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.6.3	
22	ME (→ USER)	Display "Run AT Command 3"	[alpha identifier is displayed with bold off, request IMSI]
23	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.6.1	[Command performed successfully, AT Response containing IMSI]
24	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.6.1

Logically:

## Command details

Command number: 1  
Command type: RUN AT COMMAND  
Command qualifier: "00"

## Device identities

Source device: UICC  
Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 1"

## AT Command

AT Command string: "AT+CIMI"

## Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	10	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.6.2

## Logically:

## Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

## Device identities

Source device: UICC

Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 2"

## AT Command

AT Command string: "AT+CIMI"

## Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.6.3

## Logically:

## Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

## Device identities

Source device: UICC

Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 3"

## AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.6.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

27.22.4.23.3.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.6.

27.22.4.23.3.7 RUN AT COMMAND (support of Text Attribute – Italic On)

27.22.4.23.3.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.23.3.7.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.3.7.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with italic text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.7.4 Method of test

27.22.4.23.3.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

#### 27.22.4.23.3.7.4.2 Procedure

### Expected Sequence 3.7(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.7.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.7.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with italic on, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.7.1	[Command performed successfully, AT Response containing IMSI]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.7.2	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.7.2	
10	ME (→ USER)	Display "Run AT Command 2"	[alpha identifier is displayed with italic off, request IMSI]
11	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.7.1	[Command performed successfully, AT Response containing IMSI]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.7.1	
14	ME → UICC	FETCH	
15	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.7.1	
16	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with italic on, request IMSI]
17	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.7.1	[Command performed successfully, AT Response containing IMSI]
18	UICC → ME	PROACTIVE UICC SESSION ENDED	
19	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.7.3	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.7.3	
22	ME (→ USER)	Display "Run AT Command 3"	[alpha identifier is displayed with italic off, request IMSI]
23	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.7.1	[Command performed successfully, AT Response containing IMSI]
24	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.7.1

Logically:

## Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 1"

## AT Command

AT Command string: "AT+CIMI"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	20	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.7.2

## Logically:

## Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 2"

## AT Command

AT Command string: "AT+CIMI"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.7.3

## Logically:

## Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 3"

## AT Command

AT Command string: "AT+CIMI"

## Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

## TERMINAL RESPONSE: RUN AT COMMAND 3.7.1

## Logically:

## Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## AT Response

AT Response string: IMSI

## Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

## 27.22.4.23.3.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.7.

## 27.22.4.23.3.8 RUN AT COMMAND (support of Text Attribute – Underline On)

## 27.22.4.23.3.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.23.3.8.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.3.8.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with underline text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.3.8.4 Method of test

##### 27.22.4.23.3.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

## 27.22.4.23.3.8.4.2 Procedure

**Expected Sequence 3.8(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Underline On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.8.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.8.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with underline on, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.8.1	[Command performed successfully, AT Response containing IMSI]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.8.2	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.8.2	
10	ME (→ USER)	Display "Run AT Command 2"	[alpha identifier is displayed with underline off, request IMSI]
11	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.8.1	[Command performed successfully, AT Response containing IMSI]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.8.1	
14	ME → UICC	FETCH	
15	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.8.1	
16	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with underline on, request IMSI]
17	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.8.1	[Command performed successfully, AT Response containing IMSI]
18	UICC → ME	PROACTIVE UICC SESSION ENDED	
19	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.8.3	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.8.3	
22	ME (→ USER)	Display "Run AT Command 3"	[alpha identifier is displayed with underline off, request IMSI]
23	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.8.1	[Command performed successfully, AT Response containing IMSI]
24	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.8.1

Logically:

## Command details

Command number: 1  
Command type: RUN AT COMMAND  
Command qualifier: "00"

## Device identities

Source device: UICC  
Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 1"

## AT Command

AT Command string: "AT+CIMI"

## Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	40	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.8.2

## Logically:

## Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

## Device identities

Source device: UICC

Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 2"

## AT Command

AT Command string: "AT+CIMI"

## Text Attribute

Formatting position: 0

Formatting length: 16

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.8.3

## Logically:

## Command details

Command number: 1

Command type: RUN AT COMMAND

Command qualifier: "00"

## Device identities

Source device: UICC

Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 3"

## AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.8.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

27.22.4.23.3.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.8.

27.22.4.23.3.9 RUN AT COMMAND (support of Text Attribute – Strikethrough On)

27.22.4.23.3.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.23.3.9.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.3.9.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with strikethrough text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.9.4 Method of test

27.22.4.23.3.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

#### 27.22.4.23.3.9.4.2 Procedure

### Expected Sequence 3.9(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Strikethrough On)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.9.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.9.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with strikethrough on, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.9.1	[Command performed successfully, AT Response containing IMSI]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.9.2	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.9.2	
10	ME (→ USER)	Display "Run AT Command 2"	[alpha identifier is displayed with strikethrough off, request IMSI]
11	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.9.1	[Command performed successfully, AT Response containing IMSI]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.9.1	
14	ME → UICC	FETCH	
15	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.9.1	
16	ME (→ USER)	Display " Run AT Command 1"	[alpha identifier is displayed with strikethrough on, request IMSI]
17	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.9.1	[Command performed successfully, AT Response containing IMSI]
18	UICC → ME	PROACTIVE UICC SESSION ENDED	
19	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.9.3	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.9.3	
22	ME (→ USER)	Display "Run AT Command 3"	[alpha identifier is displayed with strikethrough off, request IMSI]
23	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.9.1	[Command performed successfully, AT Response containing IMSI]
24	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.9.1

Logically:

## Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 1"

## AT Command

AT Command string: "AT+CIMI"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	80	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.9.2

## Logically:

## Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 2"

## AT Command

AT Command string: "AT+CIMI"

## Text Attribute

Formatting position: 0  
 Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

## PROACTIVE UICC COMMAND: RUN AT COMMAND 3.9.3

## Logically:

## Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: ME

## Alpha Identifier

Alpha Identifier "Run AT Command 3"

## AT Command

AT Command string: "AT+CIMI"

## Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	33	A8	07	41	54	2B	43	49
	4D	49										

## TERMINAL RESPONSE: RUN AT COMMAND 3.9.1

## Logically:

## Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## AT Response

AT Response string: IMSI

## Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

## 27.22.4.23.3.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.9.

## 27.22.4.23.3.10 RUN AT COMMAND (support of Text Attribute – Foreground and Background Colour)

## 27.22.4.23.3.10.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.23.3.10.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

## 27.22.4.23.3.10.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with foreground and background colour text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.10.4 Method of test

27.22.4.23.3.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.10.4.2 Procedure

**Expected Sequence 3.10(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Foreground and Background Colour)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.10.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.10.1	
4	ME (→ USER)	Display "Run AT Command 1"	[alpha identifier is displayed with foreground and background colour according to the text attribute configuration, request IMSI]
5	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.10.1	[Command performed successfully, AT Response containing IMSI]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	
7	UICC → ME	PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.10.2	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: RUN AT COMMAND 3.10.2	
10	ME (→ USER)	Display "Run AT Command 2"	[alpha identifier is displayed with ME's default foreground and background colour, request IMSI]
11	ME → UICC	TERMINAL RESPONSE: RUN AT COMMAND 3.10.1	[Command performed successfully, AT Response containing IMSI]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.10.1

Logically:

Command details

Command number: 1  
Command type: RUN AT COMMAND  
Command qualifier: "00"

Device identities

Source device: UICC  
Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 1"

AT Command

AT Command string: "AT+CIMI"

Text Attribute

Formatting position: 0

Formatting length: 16  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	2A	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	31	A8	07	41	54	2B	43	49
	4D	49	D0	04	00	10	00	B4				

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.10.2

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier

Alpha Identifier "Run AT Command 2"

AT Command

AT Command string: "AT+CIMI"

Coding:

BER-TLV:	D0	24	81	03	01	34	00	82	02	81	82	85
	10	52	75	6E	20	41	54	20	43	6F	6D	6D
	61	6E	64	20	32	A8	07	41	54	2B	43	49
	4D	49										

TERMINAL RESPONSE: RUN AT COMMAND 3.10.1

Logically:

Command details

Command number: 1  
 Command type: RUN AT COMMAND  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

AT Response

AT Response string: IMSI

Coding:

BER-TLV:	81	03	01	34	00	82	02	82	81	83	01	00
	A9	08	09	10	10	10	32	54	76	98		

27.22.4.23.3.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.10.

#### 27.22.4.23.4 RUN AT COMMAND (UCS2 display in Cyrillic)

##### 27.22.4.23.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.23.4.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

##### 27.22.4.23.4.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with UCS2 alpha identifier as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

##### 27.22.4.23.4.4 Method of test

###### 27.22.4.23.4.4.1 Initial conditions

The ME is connected to the UICC Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

###### 27.22.4.23.4.4.2 Procedure

#### **Expected Sequence 4.1(RUN AT COMMAND, alpha identifier presented coded with UCS2 in Cyrillic, request ME Manufacturer ID)**

See ETSI TS 102 384 [26] in subclause 27.22.4.23.4.4.2, Expected Sequence 4.1.

##### 27.22.4.23.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

#### 27.22.4.23.5 RUN AT COMMAND (UCS2 display in Chinese)

##### 27.22.4.23.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.23.5.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.5.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with UCS2 alpha identifier as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.5.4 Method of test

##### 27.22.4.23.5.4.1 Initial conditions

The ME is connected to the UICC Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

##### 27.22.4.23.5.4.2 Procedure

#### **Expected Sequence 5.1(RUN AT COMMAND, alpha identifier presented coded with UCS2 in Chinese, request ME Manufacturer ID)**

See ETSI TS 102 384 [26] in subclause 27.22.4.23.5.4.2, Expected Sequence 5.1.

#### 27.22.4.23.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

#### 27.22.4.23.6 RUN AT COMMAND (UCS2 display in Katakana)

##### 27.22.4.23.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.23.6.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- 3GPP TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- 3GPP TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.6.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with UCS2 alpha identifier as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.6.4 Method of test

##### 27.22.4.23.6.4.1 Initial conditions

The ME is connected to the UICC Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

#### 27.22.4.23.6.4.2 Procedure

### **Expected Sequence 6.1(RUN AT COMMAND, alpha identifier presented coded with UCS2 in Katakana, request ME Manufacturer ID)**

See ETSI TS 102 384 [26] in subclause 27.22.4.23.6.4.2, Expected Sequence 6.1.

#### 27.22.4.23.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

### 27.22.4.24 SEND DTMF

#### 27.22.4.24.1 SEND DTMF (Normal)

##### 27.22.4.24.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.24.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

##### 27.22.4.24.1.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that if an alpha identifier is provided by the UICC and is a null data object the ME does not give any information to the user on the fact that the ME is performing a SEND DTMF command.

##### 27.22.4.24.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.24.1.4. 2 Procedure

**Expected Sequence 1.1 (SEND DTMF, normal)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 1.1.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 1.1.1	
7	ME → USER	May give information to the user concerning what is happening. Do not locally generate audible DTMF tones and play them to the user.	
8	ME → USS	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	ME → USS	Start DTMF 1.2	["2"]
11	ME → UICC	TERMINAL RESPONSE: SEND DTMF 1.1.1	[Command performed successfully]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	User → ME	End the call	

**PROACTIVE COMMAND: SEND DTMF 1.1.1**

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 DTMF String: "1" pause "2"

Coding:

BER-TLV:	D0	0D	81	03	01	14	00	82	02	81	83	AC
	02	C1	F2									

**Start DTMF 1.1**

Logically:

DTMF String: "1"

**Start DTMF 1.2**

Logically:

DTMF String: "2"

**TERMINAL RESPONSE: SEND DTMF 1.1.1**

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.2 (SEND DTMF, containing alpha identifier)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 1.2.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 1.2.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	Alpha identifier
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 1.1.1	[Command performed successfully]
19	UICC → ME	PROACTIVE UICC SESSION ENDED	
20	User → ME	End the call	

PROACTIVE COMMAND: SEND DTMF 1.2.1

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Send DTMF"  
 DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1B	81	03	01	14	00	82	02	81	83	85
	09	53	65	6E	64	20	44	54	4D	46	AC	05
	21	43	65	87	09							

Start DTMF 1.3

Logically:

DTMF String: "3"

Start DTMF 1.4

Logically:

DTMF String: "4"

Start DTMF 1.5

Logically:

DTMF String: "5"

Start DTMF 1.6

Logically:

DTMF String: "6"

Start DTMF 1.7

Logically:

DTMF String: "7"

Start DTMF 1.8

Logically:

DTMF String: "8"

Start DTMF 1.9

Logically:

DTMF String: "9"

Start DTMF 1.10

Logically:

DTMF String: "0"

### **Expected Sequence 1.3 (SEND DTMF, containing alpha identifier with null data object)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND	
5	ME → UICC	PENDING: SEND DTMF 1.3.1	
6	UICC → ME	FETCH	Alpha identifier with null data object
7	UICC → ME	PROACTIVE COMMAND: SEND DTMF 1.3.1	
8	ME → USER	Do not give any information to the user on the fact that the ME is performing a SEND DTMF command. Do not locally generate audible DTMF tones and play them to the user.	
9	ME → USS	Start DTMF 1.1	["1"]
10	ME		No DTMF sending for 30 seconds ±20%
11	ME → USS	Start DTMF 1.2	["2"]
12	ME → UICC	TERMINAL RESPONSE: SEND DTMF 1.1.1	[Command performed successfully]
13	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	User → ME	End the call	

PROACTIVE COMMAND: SEND DTMF 1.3.1

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "" (null data object)  
 DTMF String: "1" pause pause pause pause pause pause pause pause "2"

Coding:

BER-TLV:	D0	13	81	03	01	14	00	82	02	81	83	85
	00	AC	06	C1	CC	CC	CC	CC	2C			

Expected Sequence 1.4 (SEND DTMF, mobile is not in a speech call)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND	[Mobile is not in a speech call]
2	ME → UICC	PENDING: SEND DTMF 1.1.1	
3	UICC → ME	FETCH	
4	UICC → ME	PROACTIVE COMMAND: SEND DTMF 1.1.1	
5	ME → UICC	TERMINAL RESPONSE: SEND DTMF 1.4.1	[ME currently unable to process command, not in speech call]
6	UICC → ME	PROACTIVE UICC SESSION ENDED	

TERMINAL RESPONSE: SEND DTMF 1.4.1

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: ME currently unable to process command  
 Additional information: Not in speech call

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	02	20
	07											

#### 27.22.4.24.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.4.

#### 27.22.4.24.2 SEND DTMF (Display of icons)

##### 27.22.4.24.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.24.2.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44, clause 8.31 and clause 6.5.4.

##### 27.22.4.24.2.3 Test purpose

To verify that after a call has been successfully established the ME send the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME do not locally generate audible DTMF tones and play them to the user.

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the icons which are referred to in the contents of the SEND DTMF proactive UICC command.

##### 27.22.4.24.2.4 Method of test

###### 27.22.4.24.2.4.1 Initial conditions

The ME is connected to the SIM Simulator and only connected to the System Simulator if the System Simulator is mentioned in the sequence table. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

The elementary files are coded as Toolkit default.

###### 27.22.4.24.2.4.2 Procedure

#### **Expected Sequence 2.1A (SEND DTMF, BASIC ICON self explanatory, successful)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND	
5	ME → UICC	PENDING: SEND DTMF 2.1.1	
6	UICC → ME	FETCH	[BASIC-ICON, self-explanatory]
7	ME → USER	PROACTIVE COMMAND: SEND DTMF 2.1.1 Display the BASIC-ICON Do not locally generate audible DTMF tones and play them to the user.	
8	ME → USS	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	ME → USS	Start DTMF 1.2	["2"]
11	ME → UICC	TERMINAL RESPONSE: SEND DTMF 2.1.1A	[Command performed successfully]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	User → ME	End the call	

## PROACTIVE COMMAND: SEND DTMF 2.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Basic Icon"  
 DTMF String: "1" pause "2"

## Icon identifier

Icon qualifier: icon is self-explanatory  
 Icon identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0A	42	61	73	69	63	20	49	63	6F	6E	AC
	02	C1	F2	9E	02	00	01					

## DTMF Request 2.1.1

Logically:

DTMF String: \$DTMF\_2.1.\$ = "C1 F2" (given as example)

## TERMINAL RESPONSE: SEND DTMF 2.1.1A

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 2.1B (SEND DTMF, BASIC ICON self explanatory, requested icon could not be displayed)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 2.1.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 2.1.1	[BASIC-ICON, self-explanatory]
7	ME → USER	Display "Basic Icon" without the icon Do not locally generate audible DTMF tones and play them to the user.	
8	ME → USS	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20 %
10	ME → USS	Start DTMF 1.2	["2"]
11	ME → UICC	TERMINAL RESPONSE: SEND DTMF 2.1.1B	[Command performed successfully, but requested icon could not be displayed]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	User → ME	End the call	

TERMINAL RESPONSE: SEND DTMF 2.1.1B

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully, but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	04
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 2.2A (SEND DTMF, COLOUR-ICON self explanatory, successful)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND	
5	ME → UICC	PENDING: SEND DTMF 2.2.1	
6	UICC → ME	FETCH	[COLOUR-ICON]
7	ME → USER	PROACTIVE COMMAND: SEND DTMF 2.2.1 Display the COLOUR-ICON Do not locally generate audible DTMF tones and play them to the user.	
8	ME → USS	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	ME → USS	Start DTMF 1.2	["2"]
11	ME → UICC	TERMINAL RESPONSE: SEND DTMF 2.1.1A	[Command performed successfully]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	User → ME	End the call	

PROACTIVE COMMAND: SEND DTMF 2.2.1

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Colour Icon"  
 DTMF String: "1" pause "2"

Icon identifier:

Icon qualifier: icon is self-explanatory  
 Icon identifier: record 2 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	1E	81	03	01	14	00	82	02	81	83	85
	0B	43	6F	6C	6F	75	72	20	49	63	6F	6E
	AC	02	C1	F2	9E	02	00	02				

**Expected Sequence 2.2B (SEND DTMF, COLOUR-ICON self explanatory, requested icon could not be displayed)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 2.2.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 2.2.1	[COLOUR-ICON]
7	ME → USER	Display "Colour Icon" without the icon Do not locally generate audible DTMF tones and play them to the user.	
8	ME → USS	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	ME → USS	Start DTMF 1.2	["2"]
11	ME → UICC	TERMINAL RESPONSE: SEND DTMF 2.1.1B	[Command performed successfully, but requested icon could not be displayed]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	User → ME	End the call	

### Expected Sequence 2.3A (SEND DTMF, Alpha identifier & BASIC-ICON, not self-explanatory, successful)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 2.3.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 2.3.1	[Alpha identifier & BASIC-ICON, not self-explanatory]
7	ME → USER	Display 'Send DTMF' and the BASIC-ICON Do not locally generate audible DTMF tones and play them to the user.	
8	ME → USS	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20 %
10	ME → USS	Start DTMF 1.2	["2"]
11	ME → UICC	TERMINAL RESPONSE: SEND DTMF 2.1.1A	[Command performed successfully]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	User → ME	End the call	

PROACTIVE COMMAND: SEND DTMF 2.3.1

Logically:

Command details

Command number: 1  
Command type: SEND DTMF  
Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Send DTMF"  
 DTMF String: "1" pause "2"  
 Icon identifier:  
 Icon qualifier: icon is not self-explanatory  
 Icon identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	1C	81	03	01	14	00	82	02	81	83	85
	09	53	65	6E	64	20	44	54	4D	46	AC	02
	C1	F2	9E	02	01	01						

**Expected Sequence 2.3B (SEND DTMF, Alpha identifier & BASIC-ICON, not self-explanatory, requested icon could not be displayed)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 2.3.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 2.3.1	[Alpha identifier & BASIC-ICON, not self-explanatory]
7	ME → USER	Display "Send DTMF" without the icon Do not locally generate audible DTMF tones and play them to the user.	
8	ME → USS	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	ME → USS	Start DTMF 1.2	["2"]
11	ME → UICC	TERMINAL RESPONSE: SEND DTMF 2.1.1B	[Command performed successfully, but requested icon could not be displayed]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	User → ME	End the call	

27.22.4.24.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.3.

27.22.4.24.3 SEND DTMF (UCS2 display in Cyrillic)

27.22.4.24.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.24.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646. [17].

### 27.22.4.24.3.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND DTMF proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

### 27.22.4.24.3.4 Method of test

#### 27.22.4.24.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.24.3.4.2 Procedure

### Expected Sequence 3.1 (SEND DTMF, successful, UCS2 text in Cyrillic)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 3.1.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 3.1.1	
7	ME → USER	Display "ЗДРАВСТВУЙТЕ"	["Hello" in Russian]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	ME → USS	Start DTMF 1.2	["2"]
11	ME → UICC	TERMINAL RESPONSE: SEND DTMF 3.1.1	[Command performed successfully]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	User → ME	End the call	

### PROACTIVE COMMAND: SEND DTMF 3.1.1

Logically:

#### Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

#### Device identities

Source device: UICC  
 Destination device: Network

#### Alpha Identifier

Text: "ЗДРАВСТВУЙТЕ"  
 DTMF String: "1" pause "2"

Coding:

BER-TLV:	D0	28	81	03	01	14	00	82	02	81	83	85
	19	80	04	17	04	14	04	20	04	10	04	12
	04	21	04	22	04	12	04	23	04	19	04	22
	04	15	AC	02	C1	F2						

TERMINAL RESPONSE: SEND DTMF 3.1.1

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successful

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.12.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

#### 27.22.4.24.4 SEND DTMF (support of Text Attribute)

##### 27.22.4.24.4.1 SEND DTMF (support of Text Attribute – Left Alignment)

##### 27.22.4.24.4.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.24.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

##### 27.22.4.24.4.1.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the left alignment text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.1.4 Method of test

27.22.4.24.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.24.4.1.4.2 Procedure

#### Expected Sequence 4.1 (SEND DTMF, with text attribute – Left Alignment)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.1.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.1.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with left alignment]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.1.1	[Command performed successfully]
19	UICC → ME	PROACTIVE UICC SESSION ENDED	
20	User → ME	End the call	
21	User → ME	Set up a call to "+0123456789"	
22	ME → USS	The ME attempts to set up a call to "+0123456789"	
23	USS → ME	The ME receives the CONNECT message from the USS.	
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.1.2	
25	ME → UICC	FETCH	
26	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.1.2	
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Message shall be formatted without left alignment. Remark: If left alignment is the ME's default alignment as declared in table A.2/17, no alignment change will take place]
28	ME → USS	Start DTMF 1.1	["1"]
29	ME → USS	Start DTMF 1.2	["2"]
30	ME → USS	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]

33	ME → USS	Start DTMF 1.6	["6"]
34	ME → USS	Start DTMF 1.7	["7"]
35	ME → USS	Start DTMF 1.8	["8"]
36	ME → USS	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]
38	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.1.1	[Command performed successfully]
39	UICC → ME	PROACTIVE UICC SESSION ENDED	
40	User → ME	End the call	

## PROACTIVE COMMAND: SEND DTMF 4.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.1.2

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09					

## TERMINAL RESPONSE: SEND DTMF 4.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.24.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

## 27.22.4.24.4.2 SEND DTMF (support of Text Attribute – Center Alignment)

## 27.22.4.24.4.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

## 27.22.4.24.4.2.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the center alignment text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

## 27.22.4.24.4.2.4 Method of test

## 27.22.4.24.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.24.4.2.4.2 Procedure

**Expected Sequence 4.2 (SEND DTMF, with text attribute – Center Alignment)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.2.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.2.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with center alignment]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.2.1	[Command performed successfully]
19	UICC → ME	PROACTIVE UICC SESSION ENDED	
20	User → ME	End the call	
21	User → ME	Set up a call to "+0123456789"	
22	ME → USS	The ME attempts to set up a call to "+0123456789"	
23	USS → ME	The ME receives the CONNECT message from the USS.	
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.2.2	
25	ME → UICC	FETCH	
26	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.2.2	
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Message shall be formatted without center alignment. Remark: If center alignment is the ME's default alignment as declared in table A.2/17, no alignment change will take place]
28	ME → USS	Start DTMF 1.1	["1"]
29	ME → USS	Start DTMF 1.2	["2"]
30	ME → USS	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]
33	ME → USS	Start DTMF 1.6	["6"]
34	ME → USS	Start DTMF 1.7	["7"]
35	ME → USS	Start DTMF 1.8	["8"]
36	ME → USS	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]
38	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.2.1	[Command performed successfully]
39	UICC → ME	PROACTIVE UICC SESSION ENDED	
40	User → ME	End the call	

## PROACTIVE COMMAND: SEND DTMF 4.2.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	01
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.2.2

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09					

## TERMINAL RESPONSE: SEND DTMF 4.2.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.24.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

#### 27.22.4.24.4.3 SEND DTMF (support of Text Attribute – Right Alignment)

##### 27.22.4.24.4.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.24.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

##### 27.22.4.24.4.3.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the right alignment text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

##### 27.22.4.24.4.3.4 Method of test

###### 27.22.4.24.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

###### 27.22.4.24.4.3.4.2 Procedure

#### **Expected Sequence 4.3 (SEND DTMF, with text attribute – Right Alignment)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.3.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.3.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with right alignment]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.3.1	[Command performed successfully]
19	UICC → ME	PROACTIVE UICC SESSION ENDED	
20	User → ME	End the call	
21	User → ME	Set up a call to "+0123456789"	
22	ME → USS	The ME attempts to set up a call to "+0123456789"	
23	USS → ME	The ME receives the CONNECT message from the USS.	
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.3.2	
25	ME → UICC	FETCH	
26	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.3.2	
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Message shall be formatted without right alignment. Remark: If right alignment is the ME's default alignment as declared in table A.2/17, no alignment change will take place]
28	ME → USS	Start DTMF 1.1	["1"]
29	ME → USS	Start DTMF 1.2	["2"]
30	ME → USS	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]
33	ME → USS	Start DTMF 1.6	["6"]
34	ME → USS	Start DTMF 1.7	["7"]
35	ME → USS	Start DTMF 1.8	["8"]
36	ME → USS	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]
38	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.3.1	[Command performed successfully]
39	UICC → ME	PROACTIVE UICC SESSION ENDED	
40	User → ME	End the call	

PROACTIVE COMMAND: SEND DTMF 4.3.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF  
 Command qualifier: "00"  
 Device identities  
   Source device: UICC  
   Destination device: Network  
 Alpha identifier: "Send DTMF 1"  
 DTMF String: "1234567890"  
 Text Attribute  
   Formatting position: 0  
   Formatting length: 11  
   Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
   Strikethrough Off  
   Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	B0	02
	B4											

PROACTIVE COMMAND: SEND DTMF 4.3.2

Logically:

Command details  
   Command number: 1  
   Command type: SEND DTMF  
   Command qualifier: "00"  
 Device identities  
   Source device: UICC  
   Destination device: Network  
 Alpha identifier: "Send DTMF 2"  
 DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09					

TERMINAL RESPONSE: SEND DTMF 4.3.1

Logically:

Command details  
   Command number: 1  
   Command type: SEND DTMF  
   Command qualifier: "00"  
 Device identities  
   Source device: ME  
   Destination device: UICC  
 Result  
   General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.24.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

#### 27.22.4.24.4.4 SEND DTMF (support of Text Attribute – Large Font Size)

##### 27.22.4.24.4.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.24.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

##### 27.22.4.24.4.4.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the large font size text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

##### 27.22.4.24.4.4.4 Method of test

###### 27.22.4.24.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

###### 27.22.4.24.4.4.4.2 Procedure

### **Expected Sequence 4.4 (SEND DTMF, with text attribute – Large Font Size)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.4.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.4.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with large font size]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.4.1	[Command performed successfully]
19	UICC → ME	PROACTIVE UICC SESSION ENDED	
20	User → ME	End the call	
21	User → ME	Set up a call to "+0123456789"	
22	ME → USS	The ME attempts to set up a call to "+0123456789"	
23	USS → ME	The ME receives the CONNECT message from the USS.	
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.4.2	
25	ME → UICC	FETCH	
26	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.4.2	
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with normal font size]
28	ME → USS	Start DTMF 1.1	["1"]
29	ME → USS	Start DTMF 1.2	["2"]
30	ME → USS	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]
33	ME → USS	Start DTMF 1.6	["6"]
34	ME → USS	Start DTMF 1.7	["7"]
35	ME → USS	Start DTMF 1.8	["8"]
36	ME → USS	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]
38	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.4.1	[Command performed successfully]
39	UICC → ME	PROACTIVE UICC SESSION ENDED	
40	User → ME	End the call	
41	User → ME	Set up a call to "+0123456789"	
42	ME → USS	The ME attempts to set up a call to "+0123456789"	
43	USS → ME	The ME receives the CONNECT message from the USS.	
44	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.4.1	
45	ME → UICC	FETCH	

46	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.4.1	
47	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with large font size]
48	ME → USS	Start DTMF 1.1	["1"]
49	ME → USS	Start DTMF 1.2	["2"]
50	ME → USS	Start DTMF 1.3	["3"]
51	ME → USS	Start DTMF 1.4	["4"]
52	ME → USS	Start DTMF 1.5	["5"]
53	ME → USS	Start DTMF 1.6	["6"]
54	ME → USS	Start DTMF 1.7	["7"]
55	ME → USS	Start DTMF 1.8	["8"]
56	ME → USS	Start DTMF 1.9	["9"]
57	ME → USS	Start DTMF 1.10	["0"]
58	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.4.1	[Command performed successfully]
59	UICC → ME	PROACTIVE UICC SESSION ENDED	
60	User → ME	End the call	
61	User → ME	Set up a call to "+0123456789"	
62	ME → USS	The ME attempts to set up a call to "+0123456789"	
63	USS → ME	The ME receives the CONNECT message from the USS.	
64	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.4.3	
65	ME → UICC	FETCH	
66	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.4.3	
67	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with normal font size]
68	ME → USS	Start DTMF 1.1	["1"]
69	ME → USS	Start DTMF 1.2	["2"]
70	ME → USS	Start DTMF 1.3	["3"]
71	ME → USS	Start DTMF 1.4	["4"]
72	ME → USS	Start DTMF 1.5	["5"]
73	ME → USS	Start DTMF 1.6	["6"]
74	ME → USS	Start DTMF 1.7	["7"]
75	ME → USS	Start DTMF 1.8	["8"]
76	ME → USS	Start DTMF 1.9	["9"]
77	ME → USS	Start DTMF 1.10	["0"]
78	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.4.1	[Command performed successfully]
79	UICC → ME	PROACTIVE UICC SESSION ENDED	
80	User → ME	End the call	

## PROACTIVE COMMAND: SEND DTMF 4.4.1

## Logically:

## Command details

Command number: 1  
Command type: SEND DTMF  
Command qualifier: "00"

## Device identities

Source device: UICC  
Destination device: Network

Alpha identifier: "Send DTMF 1"  
DTMF String: "1234567890"  
Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	04
	B4											

PROACTIVE COMMAND: SEND DTMF 4.4.2

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

PROACTIVE COMMAND: SEND DTMF 4.4.3

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 3"

DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

TERMINAL RESPONSE: SEND DTMF 4.4.1

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.24.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

27.22.4.24.4.5 SEND DTMF (support of Text Attribute – Small Font Size)

27.22.4.24.4.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.24.4.5.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

27.22.4.24.4.5.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the small font size text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.5.4 Method of test

27.22.4.24.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

## 27.22.4.24.4.5.4.2 Procedure

**Expected Sequence 4.5 (SEND DTMF, with text attribute – Small Font Size)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.5.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.5.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with small font size]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.5.1	[Command performed successfully]
19	UICC → ME	PROACTIVE UICC SESSION ENDED	
20	User → ME	End the call	
21	User → ME	Set up a call to "+0123456789"	
22	ME → USS	The ME attempts to set up a call to "+0123456789"	
23	USS → ME	The ME receives the CONNECT message from the USS.	
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.5.2	
25	ME → UICC	FETCH	
26	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.5.2	
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with normal font size]
28	ME → USS	Start DTMF 1.1	["1"]
29	ME → USS	Start DTMF 1.2	["2"]
30	ME → USS	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]
33	ME → USS	Start DTMF 1.6	["6"]
34	ME → USS	Start DTMF 1.7	["7"]
35	ME → USS	Start DTMF 1.8	["8"]
36	ME → USS	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]
38	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.5.1	[Command performed successfully]
39	UICC → ME	PROACTIVE UICC SESSION ENDED	
40	User → ME	End the call	
41	User → ME	Set up a call to "+0123456789"	

42	ME → USS	The ME attempts to set up a call to "+0123456789"	
43	USS → ME	The ME receives the CONNECT message from the USS.	
44	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.5.1	
45	ME → UICC	FETCH	
46	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.5.1	
47	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with small font size]
48	ME → USS	Start DTMF 1.1	["1"]
49	ME → USS	Start DTMF 1.2	["2"]
50	ME → USS	Start DTMF 1.3	["3"]
51	ME → USS	Start DTMF 1.4	["4"]
52	ME → USS	Start DTMF 1.5	["5"]
53	ME → USS	Start DTMF 1.6	["6"]
54	ME → USS	Start DTMF 1.7	["7"]
55	ME → USS	Start DTMF 1.8	["8"]
56	ME → USS	Start DTMF 1.9	["9"]
57	ME → USS	Start DTMF 1.10	["0"]
58	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.5.1	[Command performed successfully]
59	UICC → ME	PROACTIVE UICC SESSION ENDED	
60	User → ME	End the call	
61	User → ME	Set up a call to "+0123456789"	
62	ME → USS	The ME attempts to set up a call to "+0123456789"	
63	USS → ME	The ME receives the CONNECT message from the USS.	
64	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.5.3	
65	ME → UICC	FETCH	
66	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.5.3	
67	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with normal font size]
68	ME → USS	Start DTMF 1.1	["1"]
69	ME → USS	Start DTMF 1.2	["2"]
70	ME → USS	Start DTMF 1.3	["3"]
71	ME → USS	Start DTMF 1.4	["4"]
72	ME → USS	Start DTMF 1.5	["5"]
73	ME → USS	Start DTMF 1.6	["6"]
74	ME → USS	Start DTMF 1.7	["7"]
75	ME → USS	Start DTMF 1.8	["8"]
76	ME → USS	Start DTMF 1.9	["9"]
77	ME → USS	Start DTMF 1.10	["0"]
78	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.5.1	[Command performed successfully]
79	UICC → ME	PROACTIVE UICC SESSION ENDED	
80	User → ME	End the call	

PROACTIVE COMMAND: SEND DTMF 4.5.1

Logically:

Command details

Command number: 1  
Command type: SEND DTMF

Command qualifier: "00"  
 Device identities  
   Source device: UICC  
   Destination device: Network  
 Alpha identifier: "Send DTMF 1"  
 DTMF String: "1234567890"  
 Text Attribute  
   Formatting position: 0  
   Formatting length: 11  
   Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,  
   Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	08
	B4											

PROACTIVE COMMAND: SEND DTMF 4.5.2

Logically:

Command details  
   Command number: 1  
   Command type: SEND DTMF  
   Command qualifier: "00"  
 Device identities  
   Source device: UICC  
   Destination device: Network  
 Alpha identifier: "Send DTMF 2"  
 DTMF String: "1234567890"  
 Text Attribute  
   Formatting position: 0  
   Formatting length: 11  
   Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
   Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

PROACTIVE COMMAND: SEND DTMF 4.5.3

Logically:

Command details  
   Command number: 1  
   Command type: SEND DTMF  
   Command qualifier: "00"  
 Device identities  
   Source device: UICC  
   Destination device: Network  
 Alpha identifier: "Send DTMF 3"  
 DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

TERMINAL RESPONSE: SEND DTMF 4.5.1

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.24.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

27.22.4.24.4.6 SEND DTMF (support of Text Attribute – Bold On)

27.22.4.24.4.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.24.4.6.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

27.22.4.24.4.6.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the bold text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.6.4 Method of test

27.22.4.24.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.24.4.6.4.2 Procedure

### Expected Sequence 4.6 (SEND DTMF, with text attribute – Bold On)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.6.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.6.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with bold on]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.6.1	[Command performed successfully]
19	UICC → ME	PROACTIVE UICC SESSION ENDED	
20	User → ME	End the call	
21	User → ME	Set up a call to "+0123456789"	
22	ME → USS	The ME attempts to set up a call to "+0123456789"	
23	USS → ME	The ME receives the CONNECT message from the USS.	
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.6.2	
25	ME → UICC	FETCH	
26	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.6.2	
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with bold off]
28	ME → USS	Start DTMF 1.1	["1"]
29	ME → USS	Start DTMF 1.2	["2"]
30	ME → USS	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]
33	ME → USS	Start DTMF 1.6	["6"]
34	ME → USS	Start DTMF 1.7	["7"]
35	ME → USS	Start DTMF 1.8	["8"]
36	ME → USS	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]

38	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.6.1	[Command performed successfully]
39	UICC → ME	PROACTIVE UICC SESSION ENDED	
40	User → ME	End the call	
41	User → ME	Set up a call to "+0123456789"	
42	ME → USS	The ME attempts to set up a call to "+0123456789"	
43	USS → ME	The ME receives the CONNECT message from the USS.	
44	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.6.1	
45	ME → UICC	FETCH	
46	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.6.1	
47	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with bold on]
48	ME → USS	Start DTMF 1.1	["1"]
49	ME → USS	Start DTMF 1.2	["2"]
50	ME → USS	Start DTMF 1.3	["3"]
51	ME → USS	Start DTMF 1.4	["4"]
52	ME → USS	Start DTMF 1.5	["5"]
53	ME → USS	Start DTMF 1.6	["6"]
54	ME → USS	Start DTMF 1.7	["7"]
55	ME → USS	Start DTMF 1.8	["8"]
56	ME → USS	Start DTMF 1.9	["9"]
57	ME → USS	Start DTMF 1.10	["0"]
58	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.6.1	[Command performed successfully]
59	UICC → ME	PROACTIVE UICC SESSION ENDED	
60	User → ME	End the call	
61	User → ME	Set up a call to "+0123456789"	
62	ME → USS	The ME attempts to set up a call to "+0123456789"	
63	USS → ME	The ME receives the CONNECT message from the USS.	
64	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.6.3	
65	ME → UICC	FETCH	
66	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.6.3	
67	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with bold off]
68	ME → USS	Start DTMF 1.1	["1"]
69	ME → USS	Start DTMF 1.2	["2"]
70	ME → USS	Start DTMF 1.3	["3"]
71	ME → USS	Start DTMF 1.4	["4"]
72	ME → USS	Start DTMF 1.5	["5"]
73	ME → USS	Start DTMF 1.6	["6"]
74	ME → USS	Start DTMF 1.7	["7"]
75	ME → USS	Start DTMF 1.8	["8"]
76	ME → USS	Start DTMF 1.9	["9"]
77	ME → USS	Start DTMF 1.10	["0"]
78	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.6.1	[Command performed successfully]
79	UICC → ME	PROACTIVE UICC SESSION ENDED	
80	User → ME	End the call	

PROACTIVE COMMAND: SEND DTMF 4.6.1

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	10
	B4	00										

PROACTIVE COMMAND: SEND DTMF 4.6.2

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

PROACTIVE COMMAND: SEND DTMF 4.6.3

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: UICC

Destination device: Network  
 Alpha identifier: "Send DTMF 3"  
 DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

TERMINAL RESPONSE: SEND DTMF 4.6.1

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.24.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

27.22.4.24.4.7 SEND DTMF (support of Text Attribute – Italic On)

27.22.4.24.4.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.24.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

27.22.4.24.4.7.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the italic text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.7.4 Method of test

27.22.4.24.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.24.4.7.4.2 Procedure

#### Expected Sequence 4.7 (SEND DTMF, with text attribute – *Italic On*)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.7.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.7.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with italic on]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.7.1	[Command performed successfully]
19	UICC → ME	PROACTIVE UICC SESSION ENDED	
20	User → ME	End the call	
21	User → ME	Set up a call to "+0123456789"	
22	ME → USS	The ME attempts to set up a call to "+0123456789"	
23	USS → ME	The ME receives the CONNECT message from the USS.	
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.7.2	
25	ME → UICC	FETCH	
26	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.7.2	
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with italic off]
28	ME → USS	Start DTMF 1.1	["1"]
29	ME → USS	Start DTMF 1.2	["2"]
30	ME → USS	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]

33	ME → USS	Start DTMF 1.6	["6"]
34	ME → USS	Start DTMF 1.7	["7"]
35	ME → USS	Start DTMF 1.8	["8"]
36	ME → USS	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]
38	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.7.1	[Command performed successfully]
39	UICC → ME	PROACTIVE UICC SESSION ENDED	
40	User → ME	End the call	
41	User → ME	Set up a call to "+0123456789"	
42	ME → USS	The ME attempts to set up a call to "+0123456789"	
43	USS → ME	The ME receives the CONNECT message from the USS.	
44	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.7.1	
45	ME → UICC	FETCH	
46	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.7.1	
47	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with italic on]
48	ME → USS	Start DTMF 1.1	["1"]
49	ME → USS	Start DTMF 1.2	["2"]
50	ME → USS	Start DTMF 1.3	["3"]
51	ME → USS	Start DTMF 1.4	["4"]
52	ME → USS	Start DTMF 1.5	["5"]
53	ME → USS	Start DTMF 1.6	["6"]
54	ME → USS	Start DTMF 1.7	["7"]
55	ME → USS	Start DTMF 1.8	["8"]
56	ME → USS	Start DTMF 1.9	["9"]
57	ME → USS	Start DTMF 1.10	["0"]
58	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.7.1	[Command performed successfully]
59	UICC → ME	PROACTIVE UICC SESSION ENDED	
60	User → ME	End the call	
61	User → ME	Set up a call to "+0123456789"	
62	ME → USS	The ME attempts to set up a call to "+0123456789"	
63	USS → ME	The ME receives the CONNECT message from the USS.	
64	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.7.3	
65	ME → UICC	FETCH	
66	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.7.3	
67	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with italic off]
68	ME → USS	Start DTMF 1.1	["1"]
69	ME → USS	Start DTMF 1.2	["2"]
70	ME → USS	Start DTMF 1.3	["3"]
71	ME → USS	Start DTMF 1.4	["4"]
72	ME → USS	Start DTMF 1.5	["5"]
73	ME → USS	Start DTMF 1.6	["6"]
74	ME → USS	Start DTMF 1.7	["7"]
75	ME → USS	Start DTMF 1.8	["8"]
76	ME → USS	Start DTMF 1.9	["9"]
77	ME → USS	Start DTMF 1.10	["0"]
78	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.7.1	[Command performed successfully]
79	UICC → ME	PROACTIVE UICC SESSION ENDED	

80	User → ME	End the call
----	-----------	--------------

## PROACTIVE COMMAND: SEND DTMF 4.7.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	20
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.7.2

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.7.3

Logically:

## Command details

Command number: 1

Command type: SEND DTMF  
 Command qualifier: "00"  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Send DTMF 3"  
 DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

TERMINAL RESPONSE: SEND DTMF 4.7.1

Logically:

Command details  
 Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.24.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

#### 27.22.4.24.4.8 SEND DTMF (support of Text Attribute – Underline On)

##### 27.22.4.24.4.8.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.24.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

##### 27.22.4.24.4.8.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the underline text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.8.4 Method of test

##### 27.22.4.24.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.24.4.8.4.2 Procedure

### Expected Sequence 4.8 (SEND DTMF, with text attribute – Underline On)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.8.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.8.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with underline on]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.8.1	[Command performed successfully]
19	UICC → ME	PROACTIVE UICC SESSION ENDED	
20	User → ME	End the call	
21	User → ME	Set up a call to "+0123456789"	
22	ME → USS	The ME attempts to set up a call to "+0123456789"	
23	USS → ME	The ME receives the CONNECT message from the USS.	
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.8.2	
25	ME → UICC	FETCH	
26	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.8.2	
27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with underline off]
28	ME → USS	Start DTMF 1.1	["1"]

29	ME → USS	Start DTMF 1.2	["2"]
30	ME → USS	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]
33	ME → USS	Start DTMF 1.6	["6"]
34	ME → USS	Start DTMF 1.7	["7"]
35	ME → USS	Start DTMF 1.8	["8"]
36	ME → USS	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]
38	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.8.1	[Command performed successfully]
39	UICC → ME	PROACTIVE UICC SESSION ENDED	
40	User → ME	End the call	
41	User → ME	Set up a call to "+0123456789"	
42	ME → USS	The ME attempts to set up a call to "+0123456789"	
43	USS → ME	The ME receives the CONNECT message from the USS.	
44	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.8.1	
45	ME → UICC	FETCH	
46	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.8.1	
47	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with underline on]
48	ME → USS	Start DTMF 1.1	["1"]
49	ME → USS	Start DTMF 1.2	["2"]
50	ME → USS	Start DTMF 1.3	["3"]
51	ME → USS	Start DTMF 1.4	["4"]
52	ME → USS	Start DTMF 1.5	["5"]
53	ME → USS	Start DTMF 1.6	["6"]
54	ME → USS	Start DTMF 1.7	["7"]
55	ME → USS	Start DTMF 1.8	["8"]
56	ME → USS	Start DTMF 1.9	["9"]
57	ME → USS	Start DTMF 1.10	["0"]
58	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.8.1	[Command performed successfully]
59	UICC → ME	PROACTIVE UICC SESSION ENDED	
60	User → ME	End the call	
61	User → ME	Set up a call to "+0123456789"	
62	ME → USS	The ME attempts to set up a call to "+0123456789"	
63	USS → ME	The ME receives the CONNECT message from the USS.	
64	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.8.3	
65	ME → UICC	FETCH	
66	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.8.3	
67	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with underline off]
68	ME → USS	Start DTMF 1.1	["1"]
69	ME → USS	Start DTMF 1.2	["2"]
70	ME → USS	Start DTMF 1.3	["3"]
71	ME → USS	Start DTMF 1.4	["4"]
72	ME → USS	Start DTMF 1.5	["5"]
73	ME → USS	Start DTMF 1.6	["6"]
74	ME → USS	Start DTMF 1.7	["7"]
75	ME → USS	Start DTMF 1.8	["8"]
76	ME → USS	Start DTMF 1.9	["9"]

77	ME → USS	Start DTMF 1.10	["0"]
78	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.8.1	[Command performed successfully]
79	UICC → ME	PROACTIVE UICC SESSION ENDED	
80	User → ME	End the call	

## PROACTIVE COMMAND: SEND DTMF 4.8.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	40
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.8.2

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.8.3

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Send DTMF 3"  
 DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

TERMINAL RESPONSE: SEND DTMF 4.8.1

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.24.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

#### 27.22.4.24.4.9 SEND DTMF (support of Text Attribute – Strikethrough On)

##### 27.22.4.24.4.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.24.4.9.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

##### 27.22.4.24.4.9.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the strikethrough text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.9.4 Method of test

##### 27.22.4.24.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.24.4.9.4.2 Procedure

### Expected Sequence 4.9 (SEND DTMF, with text attribute – Strikethrough On)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.9.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.9.1	
7	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with strikethrough on]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.9.1	[Command performed successfully]
19	UICC → ME	PROACTIVE UICC SESSION ENDED	
20	User → ME	End the call	
21	User → ME	Set up a call to "+0123456789"	
22	ME → USS	The ME attempts to set up a call to "+0123456789"	
23	USS → ME	The ME receives the CONNECT message from the USS.	
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.9.2	
25	ME → UICC	FETCH	
26	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.9.2	

27	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with strikethrough off]
28	ME → USS	Start DTMF 1.1	["1"]
29	ME → USS	Start DTMF 1.2	["2"]
30	ME → USS	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]
33	ME → USS	Start DTMF 1.6	["6"]
34	ME → USS	Start DTMF 1.7	["7"]
35	ME → USS	Start DTMF 1.8	["8"]
36	ME → USS	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]
38	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.9.1	[Command performed successfully]
39	UICC → ME	PROACTIVE UICC SESSION ENDED	
40	User → ME	End the call	
41	User → ME	Set up a call to "+0123456789"	
42	ME → USS	The ME attempts to set up a call to "+0123456789"	
43	USS → ME	The ME receives the CONNECT message from the USS.	
44	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.9.1	
45	ME → UICC	FETCH	
46	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.9.1	
47	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with strikethrough on]
48	ME → USS	Start DTMF 1.1	["1"]
49	ME → USS	Start DTMF 1.2	["2"]
50	ME → USS	Start DTMF 1.3	["3"]
51	ME → USS	Start DTMF 1.4	["4"]
52	ME → USS	Start DTMF 1.5	["5"]
53	ME → USS	Start DTMF 1.6	["6"]
54	ME → USS	Start DTMF 1.7	["7"]
55	ME → USS	Start DTMF 1.8	["8"]
56	ME → USS	Start DTMF 1.9	["9"]
57	ME → USS	Start DTMF 1.10	["0"]
58	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.9.1	[Command performed successfully]
59	UICC → ME	PROACTIVE UICC SESSION ENDED	
60	User → ME	End the call	
61	User → ME	Set up a call to "+0123456789"	
62	ME → USS	The ME attempts to set up a call to "+0123456789"	
63	USS → ME	The ME receives the CONNECT message from the USS.	
64	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 4.9.3	
65	ME → UICC	FETCH	
66	UICC → ME	PROACTIVE COMMAND: SEND DTMF 4.9.3	
67	ME → USER	Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with strikethrough off]
68	ME → USS	Start DTMF 1.1	["1"]
69	ME → USS	Start DTMF 1.2	["2"]
70	ME → USS	Start DTMF 1.3	["3"]
71	ME → USS	Start DTMF 1.4	["4"]
72	ME → USS	Start DTMF 1.5	["5"]

73	ME → USS	Start DTMF 1.6	["6"]
74	ME → USS	Start DTMF 1.7	["7"]
75	ME → USS	Start DTMF 1.8	["8"]
76	ME → USS	Start DTMF 1.9	["9"]
77	ME → USS	Start DTMF 1.10	["0"]
78	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.9.1	[Command performed successfully]
79	UICC → ME	PROACTIVE UICC SESSION ENDED	
80	User → ME	End the call	

## PROACTIVE COMMAND: SEND DTMF 4.9.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough On  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	80B
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.9.2

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 2"

DTMF String: "1234567890"

## Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

## PROACTIVE COMMAND: SEND DTMF 4.9.3

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "Send DTMF 3"  
 DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	33
	AC	05	21	43	65	87	09					

## TERMINAL RESPONSE: SEND DTMF 4.9.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.24.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

## 27.22.4.24.4.10 SEND DTMF (support of Text Attribute – Foreground and Background Colour)

## 27.22.4.24.4.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.4.10.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

#### 27.22.4.24.4.10.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the foreground and background colour text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.10.4 Method of test

##### 27.22.4.24.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.24.4.10.4.2 Procedure

#### **Expected Sequence 4.10 (SEND DTMF, with text attribute – Foreground and Background Colour)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND	
5	ME → UICC	PENDING: SEND DTMF 4.10.1	
6	UICC → ME	FETCH	
7	ME → USER	PROACTIVE COMMAND: SEND DTMF 4.10.1 Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with foreground and background colour according to the text attribute configuration]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME → USS	Start DTMF 1.2	["2"]
10	ME → USS	Start DTMF 1.3	["3"]
11	ME → USS	Start DTMF 1.4	["4"]
12	ME → USS	Start DTMF 1.5	["5"]
13	ME → USS	Start DTMF 1.6	["6"]
14	ME → USS	Start DTMF 1.7	["7"]
15	ME → USS	Start DTMF 1.8	["8"]
16	ME → USS	Start DTMF 1.9	["9"]
17	ME → USS	Start DTMF 1.10	["0"]
18	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.10.1	[Command performed successfully]
19	UICC → ME	PROACTIVE UICC SESSION ENDED	
20	User → ME	End the call	
21	User → ME	Set up a call to "+0123456789"	
22	ME → USS	The ME attempts to set up a call to "+0123456789"	
23	USS → ME	The ME receives the CONNECT message from the USS.	
24	UICC → ME	PROACTIVE COMMAND	
25	ME → UICC	PENDING: SEND DTMF 4.10.2	
26	UICC → ME	FETCH	
27	ME → USER	PROACTIVE COMMAND: SEND DTMF 4.10.2 Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user.	[Alpha identifier is displayed with ME's default foreground and background colour]
28	ME → USS	Start DTMF 1.1	["1"]
29	ME → USS	Start DTMF 1.2	["2"]
30	ME → USS	Start DTMF 1.3	["3"]
31	ME → USS	Start DTMF 1.4	["4"]
32	ME → USS	Start DTMF 1.5	["5"]
33	ME → USS	Start DTMF 1.6	["6"]
34	ME → USS	Start DTMF 1.7	["7"]
35	ME → USS	Start DTMF 1.8	["8"]
36	ME → USS	Start DTMF 1.9	["9"]
37	ME → USS	Start DTMF 1.10	["0"]
38	ME → UICC	TERMINAL RESPONSE: SEND DTMF 4.10.1	[Command performed successfully]
39	UICC → ME	PROACTIVE UICC SESSION ENDED	
40	User → ME	End the call	

PROACTIVE COMMAND: SEND DTMF 4.10.1

Logically:

Command details

Command number: 1

Command type: SEND DTMF  
 Command qualifier: "00"  
 Device identities  
   Source device: UICC  
   Destination device: Network  
 Alpha identifier: "Send DTMF 1"  
 DTMF String: "1234567890"  
 Text Attribute  
   Formatting position: 0  
   Formatting length: 11  
   Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
   Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	23	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	31
	AC	05	21	43	65	87	09	D0	04	00	0B	00
	B4											

PROACTIVE COMMAND: SEND DTMF 4.10.2

Logically:

Command details  
   Command number: 1  
   Command type: SEND DTMF  
   Command qualifier: "00"  
 Device identities  
   Source device: UICC  
   Destination device: Network  
 Alpha identifier: "Send DTMF 2"  
 DTMF String: "1234567890"

Coding:

BER-TLV:	D0	1D	81	03	01	14	00	82	02	81	83	85
	0B	53	65	6E	64	20	44	54	4D	46	20	32
	AC	05	21	43	65	87	09					

TERMINAL RESPONSE: SEND DTMF 4.10.1

Logically:

Command details  
   Command number: 1  
   Command type: SEND DTMF  
   Command qualifier: "00"  
 Device identities  
   Source device: ME  
   Destination device: UICC  
 Result  
   General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.24.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

## 27.22.4.24.5 SEND DTMF (UCS2 Display in Chinese)

## 27.22.4.24.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.5.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters , as defined in:

- ISO/IEC 10646. [17].

## 27.22.4.24.5.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND DTMF proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.24.5.4 Method of test

## 27.22.4.24.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.24.5.4.2 Procedure

### Expected Sequence 5.1 (SEND DTMF, successful, UCS2 text in Chinese)

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 5.1.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 5.1.1	
7	ME → USER	Display "你好"	["Hello" in Chinese]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	ME → USS	Start DTMF 1.2	["2"]
11	ME → UICC	TERMINAL RESPONSE: SEND DTMF 5.1.1	[Command performed successfully]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	User → ME	End the call	

## PROACTIVE COMMAND: SEND DTMF 5.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

## Alpha Identifier

Text: "你好"  
 DTMF String: "1" pause "2"

Coding:

BER-TLV:	D0	14	81	03	01	14	00	82	02	81	83	85
	05	80	4F	60	59	7D	AC	02	C1	F2		

## TERMINAL RESPONSE: SEND DTMF 5.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successful

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.24.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

## 27.22.4.24.6 SEND DTMF (UCS2 Display in Katakana)

## 27.22.4.24.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.24.6.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- 3GPP TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters , as defined in:

- ISO/IEC 10646. [17].

## 27.22.4.24.6.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND DTMF proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.24.6.4 Method of test

## 27.22.4.24.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

## 27.22.4.24.6.4.2 Procedure

**Expected Sequence 6.1 (SEND DTMF, successful, UCS2 text)**

Some details of the DTMF protocol have been left out for clarity.

Step	Direction	MESSAGE / Action	Comments
1	User → ME	Set up a call to "+0123456789"	
2	ME → USS	The ME attempts to set up a call to "+0123456789"	
3	USS → ME	The ME receives the CONNECT message from the USS.	
4	UICC → ME	PROACTIVE COMMAND PENDING: SEND DTMF 6.1.1	
5	ME → UICC	FETCH	
6	UICC → ME	PROACTIVE COMMAND: SEND DTMF 6.1.1	
7	ME → USER	Display "ル"	["Test" in Katakana]
8	ME → USS	Start DTMF 1.1	["1"]
9	ME		No DTMF sending for 3 seconds ±20%
10	ME → USS	Start DTMF 1.2	["2"]
11	ME → UICC	TERMINAL RESPONSE: SEND DTMF 6.1.1	[Command performed successfully]
12	UICC → ME	PROACTIVE UICC SESSION ENDED	
13	User → ME	End the call	

## PROACTIVE COMMAND: SEND DTMF 6.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

## Device identities

Source device: UICC  
 Destination device: Network

## Alpha Identifier

Text: "ル"  
 DTMF String: "1" pause "2"

Coding:

BER-TLV:	D0	12	81	03	01	14	00	82	02	81	83	85
	03	80	30	EB	AC	02	C1	F2				

## TERMINAL RESPONSE: SEND DTMF 6.1.1

Logically:

Command details

Command number: 1  
 Command type: SEND DTMF  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successful

Coding:

BER-TLV:	81	03	01	14	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.24.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

## 27.22.4.25 LANGUAGE NOTIFICATION

### 27.22.4.25.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.25.2 Conformance Requirement

The ME shall conclude the command by sending TERMINAL RESPONSE (OK) to the UICC, as soon as possible after receiving the LANGUAGE NOTIFICATION proactive UICC command.

- 3GPP TS 31.111 clause 6.4.25 and clause 6.6.25.

### 27.22.4.25.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (OK) to the UICC after the ME receives the LANGUAGE NOTIFICATION proactive UICC command.

### 27.22.4.25.4 Method of Test

#### 27.22.4.25.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.25.4.2 Procedure

##### **Expected Sequence 1.1 (LANGUAGE NOTIFICATION)**

See ETSI TS 102 384 [26] in subclause 27.22.4.25.4.2, Expected Sequence 1.1.

##### **Expected Sequence 1.2 (LANGUAGE NOTIFICATION)**

See ETSI TS 102 384 [26] in subclause 27.22.4.25.4.2, Expected Sequence 1.2.

## 27.22.4.25.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 and 1.2.

## 27.22.4.26 LAUNCH BROWSER

## 27.22.4.26.1 LAUNCH BROWSER (No session already launched)

## 27.22.4.26.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.1.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15 and clause 8.31.

## 27.22.4.26.1.3 Test purpose

To verify that when the ME is in idle state, it launches properly the browser session required in LAUNCH BROWSER, and returns a successful result in the TERMINAL RESPONSE command.

## 27.22.4.26.1.4 Method of test

## 27.22.4.26.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default browser parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default browser parameters.

The mobile is in idle mode.

## Bearer Parameters

Precedence Class:	03
Delay Class:	04
Reliability Class:	03
Peak throughput class:	04
Mean throughput class:	31
Packet data protocol:	02 (IP)

## GPRS Parameters

Network access name:	TestGp.rs
User login:	UserLog
User password:	UserPwd

## UICC/ME interface transport level

Transport format:	UDP
Port number:	44444
Data destination address	01.01.01.01

## 27.22.4.26.1.4.2 Procedure

**Expected Sequence 1.1 (LAUNCH BROWSER, connect to the default URL)**

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 1.1.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id.]
4	ME → USER	ME displays the alpha identifier	
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 1.1.1	[Command performed successfully]
7	ME→USS	The ME attempts to launch the session with the default browser parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default browser session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

**PROACTIVE COMMAND: LAUNCH BROWSER 1.1.1**

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: UICC  
 Destination device: ME  
 URL  
 empty

Alpha Identifier "Default URL"

Coding:

BER-TLV:	D0	18	81	03	01	15	00	82	02	81	82	31
	00	05	0B	44	65	66	61	75	6C	74	20	55
	52	4C										

**TERMINAL RESPONSE: LAUNCH BROWSER 1.1.1**

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.2 (LAUNCH BROWSER, connect to the specified URL, alpha identifier length=0)**

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 1.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 1.2.1	[connect to defined URL, "launch browser, if not already launched, alpha identifier length=0]
4	ME → USER	No information should be displayed.	
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 1.2.1	[Command performed successfully]
7	ME→USS	The ME attempts to connect the URL specified in the LAUNCH BROWSER command.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the URL is properly connected. Then he/she ends the navigation. The ME returns in idle mode.	

**PROACTIVE COMMAND: LAUNCH BROWSER 1.2.1**

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME  
 URL: <http://xxx.yyy.zzz> (note: this URL shall be different from the default URL, but it can be reached from the gateway defined by default in the browser parameters of the mobile)

Alpha Identifier empty

Coding:

BER-TLV:	D0	1F	81	03	01	15	00	82	02	81	82	31
	12	68	74	74	70	3A	2F	2F	78	78	78	2E
	79	79	79	2E	7A	7A	7A	05	00			

**TERMINAL RESPONSE: LAUNCH BROWSER 1.2.1**

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.3 (LAUNCH BROWSER, Browser identity, no alpha identifier)**

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 1.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 1.3.1	[connect to the default URL, "launch browser, if not already launched, browser identity]
4	ME → USER	ME may display a default message of its own.	
5	USER → ME	The user may confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 1.3.1	[Command performed successfully]
7	ME→USS	The ME attempts to connect the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default browser session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

PROACTIVE COMMAND: LAUNCH BROWSER 1.3.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME  
 Browser Identity: default  
 URL: empty

Coding::

BER-TLV:	D0	0E	81	03	01	15	00	82	02	81	82	30
	01	00	31	00								

TERMINAL RESPONSE: LAUNCH BROWSER 1.3.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.4 (LAUNCH BROWSER, only GPRS bearer specified and gateway/proxy identity, GPRS supported by USS)**

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode], GPRS supported by USS, GPRS supported by the ME and activated]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 1.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 1.4.1	[connect to the default URL, "launch browser, if not already launched, 1 bearer specified, gateway/proxy id specified]
4	ME → USER	ME may display a default message	
5	USER → ME	The user may confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 1.4.1	[Command performed successfully]
7	ME→USS	The ME attempts to connect the default URL using the requested bearer and proxy identity	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the browser session is properly established with the required bearer. Then he/she ends the navigation. The ME returns in idle mode.	

PROACTIVE COMMAND: LAUNCH BROWSER 1.4.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty  
 Bearer: GPRS

Gateway/Proxy id

DCSUnpacked, 8 bits data  
 Text string: abc.def.ghi (different from the default IP address)

Coding::

BER-TLV:	D0	1C	81	03	01	15	00	82	02	81	82	31
	00	32	01	03	0D	0C	04	61	62	63	2E	64
	65	66	2E	67	68	69						

TERMINAL RESPONSE: LAUNCH BROWSER 1.4.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV: 81 03 01 15 00 82 02 82 81 83 01 00

Expected Sequence 1.5 Void

27.22.4.26.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.4

27.22.4.26.2 LAUNCH BROWSER (Interaction with current session)

27.22.4.26.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.2.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

27.22.4.26.2.3 Test purpose

To verify that when the ME is already busy in a browser session, it launches properly the browser session required in LAUNCH BROWSER, and returns a successful result in the TERMINAL RESPONSE.

27.22.4.26.2.4 Method of test

27.22.4.26.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to a Wap gateway is required. The default browser parameters (IP address, gateway/proxy identity, called number...) of the tested mobile shall be properly filled to access that gateway.

The mobile is busy in a browser session, the user navigates in pages different from the URL defined by default in browser parameters.

27.22.4.26.2.4.2 Procedure

**Expected Sequence 2.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL)**

Step	Direction	MESSAGE / Action	Comments
0	ME	The user is navigating in a browser session (not default URL).	[Browser is in use, the current session is not secured]

1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 2.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 2.1.1	[connect to the default URL, "use the existing browser", no null alpha id.]
4	ME → USER	ME displays the alpha identifier	
5	USER → ME	The user confirms the launch browser.	[user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 2.1.1	[Command performed successfully]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL.	

PROACTIVE COMMAND: LAUNCH BROWSER 2.1.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL"

Coding:

BER-TLV:	D0	18	81	03	01	15	02	82	02	81	82	31
	00	05	0B	44	65	66	61	75	6C	74	20	55
	52	4C										

TERMINAL RESPONSE: LAUNCH BROWSER 2.1.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 2.2 (LAUNCH BROWSER, close the existing browser session and launch new browser session, connect to the default URL)**

Step	Direction	MESSAGE / Action	Comments
0	ME	The user is navigating in a browser session (not default URL)..	[Browser is in use, the current session is not secured]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 2.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 2.2.1	[connect to the default URL, "close the existing browser session and launch new browser session", no null alpha id.]
4	ME → USER	ME displays the alpha identifier	
5	USER → ME	The user confirms the launch browser.	[user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 2.2.1	[Command performed successfully]
7	ME→USS	The ME closes the existing session and attempts to launch the session with the default browser parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default URL is connected; and the previous URL cannot be retrieved (to verify the previous session has been closed). Then he/she does not end the navigation.	

**PROACTIVE COMMAND: LAUNCH BROWSER 2.2.1**

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: close the existing browser session and launch new browser session  
 Device identities: Device identities  
 Source device: UICC  
 Destination device: ME  
 URL: empty  
 Alpha Identifier: "Default URL"

Coding:

BER-TLV:	D0	18	81	03	01	15	03	82	02	81	82	31
	00	05	0B	44	65	66	61	75	6C	74	20	55
	52	4C										

**TERMINAL RESPONSE: LAUNCH BROWSER 2.2.1**

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: close the existing browser session and launch new browser session

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	03	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 2.3 (LAUNCH BROWSER, if not already launched)**

Step	Direction	MESSAGE / Action	Comments
0	ME	The user is navigating in a browser session (not default URL)..	[Browser is in use, the current session is not secured]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 2.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 2.3.1	[connect to the default URL, "launch browser, if not already launched]
4	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 2.3.1	[ME unable to process command - browser unavailable]
5	UICC → ME	PROACTIVE UICC SESSION ENDED	
6	USER → ME	The user verifies that the default URL has not been connected. Then he/she ends the navigation. The ME returns in idle mode.	

**PROACTIVE COMMAND: LAUNCH BROWSER 2.3.1**

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Coding:

BER-TLV:	D0	0B	81	03	01	15	00	82	02	81	82	31
	00											

**TERMINAL RESPONSE: LAUNCH BROWSER 2.3.1**

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Launch browser generic error code

## Additional data

Browser unavailable

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	02	26
	02											

## 27.22.4.26.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.3.

## 27.22.4.26.3 LAUNCH BROWSER (UCS2 display in Cyrillic)

## 27.22.4.26.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.3.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646 [17].

## 27.22.4.26.3.3 Test purpose

To verify that the ME performs a proper user confirmation with an USC2 alpha identifier, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.26.3.4 Method of test

## 27.22.4.26.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default browser parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default browser parameters.

The mobile is busy in a browser session, the user navigates in pages different from the URL defined by default in Wap parameters.

## 27.22.4.26.3.4.2 Procedure

**Expected Sequence 3.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL, UCS2 in Cyrillic)**

Step	Direction	MESSAGE / Action	Comments
0	ME	The user is navigating in a browser session (not default URL)..	[Browser is in use, the current session is not secured]]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 3.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 3.1.1	[connect to the default URL, "use the existing browser", alpha id. In UCS2]

4	ME → USER	ME displays the alpha identifier "ЗДРАВСТВУЙТЕ"	["Hello" in Russian]
5	USER → ME	The user confirms the launch browser.	[user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 3.1.1	[Command performed successfully]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL.	

## PROACTIVE COMMAND: LAUNCH BROWSER 3.1.1

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

## Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

## Alpha Identifier

Data coding scheme: UCS2 (16 bits)  
 Text: "ЗДРАВСТВУЙТЕ"

Coding:

BER-TLV:	D0	26	81	03	01	15	02	82	02	81	82	31
	00	05	19	80	04	17	04	14	04	20	04	10
	04	12	04	21	04	22	04	12	04	23	04	19
	04	22	04	15								

## TERMINAL RESPONSE: LAUNCH BROWSER 3.1.1

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.26.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequence 3.1.

## 27.22.4.26.4 LAUNCH BROWSER (icons support)

## 27.22.4.26.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.4.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

## 27.22.4.26.4.3 Test purpose

To verify that the ME performs a proper user confirmation with an icon identifier, launches the browser session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.26.4.4 Method of test

## 27.22.4.26.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default browser parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default browser parameters.

The mobile is busy in a browser session, the user navigates in pages different from the URL defined by default in browser parameters.

## 27.22.4.26.4.4.2 Procedure

**Expected Sequence 4.1A (LAUNCH BROWSER, use the existing browser, icon not self explanatory, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 4.1.1	[Browser is in use, the current session is not secured]]
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 4.1.1	[connect to the default URL, "use the existing browser", no null alpha id.]
4	ME → USER	ME displays the alpha identifier and the icon	["Not self explan."]
5	USER → ME	The user confirms the launch browser.	[user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 4.1.1 A	[Command performed successfully]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	

9	USER → ME	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL.	
---	-----------	---	--

PROACTIVE COMMAND: LAUNCH BROWSER 4.1.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier

"Not self explan."

Icon identifier:

Icon qualifier: not self-explanatory  
 Icon identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	21	81	03	01	15	02	82	02	81	82	31
	00	05	10	4E	6F	74	20	73	65	6C	66	20
	65	78	70	6C	61	6E	2E	1E	02	01	01	

TERMINAL RESPONSE: LAUNCH BROWSER 4.1.1 A

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 4.1B (LAUNCH BROWSER, use the existing browser, icon not self explanatory, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 4.1.1	[Browser is in use, the current session is not secured]]
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 4.1.1	[connect to the default URL, "use the existing browser", no null alpha id.]
4	ME → USER	ME displays the alpha identifier Without the icon	["Not self explan."]
5	USER → ME	The user confirms the launch browser.	[user confirmation]

6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 4.1.1 B	[Command performed successfully but requested icon could not be displayed]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL.	

## TERMINAL RESPONSE: LAUNCH BROWSER 4.1.1 B

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	04
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 4.2A (LAUNCH BROWSER, use the existing browser, icon self explanatory, successful)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 4.2.1	[Browser is in use, the current session is not secured]]
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 4.2.1	[connect to the default URL, "use the existing browser", alpha id. In UCS2]
4	ME → USER	ME displays only the icon	["Self explan."]
5	USER → ME	The user confirms the launch browser.	[user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 4.2.1 A	[Command performed successfully]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL.	

## PROACTIVE COMMAND: LAUNCH BROWSER 4.2.1

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER

Command qualifier: use the existing browser  
 Device identities  
     Source device: UICC  
     Destination device: ME  
     URL: empty  
 Alpha Identifier: "Self explan."  
 Icon identifier:  
     Icon qualifier: self-explanatory  
     Icon identifier: record 1 in EF<sub>(IMG)</sub>

Coding:

BER-TLV:	D0	1D	81	03	01	15	02	82	02	81	82	31
	00	05	0C	53	65	6C	66	20	65	78	70	6C
	61	6E	2E	1E	02	00	01					

TERMINAL RESPONSE: LAUNCH BROWSER 4.2.1 A

Logically:

Command details  
     Command number: 1  
     Command type: LAUNCH BROWSER  
     Command qualifier: use the existing browser  
 Device identities  
     Source device: ME  
     Destination device: UICC  
 Result  
     General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 4.2B (LAUNCH BROWSER, use the existing browser, icon self explanatory, requested icon could not be displayed)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 4.2.1	[Browser is in use, the current session is not secured]
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 4.2.1	[connect to the default URL, "use the existing browser", alpha id. In UCS2]
4	ME → USER	ME displays only the alpha identifier	["Self explan."]
5	USER → ME	The user confirms the launch browser.	[user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 4.2.1 B	[Command performed successfully] [Command performed successfully but requested icon could not be displayed]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL.	

TERMINAL RESPONSE: LAUNCH BROWSER 4.2.1 B

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully but requested icon could not be displayed

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	04
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.26.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.1A to 4.2B.

27.22.4.26.5 LAUNCH BROWSER (support of Text Attribute)

27.22.4.26.5.1 LAUNCH BROWSER (support of Text Attribute – Left Alignment)

27.22.4.26.5.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.5.1.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111[15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

27.22.4.26.5.1.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the left alignment text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.5.1.4 Method of test

27.22.4.26.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

27.22.4.26.5.1.4.2 Procedure

**Expected Sequence 5.1 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Left Alignment)**

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.1.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
4	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with left alignment]
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.1.1	[Command performed successfully]
7	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.1.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.1.2	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
13	ME → USER	ME displays the alpha identifier	[Message shall be formatted without left alignment. Remark: If left alignment is the ME's default alignment as declared in table A.2/18, no alignment change will take place]
14	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
15	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.1.1	[Command performed successfully]
16	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
17	UICC → ME	PROACTIVE UICC SESSION ENDED	
18	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

PROACTIVE COMMAND: LAUNCH BROWSER 5.1.1

Logically:

Command details

- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities

- Source device: UICC
- Destination device: ME
- URL: empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0

Formatting length: 13

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	00	B4		

PROACTIVE COMMAND: LAUNCH BROWSER 5.1.2

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC

Destination device: ME

URL empty

Alpha Identifier "Default URL 2"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32								

TERMINAL RESPONSE: LAUNCH BROWSER 5.1.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.26.5.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.1.

27.22.4.26.5.2 LAUNCH BROWSER (support of Text Attribute – Center Alignment)

27.22.4.26.5.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.5.2.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

## 27.22.4.26.5.2.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the center alignment text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.26.5.2.4 Method of test

## 27.22.4.26.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

## 27.22.4.26.5.2.4.2 Procedure

### Expected Sequence 5.2 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.2.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
4	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with center alignment]
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.2.1	[Command performed successfully]
7	ME→USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

10	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.2.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.2.2	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
13	ME → USER	ME displays the alpha identifier	[Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/18, no alignment change will take place]
14	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
15	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.2.1	[Command performed successfully]
16	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
17	UICC → ME	PROACTIVE UICC SESSION ENDED	
18	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

PROACTIVE COMMAND: LAUNCH BROWSER 5.2.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	01	B4		

PROACTIVE COMMAND: LAUNCH BROWSER 5.2.2

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 2"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32								

TERMINAL RESPONSE: LAUNCH BROWSER 5.2.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.26.5.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.2.

#### 27.22.4.26.5.3 LAUNCH BROWSER (support of Text Attribute – Right Alignment)

##### 27.22.4.26.5.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.26.5.3.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

##### 27.22.4.26.5.3.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the right alignment text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.26.5.3.4 Method of test

###### 27.22.4.26.5.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

#### 27.22.4.26.5.3.4.2 Procedure

### Expected Sequence 5.3 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.3.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
4	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with right alignment]
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.3.1	[Command performed successfully]
7	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.3.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.3.2	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
13	ME → USER	ME displays the alpha identifier	[Message shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/18, no alignment change will take place]
14	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
15	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.3.1	[Command performed successfully]
16	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
17	UICC → ME	PROACTIVE UICC SESSION ENDED	
18	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

PROACTIVE COMMAND: LAUNCH BROWSER 5.3.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched  
 Device identities  
     Source device: UICC  
     Destination device: ME  
     URL: empty  
 Alpha Identifier "Default URL 1"  
 Text Attribute  
     Formatting position: 0  
     Formatting length: 13  
     Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	02	B4		

PROACTIVE COMMAND: LAUNCH BROWSER 5.3.2

Logically:

Command details  
     Command number: 1  
     Command type: LAUNCH BROWSER  
     Command qualifier: launch browser, if not already launched  
 Device identities  
     Source device: UICC  
     Destination device: ME  
     URL: empty  
 Alpha Identifier "Default URL 2"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32								

TERMINAL RESPONSE: LAUNCH BROWSER 5.3.1

Logically:

Command details  
     Command number: 1  
     Command type: LAUNCH BROWSER  
     Command qualifier: launch browser, if not already launched  
 Device identities  
     Source device: ME  
     Destination device: UICC  
 Result  
     General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.26.5.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.3.

## 27.22.4.26.5.4 LAUNCH BROWSER (support of Text Attribute – Large Font Size)

## 27.22.4.26.5.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.5.4.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.124 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

## 27.22.4.26.5.4.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the large font size text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.26.5.4.4 Method of test

## 27.22.4.26.5.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

## 27.22.4.26.5.4.4.2 Procedure

### Expected Sequence 5.4 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Large Font Size)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.4.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
4	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with large font size]
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1	[Command performed successfully]
7	ME→USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	

9	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation.	
10	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.4.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.4.2	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
13	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with normal font size]
14	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
15	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1	[Command performed successfully]
16	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
17	UICC → ME	PROACTIVE UICC SESSION ENDED	
18	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
19	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.4.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.4.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
22	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with large font size]
23	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
24	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1	[Command performed successfully]
25	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
26	UICC → ME	PROACTIVE UICC SESSION ENDED	
27	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
28	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.4.3	
29	ME → UICC	FETCH	
30	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.4.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
31	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with normal font size]
32	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
33	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1	[Command performed successfully]
34	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
35	UICC → ME	PROACTIVE UICC SESSION ENDED	

36	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
----	-----------	---	--

## PROACTIVE COMMAND: LAUNCH BROWSER 5.4.1

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 1"

## Text Attribute

Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	04	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.4.2

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 2"

## Text Attribute

Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.4.3

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier: "Default URL 3"

## Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

## TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1

## Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.26.5.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.4.

## 27.22.4.26.5.5 LAUNCH BROWSER (support of Text Attribute – Small Font Size)

## 27.22.4.26.5.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.5.5.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

## 27.22.4.26.5.5.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the small font size text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.26.5.5.4 Method of test

## 27.22.4.26.5.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

## 27.22.4.26.5.5.4.2 Procedure

### Expected Sequence 5.5 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Small Font Size)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.5.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
4	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with small font size]
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1	[Command performed successfully]
7	ME→USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.5.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.5.2	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
13	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with normal font size]
14	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
15	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1	[Command performed successfully]
16	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
17	UICC → ME	PROACTIVE UICC SESSION ENDED	

18	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation.	
19	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.5.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.5.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
22	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with small font size]
23	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
24	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1	[Command performed successfully]
25	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
26	UICC → ME	PROACTIVE UICC SESSION ENDED	
27	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation.	
28	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.5.3	
29	ME → UICC	FETCH	
30	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.5.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
31	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with normal font size]
32	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
33	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1	[Command performed successfully]
34	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
35	UICC → ME	PROACTIVE UICC SESSION ENDED	
36	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

### PROACTIVE COMMAND: LAUNCH BROWSER 5.5.1

Logically:

#### Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

#### Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 1"

#### Text Attribute

Formatting position: 0  
 Formatting length: 13

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,  
Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	08	B4		

#### PROACTIVE COMMAND: LAUNCH BROWSER 5.5.2

Logically:

Command details

Command number: 1  
Command type: LAUNCH BROWSER  
Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
Destination device: ME  
URL empty

Alpha Identifier "Default URL 2"

Text Attribute

Formatting position: 0  
Formatting length: 13  
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

#### PROACTIVE COMMAND: LAUNCH BROWSER 5.5.3

Logically:

Command details

Command number: 1  
Command type: LAUNCH BROWSER  
Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
Destination device: ME  
URL empty

Alpha Identifier "Default URL 3"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

#### TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1

Logically:

Command details

Command number: 1

Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.26.5.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.5.

#### 27.22.4.26.5.6 LAUNCH BROWSER (support of Text Attribute – Bold on)

##### 27.22.4.26.5.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.26.5.6.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

##### 27.22.4.26.5.6.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the bold text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.26.5.6.4 Method of test

###### 27.22.4.26.5.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

## 27.22.4.26.5.6.4.2 Procedure

**Expected Sequence 5.6 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Bold On)**

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.6.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
4	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with bold on]
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1	[Command performed successfully]
7	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.6.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.6.2	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
13	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with bold off]
14	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
15	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1	[Command performed successfully]
16	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
17	UICC → ME	PROACTIVE UICC SESSION ENDED	
18	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
19	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.6.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.6.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
22	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with bold on]
23	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
24	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1	[Command performed successfully]
25	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
26	UICC → ME	PROACTIVE UICC SESSION ENDED	

27	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation.	
28	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.6.3	
29	ME → UICC	FETCH	
30	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.6.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
31	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with bold off]
32	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
33	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1	[Command performed successfully]
34	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
35	UICC → ME	PROACTIVE UICC SESSION ENDED	
36	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

PROACTIVE COMMAND: LAUNCH BROWSER 5.6.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	10	B4		

PROACTIVE COMMAND: LAUNCH BROWSER 5.6.2

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME

URL empty  
 Alpha Identifier "Default URL 2"  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

PROACTIVE COMMAND: LAUNCH BROWSER 5.6.3

Logically:

Command details  
 Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched  
 Device identities  
 Source device: UICC  
 Destination device: ME  
 URL empty  
 Alpha Identifier "Default URL 3"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1

Logically:

Command details  
 Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.26.5.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.6.

## 27.22.4.26.5.7 LAUNCH BROWSER (support of Text Attribute – Italic On)

## 27.22.4.26.5.7.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.5.7.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

## 27.22.4.26.5.7.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the italic text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.26.5.7.4 Method of test

## 27.22.4.26.5.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

## 27.22.4.26.5.7.4.2 Procedure

### Expected Sequence 5.7 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.7.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.7.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
4	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with italic on]
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1	[Command performed successfully]
7	ME→USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	

9	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.7.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.7.2	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
13	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with italic off]
14	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
15	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1	[Command performed successfully]
16	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
17	UICC → ME	PROACTIVE UICC SESSION ENDED	
18	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
19	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.7.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.7.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
22	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with italic on]
23	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
24	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1	[Command performed successfully]
25	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
26	UICC → ME	PROACTIVE UICC SESSION ENDED	
27	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
28	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.7.3	
29	ME → UICC	FETCH	
30	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.7.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
31	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with italic off]
32	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
33	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1	[Command performed successfully]
34	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
35	UICC → ME	PROACTIVE UICC SESSION ENDED	
36	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

## PROACTIVE COMMAND: LAUNCH BROWSER 5.7.1

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 1"

## Text Attribute

Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	20	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.7.2

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 2"

## Text Attribute

Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.7.3

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty  
 Alpha Identifier: "Default URL 3"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.26.5.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.7.

#### 27.22.4.26.5.8 LAUNCH BROWSER (support of Text Attribute – Underline On)

##### 27.22.4.26.5.8.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.26.5.8.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

##### 27.22.4.26.5.8.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the underline text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.26.5.8.4 Method of test

###### 27.22.4.26.5.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

#### 27.22.4.26.5.8.4.2 Procedure

### Expected Sequence 5.8 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Underline On)

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.8.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.8.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
4	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with underline on]
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1	[Command performed successfully]
7	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.8.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.8.2	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
13	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with underline off]
14	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
15	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1	[Command performed successfully]
16	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
17	UICC → ME	PROACTIVE UICC SESSION ENDED	
18	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
19	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.8.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.8.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
22	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with underline on]

23	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
24	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1	[Command performed successfully]
25	ME USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
26	UICC → ME	PROACTIVE UICC SESSION ENDED	
27	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation.	
28	UICC → ME	The ME returns in idle mode. PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.8.3	
29	ME → UICC	FETCH	
30	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.8.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
31	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with underline off]
32	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
33	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1	[Command performed successfully]
34	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
35	UICC → ME	PROACTIVE UICC SESSION ENDED	
36	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	

PROACTIVE COMMAND: LAUNCH BROWSER 5.8.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	40	B4		

PROACTIVE COMMAND: LAUNCH BROWSER 5.8.2

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: UICC  
 Destination device: ME  
 URL empty

Alpha Identifier "Default URL 2"

## Text Attribute

Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.8.3

## Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: UICC  
 Destination device: ME  
 URL empty

Alpha Identifier "Default URL 3"

## Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

## TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1

## Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.26.5.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.8.

## 27.22.4.26.5.9 LAUNCH BROWSER (support of Text Attribute – Strikethrough On)

## 27.22.4.26.5.9.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.5.9.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

## 27.22.4.26.5.9.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the strikethrough text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.26.5.9.4 Method of test

## 27.22.4.26.5.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

## 27.22.4.26.5.9.4.2 Procedure

**Expected Sequence 5.9 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Strikethrough On)**

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.9.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.9.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
4	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with strikethrough on]
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1	[Command performed successfully]

7	ME→USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation.	
10	UICC → ME	The ME returns in idle mode. PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.9.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.9.2	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
13	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with strikethrough off]
14	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
15	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1	[Command performed successfully]
16	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
17	UICC → ME	PROACTIVE UICC SESSION ENDED	
18	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation.	
19	UICC → ME	The ME returns in idle mode. PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.9.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.9.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
22	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with strikethrough on]
23	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
24	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1	[Command performed successfully]
25	ME USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
26	UICC → ME	PROACTIVE UICC SESSION ENDED	
27	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation.	
28	UICC → ME	The ME returns in idle mode. PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.9.3	
29	ME → UICC	FETCH	
30	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.9.3	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
31	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with strikethrough off]
32	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
33	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1	[Command performed successfully]

34	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL. PROACTIVE UICC SESSION ENDED
35	UICC → ME	
36	USER → ME	

PROACTIVE COMMAND: LAUNCH BROWSER 5.9.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	80	B4		

PROACTIVE COMMAND: LAUNCH BROWSER 5.9.2

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 2"

Text Attribute

Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32	D0	04	00	0D	00	B4		

## PROACTIVE COMMAND: LAUNCH BROWSER 5.9.3

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier: "Default URL 3"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	33								

## TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1

Logically:

## Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.26.5.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.9.

## 27.22.4.26.5.10 LAUNCH BROWSER (support of Text Attribute – Foreground and Background Colour)

## 27.22.4.26.5.10.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.5.10.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

## 27.22.4.26.5.10.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the foreground and background colour text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.26.5.10.4 Method of test

## 27.22.4.26.5.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

## 27.22.4.26.5.10.4.2 Procedure

**Expected Sequence 5.10 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Foreground and Background Colour)**

Step	Direction	MESSAGE / Action	Comments
0	ME		[the ME is in idle mode]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.10.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.10.1	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
4	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with foreground and background colour according to the text attribute configuration]
5	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.10.1	[Command performed successfully]
7	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.	
10	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.10.2	
11	ME → UICC	FETCH	
12	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 5.10.2	[connect to the default URL, "launch browser, if not already launched", no null alpha id]
13	ME → USER	ME displays the alpha identifier	[alpha identifier is displayed with ME's default foreground and background colour]
14	USER → ME	The user may have to confirm the launch browser.	[option: user confirmation]
15	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 5.10.1	[Command performed successfully]
16	ME → USS	The ME attempts to launch the session with the default Wap parameters and the default URL.	

17	UICC → ME	PROACTIVE UICC SESSION ENDED
18	USER → ME	The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode.

PROACTIVE COMMAND: LAUNCH BROWSER 5.10.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 1"

Text Attribute

Formatting position: 0  
 Formatting length: 13  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	20	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	31	D0	04	00	0D	00	B4		

PROACTIVE COMMAND: LAUNCH BROWSER 5.10.2

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier "Default URL 2"

Coding:

BER-TLV:	D0	1A	81	03	01	15	00	82	02	81	82	31
	00	05	0D	44	65	66	61	75	6C	74	20	55
	52	4C	20	32								

TERMINAL RESPONSE: LAUNCH BROWSER 5.10.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: launch browser, if not already launched

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	15	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.26.5.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.10.

## 27.22.4.26.6 LAUNCH BROWSER (UCS2 Display in Chinese)

## 27.22.4.26.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.26.6.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in:

- ISO/IEC 10646 [17].

## 27.22.4.26.6.3 Test purpose

To verify that the ME performs a proper user confirmation with an USC2 alpha identifier, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.26.6.4 Method of test

## 27.22.4.26.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The mobile is busy in a Wap session, the user navigates in pages different from the URL defined by default in Wap parameters.

27.22.4.26.6.4.2 Procedure

**Expected Sequence 6.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL, UCS2 in Chinese)**

Step	Direction	MESSAGE / Action	Comments
0	ME	The user is navigating in a Wap session (not default URL).	[Browser is in use, the current session is not secured]]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 6.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 6.1.1	[connect to the default URL, "use the existing browser", alpha id. In UCS2]
4	ME → USER	ME displays the alpha identifier "你好"	["Hello" in Chinese]
5	USER → ME	The user confirms the launch browser.	[user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 6.1.1	[Command performed successfully]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL.	

PROACTIVE COMMAND: LAUNCH BROWSER 6.1.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier

Data coding scheme: UCS2 (16 bits)  
 Text: "你好"

Coding:

BER-TLV:	D0	12	81	03	01	15	02	82	02	81	82	31
	00	05	05	80	4F	60	59	7D				

TERMINAL RESPONSE: LAUNCH BROWSER 6.1.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.26.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

27.22.4.26.7 LAUNCH BROWSER (UCS2 Display in Katakana)

27.22.4.26.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.26.7.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in:

- ISO/IEC 10646 [17].

27.22.4.26.7.3 Test purpose

To verify that the ME performs a proper user confirmation with an USC2 alpha identifier, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.26.7.4 Method of test

27.22.4.26.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL ...) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The mobile is busy in a Wap session, the user navigates in pages different from the URL defined by default in Wap parameters.

27.22.4.26.7.4.2 Procedure

**Expected Sequence 7.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL, UCS2 in Katakana)**

Step	Direction	MESSAGE / Action	Comments
------	-----------	------------------	----------

0	ME	The user is navigating in a Wap session (not default URL).	[Browser is in use, the current session is not secured]]
1	UICC → ME	PROACTIVE COMMAND PENDING: LAUNCH BROWSER 7.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: LAUNCH BROWSER 7.1.1	[connect to the default URL, "use the existing browser", alpha id. In UCS2]
4	ME → USER	ME displays the alpha identifier "ル"	["Test" in Katakana]
5	USER → ME	The user confirms the launch browser.	[user confirmation]
6	ME → UICC	TERMINAL RESPONSE: LAUNCH BROWSER 7.1.1	[Command performed successfully]
7	ME→USS	The ME does not close the existing session and attempts to connect the default URL.	
8	UICC → ME	PROACTIVE UICC SESSION ENDED	
9	USER → ME	The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL.	

PROACTIVE COMMAND: LAUNCH BROWSER 7.1.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

Device identities

Source device: UICC  
 Destination device: ME  
 URL: empty

Alpha Identifier

Data coding scheme: UCS2 (16 bits)  
 Text: "ル"

Coding:

BER-TLV:	D0	10	81	03	01	15	02	82	02	81	82	31
	00	05	03	80	30	EB						

TERMINAL RESPONSE: LAUNCH BROWSER 7.1.1

Logically:

Command details

Command number: 1  
 Command type: LAUNCH BROWSER  
 Command qualifier: use the existing browser

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	15	02	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.26.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

## 27.22.4.27 OPEN CHANNEL

## 27.22.4.27.1 Void

## 27.22.4.27.2 Open Channel (related to GPRS)

## 27.22.4.27.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.27.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111[15] clause 5.2, clauses 6.4.27 and 6.6.27, clause 8.6, clause 8.7, clause 9.2, clause 8.2, clause 8.15, clause 8.31 and clause 8.70..

## 27.22.4.27.2.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (OK); or
- TERMINAL RESPONSE (Command performed with modification); or
- TERMINAL RESPONSE (User did not accept the proactive command);
- TERMINAL RESPONSE (ME currently unable to process command);

to the UICC after the ME receives the OPEN CHANNEL proactive command. The TERMINAL RESPONSE sent back to the UICC is the result of the ME and the network capabilities against requested parameters by the UICC.

## 27.22.4.27.2.4 Method of test

## 27.22.4.27.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context for test cases using packet services:

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME's default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP ContextDch, as specified in TS 34.123-3 [27], clause 8.10 for test cases using packet services:

## Bearer Parameters

Precedence Class:	03
Delay Class:	04
Reliability Class:	03
Peak throughput class:	04
Mean throughput class:	31
Packet data protocol:	02 (IP)

## GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd  
 UICC/ME interface transport level  
  
 Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

Prior to test case execution the apparatus supplier shall have provided the "Preferred buffer size supported by the terminal for Open Channel command" as requested in table A.2/29.

Pre-condition for successful execution of expected sequence 2.1:

If the terminal does not support the execution of an Open Channel (GPRS) command when no Network Access Name TLV is present in the proactive command and when no default Access Point Name is set in the terminal configuration (s.a. table A.1/48), then "TestGp.rs" shall be set and activated as default Access Point Name in the terminal configuration prior to execution of the proactive command in expected sequence 2.1.

#### 27.22.4.27.2.4.2 Procedure

#### Expected Sequence 2.1 (OPEN CHANNEL, immediate link establishment, GPRS, no local address, no alpha identifier, no network access name)

Step	Direction	MESSAGE / Action	Comments
1	USER → ME	Set and activate APN "TestGp.rs" in the terminal configuration if required	[see initial conditions]
2	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.1.1	
3	ME → UICC	FETCH	
4	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 2.1.1	
5	ME → user	The ME may display channel opening information	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 2.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 2.1.1B	[Command performed successfully]

#### PROACTIVE COMMAND: OPEN CHANNEL 2.1.1

Logically:

##### Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

##### Device identities

Source device: UICC  
 Destination device: ME

##### Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)  
 UICC/ME interface transport level  
 Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

## Coding:

BER-TLV:	D0	36	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	05	78
	0D	08	F4	55	73	65	72	4C	6F	67	0D	08
	F4	55	73	65	72	50	77	64	3C	03	01	AD
	9C	3E	05	21	01	01	01	01				

## TERMINAL RESPONSE: OPEN CHANNEL 2.1.1A

## Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel status: Channel identifier 1 and link established or PDP context activated

## Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

## TERMINAL RESPONSE: OPEN CHANNEL 2.1.1B

## Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS

Bearer parameter:

Precedence Class: 00

Delay Class: 04

Reliability Class: 03

Peak throughput class: 04

Mean throughput class: 31

Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

**Expected Sequence 2.2 (OPEN CHANNEL, immediate link establishment GPRS, no alpha identifier, with network access name)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 2.2.1	
4	ME → user	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 2.2.1A or TERMINAL RESPONSE: OPEN CHANNEL 2.2.1B	[Command performed successfully]

**PROACTIVE COMMAND: OPEN CHANNEL 2.2.1**

Logically:

Command details

Command number: 1

Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities

Source device: UICC

Destination device: ME

Bearer

Bearer type: GPRS

Bearer parameter:

Precedence Class: 03

Delay Class: 04

Reliability Class: 03

Peak throughput class: 04

Mean throughput class: 31

Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP

Port number: 44444  
Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	42	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	05	78
	47	0A	06	54	65	73	74	47	70	02	72	73
	0D	08	F4	55	73	65	72	4C	6F	67	0D	08
	F4	55	73	65	72	50	77	64	3C	03	01	AD
	9C	3E	05	21	01	01	01	01				

TERMINAL RESPONSE: OPEN CHANNEL 2.2.1A

Logically:

Command details

Command number: 1  
Command type: OPEN CHANNEL  
Command qualifier: immediate link establishment  
Device identities  
Source device: ME  
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer Description:

Bearer Type: GPRS  
Bearer parameter:  
Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

Buffer

Buffer size 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 2.2.1B

Logically:

Command details

Command number: 1  
Command type: OPEN CHANNEL  
Command qualifier: immediate link establishment  
Device identities  
Source device: ME  
Destination device: UICC

Result

General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer Description:

Bearer Type: GPRS  
Bearer parameter:  
Precedence Class: 00

Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size 1400

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

**Expected Sequence 2.3 (OPEN CHANNEL, immediate link establishment, GPRS, with alpha identifier)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 2.3.1	
4	ME → user	Confirmation phase with alpha ID	'Open ID'
5	user → ME	The user confirms	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 2.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 2.1.1B	[Command performed successfully]

## PROACTIVE COMMAND: OPEN CHANNEL 2.3.1

## Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier Open ID

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

## Coding:

BER-TLV:	D0	4B	81	03	01	40	01	82	02	81	82	05
	07	4F	70	65	6E	20	49	44	35	07	02	03
	04	03	04	1F	02	39	02	05	78	47	0A	06
	54	65	73	74	47	70	02	72	73	0D	08	F4
	55	73	65	72	4C	6F	67	0D	08	F4	55	73
	65	72	50	77	64	3C	03	01	AD	9C	3E	05
	21	01	01	01	01							

**Expected Sequence 2.4 (OPEN CHANNEL, immediate link establishment, GPRS, with null alpha identifier)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 2.4.1	
4	ME → user	Confirmation phase	[The ME should not give any information]
5	user → ME	The user confirms	[Only if the ME asks for user confirmation]
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 2.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 2.1.1B	[Command performed successfully]

**PROACTIVE COMMAND: OPEN CHANNEL 2.4.1**

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Alpha Identifier Null

Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400  
 Network access name: . TestGprs

Other Address

Length: 00

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	46	81	03	01	40	01	82	02	81	82	05
	00	35	07	02	03	04	03	04	1F	02	39	02
	05	78	47	0A	06	54	65	73	74	47	70	02
	6F	67	3E	00	0D	08	F4	55	73	65	72	4C
	6F	67	0D	08	F4	55	73	65	72	50	77	64
	3C	03	01	AD	9C	3E	05	21	01	01	01	01

**Expected Sequence 2.5 (OPEN CHANNEL, immediate link establishment, GPRS, command performed with modifications (buffer size) )**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 2.5.1	
4	ME → user	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 2.5.1A or TERMINAL RESPONSE: OPEN CHANNEL 2.5.1B	[Command performed with modification]

**PROACTIVE COMMAND: OPEN CHANNEL 2.5.1**

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 65535  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)  
 UICC/ME interface transport level  
 Transport format: UDP  
 Port number: 44444  
 Data destination address: 01.01.01.01

Coding:

BER-TLV:	D0	42	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	FF	FF

47	0A	06	54	65	73	74	47	70	02	72	73
0D	08	F4	55	73	65	72	4C	6F	67	0D	08
F4	55	73	65	72	50	77	64	3C	03	01	AD
9C	3E	05	21	01	01	01	01				

## TERMINAL RESPONSE: OPEN CHANNEL 2.5.1A

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed with modifications (07)

## Channel status

Channel identifier 1 and link established or PDP context activated

## Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: The buffer size TLV shall be attached and contain the value stated in table A.2/aa "Preferred buffer size supported by the terminal for Open Channel command".

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	07
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	Note 1										

Note1: The buffer size TLV shall be attached and contain the value stated in table A.2/29 "Preferred buffer size supported by the terminal for Open Channel command".

## TERMINAL RESPONSE: OPEN CHANNEL 2.5.1B

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed with modifications (07)

## Channel status

Channel identifier 1 and link established or PDP context activated

## Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04

Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: The buffer size TLV shall be attached and contain the value stated in table A.2/29 "Preferred buffer size supported by the terminal for Open Channel command".

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	07
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	Note 1										

Note1: The buffer size TLV shall be attached and contain the value stated in table A.2/29 "Preferred buffer size supported by the terminal for Open Channel command".

**Expected Sequence 2.6 Void****Expected Sequence 2.7 (OPEN CHANNEL, immediate link establishment, GPRS, open command with alpha identifier, User did not accept the proactive command)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.7.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 2.7.1	
4	ME → user	Confirmation phase with alpha ID	[The ME shall display 'Open ID']
5	user → ME	The user rejects	
6	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 2.7.1A or TERMINAL RESPONSE: OPEN CHANNEL 2.7.1B	[User did not accept the proactive command]

## PROACTIVE COMMAND: OPEN CHANNEL 2.7.1

## Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID"

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400

Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)

UICC/ME interface transport level  
 Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4B	81	03	01	40	01	82	02	81	82	05
	07	4F	70	65	6E	20	49	44	35	07	02	03
	04	03	04	1F	02	39	02	05	78	47	0A	06
	54	65	73	74	47	70	02	72	73	0D	08	F4
	55	73	65	72	4C	6F	67	0D	08	F4	55	73
	65	72	50	77	64	3C	03	01	AD	9C	3E	05
	21	01	01	01	01							

TERMINAL RESPONSE: OPEN CHANNEL 2.7.1A

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: User did not accept the proactive command

Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: Because the value depends in this case on the terminal's implementation, it shall be ignored.

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	22
	35	07	02	03	04	03	04	1F	02	Note 1		

Note1: The buffer size TLV shall be present and because the value depends in this case on the terminal's implementation, the value shall be ignored.

TERMINAL RESPONSE: OPEN CHANNEL 2.7.1B

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: User did not accept the proactive command

## Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: Because the value depends in this case on the terminal's implementation, it shall be ignored.

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	22
	35	07	02	00	04	03	04	1F	02	Note 1		

Note1: The buffer size TLV shall be present and because the value depends in this case on the terminal's implementation, the value shall be ignored.

**Expected Sequence 2.8 Void**

## 27.22.4.27.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.8.

## 27.22.4.27.3 Open Channel (default bearer)

TBD

## 27.22.4.27.4 Open Channel (Local Bearer)

TBD

## 27.22.4.27.5 Open Channel (GPRS, support of Text Attribute)

## 27.22.4.27.5.1 Open Channel (GPRS, support of Text Attribute – Left Alignment)

## 27.22.4.27.5.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.27.5.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

## 27.22.4.27.5.1.3 Test purpose

To verify that the ME displays an alpha identifier according to the left alignment text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

## 27.22.4.27.5.1.4 Method of test

## 27.22.4.27.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class:	03
Delay Class:	04
Reliability Class:	03
Peak throughput class:	04
Mean throughput class:	31
Packet data protocol:	02 (IP)

#### GPRS Parameters

Network access name:	TestGp.rs
User login:	UserLog
User password:	UserPwd

#### UICC/ME interface transport level

Transport format:	UDP
Port number:	44444
Data destination address	01.01.01.01

## 27.22.4.27.5.1.4.2 Procedure

**Expected Sequence 5.1 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Left Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.1.1	
4	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with left alignment]
5	USER → ME	The user confirms	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 5.1.1B	[Command performed successfully]
9	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	ME → USS	PDP context deactivation request	
13	USS → ME	PDP context deactivation accept	
14	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.1.2	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.1.2	
18	ME → USER	Confirmation phase with alpha ID	[Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/19, no alignment change will take place]
19	USER → ME	The user confirms	
20	ME → USS	PDP context activation request	
21	USS → ME	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 5.1.1B	[Command performed successfully]
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	ME → USS	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

## PROACTIVE COMMAND: OPEN CHANNEL 5.1.1

Logically:

## Command details

Command number: 1  
Command type: OPEN CHANNEL  
Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME  
 Alpha Identifier "Open ID 1"  
 Bearer  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)  
 UICC/ME interface transport level  
 Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	00
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.1.2

## Logically:

Command details  
 Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment  
 Device identities  
 Source device: UICC  
 Destination device: ME  
 Alpha Identifier "Open ID 2"  
 Bearer  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)  
 UICC/ME interface transport level  
   Transport format: UDP  
   Port number: 44444  
 Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1

Logically:

Command details  
   Command number: 1  
   Command type: CLOSE CHANNEL  
   Command qualifier: RFU  
 Device identities  
   Source device: UICC  
   Destination device: Channel  
 Alpha Identifier "Close ID"

Coding:

BER-TLV:	D0	14	81	03	01	41	00	82	02	81	21
	85	08	43	6C	6F	73	65	20	49	44	

TERMINAL RESPONSE: OPEN CHANNEL 5.1.1A

Logically:

Command details  
   Command number: 1  
   Command type: OPEN CHANNEL  
   Command qualifier: immediate link establishment  
 Device identities  
   Source device: ME  
   Destination device: UICC  
 Result  
 General Result: Command performed successfully  
   Channel status: Channel identifier 1 and link established or PDP context activated  
 Bearer description  
   Bearer type: GPRS  
   Bearer parameter:  
   Precedence Class: 03  
   Delay Class: 04  
   Reliability Class: 03  
   Peak throughput class: 04  
   Mean throughput class: 31  
   Packet data protocol: 02 (IP)  
 Buffer  
   Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.1.1B

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel status: Channel identifier 1 and link established or PDP context activated

## Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: CLOSE CHANNEL 5.1.1

Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.27.5.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.1.

27.22.4.27.5.2 Open Channel (GPRS, support of Text Attribute – Center Alignment)

27.22.4.27.5.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

27.22.4.27.5.2.3 Test purpose

To verify that the ME displays an alpha identifier according to the center alignment text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.2.4 Method of test

27.22.4.27.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class:	03
Delay Class:	04
Reliability Class:	03
Peak throughput class:	04
Mean throughput class:	31
Packet data protocol:	02 (IP)

GPRS Parameters

Network access name:	TestGp.rs
User login:	UserLog
User password:	UserPwd

UICC/ME interface transport level

Transport format:	UDP
Port number:	44444
Data destination address	01.01.01.01

## 27.22.4.27.5.2.4.2 Procedure

**Expected Sequence 5.2 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Center Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.2.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.2.1	
4	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with center alignment]
5	USER → ME	The user confirms	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.2.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.2.1B	[Command performed successfully]
9	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	ME → USS	PDP context deactivation request	
13	USS → ME	PDP context deactivation accept	
14	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.2.2	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.2.2	
18	ME → USER	Confirmation phase with alpha ID	[Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/19, no alignment change will take place]
19	USER → ME	The user confirms	
20	ME → USS	PDP context activation request	
21	USS → ME	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.2.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.2.1B	[Command performed successfully]
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	ME → USS	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

## PROACTIVE COMMAND: OPEN CHANNEL 5.2.1

Logically:

## Command details

Command number: 1  
Command type: OPEN CHANNEL  
Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME  
 Alpha Identifier "Open ID 1"  
 Bearer  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)  
 UICC/ME interface transport level  
 Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	01
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.2.2

## Logically:

Command details  
 Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment  
 Device identities  
 Source device: UICC  
 Destination device: ME  
 Alpha Identifier "Open ID 2"  
 Bearer  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)  
 UICC/ME interface transport level  
   Transport format: UDP  
   Port number: 44444  
 Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

TERMINAL RESPONSE: OPEN CHANNEL 5.2.1A

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.2.1B

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

#### 27.22.4.27.5.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.2.

#### 27.22.4.27.5.3 Open Channel (GPRS, support of Text Attribute – Right Alignment)

##### 27.22.4.27.5.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.27.5.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.27.5.3.3 Test purpose

To verify that the ME displays an alpha identifier according to the right alignment text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.27.5.3.4 Method of test

###### 27.22.4.27.5.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31

Packet data protocol: 02 (IP)  
GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.27.5.3.4.2 Procedure

**Expected Sequence 5.3 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Right Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.3.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.3.1	
4	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with right alignment]
5	USER → ME	The user confirms	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.3.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.3.1B	[Command performed successfully]
9	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	ME → USS	PDP context deactivation request	
13	USS → ME	PDP context deactivation accept	
14	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.3.2	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.3.2	
18	ME → USER	Confirmation phase with alpha ID	[Message shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/19, no alignment change will take place]
19	USER → ME	The user confirms	
20	ME → USS	PDP context activation request	
21	USS → ME	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.3.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.3.1B	[Command performed successfully]
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	ME → USS	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

PROACTIVE COMMAND: OPEN CHANNEL 5.3.1

Logically:

Command details

Command number: 1  
Command type: OPEN CHANNEL  
Command qualifier: immediate link establishment

Device identities

Source device: UICC  
 Destination device: ME  
 Alpha Identifier "Open ID 1"  
 Bearer  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)  
 UICC/ME interface transport level  
 Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	02
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.3.2

## Logically:

Command details  
 Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment  
 Device identities  
 Source device: UICC  
 Destination device: ME  
 Alpha Identifier "Open ID 2"  
 Bearer  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)  
 UICC/ME interface transport level  
   Transport format: UDP  
   Port number: 44444  
 Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

TERMINAL RESPONSE: OPEN CHANNEL 5.3.1A

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.3.1B

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

#### 27.22.4.27.5.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.3.

#### 27.22.4.27.5.4 Open Channel (GPRS, support of Text Attribute – Large Font Size)

##### 27.22.4.27.5.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.27.5.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.27.5.4.3 Test purpose

To verify that the ME displays an alpha identifier according to the large font size text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.27.5.4.4 Method of test

###### 27.22.4.27.5.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31

Packet data protocol: 02 (IP)  
GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.27.5.4.4.2 Procedure

**Expected Sequence 5.4 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Large Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.4.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.4.1	
4	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with large font size]
5	USER → ME	The user confirms	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.4.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.4.1B	[Command performed successfully]
9	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	ME → USS	PDP context deactivation request	
13	USS → ME	PDP context deactivation accept	
14	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.4.2	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.4.2	
18	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with normal font size]
19	USER → ME	The user confirms	
20	ME → USS	PDP context activation request	
21	USS → ME	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.4.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.4.1B	[Command performed successfully]
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	ME → USS	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
29	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.4.1	
30	ME → UICC	FETCH	
31	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.4.1	
32	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with large font size]
33	USER → ME	The user confirms	
34	ME → USS	PDP context activation request	
35	USS → ME	PDP context activation accept	
36	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.4.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.4.1B	[Command performed successfully]

37	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
38	ME → UICC	FETCH	
39	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
40	ME → USS	PDP context deactivation request	
41	USS → ME	PDP context deactivation accept	
42	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
43	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.4.3	
44	ME → UICC	FETCH	
45	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.4.3	
46	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with normal font size]
47	USER → ME	The user confirms	
48	ME → USS	PDP context activation request	
49	USS → ME	PDP context activation accept	
50	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.4.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE : OPEN CHANNEL 5.4.1B	
51	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
52	ME → UICC	FETCH	
53	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
54	ME → USS	PDP context deactivation request	
55	USS → ME	PDP context deactivation accept	
56	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

## PROACTIVE COMMAND: OPEN CHANNEL 5.4.1

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 1"

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	04
	B4											

PROACTIVE COMMAND: OPEN CHANNEL 5.4.2

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	00
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.4.3

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 3"

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

## TERMINAL RESPONSE: OPEN CHANNEL 5.4.1A

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.4.1B

Logically:

Command details  
 Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

#### 27.22.4.27.5.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.4.

#### 27.22.4.27.5.5 Open Channel (GPRS, support of Text Attribute – Small Font Size)

##### 27.22.4.27.5.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.27.5.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.27.5.5.3 Test purpose

To verify that the ME displays an alpha identifier according to the small font size text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.27.5.5.4 Method of test

##### 27.22.4.27.5.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class:	03
Delay Class:	04
Reliability Class:	03
Peak throughput class:	04
Mean throughput class:	31
Packet data protocol:	02 (IP)

#### GPRS Parameters

Network access name:	TestGp.rs
User login:	UserLog
User password:	UserPwd

#### UICC/ME interface transport level

Transport format:	UDP
Port number:	44444
Data destination address	01.01.01.01

## 27.22.4.27.5.5.4.2 Procedure

**Expected Sequence 5.5 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Small Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.5.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.5.1	
4	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with small font size]
5	USER → ME	The user confirms	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.5.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.5.1B	[Command performed successfully]
9	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	ME → USS	PDP context deactivation request	
13	USS → ME	PDP context deactivation accept	
14	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.5.2	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.5.2	
18	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with normal font size]
19	USER → ME	The user confirms	
20	ME → USS	PDP context activation request	
21	USS → ME	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.5.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.5.1B	[Command performed successfully]
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	ME → USS	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
29	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.5.1	
30	ME → UICC	FETCH	
31	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.5.1	
32	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with small font size]
33	USER → ME	The user confirms	
34	ME → USS	PDP context activation request	
35	USS → ME	PDP context activation accept	
36	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.5.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.5.1B	[Command performed successfully]

37	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
38	ME → UICC	FETCH	
39	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
40	ME → USS	PDP context deactivation request	
41	USS → ME	PDP context deactivation accept	
42	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
43	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.5.3	
44	ME → UICC	FETCH	
45	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.5.3	
46	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with normal font size]
47	USER → ME	The user confirms	
48	ME → USS	PDP context activation request	
49	USS → ME	PDP context activation accept	
50	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.5.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.5.1B	[Command performed successfully]
51	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
52	ME → UICC	FETCH	
53	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
54	ME → USS	PDP context deactivation request	
55	USS → ME	PDP context deactivation accept	
46	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

## PROACTIVE COMMAND: OPEN CHANNEL 5.5.1

Logically:

## Command details

Command number: 1  
Command type: OPEN CHANNEL  
Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
Destination device: ME

Alpha Identifier "Open ID 1"

## Bearer

Bearer type: GPRS  
Bearer parameter:  
Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400  
Network access name: TestGp.rs  
Text String: UserLog (User login)  
Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	08
	B4											

PROACTIVE COMMAND: OPEN CHANNEL 5.5.2

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	00
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.5.3

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 3"

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

## TERMINAL RESPONSE: OPEN CHANNEL 5.5.1A

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.5.1B

Logically:

Command details  
 Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

#### 27.22.4.27.5.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.5.

#### 27.22.4.27.5.6 Open Channel (GPRS, support of Text Attribute – Bold On)

#### 27.22.4.27.5.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.27.5.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.27.5.6.3 Test purpose

To verify that the ME displays an alpha identifier according to the bold text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.27.5.6.4 Method of test

##### 27.22.4.27.5.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class:	03
Delay Class:	04
Reliability Class:	03
Peak throughput class:	04
Mean throughput class:	31
Packet data protocol:	02 (IP)

#### GPRS Parameters

Network access name:	TestGp.rs
User login:	UserLog
User password:	UserPwd

#### UICC/ME interface transport level

Transport format:	UDP
Port number:	44444
Data destination address	01.01.01.01

## 27.22.4.27.5.6.4.2 Procedure

**Expected Sequence 5.6 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Bold On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.6.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.6.1	
4	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with bold on]
5	USER → ME	The user confirms	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.6.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.6.1B	[Command performed successfully]
9	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	ME → USS	PDP context deactivation request	
13	USS → ME	PDP context deactivation accept	
14	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.6.2	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.6.2	
18	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with bold off]
19	USER → ME	The user confirms	
20	ME → USS	PDP context activation request	
21	USS → ME	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.6.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.6.1B	[Command performed successfully]
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	ME → USS	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
29	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.6.1	
30	ME → UICC	FETCH	
31	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.6.1	
32	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with bold on]
33	USER → ME	The user confirms	
34	ME → USS	PDP context activation request	
35	USS → ME	PDP context activation accept	
36	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.6.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.6.1B	[Command performed successfully]

37	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
38	ME → UICC	FETCH	
39	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
40	ME → USS	PDP context deactivation request	
41	USS → ME	PDP context deactivation accept	
42	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
43	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.6.3	
44	ME → UICC	FETCH	
45	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.6.3	
46	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with bold off]
47	USER → ME	The user confirms	
48	ME → USS	PDP context activation request	
49	USS → ME	PDP context activation accept	
50	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.6.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.6.1B	[Command performed successfully]
51	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
52	ME → UICC	FETCH	
53	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
54	ME → USS	PDP context deactivation request	
55	USS → ME	PDP context deactivation accept	
56	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

## PROACTIVE COMMAND: OPEN CHANNEL 5.6.1

Logically:

## Command details

Command number: 1  
Command type: OPEN CHANNEL  
Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
Destination device: ME

Alpha Identifier "Open ID 1"

## Bearer

Bearer type: GPRS  
Bearer parameter:  
Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400  
Network access name: TestGp.rs  
Text String: UserLog (User login)  
Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	10
	B4											

PROACTIVE COMMAND: OPEN CHANNEL 5.6.2

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	00
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.6.3

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 3"

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

## TERMINAL RESPONSE: OPEN CHANNEL 5.6.1A

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.6.1B

Logically:

Command details  
 Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

#### 27.22.4.27.5.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.6.

#### 27.22.4.27.5.7 Open Channel (GPRS, support of Text Attribute – Italic On)

##### 27.22.4.27.5.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.27.5.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.27.5.7.3 Test purpose

To verify that the ME displays an alpha identifier according to the italic text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.27.5.7.4 Method of test

##### 27.22.4.27.5.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class:	03
Delay Class:	04
Reliability Class:	03
Peak throughput class:	04
Mean throughput class:	31
Packet data protocol:	02 (IP)

#### GPRS Parameters

Network access name:	TestGp.rs
User login:	UserLog
User password:	UserPwd

#### UICC/ME interface transport level

Transport format:	UDP
Port number:	44444
Data destination address	01.01.01.01

## 27.22.4.27.5.7.4.2 Procedure

**Expected Sequence 5.7 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Italic On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.7.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.7.1	
4	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with italic on]
5	USER → ME	The user confirms	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.7.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.7.1B	[Command performed successfully]
9	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	ME → USS	PDP context deactivation request	
13	USS → ME	PDP context deactivation accept	
14	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.7.2	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.7.2	
18	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with italic off]
19	USER → ME	The user confirms	
20	ME → USS	PDP context activation request	
21	USS → ME	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.7.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.7.1B	[Command performed successfully]
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	ME → USS	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
29	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.7.1	
30	ME → UICC	FETCH	
31	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.7.1	
32	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with italic on]
33	USER → ME	The user confirms	
34	ME → USS	PDP context activation request	
35	USS → ME	PDP context activation accept	
36	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.7.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.7.1B	[Command performed successfully]

37	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
38	ME → UICC	FETCH	
39	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
40	ME → USS	PDP context deactivation request	
41	USS → ME	PDP context deactivation accept	
42	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
43	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.7.3	
44	ME → UICC	FETCH	
45	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.7.3	
46	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with italic off]
47	USER → ME	The user confirms	
48	ME → USS	PDP context activation request	
49	USS → ME	PDP context activation accept	
50	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.7.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE : OPEN CHANNEL 5.7.1B	
51	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
52	ME → UICC	FETCH	
53	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
54	ME → USS	PDP context deactivation request	
55	USS → ME	PDP context deactivation accept	
56	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

## PROACTIVE COMMAND: OPEN CHANNEL 5.7.1

Logically:

## Command details

Command number: 1  
Command type: OPEN CHANNEL  
Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
Destination device: ME

Alpha Identifier "Open ID 1"

## Bearer

Bearer type: GPRS  
Bearer parameter:  
Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400  
Network access name: TestGp.rs  
Text String: UserLog (User login)  
Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	20
	B4											

PROACTIVE COMMAND: OPEN CHANNEL 5.7.2

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	00
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.7.3

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 3"

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

## TERMINAL RESPONSE: OPEN CHANNEL 5.7.1A

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.7.1B

Logically:

Command details  
 Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

#### 27.22.4.27.5.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.7.

#### 27.22.4.27.5.8 Open Channel (GPRS, support of Text Attribute – Underline On)

#### 27.22.4.27.5.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.27.5.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.27.5.8.3 Test purpose

To verify that the ME displays an alpha identifier according to the underline text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.27.5.8.4 Method of test

##### 27.22.4.27.5.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class:	03
Delay Class:	04
Reliability Class:	03
Peak throughput class:	04
Mean throughput class:	31
Packet data protocol:	02 (IP)

#### GPRS Parameters

Network access name:	TestGp.rs
User login:	UserLog
User password:	UserPwd

#### UICC/ME interface transport level

Transport format:	UDP
Port number:	44444
Data destination address	01.01.01.01

## 27.22.4.27.5.8.4.2 Procedure

**Expected Sequence 5.8 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Underline On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.8.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.8.1	
4	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with underline on]
5	USER → ME	The user confirms	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.8.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.8.1B	[Command performed successfully]
9	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	ME → USS	PDP context deactivation request	
13	USS → ME	PDP context deactivation accept	
14	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.8.2	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.8.2	
18	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with underline off]
19	USER → ME	The user confirms	
20	ME → USS	PDP context activation request	
21	USS → ME	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 5.8.1A or TERMINAL RESPONSE: OPEN CHANNEL 5.8.1B	[Command performed successfully]
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	ME → USS	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
29	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.8.1	
30	ME → UICC	FETCH	
31	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.8.1	
32	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with underline on]
33	USER → ME	The user confirms	
34	ME → USS	PDP context activation request	
35	USS → ME	PDP context activation accept	
36	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.8.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.8.1B	[Command performed successfully]

37	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
38	ME → UICC	FETCH	
39	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
40	ME → USS	PDP context deactivation request	
41	USS → ME	PDP context deactivation accept	
42	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
43	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.8.3	
44	ME → UICC	FETCH	
45	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.8.3	
46	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with underline off]
47	USER → ME	The user confirms	
48	ME → USS	PDP context activation request	
49	USS → ME	PDP context activation accept	
50	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.8.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.8.1B	[Command performed successfully]
51	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
52	ME → UICC	FETCH	
53	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
54	ME → USS	PDP context deactivation request	
55	USS → ME	PDP context deactivation accept	
56	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

## PROACTIVE COMMAND: OPEN CHANNEL 5.8.1

Logically:

## Command details

Command number: 1  
Command type: OPEN CHANNEL  
Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
Destination device: ME

Alpha Identifier "Open ID 1"

## Bearer

Bearer type: GPRS  
Bearer parameter:  
Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400  
Network access name: TestGp.rs  
Text String: UserLog (User login)  
Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	40
	B4											

PROACTIVE COMMAND: OPEN CHANNEL 5.8.2

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	00
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.8.3

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 3"

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

## TERMINAL RESPONSE: OPEN CHANNEL 5.8.1A

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.8.1B

Logically:

Command details  
 Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

#### 27.22.4.27.5.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.8.

#### 27.22.4.27.5.9 Open Channel (GPRS, support of Text Attribute – Strikethrough On)

#### 27.22.4.27.5.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.27.5.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.27.5.9.3 Test purpose

To verify that the ME displays an alpha identifier according to the strikethrough text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.27.5.9.4 Method of test

##### 27.22.4.27.5.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class:	03
Delay Class:	04
Reliability Class:	03
Peak throughput class:	04
Mean throughput class:	31
Packet data protocol:	02 (IP)

#### GPRS Parameters

Network access name:	TestGp.rs
User login:	UserLog
User password:	UserPwd

#### UICC/ME interface transport level

Transport format:	UDP
Port number:	44444
Data destination address	01.01.01.01

## 27.22.4.27.5.9.4.2 Procedure

**Expected Sequence 5.9 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Strikethrough On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.9.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.9.1	
4	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with strikethrough on]
5	USER → ME	The user confirms	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.9.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.9.1B	[Command performed successfully]
9	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	ME → USS	PDP context deactivation request	
13	USS → ME	PDP context deactivation accept	
14	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.9.2	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.9.2	
18	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with strikethrough off]
19	USER → ME	The user confirms	
20	ME → USS	PDP context activation request	
21	USS → ME	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.9.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.9.1B	[Command performed successfully]
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	ME → USS	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
29	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.9.1	
30	ME → UICC	FETCH	
31	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.9.1	
32	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with strikethrough on]
33	USER → ME	The user confirms	
34	ME → USS	PDP context activation request	
35	USS → ME	PDP context activation accept	
36	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.9.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.9.1B	[Command performed successfully]

37	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
38	ME → UICC	FETCH	
39	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
40	ME → USS	PDP context deactivation request	
41	USS → ME	PDP context deactivation accept	
42	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
43	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.9.3	
44	ME → UICC	FETCH	
45	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.9.3	
46	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with strikethrough off]
47	USER → ME	The user confirms	
48	ME → USS	PDP context activation request	
49	USS → ME	PDP context activation accept	
50	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.9.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE : OPEN CHANNEL 5.9.1B	
51	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
52	ME → UICC	FETCH	
53	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
54	ME → USS	PDP context deactivation request	
55	USS → ME	PDP context deactivation accept	
56	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

## PROACTIVE COMMAND: OPEN CHANNEL 5.9.1

Logically:

## Command details

Command number: 1  
Command type: OPEN CHANNEL  
Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
Destination device: ME

Alpha Identifier "Open ID 1"

## Bearer

Bearer type: GPRS  
Bearer parameter:  
Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400  
Network access name: TestGp.rs  
Text String: UserLog (User login)  
Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	80
	B4											

PROACTIVE COMMAND: OPEN CHANNEL 5.9.2

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 2"

Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0  
 Formatting length: 9  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	00
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.9.3

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

Alpha Identifier "Open ID 3"

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	33	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

## TERMINAL RESPONSE: OPEN CHANNEL 5.9.1A

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.9.1B

Logically:

Command details  
 Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Channel status Channel identifier 1 and link established or PDP context activated  
 Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)  
 Buffer  
 Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

#### 27.22.4.27.5.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.9.

27.22.4.27.5.10 Open Channel (GPRS, support of Text Attribute – Foreground and Background Colour)

27.22.4.27.5.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

27.22.4.27.5.10.3 Test purpose

To verify that the ME displays an alpha identifier according to the foreground and background colour text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.10.4 Method of test

27.22.4.27.5.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class:	03
Delay Class:	04
Reliability Class:	03
Peak throughput class:	04
Mean throughput class:	31
Packet data protocol:	02 (IP)

#### GPRS Parameters

Network access name:	TestGp.rs
User login:	UserLog
User password:	UserPwd

#### UICC/ME interface transport level

Transport format:	UDP
Port number:	44444
Data destination address	01.01.01.01

## 27.22.4.27.5.10.4.2 Procedure

**Expected Sequence 5.10 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Foreground and Background Colour)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.10.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.10.1	
4	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with foreground and background colour according to the text attribute]
5	USER → ME	The user confirms	
6	ME → USS	PDP context activation request	
7	USS → ME	PDP context activation accept	
8	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.10.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.10.1B	[Command performed successfully]
9	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
10	ME → UICC	FETCH	
11	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
12	ME → USS	PDP context deactivation request	
13	USS → ME	PDP context deactivation accept	
14	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]
15	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.10.2	
16	ME → UICC	FETCH	
17	UICC → ME	PROACTIVE COMMAND : OPEN CHANNEL 5.10.2	
18	ME → USER	Confirmation phase with alpha ID	[alpha identifier is displayed with ME"s default foreground and background colour]
19	USER → ME	The user confirms	
20	ME → USS	PDP context activation request	
21	USS → ME	PDP context activation accept	
22	ME → UICC	TERMINAL RESPONSE : OPEN CHANNEL 5.10.1A or TERMINAL RESPONSE : OPEN CHANNEL 5.10.1B	[Command performed successfully]
23	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1	
26	ME → USS	PDP context deactivation request	
27	USS → ME	PDP context deactivation accept	
28	ME → UICC	TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1	[Command performed successfully]

## PROACTIVE COMMAND: OPEN CHANNEL 5.10.1

Logically:

## Command details

Command number: 1  
Command type: OPEN CHANNEL  
Command qualifier: immediate link establishment

## Device identities

Source device: UICC

Destination device: ME  
 Alpha Identifier "Open ID 1"  
 Bearer  
   Bearer type: GPRS  
   Bearer parameter:  
   Precedence Class: 03  
   Delay Class: 04  
   Reliability Class: 03  
   Peak throughput class: 04  
   Mean throughput class: 31  
   Packet data protocol: 02 (IP)  
 Buffer  
   Buffer size: 1400  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)  
 UICC/ME interface transport level  
   Transport format: UDP  
   Port number: 44444  
 Data destination address 01.01.01.01  
 Text Attribute  
   Formatting position: 0  
   Formatting length: 9  
   Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
   Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	53	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	31	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01	D0	04	00	09	00
	B4											

## PROACTIVE COMMAND: OPEN CHANNEL 5.10.2

## Logically:

Command details  
   Command number: 1  
   Command type: OPEN CHANNEL  
   Command qualifier: immediate link establishment  
 Device identities  
   Source device: UICC  
   Destination device: ME  
 Alpha Identifier "Open ID 2"  
 Bearer  
   Bearer type: GPRS  
   Bearer parameter:  
   Precedence Class: 03  
   Delay Class: 04  
   Reliability Class: 03  
   Peak throughput class: 04  
   Mean throughput class: 31  
   Packet data protocol: 02 (IP)  
 Buffer  
   Buffer size: 1400  
 Network access name: TestGp.rs

Text String: UserLog (User login)  
 Text String: UserPwd (User password)  
 UICC/ME interface transport level  
   Transport format: UDP  
   Port number: 44444  
 Data destination address 01.01.01.01

Coding:

BER-TLV:	D0	4D	81	03	01	40	01	82	02	81	82	05
	09	4F	70	65	6E	20	49	44	20	32	35	07
	02	03	04	03	04	1F	02	39	02	05	78	47
	0A	06	54	65	73	74	47	70	02	72	73	0D
	08	F4	55	73	65	72	4C	6F	67	0D	08	F4
	55	73	65	72	50	77	64	3C	03	01	AD	9C
	3E	05	21	01	01	01	01					

TERMINAL RESPONSE: OPEN CHANNEL 5.10.1A

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	05	78							

TERMINAL RESPONSE: OPEN CHANNEL 5.10.1B

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Channel status	Channel identifier 1 and link established or PDP context activated
Bearer description	
Bearer type:	GPRS
Bearer parameter:	
Precedence Class:	00
Delay Class:	04
Reliability Class:	03
Peak throughput class:	04
Mean throughput class:	31
Packet data protocol:	02 (IP)
Buffer	
Buffer size:	1400

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	05	78							

#### 27.22.4.27.5.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.10.

### 27.22.4.28 CLOSE CHANNEL

#### 27.22.4.28.1 CLOSE CHANNEL(normal)

##### 27.22.4.28.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.28.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.28.1.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (Command Performed Successfully); or
- TERMINAL RESPONSE (Bearer Independent Protocol Error);

to the UICC after the ME receives the CLOSE CHANNEL proactive command. The TERMINAL RESPONSE sent back to the UICC is function of the ME and the network capabilities against asked parameters by the UICC.

##### 27.22.4.28.1.4 Method of Test

###### 27.22.4.28.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME's default channel identifier as declared in table A.2/27

The following Bearer Parameters used are those defined in the default Test PDP context for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

#### 27.22.4.28.1.4.2 Procedure

#### Expected sequence 1.1 (CLOSE CHANNEL, successful)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 1.1.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 1.1.1	
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	
13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 1.1.1	[Command performed successfully]

PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

#### Command details

Command number: 1  
 Command type: OPEN CHANNEL

Command qualifier: immediate link establishment

Device identities  
 Source device: UICC  
 Destination device: ME

Bearer  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer  
 Buffer size: 1000  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)

UICC/ME interface transport level  
 Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

Coding:

BER-TLV	D0	42	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	03	E8
	47	0A	06	54	65	73	74	47	70	02	72	73
	0D	08	F4	55	73	65	72	4C	6F	67	0D	08
	F4	55	73	65	72	50	77	64	3C	03	01	AD
	9C	3E	05	21	01	01	01	01				

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details  
 Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities  
 Source device: ME  
 Destination device: UICC

Result  
 General Result: Command performed successfully

Channel status  
 Channel identifier 1 and link established or PDP context activated

Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer  
 Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F

02	39	02	03	E8								
----	----	----	----	----	--	--	--	--	--	--	--	--

## TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Channel status

Channel identifier 1 and link established or PDP context activated

## Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							

## PROACTIVE COMMAND: CLOSE CHANNEL 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Coding:

BER-TLV:	D0	09	81	03	01	41	00	82	02	81	21
----------	----	----	----	----	----	----	----	----	----	----	----

## TERMINAL RESPONSE: CLOSE CHANNEL 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

### Expected sequence 1.2 (CLOSE CHANNEL, with an invalid channel identifier)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 1.2.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 1.2.1	
11	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 1.2.1	[Invalid channel number]

PROACTIVE COMMAND: CLOSE CHANNEL 1.2.1

Logically:

Command details

Command number: 1  
Command type: CLOSE CHANNEL  
Command qualifier: RFU

Device identities

Source device: UICC  
Destination device: Channel 2

Coding:

BER-TLV:	D0	09	81	03	01	41	00	82	02	81	22
----------	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: CLOSE CHANNEL 1.2.1

Logically:

Command details

Command number: 1  
Command type: CLOSE CHANNEL  
Command qualifier: RFU

Device identities

Source device: ME  
Destination device: UICC

Result

General Result: Bearer Independent Protocol error  
Additional Result: Channel identifier not valid

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	02	3A
	03											

**Expected sequence 1.3 (CLOSE CHANNEL, on an already closed channel)**

Step	Direction	MESSAGE / Action	Comments	
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions	
2	ME → UICC	FETCH		
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1		
4	ME → USER	The ME may display channel opening information		
5	ME → USS	PDP context activation request		
6	USS → ME	PDP context activation accept		
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B		[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 1.1.1	[Command performed successfully]	
9	ME → UICC	FETCH		
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 1.1.1		
11	ME → USS	PDP context deactivation request		
12	USS → ME	PDP context deactivation accept		
13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 1.1.1		
14	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 1.3.1		
15	ME → UICC	FETCH		
16	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 1.3.1		
17	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 1.3.1A or TERMINAL RESPONSE CLOSE CHANNEL 1.3.1B		[Channel closed]  [Channel identifier invalid]

**PROACTIVE COMMAND: CLOSE CHANNEL 1.3.1**

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Coding:

BER-TLV:	D0	09	81	03	01	41	00	82	02	81	21
----------	----	----	----	----	----	----	----	----	----	----	----

**TERMINAL RESPONSE: CLOSE CHANNEL 1.3.1A**

Logically:

Command details

Command number: 1

Command type: CLOSE CHANNEL  
 Command qualifier: RFU  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Bearer Independent Protocol error  
 Additional Result: Channel closed

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	02	3A
	02											

TERMINAL RESPONSE: CLOSE CHANNEL 1.3.1B

Logically:

Command details  
 Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Bearer Independent Protocol error  
 Additional Result: Channel identifier invalid

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	02	3A
	03											

27.22.4.28.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

27.22.4.28.2 CLOSE CHANNEL (support of Text Attribute)

27.22.4.28.2.1 CLOSE CHANNEL (support of Text Attribute – Left Alignment)

27.22.4.28.2.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

27.22.4.28.2.1.3 Test purpose

To verify that the ME shall display the alpha identifier according to the left alignment text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

## 27.22.4.28.2.1.4 Method of Test

## 27.22.4.28.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

## Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

## 27.22.4.28.2.1.4.2 Procedure

**Expected sequence 2.1 (CLOSE CHANNEL, with Text Attribute – Left Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.1.1	[alpha identifier is displayed with left alignment]
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	

13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.1.1	[Command performed successfully]
14	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	ME → USER	The ME may display channel opening information	
18	ME → USS	PDP context activation request	
19	USS → ME	PDP context activation accept	
20	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
21	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.1.2	
22	ME → UICC	FETCH	
23	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.1.2	[Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/20, no alignment change will take place]
24	ME → USS	PDP context deactivation request	
25	USS → ME	PDP context deactivation accept	
26	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.1.1	[Command performed successfully]

PROACTIVE COMMAND: CLOSE CHANNEL 2.1.1

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	00	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.1.2

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1  
 Alpha Identifier "Close ID 2"

## Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32										

## TERMINAL RESPONSE: CLOSE CHANNEL 2.1.1

## Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.28.2.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1.

## 27.22.4.28.2.2 CLOSE CHANNEL (support of Text Attribute – Center Alignment)

## 27.22.4.28.2.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.28.2.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

## 27.22.4.28.2.2.3 Test purpose

To verify that the ME shall display the alpha identifier according to the center alignment text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

## 27.22.4.28.2.2.4 Method of Test

## 27.22.4.28.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

#### 27.22.4.28.2.2.4.2 Procedure

#### Expected sequence 2.2 (CLOSE CHANNEL, with Text Attribute – Center Alignment)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.2.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.2.1	[alpha identifier is displayed with center alignment]
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	

13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.2.1	[Command performed successfully]
14	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	ME → USER	The ME may display channel opening information	
18	ME → USS	PDP context activation request	
19	USS → ME	PDP context activation accept	
20	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
21	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.2.2	
22	ME → UICC	FETCH	
23	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.2.2	[Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/20, no alignment change will take place]
24	ME → USS	PDP context deactivation request	
25	USS → ME	PDP context deactivation accept	
26	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.2.1	[Command performed successfully]

PROACTIVE COMMAND: CLOSE CHANNEL 2.2.1

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	01	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.2.2

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1  
 Alpha Identifier "Close ID 2"

## Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32										

## TERMINAL RESPONSE: CLOSE CHANNEL 2.2.1

## Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.28.2.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.2.

## 27.22.4.28.2.3 CLOSE CHANNEL (support of Text Attribute – Right Alignment)

## 27.22.4.28.2.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.28.2.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

## 27.22.4.28.2.3.3 Test purpose

To verify that the ME shall display the alpha identifier according to the right alignment text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

## 27.22.4.28.2.3.4 Method of Test

## 27.22.4.28.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

#### 27.22.4.28.2.3.4.2 Procedure

### Expected sequence 2.3 (CLOSE CHANNEL, with Text Attribute – Right Alignment)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.3.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.3.1	[alpha identifier is displayed with right alignment]
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	

13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.3.1	[Command performed successfully]	
14	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1		
15	ME → UICC	FETCH		
16	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1		
17	ME → USER	The ME may display channel opening information		
18	ME → USS	PDP context activation request		
19	USS → ME	PDP context activation accept		
20	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B		[Command performed successfully]
21	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.3.2		
22	ME → UICC	FETCH		
23	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.3.2		[Message shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/20, no alignment change will take place]
24	ME → USS	PDP context deactivation request		
25	USS → ME	PDP context deactivation accept		
26	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.3.1	[Command performed successfully]	

PROACTIVE COMMAND: CLOSE CHANNEL 2.3.1

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	02	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.3.2

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC

Destination device: Channel 1  
Alpha Identifier "Close ID 2"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32										

TERMINAL RESPONSE: CLOSE CHANNEL 2.3.1

Logically:

Command details

Command number: 1  
Command type: CLOSE CHANNEL  
Command qualifier: RFU

Device identities

Source device: ME  
Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.28.2.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.3.

#### 27.22.4.28.2.4 CLOSE CHANNEL (support of Text Attribute – Large Font Size)

##### 27.22.4.28.2.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.28.2.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.28.2.4.3 Test purpose

To verify that the ME shall display the alpha identifier according to the large font size text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

##### 27.22.4.28.2.4.4 Method of Test

###### 27.22.4.28.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The

corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

#### 27.22.4.28.2.4.4.2 Procedure

### Expected sequence 2.4 (CLOSE CHANNEL, with Text Attribute – Large Font Size)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND	See initial conditions
		PENDING: OPEN CHANNEL 1.1.1	
2	ME → UICC	FETCH	[Command performed successfully]
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.1	
9	ME → UICC	FETCH	[alpha identifier is displayed with large font size]
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1	
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	

13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.4.1	[Command performed successfully]
14	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	ME → USER	The ME may display channel opening information	
18	ME → USS	PDP context deactivation request	
19	USS → ME	PDP context deactivation accept	
20	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
21	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2	
22	ME → UICC	FETCH	
23	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2	[alpha identifier is displayed with normal font size]
24	ME → USS	PDP context deactivation request	
25	USS → ME	PDP context deactivation accept	
26	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.4.1	[Command performed successfully]
27	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
30	ME → USER	The ME may display channel opening information	
31	ME → USS	PDP context activation request	
32	USS → ME	PDP context activation accept	
33	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
34	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1	[alpha identifier is displayed with large font size]
37	ME → USS	PDP context deactivation request	
38	USS → ME	PDP context deactivation accept	

39	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.4.1	[Command performed successfully]
40	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	ME → UICC	FETCH	
42	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
43	ME → USER	The ME may display channel opening information	
44	ME → USS	PDP context activation request	
45	USS → ME	PDP context activation accept	
46	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
47	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.3	
48	ME → UICC	FETCH	
49	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.4.3	[alpha identifier is displayed with normal font size]
50	ME → USS	PDP context deactivation request	
51	USS → ME	PDP context deactivation accept	
52	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.4.1	[Command performed successfully]

PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	04	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 2"

## Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

## PROACTIVE COMMAND: CLOSE CHANNEL 2.4.3

## Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1  
 Alpha Identifier "Close ID 3"

## Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

## TERMINAL RESPONSE: CLOSE CHANNEL 2.4.1

## Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.28.2.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.4.

## 27.22.4.28.2.5 CLOSE CHANNEL (support of Text Attribute – Small Font Size)

## 27.22.4.28.2.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.2.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.28.2.5.3 Test purpose

To verify that the ME shall display the alpha identifier according to the small font size text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.28.2.5.4 Method of Test

##### 27.22.4.28.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.28.2.5.4.2 Procedure

**Expected sequence 2.5 (CLOSE CHANNEL, with Text Attribute – Small Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.5.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.5.1	[alpha identifier is displayed with small font size]
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	
13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.5.1	[Command performed successfully]
14	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	ME → USER	The ME may display channel opening information	
18	ME → USS	PDP context activation request	
19	USS → ME	PDP context activation accept	
20	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
21	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.5.2	
22	ME → UICC	FETCH	
23	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.5.2	[alpha identifier is displayed with normal font size]
24	ME → USS	PDP context deactivation request	
25	USS → ME	PDP context deactivation accept	

26	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.5.1	[Command performed successfully]
27	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
30	ME → USER	The ME may display channel opening information	
31	ME → USS	PDP context activation request	
32	USS → ME	PDP context activation accept	
33	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
34	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.5.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.5.1	[alpha identifier is displayed with small font size]
37	ME → USS	PDP context deactivation request	
38	USS → ME	PDP context deactivation accept	
39	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.5.1	[Command performed successfully]
40	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	ME → UICC	FETCH	
42	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
43	ME → USER	The ME may display channel opening information	
44	ME → USS	PDP context activation request	
45	USS → ME	PDP context activation accept	
46	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
47	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.5.3	
48	ME → UICC	FETCH	
49	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.5.3	[alpha identifier is displayed with normal font size]
50	ME → USS	PDP context deactivation request	
51	USS → ME	PDP context deactivation accept	
52	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.5.1	[Command performed successfully]

### PROACTIVE COMMAND: CLOSE CHANNEL 2.5.1

Logically:

#### Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

#### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 1"

#### Text Attribute

Formatting position: 0  
 Formatting length: 10

Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off,  
Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	08	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.5.2

Logically:

Command details

Command number: 1  
Command type: CLOSE CHANNEL  
Command qualifier: RFU

Device identities

Source device: UICC  
Destination device: Channel 1

Alpha Identifier "Close ID 2"

Text Attribute

Formatting position: 0  
Formatting length: 10  
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.5.3

Logically:

Command details

Command number: 1  
Command type: CLOSE CHANNEL  
Command qualifier: RFU

Device identities

Source device: UICC  
Destination device: Channel 1

Alpha Identifier "Close ID 3"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

#### TERMINAL RESPONSE: CLOSE CHANNEL 2.5.1

Logically:

Command details

Command number: 1  
Command type: CLOSE CHANNEL  
Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.28.2.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.5.

## 27.22.4.28.2.6 CLOSE CHANNEL (support of Text Attribute – Bold On)

## 27.22.4.28.2.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.28.2.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

## 27.22.4.28.2.6.3 Test purpose

To verify that the ME shall display the alpha identifier according to the bold text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

## 27.22.4.28.2.6.4 Method of Test

## 27.22.4.28.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

## Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog

User password: UserPwd  
UICC/ME interface transport level

Transport format:UDP  
Port number: 44444  
Data destination address 01.01.01.01

27.22.4.28.2.6.4.2 Procedure

**Expected sequence 2.6 (CLOSE CHANNEL, with Text Attribute – Bold On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.6.1	[alpha identifier is displayed with bold on]
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	
13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.6.1	[Command performed successfully]
14	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	ME → USER	The ME may display channel opening information	
18	ME → USS	PDP context activation request	
19	USS → ME	PDP context activation accept	
20	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
21	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.2	
22	ME → UICC	FETCH	
23	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.6.2	[alpha identifier is displayed with bold off]
24	ME → USS	PDP context deactivation request	
25	USS → ME	PDP context deactivation accept	

26	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.6.1	[Command performed successfully]
27	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
30	ME → USER	The ME may display channel opening information	
31	ME → USS	PDP context activation request	
32	USS → ME	PDP context activation accept	
33	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
34	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.6.1	[alpha identifier is displayed with bold on]
37	ME → USS	PDP context deactivation request	
38	USS → ME	PDP context deactivation accept	
39	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.6.1	[Command performed successfully]
40	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	ME → UICC	FETCH	
42	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
43	ME → USER	The ME may display channel opening information	
44	ME → USS	PDP context activation request	
45	USS → ME	PDP context activation accept	
46	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A	[Command performed successfully]
		or	
		TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
47	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.3	
48	ME → UICC	FETCH	
49	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.6.3	[alpha identifier is displayed with bold off]
50	ME → USS	PDP context deactivation request	
51	USS → ME	PDP context deactivation accept	
52	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.6.1	[Command performed successfully]

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.6.1

Logically:

##### Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 1"

##### Text Attribute

Formatting position: 0  
 Formatting length: 10

Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	10	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.6.2

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 2"

Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.6.3

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 3"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

#### TERMINAL RESPONSE: CLOSE CHANNEL 2.6.1

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.28.2.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.6.

## 27.22.4.28.2.7 CLOSE CHANNEL (support of Text Attribute – Italic On)

## 27.22.4.28.2.7.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.28.2.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

## 27.22.4.28.2.7.3 Test purpose

To verify that the ME shall display the alpha identifier according to the italic text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

## 27.22.4.28.2.7.4 Method of Test

## 27.22.4.28.2.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

## Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog

User password: UserPwd  
UICC/ME interface transport level

Transport format:UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.28.2.7.4.2 Procedure

**Expected sequence 2.7 (CLOSE CHANNEL, with Text Attribute – Italic On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.7.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.7.1	[alpha identifier is displayed with bold on]
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	
13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.7.1	[Command performed successfully]
14	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	ME → USER	The ME may display channel opening information	
18	ME → USS	PDP context activation request	
19	USS → ME	PDP context activation accept	
20	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
21	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.2	
22	ME → UICC	FETCH	
23	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.7.2	[alpha identifier is displayed with bold off]
24	ME → USS	PDP context deactivation request	
25	USS → ME	PDP context deactivation accept	
26	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.7.1	[Command performed successfully]
27	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
30	ME → USER	The ME may display channel opening information	
31	ME → USS	PDP context activation request	
32	USS → ME	PDP context activation accept	
33	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]

34	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.7.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.7.1	[alpha identifier is displayed with bold on]
37	ME → USS	PDP context deactivation request	
38	USS → ME	PDP context deactivation accept	
39	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.7.1	[Command performed successfully]
40	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	ME → UICC	FETCH	
42	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
43	ME → USER	The ME may display channel opening information	
44	ME → USS	PDP context activation request	
45	USS → ME	PDP context activation accept	
46	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
47	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.7.3	
48	ME → UICC	FETCH	
49	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.7.3	[alpha identifier is displayed with bold off]
50	ME → USS	PDP context deactivation request	
51	USS → ME	PDP context deactivation accept	
52	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.7.1	[Command performed successfully]

PROACTIVE COMMAND: CLOSE CHANNEL 2.7.1

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	20	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.7.2

Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 2"

## Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

## PROACTIVE COMMAND: CLOSE CHANNEL 2.7.3

## Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 3"

## Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

## TERMINAL RESPONSE: CLOSE CHANNEL 2.7.1

## Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.28.2.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.7.

27.22.4.28.2.8 CLOSE CHANNEL (support of Text Attribute – Underline On)

27.22.4.28.2.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

27.22.4.28.2.8.3 Test purpose

To verify that the ME shall display the alpha identifier according to the underline text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.8.4 Method of Test

27.22.4.28.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03

Delay Class: 04

Reliability Class: 03

Peak throughput class: 04

Mean throughput class: 31

Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs

User login: UserLog

User password: UserPwd

UICC/ME interface transport level

Transport format: UDP

Port number: 44444

Data destination address 01.01.01.01

## 27.22.4.28.2.8.4.2 Procedure

**Expected sequence 2.8 (CLOSE CHANNEL, with Text Attribute – Underline On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.8.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.8.1	[alpha identifier is displayed with underline on]
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	
13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.8.1	[Command performed successfully]
14	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	ME → USER	The ME may display channel opening information	
18	ME → USS	PDP context activation request	
19	USS → ME	PDP context activation accept	
20	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
21	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.8.2	
22	ME → UICC	FETCH	
23	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.8.2	[alpha identifier is displayed with underline off]
24	ME → USS	PDP context deactivation request	
25	USS → ME	PDP context deactivation accept	
26	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.8.1	[Command performed successfully]
27	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
30	ME → USER	The ME may display channel opening information	
31	ME → USS	PDP context activation request	
32	USS → ME	PDP context activation accept	

33	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
34	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.8.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.8.1	[alpha identifier is displayed with underline on]
37	ME → USS	PDP context deactivation request	
38	USS → ME	PDP context deactivation accept	
39	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.8.1	[Command performed successfully]
40	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	ME → UICC	FETCH	
42	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
43	ME → USER	The ME may display channel opening information	
44	ME → USS	PDP context activation request	
45	USS → ME	PDP context activation accept	
46	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
47	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.8.3	
48	ME → UICC	FETCH	
49	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.8.3	[alpha identifier is displayed with underline off]
50	ME → USS	PDP context deactivation request	
51	USS → ME	PDP context deactivation accept	
52	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.8.1	[Command performed successfully]

#### PROACTIVE COMMAND: CLOSE CHANNEL 2.8.1

Logically:

##### Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 1"

##### Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	40	B4				

## PROACTIVE COMMAND: CLOSE CHANNEL 2.8.2

Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 2"

## Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

## PROACTIVE COMMAND: CLOSE CHANNEL 2.8.3

Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 3"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

## TERMINAL RESPONSE: CLOSE CHANNEL 2.8.1

Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.28.2.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.8.

#### 27.22.4.28.2.9 CLOSE CHANNEL (support of Text Attribute – Strikethrough On)

##### 27.22.4.28.2.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.28.2.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.28.2.9.3 Test purpose

To verify that the ME shall display the alpha identifier according to the strikethrough text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

##### 27.22.4.28.2.9.4 Method of Test

###### 27.22.4.28.2.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

## 27.22.4.28.2.9.4.2 Procedure

**Expected sequence 2.9 (CLOSE CHANNEL, with Text Attribute – Strikethrough On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.9.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.9.1	[alpha identifier is displayed with strikethrough on]
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	
13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.9.1	[Command performed successfully]
14	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	ME → USER	The ME may display channel opening information	
18	ME → USS	PDP context activation request	
19	USS → ME	PDP context activation accept	
20	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
21	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.9.2	
22	ME → UICC	FETCH	
23	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.9.2	[alpha identifier is displayed with strikethrough off]
24	ME → USS	PDP context deactivation request	
25	USS → ME	PDP context deactivation accept	
26	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.9.1	[Command performed successfully]
27	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
30	ME → USER	The ME may display channel opening information	
31	ME → USS	PDP context activation request	
32	USS → ME	PDP context activation accept	
33	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]

34	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.9.1	
35	ME → UICC	FETCH	
36	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.9.1	[alpha identifier is displayed with strikethrough on]
37	ME → USS	PDP context deactivation request	
38	USS → ME	PDP context deactivation accept	
39	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.9.1	[Command performed successfully]
40	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
41	ME → UICC	FETCH	
42	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
43	ME → USER	The ME may display channel opening information	
44	ME → USS	PDP context activation request	
45	USS → ME	PDP context activation accept	
46	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
47	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.9.3	
48	ME → UICC	FETCH	
49	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.9.3	[alpha identifier is displayed with strikethrough off]
50	ME → USS	PDP context deactivation request	
51	USS → ME	PDP context deactivation accept	
52	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.9.1	[Command performed successfully]

PROACTIVE COMMAND: CLOSE CHANNEL 2.9.1

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	80	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.9.2

Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 2"

## Text Attribute

Formatting position: 0  
 Formatting length: 10  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

## Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32	D0	04	00	0A	00	B4				

## PROACTIVE COMMAND: CLOSE CHANNEL 2.9.3

## Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Close ID 3"

## Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	33										

## TERMINAL RESPONSE: CLOSE CHANNEL 2.9.1

## Logically:

## Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.4.28.2.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.9.

27.22.4.28.2.10 CLOSE CHANNEL (support of Text Attribute – Foreground and Background Colour)

27.22.4.28.2.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.28.2.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

27.22.4.28.2.10.3 Test purpose

To verify that the ME shall display the alpha identifier according to the foreground and background colour text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.28.2.10.4 Method of Test

27.22.4.28.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03

Delay Class: 04

Reliability Class: 03

Peak throughput class: 04

Mean throughput class: 31

Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs

User login: UserLog

User password: UserPwd

UICC/ME interface transport level

Transport format: UDP

Port number: 44444

Data destination address 01.01.01.01

## 27.22.4.28.2.10.4.2 Procedure

**Expected sequence 2.10 (CLOSE CHANNEL, with Text Attribute – Foreground and Background Colour)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.10.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.10.1	[alpha identifier is displayed with foreground and background colour according to the text attribute configuration]
11	ME → USS	PDP context deactivation request	
12	USS → ME	PDP context deactivation accept	
13	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.10.1	[Command performed successfully]
14	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	
15	ME → UICC	FETCH	
16	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
17	ME → USER	The ME may display channel opening information	
18	ME → USS	PDP context activation request	
19	USS → ME	PDP context activation accept	
20	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
21	UICC → ME	PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.10.2	
22	ME → UICC	FETCH	
23	UICC → ME	PROACTIVE COMMAND: CLOSE CHANNEL 2.10.2	[alpha identifier is displayed with ME"s default foreground and background colour]
24	ME → USS	PDP context deactivation request	
25	USS → ME	PDP context deactivation accept	
26	ME → UICC	TERMINAL RESPONSE CLOSE CHANNEL 2.10.1	[Command performed successfully]

PROACTIVE COMMAND: CLOSE CHANNEL 2.10.1

Logically:

Command details

Command number: 1  
 Command type: CLOSE CHANNEL  
 Command qualifier: RFU

Device identities

Source device: UICC

Destination device:Channel 1  
 Alpha Identifier "Close ID 1"  
 Text Attribute  
     Formatting position: 0  
     Formatting length: 10  
     Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	1B	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	31	D0	04	00	0A	00	B4				

PROACTIVE COMMAND: CLOSE CHANNEL 2.10.2

Logically:

Command details  
     Command number: 1  
     Command type: CLOSE CHANNEL  
     Command qualifier: RFU  
 Device identities  
     Source device: UICC  
     Destination device:Channel 1  
 Alpha Identifier "Close ID 2"

Coding:

BER-TLV:	D0	15	81	03	01	41	00	82	02	81	21
	85	0A	43	6C	6F	73	65	20	49	44	20
	32										

TERMINAL RESPONSE: CLOSE CHANNEL 2.10.1

Logically:

Command details  
     Command number: 1  
     Command type: CLOSE CHANNEL  
     Command qualifier: RFU  
 Device identities  
     Source device: ME  
     Destination device: UICC  
 Result  
     General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	41	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

27.22.4.28.2.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.10.

## 27.22.4.29 RECEIVE DATA

### 27.22.4.29.1 RECEIVE DATA (NORMAL)

#### 27.22.4.29.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.29.1.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (Command Performed Successfully); or
- TERMINAL RESPONSE (ME currently unable to process command); or
- TERMINAL RESPONSE (Bearer Independent Protocol Error);

to the UICC after the ME receives the RECEIVE DATA proactive command. The TERMINAL RESPONSE sent back to the UICC is function of the ME and the network capabilities against asked parameters by the UICC.

#### 27.22.4.29.1.4 Method of test

##### 27.22.4.29.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME's default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 51.010-1 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog

User password: UserPwd  
UICC/ME interface transport level

Transport format:UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.29.1.4.2 Procedure

**Expected sequence 1.1 (RECEIVE DATA, already opened channel)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	USS → ME	Transfer of 1000 Bytes of data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Data available 1.1.1	(1000 Bytes of data in the ME buffer)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 1.1.1	200 Bytes
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 1.1.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.2	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 1.1.2	200 Bytes
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 1.1.2	
27	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.3	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 1.1.3	200 Bytes
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 1.1.3	
31	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.4	
32	ME → UICC	FETCH	
33	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 1.1.4	200 Bytes
34	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 1.1.4	
35	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.5	
36	ME → UICC	FETCH	
37	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 1.1.5	200 Bytes
38	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 1.1.5	

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: ME

Event list Data available

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	09										

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: RFU

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: UICC  
 Destination device: ME

Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Coding:

BER-TLV	D0	42	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	03	E8
	47	0A	06	54	65	73	74	47	70	02	72	73
	0D	08	F4	55	73	65	72	4C	6F	67	0D	08
	F4	55	73	65	72	50	77	64	3C	03	01	AD
	9C	3E	05	21	01	01	01	01				

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Channel status

Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	03	E8							

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Channel status

Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04

Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1000

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							

## PROACTIVE COMMAND: SEND DATA 1.1.1

## Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: UICC  
 Destination device: Channel 1

## Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

## Coding:

BER-TLV:	D0	13	81	03	01	43	01	82	02	81	21	B6
	08	00	01	02	03	04	05	06	07			

## TERMINAL RESPONSE: SEND DATA 1.1.1

## Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

## Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

## ENVELOPE: EVENT DOWNLOAD - Data available 1.1.1

## Logically:

## Event list

Event: Data available

## Device identities

Source device: ME  
 Destination device: UICC

## Channel status

Channel status: Channel 1 open, link established  
 Channel Data Length  
 Channel data length: FF (more than 255 bytes are available)

Coding:

BER-TLV:	D6	0E	99	01	09	82	02	82	81	B8	02	81
	00	B7	01	FF								

PROACTIVE COMMAND: RECEIVE DATA 1.1.1

Logically:

Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	0C	81	03	01	42	00	82	02	81	21	B7
	01	C8										

PROACTIVE COMMAND: RECEIVE DATA 1.1.2

Logically:

Command details

Command number: 2  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	0C	81	03	02	42	00	82	02	81	21	B7
	01	C8										

PROACTIVE COMMAND: RECEIVE DATA 1.1.3

Logically:

Command details

Command number: 3  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	0C	81	03	03	42	00	82	02	81	21	B7
	01	C8										

## PROACTIVE COMMAND: RECEIVE DATA 1.1.4

Logically:

## Command details

Command number: 4  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

## Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	0C	81	03	04	42	00	82	02	81	21	B7
	01	C8										

## PROACTIVE COMMAND: RECEIVE DATA 1.1.5

Logically:

## Command details

Command number: 5  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

## Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	0C	81	03	05	42	00	82	02	81	21	B7
	01	C8										

## TERMINAL RESPONSE: RECEIVE DATA 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel Data : 00 01 02 .. C7 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02	..	C7	B7	01	FF	

## TERMINAL RESPONSE: RECEIVE DATA 1.1.2

Logically:

## Command details

Command number: 2  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel Data : C8 C9 CA .. FF 00 01 .. 8F (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	02	42	00	82	02	82	81	83	01	00
	B6	81	C8	C8	C9	CA	..	FF	00	01	02	..
	8F	B7	01	FF								

## TERMINAL RESPONSE: RECEIVE DATA 1.1.3

Logically:

## Command details

Command number: 3  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel Data : 90 91 .. FF 00 01 – 57 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	03	42	00	82	02	82	81	83	01	00
	B6	81	C8	90	91	92	..	FF	00	01	02	..
	57	B7	01	FF								

## TERMINAL RESPONSE: RECEIVE DATA 1.1.4

Logically:

## Command details

Command number: 4  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel Data : 58 59 .. FF 00 01 .. 1F (200 Bytes of data)  
 Channel data length: C8

Coding:

BER-TLV:	81	03	04	42	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

B6	81	C8	58	59	5A	..	FF	00	01	02	..
1F	B7	01	C8								

#### TERMINAL RESPONSE: RECEIVE DATA 1.1.5

Logically:

##### Command details

Command number: 5  
 Command type: RECEIVE DATA  
 Command qualifier: RFUDevice identities  
 Source device: ME  
 Destination device: UICC

##### Result

General Result: Command performed successfully  
 Channel Data: 20 21 .. E7 (200 Bytes of data)  
 Channel data length: 00

Coding:

BER-TLV:	81	03	05	42	00	82	02	82	81	83	01	00
	B6	81	C8	20	21	22	..	E7	B7	01	00	

#### 27.22.4.29.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

#### 27.22.4.29.2 RECEIVE DATA (support of Text Attribute)

##### 27.22.4.29.2.1 RECEIVE DATA (support of Text Attribute – Left Alignment)

##### 27.22.4.29.2.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.29.2.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.29.2.1.3 Test purpose

To verify that the ME shall display the alpha identifier according to the left alignment text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

##### 27.22.4.29.2.1.4 Method of test

##### 27.22.4.29.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.29.2.1.4.2 Procedure

**Expected sequence 2.1 (RECEIVE DATA, with Text Attribute – Left Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	USS → ME	Transfer of 400 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1 ENVELOPE (Data Available)	(400 Bytes of data in the ME buffer)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.1.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.1.1	200 Bytes with alpha identifier is displayed with left alignment
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.1.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.1.2	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.1.2	200 Bytes with alpha identifier shall be formatted without left alignment. Remark: If left alignment is the ME's default alignment as declared in table A.2/21, no alignment change will take place
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.1.1	

**PROACTIVE COMMAND: SEND DATA 1.1.1**

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

**TERMINAL RESPONSE: SEND DATA 1.1.1**

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

## ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Logically:

Event list  
 Event: Data available

Device identities  
 Source device: ME  
 Destination device: UICC

Channel status  
 Channel status: Channel 1 open, link established

Channel Data Length  
 Channel data length: FF (more than 255 bytes are available)

Coding:

BER-TLV:	D6	0E	99	01	09	82	02	82	81	B8	02	81
	00	B7	01	FF								

## PROACTIVE COMMAND: RECEIVE DATA 2.1.1

Logically:

Command details  
 Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

Device identities  
 Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 1"

Channel Data Length  
 Channel Data Length: 200

Text Attribute  
 Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	00	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.1.2

Logically:

Command details  
 Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

Device identities  
 Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 2"

Channel Data Length  
 Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.1.1

Logically:

Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel Data : 00 01 02 .. C7 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02	..	C7	B7	01	FF	

#### 27.22.4.29.2.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1.

#### 27.22.4.29.2.2 RECEIVE DATA (support of Text Attribute – Center Alignment)

##### 27.22.4.29.2.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.29.2.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.29.2.2.3 Test purpose

To verify that the ME shall display the alpha identifier according to the center alignment text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

##### 27.22.4.29.2.2.4 Method of test

###### 27.22.4.29.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.29.2.2.4.2 Procedure

**Expected sequence 2.2 (RECEIVE DATA, with Text Attribute – Center Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	USS → ME	Transfer of 400 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1	(400 Bytes of data in the ME buffer)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.2.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.2.1	200 Bytes with alpha identifier is displayed with center alignment
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.2.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.2.2	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.2.2	200 Bytes with alpha identifier shall be formatted without center alignment. Remark: If center alignment is the ME's default alignment as declared in table A.2/21, no alignment change will take place
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.2.1	

**PROACTIVE COMMAND: SEND DATA 1.1.1**

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

**TERMINAL RESPONSE: SEND DATA 1.1.1**

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

PROACTIVE COMMAND: RECEIVE DATA 2.2.1

Logically:

Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 1"

Channel Data Length

Channel Data Length: 200

Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	01	B4

PROACTIVE COMMAND: RECEIVE DATA 2.2.2

Logically:

Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 2"

Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.2.1

Logically:

Command details

Command number: 1  
 Command type: RECEIVE DATA

Command qualifier: RFU  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Channel Data : 00 01 02 .. C7 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02	..	C7	B7	01	FF	

#### 27.22.4.29.2.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.2.

#### 27.22.4.29.2.3 RECEIVE DATA (support of Text Attribute – Right Alignment)

##### 27.22.4.29.2.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.29.2.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.29.2.3.3 Test purpose

To verify that the ME shall display the alpha identifier according to the right alignment text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

##### 27.22.4.29.2.3.4 Method of test

###### 27.22.4.29.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04

Mean throughput class: 31  
Packet data protocol:02 (IP)

GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

UICC/ME interface transport level

Transport format:UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.29.2.3.4.2 Procedure

**Expected sequence 2.3 (RECEIVE DATA, with Text Attribute – Right Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	USS → ME	Transfer of 400 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1	(400 Bytes of data in the ME buffer)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.3.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.3.1	200 Bytes with alpha identifier is displayed with right alignment
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.3.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.3.2	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.3.2	200 Bytes with alpha identifier shall be formatted without right alignment. Remark: If right alignment is the ME's default alignment as declared in table A.2/21, no alignment change will take place
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.3.1	

**PROACTIVE COMMAND: SEND DATA 1.1.1**

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

**TERMINAL RESPONSE: SEND DATA 1.1.1**

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

## ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

## PROACTIVE COMMAND: RECEIVE DATA 2.3.1

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 1"

## Channel Data Length

Channel Data Length: 200

## Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	02	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.3.2

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 2"

## Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8						

## TERMINAL RESPONSE: RECEIVE DATA 2.3.1

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA

Command qualifier: RFU  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Channel Data : 00 01 02 .. C7 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02	..	C7	B7	01	FF	

#### 27.22.4.29.2.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.3.

#### 27.22.4.29.2.4 RECEIVE DATA (support of Text Attribute – Large Font Size)

##### 27.22.4.29.2.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.29.2.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.29.2.4.3 Test purpose

To verify that the ME shall display the alpha identifier according to the large font size text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

##### 27.22.4.29.2.4.4 Method of test

###### 27.22.4.29.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04

Mean throughput class: 31  
Packet data protocol:02 (IP)

GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

UICC/ME interface transport level

Transport format:UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.29.2.4.4.2 Procedure

**Expected sequence 2.4 (RECEIVE DATA, with Text Attribute – Large Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	USS → ME	Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1	(800 Bytes of data in the ME buffer)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.4.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.4.1	200 Bytes with alpha identifier is displayed with large font size
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.4.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.4.2	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.4.2	200 Bytes with alpha identifier is displayed with normal font size
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.4.1	
27	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.4.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.4.1	200 Bytes with alpha identifier is displayed with large font size
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.4.1	
31	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.4.3	
32	ME → UICC	FETCH	
33	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.4.3	200 Bytes with alpha identifier is displayed with normal font size
34	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.4.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

#### PROACTIVE COMMAND: RECEIVE DATA 2.4.1

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 1"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Large Font, Bold On, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	04	B4

#### PROACTIVE COMMAND: RECEIVE DATA 2.4.2

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 2"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

PROACTIVE COMMAND: RECEIVE DATA 2.4.3

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 3"

## Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.4.1

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel Data : 00 01 02 .. C7 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02	..	C7	B7	01	FF	

## 27.22.4.29.2.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.4.

## 27.22.4.29.2.5 RECEIVE DATA (support of Text Attribute – Small Font Size)

## 27.22.4.29.2.5.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.29.2.5.3 Test purpose

To verify that the ME shall display the alpha identifier according to small font size the text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.5.4 Method of test

##### 27.22.4.29.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.29.2.5.4.2 Procedure

**Expected sequence 2.5 (RECEIVE DATA, with Text Attribute – Small Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	USS → ME	Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1	(800 Bytes of data in the ME buffer)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.5.1	200 Bytes with alpha identifier is displayed with small font size
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.5.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.2	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.5.2	200 Bytes with alpha identifier is displayed with normal font size
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.5.1	
27	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.5.1	200 Bytes with alpha identifier is displayed with small font size
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.5.1	
31	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.3	
32	ME → UICC	FETCH	
33	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.5.3	200 Bytes with alpha identifier is displayed with normal font size
34	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.5.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

#### PROACTIVE COMMAND: RECEIVE DATA 2.5.1

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 1"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Small Font, Bold On, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	08	B4

#### PROACTIVE COMMAND: RECEIVE DATA 2.5.2

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 2"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

PROACTIVE COMMAND: RECEIVE DATA 2.5.3

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 3"

## Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.5.1

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel Data : 00 01 02 .. C7 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02	..	C7	B7	01	FF	

## 27.22.4.29.2.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.5.

## 27.22.4.29.2.6 RECEIVE DATA (support of Text Attribute – Bold On)

## 27.22.4.29.2.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.29.2.6.3 Test purpose

To verify that the ME shall display the alpha identifier according to the bold text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.6.4 Method of test

##### 27.22.4.29.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.29.2.6.4.2 Procedure

**Expected sequence 2.6 (RECEIVE DATA, with Text Attribute – Bold On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	USS → ME	Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1	(800 Bytes of data in the ME buffer)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.6.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.6.1	200 Bytes with alpha identifier is displayed with bold on
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.6.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.6.2	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.6.2	200 Bytes with alpha identifier is displayed with bold off
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.6.1	
27	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.6.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.6.1	200 Bytes with alpha identifier is displayed with bold on
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.6.1	
31	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.6.3	
32	ME → UICC	FETCH	
33	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.6.3	200 Bytes with alpha identifier is displayed with bold off
34	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.6.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

#### PROACTIVE COMMAND: RECEIVE DATA 2.6.1

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 1"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	10	B4

#### PROACTIVE COMMAND: RECEIVE DATA 2.6.2

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 2"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

PROACTIVE COMMAND: RECEIVE DATA 2.6.3

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 3"

## Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.6.1

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel Data : 00 01 02 .. C7 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02	..	C7	B7	01	FF	

## 27.22.4.29.2.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.6.

## 27.22.4.29.2.7 RECEIVE DATA (support of Text Attribute – Italic On)

## 27.22.4.29.2.7.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.29.2.7.3 Test purpose

To verify that the ME shall display the alpha identifier according to the italic text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.7.4 Method of test

##### 27.22.4.29.2.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.29.2.7.4.2 Procedure

**Expected sequence 2.7 (RECEIVE DATA, with Text Attribute – Italic On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	USS → ME	Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1ENVELOPE	(800 Bytes of data in the ME buffer)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.7.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.7.1	200 Bytes with alpha identifier is displayed with italic on
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.7.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.7.2	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.7.2	200 Bytes with alpha identifier is displayed with italic off
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.7.1	
27	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.7.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.7.1	200 Bytes with alpha identifier is displayed with italic on
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.7.1	
31	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.7.3	
32	ME → UICC	FETCH	
33	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.7.3	200 Bytes with alpha identifier is displayed with italic off
34	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.7.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

#### PROACTIVE COMMAND: RECEIVE DATA 2.7.1

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 1"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	20	B4

#### PROACTIVE COMMAND: RECEIVE DATA 2.7.2

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 2"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

PROACTIVE COMMAND: RECEIVE DATA 2.7.3

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 3"

## Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.7.1

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel Data : 00 01 02 .. C7 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02	..	C7	B7	01	FF	

## 27.22.4.29.2.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.7.

## 27.22.4.29.2.8 RECEIVE DATA (support of Text Attribute – Underline On)

## 27.22.4.29.2.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.29.2.8.3 Test purpose

To verify that the ME shall display the alpha identifier according to the underline text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.8.4 Method of test

##### 27.22.4.29.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.29.2.8.4.2 Procedure

**Expected sequence 2.8 (RECEIVE DATA, with Text Attribute – Underline On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	USS → ME	Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1	(800 kBytes of data in the ME buffer)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.8.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.8.1	200 Bytes with alpha identifier is displayed with underline on
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.8.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.8.2	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.8.2	200 Bytes with alpha identifier is displayed with underline off
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.8.1	
27	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.8.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.8.1	200 Bytes with alpha identifier is displayed with underline on
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.8.1	
31	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.8.3	
32	ME → UICC	FETCH	
33	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.8.3	200 Bytes with alpha identifier is displayed with underline off
34	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.8.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

#### PROACTIVE COMMAND: RECEIVE DATA 2.8.1

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 1"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	40	B4

#### PROACTIVE COMMAND: RECEIVE DATA 2.8.2

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 2"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

PROACTIVE COMMAND: RECEIVE DATA 2.8.3

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 3"

## Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.8.1

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel Data : 00 01 02 .. C7 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02	..	C7	B7	01	FF	

## 27.22.4.29.2.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.8.

## 27.22.4.29.2.9 RECEIVE DATA (support of Text Attribute – Strikethrough On)

## 27.22.4.29.2.9.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.29.2.9.3 Test purpose

To verify that the ME shall display the alpha identifier according to the strikethrough text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.9.4 Method of test

##### 27.22.4.29.2.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.29.2.9.4.2 Procedure

**Expected sequence 2.9 (RECEIVE DATA, with Text Attribute – Strikethrough On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	USS → ME	Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1	(800 Bytes of data in the ME buffer)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.9.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.9.1	200 Bytes with alpha identifier is displayed with strikethrough on
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.9.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.9.2	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.9.2	200 Bytes with alpha identifier is displayed with strikethrough off
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.9.1	
27	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.9.1	
28	ME → UICC	FETCH	
29	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.9.1	200 Bytes with alpha identifier is displayed with strikethrough on
30	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.9.1	
31	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.9.3	
32	ME → UICC	FETCH	
33	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.9.3	200 Bytes with alpha identifier is displayed with strikethrough off
34	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.9.1	

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

#### ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

#### PROACTIVE COMMAND: RECEIVE DATA 2.9.1

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 1"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	80	B4

#### PROACTIVE COMMAND: RECEIVE DATA 2.9.2

Logically:

##### Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

##### Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 2"

##### Channel Data Length

Channel Data Length: 200

##### Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8	D0	04	00	0E	00	B4

PROACTIVE COMMAND: RECEIVE DATA 2.9.3

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 3"

## Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	33	B7	01	C8						

TERMINAL RESPONSE: RECEIVE DATA 2.9.1

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel Data : 00 01 02 .. C7 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02	..	C7	B7	01	FF	

## 27.22.4.29.2.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.9.

## 27.22.4.29.2.10 RECEIVE DATA (support of Text Attribute – Foreground and Background Colour)

## 27.22.4.29.2.10.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.29.2.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.29.2.10.3 Test purpose

To verify that the ME shall display the alpha identifier according to the foreground and background colour text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.10.4 Method of test

##### 27.22.4.29.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.29.2.10.4.2 Procedure

**Expected sequence 2.10 (RECEIVE DATA, with Text Attribute – Foreground and Background Colour)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
15	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
16	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
17	USS → ME	Transfer of 400 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15	
18	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1	(400 Bytes of data in the ME buffer)
19	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.10.1	
20	ME → UICC	FETCH	
21	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.10.1	200 Bytes with alpha identifier is displayed with foreground and background colour
22	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.10.1	
23	UICC → ME	PROACTIVE COMMAND PENDING: RECEIVE DATA 2.10.2	
24	ME → UICC	FETCH	
25	UICC → ME	PROACTIVE COMMAND: RECEIVE DATA 2.10.2	200 Bytes with alpha identifier is displayed with ME's default foreground and background colour
26	ME → UICC	TERMINAL RESPONSE: RECEIVE DATA 2.10.1	

**PROACTIVE COMMAND: SEND DATA 1.1.1**

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

**TERMINAL RESPONSE: SEND DATA 1.1.1**

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

## ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

## PROACTIVE COMMAND: RECEIVE DATA 2.10.1

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 1"

## Channel Data Length

Channel Data Length: 200

## Text Attribute

Formatting position: 0  
 Formatting length: 14  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	22	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	31	B7	01	C8	D0	04	00	0E	00	B4

## PROACTIVE COMMAND: RECEIVE DATA 2.10.2

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Receive Data 2"

## Channel Data Length

Channel Data Length: 200

Coding:

BER-TLV:	D0	1C	81	03	01	42	00	82	02	81	21	85
	0E	52	65	63	65	69	76	65	20	44	61	74
	61	20	32	B7	01	C8						

## TERMINAL RESPONSE: RECEIVE DATA 2.10.1

Logically:

## Command details

Command number: 1  
 Command type: RECEIVE DATA  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully  
 Channel Data : 00 01 02 .. C7 (200 Bytes of data)  
 Channel data length: FF

Coding:

BER-TLV:	81	03	01	42	00	82	02	82	81	83	01	00
	B6	81	C8	00	01	02	..	C7	B7	01	FF	

#### 27.22.4.29.2.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.10.

### 27.22.4.30 SEND DATA

#### 27.22.4.30.1 SEND DATA (normal)

##### 27.22.4.30.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.30.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.30.1.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (Command Performed Successfully); or
- TERMINAL RESPONSE (ME currently unable to process command); or
- TERMINAL RESPONSE (Bearer Independent Protocol Error);
- TERMINAL RESPONSE (Proactive USIM session terminated by the user);

to the UICC after the ME receives the SEND DATA proactive command. The TERMINAL RESPONSE sent back to the UICC is the result of the ME and the network capabilities against requested parameters by the UICC.

##### 27.22.4.30.1.4 Method of test

###### 27.22.4.30.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME's default channel identifier as declared in table A.2/27

The following Bearer Parameters used are those defined in the default Test PDP context for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

#### 27.22.4.30.1.4.2 Procedure

#### Expected sequence 1.1 (SEND DATA, immediate mode)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
11	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	
12	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]

#### PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

##### Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

##### Device identities

Source device: UICC  
 Destination device: ME

##### Bearer

Bearer type: GPRS

Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer  
 Buffer size: 1000  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)

UICC/ME interface transport level  
 Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

Coding:

BER-TLV	D0	42	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	03	E8
	47	0A	06	54	65	73	74	47	70	02	72	73
	0D	08	F4	55	73	65	72	4C	6F	67	0D	08
	F4	55	73	65	72	50	77	64	3C	03	01	AD
	9C	3E	05	21	01	01	01					

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details  
 Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities  
 Source device: ME  
 Destination device: UICC

Result  
 General Result: Command performed successfully

Channel status  
 Channel identifier 1 and link established or PDP context activated

Bearer description  
 Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer  
 Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	03	E8							

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Channel status

Channel identifier 1 and link established or PDP context activated

## Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1000

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							

## PROACTIVE COMMAND: SEND DATA 1.1.1

## Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: UICC  
 Destination device: Channel 1

## Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

## Coding:

BER-TLV:	D0	13	81	03	01	43	01	82	02	81	21	B6
	08	00	01	02	03	04	05	06	07			

## TERMINAL RESPONSE: SEND DATA 1.1.1

## Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

**Expected sequence 1.2 (SEND DATA, Store mode)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.2.1	Send 500 Bytes of data (200 + 200 + 100)
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.2.1	[Command performed successfully]
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.2.1	
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.2.2	[200 Bytes]
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.2.2	[Command performed successfully]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.2.2	
16	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.2.3	[100 Bytes]
17	ME → UICC	FETCH	
18	UICC → ME	PROACTIVE COMMAND: SEND DATA (Immediate mode) 1.2.3	Transfer of 500 Bytes of data to the USS through channel 1
19	ME → USS		
20	ME → UICC	TERMINAL RESPONSE: SEND DATA (Immediate mode) 1.2.3	[Command performed successfully]

**PROACTIVE COMMAND: SEND DATA 1.2.1**

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Store mode

Device identities

Source device: UICC  
 Destination device: Channel 1

Channel Data

Channel Data : 00 01 .. C7 (200 Bytes of data)

Coding:

BER-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
	B6	81	C8	00	01	..	C7					

## TERMINAL RESPONSE: SEND DATA 1.2.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Store mode

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
	B7	01	FF									

## PROACTIVE COMMAND: SEND DATA 1.2.2

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Store mode

## Device identities

Source device: UICC  
 Destination device: Channel 1

## Channel Data

Channel Data : C8 C9 .. FF 00 01 .. 8F (200 Bytes of data)

Coding:

BER-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
	B6	81	C8	C8	C9	..	FF	00	01	..	8F	

## TERMINAL RESPONSE: SEND DATA 1.2.2

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Store mode

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
	B7	01	FF									

## PROACTIVE COMMAND: SEND DATA 1.2.3

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Immediate mode

## Device identities

Source device: UICC  
 Destination device: Channel 1

## Channel Data

Channel Data : 90 91 .. F3 (100 Bytes of data)

## Coding:

BER-TLV:	D0	6F	81	03	01	43	01	82	02	81	21	B6
	64	90	91	..	F3							

TERMINAL RESPONSE: SEND DATA 1.2.3

## Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Immediate mode

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

## Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

**Expected sequence 1.3 (SEND DATA, Store mode, Tx buffer fully used)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.1	Send 1000 Bytes of data by packet of 200 Bytes
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.1	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.2	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.2	[200 Bytes]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.2	[Command performed successfully]
16	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.3	
17	ME → UICC	FETCH	
18	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.3	[200 Bytes]
19	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.3	[Command performed successfully]
20	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.4	
21	ME → UICC	FETCH	
22	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.4	[200 Bytes]
23	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.4	[Command performed successfully]
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.5	
25	ME → UICC	FETCH	
26	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.3.5	[200 Bytes]
27	ME → USS	Transfer of 1000 Bytes of data to the USS through channel 1	
28	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.3.5	[Command performed successfully]

**PROACTIVE COMMAND: SEND DATA 1.3.1**

Logically:

## Command details

Command number: 1  
Command type: SEND DATA  
Command qualifier: Store mode

## Device identities

Source device: UICC  
Destination device: Channel 1

## Channel Data

Channel Data : 00 01 02 .. C7 (200 Bytes of data)

## Coding:

BER-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
	B6	81	C8	00	01	02	...	C7				

## TERMINAL RESPONSE: SEND DATA 1.3.1

## Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Store mode

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

## Coding:

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
	B7	01	FF									

## PROACTIVE COMMAND: SEND DATA 1.3.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Store mode

## Device identities

Source device: UICC  
 Destination device: Channel 1

## Channel Data

Channel Data : C8 C9 CA .. FF 00 01 .. 8F (200 Bytes of data)

## Coding:

BER-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
	B6	81	C8	C8	C9	CA	...	FF	00	02	..	8F

## TERMINAL RESPONSE: SEND DATA 1.3.2

## Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Store mode

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
	B7	01	FF									

PROACTIVE COMMAND: SEND DATA 1.3.3

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Store mode

## Device identities

Source device: UICC  
 Destination device: Channel 1

## Channel Data

Channel Data : 90 91 .. FF 00 01 .. 57 (200 Bytes of data)

Coding:

BER-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
	B6	81	C8	90	91	..	FF	00	01	..	57	

TERMINAL RESPONSE: SEND DATA 1.3.3

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Store mode

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
	B7	01	FF									

PROACTIVE COMMAND: SEND DATA 1.3.4

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Store mode

## Device identities

Source device: UICC  
 Destination device: Channel 1

## Channel Data

Channel Data : 58 59 .. FF 00 01 .. 1F (200 Bytes of data)

Coding:

BER-TLV:	D0	81	D4	81	03	01	43	00	82	02	81	21
	B6	81	C8	58	59	..	FF	00	01	..	1F	

TERMINAL RESPONSE: SEND DATA 1.3.4

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Store mode

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel data length: 200 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	00	82	02	82	81	83	01	00
	B7	01	C8									

PROACTIVE COMMAND: SEND DATA 1.3.5

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

Device identities

Source device: UICC  
 Destination device: Channel 1

Channel Data

Channel Data: 20 21 .. E7 (200 Bytes of data)

Coding:

BER-TLV:	D0	81	D4	81	03	01	43	01	82	02	81	21
	B6	81	C8	20	21	..	E7					

TERMINAL RESPONSE: SEND DATA 1.3.5

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

## Expected sequence 1.4 (SEND DATA, 2 consecutive SEND DATA Store mode)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.1	Send 1000 Bytes of data by packet of 200 Bytes
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.1	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.2	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.2	[200 Bytes]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.2	[Command performed successfully]
16	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.3	
17	ME → UICC	FETCH	
18	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.3	[200 Bytes]
19	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.3	[Command performed successfully]
20	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.4	
21	ME → UICC	FETCH	
22	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.4	[200 Bytes]
23	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.4	[Command performed successfully]
24	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.5	...
25	ME → UICC	FETCH	
26	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.3.5	[200 Bytes]
27	ME → USS	Transfer of 1000 Bytes of data to the USS through channel 1	
28	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.3.5	[Command performed successfully]
29	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.1	
30	ME → UICC	FETCH	
31	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.1	Send 1000 Bytes of data by packet of 200 Bytes
32	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.1	[Command performed successfully]
33	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.2	
34	ME → UICC	FETCH	
35	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.2	[200 Bytes]
36	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.2	[Command performed successfully]

37	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.3	
38	ME → UICC	FETCH	
39	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.3	[200 Bytes]
40	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.3	[Command performed successfully]
41	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.4	
42	ME → UICC	FETCH	
43	UICC → ME	PROACTIVE COMMAND: SEND DATA (store mode) 1.3.4	[200 Bytes]
44	ME → UICC	TERMINAL RESPONSE: SEND DATA (store mode) 1.3.4	[Command performed successfully]
45	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.3.5	...
46	ME → UICC	FETCH	
47	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.3.5	[200 Bytes]
48	ME → USS	Transfer of 1000 Bytes of data to the USS through channel 1	
49	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.3.5	[Command performed successfully]

#### Expected sequence 1.5 (SEND DATA, immediate mode with a bad channel identifier)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.5.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.5.1	
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.5.1	[Invalid channel number]

#### PROACTIVE COMMAND: SEND DATA 1.5.1

Logically:

##### Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

##### Device identities

Source device: UICC  
 Destination device: Channel 2

##### Channel Data

Channel Data : 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	13	81	03	01	43	01	82	02	81	22	B6
	08	00	01	02	03	04	05	06	07			

TERMINAL RESPONSE: SEND DATA 1.5.1

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Bearer Independent Protocol error (3A)  
 Additional Result: Channel identifier not valid (03)

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	02	3A
	03											

**Expected sequence 1.6 Void**

27.22.4.30.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.5.

27.22.4.30.2 SEND DATA (support of Text Attribute)

27.22.4.30.2.1 SEND DATA (support of Text Attribute – Left Alignment)

27.22.4.30.2.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.30.2.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

27.22.4.30.2.1.3 Test purpose

To verify that the ME shall display the alpha identifier according to the left alignment text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.1.4 Method of test

27.22.4.30.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The

corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

#### 27.22.4.30.2.1.4.2 Procedure

#### Expected sequence 2.1 (SEND DATA with Text Attribute – Left Alignment)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND	See initial conditions
2	ME → UICC	PENDING: OPEN CHANNEL 1.1.1 FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	[Command performed successfully]
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.1.1	
9	ME → UICC	FETCH	[alpha identifier shall be displayed with left alignment]
10	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.1.1	
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.1.1	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.1.2	[Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/22, no alignment change will take place]
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.1.2	
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.1.1	[Command performed successfully]

PROACTIVE COMMAND: SEND DATA 2.1.1

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately  
 Device identities  
   Source device: UICC  
   Destination device: Channel 1  
 Alpha Identifier "Send Data 1"  
 Channel Data  
   Channel Data: 00 01 .. 07 (8 Bytes of data)  
 Text Attribute  
   Formatting position: 0  
   Formatting length: 11  
   Formatting mode: Left Alignment, Normal Font, Bold On, Italic On, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

PROACTIVE COMMAND: SEND DATA 2.1.2

Logically:

Command details  
   Command number: 1  
   Command type: SEND DATA  
   Command qualifier: Send Immediately  
 Device identities  
   Source device: UICC  
   Destination device: Channel 1  
 Alpha Identifier "Send Data 2"  
 Channel Data  
   Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.1.1

Logically:

Command details  
   Command number: 1  
   Command type: SEND DATA  
   Command qualifier: Send Immediately  
 Device identities  
   Source device: ME  
   Destination device: UICC  
 Result  
   General Result: Command performed successfully  
   Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

## 27.22.4.30.2.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1.

## 27.22.4.30.2.2 SEND DATA (support of Text Attribute – Center Alignment)

## 27.22.4.30.2.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.30.2.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

## 27.22.4.30.2.2.3 Test purpose

To verify that the ME shall display the alpha identifier according to the center alignment text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

## 27.22.4.30.2.2.4 Method of test

## 27.22.4.30.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

## Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

## GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

## UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

27.22.4.30.2.2.4.2 Procedure

**Expected sequence 2.2 (SEND DATA with Text Attribute – Center Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.2.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.2.1	[alpha identifier shall be displayed with center alignment]
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.2.1	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.2.2	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.2.2	[Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/22, no alignment change will take place]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.2.1	[Command performed successfully]

PROACTIVE COMMAND: SEND DATA 2.2.1

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier

"Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Center Alignment, Normal Font, Bold On, Italic On, Underline Off,  
 Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	01	B4								

## PROACTIVE COMMAND: SEND DATA 2.2.2

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: UICC  
 Destination device: Channel 1

## Alpha Identifier

"Send Data 2"

## Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07		

## TERMINAL RESPONSE: SEND DATA 2.2.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

## 27.22.4.30.2.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.2.

## 27.22.4.30.2.3 SEND DATA (support of Text Attribute – Right Alignment)

## 27.22.4.30.2.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.30.2.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

### 27.22.4.30.2.3.3 Test purpose

To verify that the ME shall display the alpha identifier according to the right alignment text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

### 27.22.4.30.2.3.4 Method of test

#### 27.22.4.30.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

27.22.4.30.2.3.4.2 Procedure

**Expected sequence 2.3 (SEND DATA with Text Attribute – Right Alignment)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.3.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.3.1	[alpha identifier shall be displayed with right alignment]
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.3.1	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.3.2	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.3.2	[Message shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/22, no alignment change will take place]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.3.1	[Command performed successfully]

PROACTIVE COMMAND: SEND DATA 2.3.1

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier

"Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Right Alignment, Normal Font, Bold On, Italic On, Underline Off,  
 Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	02	B4								

## PROACTIVE COMMAND: SEND DATA 2.3.2

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: UICC  
 Destination device: Channel 1

## Alpha Identifier

"Send Data 2"

## Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07		

## TERMINAL RESPONSE: SEND DATA 2.3.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

## 27.22.4.30.2.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.3.

## 27.22.4.30.2.4 SEND DATA (support of Text Attribute – Large Font Size)

## 27.22.4.30.2.4.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.30.2.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

#### 27.22.4.30.2.4.3 Test purpose

To verify that the ME shall display the alpha identifier according to the large font size text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.30.2.4.4 Method of test

##### 27.22.4.30.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.30.2.4.4.2 Procedure

**Expected sequence 2.4 (SEND DATA with Text Attribute – Large Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.4.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.4.1	[alpha identifier shall be displayed with large font size]
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.4.1	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.4.2	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.4.2	[alpha identifier shall be displayed with normal font size]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.4.1	[Command performed successfully]
16	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.4.1	
17	ME → UICC	FETCH	
18	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.4.1	[alpha identifier shall be displayed with large font size]
19	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.4.1	[Command performed successfully]
20	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.4.3	
21	ME → UICC	FETCH	
22	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.4.3	[alpha identifier shall be displayed with normal font size]
23	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.4.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND DATA 2.4.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Send Data 1"

## Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

## Text Attribute

Formatting position: 0  
 Formatting length: 11

Formatting mode: Left Alignment, Large Font, Bold On, Italic On, Underline Off,  
Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	04	B4								

PROACTIVE COMMAND: SEND DATA 2.4.2

Logically:

Command details

Command number: 1  
Command type: SEND DATA  
Command qualifier: Send Immediately

Device identities

Source device: UICC  
Destination device: Channel 1

Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0  
Formatting length: 11  
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

PROACTIVE COMMAND: SEND DATA 2.4.3

Logically:

Command details

Command number: 1  
Command type: SEND DATA  
Command qualifier: Send Immediately

Device identities

Source device: UICC  
Destination device: Channel 1

Alpha Identifier "Send Data 3"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	B6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.4.1

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

#### 27.22.4.30.2.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.4.

#### 27.22.4.30.2.5 SEND DATA (support of Text Attribute – Small Font Size)

##### 27.22.4.30.2.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.30.2.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.30.2.5.3 Test purpose

To verify that the ME shall display the alpha identifier according to the small font size text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

##### 27.22.4.30.2.5.4 Method of test

###### 27.22.4.30.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04

Mean throughput class: 31  
 Packet data protocol:02 (IP)

## GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

UICC/ME interface transport level

Transport format:UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

## 27.22.4.30.2.5.4.2 Procedure

**Expected sequence 2.5 (SEND DATA with Text Attribute – Small Font Size)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.5.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.5.1	[alpha identifier shall be displayed with small font size]
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.5.1	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.5.2	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.5.2	[alpha identifier shall be displayed with normal font size]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.5.1	[Command performed successfully]
16	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.5.1	
17	ME → UICC	FETCH	
18	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.5.1	[alpha identifier shall be displayed with small font size]
19	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.5.1	[Command performed successfully]
20	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.5.3	
21	ME → UICC	FETCH	
22	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.5.3	[alpha identifier shall be displayed with normal font size]
23	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.5.1	[Command performed successfully]

PROACTIVE COMMAND: SEND DATA 2.5.1

Logically:

Command details

Command number: 1

Command type: SEND DATA  
 Command qualifier: Send Immediately  
 Device identities  
 Source device: UICC  
 Destination device: Channel 1  
 Alpha Identifier "Send Data 1"  
 Channel Data  
 Channel Data: 00 01 .. 07 (8 Bytes of data)  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Small Font, Bold On, Italic On, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	08	B4								

#### PROACTIVE COMMAND: SEND DATA 2.5.2

Logically:

Command details  
 Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately  
 Device identities  
 Source device: UICC  
 Destination device: Channel 1  
 Alpha Identifier "Send Data 2"  
 Channel Data  
 Channel Data: 00 01 .. 07 (8 Bytes of data)  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

#### PROACTIVE COMMAND: SEND DATA 2.5.3

Logically:

Command details  
 Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately  
 Device identities  
 Source device: UICC  
 Destination device: Channel 1  
 Alpha Identifier "Send Data 3"

## Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

## Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	B6	08	00	01	02	03	04	05	06	07		

## TERMINAL RESPONSE: SEND DATA 2.5.1

## Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

## Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

## 27.22.4.30.2.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.5.

## 27.22.4.30.2.6 SEND DATA (support of Text Attribute – Bold On)

## 27.22.4.30.2.6.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.30.2.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

## 27.22.4.30.2.6.3 Test purpose

To verify that the ME shall display the alpha identifier according to the bold text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

## 27.22.4.30.2.6.4 Method of test

## 27.22.4.30.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The

corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.30.2.6.4.2 Procedure

**Expected sequence 2.6 (SEND DATA with Text Attribute – Bold On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.6.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.6.1	[alpha identifier shall be displayed with Bold on]
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.6.1	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.6.2	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.6.2	[alpha identifier shall be displayed with bold off]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.6.1	[Command performed successfully]
16	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.6.1	
17	ME → UICC	FETCH	
18	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.6.1	[alpha identifier shall be displayed with bold on]
19	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.6.1	[Command performed successfully]
20	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.6.3	
21	ME → UICC	FETCH	
22	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.6.3	[alpha identifier shall be displayed with bold off]
23	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.6.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND DATA 2.6.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Send Data 1"

## Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

## Text Attribute

Formatting position: 0

Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold On , Italic Off, Underline Off,  
Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	10	B4								

#### PROACTIVE COMMAND: SEND DATA 2.6.2

Logically:

##### Command details

Command number: 1  
Command type: SEND DATA  
Command qualifier: Send Immediately

##### Device identities

Source device: UICC  
Destination device: Channel 1

Alpha Identifier "Send Data 2"

##### Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

##### Text Attribute

Formatting position: 0  
Formatting length: 11  
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

#### PROACTIVE COMMAND: SEND DATA 2.6.3

Logically:

##### Command details

Command number: 1  
Command type: SEND DATA  
Command qualifier: Send Immediately

##### Device identities

Source device: UICC  
Destination device: Channel 1

Alpha Identifier "Send Data 3"

##### Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	B6	08	00	01	02	03	04	05	06	07		

#### TERMINAL RESPONSE: SEND DATA 2.6.1

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

#### 27.22.4.30.2.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.6.

#### 27.22.4.30.2.7 SEND DATA (support of Text Attribute – Italic On)

##### 27.22.4.30.2.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.30.2.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.30.2.7.3 Test purpose

To verify that the ME shall display the alpha identifier according to the italic text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

##### 27.22.4.30.2.7.4 Method of test

###### 27.22.4.30.2.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31

Packet data protocol:02 (IP)

GPRS Parameters

Network access name: TestGp.rs

User login: UserLog

User password: UserPwd

UICC/ME interface transport level

Transport format:UDP

Port number: 44444

Data destination address 01.01.01.01

27.22.4.30.2.7.4.2 Procedure

### Expected sequence 2.7 (SEND DATA with Text Attribute – Italic On)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.7.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.7.1	[alpha identifier shall be displayed with Italic on]
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.7.1	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.7.2	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.7.2	[alpha identifier shall be displayed with italic off]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.7.1	[Command performed successfully]
16	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.7.1	
17	ME → UICC	FETCH	
18	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.7.1	[alpha identifier shall be displayed with italic on]
19	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.7.1	[Command performed successfully]
20	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.7.3	
21	ME → UICC	FETCH	
22	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.7.3	[alpha identifier shall be displayed with italic off]
23	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.7.1	[Command performed successfully]

PROACTIVE COMMAND: SEND DATA 2.7.1

Logically:

Command details

Command number: 1

Command type: SEND DATA

Command qualifier: Send Immediately

Device identities

Source device: UICC

Destination device: Channel 1

Alpha Identifier "Send Data 1"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0

Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	20	B4								

#### PROACTIVE COMMAND: SEND DATA 2.7.2

Logically:

Command details

Command number: 1

Command type: SEND DATA

Command qualifier: Send Immediately

Device identities

Source device: UICC

Destination device: Channel 1

Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0

Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

#### PROACTIVE COMMAND: SEND DATA 2.7.3

Logically:

Command details

Command number: 1

Command type: SEND DATA

Command qualifier: Send Immediately

Device identities

Source device: UICC

Destination device: Channel 1

Alpha Identifier "Send Data 3"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	B6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.7.1

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

#### 27.22.4.30.2.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.7.

#### 27.22.4.30.2.8 SEND DATA (support of Text Attribute – Underline On)

##### 27.22.4.30.2.8.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.30.2.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.30.2.8.3 Test purpose

To verify that the ME shall display the alpha identifier according to the underline text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

##### 27.22.4.30.2.8.4 Method of test

###### 27.22.4.30.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.30.2.8.4.2 Procedure

**Expected sequence 2.8 (SEND DATA with Text Attribute – Underline On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.8.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.8.1	[alpha identifier shall be displayed with underline on]
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.8.1	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.8.2	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.8.2	[alpha identifier shall be displayed with underline off]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.8.1	[Command performed successfully]
16	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.8.1	
17	ME → UICC	FETCH	
18	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.8.1	[alpha identifier shall be displayed with underline on]
19	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.8.1	[Command performed successfully]
20	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.8.3	
21	ME → UICC	FETCH	
22	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.8.3	[alpha identifier shall be displayed with underline off]
23	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.8.1	[Command performed successfully]

## PROACTIVE COMMAND: SEND DATA 2.8.1

Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Send Data 1"

## Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

## Text Attribute

Formatting position: 0  
 Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	40	B4								

PROACTIVE COMMAND: SEND DATA 2.8.2

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Send Data 2"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute

Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

PROACTIVE COMMAND: SEND DATA 2.8.3

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

Device identities

Source device: UICC  
 Destination device: Channel 1

Alpha Identifier "Send Data 3"

Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	B6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.8.1

Logically:

Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

#### 27.22.4.30.2.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.8.

#### 27.22.4.30.2.9 SEND DATA (support of Text Attribute – Strikethrough On)

##### 27.22.4.30.2.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.30.2.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

##### 27.22.4.30.2.9.3 Test purpose

To verify that the ME shall display the alpha identifier according to the strikethrough text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

##### 27.22.4.30.2.9.4 Method of test

###### 27.22.4.30.2.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04

Mean throughput class: 31  
 Packet data protocol:02 (IP)

## GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

UICC/ME interface transport level

Transport format:UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

## 27.22.4.30.2.9.4.2 Procedure

**Expected sequence 2.9 (SEND DATA with Text Attribute – Strikethrough On)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.9.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.9.1	[alpha identifier shall be displayed with strikethrough on]
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.9.1	[Command performed successfully]
12	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.9.2	
13	ME → UICC	FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.9.2	[alpha identifier shall be displayed with strikethrough off]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.9.1	[Command performed successfully]
16	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.9.1	
17	ME → UICC	FETCH	
18	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.9.1	[alpha identifier shall be displayed with strikethrough on]
19	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.9.1	[Command performed successfully]
20	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 2.9.3	
21	ME → UICC	FETCH	
22	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.9.3	[alpha identifier shall be displayed with strikethrough off]
23	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.9.1	[Command performed successfully]

PROACTIVE COMMAND: SEND DATA 2.9.1

Logically:

Command details

Command number: 1

Command type: SEND DATA  
 Command qualifier: Send Immediately  
 Device identities  
 Source device: UICC  
 Destination device: Channel 1  
 Alpha Identifier "Send Data 1"  
 Channel Data  
 Channel Data: 00 01 .. 07 (8 Bytes of data)  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	80	B4								

#### PROACTIVE COMMAND: SEND DATA 2.9.2

Logically:

Command details  
 Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately  
 Device identities  
 Source device: UICC  
 Destination device: Channel 1  
 Alpha Identifier "Send Data 2"  
 Channel Data  
 Channel Data: 00 01 .. 07 (8 Bytes of data)  
 Text Attribute  
 Formatting position: 0  
 Formatting length: 11  
 Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

#### PROACTIVE COMMAND: SEND DATA 2.9.3

Logically:

Command details  
 Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately  
 Device identities  
 Source device: UICC  
 Destination device: Channel 1  
 Alpha Identifier "Send Data 3"

## Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

## Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	33
	B6	08	00	01	02	03	04	05	06	07		

## TERMINAL RESPONSE: SEND DATA 2.9.1

## Logically:

## Command details

Command number: 1  
 Command type: SEND DATA  
 Command qualifier: Send Immediately

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully  
 Channel data length: More than 255 bytes of space available in the Tx buffer

## Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

## 27.22.4.30.2.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.9.

## 27.22.4.30.2.10 SEND DATA (support of Text Attribute – Foreground and Background Colour)

## 27.22.4.30.2.10.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.30.2.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

## 27.22.4.30.2.10.3 Test purpose

To verify that the ME shall display the alpha identifier according to the foreground and background colour text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

## 27.22.4.30.2.10.4 Method of test

## 27.22.4.30.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The

corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

#### Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

#### GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

#### UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

#### 27.22.4.30.2.10.4.2 Procedure

### Expected sequence 2.10 (SEND DATA with Text Attribute – Foreground and Background Colour)

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND	See initial conditions
2	ME → UICC	PENDING: OPEN CHANNEL 1.1.1 FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	[Command performed successfully]
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	[Command performed successfully]
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
8	UICC → ME	PROACTIVE COMMAND	[alpha identifier shall be displayed with foreground and background colour according to the text attribute configuration]
9	ME → UICC	PENDING: SEND DATA 2.10.1 FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.10.1	[Command performed successfully]
11	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.10.1	
12	UICC → ME	PROACTIVE COMMAND	[alpha identifier shall be displayed with ME's default foreground and background colour]
13	ME → UICC	PENDING: SEND DATA 2.10.2 FETCH	
14	UICC → ME	PROACTIVE COMMAND: SEND DATA 2.10.2	[Command performed successfully]
15	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 2.10.1	

PROACTIVE COMMAND: SEND DATA 2.10.1

Logically:

Command details

Command number: 1

Command type: SEND DATA  
 Command qualifier: Send Immediately  
 Device identities  
   Source device: UICC  
   Destination device: Channel 1  
 Alpha Identifier "Send Data 1"  
 Channel Data  
   Channel Data: 00 01 .. 07 (8 Bytes of data)  
 Text Attribute  
   Formatting position: 0  
   Formatting length: 11  
   Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off,  
   Strikethrough Off  
 Colour: Dark Green Foreground, Bright Yellow Background

Coding:

BER-TLV:	D0	26	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	31
	B6	08	00	01	02	03	04	05	06	07	D0	04
	00	0B	00	B4								

PROACTIVE COMMAND: SEND DATA 2.10.2

Logically:

Command details  
   Command number: 1  
   Command type: SEND DATA  
   Command qualifier: Send Immediately  
 Device identities  
   Source device: UICC  
   Destination device: Channel 1  
 Alpha Identifier "Send Data 2"  
 Channel Data  
   Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

BER-TLV:	D0	20	81	03	01	43	01	82	02	81	21	85
	0B	53	65	6E	64	20	44	61	74	61	20	32
	B6	08	00	01	02	03	04	05	06	07		

TERMINAL RESPONSE: SEND DATA 2.10.1

Logically:

Command details  
   Command number: 1  
   Command type: SEND DATA  
   Command qualifier: Send Immediately  
 Device identities  
   Source device: ME  
   Destination device: UICC  
 Result  
   General Result: Command performed successfully  
   Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

## 27.22.4.30.2.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.10.

## 27.22.4.31 GET CHANNEL STATUS

## 27.22.4.31.1 Definition and applicability

See clause 3.2.2.

## 27.22.4.31.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

## 27.22.4.31.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC after the ME receives the GET STATUS proactive command. The TERMINAL RESPONSE sent back to the UICC is function of the ME and the network capabilities against asked parameters by the UICC.

## 27.22.4.31.4 Method of test

## 27.22.4.31.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context<sup>3</sup>, for test cases using packet services:

## Bearer Parameters

Precedence Class: 03  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

## GPRS Parameters

Network access name: TestGp.rs  
User login: UserLog  
User password: UserPwd

## UICC/ME interface transport level

Transport format: UDP  
Port number: 44444  
Data destination address 01.01.01.01

## 27.22.4.31.4.2 Procedure

**Expected sequence 1.1 (GET STATUS, without any BIP channel opened)**

For that test, no channel has been opened.

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: GET CHANNEL STATUS 1.1.1	[Command performed successfully]
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: GET STATUS 1.1.1	
4	ME → UICC	TERMINAL RESPONSE GET STATUS 1.1.1 A Or TERMINAL RESPONSE: GET STATUS 1.1.1B Or TERMINAL RESPONSE: GET STATUS 1.1.1C	

PROACTIVE COMMAND: GET STATUS 1.1.1

Logically:

Command details

Command number: 1  
 Command type: GET STATUS  
 Command qualifier: RFU

Device identities

Source device: UICC  
 Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	44	00	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: GET STATUS 1.1.1A

Logically:

Command details

Command number: 1  
 Command type: GET STATUS  
 Command qualifier: RFU

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: GET STATUS 1.1.1B

Logically:

Command details

Command number: 1  
 Command type: GET STATUS  
 Command qualifier: RFU

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Channel status

Channel status: No Channel available, link not established or PDP context not activated

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
	B8	02	00	00								

TERMINAL RESPONSE: GET STATUS 1.1.1C

Logically:

Command details

Command number: 1  
 Command type: GET STATUS  
 Command qualifier: RFU

Device identities

Source device: ME  
 Destination device: SIM

Result

General Result: Command performed successfully

Channel status

Channel 1 status: Channel identifier 1, Link not established or PDP context not activated

Channel 2 status: Channel identifier 2, Link not established or PDP context not activated

.

.

Channel n status: Channel identifier n, Link not established or PDP context not activated

The number of channel status data objects shall be same as the number of channels(n) supported by the ME

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
	Note1											

Note1: The Terminal Response shall contain as many channel status TLVs as channels are supported by the ME. Each channel status TLV coding shall indicate the corresponding channel identifier and shall state "Link not established or PDP context not activated". As an example, if the mobile supports two channels then the corresponding channel status data objects coding would be : 'B8 02 01 00 B8 02 02 00'.

**Expected sequence 1.2 (GET STATUS, with a BIP channel currently opened)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
4	ME → USS	PDP context activation request	
5	USS → ME	PDP context activation accept	
6	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
7	UICC → ME	PROACTIVE COMMAND PENDING: GET CHANNEL STATUS 1.2.1	
8	ME → UICC	FETCH	
9	UICC → ME	PROACTIVE COMMAND: GET STATUS 1.2.1	
10	ME → UICC	TERMINAL RESPONSE GET STATUS 1.2.1 A Or TERMINAL RESPONSE: GET STATUS 1.2.1B	[Command performed successfully]

**PROACTIVE COMMAND: OPEN CHANNEL 1.1.1**

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1000

## Network access name:

TestGp.rs

## Text String:

UserLog (User login)

## Text String:

UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

## Data destination address

01.01.01.01

Coding:

BER-TLV	D0	42	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	03	E8

47	0A	06	54	65	73	74	47	70	02	72	73
0D	08	F4	55	73	65	72	4C	6F	67	0D	08
F4	55	73	65	72	50	77	64	3C	03	01	AD
9C	3E	05	21	01	01	01	01				

## TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Channel status

Channel identifier 1 and link established or PDP context activated

## Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	03	E8							

## TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Channel status

Channel identifier 1 and link established or PDP context activated

## Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							

PROACTIVE COMMAND: GET STATUS 1.2.1

Logically:

## Command details

Command number: 1  
 Command type: GET STATUS  
 Command qualifier: RFU

## Device identities

Source device: UICC  
 Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	44	00	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: GET STATUS 1.2.1A

Logically:

## Command details

Command number: 1  
 Command type: GET STATUS  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Channel status

Channel status: Channel 1 open, link established or PDP context activated

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
	B8	02	81	00								

TERMINAL RESPONSE: GET STATUS 1.2.1B

Logically:

## Command details

Command number: 1  
 Command type: GET STATUS  
 Command qualifier: RFU

## Device identities

Source device: ME  
 Destination device: SIM

## Result

General Result: Command performed successfully

## Channel status

Channel 1 status: Channel identifier 1 open, Link established or PDP context activated

Channel 2 status: Channel identifier 2, Link not established or PDP context not activated

Channel n status: Channel identifier n, Link not established or PDP context not activated

The number of channel status data objects shall be same as the number of channels(n) supported by the ME

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
	Note1											

Note1: The Terminal Response shall contain as many channel status TLVs as channels are supported by the ME. The channel status TLV coding of the opened channel shall state "Link established or PDP context activated". Each other channel status TLV coding shall indicate the corresponding channel identifier and shall state "Link is not established or PDP context not activated". As an example, if the mobile supports two channels and channel 1 is opened then the corresponding channel status data objects coding would be : 'B8 02 81 00 B8 02 02 00'.

**Expected sequence 1.3 (GET STATUS, after a link dropped)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	[Command performed successfully]
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USS	PDP context activation request	
9	USS → ME	PDP context activation accept	
10	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
11	USS → ME	DROP LINK	
12	ME → UICC	ENVELOPE EVENT DOWNLOAD: CHANNEL STATUS 1.3.1	[Link dropped]
13	UICC → ME	PROACTIVE COMMAND PENDING: GET STATUS 1.3.1	
14	ME → UICC	FETCH	
15	UICC → ME	PROACTIVE COMMAND: GET STATUS 1.3.1	
16	ME → UICC	TERMINAL RESPONSE: GET STATUS 1.3.1A Or TERMINAL RESPONSE: GET STATUS 1.3.1B Or TERMINAL RESPONSE: GET STATUS 1.3.1C Or TERMINAL RESPONSE: GET STATUS 1.3.1D Or TERMINAL RESPONSE: GET STATUS 1.3.1E	[Command performed successfully]

TERMINAL RESPONSE: GET STATUS 1.3.1A

Same as TERMINAL RESPONSE: GET STATUS 1.1.1A

TERMINAL RESPONSE: GET STATUS 1.3.1B

Same as TERMINAL RESPONSE: GET STATUS 1.1.1B

TERMINAL RESPONSE: GET STATUS 1.3.1C

Same as TERMINAL RESPONSE: GET STATUS 1.1.1C

TERMINAL RESPONSE: GET STATUS 1.3.1D

Logically:

Command details

Command number: 1  
 Command type: GET STATUS  
 Command qualifier: RFU

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Channel status

Channel status: Channel 1, link dropped

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
	B8	02	01	05								

TERMINAL RESPONSE: GET STATUS 1.3.1E

Logically:

Command details

Command number: 1  
 Command type: GET STATUS  
 Command qualifier: RFU

Device identities

Source device: ME  
 Destination device: SIM

Result

General Result: Command performed successfully

Channel status

Channel 1 status: Channel identifier 1, link dropped

Channel 2 status: Channel identifier 2, Link not established or PDP context not activated

.

.

Channel n status: Channel identifier n, Link not established or PDP context not activated

The number of channel status data objects shall be same as the number of channels(n) supported by the ME

Coding:

BER-TLV:	81	03	01	44	00	82	02	82	81	83	01	00
	B8	02	01	05	Note1							

Note1: The Terminal Response shall contain as many channel status TLVs as channels are supported by the ME. Each channel status TLV coding except that one for which the link was dropped by the SS shall indicate the corresponding channel identifier and shall state "Link not established or PDP context not activated". As an example, if the mobile supports two channels then the corresponding channel status data objects coding would be : 'B8 02 01 05 B8 02 02 00'.

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: UICC

Destination device: ME

Event list

Event 1: Channel Status

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82
	99	01	0A								

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST

Command qualifier: '00'

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### ENVELOPE EVENT DOWNLOAD: CHANNEL STATUS 1.3.1

Logically:

Event list

Event list: Channel Status

Device identities

Source device: ME

Destination device: UICC

Channel status

Channel status: Channel 1, link dropped

Coding:

BER-TLV:	D6	0B	99	01	0A	82	02	82	81	B8	02	01
	05											

#### PROACTIVE COMMAND: GET STATUS 1.3.1

Logically:

Command details

Command number: 1

Command type: GET STATUS

Command qualifier: RFU

Device identities

Source device: UICC

Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	44	00	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.4.31.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

### 27.22.5 Data Download to UICC

#### 27.22.5.1 SMS-PP Data Download

##### 27.22.5.1.1 Definition and applicability

See clause 3.2.2.

### 27.22.5.1.2 Conformance requirement

The ME shall support the Proactive UICC: SMS-PP Data Download facility as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 5, clause 7.1, clause 8.1, clause 8.7 and clause 8.13.

### 27.22.5.1.3 Test purpose

To verify that the ME transparently passes the "data download via SMS Point-to-point" messages to the UICC.

To verify that the ME returns the RP-ACK message back to the USS, if the UICC responds with '90 00' or '91 XX'.

To verify that the ME returns the RP-ERROR message back to the system Simulator, if the UICC responds with '62 XX' or '63 XX'.

To verify that the ME returns the response data from the UICC back to the USS in the TP-User-Data element of the RP-ACK message, if the UICC returns response data'.

### 27.22.5.1.4 Method of Test

#### 27.22.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The "data download via SMS-PP" service is available in the USIM Service Table.

#### 27.22.5.1.4.2 Procedure

#### Expected Sequence 1.1 (void)

#### Expected Sequence 1.2 (SMS-PP Data Download, General Data Coding, Acknowledgement)

Step	Direction	MESSAGE / Action	Comments
1	USS → ME	SMS-PP Data Download Message 1.2.1	
2	ME → USER	The ME shall not display the message or alert the user of a short message waiting.	
3	ME → UICC	ENVELOPE: SMS-PP DOWNLOAD 1.2.2	
4	UICC → ME	SMS-PP Data Download UICC Acknowledgement 1.2.4	[SW1 / SW2 of '90 00'
5	ME → USS	SMS-PP Data Download UICC Acknowledgement 1.2.4 in the TP-User-Data element of the RP-ACK message. The values of protocol identifier and data coding scheme in RP-ACK shall be as in the original message.	

**Expected Sequence 1.3 (SMS-PP Data Download, General Data CodingFETCH, MORE TIME)**

Step	Direction	MESSAGE / Action	Comments
1	USS → ME	SMS-PP Data Download Message 1.3.1	
2	ME → USER	The ME shall not display the message or alert the user of a short message waiting	
3	ME → UICC	ENVELOPE: SMS-PP DOWNLOAD 1.3.2	[SW1 / SW2 of '91 0B']
4	UICC → ME	PROACTIVE COMMAND PENDING: MORE TIME 1.3.4	
5	ME → USS	RP-ACK	
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: MORE TIME 1.3.4	
8	ME → UICC	TERMINAL RESPONSE: MORE TIME 1.3.5	
9	UICC → ME	PROACTIVE UICC SESSION ENDED	

**PROACTIVE COMMAND: MORE TIME 1.3.4**

Logically:

Command details

Command number: 1  
 Command type: MORE TIME  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	02	00	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

**TERMINAL RESPONSE: MORE TIME 1.3.5**

Logically:

Command details

Command number: 1  
 Command type: MORE TIME  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	02	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.4 (SMS-PP Data Download, General Data Coding)**

Step	Direction	MESSAGE / Action	Comments
1	USS → ME	SMS-PP Data Download Message 1.4.1	
2	ME	The ME shall not display the message or alert the user of a short message waiting	
3	ME → UICC	ENVELOPE: SMS-PP DOWNLOAD 1.4.2	
4	UICC → ME	SW1 / SW2 of '90 00'	
5	ME → USS	RP-ACK	

SMS-PP (Data Download) Message 1.2.1 / 1.3.1 / 1.4.1

Logically:

SMS TPDU

TP-MTI SMS-DELIVER  
 TP-MMS No more messages waiting for the MS in this SC  
 TP-RP TP-Reply-Path is not set in this SMS-DELIVER  
 TP-UDHI TP-UD field contains only the short message  
 TP-SRI A status report will not be returned to the SME  
 TP-OA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "1234"  
 TP-PID (U)SIM Data download  
 TP-DCS  
 Coding Group General Data Coding  
 Compression Text is uncompressed  
 Message Class Class 2 (U)SIM Specific Message  
 Alphabet 8 bit data  
 TP-SCTS: 01/01/98 00:00:00 +0  
 TP-UDL 13  
 TP-UD "Short Message"

Coding:

Coding	04	04	91	21	43	7F	16	89	10	10	00	00
	00	00	0D	53	68	6F	72	74	20	4D	65	73
	73	61	67	65								

ENVELOPE: SMS-PP DOWNLOAD 1.2.2 / 1.3.2 / 1.4.2

Logically:

SMS-PP Download

Device identities  
 Source device: Network  
 Destination device: UICC  
 Address  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"  
 SMS TPDU  
 TP-MTI SMS-DELIVER  
 TP-MMS No more messages waiting for the MS in this SC  
 TP-RP TP-Reply-Path is not set in this SMS-DELIVER  
 TP-UDHI TP-UD field contains only the short message  
 TP-SRI A status report will not be returned to the SME  
 TP-OA

TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "1234"  
 TP-PID (U)SIM Data download  
 TP-DCS  
 Coding Group General Data Coding  
 Compression Text is uncompressed  
 Message Class Class 2 (U)SIM Specific Message  
 Alphabet 8 bit data  
 TP-SCTS: 01/01/98 00:00:00 +0  
 TP-UDL 13  
 TP-UD "Short Message"

Coding:

BER-TLV:	D1	2D	82	02	83	81	06	09	91	11	22	33
	44	55	66	77	F8	8B	1C	04	04	91	21	43
	7F	16	89	10	10	00	00	00	00	0D	53	68
	6F	72	74	20	4D	65	73	73	61	67	65	

### Expected Sequence 1.5 (void)

### Expected Sequence 1.6 (SMS-PP Data Download, with Data Coding / Message Class)

Step	Direction	MESSAGE / Action	Comments
1	USS → ME	SMS-PP Data Download Message 1.6.1	
2	ME	The ME shall not display the message or alert the user of a short message waiting	
3	ME → UICC	ENVELOPE: SMS-PP DOWNLOAD 1.6.2	
4	UICC → ME	SW1 / SW2 of '90 00'	
5	ME → USS	RP-ACK	

SMS-PP (Data Download) Message 1.6.1

Logically:

SMS TPDU

TP-MTI SMS-DELIVER  
 TP-MMS No more messages waiting for the MS in this SC  
 TP-RP TP-Reply-Path is not set in this SMS-DELIVER  
 TP-UDHI TP-UD field contains only the short message  
 TP-SRI A status report will not be returned to the SME  
 TP-OA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "1234"  
 TP-PID (U)SIM Data download  
 TP-DCS  
 Coding Group Data Coding / Message Class  
 Message Coding 8 bit data  
 Message Class Class 2 (U)SIM Specific Message  
 TP-SCTS: 01/01/98 00:00:00 +0  
 TP-UDL 13  
 TP-UD "Short Message"

Coding:

Coding	04	04	91	21	43	7F	F6	89	10	10	00	00
	00	00	0D	53	68	6F	72	74	20	4D	65	73
	73	61	67	65								

## ENVELOPE: SMS-PP DOWNLOAD 1.6.2

Logically:

## SMS-PP Download

Device identities  
 Source device: Network  
 Destination device: UICC  
 Address  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"  
 SMS TPDU  
 TP-MTI SMS-DELIVER  
 TP-MMS No more messages waiting for the MS in this SC  
 TP-RP TP-Reply-Path is not set in this SMS-DELIVER  
 TP-UDHI TP-UD field contains only the short message  
 TP-SRI A status report will not be returned to the SME  
 TP-OA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "1234"  
 TP-PID (U)SIM Data download  
 TP-DCS  
 Coding Group Data Coding / Message Class  
 Message Coding 8 bit data  
 Message Class Class 2 (U)SIM Specific Message  
 TP-SCTS: 01/01/98 00:00:00 +0  
 TP-UDL 13  
 TP-UD "Short Message"

Coding:

BER-TLV:	D1	2D	82	02	83	81	06	09	91	11	22	33
	44	55	66	77	F8	8B	1C	04	04	91	21	43
	7F	F6	89	10	10	00	00	00	00	0D	53	68
	6F	72	74	20	4D	65	73	73	61	67	65	

**Expected Sequence 1.7 (SMS-PP Data Download error)**

Step	Direction	MESSAGE / Action	Comments
1	USS → ME	SMS-PP Data Download Message 1.2.1	
2	ME → USER	The ME shall not display the message or alert the user of a short message waiting.	
3	ME → UICC	ENVELOPE: SMS-PP DOWNLOAD 1.2.2	[SW1 / SW2 of '62 xx' or '63 xx']
4	UICC → ME	SMS-PP Data Download UICC Acknowledgement 1.2.4	
5	ME → UICC	Retrieve RP-Error information provided by the USIM	
6	ME → USS	SMS-PP Data Download UICC Acknowledgement 1.2.4 in the TP-User-Data element of the RP-ERROR message. The values of protocol identifier and data coding scheme in RP-ERROR shall be as in the original message.	

## SMS-PP Data Download UICC Acknowledgement 1.2.4

Coding:

Coding	50	68	69	6C	20	48	6F	6F	6B	65	72
--------	----	----	----	----	----	----	----	----	----	----	----

## 27.22.5.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.2 to 1.7.

## 27.22.5.2 SMS-CB Data Download

## 27.22.5.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.5.2.2 Conformance requirement

The ME shall support the Proactive UICC: SMS-CB Data Download facility as defined in:

- 3GPP TS 31.111 [15] clause 5, clause 7.1.2, clause 8.5 and clause 8.7.

## 27.22.5.2.3 Test purpose

To verify that the ME transparently passes the "data download via SMS Cell Broadcast" messages to the UICC, which contain a message identifier found in EF<sub>CBMID</sub>.

## 27.22.5.2.4 Method of Test

## 27.22.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.5.2.4.2 Procedure

**Expected Sequence 1.1 (SMS-CB (Data Download), ENVELOPE(SMS-CB DOWNLOAD), ME does not display message)**

Step	Direction	MESSAGE / Action	Comments
1	USS → ME	SMS-CB (DATA DOWNLOAD) 1.1	Message identifier '10 01'
2	ME → UICC	ENVELOPE (SMS-CB DOWNLOAD) 1.1	
3	UICC → ME	SW1, SW2 '90 00'	

SMS-CB (Data Download) Message 1.1

Logically:

Message Content

Serial Number  
 Geographical scope: Cell wide, normal display mode  
 Message code: 1  
 Update number: 1  
 Message Identifier: "1001"  
 Data coding Scheme  
 Message Coding: 7 bit data  
 Message class: No message class  
 Page Parameter  
 Total number of pages: 1  
 Page number: 1  
 Content of message: "Cell Broadcast "..

Coding:

Coding	C0	11	10	01	F0	11	C3	32	9B	0D	12	CA
	DF	61	F2	38	3C	A7	83	40	20	10	08	04
	02	81	40	20	10	08	04	02	81	40	20	10
	08	04	02	81	40	20	10	08	04	02	81	40
	20	10	08	04	02	81	40	20	10	08	04	02
	81	40	20	10	08	04	02	81	40	20	10	08
	04	02	81	40	20	10	08	04	02	81	40	20
	10	08	04	02								

ENVELOPE: SMS-CB DOWNLOAD 1.1

Logically:

Cell Broadcast Download

Device identities  
 Source device: Network  
 Destination device: UICC

Cell Broadcast page

Serial Number  
 Geographical scope: Cell wide, normal display mode  
 Message code: 1  
 Update number: 1  
 Message Identifier: "1001"  
 Data coding Scheme  
 Message Coding: 7 bit data  
 Message class: No message class  
 Page Parameter  
 Number of pages: 1  
 Page number: 1  
 Content of message: "Cell Broadcast "..

Coding:

BER-TLV:	D2	5E	82	02	83	81	8C	58	C0	11	10	01
	F0	11	C3	32	9B	0D	12	CA	DF	61	F2	38
	3C	A7	83	40	20	10	08	04	02	81	40	20
	10	08	04	02	81	40	20	10	08	04	02	81
	40	20	10	08	04	02	81	40	20	10	08	04
	02	81	40	20	10	08	04	02	81	40	20	10
	08	04	02	81	40	20	10	08	04	02	81	40
	20	10	08	04	02	81	40	20	10	08	04	02

**Expected Sequence 1.2 (SMS-CB(DATA DOWNLOAD), ENVELOPE(SMS-CB DATA DOWNLOAD), FETCH, MORE TIME, ME does not display message)**

Step	Direction	MESSAGE / Action	Comments
1	USS → ME	SMS-CB (DATA DOWNLOAD) 1.1	Message identifier '10 01'
2	ME → UICC	ENVELOPE (SMS-CB DOWNLOAD) 1.1	
3	UICC → ME	PROACTIVE COMMAND PENDING: MORE TIME 1.1	SW1/SW2 '61 0B'
4	ME → UICC	FETCH 1.1	
5	UICC → ME	PROACTIVE COMMAND:MORE TIME 1.1	
6	ME → UICC	TERMINAL RESPONSE: MORE TIME 1.1	
7	UICC → ME	SW1/SW2 '90 00'	UICC session ended

PROACTIVE COMMAND: MORE TIME 1.1

Logically:

Command details

Command number: 1  
 Command type: MORE TIME  
 Command qualifier: "00"

Device identities

Source device: UICC  
 Destination device: ME

Coding:

BER-TLV:	D0	09	81	03	01	02	00	82	02	81	82
----------	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: MORE TIME 1.1

Logically:

Command details

Command number: 1  
 Command type: MORE TIME  
 Command qualifier: "00"

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	02	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.3 (SMS-CB (DATA DOWNLOAD), ME displays message)**

Step	Direction	MESSAGE / Action	Comments
1	USS → ME	SMS-CB (DATA DOWNLOAD) 1.2	Message identifier '03 E7'
2a	ME → USER	ME may display the message	
2b	ME → UICC	ME shall not download the CB message to the UICC using ENVELOPE (SMS-CB download)	
3	USER → ME	The user shall use a MMI dependent procedure to initiate the display of the received CB message	[only if message has not been displayed in step 2a]
4	ME → USER	ME displays the message	[only if message has not been displayed in step 2a]

SMS-CB (Data Download) Message 1.2

Logically:

Message Content

Serial Number  
 Geographical scope: Cell wide, normal display mode  
 Message code: 1  
 Update number: 1  
 Message Identifier: "03E7"  
 Data coding Scheme  
 Message Coding: 7 bit data  
 Message class: No message class  
 Page Parameter  
 Total number of pages: 1  
 Page number: 1  
 Content of message: "Cell Broadcast".

Coding:

Coding	C0	11	03	E7	F0	11	C3	32	9B	0D	12	CA
	DF	61	F2	38	3C	A7	83	40	20	10	08	04
	02	81	40	20	10	08	04	02	81	40	20	10
	08	04	02	81	40	20	10	08	04	02	81	40
	20	10	08	04	02	81	40	20	10	08	04	02
	81	40	20	10	08	04	02	81	40	20	10	08
	04	02	81	40	20	10	08	04	02	81	40	20
	10	08	04	02								

27.22.5.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

27.22.6 CALL CONTROL BY USIM

27.22.6.1 Procedure for Mobile Originated calls

27.22.6.1.1 Definition and applicability

See clause 3.2.2.

27.22.6.1.2 Conformance requirement

The ME shall support the CALL CONTROL facility as defined in:

- 3GPP TS 31.111 [15] clause 7.3

### 27.22.6.1.3 Test purpose

To verify that for all call set-up attempts, even those resulting from a SET UP CALL proactive UICC command, the ME shall first pass the call set-up details (dialled digits and associated parameters) to the UICC, using the ENVELOPE (CALL CONTROL).

To verify that if the UICC responds with '90 00', the ME shall set up the call with the dialled digits and other parameters as sent to the UICC.

To verify that if the UICC returns response data, the ME shall use the response data appropriately to set up the call as proposed, not set up the call, or set up a call using the data supplied by the UICC.

To verify that, in the case where the initial call set-up request results from a proactive SET UP CALL, if the call control result is "not allowed" or "allowed with modifications", the ME shall inform the UICC using TERMINAL RESPONSE "interaction with call control by UICC or MO short message control by UICC, action not allowed".

To verify that it is possible for the UICC to request the ME to set up an emergency call by supplying the number "112" as the response data.

### 27.22.6.1.4 Method of tests

#### 27.22.6.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and USS and has performed the location update procedure.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The elementary files are coded as USIM Application Toolkit default with the following exception:

The call control service is available in the USIM Service Table.

27.22.6.1.4.2 Procedure

**Expected Sequence 1.1 (CALL CONTROL BY USIM , set up call attempt by user, the USIM responds with '90 00')**

Step	Direction	Message / Action	Comments
1	User → ME	Set up a call to "+01234567890123456789"	
2	ME → UICC	ENVELOPE CALL CONTROL 1.1.1A Or ENVELOPE CALL CONTROL 1.1.1B	[Option A shall apply for 3GPP parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	90 00	
4	ME → USS	The ME sets up the call without modification	[Set up call to "+01234567890123456789"

ENVELOPE CALL CONTROL 1.1.1A

Logically:

Device identities

Source device: ME  
Destination device: UICC

Address

TON: International  
NPI: "ISDN / telephone numbering plan" or "unknown"  
Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)  
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	Note 5	07	00
	F1	10	00	01	00	01	Note 6	Note 4				

ENVELOPE CALL CONTROL 1.1.1B

Logically:

Device identities

Source device: ME  
Destination device: UICC

Address

TON: International  
NPI: "ISDN / telephone numbering plan" or "unknown"  
Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)  
 Capability configuration parameters 2  
 This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

#### Expected Sequence 1.2 (CALL CONTROL BY USIM , set up call attempt by user, allowed without modification)

Step	Direction	Message / Action	Comments
1	User → ME	Set up a call to "+01234567890123456789"	
2	ME → UICC	ENVELOPE CALL CONTROL 1.2.1 A or ENVELOPE CALL CONTROL 1.2.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 1.2.1	[Call control result: "Allowed, no modification"]
4	ME → USS	The ME sets up the call without modification	[Set up call to "+01234567890123456789"]

#### ENVELOPE CALL CONTROL 1.2.1A

Logically:

Device identities

Source device: ME  
 Destination device: UICC

Address

TON: International  
 NPI: "ISDN / telephone numbering plan" or "unknown"  
 Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)  
 Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	Note 5	00
	F1	10	00	01	00	01	Note 6	Note 4				

## ENVELOPE CALL CONTROL 1.2.1B

Logically:

## Device identities

Source device: ME  
Destination device: UICC

## Address

TON: International  
NPI: "ISDN / telephone numbering plan" or "unknown"  
Dialling number string "01234567890123456789"

## Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

## Subaddress

This parameter is optional. If present, the contents shall not be checked.

## Location Information

MCC & MNC the mobile country and network code (001110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)

## Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

## CALL CONTROL RESULT 1.2.1

Logically:

Call control result : '00' = Allowed, no modification

Coding:

BER-TLV:	00	00
----------	----	----

**Expected Sequence 1.3A (CALL CONTROL BY USIM , set up call attempt resulting from a set up call proactive command, allowed without modification)**

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.3.1 PENDING	[This test applies to MEs asking for user confirmation before sending the ENVELOPE CALL CONTROL command]
2	ME→UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.3.1	[Set up call to "+012340123456"]
4	ME → USER	ME displays "+012340123456" during user confirmation phase.	
5	USER → ME	The user confirms the call set up	[user confirmation]
6	ME → UICC	ENVELOPE CALL CONTROL 1.3.1A or ENVELOPE CALL CONTROL 1.3.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
7	UICC → ME	CALL CONTROL RESULT 1.3.1	[Call control result: "Allowed, no modification"]
8	ME → USS	The ME sets up the call without modification	[Set up call to "+012340123456"]
9	ME → UICC	TERMINAL RESPONSE: SET UP CALL 1.3.1	[command performed successfully]

**Expected Sequence 1.3 B (CALL CONTROL BY USIM , set up call attempt resulting from a set up call proactive command, allowed without modification)**

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.3.1 PENDING	[This test applies to MEs asking for user confirmation after sending the ENVELOPE CALL CONTROL command]
2	ME→UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.3.1	[Set up call to "+012340123456"]
4	ME → UICC	ENVELOPE CALL CONTROL 1.3.1A or ENVELOPE CALL CONTROL 1.3.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
5	UICC → ME	CALL CONTROL RESULT 1.3.1	[Call control result: "Allowed, no modification"]
6	ME → USER	ME displays "+012340123456" during user confirmation phase.	
7	USER → ME	The user confirms the call set up	[user confirmation]
8	ME → USS	The ME sets up the call without modification	[Set up call to "+012340123456"]
9	ME → UICC	TERMINAL RESPONSE: SET UP CALL 1.3.1	[command performed successfully]

PROACTIVE COMMAND: SET UP CALL 1.3.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: Only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: "+012340123456"

Address

TON: International

NPI: "ISDN / telephone numbering plan"  
 Dialling number string "012340123456"

Coding:

BER-TLV:	D0	21	81	03	01	10	00	82	02	81	83
	05	0D	2B	30	31	32	33	34	30	31	32
	33	34	35	36	86	07	91	10	32	04	21
	43	65									

### ENVELOPE CALL CONTROL 1.3.1A

Logically:

Device identities

Source device: ME  
 Destination device: UICC

Address

TON: International  
 NPI: "ISDN / telephone numbering plan" or "unknown"  
 Dialling number string "012340123456"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)  
 Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	02	02	82	81	06	07	91	10	32
	04	21	43	65	Note 2	Note 3	13	Note 5	00	F1	10
	00	01	00	01	Note 6	Note 4					

### ENVELOPE CALL CONTROL 1.3.1B

Logically:

Device identities

Source device: ME  
 Destination device: UICC

Address

TON: International  
 NPI: "ISDN / telephone numbering plan" or "unknown"  
 Dialling number string "012340123456"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	02	02	82	81	06	07	91	10	32
	04	21	43	65	Note 2	Note 3	13	07	00	11	10
	00	01	00	01	Note 4						

- Note 1: Length of BER-TLV is '16' plus the actual length of all the present optional SIMPLE-TLV data objects.
- Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.
- Note 3: Subaddress may be present at this place. If present, it may take up several octets.
- Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.
- Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'
- Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

CALL CONTROL RESULT 1.3.1

Logically:

Call control result : '00' = Allowed, no modification

Coding:

BER-TLV:	00	00
----------	----	----

TERMINAL RESPONSE: SET UP CALL 1.3.1

Logically:

Command details

- Command number: 1
- Command type: SET UP CALL
- Command qualifier: Only if not currently busy on another call

Device identities

- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.4 (CALL CONTROL BY USIM , set up call attempt by user, not allowed)**

Step	Direction	Message / Action	Comments
1	User → ME	Set up a call to "+01234567890123456789"	
2	ME → UICC	ENVELOPE CALL CONTROL 1.4.1 A or ENVELOPE CALL CONTROL 1.4.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 1.4.1	[Call control result: "not Allowed"]
4	ME → USS	The ME does not set up the call	

ENVELOPE CALL CONTROL 1.4.1A

Logically:

Device identities

Source device: ME  
 Destination device: UICC

Address  
 TON: International  
 NPI: "ISDN / telephone numbering plan" or "unknown"  
 Dialling number string "+01234567890123456789"

Capability configuration parameters 1  
 This parameter is optional. If present, the contents shall not be checked.

Subaddress  
 This parameter is optional. If present, the contents shall not be checked.

Location Information  
 MCC & MNC the mobile country and network code (00F110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)  
 Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2  
 This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	Note 5	00
	F1	10	00	01	00	01	Note 6	Note 4				

#### ENVELOPE CALL CONTROL 1.4.1B

Logically:

Device identities  
 Source device: ME  
 Destination device: UICC

Address  
 TON: International  
 NPI: "ISDN / telephone numbering plan" or "unknown"  
 Dialling number string "+01234567890123456789"

Capability configuration parameters 1  
 This parameter is optional. If present, the contents shall not be checked.

Subaddress  
 This parameter is optional. If present, the contents shall not be checked.

Location Information  
 MCC & MNC the mobile country and network code (001110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)

Capability configuration parameters 2  
 This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

#### CALL CONTROL RESULT 1.4.1

Logically:

Call control result: '01' = not Allowed

Coding:

BER-TLV:	01	00
----------	----	----

#### Expected Sequence 1.5A (CALL CONTROL BY USIM , set up call attempt resulting from a set up call proactive command, not allowed)

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.5.1 PENDING	[This test applies to MEs asking for user confirmation before sending the ENVELOPE CALL CONTROL command]
2	ME→UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.5.1	[Set up call to "+012340123456"]
4	ME → USER	ME displays "+012340123456" during user confirmation phase.	
5	USER → ME	The user confirms the call set up	[user confirmation]
6	ME → UICC	ENVELOPE CALL CONTROL 1.5.1A or ENVELOPE CALL CONTROL 1.5.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
7	UICC → ME	CALL CONTROL RESULT 1.5.1	[Call control result: "Not Allowed"]
8	ME → UICC	TERMINAL RESPONSE: SET UP CALL 1.5.1	[Permanent Problem - Interaction with Call Control by USIM]
9	ME → USS	The ME does not set up the call	

#### Expected Sequence 1.5 B (CALL CONTROL BY USIM , set up call attempt resulting from a set up call proactive command, not allowed)

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.5.1 PENDING	[This test applies to MEs asking for user confirmation after sending the ENVELOPE CALL CONTROL command]
2	ME→UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.5.1	[Set up call to "+012340123456"]
4	ME → UICC	ENVELOPE CALL CONTROL 1.5.1A or ENVELOPE CALL CONTROL 1.5.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
5	UICC → ME	CALL CONTROL RESULT 1.5.1	[Call control result: "Not Allowed"] [No user confirmation phase because Call Control has disallowed the request]
6	ME → UICC	TERMINAL RESPONSE: SET UP CALL 1.5.1	[Permanent Problem - Interaction with Call Control by USIM]
7	ME → USS	The ME does not set up the call	

#### PROACTIVE COMMAND: SET UP CALL 1.5.1

Logically:

Command details

Command number: 1

Command type: SET UP CALL  
 Command qualifier: Only if not currently busy on another call  
 Device identities  
     Source device: UICC  
     Destination device: Network  
 Alpha identifier: "+012340123456"  
 Address  
     TON: International  
     NPI: "ISDN / telephone numbering plan"  
     Dialling number string "012340123456"

Coding:

BER-TLV:	D0	21	81	03	01	10	00	82	02	81	83
	05	0D	2B	30	31	32	33	34	30	31	32
	33	34	35	36	86	07	91	10	32	04	21
	43	65									

ENVELOPE CALL CONTROL 1.5.1A

Logically:

Device identities  
     Source device: ME  
     Destination device: UICC  
 Address  
     TON: International  
     NPI: "ISDN / telephone numbering plan" or "unknown"  
     Dialling number string "012340123456"  
 Capability configuration parameters 1  
     This parameter is optional. If present, the contents shall not be checked.  
 Subaddress  
     This parameter is optional. If present, the contents shall not be checked.  
 Location Information  
     MCC & MNC the mobile country and network code (00F110)  
     LAC the location Area Code (0001)  
     Cell ID Cell Identity Value (0001)  
     Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6  
 Capability configuration parameters 2  
     This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	02	02	82	81	06	07	91	10	32
	04	21	43	65	Note 2	Note 3	13	Note 5	00	F1	10
	00	01	00	01	Note 6	Note 4					

ENVELOPE CALL CONTROL 1.5.1B

Logically:

Device identities  
     Source device: ME  
     Destination device: UICC  
 Address  
     TON: International  
     NPI: "ISDN / telephone numbering plan" or "unknown"  
     Dialling number string "012340123456"  
 Capability configuration parameters 1  
     This parameter is optional. If present, the contents shall not be checked.  
 Subaddress  
     This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	02	02	82	81	06	07	91	10	32
	04	21	43	65	Note 2	Note 3	13	07	00	11	10
	00	01	00	01	Note 4						

Note 1: Length of BER-TLV is '16' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

CALL CONTROL RESULT 1.5.1

Logically:

Call control result: '01' = not Allowed

Coding:

BER-TLV:	01	00
----------	----	----

TERMINAL RESPONSE: SET UP CALL 1.5.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: Only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Interaction with call control by USIM or MO short message control by USIM, permanent problem  
 Additional information: Action not allowed

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	02	39
	01											

**Expected Sequence 1.6 (CALL CONTROL BY USIM , set up call attempt by user, allowed with modifications)**

Step	Direction	Message / Action	Comments
1	User → ME	Set up a call to "+01234567890123456789"	
2	ME → UICC	ENVELOPE CALL CONTROL 1.6.1 A or ENVELOPE CALL CONTROL 1.6.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 1.6.1	[Call control result: "Allowed with modifications", ]
4	ME → USS	The ME sets up the call to "+010203"	

ENVELOPE CALL CONTROL 1.6.1A

Logically:

Device identities

Source device: ME  
Destination device: UICC

Address

TON: International  
NPI: "ISDN / telephone numbering plan" or "unknown"  
Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)  
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	Note 5	00
	F1	10	00	01	00	01	Note 6	Note 4				

ENVELOPE CALL CONTROL 1.6.1B

Logically:

Device identities

Source device: ME  
Destination device: UICC

Address

TON: International  
NPI: "ISDN / telephone numbering plan" or "unknown"  
Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)  
LAC the location Area Code (0001)

Cell ID Cell Identity Value (0001)  
 Capability configuration parameters 2  
 This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

- Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.
- Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.
- Note 3: Subaddress may be present at this place. If present, it may take up several octets.
- Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.
- Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'
- Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 1.6.1

Logically:

Call control result: '02' = Allowed with modifications  
 Address  
 TON: International  
 NPI: "ISDN / telephone numbering plan" or "unknown"  
 Dialling number string "010203"

Coding:

BER-TLV:	02	06	86	04	91	10	20	30
----------	----	----	----	----	----	----	----	----

**Expected Sequence 1.7A (CALL CONTROL BY USIM, set up call attempt resulting from a set up call proactive command, allowed with modifications)**

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.7.1 PENDING	[This test applies to MEs asking for user confirmation before sending the ENVELOPE CALL CONTROL command]
2	ME→UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.7.1	[Set up call to "+012340123456"]
4	ME → USER	ME displays "+012340123456" during user confirmation phase.	
5	USER → ME	The user confirms the call set up	[user confirmation]
6	ME → UICC	ENVELOPE CALL CONTROL 1.7.1A or ENVELOPE CALL CONTROL 1.7.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
7	UICC → ME	CALL CONTROL RESULT 1.7.1	[Call control result: "Allowed with modifications"]
8	ME → USS	The ME sets up the call to "+011111111111"	
9	ME → UICC	TERMINAL RESPONSE: SET UP CALL 1.7.1	[command performed successfully]

**Expected Sequence 1.7 B (CALL CONTROL BY USIM, set up call attempt resulting from a set up call proactive command, allowed with modifications)**

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.7.1 PENDING	[This test applies to MEs asking for user confirmation after sending the ENVELOPE CALL CONTROL command]
2	ME→UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP CALL 1.7.1	[Set up call to "+012340123456"]
4	ME → UICC	ENVELOPE CALL CONTROL 1.7.1A or ENVELOPE CALL CONTROL 1.7.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
5	UICC → ME	CALL CONTROL RESULT 1.7.1	[Call control result: "Allowed with modifications"]
6	ME → USER	ME displays "+012340123456" during user confirmation phase.	
7	USER → ME	The user confirms the call set up	[user confirmation]
8	ME → USS	The ME sets up the call to "+011111111111"	[call is set up to modified address]
9	ME → UICC	TERMINAL RESPONSE: SET UP CALL 1.7.1	[command performed successfully]

**PROACTIVE COMMAND: SET UP CALL 1.7.1**

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: Only if not currently busy on another call

Device identities

Source device: UICC  
 Destination device: Network

Alpha identifier: '+012340123456'

Address

TON: International  
 NPI: "ISDN / telephone numbering plan" or "unknown"  
 Dialling number string "012340123456"

Coding:

BER-TLV:	D0	21	81	03	01	10	00	82	02	81	83
	05	0D	2B	30	31	32	33	34	30	31	32
	33	34	35	36	86	07	91	10	32	04	21
	43	65									

**ENVELOPE CALL CONTROL 1.7.1A**

Logically:

Device identities

Source device: ME  
 Destination device: UICC

Address

TON: International  
 NPI: "ISDN / telephone numbering plan" or "unknown"  
 Dialling number string "012340123456"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

## Location Information

MCC & MNC the mobile country and network code (00F110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)  
 Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

## Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	02	02	82	81	06	07	91	10	32
	04	21	43	65	Note 2	Note 3	13	Note 5	00	F1	10
	00	01	00	01	Note 6	Note 4					

## ENVELOPE CALL CONTROL 1.7.1B

## Logically:

## Device identities

Source device: ME  
 Destination device: UICC

## Address

TON: International  
 NPI: "ISDN / telephone numbering plan" or "unknown"  
 Dialling number string "012340123456"

## Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

## Subaddress

This parameter is optional. If present, the contents shall not be checked.

## Location Information

MCC & MNC the mobile country and network code (001110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)

## Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	02	02	82	81	06	07	91	10	32
	04	21	43	65	Note 2	Note 3	13	07	00	11	10
	00	01	00	01	Note 4						

Note 1: Length of BER-TLV is '16' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

## CALL CONTROL RESULT 1.7.1

## Logically:

Call control result: '02' = Allowed with modifications

## Address

TON: International  
 NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string "01111111111"

Coding:

BER-TLV:	02	09	86	07	91	10	11	11	11	11	11
----------	----	----	----	----	----	----	----	----	----	----	----

TERMINAL RESPONSE: SET UP CALL 1.7.1

Logically:

Command details

Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: Only if not currently busy on another call

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.8 (CALL CONTROL BY USIM , set up call attempt by user, allowed with modifications: emergency call)**

Step	Direction	Message / Action	Comments
1	User → ME	Set up a call to "+01234567890123456789"	
2	ME → UICC	ENVELOPE CALL CONTROL 1.8.1A or ENVELOPE CALL CONTROL 1.8.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 1.8.1	[Call control result: "Allowed with modifications"]
4	ME → USS	The ME sets up an emergency call;	

ENVELOPE CALL CONTROL 1.8.1A

Logically:

Device identities

Source device: ME  
 Destination device: UICC

Address

TON: International  
 NPI: "ISDN / telephone numbering plan" or "unknown"  
 Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)  
 Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	Note 5	00
	F1	10	00	01	00	01	Note 6	Note 4				

## ENVELOPE CALL CONTROL 1.8.1B

Logically:

## Device identities

Source device: ME  
Destination device: UICC

## Address

TON: International  
NPI: "ISDN / telephone numbering plan" or "unknown"  
Dialling number string "01234567890123456789"

## Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

## Subaddress

This parameter is optional. If present, the contents shall not be checked.

## Location Information

MCC & MNC the mobile country and network code (001110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)

## Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

## CALL CONTROL RESULT 1.8.1

Logically:

Call control result Allowed, with modification

## Address

TON Unknown  
NPI "ISDN / telephone numbering plan"  
Address value "112"

Coding:

BER-TLV:	02	05	86	03	81	11	F2
----------	----	----	----	----	----	----	----

**Expected Sequence 1.9 (CALL CONTROL BY USIM , set up call attempt by user, allowed with modifications: number in EF<sub>ECC</sub>)**

Step	Direction	Message / Action	Comments
1	User → ME	Set up a call to "+01234567890123456789"	
2	ME → UICC	ENVELOPE CALL CONTROL 1.9.1A or ENVELOPE CALL CONTROL 1.9.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 1.9.1	[Call control result: "Allowed with modifications"]
4	ME → USS	The ME sets up call with the dialled digits "1020". The ME does not set up an emergency call, but sets up a normal call	

ENVELOPE CALL CONTROL 1.9.1A

Logically:

Device identities

Source device: ME  
Destination device: UICC

Address

TON: International  
NPI: "ISDN / telephone numbering plan" or "unknown"  
Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)  
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	Note 5	00
	F1	10	00	01	00	01	Note 6	Note 4				

ENVELOPE CALL CONTROL 1.9.1B

Logically:

Device identities

Source device: ME  
Destination device: UICC

Address

TON: International  
NPI: "ISDN / telephone numbering plan" or "unknown"  
Dialling number string "01234567890123456789"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)  
 Capability configuration parameters 2  
 This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	0B	91	10	32	54
	76	98	10	32	54	76	98	Note 2	Note 3	13	07	00
	11	10	00	01	00	01	Note 4					

- Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.
- Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.
- Note 3: Subaddress may be present at this place. If present, it may take up several octets.
- Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.
- Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'
- Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 1.9.1

Logically:

Call control result Allowed, with modification  
 Address  
 TON Unknown  
 NPI "ISDN / telephone numbering plan"  
 Address value "1020"

Coding:

BER-TLV:	02	05	86	03	81	01	02
----------	----	----	----	----	----	----	----

**Expected Sequence 1.10 (CALL CONTROL BY USIM , set up call attempt by user to an emergency call)**

Step	Direction	Message / Action	Comments
1	User → ME	Set up a call to "112"	
2	ME → UICC	The ME does not send any ENVELOPE CALL CONTROL	
3	ME → USS	The ME sets up an emergency call	

**Expected Sequence 1.11 (CALL CONTROL BY USIM , set up call through call register, the USIM responds with '90 00')**

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers allowed by call control in its register.

Step	Direction	Message / Action	Comments
1	User → ME	Set up a call to "+01234567890123456789"	
2	ME → UICC	ENVELOPE CALL CONTROL 1.1.1A or ENVELOPE CALL CONTROL 1.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	90 00	

4	ME → USS	The ME sets up the call without modification	[Set up call to "+01234567890123456789"]
5	USER → ME	End Call.	
6	USER → ME	Recall the last dialled number	
7	ME → UICC	ENVELOPE CALL CONTROL 1.1.1A or ENVELOPE CALL CONTROL 1.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
8	UICC → ME	90 00	
9	ME → USS	The ME sets up the call without modification	[Set up call to "+01234567890123456789"]
10	USER → ME	End Call.	

### Expected Sequence 1.12 (CALL CONTROL BY USIM , set up call through call register, allowed without modification)

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers allowed by call control in its register.

Step	Direction	Message / Action	Comments
1	User → ME	Set up a call to "+01234567890123456789"	
2	ME → UICC	ENVELOPE CALL CONTROL 1.2.1A or ENVELOPE CALL CONTROL 1.2.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 1.2.1	[Call control result: "Allowed, no modification"]
4	ME → USS	The ME sets up the call without modification	[Set up call to "+01234567890123456789"]
5	User → ME	End the call then call the last dialled number	
6	ME → UICC	ENVELOPE CALL CONTROL 1.2.1A or ENVELOPE CALL CONTROL 1.2.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
7	UICC → ME	CALL CONTROL RESULT 1.2.1	
8	ME → USS	The ME sets up the call without modification	[Set up call to "+01234567890123456789"]

### Expected Sequence 1.13 (CALL CONTROL BY USIM , set up call through call register, not allowed)

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers not allowed by call control in its register.

Step	Direction	Message / Action	Comments
1	User → ME	Set up a call to "+01234567890123456789"	
2	ME → UICC	ENVELOPE CALL CONTROL 1.4.1A or ENVELOPE CALL CONTROL 1.4.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 1.4.1	[Call control result: "not Allowed"]
4	ME → USS	The ME does not set up the call	
5	User → ME	The user calls the last dialled number	
6	ME → UICC	ENVELOPE CALL CONTROL 1.4.1A or ENVELOPE CALL CONTROL 1.4.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
7	UICC → ME	CALL CONTROL RESULT 1.4.1	[Call control result: "not Allowed"]
8	ME → USS	The ME does not set up the call	

### Expected Sequence 1.14 (CALL CONTROL BY USIM , set up call through call register, allowed with modifications)

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers allowed with modification by call control in its register.

Step	Direction	Message / Action	Comments
1	User → ME	Set up a call to "+01234567890123456789"	
2	ME → UICC	ENVELOPE CALL CONTROL 1.6.1A or ENVELOPE CALL CONTROL 1.6.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 1.6.1	[Call control result: "Allowed with modifications"]
4	ME → USS	The ME sets up the call to "+010203"	
5	User → ME	End call and then set up a call to "+01234567890123456789"	
6	ME → UICC	ENVELOPE CALL CONTROL 1.6.1A or ENVELOPE CALL CONTROL 1.6.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
7	UICC → ME	CALL CONTROL RESULT 1.6.1	[Call control result: "Allowed with modifications"]
8	ME → USS	The ME sets up the call to "+010203"	

#### 27.22.6.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.14.

#### 27.22.6.2 Procedure for Supplementary (SS) Services

##### 27.22.6.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.6.2.2 Conformance requirement

The ME shall support the CALL CONTROL facility as defined in the following technical specifications:

- 3GPP TS 31.111 [15] clause 7.3.1.2.

#### 27.22.6.2.3 Test purpose

To verify that the ME first pass the supplementary service control string corresponding to the supplementary service operation to the USIM, using the ENVELOPE (CALL CONTROL) command.

To verify that, if the UICC responds with '90 00', the ME shall send the supplementary service operation with the information as sent to the UICC.

To verify that, if the UICC returns response data, the ME shall use the response data appropriately to send the supplementary service operation as proposed, not send the SS operation, or instead send the USS operation using the data supplied by the UICC.

#### 27.22.6.2.4 Method of tests

##### 27.22.6.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The elementary files are coded as USIM Application Toolkit default with the following exception:

The call control service is available in the USIM Service Table.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01 ;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

27.22.6.2.4.2 Procedure

**Expected Sequence 2.1 (CALL CONTROL BY USIM , send SS, the USIM responds with '90 00')**

Step	Direction	Message / Action	Comments
1	User → ME	The user selects the facility of the ME which requires an unconditional call forward supplementary service operation to be sent to the network (System Simulator).	
2	ME → UICC	ENVELOPE CALL CONTROL 2.1.1A or ENVELOPE CALL CONTROL 2.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	90 00	
4	ME → USS	REGISTER 2.1	[The ME sends the supplementary service operation with the information as sent to the UICC]
5	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 2.1	

ENVELOPE CALL CONTROL 2.1.1A

Logically:

Device identities

Source device: ME  
Destination device: UICC

SS String

TON/NPI: "FF"  
Dialling number string "\*21\*\*10#"

Location Information

MCC & MNC the mobile country and network code (00F110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)  
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

BER-TLV:	D4	Note1	82	02	82	81	89	05	FF	2A	A1	1A
	B0	13	Note 2	00	F1	10	00	01	00	01	Note 3	

Note 1: Length of BER-TLV is '14' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

ENVELOPE CALL CONTROL 2.1.1B

Logically:

Device identities

Source device: ME  
Destination device: UICC

SS String

TON/NPI: "FF"  
Dialling number string "\*21\*\*10#"

Location Information

MCC & MNC the mobile country and network code (001110)  
LAC the location Area Code (0001)

Cell ID                      Cell Identity Value (0001)

Coding:

BER-TLV:	D4	14	82	02	82	81	89	05	FF	2A	A1	1A
	B0	13	07	00	11	10	00	01	00	01		

## REGISTER 2.1

Logically (only SS argument):

### ACTIVATE SS ARGUMENT

SS-Code:

- Call Forwarding Unconditional

TeleserviceCode

- All Tele Services

Coding:

Coding	30	06	04	01	21	83	01	00				
--------	----	----	----	----	----	----	----	----	--	--	--	--

## RELEASE COMPLETE (SS RETURN RESULT) 2.1

Logically (only from operation code):

### ACTIVATE SS RETURN RESULT

ForwardingInfo

SS-Code

- Call Forwarding Unconditional

ForwardFeatureList

ForwardingFeature

TeleserviceCode

- All Tele Services

SS-Status

- state ind.: operative

- provision ind.: provisioned

- registration ind.: registered

- activation ind.: active

Coding:

Coding	0C	A0	0D	04	01	21	30	08	30	06	83	01
	00	84	01	07								

**Expected Sequence 2.2 (CALL CONTROL BY USIM , send SS, allowed without modifications)**

Step	Direction	Message / Action	Comments
1	User → ME	The user selects the facility of the ME which requires an unconditional call forward supplementary service operation to be sent to the network (System Simulator).	
2	ME → UICC	ENVELOPE CALL CONTROL 2.2.1A or ENVELOPE CALL CONTROL 2.2.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 2.2.1	[Call control result: "Allowed without modifications"]
4	ME → USS	REGISTER 2.1	The ME sends the supplementary service operation with the information as sent to the UICC
5	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 2.1	

**ENVELOPE CALL CONTROL 2.2.1A**

Logically:

Device identities

Source device: ME  
Destination device: UICC

SS String

TON/NPI: "FF"  
Dialling number string "\*21\*\*10#"

Location Information

MCC & MNC the mobile country and network code (00F110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	89	05	FF	2A	A1	1A
	B0	13	Note 2	00	F1	10	00	01	00	01	Note 3	

Note 1: Length of BER-TLV is '14' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

**ENVELOPE CALL CONTROL 2.2.1B**

Logically:

Device identities

Source device: ME  
Destination device: UICC

SS String

TON/NPI: "FF"  
Dialling number string "\*21\*\*10#"

Location Information

MCC & MNC the mobile country and network code (001110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)

Coding:

BER-TLV:	D4	14	82	02	82	81	89	05	FF	2A	A1	1A
	B0	13	07	00	11	10	00	01	00	01		

## CALL CONTROL RESULT 2.2.1

Logically:

Call control result      Allowed, no modifications

Coding:

BER-TLV:	00	00
----------	----	----

**Expected Sequence 2.3 (CALL CONTROL BY USIM , send SS, not allowed)**

Step	Direction	Message / Action	Comments
1	User → ME	The user selects the facility of the ME which requires an unconditional call forward supplementary service operation to be sent to the network (System Simulator).	
2	ME → UICC	ENVELOPE CALL CONTROL 2.3.1A or ENVELOPE CALL CONTROL 2.3.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 2.3.1	[Call control result: "Not Allowed"]
4	ME → USS	The ME does not send the supplementary service operation	

## ENVELOPE CALL CONTROL 2.3.1A

Logically:

Device identities

Source device:      ME  
Destination device:      UICC

SS String

TON/NPI:      "FF"  
Dialling number string      "\*21#"

Location Information

MCC & MNC      the mobile country and network code (00F110)  
LAC      the location Area Code (0001)  
Cell ID      Cell Identity Value (0001)  
Extended Cell ID      RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	89	03	FF	2A	B1	13
	Note 2	00	F1	10	00	01	00	01	Note 3			

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

## ENVELOPE CALL CONTROL 2.3.1B

Logically:

Device identities  
 Source device: ME  
 Destination device: UICC  
 SS String  
 TON/NPI: "FF"  
 Dialling number string "\*21#"  
 Location Information  
 MCC & MNC the mobile country and network code (001110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)

Coding:

BER-TLV:	D4	12	82	02	82	81	89	03	FF	2A	B1	13
	07	00	11	10	00	01	00	01				

CALL CONTROL RESULT 2.3.1

Logically:

Call control result Not Allowed

Coding:

BER-TLV:	01	00
----------	----	----

**Expected Sequence 2.4 (CALL CONTROL BY USIM , send SS, allowed with modifications)**

Step	Direction	Message / Action	Comments
1	User → ME	The user selects the facility of the ME which requires an unconditional call forward supplementary service operation to be sent to the network (System Simulator).	
2	ME → UICC	ENVELOPE CALL CONTROL 2.4.1A or ENVELOPE CALL CONTROL 2.4.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 2.4.1	[Call control result: "Allowed with modifications"]
4	ME → USS	REGISTER 2.4	[The ME sends the supplementary service operation with the information as sent by the UICC]
5	USS → ME	RELEASE COMPLETE (SS RETURN RESULT) 2.4	

ENVELOPE CALL CONTROL 2.4.1A

Logically:

Device identities  
 Source device: ME  
 Destination device: UICC  
 SS String  
 TON/NPI: "FF"  
 Dialling number string "\*21#"  
 Location Information  
 MCC & MNC the mobile country and network code (00F110)  
 LAC the location Area Code (0001)

Cell ID                      Cell Identity Value (0001)  
 Extended Cell ID         RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	89	03	FF	2A	B1	13
	Note 2	00	F1	10	00	01	00	01	Note 3			

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### ENVELOPE CALL CONTROL 2.4.1B

Logically:

Device identities

Source device:         ME  
 Destination device:    UICC

SS String

TON/NPI:                "FF"  
 Dialling number string "\*"21#"

Location Information

MCC & MNC             the mobile country and network code (001110)  
 LAC                      the location Area Code (0001)  
 Cell ID                 Cell Identity Value (0001)

Coding:

BER-TLV:	D4	12	82	02	82	81	89	03	FF	2A	B1	13
	07	00	11	10	00	01	00	01				

#### CALL CONTROL RESULT 2.4.1

Logically:

Call control result      Allowed, with modifications  
 SS String  
 TON/NPI                "FF"  
 SS String                "\*"21#"

Coding:

BER-TLV:	02	06	89	04	FF	BA	12	FB
----------	----	----	----	----	----	----	----	----

#### REGISTER 2.4

Logically (only SS argument):

INTERROGATE SS ARGUMENT  
 SS-Code  
 - Call Forwarding Unconditional

Coding:

BER-TLV	30	03	04	01	21
---------	----	----	----	----	----

#### RELEASE COMPLETE (SS RETURN RESULT) 2.4

Logically (only from operation code):

## INTERROGATE SS RESULT

Call Forwarding Unconditional

SS-Status

- state ind.: operative
- provision ind.: provisioned
- registration ind.: registered
- activation ind.: not active

Coding:

BER-TLV	80	01	06						
---------	----	----	----	--	--	--	--	--	--

## 27.22.6.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.4.

## 27.22.6.3 Interaction with Fixed Dialling Number (FDN)

## 27.22.6.3.1 Definition and applicability

See clause 3.2.2.

## 27.22.6.3.2 Conformance requirement

The ME shall support the CALL CONTROL facility as defined in:

- 3GPP TS 31.111 [15] clause 7.3.1.4.

## 27.22.6.3.3 Test purpose

To verify that the ME checks that the number entered through the MMI is on the FDN list.

To verify that, if the MMI input does not pass the FDN check, the call shall not be set up.

To verify that, if the MMI input does pass the FDN check, the ME shall pass the dialled digits and other parameters to the UICC, using the ENVELOPE (CALL CONTROL) command.

To verify that, if the UICC responds with "allowed, no modification", the ME shall set up the call as proposed.

To verify that, if the UICC responds with "not allowed", the ME shall not set up the call.

To verify that, if the UICC responds with "allowed with modifications", the ME shall set up the call in accordance with the response from the UICC. If the modifications involve changing the dialled digits, the ME shall not re-check this modified number against the FDN list.

## 27.22.6.3.4 Method of tests

## 27.22.6.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The elementary files are coded as SIM Application Toolkit default with the following exceptions:

The call control service is available in the USIM Service Table.

Fixed Dialling Number service is enabled.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;

- Mobile Network Code (MNC) = 01 ;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

#### 27.22.6.3.4.2 Procedure

##### Expected Sequence 3.1 (CALL CONTROL BY USIM , set up a call not in EF<sub>F<sub>DN</sub></sub>)

Step	Direction	Message / Action	Comments
1	User → ME	The user sets up a call to "4321"	
2	ME → UICC	The ME does not send the ENVELOPE (CALL CONTROL) command to the USIM.	
3	ME → USS	The ME does not set up the call.	

##### Expected Sequence 3.2 (CALL CONTROL BY USIM , set up a call in EF<sub>F<sub>DN</sub></sub> , the USIM responds with '90 00')

Step	Direction	Message / Action	Comments
1	User → ME	The user sets up a call to "123"	
2	ME → UICC	ENVELOPE CALL CONTROL 3.2.1A or ENVELOPE CALL CONTROL 3.2.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	90 00	
4	ME → USS	The ME sets up the call without modification	[Set up call to "123"]

#### ENVELOPE CALL CONTROL 3.2.1A

Logically:

Device identities

Source device: ME  
Destination device: UICC

Address

TON Unknown  
NPI "ISDN / telephone numbering plan"  
Dialling number string "123"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	21	F3	Note 2
	Note 3	13	Note 5	00	F1	10	00	01	00	01	Note 6	Note 4

ENVELOPE CALL CONTROL 3.2.1B

Logically:

Device identities

Source device: ME  
 Destination device: UICC

Address

TON Unknown  
 NPI "ISDN / telephone numbering plan"  
 Dialling number string "123"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	21	F3	Note 2
	Note 3	13	07	00	11	10	00	01	00	01	Note 4	

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

**Expected Sequence 3.3 (CALL CONTROL BY USIM , set up a call in EF<sub>F<sub>DN</sub></sub>, Allowed without modifications)**

Step	Direction	Message / Action	Comments
1	User → ME	The user sets up a call to "9876"	
2	ME → UICC	ENVELOPE CALL CONTROL 3.3.1A or ENVELOPE CALL CONTROL 3.3.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 3.3.1	[Call control result: "Allowed without modifications"]
4	ME → USS	The ME sets up the call without modification	[Set up call to "9876"]

ENVELOPE CALL CONTROL 3.3.1A

Logically:

Device identities

Source device: ME  
Destination device: UICC

Address

TON Unknown  
NPI "ISDN / telephone numbering plan"  
Dialling number string "9876"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)  
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
	Note 3	13	Note 5	00	F1	10	00	01	00	01	Note 6	Note 4

### ENVELOPE CALL CONTROL 3.3.1B

Logically:

Device identities

Source device: ME  
Destination device: UICC

Address

TON Unknown  
NPI "ISDN / telephone numbering plan"  
Dialling number string "9876"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
	Note 3	13	07	00	11	10	00	01	00	01	Note 4	

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

### CALL CONTROL RESULT 3.3.1

Logically:

Call control result      Allowed, no modifications

Coding:

BER-TLV:	00	00
----------	----	----

### Expected Sequence 3.4 (CALL CONTROL BY USIM , set up a call in EF<sub>FDN</sub> , Not Allowed)

Step	Direction	Message / Action	Comments
1	User → ME	The user sets up a call to "9876"	
2	ME → UICC	ENVELOPE CALL CONTROL 3.4.1A or ENVELOPE CALL CONTROL 3.4.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 3.4.1	[Call control result: "Not Allowed"]
4	ME → USS	The ME does not set up the call	

### ENVELOPE CALL CONTROL 3.4.1A

Logically:

Device identities

Source device:      ME  
Destination device:      UICC

Address

TON                      Unknown  
NPI                      "ISDN / telephone numbering plan"  
Dialling number string      "9876"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC              the mobile country and network code (00F110)  
LAC                      the location Area Code (0001)  
Cell ID                    Cell Identity Value (0001)  
Extended Cell ID        RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
	Note 3	13	Note 5	00	F1	10	00	01	00	01	Note 6	Note 4

### ENVELOPE CALL CONTROL 3.4.1B

Logically:

Device identities

Source device:      ME  
Destination device:      UICC

Address

TON                      Unknown

NPI "ISDN / telephone numbering plan"  
 Dialling number string "9876"  
 Capability configuration parameters 1  
 This parameter is optional. If present, the contents shall not be checked.  
 Subaddress  
 This parameter is optional. If present, the contents shall not be checked.  
 Location Information  
 MCC & MNC the mobile country and network code (001110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)  
 Capability configuration parameters 2  
 This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
	Note 3	13	07	00	11	10	00	01	00	01	Note 4	

- Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.
- Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.
- Note 3: Subaddress may be present at this place. If present, it may take up several octets.
- Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.
- Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'
- Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 3.4.1

Logically:

Call control result Not Allowed

Coding:

BER-TLV:	01	00
----------	----	----

**Expected Sequence 3.5 (CALL CONTROL BY USIM , set up a call in EF<sub>FDN</sub> , Allowed with modifications)**

Step	Direction	Message / Action	Comments
1	User → ME	The user sets up a call to "9876"	
2	ME → UICC	ENVELOPE CALL CONTROL 3.5.1A or ENVELOPE CALL CONTROL 3.5.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	CALL CONTROL RESULT 3.5.1	[Call control result: "Allowed with modifications"]
4	ME → USS	The ME sets up the call with data sent by the UICC	[Set up call to "3333"]

ENVELOPE CALL CONTROL 3.5.1A

Logically:

Device identities  
 Source device: ME  
 Destination device: UICC

## Address

TON Unknown  
 NPI "ISDN / telephone numbering plan"  
 Dialling number string "9876"

## Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

## Subaddress

This parameter is optional. If present, the contents shall not be checked.

## Location Information

MCC & MNC the mobile country and network code (00F110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)  
 Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

## Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
	Note3	13	Note 5	00	F1	10	00	01	00	01	Note 6	Note 4

## ENVELOPE CALL CONTROL 3.5.1B

## Logically:

## Device identities

Source device: ME  
 Destination device: UICC

## Address

TON Unknown  
 NPI "ISDN / telephone numbering plan"  
 Dialling number string "9876"

## Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

## Subaddress

This parameter is optional. If present, the contents shall not be checked.

## Location Information

MCC & MNC the mobile country and network code (001110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)

## Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

## Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	89	67	Note 2
	Note3	13	07	00	11	10	00	01	00	01	Note 4	

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

## CALL CONTROL RESULT 3.5.1

Logically:

Call control result	Allowed with modifications
Address	
TON	Unknown
NPI	"ISDN / telephone numbering plan"
Address value	"3333"

Coding:

BER-TLV:	02	05	86	03	81	33	33
----------	----	----	----	----	----	----	----

### 27.22.6.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1 to 3.5.

## 27.22.6.4 Support of Barred Dialling Number (BDN) service

### 27.22.6.4.1 Definition and applicability

Barred Dialling Numbers (BDN) is a service defined for the USIM. An enabled BDN service results in call restrictions for the ME. The call restrictions are controlled by the Terminal. To ascertain the type of USIM and state of BDN the ME runs the BDN capability request procedure during UICC-Terminal initialisation. At the time an emergency call is setup using the emergency call code read from the EF<sub>ECC</sub>, the Rel-4+ ME shall use the category of the emergency service indicated.

### 27.22.6.4.2 Conformance requirement

- 1) Recognising the state of the USIM (BDN enabled) the ME shall perform the UICC initialisation procedure as specified.
- 2) The ME shall prevent call set-up to any number stored in EF<sub>BDN</sub> if BDN service is enabled.
- 3) The ME shall allow call set-up to any number stored in EF<sub>BDN</sub> if BDN service is disabled.
- 4) Any change to the EF<sub>BDN</sub> or EF<sub>EST</sub> does request PIN2.
- 5) The ME allows call set-up of an emergency call, even if this number is stored in the USIM.

References:

- R99: TS 22.101[22], clause 8 and A.19;
- Rel-4: TS 22.101[22], clause 9 and A.20;
- Rel-5+: TS 22.101[22], clause 10 and A.21;
- TS 31.102[14], subclauses 4.2.44, 4.4.2.3, 5.1.1 and 5.3.2;
- TS 24.008[10], subclause 10.5.4.33;
- TS 31.111[15], subclause 7.3.1.5

### 27.22.6.4.3 Test purpose

- 1) To verify that the Terminal rejects call set-up to any number that has an entry in EF<sub>BDN</sub> if BDN service is enabled.
- 2) To verify that the Terminal allows call set-up to any number not stored in EF<sub>BDN</sub>.
- 3) To verify that the Terminal allows emergency call set-up even if the number is stored in EF<sub>BDN</sub>.
- 4) To verify that the Rel-4+ Terminal reads correctly the emergency service category stored in EF<sub>ECC</sub>.

- 5) To verify that, if the UICC responds with "not allowed", the ME does not set up the call.
- 6) To verify that, if the UICC responds with "allowed, no modification", the ME shall set up the call (or the supplementary service operation) as proposed.
- 7) To verify that, if the UICC responds with "allowed with modifications", the ME sets up the call in accordance with the response from the UICC. If the modifications involve changing the dialled number the ME does not re-check this modified number against the FDN list when FDN is enabled.
- 8) To verify that updating EF BDN or changing the status of BDN service shall be performed by the use of second application PIN only.
- 9) To verify that the ME allows call set up to a BDN number if BDN service is disabled.

#### 27.22.6.4.4 Method of tests

##### 27.22.6.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The call control service is available in the USIM Service Table.

The elementary files are coded as USIM Application Toolkit default with the following exceptions:

Barred Dialling Number service is enabled.

Fixed Dialling Number service is disabled.

Only prior to the execution of expected sequence 4.3 the FDN service shall be enabled.

The Second Application PIN (key reference 81) shall be enabled, but not verified.

Only in expected sequence 4.2B EF<sub>ECC</sub> shall be used with the following values:

EF<sub>ECC</sub> (Emergency Call Codes)

Logically:	Emergency call code:	"122";
	Emergency call code alpha identifier:	"TEST";
	Emergency call Service Category:	"Mountain Rescue".

Coding:	B1	B2	B3	B4	B5	B6	B7	B8
Hex	21	F2	FF	54	45	53	54	10

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01 ;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

## 27.22.6.4.4.2 Procedure

**Expected Sequence 4.1 (CALL CONTROL BY USIM, BDN service enabled)**

Step	Direction	Message / Action	Comments
1	User → ME	The user sets up a call to "+1357924680"	[Number as stored in record 1 of EF BDN]
2	ME → UICC	ENVELOPE CALL CONTROL 4.1.1	
3	UICC → ME	CALL CONTROL RESULT 4.1.1	[Call control result: "Not Allowed"]
4	ME → USS	The ME does not set up the call	
5	User → ME	The user sets up a call to the number stored in record 1 of EF ADN	
6	ME → UICC	ENVELOPE CALL CONTROL 4.1.2	
7	UICC → ME	CALL CONTROL RESULT 4.1.2	[Call control result: "Allowed without modifications"]
8	ME → USS	The ME sets up the call without modification	
9	User → ME	The user sets up a call to '123456'	
10	ME → UICC	ENVELOPE CALL CONTROL 4.1.3	
11	UICC → ME	CALL CONTROL RESULT 4.1.2	[Call control result: "Allowed without modifications"]
12	ME → USS	The ME sets up the call without modification	
13	User → ME	The user sets up a call to "1111"	
14	ME → UICC	ENVELOPE CALL CONTROL 4.1.4	
15	UICC → ME	CALL CONTROL RESULT 4.1.3	[Call control result: "Allowed with modifications"]
16	ME → USS	The ME sets up the call with data sent by the UICC	[Set up call to "2222"]
17	User → ME	The user shall use a MMI dependent procedure to initiate the disabling of the BDN service	
18	ME → User	Ask for second application PIN verification	
19	User → ME	The user shall enter the second application PIN	
20	ME → UICC	Update EF EST to disable BDN service	
21	UICC → ME	UICC responds with SW = '90 00'	
22	ME → User	Indicate that the BDN service was disabled successfully	
23	User → ME	The user uses the MMI to store the directory number "+876543210" in EF <sub>BDN</sub> as barred dialling number 1 (record 1).	[The alpha identifier is not changed.]
24	ME → UICC	Update EF BDN	
25	UICC → ME	UICC responds with SW = '90 00'	
26	ME → User	The user attempts to set up a call to '+876543210'.	
27a	ME → UICC	No Envelope call control is sent	
27b	ME → USS	The ME sets up the call without modification	

## ENVELOPE CALL CONTROL 4.1.1

Logically:

Device identities

Source device: ME  
Destination device: UICC

Address

TON International  
 NPI "ISDN / telephone numbering plan"  
 Dialling number string "1357924680"  
 Capability configuration parameters 1  
 This parameter is optional. If present, the contents shall not be checked.  
 Location Information  
 MCC & MNC the mobile country and network code (00F110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)  
 Capability configuration parameters 2  
 This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	06	91	31	75	29
	64	08	Note 2	13	Note 4	00	F1	10	00	01	00	01
	Note5	Note 3										

Note 1: Length of BER-TLV is '15' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### ENVELOPE CALL CONTROL 4.1.2

Logically:

Device identities  
 Source device: ME  
 Destination device: UICC  
 Address  
 TON Unknown  
 NPI "ISDN / telephone numbering plan"  
 Dialling number string "123"  
 Capability configuration parameters 1  
 This parameter is optional. If present, the contents shall not be checked.  
 Location Information  
 MCC & MNC the mobile country and network code (00F110)  
 LAC the location Area Code (0001)  
 Cell ID Cell Identity Value (0001)  
 Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 5  
 Capability configuration parameters 2  
 This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	21	F3	Note 2
	13	Note 4	00	F1	10	00	01	00	01	Note 5	Note 3	

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### ENVELOPE CALL CONTROL 4.1.3

Logically:

##### Device identities

Source device: ME  
Destination device: UICC

##### Address

TON Unknown  
NPI "ISDN / telephone numbering plan"  
Dialling number string "123456"

##### Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

##### Location Information

MCC & MNC the mobile country and network code (00F110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 5

##### Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	04	81	21	43	65
	Note 2	13	Note 4	00	F1	10	00	01	00	01	Note 5	Note 3

Note 1: Length of BER-TLV is '13' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'.

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### ENVELOPE CALL CONTROL 4.1.4

Logically:

##### Device identities

Source device: ME  
Destination device: UICC

##### Address

TON Unknown  
NPI "ISDN / telephone numbering plan"  
Dialling number string "1111"

##### Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

##### Location Information

MCC & MNC the mobile country and network code (00F110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)

Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 5

##### Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	11	11	Note 2
	13	Note 4	00	F1	10	00	01	00	01	Note 5	Note 3	

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### CALL CONTROL RESULT 4.1.1

Logically:

Call control result      Not Allowed

Coding:

BER-TLV:	01	00
----------	----	----

#### CALL CONTROL RESULT 4.1.2

Logically:

Call control result      Allowed, no modifications

Coding:

BER-TLV:	00	00
----------	----	----

#### CALL CONTROL RESULT 4.1.3

Logically:

Call control result      Allowed with modifications  
 Address  
 TON                      Unknown  
 NPI                      "ISDN / telephone numbering plan"  
 Address value          "2222"

Coding:

BER-TLV:	02	05	86	03	81	22	22
----------	----	----	----	----	----	----	----

#### Expected Sequence 4.2A (CALL CONTROL BY USIM, BDN service enabled, interaction with emergency call codes, R99 only)

Step	Direction	Message / Action	Comments
1	User → ME	The user sets up an emergency call to an emergency number stored in the terminal.	The used emergency number shall be one of the emergency call codes, which are available when a SIM/USIM is present, according to TS 22.101[22], subclause 8 is used (i.e. "112", or "911").
2a	ME → UICC	No Envelope call control is sent	
2b	ME → USS	The ME shall allow an emergency call by indicating the call setup as "Emergency Call".	
3	User → ME	End the emergency call.	

**Expected Sequence 4.2B (CALL CONTROL BY USIM, BDN service enabled, interaction with emergency call codes, Rel-4+)**

Step	Direction	Message / Action	Comments
1	User → ME	The user sets up an emergency call to an emergency number stored in the terminal.	The used emergency number shall be one of the emergency call codes, which are available when a SIM/USIM is present, according to TS 22.101[22], subclause 9 (Rel-4) or 10 (Rel-5+) is used (i.e. "112", or "911").
2a	ME → UICC	No Envelope call control is sent	
2b	ME → USS	The ME shall allow an emergency call by indicating the call setup as "Emergency Call".	
3	User → ME	End the emergency call.	
4	User → ME	The user sets up an emergency call to an emergency number stored in the USIM.	
5a	ME → UICC	No Envelope call control is sent	
5b	ME → USS	The ME shall allow an emergency call by sending the emergency service category correctly as 'Mountain Rescue'.	
6	User → ME	End the emergency call.	

**Expected Sequence 4.3 (CALL CONTROL BY USIM , FDN and BDN enabled, set up a call in EF<sub>FDN</sub>, Allowed with modifications)**

Step	Direction	Message / Action	Comments
1	User → ME	The user sets up a call to "123"	[Call control result: "Allowed with modifications"] [Set up call to "24680"the ME does not re-check this modified number against the FDN list]
2	ME → UICC	ENVELOPE CALL CONTROL 4.3.1	
3	UICC → ME	CALL CONTROL RESULT 4.3.1	
4	ME → USS	The ME sets up the call with data sent by the UICC	

ENVELOPE CALL CONTROL 4.3.1

Logically:

Device identities

Source device: ME  
Destination device: UICC

Address

TON Unknown  
NPI "ISDN / telephone numbering plan"  
Dialling number string "123"

Capability configuration parameters 1

This parameter is optional. If present, the contents shall not be checked.

Subaddress

This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)  
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 5

Capability configuration parameters 2

This parameter is optional. If present, the contents shall not be checked.

Coding:

BER-TLV:	D4	Note 1	82	02	82	81	86	03	81	21	F3	Note 2
	13	Note 4	00	F1	10	00	01	00	01	Note 5	Note 3	

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### CALL CONTROL RESULT 4.3.1

Logically:

Call control result	Allowed with modifications
Address	
TON	Unknown
NPI	"ISDN / telephone numbering plan"
Address value	"24680"

Coding:

BER-TLV:	02	06	86	04	81	42	86	F0		
----------	----	----	----	----	----	----	----	----	--	--

#### 27.22.6.4.5 Test requirement

The ME shall operate in the manner defined in expected sequences 4.1 to 4.3.

#### 27.22.6.5 Barred Dialling Number (BDN) service handling for terminals not supporting BDN

##### 27.22.6.5.1 Definition and applicability

Barred Dialling Numbers (BDN) is a service defined for the USIM. An enabled BDN service results in call restrictions for the ME. The call restrictions are controlled by the Terminal. If BDN is enabled, an ME which does not support Call Control shall allow emergency calls but shall not allow MO-CS calls.

##### 27.22.6.5.2 Conformance requirement

- 1) Recognising the state of the USIM (BDN enabled) the ME shall perform the UICC initialisation procedure as specified.
- 2) The ME shall prevent MO-CS call set-up to any number except to emergency call numbers if the BDN service is enabled.

References:

Rel-5+: TS 22.101[22], clause 10 and A.21;

TS 31.102[14], subclauses 4.2.44, 4.4.2.3, 5.1.1.2 and 5.3.2;

TS 31.111[15], subclause 7.3.1.5

### 27.22.6.5.3 Test purpose

- 1) To verify that the Terminal rejects MO-CS call set-up to any number except to emergency call numbers if BDN service is enabled.
- 2) To verify that the Terminal allows emergency call set-up even if the BDN service is enabled.

### 27.22.6.5.4 Method of tests

#### 27.22.6.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The call control service is available in the USIM Service Table.

The elementary files are coded as USIM Application Toolkit default with the following exceptions:

Barred Dialling Number service is enabled.

#### 27.22.6.5.4.2 Procedure

#### **Expected Sequence 5.1 (CALL CONTROL BY USIM, BDN service enabled, ME not supporting BDN)**

Step	Direction	Message / Action	Comments
1	User → ME	The user sets up a call to "+1357924680"	[Number as stored in record 1 of EF BDN]
2a	ME → UICC	No ENVELOPE CALL CONTROL is sent	
2b	ME → USS	The ME does not set up the call	
3	User → ME	The user sets up a call to the number stored in record 1 of EF ADN	
4a	ME → UICC	No ENVELOPE CALL CONTROL is sent	
4b	ME → USS	The ME does not set up the call	
5	User → ME	The user sets up an emergency call to "112"	
6a	ME → UICC	No ENVELOPE CALL CONTROL is sent	
6b	ME → USS	The ME sets up the emergency call to "112"	
7	User → ME	The user shall terminate the emergency call after 5 seconds. The ME returns to idle mode.	

## 27.22.7 EVENT DOWNLOAD

### 27.22.7.1 MT Call Event

#### 27.22.7.1.1 MT Call Event (normal)

##### 27.22.7.1.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.7.1.1.2 Conformance requirement

The ME shall support the EVENT: MT Call event as defined in:

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

27.22.7.1.1.3 Test purpose

To verify that the ME informs the UICC that an Event: MT Call has occurred using the ENVELOPE (EVENT DOWNLOAD - MT Call) command.

27.22.7.1.1.4 Method of test

27.22.7.1.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

27.22.7.1.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD -MT Call event)**

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	USS → ME	CALL SET UP without CLI	[MT Call Set Up Without CLI]
6	ME → UICC	ENVELOPE: EVENT DOWNLOAD - MT Call 1.1.1	
7	USS → ME	CALL DISCONNECT	
8	USS → ME	CALL SET UP with CLI	[MT Call Set Up With CLI]
9	ME → UICC	ENVELOPE: EVENT DOWNLOAD - MT Call 1.1.2	
10	USS → ME	CALL DISCONNECT	

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

Device identities

Source device: UICC  
 Destination device: ME

Event list

Event 1: MT call

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	00										

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1

Command type: SET UP EVENT LIST  
 Command qualifier: '00'  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### EVENT DOWNLOAD - MT CALL 1.1.1

Logically:

Event list: MT call event  
 Device identities  
 Source device: Network  
 Destination device: UICC  
 Transaction identifier:  
 Ti value: 0 (bit 5-7)  
 Ti flag: 0 (bit 8)

Coding:

BER-TLV:	D6	0A	19	01	00	82	02	83	81	1C	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### EVENT DOWNLOAD - MT CALL 1.1.2

Logically:

Event list: MT call event  
 Device identities  
 Source device: Network  
 Destination device: UICC  
 Transaction identifier:  
 Ti value: 0 (bit 5-7)  
 Ti flag: 0 (bit 8)  
 Address:  
 TON: Unknown  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string: "9876"

Coding:

BER-TLV:	D6	0F	19	01	00	82	02	83	81	1C	01	00
	86	03	81	89	67							

#### 27.22.7.1.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

#### 27.22.7.2 Call Connected Event

##### 27.22.7.2.1 Call Connected Event (MT and MO call)

##### 27.22.7.2.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.2.1.2 Conformance requirement

The ME shall support the EVENT: Call Connected event as defined in:

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

## 27.22.7.2.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Call Connected has occurred using the ENVELOPE (EVENT DOWNLOAD -Call Connected) command.

## 27.22.7.2.1.4 Method of test

## 27.22.7.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

## 27.22.7.2.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD -CALL CONNECTED)**

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	[EVENT: Call Connected active]
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	USS → ME	SETUP	[MT Call] Ti = 0
6	USER → ME	Accept Call Set Up	
7	ME → USS	CONNECT	
8	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Call Connected 1.1.1	
9	USS → ME	DISCONNECT	
10	USER → ME	Initiate Call to "123"	
11	ME → USS	SETUP	[MO Call] Ti = 0
12	USS → ME	CONNECT	
13	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Call Connected 1.1.2	
14	USER → ME	End Call	
15	ME → USS	DISCONNECT	

## PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

## Device identities

Source device: UICC  
 Destination device: ME

## Event list

Event 1: Call Connected

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	01										

## TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## EVENT DOWNLOAD - CALL CONNECTED 1.1.1

Logically:

Event list: Call connected

## Device identities

Source device: ME  
 Destination device: UICC

## Transaction identifier:

Ti value: 0 (bit 5-7)  
 Ti flag: 1 (bit 8)

Coding:

BER-TLV:	D6	0A	19	01	01	82	02	82	81	1C	01	80
----------	----	----	----	----	----	----	----	----	----	----	----	----

## EVENT DOWNLOAD - CALL CONNECTED 1.1.2

Logically:

Event list: Call connected

## Device identities

Source device: Network  
 Destination device: UICC

## Transaction identifier:

Ti value: 0 (bit 5-7)  
 Ti flag: 1 (bit 8)

Coding:

BER-TLV:	D6	0A	19	01	01	82	02	83	81	1C	01	80
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.7.2.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

## 27.22.7.2.2 Call Connected Event (ME supporting SET UP CALL)

## 27.22.7.2.2.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.2.2.2 Conformance requirement

Additionally the ME shall support the SET UP CALL Proactive UICC Command as defined in:

- 3GPP TS 31.111 [15] clause 7.5, clause 6.4.13 and clause 6.6.12.

## 27.22.7.2.2.3 Test purpose

To verify that the ME informs the UICC that an Event: Call Connected has occurred using the ENVELOPE (EVENT DOWNLOAD -Call Connected) command.

## 27.22.7.2.2.4 Method of test

## 27.22.7.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

## 27.22.7.2.2.4.2 Procedure

**Expected Sequence 2.1 (EVENT DOWNLOAD -CALL CONNECTED, ME supporting SET UP CALL)**

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 2.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 2.1.1	[EVENT: Call Connected active]
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 2.1.1	
5	UICC → ME	PROACTIVE COMMAND PENDING: SET UP CALL 2.1.1	
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: SET UP CALL 2.1.1	[SAT Call]
8	ME → USER	ME displays "+012340123456" during the user confirmation phase.	ME BEHAVIOUR: SET UP CALL
9	USER → ME	Confirm call set up	
10	ME → USS	SETUP	Ti=0
11	USS → ME	CONNECT	
12	ME → UICC	TERMINAL RESPONSE: SET UP CALL 2.1.1	
13	ME → UICC	ENVELOPE: CALL CONNECTED 2.1.1	

PROACTIVE COMMAND: SET UP EVENT LIST 2.1.1

Logically:

Command details

Command number: 1  
Command type: SET UP EVENT LIST  
Command qualifier: '00'

Device identities

Source device: UICC  
 Destination device: ME  
 Event list  
 Event 1: Call Connected

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	01										

TERMINAL RESPONSE: SET UP EVENT LIST 2.1.1

Logically:

Command details  
 Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

PROACTIVE COMMAND: SET UP CALL 2.1.1

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: Only if not currently busy on another call  
 Device identities  
 Source device: UICC  
 Destination device: Network  
 Alpha identifier: "+012340123456"  
 Address  
 TON: International  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "012340123456"

Coding:

BER-TLV:	D0	21	81	03	01	10	00	82	02	81	83
	05	0D	2B	30	31	32	33	34	30	31	32
	33	34	35	36	86	07	91	10	32	04	21
	43	65									

TERMINAL RESPONSE: SET UP CALL 2.1.1

Logically:

Command details  
 Command number: 1  
 Command type: SET UP CALL  
 Command qualifier: Only if not currently busy on another call  
 Device identities  
 Source device: ME

Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	10	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### EVENT DOWNLOAD - CALL CONNECTED 2.1.1

Logically:

Event list: Call connected  
 Device identities  
 Source device: Network  
 Destination device: UICC  
 Transaction identifier:  
 Ti value: 0 (bit 5-7)  
 Ti flag: 1 (bit 8)

Coding:

BER-TLV:	D6	0A	19	01	01	82	02	83	81	1C	01	80
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### 27.22.7.2.2.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 2.1'.

### 27.22.7.3 Call Disconnected Event

#### 27.22.7.3.1 Call Disconnected Event

##### 27.22.7.3.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.7.3.1.2 Conformance requirement

The ME shall support the EVENT: Call Disconnected event as defined in:

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

##### 27.22.7.3.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Call Disconnected has occurred using the ENVELOPE (EVENT DOWNLOAD -Call Disconnected) command.

##### 27.22.7.3.1.4 Method of test

###### 27.22.7.3.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

## 27.22.7.3.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD -CALL DISCONNECTED)**

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	[EVENT: Call Disconnected active]
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	USS → ME	SETUP	[ incoming call ] Ti=0
6	USER → ME	Accept Call Set Up	
7	USS → ME	RELEASE	[MT RELEASE]
8	ME→ UICC	ENVELOPE: CALL DISCONNECTED 1.1.1	
9	USS → ME	SETUP	[ incoming call ] Ti=0
10	USER → ME	Accept Call Set Up	
11	USS → ME	RELEASE COMPLETE	[MT RELEASE COMPLETE]
12	ME→ UICC	ENVELOPE: CALL DISCONNECTED 1.1.1	
13	USS → ME	SETUP	[ incoming call ] Ti=0
14	USER → ME	Accept Call Set Up	
15	USER → ME	End Call	
16	ME → USS	DISCONNECT	[MO DISCONNECT]
17	ME → UICC	ENVELOPE: CALL DISCONNECTED 1.1.2A or ENVELOPE: CALL DISCONNECTED 1.1.2B or ENVELOPE: CALL DISCONNECTED 1.1.2C	
18	USS → ME	SETUP	[ incoming call ] Ti=0
19	USER → ME	Accept Call Set Up	
20	USS → ME	DISCONNECT	[MT DISCONNECT + CAUSE: normal call clearing ]
21	ME→ UICC	ENVELOPE: CALL DISCONNECTED 1.1.3A or ENVELOPE: CALL DISCONNECTED 1.1.3B	
22	USS → ME	SETUP	Ti=0
23	USER → ME	Accept Call Set Up	
24	USS	TX POWER to XX	[RADIO LINK FAILURE]
25	ME→ UICC	ENVELOPE: CALL DISCONNECTED 1.1.4A or 1.1.4B	

## PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

## Device identities

Source device: UICC  
 Destination device: ME

## Event list

Event 1: Call Disconnected

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	02										

## TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## EVENT DOWNLOAD - CALL DISCONNECTED 1.1.1

Logically:

Event list: Call Disconnected

## Device identities

Source device: Network  
 Destination device: UICC

## Transaction identifier:

Ti value: 0 (bit 5-7)  
 Ti flag: 0 (bit 8)

Cause:

Coding:

BER-TLV:	D6	0A	19	01	02	82	02	83	81	1C	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## EVENT DOWNLOAD - CALL DISCONNECTED 1.1.2A

Logically:

Event list: Call Disconnected

## Device identities

Source device: ME  
 Destination device: UICC

## Transaction identifier:

Ti value: 0 (bit 5-7)  
 Ti flag: 1 (bit 8)

Coding:

BER-TLV:	D6	0A	19	01	02	82	02	82	81	1C	01	80
----------	----	----	----	----	----	----	----	----	----	----	----	----

## EVENT DOWNLOAD - CALL DISCONNECTED 1.1.2B

Logically:

Event list: Call Disconnected

## Device identities

Source device: ME  
 Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7)

Ti flag: 1 (bit 8)

Cause: normal call clearing

Coding:

BER-TLV:	D6	0E	19	01	02	82	02	82	81	1C	01	80
	9A	02	60	90								

#### EVENT DOWNLOAD - CALL DISCONNECTED 1.1.2C

Logically:

Event list: Call Disconnected

Device identities

Source device: ME

Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7)

Ti flag: 1 (bit 8)

Cause: normal call clearing

Coding:

BER-TLV:	D6	0E	19	01	02	82	02	82	81	1C	01	80
	9A	02	E0	90								

#### EVENT DOWNLOAD - CALL DISCONNECTED 1.1.3A

Logically:

Event list: Call Disconnected

Device identities

Source device: Network

Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7)

Ti flag: 0 (bit 8)

Cause: normal call clearing

Coding:

BER-TLV:	D6	0E	19	01	02	82	02	83	81	1C	01	00
	9A	02	60	90								

#### EVENT DOWNLOAD - CALL DISCONNECTED 1.1.3B

Logically:

Event list: Call Disconnected

Device identities

Source device: Network

Destination device: UICC

Transaction identifier:

Ti value: 0 (bit 5-7)

Ti flag: 0 (bit 8)

Cause: normal call clearing

Coding:

BER-TLV:	D6	0E	19	01	02	82	02	83	81	1C	01	00
	9A	02	E0	90								

## EVENT DOWNLOAD - CALL DISCONNECTED 1.1.4A

Logically:

Event list: Call Disconnected  
Device identities  
Source device: ME  
Destination device: UICC  
Transaction identifier:  
Ti value: 0 (bit 5-7)  
Ti flag: 1 (bit 8)  
Cause: radio link failure

Coding:

BER-TLV:	D6	0C	19	01	02	82	02	82	81	1C	01	80
	9A	00										

## EVENT DOWNLOAD - CALL DISCONNECTED 1.1.4B

Logically:

Event list: Call Disconnected  
Device identities  
Source device: ME  
Destination device: UICC  
Transaction identifier:  
Ti value: 0 (bit 5-7)  
Ti flag: 0 (bit 8)  
Cause: radio link failure

Coding:

BER-TLV:	D6	0C	19	01	02	82	02	82	81	1C	01	00
	9A	00										

## 27.22.7.3.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

## 27.22.7.4 Location Status Event

## 27.22.7.4.1 Location Status Event (normal)

## 27.22.7.4.1.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.4.1.2 Conformance requirement

The ME shall support the EVENT: Location Status event as defined in:

- 3GPP TS 31.111 [15] clause 7.5 and clause 6.4.16.

#### 27.22.7.4.1.3 Test purpose

To verify that the ME informs the UICC that an Event: MM\_IDLE state has occurred using the ENVELOPE (EVENT DOWNLOAD - Location Status) command.

#### 27.22.7.4.1.4 Method of test

##### 27.22.7.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01 ;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

Two cells are defined. Cell 1 has location area code 1 and cell 2 has location area code 2.

MS is in service on Cell 1.

27.22.7.4.1.4.2 Procedure

**Expected Sequence 1.1(EVENT DOWNLOAD -LOCATION STATUS)**

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	
5	USS	Cell 1 is switched off	
6	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Location Status 1.1.1	
7	USS	Cell 2 is switched on after Location Status 'No service' has been received in step 6	
8	ME	ME performs cell reselection to cell 2	
9	ME → USS	Location Updating Request	
10	USS → ME	Location updating accept	
11	ME → UICC	ENVELOPE: EVENT DOWNLOAD - Location Status 1.1.2A or ENVELOPE: EVENT DOWNLOAD - Location Status 1.1.2B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters] [NOTE: The inclusion of the location information is optional: (If location status indicates normal status)]

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

Device identities

Source device: UICC  
 Destination device: ME

Event list

Event 1: Location status

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82	99
	01	03										

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## EVENT DOWNLOAD - LOCATION STATUS 1.1.1

Logically:

Event list: Location status  
 Device identities  
   Source device: ME  
   Destination device: UICC  
 Location status: No service

Coding:

BER-TLV:	D6	0A	19	01	03	82	02	82	81	1B	01	02
----------	----	----	----	----	----	----	----	----	----	----	----	----

## EVENT DOWNLOAD - LOCATION STATUS 1.1.2A

Logically:

Event list: Location status  
 Device identities  
   Source device: ME  
   Destination device: UICC  
 Location status: normal service  
 Location Information  
   MCC & MNC the mobile country and network code (00F110)  
   LAC the location Area Code (0002)  
   Cell ID Cell Identity Value (0002)

Coding:

BER-TLV:	D6	13	19	01	03	82	02	82	81	1B	01	00
	13	07	00	F1	10	00	02	00	02			

## EVENT DOWNLOAD - LOCATION STATUS 1.1.2B

Logically:

Event list: Location status  
 Device identities  
   Source device: ME  
   Destination device: UICC  
 Location status: normal service  
 Location Information  
   MCC & MNC the mobile country and network code (001110)  
   LAC the location Area Code (0002)  
   Cell ID Cell Identity Value (0002)

Coding:

BER-TLV:	D6	13	19	01	03	82	02	82	81	1B	01	00
	13	07	00	11	10	00	02	00	02			

## 27.22.7.4.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

## 27.22.7.5 User Activity Event

### 27.22.7.5.1 User Activity Event (normal)

#### 27.22.7.5.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.5.1.2 Conformance Requirement

The ME shall support the EVENT DOWNLOAD -USER ACTIVITY as defined in:

- 3GPP TS 31.111 [15] clause 5.2, clause 6.4.16, clause 6.8, clause 6.6.16, clause 6.11, clause 7.5, clause 8.6 and clause 8.25.

#### 27.22.7.5.1.3 Test purpose

To verify that the ME performed correctly the procedure of USER ACTIVITY EVENT.

#### 27.22.7.5.1.4 Method of Test

##### 27.22.7.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.7.5.1.4.2 Procedure

#### **Expected Sequence 1.1 (EVENT DOWNLOAD -USER ACTIVITY)**

See ETSI TS 102 384 [26] in subclause 27.22.7.5.1.4.2, Expected Sequence 1.1.

##### 27.22.7.5.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.7.6 Idle screen available event

### 27.22.7.6.1 Idle Screen Available (normal)

#### 27.22.7.6.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.6.1.2 Conformance requirement

The ME shall support the EVENT: IDLE SCREEN AVAILABLE event as defined in:

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

##### 27.22.7.6.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Idle Screen Available has occurred using the ENVELOPE (EVENT DOWNLOAD - IDLE SCREEN AVAILABLE) command.

27.22.7.6.1.4 Method of test

27.22.7.6.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.7.6.1.4.2 Procedure

#### **Expected Sequence 1.1 (EVENT DOWNLOAD - IDLE SCREEN AVAILABLE)**

See ETSI TS 102 384 [26] in subclause 27.22.7.6.1.4.2, Expected Sequence 1.1.

27.22.7.6.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

### **27.22.7.7 Card reader status event**

27.22.7.7.1 Card Reader Status (normal)

27.22.7.7.1.1 Definition and applicability

See clause 3.2.2.

27.22.7.7.1.2 Conformance requirement

The ME shall support the EVENT: Call Card Reader Status event as defined in:

- 3GPP TS 31.111 [15] clause 4.7, clause 4.9, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, clause 8.25, clause 8.33, annex F, annex G, clause 8.25 and clause 8.7.

27.22.7.7.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Card Reader Status has changed using the ENVELOPE (EVENT DOWNLOAD - Card Reader Status) command.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

27.22.7.7.1.4 Method of test

27.22.7.7.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

27.22.7.7.1.4.2 Procedure

#### **Expected Sequence 1.1 (EVENT DOWNLOAD, Card reader status, Card reader 1, card reader attached, no card inserted)**

See ETSI TS 102 384 [26] in subclause 27.22.7.7.1.4.2, Expected Sequence 1.1.

#### 27.22.7.7.1.5 Test requirement

The behaviour of the test is as defined in expected Sequence 1.1.

#### 27.22.7.7.2 Card Reader Status(detachable card reader)

##### 27.22.7.7.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.7.7.2.2 Conformance requirement

The ME shall support the EVENT: Call Card Reader Status event as defined in:

- 3GPP TS 31.111 [15] clause 4.7, clause 4.9, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, clause 8.25, clause 8.33, annex F, annex G, clause 8.25 and clause 8.7.

##### 27.22.7.7.2.3 Test purpose

To verify that the ME informs the UICC that an Event: Card Reader Status has changed using the ENVELOPE (EVENT DOWNLOAD - Card Reader Status) command.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen as an example.

##### 27.22.7.7.2.4 Method of test

###### 27.22.7.7.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

###### 27.22.7.7.2.4.2 Procedure

#### **Expected Sequence 2.1 (EVENT DOWNLOAD, Detachable reader, Card reader 1, detachable card reader not attached, no card inserted)**

See ETSI TS 102 384 [26] in subclause 27.22.7.7.2.4.2, Expected Sequence 2.1.

##### 27.22.7.7.2.5 Test requirement

The behaviour of the test is as defined in expected Sequence 2.1.

#### 27.22.7.8 Language selection event

##### 27.22.7.8.1 Language selection event (normal)

###### 27.22.7.8.1.1 Definition and applicability

See clause 3.2.2.

###### 27.22.7.8.1.2 Conformance requirement

The ME shall support the EVENT: LANGUAGE SELECTION event as defined in:

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

#### 27.22.7.8.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Language selection has occurred using the ENVELOPE (EVENT DOWNLOAD - LANGUAGE SELECTION ) command.

#### 27.22.7.8.1.4 Method of test

##### 27.22.7.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The current language shall have been set to English. Another language has to be supported, German is an example.

##### 27.22.7.8.1.4.2 Procedure

#### **Expected Sequence 1.1 (EVENT DOWNLOAD - LANGUAGE SELECTION)**

See ETSI TS 102 384 [26] in subclause 27.22.7.8.1.4.2, Expected Sequence 1.1.

#### 27.22.7.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

### 27.22.7.9 Browser termination event

#### 27.22.7.9.1 Browser termination (normal)

##### 27.22.7.9.1.1 Definition and applicability

This test is only applicable to ME's that support the EVENT: browser termination event driven information.

##### 27.22.7.9.1.2 Conformance requirement

The ME shall support the EVENT: Browser termination event as defined in:

- 3GPP TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, , clause 8.25, clause 8.51, annex F and clause 8.7.

##### 27.22.7.9.1.3 Test purpose

To verify that the ME informs the UICC of an Event: Browser termination using the ENVELOPE (EVENT DOWNLOAD - Browser Termination) command.

This test applies for MEs which have a browser.

##### 27.22.7.9.1.4 Method of test

##### 27.22.7.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

A valid access to a Wap gateway is required. The default browser parameters (IP address, gateway/proxy identity, called number...) of the tested mobile shall be properly filled to access that gateway.

27.22.7.9.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD - Browser termination)**

Step	Direction	Message / Action	Comments
1	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	[EVENT: Browser termination Status]
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	[Successfully]
5	User→ME	Launch the browser with the URL selected by the user	
6	ME→USS	The ME attempts to launch the session with the default browser parameters and the URL selected by the user.	
7	User→ME	Stop the session and the browser.	
8	ME→ UICC	ENVELOPE: BROWSER TERMINATION 1.1.1	

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

Device identities

Source device: UICC  
 Destination device: ME

Event list

Event 1: Browser termination

Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82
	99	01	08								

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

ENVELOPE: EVENT DOWNLOAD BROWSER TERMINATION 1.1.1

Logically:

## Event list

Event 1:	Browser termination
Device identities	
Source device:	ME
Destination device:	UICC
Browser termination cause:	User termination

## Coding:

BER-TLV:	D6	0A	99	01	08	82	02	82	81	B4	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## 27.22.7.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.7.10 Data available event

## 27.22.7.10.1 Definition and applicability

See clause 3.2.2.

## 27.22.7.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

Additionally the ME shall support ENVELOPE (EVENT DOWNLOAD - Data available).

## 27.22.7.10.3 Test purpose

To verify that the ME shall send an ENVELOPE (EVENT DOWNLOAD - Data available) to the UICC after the ME receives a packet of data from the server by the BIP channel previously opened.

## 27.22.7.10.4 Method of test

## 27.22.7.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure. The UICC must have sent the SET UP EVENT LIST to the ME to supply a set of events (event Data available).

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, for test cases using packet services:

## Bearer Parameters

Precedence Class:	03
Delay Class:	04
Reliability Class:	03

Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

## 27.22.7.10.4.2 Procedure

**Expected sequence 1.1 (EVENT DOWNLOAD - Data available)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	[Command performed successfully]
4	ME → USER	The ME may display channel opening information	
5	ME → USS	PDP context activation request	
6	USS → ME	PDP context activation accept	
7	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	
8	UICC → ME	PROACTIVE COMMAND PENDING: SEND DATA 1.1.1	
9	ME → UICC	FETCH	
10	UICC → ME	PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1	
11	ME → USS	Transfer of 8 Bytes of data to the USS through channel 1	[To retrieve ME's port number]
12	ME → UICC	TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1	[Command performed successfully]
13	USS → ME	Data sent through the BIP channel using the ME's port number, which was retrieved in step 11	
14	ME → UICC	ENVELOPE 1.1.1 (Event-Data Available)	

## PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03

Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1000  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)  
 UICC/ME interface transport level  
 Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

## Coding:

BER-TLV	D0	42	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	03	E8
	47	0A	06	54	65	73	74	47	70	02	72	73
	0D	08	F4	55	73	65	72	4C	6F	67	0D	08
	F4	55	73	65	72	50	77	64	3C	03	01	AD
	9C	3E	05	21	01	01	01	01				

## TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

## Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

## Channel status

Channel identifier 1 and link established or PDP context activated

## Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1000

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	03	E8							

## TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

## Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: ME  
Destination device: UICC

## Result

General Result: Command performed successfully

## Channel status

Channel identifier 1 and link established or PDP context activated

## Bearer description

Bearer type: GPRS  
Bearer parameter:  
Precedence Class: 00  
Delay Class: 04  
Reliability Class: 03  
Peak throughput class: 04  
Mean throughput class: 31  
Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1000

## Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							

## PROACTIVE COMMAND: SEND DATA 1.1.1

## Logically:

## Command details

Command number: 1  
Command type: SEND DATA  
Command qualifier: Send Immediately

## Device identities

Source device: UICC  
Destination device: Channel 1

## Channel Data

Channel Data: 00 01 .. 07 (8 Bytes of data)

## Coding:

BER-TLV:	D0	13	81	03	01	43	01	82	02	81	21	B6
	08	00	01	02	03	04	05	06	07			

## TERMINAL RESPONSE: SEND DATA 1.1.1

## Logically:

## Command details

Command number: 1  
Command type: SEND DATA  
Command qualifier: Send Immediately

## Device identities

Source device: ME  
Destination device: UICC

## Result

General Result: Command performed successfully  
Channel data length: More than 255 bytes of space available in the Tx buffer

## Coding:

BER-TLV:	81	03	01	43	01	82	02	82	81	83	01	00
	B7	01	FF									

ENVELOPE: EVENT DOWNLOAD - Data available 1.1.1

Logically:

Event list  
 Event: Data available  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Channel status  
 Channel status: Channel 1 open, link established  
 Channel Data Length  
 Channel data length: 8 Bytes available in Rx buffer

Coding:

BER-TLV:	D6	0E	99	01	09	82	02	82	81	B8	02	81
	00	B7	01	08								

#### 27.22.7.10.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

### 27.22.7.11 Channel Status event

#### 27.22.7.11.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.11.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- 3GPP TS 31.111 [15].

Additionally the ME shall support ENVELOPE (EVENT DOWNLOAD - Channel Status).

#### 27.22.7.11.3 Test purpose

To verify that the ME shall send an ENVELOPE (EVENT DOWNLOAD - Channel Status) to the UICC after the link dropped between the NETWORK and the ME.

#### 27.22.7.11.4 Method of test

##### 27.22.7.11.4.1 Initial conditions

The ME is connected to the USIM Simulator and the System Simulator. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, for test cases using packet services:

Bearer Parameters

Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## GPRS Parameters

Network access name: TestGp.rs  
 User login: UserLog  
 User password: UserPwd

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444  
 Data destination address 01.01.01.01

## 27.22.7.11.4.2 Procedure

**Expected sequence 1.1 (EVENT DOWNLOAD - Channel Status on a link dropped)**

Step	Direction	MESSAGE / Action	Comments
1	UICC → ME	PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1	
2	ME → UICC	FETCH	
3	UICC → ME	PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1	[EVENT: channel status]
4	ME → UICC	TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1	[command performed successfully]
5	UICC → ME	PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1	See initial conditions
6	ME → UICC	FETCH	
7	UICC → ME	PROACTIVE COMMAND: OPEN CHANNEL 1.1.1	
8	ME → USER	The ME may display channel opening information	
9	ME → USS	PDP context activation request	
10	USS → ME	PDP context activation accept	
11	ME → UICC	TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B	[Command performed successfully]
12	USS → ME	Link dropped	
13	ME → UICC	ENVELOPE 1.1.1 (Event-Channel Status)	

## PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

## Logically:

## Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

## Device identities

Source device: UICC  
 Destination device: ME

## Event list

Event 1: Channel Status

## Coding:

BER-TLV:	D0	0C	81	03	01	05	00	82	02	81	82
	99	01	0A								

## TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: SET UP EVENT LIST  
 Command qualifier: '00'

## Device identities

Source device: ME  
 Destination device: UICC

## Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	05	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

## PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

## Device identities

Source device: UICC  
 Destination device: ME

## Bearer

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

## Buffer

Buffer size: 1000  
 Network access name: TestGp.rs  
 Text String: UserLog (User login)  
 Text String: UserPwd (User password)

## UICC/ME interface transport level

Transport format: UDP  
 Port number: 44444

Data destination address 01.01.01.01

Coding:

BER-TLV	D0	42	81	03	01	40	01	82	02	81	82	35
	07	02	03	04	03	04	1F	02	39	02	03	E8
	47	0A	06	54	65	73	74	47	70	02	72	73
	0D	08	F4	55	73	65	72	4C	6F	67	0D	08
	F4	55	73	65	72	50	77	64	3C	03	01	AD
	9C	3E	05	21	01	01	01	01				

## TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Channel status

Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 03  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	03	04	03	04	1F
	02	39	02	03	E8							

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

Command details

Command number: 1  
 Command type: OPEN CHANNEL  
 Command qualifier: immediate link establishment

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Command performed successfully

Channel status

Channel identifier 1 and link established or PDP context activated

Bearer description

Bearer type: GPRS  
 Bearer parameter:  
 Precedence Class: 00  
 Delay Class: 04  
 Reliability Class: 03  
 Peak throughput class: 04  
 Mean throughput class: 31  
 Packet data protocol: 02 (IP)

Buffer

Buffer size: 1000

Coding:

BER-TLV:	81	03	01	40	01	82	02	82	81	83	01	00
	38	02	81	00	35	07	02	00	04	03	04	1F
	02	39	02	03	E8							

ENVELOPE: EVENT DOWNLOAD - Channel Status 1.1.1

Logically:

Event list  
 Event: Channel Status  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Channel status  
 Channel status: Channel 1, link dropped

Coding:

BER-TLV:	D6	0B	99	01	0A	82	02	82	81	B8	02	01
	05											

#### 27.22.7.11.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

#### 27.22.7.12 Access Technology Change event

TBD

#### 27.22.7.13 Local Connection event

TBD

#### 27.22.7.14 Network search mode change event

TBD

#### 27.22.7.15 Browsing status event

TBD

### 27.22.8 MO SHORT MESSAGE CONTROL BY USIM

#### 27.22.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.8.2 Conformance requirement

The ME shall support the MO SEND SHORT MESSAGE CONTROL facility as defined in:

- 3GPP TS 31.111 [15] clause 7.3.2.

The ME shall also support the SEND SMS facility as specified in

- 3GPP TS 31.111 [15] clause 6.4.10

#### 27.22.8.3 Test purpose

To verify that for all SMS sending attempts, even those resulting from a SEND SHORT MESSAGE proactive UICC command, the ME shall first pass the RP\_destination\_address of the service center and the TP\_Destination\_Address to the UICC, using the ENVELOPE (MO Short Message CONTROL).

To verify that if the UICC responds with '90 00', the ME shall send the SMS with the address unchanged.

To verify that if the UICC responds with '93 00', the ME shall not send the SMS and may retry the command.

To verify that if the UICC returns response data, the ME shall use the response data appropriately to send the SM as proposed, not send the SM, or send the SM using the data supplied by the UICC.

To verify that, in the case where the initial SM request results from a proactive SEND SHORT MESSAGE, if the MO SMS CONTROL result is "not allowed" or "allowed with modifications", the ME shall inform the UICC using TERMINAL RESPONSE "interaction with call control by UICC or MO short message control by USIM, action not allowed".

#### 27.22.8.4 Method of tests

##### 27.22.8.4.1 Initial conditions

The ME is connected to the System Simulator and the USIM Simulator.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The MO SMS control service is available in the USIM Service Table.

The SMS service center address in the ME shall be set to '+112233445566778' prior to the execution of the tests.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

## 27.22.8.4.2 Procedure

**Expected Sequence 1.1 (MO SM CONTROL BY USIM , with Proactive command, Allowed, no modification')**

Step	Direction	Message / Action	Comments
1	UICC -> ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.1.1	
2	ME -> UICC	FETCH	
3	UICC -> ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1	
4	ME -> USER	Display "Send SM"	[Alpha Identifier]
5	ME -> UICC	ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1A Or ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
6	UICC -> ME	MO SMS CONTROL RESULT 1.1.1	[ 'Allowed, no modification']
7	ME -> USS	Send SMS-PP Message 1.1	[The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1.1 without modification]
8	USS -> ME	SMS RP-ACK	
9	ME -> UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1	

## PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1

Logically:

## Command details

Command number: 1  
 Command type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

## Device identities

Source device: UICC  
 Destination device: Network  
 Alpha identifier: "Send SM"

## Address

TON: International number  
 NPI: "ISDN / telephone numbering plan"  
 Dialling number string "112233445566778"

## SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field not present  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "00"  
 TP-DA  
 TON International number  
 NPI "ISDN / telephone numbering plan"  
 Address value "012345678"  
 TP-PID Short message type 0  
 TP-DCS  
 Message coding 8-bit data  
 Message class class 0  
 TP-UDL 12  
 TP-UD "Test Message"

Coding:

BER-TLV:	D0	37	81	03	01	13	00	82	02	81	83	85
	07	53	65	6E	64	20	53	4D	86	09	91	11
	22	33	44	55	66	77	F8	8B	18	01	00	09
	91	10	32	54	76	F8	40	F4	0C	54	65	73
	74	20	4D	65	73	73	61	67	65			

## SMS-PP (SEND SHORT MESSAGE) Message 1.1

Logically:

## SMS TPDU

TP-MTI	SMS-SUBMIT
TP-RD	Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF	TP-VP field not present
TP-RP	TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI	The TP-UD field contains only the short message
TP-SRR	A status report is not requested
TP-MR	"01"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"012345678"
TP-PID	Short message type 0
TP-DCS	
Message coding	8-bit data
Message class	class 0
TP-UDL	12
TP-UD	"Test Message"

Coding:

Coding	01	01	09	91	10	32	54	76	F8	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

## ENVELOPE MO SHORT MESSAGE CONTROL 1.1.1A

Logically:

## Device identities

Source device:	ME
Destination device:	UICC

## RP Destination Address

TON:	International
NPI:	"ISDN / telephone numbering plan" or "unknown"
Dialling number string	'112233445566778'

## TP Destination Address

TON:	International
NPI:	"ISDN / telephone numbering plan" or "unknown"
Dialling number string	'012345678'

## Location Information

MCC & MNC	the mobile country and network code (00F110)
LAC	the location Area Code (0001)
Cell ID	Cell Identity Value (0001)
Extended Cell ID	RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

Coding	D5	Note 1	02	02	82	81	06	09	91	11	22
	33	44	55	66	77	F8	06	06	91	10	32
	54	76	F8	13	Note 2	00	F1	10	00	01	00
	01	Note 3									

Note 1: Length of BER-TLV is '20' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

#### ENVELOPE MO SHORT MESSAGE CONTROL 1.1.1B

Logically:

##### Device identities

Source device: ME  
Destination device: UICC

##### RP Destination Address

TON: International  
NPI: "ISDN / telephone numbering plan" or "unknown"  
Dialling number string '112233445566778'

##### TP Destination Address

TON: International  
NPI: "ISDN / telephone numbering plan" or "unknown"  
Dialling number string '012345678'

##### Location Information

MCC & MNC the mobile country and network code (001110)  
LAC the location Area Code (0001)  
Cell ID Cell Identity Value (0001)

Coding:

BER-TLV:	D5	20	02	02	82	81	06	09	91	11	22
	33	44	55	66	77	F8	06	06	91	10	32
	54	76	F8	13	07	00	11	10	00	01	00
	01										

#### MO SHORT MESSAGE CONTROL RESULT 1.1.1

Logically:

MO Short Message control result : '00' = Allowed, no modification

Coding:

BER-TLV:	00	00
----------	----	----

#### TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1

Logically:

##### Command details

Command number: 1  
Command type: SEND SHORT MESSAGE  
Command qualifier: packing not required

##### Device identities

Source device: ME  
Destination device: UICC

##### Result

General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

**Expected Sequence 1.2 (MO SM CONTROL BY USIM , with user SMS, Allowed, no modification')**

Step	Direction	Message / Action	Comments
1	USER -> ME	The user makes a SMS with the user data 'Test Message' and sends it to +012345678.	[The data entered and the ME settings shall lead to the same SMS-TPDU as defined in SMS-PP (SEND SHORT MESSAGE) Message 1.2.
2	ME -> UICC	ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1A or ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC -> ME	MO SHORT MESSAGE CONTROL RESULT 1.1.1	[ 'Allowed, no modification']
4	ME -> USS	Send SMS-PP Message 1.2	[The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1.2 without modification]
5	USS -> ME	SMS RP-ACK	

## SMS-PP (SEND SHORT MESSAGE) Message 1.2

Logically:

## SMS TPDU

TP-MTI	SMS-SUBMIT
TP-RD	Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF	TP-VP field present - relative format
TP-RP	TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI	The TP-UD field contains only the short message
TP-SRR	A status report is not requested
TP-MR	"01"
TP-DA	
TON	International number
NPI	"ISDN / telephone numbering plan"
Address value	"012345678"
TP-PID	0
TP-DCS	
Message coding	GSM 7 bit default alphabet
Message class	No message class
TP-VP	Maximum
TP-UDL	12
TP-UD	"Test Message"

Coding:

Coding	11	01	09	91	10	32	54	76	F8	00	00	FF
	0C	D4	F2	9C	0E	6A	96	E7	F3	F0	B9	0C

**Expected Sequence 1.3 (MO SM CONTROL BY USIM , with Proactive command, Not allowed')**

Step	Direction	Message / Action	Comments
1	UICC -> ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.1.1	
2	ME -> UICC	FETCH	
3	UICC -> ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1	
4	ME -> USER	Display "Send SM"	[Alpha Identifier]
5	ME -> UICC	ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1A or ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
6	UICC -> ME	MO SHORT MESSAGE CONTROL RESULT 1.3.1	[ 'not Allowed']
7	ME -> UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.3.1	[ Permanent Problem - Interaction with Call Control or MO short message control by USIM ]
8	ME -> USS	The ME does not send the Short Message	

MO SHORT MESSAGE CONTROL RESULT 1.3.1

Logically:

MO Short Message control result : '01' = Not Allowed

Coding:

BER-TLV:	01	00
----------	----	----

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.3.1

Logically:

Command details

Command number: 01  
 Command Type: SEND SHORT MESSAGE  
 Command qualifier: packing not required

Device identities

Source device: ME  
 Destination device: UICC

Result

General Result: Interaction with call control or MO-SM by USIM permanent problem  
 Additional information: Action not allowed

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	02	39
	01											

**Expected Sequence 1.4 (MO SM CONTROL BY USIM , with user SMS, Not allowed ')**

Step	Direction	Message / Action	Comments
1	USER -> ME	The user makes a SMS with the user data 'Test Message' and sends it to +012345678.	[The data entered and the ME settings shall lead to the same SMS-TPDU as defined in SMS-PP (SEND SHORT MESSAGE) Message 1.2.
2	ME -> UICC	ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1A or ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC -> ME	MO SM CONTROL RESULT 1.3.1	[ 'Not allowed']
4	ME -> USS	The ME does not send the Short Message	

**Expected Sequence 1.5 (MO SM CONTROL BY USIM , with Proactive command, Allowed with modifications')**

Step	Direction	Message / Action	Comments
1	UICC -> ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.1.1	
2	ME -> UICC	FETCH	
3	UICC -> ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1	Send SMS to '+012345678'
4	ME -> USER	Display "Send SM"	[Alpha Identifier]
5	ME -> UICC	ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1A or ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
6	UICC -> ME	MO SM CONTROL RESULT 1.5.1	['Allowed with modifications']
7	ME -> USS	Send SMS-PP Message 1.5	[The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1.5 with the data provided by the UICC to the changed Service Center Address '+112233445566779' ]
8	USS -> ME	SMS RP-ACK	
9	ME -> UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.5.1	

**MO SHORT MESSAGE CONTROL RESULT 1.5.1**

Logically:

MO Short Message control result : '02' = Allowed with modifications

RP Destination\_Address of the Service Center

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string: '112233445566779'

TP Destination Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string: '012345679'

Coding:

02	13	86	09	91	11	22	33	44	55	66
77	F9	86	06	91	10	32	54	76	F9	

**SMS-PP (SEND SHORT MESSAGE) Message 1.5**

Logically:

SMS TPDU

TP-MTI SMS-SUBMIT

TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM

TP-VPF TP-VP field not present

TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

TP-UDHI The TP-UD field contains only the short message

TP-SRR A status report is not requested

TP-MR "01"

TP-DA

TON International number

NPI "ISDN / telephone numbering plan"

Address value "012345679"

TP-PID Short message type 0

TP-DCS  
 Message coding 8-bit data  
 Message class class 0  
 TP-UDL 12  
 TP-UD "Test Message"

Coding:

Coding	01	01	09	91	10	32	54	76	F9	40	F4	0C
	54	65	73	74	20	4D	65	73	73	61	67	65

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.5.1

Logically:

Command details  
 Command number: 01  
 Command Type: SEND SHORT MESSAGE  
 Command qualifier: packing not required  
 Device identities  
 Source device: ME  
 Destination device: UICC  
 Result  
 General Result: Command performed successfully

Coding:

BER-TLV:	81	03	01	13	00	82	02	82	81	83	01	00
----------	----	----	----	----	----	----	----	----	----	----	----	----

#### Expected Sequence 1.6 (MO SM CONTROL BY USIM , with user SMS, Allowed with modifications')

Step	Direction	Message / Action	Comments
1	USER -> ME	The user makes a SMS with the user data 'Test Message' and sends it to +012345678.	[The data entered and the ME settings shall lead to the same SMS-TPDU as defined in SMS-PP (SEND SHORT MESSAGE) Message 1.2.
2	ME -> UICC	ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1A or ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC -> ME	MO SM CONTROL RESULT 1.5.1	[ 'Allowed with modifications']
4	ME-> USS	Send SMS-PP Message 1.6	[The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1. 6 with the data provided by the UICC to the changed Service Center Adress '+112233445566779']
5	USS -> ME	SMS RP-ACK	

SMS-PP (SEND SHORT MESSAGE) Message 1.6

Logically:

SMS TPDU

TP-MTI SMS-SUBMIT  
 TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM  
 TP-VPF TP-VP field present - relative format  
 TP-RP TP-Reply-Path is not set in this SMS-SUBMIT  
 TP-UDHI The TP-UD field contains only the short message  
 TP-SRR A status report is not requested  
 TP-MR "01"  
 TP-DA  
 TON International number

NPI "ISDN / telephone numbering plan"  
 Address value "012345679"  
 TP-PID 0  
 TP-DCS  
 Message coding TP-VP field present - relative format  
 Message class No message class  
 TP-VP Maximum  
 TP-UDL 12  
 TP-UD "Test Message"

Coding:

Coding	11	01	09	91	10	32	54	76	F9	00	00	FF
	0C	D4	F2	9C	0E	6A	96	E7	F3	F0	B9	0C

**Expected Sequence 1.7 (MO SM CONTROL BY USIM , with Proactive command, the USIM responds with '90 00', Allowed, no modification)**

Step	Direction	Message / Action	Comments
1	UICC -> ME	PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.1.1	
2	ME -> UICC	FETCH	
3	UICC -> ME	PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1	Send SMS to '+012345678'
4	ME -> USER	Display "Send SM"	[Alpha Identifier]
5	ME -> UICC	ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1A	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
		or	
6	UICC -> ME	ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1B	
7	ME -> USS	90 00 Send SMS-PP	[The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1.1 without modification]
8	USS -> ME	SMS RP-ACK	
9	ME -> UICC	TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1	

**Expected Sequence 1.8 (MO SM CONTROL BY USIM , Send Short Message attempt by user, the USIM responds with '90 00', Allowed, no modification)**

Step	Direction	Message / Action	Comments
1	User → ME	The user makes a SMS with the user data 'Test Message' and sends it to +012345678.	[The data entered and the ME settings shall lead to the same SMS-TPDU as defined in SMS-PP (SEND SHORT MESSAGE) Message 1.2.
2	ME → UICC	ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1 A or ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1B	[Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters]
3	UICC → ME	90 00	
4	ME → USS	Send SMS-PP	[The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1.2 without modification]
5	USS -> ME	SMS RP-ACK	

Expected Sequence 1.9void

### 27.22.8.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.9.

## 27.22.9 Handling of command number

### 27.22.9.1 Definition and applicability

See clause 3.2.2.

### 27.22.9.2 Conformance requirement

The ME shall support the facility as defined in ETSI TS 102 223 [16] clause 6.5.1, clause 6.8 and clause 8.6

### 27.22.9.3 Test purpose

To verify that the ME sends a Terminal Response with the Command number equivalent to the value in the corresponding proactive command.

### 27.22.9.4 Method of tests

#### 27.22.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

The ME shall support the DISPLAY TEXT command.

#### 27.22.9.4.2 Procedure

##### **Expected Sequence 1.1 (DISPLAY TEXT normal priority, Unpacked 8 bit data for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.9.4.2, Expected Sequence 1.1.

### 27.22.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1

## Annex A (normative): Details of Test-SIM (TestSIM)

The TestSIM shall be able to present the following data:

### ANSWER TO RESET

Logically:

TS (Initial character):	'3B'
T0 (Format character):	'86' (Following interface characters: TD(1), number of historical characters: 6)
TD1:	'00' (Following interface characters: none, Transfer protocol: T=0)
T1:	91
T2:	99
T3:	00
T4:	12
T5:	C1
T6:	00

Coding:

Coding:	3B	86	00	91	99	00	12	C1	00
---------	----	----	----	----	----	----	----	----	----

1. For a successful outcome of the command "Select MasterFile" the TestSIM shall send SW1/SW2 "9F 1B".
2. For a successful outcome of the command "Get Response with Length 1B" on the MasterFile the TestSIM shall respond:

RFU:	'00 00'
Not allocated memory:	'653 bytes'
File ID:	Master File
Type of file:	MF
RFU:	00 00 22 FF 01'
Length of following data:	14 bytes'
File characteristics:	
Clock Stop:	Not allowed
Min. frequency for GSM algorithm:	13/8 MHz
Technology identification:	3V Technology SIM
CHV1:	disabled
DFs in current directory:	2
EFs in current directory:	8
Number of CHV and admin. Codes:	3
RFU byte 18:	00
CHV1 status:	
False representations remaining:	3
RFU-bits 7-5:	000
Secret code:	Initialized
Unlock CHV1 status:	
False representations remaining:	10
RFU-bits 7-5:	000
Secret code:	Initialized
CHV2 status:	
False representations remaining:	3
RFU-bits 7-5:	000
Secret code:	Initialized
Unlock CHV2 status:	
False representations remaining:	10
RFU-bits 7-5:	000
Secret code:	Initialized
RFU bytes 23:	00

Reserved for admin. management: 00 83 00 FF  
 Status Words  
 SW1 / SW2: Normal ending of command

Coding:

Coding	00	00	02	8D	3F	00	01	00	00	22	FF	01
	0E	9B	02	08	03	00	83	8A	83	8A	00	00
	83	00	FF	90	00							

1. For a successful outcome of the command "Select GSM" the TestSIM shall send SW1/SW2 "9F 1B".
2. For a successful outcome of the command "Select PLMN" the TestSIM shall send SW1/SW2 "9F 0F".
3. EF<sub>PLMN</sub> Information:

RFU-Bytes 1-2: 00 00  
 File size: 102 bytes  
 File ID: 6F30  
 Type of File: Elementary file  
 Byte 8  
 RFU: 00  
 Access Condition:  
 UPDATE: CHV1  
 READ/SEEK: CHV1  
 RFU-bits 4-1: 1111  
 INCREASE: NEVER  
 INVALIDATE: NEVER  
 REHABILITATE: NEVER  
 File Status:  
 Invalidation status: File not invalidated  
 Readable/updateable: Not readable/updatable when invalidated  
 RFU-bits 8-4, 2: 0000 0  
 Length of following data: 2 bytes  
 Structure: Transparent  
 Length of record: 00

The initial coding of the EF<sub>PLMN</sub> shall be FF FF ... FF (logically: Empty).

## Annex B (normative): Details of terminal profile support

**Table E.1: TERMINAL PROFILE support**

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
1	1.1	Profile Download	3GPP TS 31.111 §5.2	R99	M		PD_Pro_Dvnl
2	1.2	SMS-PP data download	3GPP TS 31.111 §5.2	R99	M		PD_SMS_PP
3	1.3	Cell Broadcast data download	3GPP TS 31.111 §5.2	R99	M		PD_CB
4	1.4	Menu selection	3GPP TS 31.111 §5.2	R99	M		PD_Menu_sel
5	1.5	Bit =1 if SMS-PP data Download supported	3GPP TS 31.111 §5.2	R99	M		PD_SMS_PP
6	1.6	Timer expiration	3GPP TS 31.111 §5.	R99	M		PD_TExpir
7	1.7	Bit=1 if Call control supported	3GPP TS 31.111 §5.2.	R99	M		PD_CC
8	1.8	Bit=1 if Call control supported	3GPP TS 31.111 §5.2	R99	M		PD_CC
9	2.1	Command result	3GPP TS 31.111 §5.2	R99	M		PD_Cmd_Res
10	2.2	Call Control by USIM	3GPP TS 31.111 §5.2	R99	M		PD_CC
11	2.3	Bit=1 if Call control supported	3GPP TS 31.111 §5.2	R99	M		PD_CC
12	2.4	MO short message control by USIM	3GPP TS 31.111 §5.2	R99	M		PD_MO_SMS_CC
13	2.5	Bit=1 if Call control supported	3GPP TS 31.111 §5.2	R99	M		PD_CC
14	2.6	UCS2 Entry supported	3GPP TS 31.111 §5.2	R99	C203		PD_UCS2_entry
15	2.7	UCS2 Display supported	3GPP TS 31.111 §5.2	R99	C203		PD_UCS2_Display
16	2.8	Bit=1 if Display Text supported	3GPP TS 31.111 §5.2	R99	M		PD_Display_Text
17	3.1	DISPLAY TEXT	3GPP TS 31.111 §5.2	R99	M		PD_Display_Text
18	3.2	GET INKEY	3GPP TS 31.111 §5.2	R99	M		PD_Get_Inkey
19	3.3	GET INPUT	3GPP TS 31.111 §5.2	R99	M		PD_Get_Input
20	3.4	MORE TIME	3GPP TS 31.111 §5.2	R99	M		PD_More_Time
21	3.5	PLAY TONE	3GPP TS 31.111 §5.2 3GPP TS 11.14, 5	R99	M		PD_Play_Tone
22	3.6	POLL INTERVAL	3GPP TS 31.111 §5.2 3GPP TS 11.14, 5	R99	M		PD_Poll_interval
23	3.7	POLLING OFF	3GPP TS 31.111 §5.2	R99	M		PD_Polling_Off
24	3.8	REFRESH	3GPP TS 31.111 §5.2	R99	M		PD_Refresh
25	4.1	SELECT ITEM	3GPP TS 31.111 §5.2	R99	M		PD_Select_Item
26	4.2	SEND SHORT MESSAGE	3GPP TS 31.111 §5.2	R99	M		PD_Send_SMS
27	4.3	SEND SS	3GPP TS 31.111 §5.2	R99	M		PD_Send_SS

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
28	4.4	SEND USSD	3GPP TS 31.111 §5.2	R99	M		PD_Send_USSD
29	4.5	SET UP CALL	3GPP TS 31.111 §5.2	R99	M		PD_SetUp_Call
30	4.6	SET UP MENU	3GPP TS 31.111 §5.2	R99	M		PD_SetUp_Menu
31	4.7	PROVIDE LOCAL INFORMATION (LOCI & IMEI)	3GPP TS 31.111 §5.2	R99	M		PD_Provide_Local

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
32	4.8	PROVIDE LOCAL INFORMATION (NMR)	3GPP TS 31.111 §5.2	R99	M		PD_Provide_Local_NMR
33	5.1	SET UP EVENT LIST	3GPP TS 31.111 §5.2	R99	M		PD_Setup_Evt_List
34	5.2	Event: MT call	3GPP TS 31.111 §5.2	R99	M		PD_MT_Call
35	5.3	Event: Call connected	3GPP TS 31.111 §5.2	R99	M		PD_Call_Conn
36	5.4	Event: Call disconnected	3GPP TS 31.111 §5.2	R99	M		PD_Call_Disc
37	5.5	Event: Location status	3GPP TS 31.111 §5.2	R99	M		PD_Loc_Status
38	5.6	Event: User activity	3GPP TS 31.111 §5.2	R99	M		PD_User_Act
39	5.7	Event: Idle screen available	3GPP TS 31.111 §5.2	R99	M		PD_Idle_Scr_Avail
40	5.8	Event: Card reader status	3GPP TS 31.111 §5.2	R99	C206		PD_Evt_Rdr_Status
41	6.1	Event: Language selection	3GPP TS 31.111 §5.2	R99	M		PD_Lang_Select
42	6.2	Event: Browser Termination	3GPP TS 31.111 §5.2	R99	C212		PD_Browser_Term
43	6.3	Event: Data available	3GPP TS 31.111 §5.2	R99	C223		PD_Data_Avail
44	6.4	Event: Channel status	3GPP TS 31.111 §5.2	R99	C223		PD_Evt_Ch_Status
45	6.5	Event: Access Technology Change	3GPP TS 31.111 §5.2	Rel-4	M		PD_Evt_ATC
46	6.6	Event: Display Parameters Changed	3GPP TS 31.111 §5.2	Rel-4	C218		PD_Displ_Resiz
47	6.7	Event: Local Connexion	3GPP TS 31.111 §5.2	Rel-4	M		PD_Evt_LC
48	6.8	Event: Network Search Mode Change	3GPP TS 31.111 §5.2	Rel-6	M		PD_Evt_NSNC
49	7.1	POWER ON CARD	3GPP TS 31.111 §5.2	R99	C206		PD_C_On
50	7.2	POWER OFF CARD	3GPP TS 31.111 §5.2	R99	C206		PD_C_Off
51	7.3	PERFORM CARD APDU	3GPP TS 31.111 §5.2	R99	C206		PD_C_APDU
52	7.4	GET READER STATUS (Card reader status)	3GPP TS 31.111 §5.2	R99	C206		PD_Get_Rdr_Status
53	7.5	GET READER STATUS (Card reader identifier)	3GPP TS 31.111 §5.2	R99	C208		PD_Get_Rdr_Id
54	7.6	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_54
55	7.7	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_55
56	7.8	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_56
57	8.1	TIMER MANAGEMENT (start, stop)	3GPP TS 31.111 §5.2	R99	M		PD_Timer_Mgt_Start_Stop
58	8.2	TIMER MANAGEMENT (get current value)	3GPP TS 31.111 §5.2	R99	M		PD_Timer_Val
59	8.3	PROVIDE LOCAL INFORMATION (date, time and time zone)	3GPP TS 31.111 §5.2	R99	M		PD_Provide_Local_D_Time
60	8.4	Bit=1 if Get Inkey	3GPP TS 31.111 §5.2	R99	M		PD_Get_Inkey
61	8.5	SET UP IDLE MODE TEXT	3GPP TS 31.111 §5.2	R99	M		PD_Stup_Id_Mod_Txt
62	8.6	RUN AT COMMAND (i.e. class "b" is supported)	3GPP TS 31.111 §5.2	R99	C209		PD_Run_AT
63	8.7	Bit=1 if Set UpCall	3GPP TS 31.111 §5.2	R99	M		PD_SetUp_Call

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
64	8.8	Bit=1 if Call Control	3GPP TS 31.111 §5.2	R99	M		PD_CC
65	9.1	Bit=1 if Display Text	3GPP TS 31.111 §5.2	R99	M		PD_Display_Text
66	9.2	SEND DTMF command	3GPP TS 31.111 §5.2	R99	M		PD_Send_DTMF
67	9.3	Bit = 1 if Provide Local Information (NMR) supported	3GPP TS 31.111 §5.2	R99	M		PD_Provide_Local
68	9.4	PROVIDE LOCAL INFORMATION (language)	3GPP TS 31.111 §5.2	R99	M		PD_Provide_Local_L S
69	9.5	PROVIDE LOCAL INFORMATION (Timing Advance)	3GPP TS 31.111 §5.2	R99	M		PD_Provide_Local_T A
70	9.6	LANGUAGE NOTIFICATION	3GPP TS 31.111 §5.2	R99	M		PD_Lang_Notif
71	9.7	LAUNCH BROWSER	3GPP TS 31.111 §5.2	R99	C212		PD_Launch_Brws
72	9.8	PROVIDE LOCAL INFORMATION (Access Technology)	3GPP TS 31.111 §5.2	Rel-4	M		PD_Provide_Local_A T
73	10.1	Soft keys support for SELECT ITEM	3GPP TS 31.111 §5.2	R99	C213		PD_Softkey_Select_I tem
74	10.2	Soft Keys support for SET UP MENU	3GPP TS 31.111 §5.2	R99	C213		PD_Softkey_SetUp _Menu
75	10.3	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_75
76	10.4	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_76
77	10.5	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_77
78	10.6	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_78
79	10.7	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_79
80	10.8	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_80
81	11.1	Maximum number of soft keys available ('FF' = RFU)	3GPP TS 31.111 §5.2	R99	C214		PD_Max_SoftKey
82	11.2	Maximum number of soft keys available ('FF' = RFU)	3GPP TS 31.111 §5.2	R99	C214		PD_Max_SoftKey
83	11.3	Maximum number of soft keys available ('FF' = RFU)	3GPP TS 31.111 §5.2	R99	C214		PD_Max_SoftKey
84	11.4	Maximum number of soft keys available ('FF' = RFU)	3GPP TS 31.111 §5.2	R99	C214		PD_Max_SoftKey
85	11.5	Maximum number of soft keys available ('FF' = RFU)	3GPP TS 31.111 §5.2	R99	C214		PD_Max_SoftKey
86	11.6	Maximum number of soft keys available ('FF' = RFU)	3GPP TS 31.111 §5.2	R99	C214		PD_Max_SoftKey
87	11.7	Maximum number of soft keys available ('FF' = RFU)	3GPP TS 31.111 §5.2	R99	C214		PD_Max_SoftKey
88	11.8	Maximum number of soft keys available ('FF' = RFU)	3GPP TS 31.111 §5.2	R99	C214		PD_Max_SoftKey
89	12.1	OPEN CHANNEL	3GPP TS 31.111 §5.2	R99	C223		PD_Open_Ch
90	12.2	CLOSE CHANNEL	3GPP TS 31.111 §5.2	R99	C223		PD_Close_Ch
91	12.3	RECEIVE DATA	3GPP TS 31.111 §5.2	R99	C223		PD_Rx_Data
92	12.4	SEND DATA	3GPP TS 31.111 §5.2	R99	C223		PD_Send_Data
93	12.5	GET CHANNEL STATUS	3GPP TS 31.111 §5.2	R99	C223		PD_Get_Ch_Status
94	12.6	SERVICE SEARCH	3GPP TS 31.111 §5.2	Rel-4	C224		PD_Serv_Search

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
95	12.7	GET SERVICE INFORMATION	3GPP TS 31.111 §5.2	Rel-4	C224		PD_Get_Serv_Info
96	12.8	DECLARE SERVICE	3GPP TS 31.111 §5.2	Rel-4	C224		PD_Declare_Serv
97	13.1	CSD supported by ME	3GPP TS 31.111 §5.2	R99	C207		PD_CSD
98	13.2	GPRS supported by ME	3GPP TS 31.111 §5.2	R99	C222		PD_GPRS
99	13.3	Bluetooth supported by terminal	3GPP TS 31.111 §5.2	Rel-4	C225		PD_BT
100	13.4	IrDA Supported by terminal	3GPP TS 31.111 §5.2	Rel-4	C226		PD_IrDA
101	13.5	RS232 Supported by terminal	3GPP TS 31.111 §5.2	Rel-4	C227		PD_RS232
102	13.6	Number of channels supported by ME	3GPP TS 31.111 §5.2	R99	C223		PD_Nb_Channel

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
103	13.7	Number of channels supported by ME	3GPP TS 31.111 §5.2	R99	C223		PD_Nb_Channel
104	13.8	Number of channels supported by ME	3GPP TS 31.111 §5.2	R99	C223		PD_Nb_Channel
105	14.1	Number of characters supported down the ME	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char
106	14.2	Number of characters supported down the ME	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char
107	14.3	Number of characters supported down the ME	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char
108	14.4	Number of characters supported down the ME	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char
109	14.5	Number of characters supported down the ME	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char
110	14.6	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_110
111	14.7	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_111
112	14.8	Screen Sizing Parameters	3GPP TS 31.111 §5.2	R99	C216		PD_Screen_Siz
113	15.1	Number of characters supported across the ME display	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char_Dis
114	15.2	Number of characters supported across the ME display	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char_Dis
115	15.3	Number of characters supported across the ME display	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char_Dis
116	15.4	Number of characters supported across the ME display	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char_Dis
117	15.5	Number of characters supported across the ME display	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char_Dis
118	15.6	Number of characters supported across the ME display	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char_Dis
119	15.7	Number of characters supported across the ME display	3GPP TS 31.111 §5.2	R99	C217		PD_Nb_Char_Dis
120	15.8	Variable size fonts Supported	3GPP TS 31.111 §5.2	R99	C217		PD_Var_Font
121	16.1	Display can be resized	3GPP TS 31.111 §5.2	R99	C218		PD_Dis_Resize
122	16.2	Text Wrapping supported	3GPP TS 31.111 §5.2	R99	C218		PD_Txt_Wrap
123	16.3	Text Scrolling supported	3GPP TS 31.111 §5.2	R99	C218		PD_Txt_Scroll
124	16.4	Text attributes supported	3GPP TS 31.111 §5.2	Rel-5	C228		PD_Text_Attrib
125	16.5	RFU	3GPP TS 11.14, 5	R96	X		PD_RFU_125
126	16.6	Width reduction when in a menu	3GPP TS 31.111 §5.2	R99	C217		PD_Width_Reduc
127	16.7	Width reduction when in a menu	3GPP TS 31.111 §5.2	R99	C217		PD_Width_Reduc
128	16.8	Width reduction when in a menu	3GPP TS 31.111 §5.2	R99	C217		PD_Width_Reduc
129	17.1	TCP	3GPP TS 31.111 §5.2	R99	C220		PD_TCP
130	17.2	UDP	3GPP TS 31.111 §5.2	R99	C221		PD_UDP
131	17.3	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_131

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
132	17.4	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_132
133	17.5	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_133
134	17.6	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_134
135	17.7	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_135
136	17.8	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_136
137	18.1	DISPLAY TEXT (Variable time out)	3GPP TS 31.111 §5.2	Rel-4	C229		
138	18.2	GET INKEY (help is supported while waiting for immediate response or variable time out)	3GPP TS 31.111 §5.2	Rel-4	C231		
139	18.3	USB supported by ME	3GPP TS 31.111 §5.2	Rel-4	C232		
140	18.4	GET INKEY (Variable time out)	3GPP TS 31.111 §5.2	Rel-4	C229		
141	18.5	PROVIDE LOCAL INFORMATION (ESN)	See 3GPP2	R99	X		Reserved
142	18.6	CALL CONTROL on GPRS	3GPP TS 31.111 §5.2	Rel-5	C242		PD_CC_GPRS
143	18.7	PROVIDE LOCAL INFORMATION (IMEISV)	3GPP TS 31.111 §5.2	Rel-6	M		PD_Provide_Local_S V
144	18.8	PROVIDE LOCAL INFORMATION (search mode change)	3GPP TS 31.111 §5.2	Rel-6	M		PD_Provide_Local_S MC
145	19.1	Protocol Version	3GPP TS 31.111 §5.2	R99	X		Reserved
146	19.2	Protocol Version	3GPP TS 31.111 §5.2	R99	X		Reserved
147	19.3	Protocol Version	3GPP TS 31.111 §5.2	R99	X		Reserved
148	19.4	Protocol Version	3GPP TS 31.111 §5.2	R99	X		Reserved
149	19.5	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_149
150	19.6	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_150
151	19.7	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_151
152	19.8	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_152
153	20.1	Reserved by TIA/EIA/IS-820 [25]	3GPP TS 31.111 §5.2	R99	X		Reserved
154	20.2	Reserved by TIA/EIA/IS-820 [25]	3GPP TS 31.111 §5.2	R99	X		Reserved
155	20.3	Reserved by TIA/EIA/IS-820 [25]	3GPP TS 31.111 §5.2	R99	X		Reserved
156	20.4	Reserved by TIA/EIA/IS-820 [25]	3GPP TS 31.111 §5.2	R99	X		Reserved
157	20.5	Reserved by TIA/EIA/IS-820 [25]	3GPP TS 31.111 §5.2	R99	X		Reserved
158	20.6	Reserved by TIA/EIA/IS-820 [25]	3GPP TS 31.111 §5.2	R99	X		Reserved
159	20.7	Reserved by TIA/EIA/IS-820 [25]	3GPP TS 31.111 §5.2	R99	X		Reserved
160	20.8	Reserved by TIA/EIA/IS-820 [25]	3GPP TS 31.111 §5.2	R99	X		Reserved
161	21.1	WML browser supported	3GPP TS 31.111 §5.2	Rel-6	C233		PD_WML
162	21.2	XHTML browser supported	3GPP TS 31.111 §5.2	Rel-6	C234		PD_XHTML

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
163	21.3	HTML browser supported	3GPP TS 31.111 §5.2	Rel-6	C235		PD_HTML
164	21.4	CHTML browser supported	3GPP TS 31.111 §5.2	Rel-6	C236		PD_CHTML
165	21.5	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_165_
166	21.6	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_166
167	21.7	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_167
168	21.8	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_168
169	22.1	Support of UTRAN PS with extended parameters	3GPP TS 31.111 §5.2	Rel-6	TBD		PD_Provide_Local_P S
170	22.2	PROVIDE LOCAL INFORMATION (Battery state) if class 'g' supported	3GPP TS 31.111 §5.2	Rel-6	C239		PD_Provide_Local_B att
171	22.3	PLAY TONE (Melody tones & themed tones supported)	3GPP TS 31.111 §5.2	Rel-6	C241		PD_Tones
172	22.4	Multi-media in SET UP CALL supported (if class 'h' supported)	3GPP TS 31.111 §5.2	Rel-6	C240		PD_Xmedia_Call
173	22.5	MMS Management (class 'j' supported)	3GPP TS 31.111 §5.2	Rel-6	C238		PD_MMS
174	22.6	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_174
175	22.7	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_175
176	22.8	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_176
177	23.1	SET FRAMES supported (if class 'i' supported)	3GPP TS 31.111 §5.2	Rel-6	C237		PD_Set_Frames
178	23.2	GET FRAMES STATUS supported (if class 'i' supported)	3GPP TS 31.111 §5.2	Rel-6	C237		PD_Get_Frames_Sta t
179	23.3	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_179
180	23.4	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_180
181	23.5	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_181
182	23.6	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_182
183	23.7	PROVIDE LOCAL INFORMATION (UTRAN NMR)	3GPP TS 31.111 §5.2	Rel-6	M		PD_Provide_Local_N MR
184	23.8	USSD Data Download and application mode	3GPP TS 31.111 §5.2	Rel-6	M		PD_USSD_DD
185	24.1	Maximum number of frames supported (if class 'i' supported)	3GPP TS 31.111 §5.2	Rel-6	C256		PD_Max_Frames
186	24.2	Maximum number of frames supported (if class 'i' supported)	3GPP TS 31.111 §5.2	Rel-6	C256		PD_Max_Frames
187	24.3	Maximum number of frames supported (if class 'i' supported)	3GPP TS 31.111 §5.2	Rel-6	C256		PD_Max_Frames
188	24.4	Maximum number of frames supported (if class 'i' supported)	3GPP TS 31.111 §5.2	Rel-6	C256		PD_Max_Frames
189	24.5	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_189
190	24.6	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_190

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
191	24.7	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_191
192	24.8	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_192
193	25.1	Event: browsing status	3GPP TS 31.111 §5.2	Rel-6	M		PD_Browser_Stat
194	25.2	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_194
195	25.3	Event Frame parameters changed (if class 'i' supported)	3GPP TS 31.111 §5.2	Rel-6	C237		PD_Event_Frames
196	25.4	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_196
197	25.5	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_197
198	25.6	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_198
199	25.7	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_199
200	25.8	RFU	3GPP TS 31.111 §5.2	R99	X		PD_RFU_200
201	26.1	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_201
202	26.2	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_202
203	26.3	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_203
204	26.4	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_204
205	26.5	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_205
206	26.6	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_206
207	26.7	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_207
208	26.8	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_208
209	27.1	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_209
210	27.2	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_210
211	27.3	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_211
212	27.4	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_212
213	27.5	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_213
214	27.6	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_214
215	27.7	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_215
216	27.8	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_216
217	28.1	Alignment left supported	3GPP TS 31.111 §5.2	Rel-5	C243		PD_Text_Attrib_Left
218	28.2	Alignment center supported	3GPP TS 31.111 §5.2	Rel-5	C244		PD_Text_Attrib_Center
219	28.3	Alignment right supported	3GPP TS 31.111 §5.2	Rel-5	C245		PD_Text_Attrib_Right
220	28.4	Font size normal supported	3GPP TS 31.111 §5.2	Rel-5	C246		PD_Text_Attrib_Normal
221	28.5	Font size large supported	3GPP TS 31.111 §5.2	Rel-5	C247		PD_Text_Attrib_Large
222	28.6	Font size small supported	3GPP TS 31.111 §5.2	Rel-5	C248		PD_Text_Attrib_Small

Item	Byte.bit	Terminal Profile	Ref.	Release	Status	Support	Mnemonic
223	28.7	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_223
224	28.8	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_224
225	29.1	Style normal supported	3GPP TS 31.111 §5.2	Rel-5	C249		PD_Text_Attrib_Styl_ Norm
226	29.2	Style bold supported	3GPP TS 31.111 §5.2	Rel-5	C250		PD_Text_Attrib_Styl_ Bold
227	29.3	Style italic supported	3GPP TS 31.111 §5.2	Rel-5	C251		PD_Text_Attrib_Styl_ Italic
228	29.4	Style underlined supported	3GPP TS 31.111 §5.2	Rel-5	C252		PD_Text_Attrib_Styl_ Underl
229	29.5	Style strikethrough supported	3GPP TS 31.111 §5.2	Rel-5	C253		PD_Text_Attrib_Styl_ Strik
230	29.6	Style text foreground colour supported	3GPP TS 31.111 §5.2	Rel-5	C254		PD_Text_Attrib_Styl_ Text_Fore
231	29.7	Style text background colour supported	3GPP TS 31.111 §5.2	Rel-5	C255		PD_Text_Attrib_Styl_ Text_Back
232	29.8	RFU	3GPP TS 31.111 §5.2	Rel-6	X		PD_RFU_224

C201	[void]	-- [void]
C202	[void]	-- [void]
C203	IF A.1/3 THEN M	-- O_Ucs2_Entry
C204	IF A.1/15 THEN M	-- O_Ucs2_Disp
C205	[void]	-- [void]
C206	IF A.1/7 THEN M	-- O_Dual_Slot
C207	IF A.1/12 THEN M	-- O_BIP_CSD
C208	IF (A.1/7 AND A.1/8) THEN M	-- O_Dual_Slot AND O_Detach_Rdr
C209	IF A.1/9 THEN M	-- O_Run_At
C210	[void]	-- [void]
C211	[void]	-- [void]
C212	IF A.1/10 THEN M	-- O_LB
C213	IF A.1/11 THEN M for at least one of the bits 1 - 2 of byte 10	-- O_Softkey
C214	IF C213 THEN M for at least one, but not for all of the bits 1 - 8 of byte 11	-- O_Softkey (parameters)
C215	Void	-- Void
C216	IF A.1/13 THEN M	-- O_Scr_Siz
C217	IF C216 THEN bit values "0" / "1" allowed	-- O_Scr_Siz (parameters)
C218	IF A.1/14 THEN M	-- O_Scr_Resiz
C219	IF C218 THEN bit values "0" / "1" allowed	-- O_Scr_Resiz (parameters)
C220	IF A.1/18 THEN M	-- O_TCP
C221	IF A.1/17 THEN M	-- O_UDP
C222	IF A.1/21 THEN M	-- O_BIP_GPRS
C223	IF (C207 OR C222) THEN M	-- O_BIP
C224	IF (C223 AND A1.26) THEN M	-- O_BIP AND O_BIP_Local
C225	IF (C224 AND A1.27) THEN M	-- O_BIP_BT
C226	IF (C224 AND A1.28) THEN M	-- O_BIP_IrDA
C227	IF (C224 AND A1.29) THEN M	-- O_BIP_RS232
C228	IF (A1./50 OR A.1/51 OR A.1/52 OR A.1/53 OR A.1/54 OR A.1/55 OR A.1/56 OR A.1/57 OR A.1/58 OR A.1/59 OR A.1/60 OR A.1/61 OR A.1/62) THEN M	-- O_TAT_AL OR O_TAT_AC OR O_TAT_AR OR O_TAT_FSN OR O_TAT_FSL OR O_TAT_FSS OR O_TAT_SN OR O_TAT_SB OR O_TAT_SI OR O_TAT_SU OR O_TAT_SS OR O_TAT_STFC OR O_TAT_STFB
C229		-- O_Duration
C230	IF A.1/24 THEN M	-- O_Imm_Resp
C231	IF A.1/23 THEN M	-- O_Help AND (O_Duration OR O_Imm_Resp)
C232	IF A.1/30 THEN M	-- O_USB
C233	IF A.1/31 THEN M	-- O_WML
C234	IF A.1/32 THEN M	-- O_XHTML
C235	IF A.1/33 THEN M	-- O_HTML
C236	IF A.1/34 THEN M	-- O_CHTML
C237	IF A.1/37 THEN M	-- O_Frames
C238	IF A.1/38 THEN M	-- O_MMS
C239	IF A.1/35 THEN M	-- O_Batt
C240	IF A.1/36 THEN M	-- O_Xmedia Call
C241	IF A.1/29 THEN M	-- O_Tones
C242	IF A.1/16 THEN M	-- O_CC_GPRS
C243	IF A.1/50 THEN M	-- O_TAT_AL
C244	IF A.1/51 THEN M	-- O_TAT_AC
C245	IF A.1/52 THEN M	-- O_TAT_AR
C246	IF A.1/53 THEN M	-- O_TAT_FSN
C247	IF A.1/54 THEN M	-- O_TAT_FSL
C248	IF A.1/55 THEN M	-- O_TAT_FSS
C249	IF A.1/56 THEN M	-- O_TAT_SN
C250	IF A.1/57 THEN M	-- O_TAT_SB
C251	IF A.1/58 THEN M	-- O_TAT_SI
C252	IF A.1/59 THEN M	-- O_TAT_SU
C253	IF A.1/60 THEN M	-- O_TAT_SS
C254	IF A.1/61 THEN M	-- O_TAT_STFC
C255	IF A.1/62 THEN M	-- OR O_TAT_STFB
C256	IF C237 THEN M for at least one of the bits 1 - 4 of byte 24	-- O_Frames

## Annex C (informative): Change history

CR	REV	CP-doc	Meeting	SUBJECT	CAT	NEW_VERS
		TP-050016	2.0.0	Approved TP-27, March 2005		6.0.0
001		CP-050144	CT-28	Correction of coding in MT Call Event	F	6.1.0
002		CP-050144	CT-28	Correction of applicability table	F	6.1.0
003		CP-050144	CT-28	Essential Corrections	F	6.1.0
004		CP-050144	CT-28	Correction of coding in MT Call Event	F	6.1.0
005		CP-050144	CT-28	Removal of GET RESPONSE references	F	6.1.0
006		CP-050447	CT-29	Rel-6: Correction of release dependent EF values	F	6.2.0
007				Correction of applicability and terminal profile support tables	F	
008				Correction of EF_BDN coding	F	
009				Incorrect Dialling Number string in clause 27.22.4.13.1 SEQ 1.9 for PCS 1900	F	
010				Essential corrections in display icons Setup Menu and Select Item	f	
011				Incorrect Ti Flag value for SET UP 1.4.1 in clause 27.22.4.16.1	F	
012				Correction of TP-MR (TP Message Reference) of the SMS SUBMIT TPDU submitted to the USS (Network)	F	
013				Corrections in the Logical description and BER encoding in clause 27.22.6.2 and 27.22.4.11	F	
014				Incorrect DCS in SMS-CB data download tests	F	
015				Essential Corrections in clause 27.22.8 MO SHORT MESSAGE CONTROL BY USIM	F	
016				Introduction of BDN tests for terminals not supporting BDN	B	
017				Essential Corrections	F	
018				Incorrect SMS-PP 1.4.1 TPDU in clause 27.22.4.22.1	F	
019				Missing interactions in Bearer Independent Protocol test cases	F	
020				Correction of Refresh tests	F	
022				Applicability of TC 27.22.4.7.1 and TCs related to FDN and BDN	F	
023				Essential correction to Terminal Profile table E.1	F	
024				Correction of CB message identifier	F	
025				Rel-6: Addition of new UCS2 Tests	B	
027				Incorrect Coding of SMS-PP (Data download) Message in clause 27.22.4.7.1 and 27.22.5.1	F	
				2005-10: Editorial corrections due to the CRs approved at CP-29		6.2.1
028		CP-050495	CT-30	Correction of Send SS (UCS2) tests	F	6.3.0
029				Essential Corrections in clause 27.22.4.11	F	
030				Corrections to Select Item (icons support)	F	
031				27.22.7.4.1 Location Status Event (normal)	F	
032				Essential Corrections of Set Up Menu test	F	
033				Correction of applicability table and related addition of missing test sequences	F	
034				Correction in SMS-PP 1.4.1 TPDU of clause 27.22.4.22.1	F	
035				Essential Corrections of SMS-PP download message in Refresh test case	F	
036				Essential Correction in MO SHORT MESSAGE CONTROL BY USIM Deletion of sequence 1.9	F	
037				Deletion of SEQ 1.3 in clause 27.22.4.13.1	F	
0041		CP-060013	CT-31	Deletion of Send Data test sequence	F	6.4.0
0042				Essential correction of Provide Local Information (IMEI) test	F	
0044				Essential Correction in SEQ 1.8 of clause 27.22.8	F	
0045				Essential correction on 27.22.7.3.1 Call Disconnected Event	F	
0050				Essential correction of Channel Data length in clause 27.22.4.30	F	
0048		CP-060014		Essential Corrections in clause 27.22.4.11	F	
0052				Essential Corrections in clause 27.22.8 MO SHORT MESSAGE CONTROL BY SIM	F	
0049				Essential correction in SEQ 1.4 of clause 27.22.4.11.1 SEND SS (normal)	F	
0047				Essential corrections of Run AT Command tests	F	
0053				Essential corrections to SET UP CALL test sequences	F	
0055		CP-060015		Essential Correction in TERMINAL RESPONSE coding of clause 27.22.4.31	F	
0056				Essential corrections to Timer Expiration tests	F	
0054	1			BER-TLV suppressions	F	
0059	3	CP-060157		Add SMS PP Data Download RP-ERROR Test Case	B	
0043		CP-060022		Essential Correction in SEQ 1.7 of clause 27.22.4.13.1	F	
0046				Essential correction of Refresh test	F	
0051				Essential correction of Channel Data length in Result TLV of clause 27.22.4.30	F	

0060				CR 31.124 Rel-6: Insertion of missing REFRESH (IMSI changing procedure) test cases	F	
0057				Essential corrections of references	F	
0061		CP-060241	CT-32	Proposal to the TS 31.124 Split by referencing the relevant USAT Test procedures to TS 102 384		6.5.0
0062				Essential corrections on test cases 27.22.6.3 and 27.22.6.4 using record 2 in EF FDN		
0063				Essential corrections on TC 27.22.6.4 sequence 4.1		
0064				Essential corrections on SEND SHORT MESSAGE test cases		
0065				Essential correction of text attributes tests		
0066				Definition of appropriate QoS in BIP test cases related to GPRS for 3G		
0071				Essential correction of Refresh test in 27.22.7.4.2, seq. 2.4		
0074				Essential corrections of RUN AT Command tests		
0067				Essential correction of tables B.1 and E.1		
0068		CP-060242		Essential Correction in REGISTER 1.2B message coding of clause 27.22.4.11.1 SEND SS (normal)	F	
0069				Essential correction of 27.22.4.13.1 SET UP CALL, seq 1.4	F	
0070				Essential correction of second card reader test applicability	F	
0072				Correction of TON/NPI coding for Call Control Test case	F	
0073				Essential corrections on 27.22.4.11.1 sequence. 1.2	F	
0075				Essential correction of BIP tests	F	
0082	1	CP-060389	CT-33	Wrong reference inside test requirement of TC 27.22.7.2.2	F	6.6.0
0087	1			Essential corrections of applicability table	F	
0088	1			Essential correction of IMEISV coding for Provide Local Information	F	
0089	1			Essential corrections of text attribute tests for Send USSD and Close channel	F	
0090	1			Proposal to the TS 31.124 Split by referencing the relevant USAT Test procedures to TS 102 384	F	
0091	1			Correction to the UCS2 coding in Setup Call test	F	
0092	1			Essential correction of RUN AT Command for text attribute tests	F	
0095	1			Correction of RECEIVE DATA tests	F	
0096	1			Correction of terminology for USIM Service Table	F	
0097	1			Correction of 2nd alpha identifier usages in SET UP CALL tests	F	
0098	1			Correction of various typographical errors	F	
0101	1			Essential corrections to OPEN CHANNEL text attribute test sequences	F	
0078	1			Correction of "Precedence class" values in Bearer Independent Protocol test cases	F	
0076	1			Essential corrections on PROVIDE LOCAL INFORMATION test sequences	F	
0080	2			Essential corrections on test sequences using the TLV data object Location Information	F	
0100	2			Essential corrections to SET UP CALL (UCS2 Display) test sequences	F	
0081	3			Essential corrections to REFRESH(normal) test sequence	F	
0102	1			Essential corrections to SEND SS display tests concerning longForwardedToNumber	F	
0086	1	C6-060475		Essential corrections of MMI entries in table E.1	F	
0077	2			Corrections to SET UP CALL test case 27.22.4.13.1	F	
0099	1			Essential corrections to SEND SS concerning longForwardedToNumber	F	
0094	2			Corrections to MO SHORT MESSAGE CONTROL BY USIM tests	F	
0084	1	CP-060517		Essential corrections Set Up Call, seq. 1.9	F	

---

## History

<b>Document history</b>		
V6.0.0	March 2005	Publication
V6.1.0	June 2005	Publication
V6.2.1	October 2005	Publication
V6.3.0	December 2005	Publication
V6.4.0	March 2006	Publication
V6.5.0	June 2006	Publication
V6.6.0	September 2006	Publication