

ETSI TS 136 521-2 V9.4.0 (2011-04)

Technical Specification

**LTE;
Evolved Universal Terrestrial Radio Access (E-UTRA);
User Equipment (UE) conformance specification;
Radio transmission and reception;
Part 2: Implementation Conformance Statement (ICS)
(3GPP TS 36.521-2 version 9.4.0 Release 9)**



Reference

RTS/TSGR-0536521-2v940

Keywords

LTE

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

Individual copies of the present document can be downloaded from:

<http://www.etsi.org>

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at

<http://portal.etsi.org/tb/status/status.asp>

If you find errors in the present document, please send your comment to one of the following services:

http://portal.etsi.org/chaicor/ETSI_support.asp

Copyright Notification

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2011.
All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™**, **TIPHON™**, the TIPHON logo and the ETSI logo are Trade Marks of ETSI registered for the benefit of its Members.

3GPP™ is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

LTE™ is a Trade Mark of ETSI currently being registered

for the benefit of its Members and of the 3GPP Organizational Partners.

GSM® and the GSM logo are Trade Marks registered and owned by the GSM Association.

Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (<http://webapp.etsi.org/IPR/home.asp>).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under <http://webapp.etsi.org/key/queryform.asp>.

Contents

Intellectual Property Rights	2
Foreword.....	2
Foreword.....	4
Introduction	4
1 Scope	5
2 References	5
3 Definitions, symbols and abbreviations	6
3.1 Definitions	6
3.2 Symbols.....	7
3.3 Abbreviations	7
4 Recommended test case applicability.....	7
4.1 RF conformance test cases	9
4.2 RRM conformance test cases	13
Annex A (normative): ICS proforma for E-UTRA User Equipment.....	18
A.1 Guidance for completing the ICS proforma	18
A.1.1 Purposes and structure	18
A.1.2 Abbreviations and conventions.....	18
A.1.3 Instructions for completing the ICS proforma	19
A.2 Identification of the User Equipment	19
A.2.1 Date of the statement	19
A.2.2 User Equipment Under Test (UEUT) identification	19
A.2.3 Product supplier	20
A.2.4 Client	20
A.2.5 ICS contact person	21
A.3 Identification of the protocol.....	21
A.4 ICS proforma tables.....	21
A.4.1 UE Implementation Types	21
A.4.2 UE Service Capabilities	21
A.4.3 Baseline Implementation Capabilities	22
A.4.4 Feature group indicators	25
Annex B (informative): Change history	31
History	33

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

Introduction

The present document is part 2 of a multi-parts TS:

3GPP TS 36.521-1 [1]: Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) conformance specification Radio transmission and reception Part 1: Conformance testing.

3GPP TS 36.521-2: Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) conformance specification Radio transmission and reception Part :2 Implementation Conformance Statement (ICS).

3GPP TS 36.521-3 [2]: Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) conformance specification Radio transmission and reception Part 3: Radio Resource Management (RRM) Conformance Testing.

1 Scope

The present document provides the Implementation Conformance Statement (ICS) proforma for 3G Evolved Universal Terrestrial Radio Access (E-UTRA) User Equipment (UE), in compliance with the relevant requirements, and in accordance with the relevant guidance given in ISO/IEC 9646-1 [3] and ISO/IEC 9646-7 [4]

The present document specifies the recommended applicability statement for the test cases included in 3GPP TS 36.521-1 [1] and 3GPP TS 36.521-3 [2]. These applicability statements are based on the features implemented in the UE.

Special conformance testing functions can be found in 3GPP TS 36.509 [5] and the common test environments are included in 3GPP TS 36.508 [6].

The present document is valid for UE implemented according to 3GPP releases starting from Release 8 up to the Release indicated on the cover page of the present document.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.
 - For a Release 8 UE, references to 3GPP documents are to version 8.x.y, when available.

Editor's Note: The Reference list is incomplete and some references are still to UMTS specs.

- [1] 3GPP TS 36.521-1: "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) conformance specification Radio transmission and reception Part 1: Conformance testing".
- [2] 3GPP TS 36.521-3: "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) conformance specification Radio transmission and reception Part 3: Radio Resource Management Conformance Testing".
- [3] ISO/IEC 9646-1: "Information technology - Open systems interconnection - Conformance testing methodology and framework - Part 1: General concepts".
- [4] ISO/IEC 9646-7: "Information technology - Open systems interconnection - Conformance testing methodology and framework - Part 7: Implementation Conformance Statements".
- [5] 3GPP TS 36.509: " Evolved Universal Terrestrial Radio Access (E-UTRA); Special conformance testing functions for User Equipment".
- [6] 3GPP TS 36.508: "Evolved Universal Terrestrial Radio Access (E-UTRA); Common Test Environments for User Equipment (UE) Conformance Testing".
- [8] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [9] 3GPP TS 36.201: " LTE Physical Layer - General Description"
- [10] 3GPP TS 36.302: " Evolved Universal Terrestrial Radio Access (E-UTRA); Services provided by the physical layer for E-UTRA".
- [11] 3GPP TS 36.321: "Evolved Universal Terrestrial Radio Access (E-UTRA); Medium Access Control (MAC) protocol specification".

- [12] 3GPP TS 36.322: "Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Link Control (RLC) protocol specification".
- [13] 3GPP TS 36.323: "Evolved Universal Terrestrial Radio Access (E-UTRA); Packet Data Convergence Protocol (PDCP) specification".
- [14] 3GPP TS 36.331: "Evolved Universal Terrestrial Radio Access (E-UTRA); Radio Resource Control (RRC) Protocol Specification".
- [15] 3GPP TS 24.301: "Non-Access-Stratum (NAS) protocol for Evolved Packet System (EPS); Stage 3"
- [16] 3GPP TS 36.307: "Requirements on User Equipments (UEs) Supporting a release-independent frequency band".

3 Definitions, symbols and abbreviations

For the purposes of the present document, the following terms, definitions, symbols and abbreviations apply:

- such given in TR 21.905 [8]
- such given in ISO/IEC 9646-1 [3] and ISO/IEC 9646-7 [4]

NOTE: Some terms and abbreviations defined in [3] and [4] are explicitly included below with small modification to reflect the terminology used in 3GPP.

3.1 Definitions

Implementation Conformance Statement (ICS): statement made by the supplier of an implementation or system claimed to conform to a given specification, stating which capabilities have been implemented

ICS proforma: document, in the form of a questionnaire, which when completed for an implementation or system becomes an ICS

Implementation eXtra Information for Testing (IXIT): A statement made by a supplier or implementer of an UEUT which contains or references all of the information (in addition to that given in the ICS) related to the UEUT and its testing environment, which will enable the test laboratory to run an appropriate test suite against the UEUT

IXIT proforma: A document, in the form of a questionnaire, which when completed for an UEUT becomes an IXIT

Protocol Implementation Conformance Statement (PICS): An ICS for an implementation or system claimed to conform to a given protocol specification

Protocol Implementation eXtra Information for Testing (PIXIT): An IXIT related to testing for conformance to a given protocol specification

static conformance review: A review of the extent to which the static conformance requirements are claimed to be supported by the UEUT, by comparing the answers in the ICS(s) with the static conformance requirements expressed in the relevant specification(s)

3.2 Symbols

No specific symbols have been identified so far.

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [8].

For the purposes of the present document, the following abbreviations apply:

ICS	Implementation Conformance Statement
IXIT	Implementation eXtra Information for Testing
PICS	Protocol Implementation Conformance Statement
PIXIT	Protocol Implementation eXtra Information for Testing
RRM	Radio Resource Management
SCS	System Conformance Statement
TC	Test Case
UEUT	User Equipment Under Test

4 Recommended test case applicability

The applicability of each individual test is identified in the tables 4.1-1 or 4.2-1. This is just a recommendation based on the purpose for which the test case was written.

The applicability of every test is formally expressed by the use of Boolean expression that are based on parameters (ICS) included in annex A of the present document.

Additional information related to the Test Case (TC), e.g. affecting its dynamic behaviour or its execution may be provided as well

The columns in tables 4.1-1 / 4.2-1 have the following meaning:

Clause

The clause column indicates the clause number in TS 36.521-1 [1] or respectively TS 36.521-3 [2] that contains the test body.

Title

The title column describes the name of the test and contains the clause title of the clause in TS 36.521-1 [1] or TS 36.521-3 [2] that contains the test body.

Release

The release column indicates the earliest release from which each test case is applicable.

Applicability - Condition

The following notations are used for the applicability column:

R	recommended - the test case is recommended to all terminals supporting E-UTRA
O	optional – the test case is optional
N/A	not applicable - in the given context, the test case is not recommended.

Ci conditional - the test is recommended ("R") or not ("N/A") depending on the support of other items. "i" is an integer identifying a unique conditional status expression which is defined immediately following the table. For nested conditional expressions, the syntax "IF ... THEN (IF ... THEN ... ELSE...) ELSE ..." is used to avoid ambiguities.

Applicability - Comments

This comments column contains a verbal description of the condition included in the applicability column.

Additional Information

This column contains indication if the test case may perform differently depending on the UE capabilities.

NOTE To meet the validation requirements from certification bodies then there is a need to uniquely reference the FDD and TDD branch (i.e. different behaviour within one and the same TC) of common FDD and TDD test cases. The FDD and TDD branches of common FDD and TDD test cases can be referenced by amending a "FDD" or "TDD" suffix to the test case clause number. For example for test case 6.2.2 the FDD and TDD branches can be identified by "6.2.2 FDD" and "6.2.2 TDD".

4.1 RF conformance test cases

Table 4.1-1: Applicability of RF conformance test cases, ref. TS 36.521-1 [1]

Clause	Title	Release	Applicability		Additional Information
			Condition	Comments	
Transmitter Characteristics					
6.2.2	UE Maximum Output Power	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.2.3	Maximum Power Reduction (MPR)	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.2.4	Additional Maximum Power Reduction (A-MPR)	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.2.5	Configured UE transmitted Output Power	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.3.1	Void				
6.3.2	Minimum Output Power	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.3.3	Transmit OFF Power	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.3.4.1	General ON/OFF time mask	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.3.4.2.1	PRACH time mask	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.3.4.2.2	SRS time mask	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.3.5.1	Power Control Absolute Power Tolerance	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.3.5.2	Power Control Relative Power Tolerance	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.3.5.3	Aggregate Power Control Tolerance	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.5.1	Frequency Error	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.5.2.1	Error Vector Magnitude (EVM)	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.5.2.1A	PUSCH-EVM with exclusion period	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.5.2.2	Carrier leakage	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.5.2.3	In-band emissions for non allocated RB	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.5.2.4	EVM equalizer spectrum flatness	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.6.1	Occupied bandwidth	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.6.2.1	Spectrum Emission Mask	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.6.2.2	Additional Spectrum Emission Mask	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.6.2.3	Adjacent Channel Leakage power Ratio	Rel-8	R	UE supporting E-UTRA	FDD TDD
6.6.2.4	Void				
6.6.3.1	Transmitter Spurious emissions	Rel-8	R	UE supporting E-UTRA	FDD

Clause	Title	Release	Applicability		Additional Information
			Condition	Comments	
6.6.3.2	Spurious emission band UE co-existence	Rel-8	R	UE supporting E-UTRA	FDD
				UE supporting E-UTRA	TDD
6.6.3.3	Additional spurious emissions	Rel-8	R	UE supporting E-UTRA	FDD
					TDD
6.7	Transmit intermodulation	Rel-8	R	UE supporting E-UTRA	FDD
					TDD
Receiver Characteristics					
7.3	Reference sensitivity level	Rel-8	R	UE supporting E-UTRA	FDD
					TDD
7.4	Maximum input level	Rel-8	R	UE supporting E-UTRA	FDD
					TDD
7.5	Adjacent Channel Selectivity (ACS)	Rel-8	R	UE supporting E-UTRA	FDD
					TDD
7.6.1	In-band blocking	Rel-8	R	UE supporting E-UTRA	FDD
					TDD
7.6.2	Out of-band blocking	Rel-8	R	UE supporting E-UTRA	FDD
					TDD
7.6.3	Narrow band blocking	Rel-8	R	UE supporting E-UTRA	FDD
					TDD
7.7	Spurious response	Rel-8	R	UE supporting E-UTRA	FDD
					TDD
7.8.1	Wide band Intermodulation	Rel-8	R	UE supporting E-UTRA	FDD
					TDD
7.9	Spurious emissions	Rel-8	R	UE supporting E-UTRA	FDD
					TDD
Performance Requirement					
8.2.1.1.1	FDD PDSCH Single Antenna Port Performance	Rel-8	C01	UE supporting E-UTRA FDD	
8.2.1.1.2	FDD PDSCH Single Antenna Port Performance with 1 PRB in presence of MBSFN	Rel-8	C01	UE supporting E-UTRA FDD	
8.2.1.2.1	FDD PDSCH Transmit Diversity 2x2	Rel-8	C01	UE supporting E-UTRA FDD	
8.2.1.2.2	FDD PDSCH Transmit Diversity 4x2	Rel-8	C01	UE supporting E-UTRA FDD	
8.2.1.3.1	FDD PDSCH Open Loop Spatial Multiplexing 2x2	Rel-8	C01	UE supporting E-UTRA FDD	
8.2.1.3.2	FDD PDSCH Open Loop Spatial Multiplexing 4x2	Rel-8	C01	UE supporting E-UTRA FDD	
8.2.1.4.1	FDD PDSCH Closed Loop Single/Multi Layer Spatial Multiplexing 2x2	Rel-8	C01	UE supporting E-UTRA FDD	
8.2.1.4.2	FDD PDSCH Closed Loop Single/Multi Layer Spatial Multiplexing 4x2	Rel-8	C01	UE supporting E-UTRA FDD	
8.2.2.1	Void				
8.2.2.1.1	TDD PDSCH Single Antenna Port Performance	Rel-8	C02	UE supporting E-UTRA TDD	
8.2.2.1.2	TDD PDSCH Single Antenna Port Performance with 1PRB in the presence of MBSFN	Rel-8	C02	UE supporting E-UTRA TDD	
8.2.2.2	Void				
8.2.2.2.1	TDD PDSCH Transmit Diversity 2x2	Rel-8	C02	UE supporting E-UTRA TDD	
8.2.2.2.2	TDD PDSCH Transmit Diversity 4x2	Rel-8	C02	UE supporting E-UTRA TDD	
8.2.2.3	Void				
8.2.2.3.1	TDD PDSCH Open Loop Spatial Multiplexing 2x2	Rel-8	C02	UE supporting E-UTRA TDD	
8.2.2.3.2	TDD PDSCH Open Loop Spatial Multiplexing 4x2	Rel-8	C02	UE supporting E-UTRA TDD	
8.2.2.4	Void				
8.2.2.4.1	TDD PDSCH Closed Loop Single/Multi Layer Spatial Multiplexing 2x2	Rel-8	C02	UE supporting E-UTRA TDD	
8.2.2.4.2	TDD PDSCH Closed Loop Single/Multi Layer Spatial Multiplexing 4x2	Rel-8	C02	UE supporting E-UTRA TDD	

Clause	Title	Release	Applicability		Additional Information
			Condition	Comments	
8.3.2.1	TDD PDSCH Performance (UE-Specific Reference Symbols)	Rel-8	C02	UE supporting E-UTRA TDD	
8.3	Void				
8.4.1.1	FDD PCFICH/PDCCH Single-antenna Port Performance	Rel-8	C01	UE supporting E-UTRA FDD	
8.4.1.2	Void				
8.4.1.2.1	FDD PCFICH/PDCCH Transmit Diversity 2x2	Rel-8	C01	UE supporting E-UTRA FDD	
8.4.1.2.2	FDD PCFICH/PDCCH Transmit Diversity 4x2	Rel-8	C01	UE supporting E-UTRA FDD	
8.4.2.1	TDD PCFICH/PDCCH Single-antenna Port Performance	Rel-8	C02	UE supporting E-UTRA TDD	
8.4.2.2	Void				
8.4.2.2.1	TDD PCFICH/PDCCH Transmit Diversity 2x2	Rel-8	C02	UE supporting E-UTRA TDD	
8.4.2.2.2	TDD PCFICH/PDCCH Transmit Diversity 4x2	Rel-8	C02	UE supporting E-UTRA TDD	
8.5.1.1	FDD PHICH Single-antenna Port Performance	Rel-8	C01	UE supporting E-UTRA FDD	
8.5.1.2	Void				
8.5.1.2.1	FDD PHICH Transmit Diversity 2x2	Rel-8	C01	UE supporting E-UTRA FDD	
8.5.1.2.2	FDD PHICH Transmit Diversity 4x2	Rel-8	C01	UE supporting E-UTRA FDD	
8.5.2.1	TDD PHICH Single-antenna Port Performance	Rel-8	C02	UE supporting E-UTRA TDD	
8.5.2.2	Void				
8.5.2.2.1	TDD PHICH Transmit Diversity 2x2	Rel-8	C02	UE supporting E-UTRA TDD	
8.5.2.2.2	TDD PHICH Transmit Diversity 4x2	Rel-8	C02	UE supporting E-UTRA TDD	
8.7.1.1	FDD sustained data rate performance	Rel-9	C01	UE supporting E-UTRA FDD	
8.7.2.1	TDD sustained data rate performance	Rel-9	C02	UE supporting E-UTRA TDD	
Reporting of Channel State Information					
9.2.1.1	FDD CQI Reporting under AWGN conditions – PUCCH 1-0	Rel-8	C01	UE supporting E-UTRA FDD	
9.2.1.2	TDD CQI Reporting under AWGN conditions – PUCCH 1-0	Rel-8	C02	UE supporting E-UTRA TDD	
9.2.2.1	FDD CQI Reporting under AWGN conditions – PUCCH 1-1	Rel-8	C01	UE supporting E-UTRA FDD	
9.2.2.2	TDD CQI Reporting under AWGN conditions – PUCCH 1-1	Rel-8	C02	UE supporting E-UTRA TDD	
9.3.1.1.1	FDD CQI Reporting under fading conditions – PUSCH 3-0	Rel-8	C01	UE supporting E-UTRA FDD	
9.3.1.1.2	TDD CQI Reporting under fading conditions – PUSCH 3-0	Rel-8	C02	UE supporting E-UTRA TDD	
9.3.2.1.1	FDD CQI Reporting under fading conditions – PUCCH 1-0	Rel-8	C01	UE supporting E-UTRA FDD	
9.3.2.1.2	TDD CQI Reporting under fading conditions – PUCCH 1-0	Rel-8	C02	UE supporting E-UTRA TDD	
9.3.3.1.1	FDD CQI Reporting under fading conditions and frequency-selective interference – PUSCH 3-0	Rel-8	C01	UE supporting E-UTRA FDD	
9.3.3.1.2	TDD CQI Reporting under fading conditions and frequency-selective interference – PUSCH 3-0	Rel-8	C02	UE supporting E-UTRA TDD	
9.4.1.1.1	FDD PMI Reporting – PUSCH 3-1 (Single PMI)	Rel-8	C01	UE supporting E-UTRA FDD	
9.4.1.1.2	TDD PMI Reporting – PUSCH 3-1 (Single PMI)	Rel-8	C02	UE supporting E-UTRA TDD	
9.4.2.1.1	FDD PMI Reporting – PUSCH 1-2 (Multiple PMI)	Rel-8	C01	UE supporting E-UTRA FDD	
9.4.2.1.2	TDD PMI Reporting – PUSCH 1-2 (Multiple PMI)	Rel-8	C02	UE supporting E-UTRA TDD	
9.5.1.1	FDD RI Reporting – PUCCH 1-1	Rel-8	C01	UE supporting E-UTRA FDD	
9.5.1.2	TDD RI Reporting – PUCCH 1-1	Rel-8	C02	UE supporting E-UTRA TDD	

Table 4.1-1a: Applicability of RF conformance test cases Conditions

C01	IF A.4.1-1/1 THEN R ELSE N/A
C02	IF A.4.1-1/2 THEN R ELSE N/A

4.2 RRM conformance test cases

Table 4.2-1: Applicability of RRM conformance test cases, ref. TS 36.521-3 [2]

Clause	Title	Release	Applicability		Additional Information
			Condition	Comments	
E-UTRAN RRC_IDLE State Mobility					
4.2.1	E-UTRAN FDD - FDD cell re-selection intra frequency case	Rel-8	C01	UE supporting E-UTRA FDD	
4.2.2	E-UTRAN TDD - TDD cell re-selection intra frequency case	Rel-8	C02	UE supporting E-UTRA TDD	
4.2.3	E-UTRAN FDD - FDD cell re-selection inter frequency case	Rel-8	C01	UE supporting E-UTRA FDD	
4.2.4	E-UTRAN FDD - TDD cell re-selection inter frequency case	Rel-8	C03	UE supporting E-UTRA FDD and E-UTRA TDD	
4.2.5	E-UTRAN TDD - FDD cell re-selection inter frequency case	Rel-8	C03	UE supporting E-UTRA FDD and E-UTRA TDD	
4.2.6	E-UTRAN TDD - TDD cell re-selection inter frequency case	Rel-8	C02	UE supporting E-UTRA TDD	
4.3.1.1	E-UTRA FDD - UTRAN FDD cell re-selection	Rel-8	C04	UE supporting E-UTRA FDD and UTRA FDD	
4.3.1.2	E-UTRA FDD - UTRAN FDD cell re-selection: UTRA FDD is of lower priority	Rel-8	C04	UE supporting E-UTRA FDD and UTRA FDD	
4.3.1.3	E-UTRAN FDD - UTRAN FDD cell re-selection in fading propagation conditions: UTRA FDD is of lower priority	Rel-8	C04	UE supporting E-UTRA FDD and UTRA FDD	
4.3.2	E-UTRAN FDD - UTRAN TDD cell re-selection	Rel-8	C06	UE supporting E-UTRA FDD and UTRA TDD	
4.3.3	E-UTRAN TDD - UTRAN FDD cell re-selection	Rel-8	C07	UE supporting E-UTRA TDD and UTRA FDD	
4.3.4.1	E-UTRA TDD - UTRAN TDD cell re-selection	Rel-8	C05	UE supporting E-UTRA TDD and UTRA TDD	
4.3.4.2	E-UTRAN TDD - UTRAN TDD cell re-selection: UTRA is of lower priority	Rel-8	C05	UE supporting E-UTRA TDD and UTRA TDD	
4.4.1	E-UTRAN FDD - GSM cell re-selection	Rel-8	C08	UE supporting E-UTRA FDD and GSM	
4.4.2	E-UTRAN TDD - GSM cell re-selection	Rel-8	C09	UE supporting E-UTRA TDD and GSM	
4.5.1.1	E-UTRAN FDD - HRPD Cell re-selection: HRPD is of lower priority	Rel-8	C10	UE supporting E-UTRA FDD and cdma2000 HRPD	
4.6.1.1	E-UTRAN FDD - cdma2000 1xRTT Cell re-selection: cdma2000 1x is of lower priority	Rel-8	C11	UE supporting E-UTRA FDD and cdma2000 1xRTT	
E-UTRAN RRC_CONNECTED State Mobility					
5.1.1	E-UTRAN FDD - FDD Handover intra frequency case	Rel-8	C01	UE supporting E-UTRA FDD	
5.1.2	E-UTRAN TDD - TDD Handover intra frequency case	Rel-8	C02	UE supporting E-UTRA TDD	
5.1.3	E-UTRAN FDD - FDD Handover inter frequency case	Rel-8	C01a	UE supporting E-UTRA FDD and Feature Group Indicator 13 and Feature Group Indicator 25	
5.1.4	E-UTRAN TDD - TDD Handover inter frequency case	Rel-8	C02a	UE supporting E-UTRA TDD and Feature Group Indicator 13 and Feature Group Indicator 25	
5.1.5	E-UTRAN FDD - FDD inter frequency handover: unknown target cell	Rel-8	C01a	UE supporting E-UTRA FDD and Feature Group Indicator 13 and Feature Group Indicator 25	
5.1.6	E-UTRAN TDD-TDD inter frequency handover: unknown target cell	Rel-8	C02a	UE supporting E-UTRA TDD and Feature Group Indicator 13 and Feature Group Indicator 25	
5.2.1	E-UTRAN FDD - UTRAN FDD handover	Rel-8	C04a	UE supporting E-UTRA FDD and UTRA FDD and Feature Group Indicator 8 and Feature Group Indicator 22	
5.2.2	E-UTRAN TDD - UTRAN FDD handover	Rel-8	C07a	UE supporting E-UTRA TDD and UTRA FDD and Feature Group Indicator 8 and Feature Group Indicator 22	

Clause	Title	Release	Applicability		Additional Information
			Condition	Comments	
5.2.3	E-UTRAN FDD - GSM handover	Rel-8	C08a	UE supporting E-UTRA FDD and GSM and Feature Group Indicator 9 and Feature Group Indicator 23	
5.2.4	E-UTRAN TDD - UTRAN TDD handover	Rel-8	C05a	UE supporting E-UTRA TDD and UTRA TDD and Feature Group Indicator 8 and Feature Group Indicator 22	
5.2.5	E-UTRAN FDD - UTRAN TDD handover	Rel-8	C06a	UE supporting E-UTRA FDD and UTRA TDD and Feature Group Indicator 8 and Feature Group Indicator 22	
5.2.7	E-UTRAN FDD - UTRAN FDD handover: unknown target cell	Rel-8	C04a	UE supporting E-UTRA FDD and UTRA FDD and Feature Group Indicator 8 and Feature Group Indicator 22	
5.2.8	E-UTRAN FDD - GSM handover: unknown target cell	Rel-8	C08a	UE supporting E-UTRA FDD and GSM and Feature Group Indicator 9 and Feature Group Indicator 23	
5.2.9	E-UTRAN TDD - GSM handover: unknown target cell	Rel-8	C09b	UE supporting E-UTRA TDD and GSM and Feature Group Indicator 9 and Feature Group Indicator 23	
5.2.10	E-UTRAN TDD - UTRAN TDD handover: unknown target cell	Rel-8	C05a	UE supporting E-UTRA FDD and UTRA TDD and Feature Group Indicator 8 and Feature Group Indicator 22	
5.3.1	E-UTRAN FDD - HRPD Handover	Rel-8	C10a	UE supporting E-UTRA FDD and cdma2000 HRPD and Feature Group Indicator 12 and Feature Group Indicator 26	
5.3.2	E-UTRAN FDD - cdma2000 1xRTT handover	Rel-8	C11a	UE supporting E-UTRA FDD and cdma2000 1xRTT and Feature Group Indicator 11 and Feature Group Indicator 24	
5.3.3	E-UTRAN FDD - HRPD handover: unknown target cell	Rel-8	C10a	UE supporting E-UTRA FDD and cdma2000 HRPD and Feature Group Indicator 12 and Feature Group Indicator 26	
5.3.4	E-UTRAN FDD - cdma2000 1xRTT handover: unknown target cell	Rel-8	C11a	UE supporting E-UTRA FDD and cdma2000 1xRTT and Feature Group Indicator 11 and Feature Group Indicator 24	
RRC Connection Mobility Control					
6.1.1	E-UTRAN FDD Intra-frequency RRC Re-establishment	Rel-8	C01	UE supporting E-UTRA FDD	
6.1.2	E-UTRAN FDD Inter-frequency RRC Re-establishment	Rel-8	C01b	UE supporting E-UTRA FDD and Feature Group Indicator 25	
6.1.3	E-UTRAN TDD Intra-frequency RRC Re-establishment	Rel-8	C02	UE supporting E-UTRA TDD	
6.1.4	E-UTRAN TDD Inter-frequency RRC Re-establishment	Rel-8	C02b	UE supporting E-UTRA TDD and Feature Group Indicator 25	
6.2.1	E-UTRAN FDD - Contention Based Random Access Test	Rel-8	C01	UE supporting E-UTRA FDD	
6.2.2	E-UTRAN FDD - Non-Contention Based Random Access Test	Rel-8	C01	UE supporting E-UTRA FDD	
6.2.3	E-UTRAN TDD - Contention Based Random Access Test	Rel-8	C02	UE supporting E-UTRA TDD	
6.2.4	E-UTRAN TDD - Non-Contention Based Random Access Test	Rel-8	C02	UE supporting E-UTRA TDD	
Timing and Signalling Characteristics					
7.1.1	E-UTRAN FDD - UE Transmit Timing Accuracy	Rel-8	C01	UE supporting E-UTRA FDD	
7.1.2	E-UTRAN TDD - UE Transmit Timing Accuracy	Rel-8	C02	UE supporting E-UTRA TDD	
7.2.1	E-UTRAN FDD - UE Timing Advance Adjustment Accuracy	Rel-8	C01	UE supporting E-UTRA FDD	
7.2.2	E-UTRAN TDD - UE Timing Advance Adjustment Accuracy	Rel-8	C02	UE supporting E-UTRA TDD	
7.3.1	E-UTRAN FDD Radio Link Monitoring Test for Out-of-Sync	Rel-8	C01	UE supporting E-UTRA FDD	
7.3.2	E-UTRAN FDD Radio Link Monitoring Test for In-Sync	Rel-8	C01	UE supporting E-UTRA FDD	

Clause	Title	Release	Applicability		Additional Information
			Condition	Comments	
7.3.3	E-UTRAN TDD Radio Link Monitoring Test for Out-of-Sync	Rel-8	C02	UE supporting E-UTRA TDD	
7.3.4	E-UTRAN TDD Radio Link Monitoring Test for In-Sync	Rel-8	C02	UE supporting E-UTRA TDD	
7.3.5	E-UTRAN FDD Radio Link Monitoring Test for Out-of-sync in DRX	Rel-8	C01	UE supporting E-UTRA FDD	
7.3.6	E-UTRAN FDD Radio Link Monitoring Test for In-sync in DRX	Rel-8	C01	UE supporting E-UTRA FDD	
7.3.7	E-UTRAN TDD Radio Link Monitoring Test for Out-of-sync in DRX	Rel-8	C02	UE supporting E-UTRA TDD	
7.3.8	E-UTRAN TDD Radio Link Monitoring Test for In-sync in DRX	Rel-8	C02	UE supporting E-UTRA TDD	
UE Measurements Procedures					
8.1.1	E-UTRAN FDD-FDD intra-frequency event triggered reporting under fading propagation conditions in asynchronous cells	Rel-8	C01	UE supporting E-UTRA FDD	
8.1.2	E-UTRAN FDD-FDD intra-frequency event triggered reporting under fading propagation conditions in synchronous cells	Rel-8	C01	UE supporting E-UTRA FDD	
8.1.3	E-UTRAN FDD-FDD intra-frequency event triggered reporting under fading propagation conditions in synchronous cells with DRX	Rel-8	C01	UE supporting E-UTRA FDD	
8.1.4	Void				
8.2.1	E-UTRAN TDD-TDD intra-frequency event triggered reporting under fading propagation conditions in synchronous cells	Rel-8	C02	UE supporting E-UTRA TDD	
8.2.2	E-UTRAN TDD-TDD intra-frequency event triggered reporting under fading propagation conditions in synchronous cells with DRX	Rel-8	C02	UE supporting E-UTRA TDD	
8.3.1	E-UTRAN FDD-FDD inter-frequency event triggered reporting under fading propagation conditions in asynchronous cells	Rel-8	C01b	UE supporting E-UTRA FDD and Feature Group Indicator 25	
8.3.2	E-UTRAN FDD-FDD inter-frequency event triggered reporting when DRX is used under fading propagation conditions in asynchronous cells	Rel-8	C01b	UE supporting E-UTRA FDD and Feature Group Indicator 25	
8.3.3	E-UTRAN FDD-FDD inter frequency event triggered reporting under AWGN propagation conditions in asynchronous cells with DRX when L3 filtering is used	Rel-8	C01b	UE supporting E-UTRA FDD and Feature Group Indicator 25	
8.4.1	E-UTRAN TDD-TDD inter-frequency event triggered reporting under fading propagation conditions in synchronous cells	Rel-8	C02b	UE supporting E-UTRA TDD and Feature Group Indicator 25	
8.4.2	E-UTRAN TDD-TDD inter-frequency event triggered reporting when DRX is used under fading propagation conditions in synchronous cells	Rel-8	C02a	UE supporting E-UTRA TDD and Feature Group Indicator 25	
8.5.1	E-UTRAN FDD-UTRAN FDD event triggered reporting under fading propagation conditions	Rel-8	C04b	UE supporting E-UTRA FDD and UTRA FDD and Feature Group Indicator 22	
8.5.2	E-UTRAN FDD-UTRAN FDD SON ANR cell search reporting under AWGN propagation conditions	Rel-8	C04b	UE supporting E-UTRA FDD and UTRA FDD and Feature Group Indicator 22	
8.5.3	E-UTRAN FDD - UTRAN FDD event triggered reporting when DRX is used under fading propagation conditions	Rel-8	C04b	UE supporting E-UTRA FDD and UTRA FDD and Feature Group Indicator 22	
8.6.1	E-UTRAN TDD-UTRAN FDD event triggered reporting under fading propagation conditions	Rel-8	C07b	UE supporting E-UTRA TDD and UTRA FDD and Feature Group Indicator 22	
8.7.1	E-UTRAN TDD-UTRAN TDD cell search under fading propagation conditions	Rel-8	C05b	UE supporting E-UTRA TDD and UTRA TDD and Feature Group Indicator 22	

Clause	Title	Release	Applicability		Additional Information
			Condition	Comments	
8.7.2	E-UTRAN TDD - UTRAN TDD cell search when DRX is used under fading propagation conditions	Rel-8	C05b	UE supporting E-UTRA TDD and UTRA TDD and Feature Group Indicator 22	
8.7.3	E-UTRAN TDD - UTRAN TDD SON ANR cell search reporting under AWGN propagation conditions	Rel-8	C05b	UE supporting E-UTRA TDD and UTRA TDD and Feature Group Indicator 22	
8.8.1	E-UTRAN FDD-GSM event triggered reporting in AWGN	Rel-8	C08b	UE supporting E-UTRA FDD and GSM and Feature Group Indicator 23	
8.8.2	E-UTRAN FDD - GSM event triggered reporting when DRX is used in AWGN	Rel-8	C08b	UE supporting E-UTRA FDD and GSM and Feature Group Indicator 23	
8.9.1	E-UTRAN FDD-UTRAN TDD event triggered reporting in fading propagation conditions	Rel-8	C06b	UE supporting E-UTRA FDD and UTRA TDD and Feature Group Indicator 22	
8.10.1	E-UTRAN TDD-GSM event triggered reporting in AWGN	Rel-8	C09a	UE supporting E-UTRA TDD and GSM and Feature Group Indicator 23	
8.10.2	E-UTRAN TDD - GSM event triggered reporting when DRX is used in AWGN	Rel-8	C09a	UE supporting E-UTRA TDD and GSM and Feature Group Indicator 23	
8.11.1	Multiple E-UTRAN FDD-FDD Inter-frequency event triggered reporting under fading propagation conditions	Rel-8	C01	UE supporting E-UTRA FDD	
8.11.2	E-UTRAN TDD - E-UTRAN TDD and E-UTRAN TDD Inter-frequency event triggered reporting under fading propagation conditions	Rel-8	C07b	UE supporting E-UTRA TDD and Feature Group Indicator 22	
8.11.3	E-UTRAN FDD-FDD Inter-frequency and UTRAN FDD event triggered reporting under fading propagation conditions	Rel-8	C04	UE supporting E-UTRA FDD and UTRA FDD	
8.11.4	InterRAT E-UTRA TDD to E-UTRA TDD and UTRA TDD cell search	Rel-8	C05	UE supporting E-UTRA TDD and UTRA TDD	
8.11.5	Combined E-UTRAN FDD - E-UTRA FDD and GSM cell search; E-UTRA cells in fading; GSM cell in static propagation conditions	Rel-8	C08c	UE supporting E-UTRA FDD and GSM and Feature Group Indicator 22	
8.11.6	Combined E-UTRAN TDD - E-UTRA TDD and GSM cell search; E-UTRA cells in fading; GSM cell in static propagation conditions	Rel-8	C09c	UE supporting E-UTRA TDD and GSM and Feature Group Indicator 22	
Measurement Performance Requirements					
9.1.1.1	FDD Intra Frequency Absolute RSRP Accuracy	Rel-8	C01	UE supporting E-UTRA FDD	
9.1.1.2	FDD Intra Frequency Relative Accuracy of RSRP	Rel-8	C01	UE supporting E-UTRA FDD	
9.1.2.1	TDD Intra Frequency Absolute RSRP Accuracy	Rel-8	C02	UE supporting E-UTRA TDD	
9.1.2.2	TDD Intra Frequency Relative Accuracy of RSRP	Rel-8	C02	UE supporting E-UTRA TDD	
9.1.3.1	FDD - FDD Inter Frequency Absolute RSRP Accuracy	Rel-8	C01	UE supporting E-UTRA FDD	
9.1.3.2	FDD - FDD Inter Frequency Relative Accuracy of RSRP	Rel-8	C01	UE supporting E-UTRA FDD	
9.1.4.1	TDD - TDD Inter Frequency Absolute RSRP Accuracy	Rel-8	C02	UE supporting E-UTRA TDD	
9.1.4.2	TDD - TDD Inter Frequency Relative Accuracy of RSRP	Rel-8	C02	UE supporting E-UTRA TDD	
9.2.1.1	FDD Intra Frequency Absolute RSRQ Accuracy	Rel-8	C01	UE supporting E-UTRA FDD	
9.2.2.1	TDD Intra Frequency Absolute RSRQ Accuracy	Rel-8	C02	UE supporting E-UTRA TDD	
9.2.3.1	FDD - FDD Inter Frequency Absolute RSRQ Accuracy	Rel-8	C01	UE supporting E-UTRA FDD	
9.2.3.2	FDD - FDD Inter Frequency Relative Accuracy of RSRQ	Rel-8	C01	UE supporting E-UTRA FDD	
9.2.4.1	TDD - TDD Inter Frequency Absolute RSRQ Accuracy	Rel-8	C02	UE supporting E-UTRA TDD	
9.2.4.2	TDD -TDD Inter Frequency Relative Accuracy of RSRQ	Rel-8	C02	UE supporting E-UTRA TDD	

Clause	Title	Release	Applicability		Additional Information
			Condition	Comments	
9.3.1	E-UTRAN FDD - UTRA FDD CPICH RSCP absolute accuracy	Rel-9	C04	UE supporting E-UTRA FDD and UTRA FDD	
9.4.1	E-UTRAN FDD - UTRA FDD CPICH Ec/No absolute accuracy	Rel-9	C04	UE supporting E-UTRA FDD and UTRA FDD	
9.3.2	E-UTRAN TDD - UTRA FDD CPICH RSCP absolute accuracy	Rel-9	C07	UE supporting E-UTRA TDD and UTRA FDD	
9.4.2	E-UTRAN TDD - UTRA FDD CPICH Ec/No absolute accuracy	Rel-9	C07	UE supporting E-UTRA TDD and UTRA FDD	
9.6.2	GSM RSSI absolute accuracy for E-UTRAN TDD	Rel-9	C09	UE supporting E-UTRA TDD and GSM	

Table 4.2-1a: Applicability of RRM conformance test cases Conditions

C01	IF A.4.1-1/1 THEN R ELSE N/A
C01a	IF (A.4.1-1/1 AND A.4.4-1/13 AND A.4.4-1/25) THEN R ELSE N/A
C01b	IF (A.4.1-1/1 AND A.4.4-1/25) THEN R ELSE N/A
C02	IF A.4.1-1/2 THEN R ELSE N/A
C02a	IF (A.4.1-1/2 AND A.4.4-1/13 AND A.4.4-1/25) THEN R ELSE N/A
C02b	IF (A.4.1-1/2 AND A.4.4-1/25) THEN R ELSE N/A
C03	IF (A.4.1-1/1 AND A.4.1-1/2) THEN R ELSE N/A
C04	IF (A.4.1-1/1 AND A.4.1-1/3) THEN R ELSE N/A
C04a	IF (A.4.1-1/1 AND A.4.1-1/3 AND A.4.4-1/8 AND A.4.4-1/22) THEN R ELSE N/A
C04b	IF (A.4.1-1/1 AND A.4.1-1/3 AND A.4.4-1/22) THEN R ELSE N/A
C05	IF (A.4.1-1/2 AND A.4.1-1/4) THEN R ELSE N/A
C05a	IF (A.4.1-1/2 AND A.4.1-1/4 AND A.4.4-1/9 AND A.4.4-1/25) THEN R ELSE N/A
C05b	IF (A.4.1-1/2 AND A.4.1-1/4 AND A.4.4-1/25) THEN R ELSE N/A
C06	IF (A.4.1-1/1 AND A.4.1-1/4) THEN R ELSE N/A
C06a	IF (A.4.1-1/1 AND A.4.1-1/4 AND A.4.4-1/11 AND A.4.4-1/22) THEN R ELSE N/A
C06b	IF (A.4.1-1/1 AND A.4.1-1/4 AND A.4.4-1/22) THEN R ELSE N/A
C07	IF (A.4.1-1/2 AND A.4.1-1/3) THEN R ELSE N/A
C07a	IF (A.4.1-1/2 AND A.4.1-1/3 AND A.4.4-1/8 AND A.4.4-1/22) THEN R ELSE N/A
C07b	IF (A.4.1-1/2 AND A.4.1-1/3 AND A.4.4-1/22) THEN R ELSE N/A
C08	IF (A.4.1-1/1 AND A.4.1-1/5) THEN R ELSE N/A
C08a	IF (A.4.1-1/1 AND A.4.1-1/5 AND A.4.4-1/9 AND A.4.4-1/23) THEN R ELSE N/A
C08b	IF (A.4.1-1/1 AND A.4.1-1/5 AND A.4.4-1/23) THEN R ELSE N/A
C08c	IF (A.4.1-1/1 AND A.4.1-1/5 AND A.4.4-1/22) THEN R ELSE N/A
C09	IF (A.4.1-1/2 AND A.4.1-1/5) THEN R ELSE N/A
C09a	IF (A.4.1-1/2 AND A.4.1-1/5 AND A.4.4-1/23) THEN R ELSE N/A
C09b	IF (A.4.1-1/2 AND A.4.1-1/5 AND A.4.4-1/9 AND A.4.4-1/23) THEN R ELSE N/A
C09c	IF (A.4.1-1/2 AND A.4.1-1/5 AND A.4.4-1/22) THEN R ELSE N/A
C10	IF (A.4.1-1/1 AND A.4.1-1/6) THEN R ELSE N/A
C10a	IF (A.4.1-1/1 AND A.4.1-1/6 AND A.4.4-1/12 AND A.4.4-1/26) THEN R ELSE N/A
C11	IF (A.4.1-1/1 AND A.4.1-1/7) THEN R ELSE N/A
C11a	IF (A.4.1-1/1 AND A.4.1-1/7 AND A.4.4-1/11 AND A.4.4-1/24) THEN R ELSE N/A

Annex A (normative): ICS proforma for E-UTRA User Equipment

Notwithstanding the provisions of the copyright related to the text of the present document, The Organizational Partners of 3GPP grant that users of the present document may freely reproduce the ICS proforma in this annex so that it can be used for its intended purposes and may further publish the completed ICS.

A.1 Guidance for completing the ICS proforma

A.1.1 Purposes and structure

The purpose of this ICS proforma is to provide a mechanism whereby a supplier of an implementation of the requirements defined in relevant specifications may provide information about the implementation in a standardised manner.

The ICS proforma is subdivided into clauses for the following categories of information:

- instructions for completing the ICS proforma;
- identification of the implementation;
- identification of the protocol;
- ICS proforma tables (for example: UE implementation types, Teleservices, etc).

A.1.2 Abbreviations and conventions

The ICS proforma contained in this annex is comprised of information in tabular form in accordance with the guidelines presented in ISO/IEC 9646-7 [4].

Item column

The item column contains a number which identifies the item in the table.

Item description column

The item description column describes in free text each respective item (e.g. parameters, timers, etc.). It implicitly means "is <item description> supported by the implementation?".

Reference column

The reference column gives reference to the relevant 3GPP core specifications.

Release column

The release column indicates the earliest release from which the capability or option is relevant.

Comments column

This column is left blank for particular use by the reader of the present document.

References to items

For each possible item answer (answer in the support column) within the ICS proforma there exists a unique reference, used, for example, in the conditional expressions. It is defined as the table identifier, followed by a solidus character "/", followed by the item number in the table. If there is more than one support column in a table, the columns shall be discriminated by letters (a, b, etc.), respectively.

EXAMPLE 1: A.4.1-1/2 is the reference to the answer of item 2 in table A.4.1-1.

A.1.3 Instructions for completing the ICS proforma

The supplier of the implementation may complete the ICS proforma in each of the spaces provided. More detailed instructions are given at the beginning of the different clauses of the ICS proforma.

A.2 Identification of the User Equipment

Identification of the User Equipment should be filled in so as to provide as much detail as possible regarding version numbers and configuration options.

The product supplier information and client information should both be filled in if they are different.

A person who can answer queries regarding information supplied in the ICS should be named as the contact person.

A.2.1 Date of the statement

.....

A.2.2 User Equipment Under Test (UEUT) identification

UEUT name:

.....
.....

Hardware configuration:

.....
.....
.....

Software configuration:

.....
.....
.....

A.2.3 Product supplier

Name:

.....

Address:

.....

.....

.....

Telephone number:

.....

Facsimile number:

.....

E-mail address:

.....

Additional information:

.....

.....

.....

A.2.4 Client

Name:

.....

Address:

.....

.....

.....

Telephone number:

.....

Facsimile number:

.....

E-mail address:

.....

Additional information:

.....

.....

.....

A.2.5 ICS contact person

Name:

.....

Telephone number:

.....

Facsimile number:

.....

E-mail address:

.....

Additional information:

.....

.....

A.3 Identification of the protocol

This ICS proforma applies to the 3GPP standards listed in the normative references clause of the present document.

A.4 ICS proforma tables

Editor's Note: This clause is not completed

A.4.1 UE Implementation Types

Table A.4.1-1: UE Radio Technologies

Item	UE Radio Technologies	Ref.	Release	Comments
1	E-UTRA FDD	36.101	Rel-8	
2	E-UTRA TDD	36.101	Rel-8	
3	UTRA FDD	25.101	Rel-8	
4	UTRA TDD	25.102	Rel-8	
5	GSM	45.005	Rel-8	
6	cdma2000 HRPD	C.S0024-A	Rel-8	
7	cdma2000 1xRTT	C.S0002-A	Rel-8	

A.4.2 UE Service Capabilities

Table A.4.2-1: UE Radio Technologies

Item	UE Radio Technologies	Ref.	Release	Comments
1	FFS			

A.4.3 Baseline Implementation Capabilities

Table A.4.3-1: Supported protocols

Item	Supported protocols	Ref.	Release	Comments
1	EPS Mobility Management	24.301, 5	Rel-8	
2	EPS Session Management	24.301, 6	Rel-8	
3	GPRS Mobility Management	23.060	R99	
4	Radio Resource Control	36.331	Rel-8	
5	Packet Data Convergence Protocol	36.323	Rel-8	
6	Radio Link Control	36.322	Rel-8	
7	Medium Access Control	36.321	Rel-8	
8	Physical Layer	36.201, 36.302	Rel-8	

Table A.4.3-2: Special Conformance Testing Functions

Item	Special Conformance Testing Functions	Ref.	Release	Comments
1	UE test loop	36.509	Rel-8	
2	Max UE test loop UL RLC SDU size 65535 bits	36.509	Rel-8	

Table A.4.3-3: RF Baseline Implementation Capabilities

Item	RF Baseline Implementation Capabilities	Ref.	Release	Comments
1	Frequency band: 1920-1980, 2110-2170 MHz	36.101, 5.5	Rel-8	FDD Band 1
2	Frequency band: 1850-1910, 1930-1990 MHz	36.101, 5.5	Rel-8	FDD Band 2
3	Frequency band: 1710-1785, 1805-1880 MHz	36.101, 5.5	Rel-8	FDD Band 3
4	Frequency band: 1710-1755, 2110-2155 MHz	36.101, 5.5	Rel-8	FDD Band 4
5	Frequency band: 824-849, 869-894 MHz	36.101, 5.5	Rel-8	FDD Band 5
6	Frequency band: 830-840, 875-885 MHz	36.101, 5.5	Rel-8	FDD Band 6
7	Frequency band: 2500-2570, 2620-2690 MHz	36.101, 5.5	Rel-8	FDD Band 7
8	Frequency band: 880-915, 925-960 MHz	36.101, 5.5	Rel-8	FDD Band 8
9	Frequency band: 1749.9-1784.9, 1844.9-1879.9 MHz	36.101, 5.5	Rel-8	FDD Band 9
10	Frequency band: 1710-1770, 2110-2170 MHz	36.101, 5.5	Rel-8	FDD Band 10
11	Frequency band: 1427.9-1447.9, 1475.9-1495.9 MHz	36.101, 5.5	Rel-8	FDD Band 11
12	Frequency band: 698-716, 728-746 MHz	36.101, 5.5	Rel-8	FDD Band 12
13	Frequency band: 777-787, 746-756 MHz	36.101, 5.5	Rel-8	FDD Band 13
14	Frequency band: 788-798, 758-768 MHz	36.101, 5.5	Rel-8	FDD Band 14
15	Reserved	36.101, 5.5	Rel-8	FDD Band 15
16	Reserved	36.101, 5.5	Rel-8	FDD Band 16
17	Frequency band: 704-716, 734-746 MHz	36.101, 5.5	Rel-8	FDD Band 17
18	Frequency band: 815-830, 860-875 MHz	36.101, 5.5	Rel-9	FDD Band 18
19	Frequency band: 830-845, 875-890 MHz	36.101, 5.5	Rel-9	FDD Band 19
...				
20	Frequency band: 832-862, 791-821MHz	36.101, 5.5	Rel-9	FDD Band 20
21	Frequency band: 1447.9-1462.9, 1495.9-1510.9 MHz	36.101, 5.5	Rel-9	FDD band 21
...				
33	Frequency band: 1900-1920, 1900-1920 MHz	36.101, 5.5	Rel-8	TDD Band 33
34	Frequency band: 2010-2025, 2010-2025 MHz	36.101, 5.5	Rel-8	TDD Band 34
35	Frequency band: 1850-1910, 1850-1910 MHz	36.101, 5.5	Rel-8	TDD Band 35
36	Frequency band: 1930-1990, 1930-1990 MHz	36.101, 5.5	Rel-8	TDD Band 36
37	Frequency band: 1910-1930, 1910-1930 MHz	36.101, 5.5	Rel-8	TDD Band 37
38	Frequency band: 2570-2620, 2570-2620 MHz	36.101, 5.5	Rel-8	TDD Band 38
39	Frequency band: 1880-1920, 1880-1920 MHz	36.101, 5.5	Rel-8	TDD Band 39
40	Frequency band: 2300-2400, 2300-2400 MHz	36.101, 5.5	Rel-8	TDD Band 40
41	Frequency band: 2496-2690, 2496-2690 MHz	36.101, 5.5	Rel-10	TDD Band 41
42	Frequency band: 3400-3600, 3400-3600 MHz	36.101, 5.5	Rel-10	TDD Band 42
43	Frequency band: 3600-3800, 3600-3800 MHz	36.101, 5.5	Rel-10	TDD Band 43
Note:	The values indicated in column "Release" are to be understood as the specifications release version in which a band was introduced and not as a mandate that a UE conforming to particular release shall support a particular band. For further guidance to release independent bands see TS 36.307 [16]			

Table A.4.3-4: PUSCH physical layer Categories

Item	PUSCH physical layer categories	Ref.	Release	Comments
1	Category 1	36.306, 4.1	Rel-8	
2	Category 2	36.306, 4.1	Rel-8	
3	Category 3	36.306, 4.1	Rel-8	
4	Category 4	36.306, 4.1	Rel-8	
5	Category 5	36.306, 4.1	Rel-8	Support for 64QAM in UL

Table A.4.3-5: PDSCH physical layer Categories

Item	PDSCH physical layer categories	Ref.	Release	Comments
1	Category 1	36.306, 4.1	Rel-8	
2	Category 2	36.306, 4.1	Rel-8	
3	Category 3	36.306, 4.1	Rel-8	
4	Category 4	36.306, 4.1	Rel-8	
5	Category 5	36.306, 4.1	Rel-8	

Table A.4.3-6: Supported Mixed MBSFN-unicast capabilities

Item	Supported Mixed MBSFN-unicast capabilities	Ref.	Release	Comments
1	Mixed MBSFN-unicast	36.211, 6.5	Rel-8	Support for MBSFN subframes: 1, 2, 3, 6, 7, 8

A.4.4 Feature group indicators

Table A.4.4-1: Feature group indicators

Item	Additional information	Notes	Ref.	Release	Mnemonic	Comments
1	Support of - Intra-subframe frequency hopping for PUSCH scheduled by UL grant - DCI format 3a (TPC commands for PUCCH and PUSCH with single bit power adjustments) - Multi-user MIMO for PDSCH - Aperiodic CQI/PMI/RI reporting on PUSCH: Mode 2-0 – UE selected subband CQI without PMI - Aperiodic CQI/PMI/RI reporting on PUSCH: Mode 2-2 – UE selected subband CQI with multiple PMI		36.331, Annex B.1	Rel-8	pc_FeatrGrp_1	Corresponding to the Index of Indicator, the leftmost binary bit 1 Set to true if supporting all functionalities in the feature group
2	Support of - Simultaneous CQI and ACK/NACK on PUCCH, i.e. PUCCH format 2a and 2b - Absolute TPC command for PUSCH - Resource allocation type 1 for PDSCH - Periodic CQI/PMI/RI reporting on PUCCH: Mode 2-0 – UE selected subband CQI without PMI - Periodic CQI/PMI/RI reporting on PUCCH: Mode 2-1 – UE selected subband CQI with single PMI		36.331, Annex B.1	Rel-8	pc_FeatrGrp_2	Corresponding to the Index of Indicator, the leftmost binary bit 2 Set to true if supporting all functionalities in the feature group

3	Support of - Semi-persistent scheduling - TTI bundling - 5bit RLC UM SN - 7bit PDCP SN	- can only be set to 1 if the UE has set bit number 7 to 1.	36.331, Annex B.1	Rel-8	pc_FeatrGrp_3	Corresponding to the Index of Indicator, the leftmost binary bit 3 Set to true if supporting all functionalities in the feature group
4	Support of - Short DRX cycle	- can only be set to 1 if the UE has set bit number 5 to 1.	36.331, Annex B.1	Rel-8	pc_FeatrGrp_4	Corresponding to the Index of Indicator, the leftmost binary bit 4 Set to true if supporting all functionalities in the feature group
5	Support of - Long DRX cycle - DRX command MAC control element		36.331, Annex B.1	Rel-8	pc_FeatrGrp_5	Corresponding to the Index of Indicator, the leftmost binary bit 5 Set to true if supporting all functionalities in the feature group
6	Support of - Prioritized bit rate		36.331, Annex B.1	Rel-8	pc_FeatrGrp_6	Corresponding to the Index of Indicator, the leftmost binary bit 6 Set to true if supporting all functionalities in the feature group
7	Support of - RLC UM	- can only be set to 0 if the UE does not support voice	36.331, Annex B.1	Rel-8	pc_FeatrGrp_7	Corresponding to the Index of Indicator, the leftmost binary bit 7 Set to true if supporting all functionalities in the feature group
8	Support of - EUTRA RRC_CONNECTED to UTRA CELL_DCH PS handover	- can only be set to 1 if the UE has set bit number 22 to 1	36.331, Annex B.1	Rel-8	pc_FeatrGrp_8	Corresponding to the Index of Indicator, the leftmost binary bit 8 Set to true if supporting all functionalities in the feature group
9	Support of - EUTRA RRC_CONNECTED to GERAN GSM_Dedicated handover	- related to SR-VCC - can only be set to 1 if the UE has set bit number 23 to 1	36.331, Annex B.1	Rel-8	pc_FeatrGrp_9	Corresponding to the Index of Indicator, the leftmost binary bit 9 Set to true if supporting all functionalities in the feature group

10	Support of - EUTRA RRC_CONNECTED to GERAN (Packet_)Idle by Cell Change Order - EUTRA RRC_CONNECTED to GERAN (Packet_)Idle by Cell Change Order with NACC (Network Assisted Cell Change)		36.331, Annex B.1	Rel-8	pc_FeatrGrp_10	Corresponding to the Index of Indicator, the leftmost binary bit 10 Set to true if supporting all functionalities in the feature group
11	Support of - EUTRA RRC_CONNECTED to CDMA2000 1xRTT CS Active handover	- can only be set to 1 if the UE has sets bit number 24 to 1	36.331, Annex B.1	Rel-8	pc_FeatrGrp_11	Corresponding to the Index of Indicator, the leftmost binary bit 11 Set to true if supporting all functionalities in the feature group
12	Support of - EUTRA RRC_CONNECTED to CDMA2000 HRPD Active handover	- can only be set to 1 if the UE has set bit number 26 to 1	36.331, Annex B.1	Rel-8	pc_FeatrGrp_12	Corresponding to the Index of Indicator, the leftmost binary bit 12 Set to true if supporting all functionalities in the feature group
13	Support of - Inter-frequency handover	- can only be set to 1 if the UE has set bit number 25 to 1	36.331, Annex B.1	Rel-8	pc_FeatrGrp_13	Corresponding to the Index of Indicator, the leftmost binary bit 13 Set to true if supporting all functionalities in the feature group
14	Support of - Measurement reporting event: Event A4 – Neighbour > threshold - Measurement reporting event: Event A5 – Serving < threshold1 & Neighbour > threshold2		36.331, Annex B.1	Rel-8	pc_FeatrGrp_14	Corresponding to the Index of Indicator, the leftmost binary bit 14 Set to true if supporting all functionalities in the feature group
15	Support of - Measurement reporting event: Event B1 – Neighbour > threshold	- can only be set to 1 if the UE has set at least one of the bit number 22, 23, 24 or 26 to 1.	36.331, Annex B.1	Rel-8	pc_FeatrGrp_15	Corresponding to the Index of Indicator, the leftmost binary bit 15 Set to true if supporting all functionalities in the feature group
16	Support of - Periodical measurement reporting for non-ANR related measurements		36.331, Annex B.1	Rel-8	pc_FeatrGrp_16	Corresponding to the Index of Indicator, the leftmost binary bit 16 Set to true if supporting all functionalities in the feature group

17	Support of - Periodical measurement reporting for SON / ANR - ANR related intra-frequency measurement reporting events	- can only be set to 1 if the UE has set bit number 5 to 1.	36.331, Annex B.1	Rel-8	pc_FeatrGrp_17	Corresponding to the Index of Indicator, the leftmost binary bit 17 Set to true if supporting all functionalities in the feature group
18	Support of - ANR related inter-frequency measurement reporting events	- can only be set to 1 if the UE has set bit number 5 to 1.	36.331, Annex B.1	Rel-8	pc_FeatrGrp_18	Corresponding to the Index of Indicator, the leftmost binary bit 18 Set to true if supporting all functionalities in the feature group
19	Support of - ANR related inter-RAT measurement reporting events	- can only be set to 1 if the UE has set bit number 5 to 1.	36.331, Annex B.1	Rel-8	pc_FeatrGrp_19	Corresponding to the Index of Indicator, the leftmost binary bit 19 Set to true if supporting all functionalities in the feature group
20	If bit number 7 is set to "0": - SRB1 and SRB2 for DCCH + 8x AM DRB If bit number 7 is set to "1": - SRB1 and SRB2 for DCCH + 8x AM DRB - SRB1 and SRB2 for DCCH + 5x AM DRB + 3x UM DRB NOTE: UE which indicate support for a DRB combination also support all subsets of the DRB combination. Therefore, release of DRB(s) never results in an unsupported DRB combination.	- Regardless of what bit number 7 and bit number 20 is set to, UE shall support at least SRB1 and SRB2 for DCCH + 4x AM DRB - Regardless of what bit number 20 is set to, if bit number 7 is set to "1", UE shall support at least SRB1 and SRB2 for DCCH + 4x AM DRB + 1x UM DRB	36.331, Annex B.1	Rel-8	pc_FeatrGrp_20	Corresponding to the Index of Indicator, the leftmost binary bit 20 Set to true if supporting all functionalities in the feature group
21	Support of - Predefined intra- and inter-subframe frequency hopping for PUSCH with $N_{sb} > 1$ - Predefined inter-subframe frequency hopping for PUSCH with $N_{sb} > 1$		36.331, Annex B.1	Rel-8	pc_FeatrGrp_21	Corresponding to the Index of Indicator, the leftmost binary bit 21 Set to true if supporting all functionalities in the feature group

22	Support of - UTRAN measurements, reporting and measurement reporting event B2 in E-UTRA connected mode		36.331, Annex B.1	Rel-8	pc_FeatrGrp_22	Corresponding to the Index of Indicator, the leftmost binary bit 22 Set to true if supporting all functionalities in the feature group
23	Support of - GERAN measurements, reporting and measurement reporting event B2 in E-UTRA connected mode		36.331, Annex B.1	Rel-8	pc_FeatrGrp_23	Corresponding to the Index of Indicator, the leftmost binary bit 23 Set to true if supporting all functionalities in the feature group
24	Support of - 1xRTT measurements, reporting and measurement reporting event B2 in E-UTRA connected mode		36.331, Annex B.1	Rel-8	pc_FeatrGrp_24	Corresponding to the Index of Indicator, the leftmost binary bit 24 Set to true if supporting all functionalities in the feature group
25	Support of - Inter-frequency measurements and reporting in E-UTRA connected mode		36.331, Annex B.1	Rel-8	pc_FeatrGrp_25	Corresponding to the Index of Indicator, the leftmost binary bit 25 Set to true if supporting all functionalities in the feature group
26	Support of - HRPD measurements, reporting and measurement reporting event B2 in E-UTRA connected mode		36.331, Annex B.1	Rel-8	pc_FeatrGrp_26	Corresponding to the Index of Indicator, the leftmost binary bit 26 Set to true if supporting all functionalities in the feature group
27	Support of - EUTRA RRC_CONNECTED to UTRA CELL_DCH CS handover		36.331, Annex B.1	Rel-8	pc_FeatrGrp_27	Corresponding to the Index of Indicator, the leftmost binary bit 27 Set to true if supporting all functionalities in the feature group
28	Undefined		36.331, Annex B.1	Rel-8	pc_FeatrGrp_28	Corresponding to the Index of Indicator, the leftmost binary bit 28 Set to true if supporting all functionalities in the feature group

29	Undefined		36.331, Annex B.1	Rel-8	pc_FeatrGrp_29	Corresponding to the Index of Indicator, the leftmost binary bit 29 Set to true if supporting all functionalities in the feature group
30	Undefined		36.331, Annex B.1	Rel-8	pc_FeatrGrp_30	Corresponding to the Index of Indicator, the leftmost binary bit 30 Set to true if supporting all functionalities in the feature group
31	Undefined		36.331, Annex B.1	Rel-8	pc_FeatrGrp_31	Corresponding to the Index of Indicator, the leftmost binary bit 31 Set to true if supporting all functionalities in the feature group
32	Undefined		36.331, Annex B.1	Rel-8	pc_FeatrGrp_32	Corresponding to the Index of Indicator, the leftmost binary bit 32 Set to true if supporting all functionalities in the feature group

Annex B (informative): Change history

Date	TSG #	TSG Doc.	CR	Rev	Subject/Comment	Old	New
2008-03					Skeleton proposed for RAN#38 Malaga		0.0.1
2008-06					Updated after RAN5#39bis: - Editorial update and alignment with 36.523-2 - TC included in 36.521-1 and 36.521-3 included - Some Conditions for TC selections introduce	0.0.1	0.1.0
2008-08					Updated after RAN5#40: - Editorial update in regard to changing spec names, etc. - FDD and TDD split (R5-083839) - RRM TC numbers aligned with 36.521-3 v030	0.1.1	0.2.0
2008-10					Update after RAN5#40bis: - Table split in different clauses for Conformance and RRM test cases - Extension of applicability tables to include Additional information column - Change of applicability of TCs that apply to any E-UTRA device into "R" - recommended - Updated TCs in accordance to 36.521-1 v110 and 36.521-3 v040 - Some editorial updates	0.2.0	0.3.0
2008-11					Update After RAN5#41 (R5-055360): - Renamed 8.1.1, added new 8.1.2, - Added new TCs to RRM section Measurement Performance Requirements - Added Table A.4.3-2 with reference to test loop functions in 36.509 - Some editorial changes - Normative References updated - Change RRM TC titles to reflect their applicability to FDD only	0.3.0	2.0.0
2008-12	RAN#42	RP-080970			Approval of version 2.0.0 at RAN#42, then put to version 8.0.0.	2.0.0	8.0.0
2008-01					Editorial corrections.	8.0.0	8.0.1
2009-05	RAN#44	RP-090448	0001		CR to 36.521-2: Applicability changes and additions for RRM test cases	8.0.1	8.1.0
2009-05	RAN#44	RP-090448	0002		LTE-RF: Applicability for Output Power Dynamics test cases	8.0.1	8.1.0
2009-09	RAN#45	R5-094035	0003	-	Correction CR to 36.521-2: Applicability changes to introduce additional RRM tests	8.1.0	8.2.0
2009-09	RAN#45	R5-094572	0004	-	Applicability for Output Power Dynamics test cases	8.1.0	8.2.0
2009-09	RAN#45	R5-094710	0005	-	Resubmission-Correction CR to 36.521-2: Applicability changes to introduce additional RRM tests	8.1.0	8.2.0
2009-09	RAN#45	R5-094768	0006	-	Update of RRM Conformance test applicability for SON	8.1.0	8.2.0
2009-09	RAN#45	R5-094999	0007	-	Correction CR to 36.521-2: Applicability changes to RF PDSCH Demodulation tests	8.1.0	8.2.0
2009-12	RAN#46	R5-095519	0008		Correction CR to 36.521-2: Applicability changes to update the Demodulation of PDSCH (FDD) tests based on the CR merge results from RAN5#44	8.2.0	8.3.0
2009-12	RAN#46	R5-095778	0009		Update of RRM Conformance test applicability for RLM in DRX test cases	8.2.0	8.3.0
2009-12	RAN#46	R5-095841	0010	-	CR to 36.521-2: Applicability additions for new RRM (FDD) tests	8.2.0	8.3.0
2010-03	RAN#47	R5-100358	0011	-	CR to 36.521-2 Rel-8 Introduction of Applicability for E-UTRAN FDD - FDD Intra Frequency Cell Search with DRX when L3 filtering is used	8.3.0	8.4.0
2010-03	RAN#47	R5-100561	0012	-	CR to 36.521-2: Update baseline implementation capabilities with extended LTE1500 operating bands	8.3.0	8.4.0
2010-03	RAN#47	R5-100872	0013	-	CSI: Following up corrections to tests titles and RI clause structure	8.3.0	8.4.0
2010-03	RAN#47	-	-	-	Moved to v9.0.0 with no change	8.4.0	9.0.0
2010-06	RAN#48	R5-103147	0014	-	Adding band 20, 800MHZ in EU to TS36.521-2	9.0.0	9.1.0
2010-06	RAN#48	R5-103757	0015	-	Introduction of feature group indicator in applicability for RRM test cases	9.0.0	9.1.0
2010-09	RAN#49	R5-104246	0017	-	CR to 36.521-2 on Correction to cell search	9.1.0	9.2.0
2010-09	RAN#49	R5-104264	0018	-	Addition of applicability for new RRM test cases	9.1.0	9.2.0
2010-09	RAN#49	R5-104372	0019	-	Update of Applicability for Demodulation test cases and UE implementation Types for UTRA TDD	9.1.0	9.2.0
2010-09	RAN#49	R5-104840	0020	-	36521-2 General update to add-remove TCs applicability	9.1.0	9.2.0

Date	TSG #	TSG Doc.	CR	Rev	Subject/Comment	Old	New
					correct, TC titles and numbers and editorials		
2010-09	RAN#49	R5-105056	0021	-	Applicability of a new Rel-9 downlink sustained data rate performance test cases	9.1.0	9.2.0
2010-12	RAN#50	R5-106118	0022	-	CR to 36.521-2: Update baseline implementation capabilities for EUTRA TDD LTE band 41	9.2.0	9.3.0
2011-03	RAN#51	R5-110536	0023	-	Defining new bands 42 and 43 (3500MHz)	9.3.0	9.4.0
2011-03	RAN#51	R5-110955	0024	-	CR to 36.521-2: General update to add, remove, and correct applicability of RRM TCs	9.3.0	9.4.0

History

Document history		
V9.0.0	April 2010	Publication
V9.1.0	July 2010	Publication
V9.2.0	October 2010	Publication
V9.3.0	January 2011	Publication
V9.4.0	April 2011	Publication