ETSI TS 137 106 V16.0.0 (2020-09)



LTE; User Equipment (UE) requirements for shared spectrum channel access (3GPP TS 37.106 version 16.0.0 Release 16)



Reference
RTS/TSGR-0437106vg00

Keywords

LTE

ETSI

650 Route des Lucioles F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C Association à but non lucratif enregistrée à la Sous-Préfecture de Grasse (06) N° 7803/88

Important notice

The present document can be downloaded from: <u>http://www.etsi.org/standards-search</u>

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format at www.etsi.org/deliver.

Users of the present document should be aware that the document may be subject to revision or change of status.

Information on the current status of this and other ETSI documents is available at

https://portal.etsi.org/TB/ETSIDeliverableStatus.aspx

If you find errors in the present document, please send your comment to one of the following services: https://portal.etsi.org/People/CommitteeSupportStaff.aspx

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2020. All rights reserved.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™** and **LTE™** are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

oneM2M[™] logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners.

GSM® and the GSM logo are trademarks registered and owned by the GSM Association.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: "Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards", which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (https://ipr.etsi.org/).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found under http://webapp.etsi.org/key/queryform.asp.

Modal verbs terminology

In the present document "shall", "shall not", "should", "should not", "may", "need not", "will", "will not", "can" and "cannot" are to be interpreted as described in clause 3.2 of the <u>ETSI Drafting Rules</u> (Verbal forms for the expression of provisions).

"must" and "must not" are NOT allowed in ETSI deliverables except when used in direct citation.

Contents

| Intelle | ectual Property Rights | 2 |
|---------|---|---|
| | Notice | |
| _ | | |
| wioua | l verbs terminology | ∠ |
| Forew | vord | 4 |
| 1 | Scope | 5 |
| 2 | References | 5 |
| 3 | Definitions, symbols and abbreviations | 5 |
| 3.1 | Definitions | |
| 3.2 | Symbols | |
| 3.3 | Abbreviations | |
| 4 | General | 6 |
| 4.1 | Relationship between minimum requirements and test requirements | |
| 4.2 | Applicability of minimum requirements | |
| 5 | Channel access procedures | 6 |
| 5.1 | Uplink channel access procedure | |
| 5.1.1 | Channel access parameters | |
| 5.1.2 | Minimum requirement | |
| Anne | x A (informative): Change history | 7 |
| | ry | |
| 113101 | L y | 0 |

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
 - 1 presented to TSG for information;
 - 2 presented to TSG for approval;
 - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

1 Scope

The present document establishes the minimum UE RF characteristics for shared spectrum channel access.

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.
- [1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".
- [2] ITU-R Recommendation M.1545: "Measurement uncertainty as it applies to test limits for the terrestrial component of International Mobile Telecommunications-2000".
- [3] 3GPP TS 36.213: "Physical layer procedures".
- [4] 3GPP TS 36.101: "User Equipment (UE) radio transmission and reception".
- [5] 3GPP TS 36.521-1: "Evolved Universal Terrestrial Radio Access (E-UTRA); User Equipment (UE) conformance specification; Radio transmission and reception; Part 1: Conformance testing".

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in 3GPP TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in 3GPP TR 21.905 [1].

Channel bandwidth: The RF bandwidth supporting a single E-UTRA RF carrier with the transmission bandwidth configured in the uplink or downlink of a cell. The channel bandwidth is measured in MHz and is used as a reference for transmitter and receiver RF requirements.

3.2 Symbols

For the purposes of the present document, the following symbols apply:

BW_{Channel} Channel bandwidth

3.3 Abbreviations

For the purposes of the present document, the abbreviations given in 3GPP TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in 3GPP TR 21.905 [1].

BS Base Station

E-UTRA Evolved Universal Terrestrial Radio Access

PUSCH Physical Uplink Shared Channel

UE User Equipment

4 General

4.1 Relationship between minimum requirements and test requirements

The Minimum Requirements given in this specification make no allowance for measurement uncertainty. The test specification TS 36.521-1 [5] Annex F defines Test Tolerances. These Test Tolerances are individually calculated for each test. The Test Tolerances are used to relax the Minimum Requirements in this specification to create Test Requirements.

The measurement results returned by the Test System are compared - without any modification - against the Test Requirements as defined by the shared risk principle.

The Shared Risk principle is defined in ITU-R M.1545 [2].

4.2 Applicability of minimum requirements

- a) In this specification the Minimum Requirements are specified as general requirements and additional requirements. Where the Requirement is specified as a general requirement, the requirement is mandated to be met in all scenarios
- b) For specific scenarios for which an additional requirement is specified, in addition to meeting the general requirement, the UE is mandated to meet the additional requirements.
- c) The requirements in this specification for E-UTRA TDD operating bands apply for downlink and uplink operations using Frame Structure Type 3.

5 Channel access procedures

5.1 Uplink channel access procedure

For uplink operation in Band 46 and Band 49, a channel access procedure for PUSCH transmission as described in TS 36.213 [3], Clause 15.2.1 is specified.

5.1.1 Channel access parameters

Channel access related parameters for PUSCH are listed in Table 5.1.1-1.

Table 5.1.1-1: Channel access parameters for PUSCH

| Parameter | Unit | Value | | |
|--------------------------------|--------------|-------|-----|--|
| LBT measurement bandwidth (BW) | MHz | 20 | 10 | |
| Energy detection threshold | dBm/BW | -72 | -75 | |
| Detection timing | microseconds | 25 | , | |

5.1.2 Minimum requirement

The UE shall be able to assess whether the medium is busy or idle with at least 90% probability, using a channel access procedure with the parameters in Table 5.1.1-1.

Annex A (informative): Change history

| Change history | | | | | | | | | |
|----------------|---------|------------|----|-----|-----|--|---------|--|--|
| Date | Meeting | TDoc | CR | Rev | Cat | Subject/Comment | New | | |
| | | | | | | | version | | |
| 2018-02 | RAN4#86 | R4-1801547 | | | | TS skeleton | 0.0.1 | | |
| 2018-06 | RAN#80 | RP-181030 | | | | v1.0.0 submitted for plenary approval | 1.0.0 | | |
| 2018-06 | RAN#80 | | | | | Approved by plenary – Rel-15 spec under change control | 15.0.0 | | |
| 2020-06 | RAN#88 | - | - | - | - | Update to Rel-16 version (MCC) | 16.0.0 | | |

History

| Document history | | | | | | |
|------------------|----------------|-------------|--|--|--|--|
| V16.0.0 | September 2020 | Publication | | | | |
| | | | | | | |
| | | | | | | |
| | | | | | | |
| | | | | | | |