



**Digital cellular telecommunications system (Phase 2+) (GSM);  
Full rate speech;  
Substitution and muting of lost frames for full rate speech  
channels  
(3GPP TS 46.011 version 19.0.0 Release 19)**

---

**Reference**

---

RTS/TSGS-0446011vj00

---

---

**Keywords**

---

GSM

---

**ETSI**

---

650 Route des Lucioles  
F-06921 Sophia Antipolis Cedex - FRANCE

---

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B  
Association à but non lucratif enregistrée à la  
Sous-Préfecture de Grasse (06) N° w061004871

---

**Important notice**

---

The present document can be downloaded from the  
[ETSI Search & Browse Standards application](#).

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on [ETSI deliver repository](#).

Users should be aware that the present document may be revised or have its status changed,  
this information is available in the [Milestones listing](#).

If you find errors in the present document, please send your comments to  
the relevant service listed under [Committee Support Staff](#).

If you find a security vulnerability in the present document, please report it through our  
[Coordinated Vulnerability Disclosure \(CVD\)](#) program.

---

**Notice of disclaimer & limitation of liability**

---

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.

No recommendation as to products and services or vendors is made or should be implied.

No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.

In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

---

**Copyright Notification**

---

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.

The content of the PDF version shall not be modified without the written authorization of ETSI.

The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2025.  
All rights reserved.

---

# Intellectual Property Rights

## Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the [ETSI IPR online database](#).

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

## Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

**DECT™**, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™**, **LTE™** and **5G™** logo are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM®** and the GSM logo are trademarks registered and owned by the GSM Association.

---

# Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found at [3GPP to ETSI numbering cross-referencing](#).

---

# Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the [ETSI Drafting Rules](#) (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

# Contents

Intellectual Property Rights .....	2
Legal Notice .....	2
Modal verbs terminology.....	2
Foreword.....	4
1     Scope .....	5
2     References .....	5
3     Definitions and abbreviations.....	5
4     General .....	5
5     Requirements.....	5
5.1     First lost speech frame.....	5
5.2     Subsequent lost speech frames .....	6
5.3     First lost SID frame .....	6
5.4     Subsequent lost SID frame .....	6
6     Example solution.....	6
<b>Annex A (informative):     Change history .....</b>	<b>8</b>
History .....	9

---

# Foreword

This Technical Specification has been produced by the 3<sup>rd</sup> Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

---

# 1 Scope

The present document defines a frame substitution and muting procedure which shall be used by the RX DTX handler when one or more lost speech or SID frames are received from the radio subsystem.

The requirements of the present document are mandatory for implementation in all GSM Base Station Systems (BSS) and Mobile Stations (MS).

---

# 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document*.

- [1] GSM 01.04: "Digital cellular telecommunications system (Phase 2+); Abbreviations and acronyms".
- [2] GSM 06.10: "Digital cellular telecommunications system (Phase 2+); Full rate speech; Transcoding".
- [3] GSM 06.31: "Digital cellular telecommunications system (Phase 2+); Full rate speech; Discontinuous Transmission (DTX) for full rate speech traffic channel".

---

# 3 Definitions and abbreviations

Abbreviations used in the present document are listed in GSM 01.04 [1].

The definitions of terms used in the present document can be found in GSM 06.31 [3].

---

# 4 General

The purpose of the frame substitution is to conceal the effect of lost frames.

The purpose of muting the output in the case of several lost frames is to indicate the breakdown of the channel to the user.

---

# 5 Requirements

## 5.1 First lost speech frame

Normal decoding of lost speech frames would result in very unpleasant noise effects. In order to improve the subjective quality, the first lost speech frame shall be substituted with either a repetition or an extrapolation of the previous good speech frame(s). Lost speech frames shall not be delivered to the speech decoder, nor shall the output be muted directly.

## 5.2 Subsequent lost speech frames

For subsequent lost speech frames, a muting technique shall be used that will gradually decrease the output level, resulting in silencing of the output after a maximum of 320 ms. Clause 6 gives an example solution.

## 5.3 First lost SID frame

A single lost SID frame shall be substituted by the last valid SID frame and the procedure for valid SID frames be applied as described in GSM 06.31 [3].

## 5.4 Subsequent lost SID frame

For the second lost SID frame, a muting technique shall be used on the comfort noise that will gradually decrease the output level, resulting in silencing of the output after a maximum of 320 ms. Clause 6 gives an example solution.

For subsequent lost SID frames, the muting of the output shall be maintained.

---

# 6 Example solution

For guidance, an example solution is given.

The first lost speech frame is replaced at the speech decoder input by the previous good speech frame. Normal decoding is then performed.

The muting procedure to be used in the case of subsequent lost speech frames or for comfort noise frames following the second lost SID frame is as follows:

The pseudo-logarithmic encoded block amplitude  $X_{maxcr}$  (GSM 06.10 [2]), coded on the interval from 0 to 63, is decreased with a constant value  $d=4$  in each frame, down to the lowest possible value. Consequently,  $X_{maxcr}$  will be reduced gradually, and the output muted after a maximum of 320 ms. The grid position parameters are chosen randomly between 0 and 3 during this time.

For subsequent unusable frames, after the frame where  $X_{maxcr}$  reached the lowest possible value, "silence frames" are passed from the RX DTX handler to the speech decoder to guarantee a low output level under all conditions. The silence frame is defined in table 1.

Table 1: Encoded parameters (GSM 06.10) of the silence frame

Log area ratio 1	= 42	
Log area ratio 2	= 39	
Log area ratio 3	= 21	
Log area ratio 4	= 10	
Log area ratio 5	= 9	
Log area ratio 6	= 4	
Log area ratio 7	= 3	
Log area ratio 8	= 2	
LTP gain	= 0	
LTP lag	= 40	
Grid position	= 1	
Block amplitude	= 0	
RPE pulse no. 1	= 3	
RPE pulse no. 2	= 4	
RPE pulse no. 3	= 3	
RPE pulse no. 4	= 4	
RPE pulse no. 5	= 4	
		- repeated for each subsegment
RPE pulse no. 6	= 3	
RPE pulse no. 7	= 3	
RPE pulse no. 8	= 3	
RPE pulse no. 9	= 3	
RPE pulse no. 10	= 4	
RPE pulse no. 11	= 4	
RPE pulse no. 12	= 3	
RPE pulse no. 13	= 3	



## Annex A (informative): Change history

Change history					
SMG No.	TDoc. No.	CR. No.	Section affected	New version	Subject/Comments
SMG#07				4.0.4	ETSI Publication
SMG#20				5.0.1	Release 1996 version
SMG#27				6.0.0	Release 1997 version
SMG#28				6.0.1	ETSI Publication
SMG#29				7.0.0	Specification version 6.0.0 upgrade to Release 1998 version 7.0.0
				7.0.1	Version update for Publication
SMG#31				8.0.0	Release 1999 version

Change history							
Date	TSG #	TSG Doc.	CR	Rev	Subject/Comment	Old	New
03-2001	11				Version for Release 4		4.0.0
06-2002	16				Version for Release 5	4.0.0	5.0.0
12-2004	26				Version for Release 6	5.0.0	6.0.0
06-2007	36				Version for Release 7	6.0.0	7.0.0
12-2008	42				Version for Release 8	7.0.0	8.0.0
12-2009	46				Version for Release 9	8.0.0	9.0.0
03-2011	51				Version for Release 10	9.0.0	10.0.0
09-2012	57				Version for Release 11	10.0.0	11.0.0
09-2014	65				Version for Release 12	11.0.0	12.0.0
12-2015	70				Version for Release 13	12.0.0	13.0.0

Change history							
Date	Meeting	TDoc	CR	Rev	Cat	Subject/Comment	New version
03-2017	SA#75					Version for Release 14	14.0.0
06-2018	SA#80	-	-	-	-	Version for Release 15	15.0.0
2020-07	-	-	-	-	-	Update to Rel-16 version (MCC)	<b>16.0.0</b>
2022-04	-	-	-	-	-	Update to Rel-17 version (MCC)	<b>17.0.0</b>
2024-03	-	-	-	-	-	Update to Rel-18 version (MCC)	<b>18.0.0</b>
2025-10	-	-	-	-	-	Update to Rel-19 version (MCC)	<b>19.0.0</b>

---

# History

Document history		
V19.0.0	October 2025	Publication